



Access Profile Configuration Mode Commands

The Access Profile Configuration Mode is used to create and configure the access-profile.

Command Modes

Exec > Global Configuration > Access Profile Configuration

configure > **access-profile** *profile_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(access-profile-profile_name)#
```



Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [description, on page 1](#)
- [do show, on page 2](#)
- [end, on page 2](#)
- [exit, on page 3](#)
- [timeout, on page 3](#)

description

Allows you to enter descriptive text for this configuration.

Product

All

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration > Access Profile Configuration

configure > **access-profile** *profile_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(access-profile-profile_name)#
```

Syntax Description

description *text*
no description

no

Clears the description for this configuration.

text

Enter descriptive text as an alphanumeric string of 1 to 100 characters.

If you include spaces between words in the description, you must enclose the text within double quotation marks (" "), for example, "AAA BBBB".

Usage Guidelines

The description should provide useful information about this configuration.

do show

Executes all **show** commands while in Configuration mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

do show

Usage Guidelines

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

end

Exits the current configuration mode and returns to the Exec mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

end

Usage Guidelines

Use this command to return to the Exec mode.

exit

Exits the current mode and returns to the parent configuration mode.

Product	All
Privilege	Security Administrator, Administrator
Syntax Description	exit
Usage Guidelines	Use this command to return to the parent configuration mode.

timeout

This command allows you to configure the EMM timers, ESM timers, and Session Setup timers in access-profile.

Product	MME
Privilege	Security Administrator, Administrator
Command Modes	Exec > Global Configuration > Access Profile Configuration configure > access-profile <i>profile_name</i>
Syntax Description	Entering the above command sequence results in the following prompt: <pre>[local]host_name(access-profile-profile_name)#</pre> timeout { emm { t3422 t3450 t3460 t3470 } timeout_value esm { t3485 t3486 t3489 t3495 } timeout_value session-setup setup_timer } remove timeout { emm esm session-setup }

remove

Removes the configuration from the access-profile.

emm { t3422 | t3450 | t3460 | t3470 } timeout_value

Configures the EMM timers. The EMM timer configuration in access-profile will have higher precedence over the same timer configuration in mme-service.

- **t3422**: Timer for Retransmission of Detach Request.
- **t3450**: Timer for Retransmission of Attach Accept/TAU Accept.
- **t3460**: Timer for Retransmission of Auth Request/Security Mode.
- **t3470**: Timer for Retransmission of Identity Request.

timeout_value specifies the timeout value in seconds as an integer from 1 to 270.

esm { t3485 | t3486 | t3489 | t3495 } timeout_value

Configures the ESM timers. The ESM timer configuration in access-profile will have higher precedence over the same timer configuration in mme-service.

- **t3485**: Timer for Retransmission of Activate Default/Dedicated Bearer Request.
- **t3486**: Timer for Retransmission of Modify EPS Bearer Context Request.
- **t3489**: Timer for Retransmission of ESM Information Request.
- **t3495**: Timer for Retransmission of Deactivate EPS Bearer Request.

timeout_value specifies the timeout value in seconds as an integer from 1 to 270.

session-setup setup_timer

Configures the session setup timeout in seconds. The session setup timer configuration in access-profile will have higher precedence over the same timer configuration in mme-service.

setup_timer is an integer from 1 to 10000.

Usage Guidelines

Use this command to configure the EMM timers, ESM timers, and Session Setup timers in access-profile. The configuration in access-profile will have higher precedence over the same timer configuration in mme-service.

The device type and RAT type are not known while configuring the timer values. Hence, the valid range for these timers is defined such that it covers the maximum value for E-UTRAN and NB-IoT RAT as specified in 3GPP TS 24.301 Release 13.

The maximum timer value is $24+240 = 264$ seconds for NB-IoT CE-mode. Hence, the maximum configurable value for timers is 270 seconds.

Example

The following command configures the *t3450* EMM timer with timeout value set to *100* seconds:

```
timeout emm t3450 100
```