



Release Notes for Cisco Unified Provisioning Manager 1.3.1

Revised: January 28, 2009, OL-18854-01

Contents

These release notes provide:

- [Introduction, page 1](#)
- [SUPPLEMENTAL LICENSE AGREEMENT, page 1](#)
- [New Features in Cisco Unified Provisioning Manager 1.3.1, page 2](#)
- [Product Documentation, page 3](#)
- [Known Problems, page 4](#)
- [Resolved Problems, page 17](#)
- [Obtaining Documentation and Submitting a Service Request, page 18](#)

Introduction

These release notes are for use with Cisco Unified Provisioning Manager (Provisioning Manager).

SUPPLEMENTAL LICENSE AGREEMENT

SUPPLEMENTAL LICENSE AGREEMENT FOR CISCO SYSTEMS NETWORK MANAGEMENT SOFTWARE: CISCO UNIFIED PROVISIONING MANAGER

IMPORTANT-READ CAREFULLY: This Supplemental License Agreement ("SLA") contains additional limitations on the license to the Software provided to Customer under the End User License Agreement between Customer and Cisco. Capitalized terms used in this SLA and not otherwise defined



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

herein shall have the meanings assigned to them in the End User License Agreement. To the extent that there is a conflict among any of these terms and conditions applicable to the Software, the terms and conditions in this SLA shall take precedence.

By installing, downloading, accessing or otherwise using the Software, Customer agrees to be bound by the terms of this SLA. If Customer does not agree to the terms of this SLA, Customer may not install, download or otherwise use the Software.

ADDITIONAL LICENSE RESTRICTIONS:

- **Installation and Use.** The Software components are provided to Customer solely to install, update, supplement, or replace existing functionality of the applicable Network Management Software product. Customer may install and use the following Software components:
 - Cisco Unified Provisioning Manager: May be installed on a server in Customer's network management environment.

For each Software license granted, Customers may install and run the Software on a single server to manage the number of IP phones specified in the license file provided with the Software, or as specified in the Software License Claim Certificate. Customers whose requirements exceed the IP phone limit must purchase upgrade licenses or additional copies of the Software. The IP phone limit is enforced by license registration.

- **Reproduction and Distribution.** Customers may not reproduce nor distribute the Software.

DESCRIPTION OF OTHER RIGHTS AND LIMITATIONS.

Please refer to the Cisco Systems, Inc. End User License Agreement.

New Features in Cisco Unified Provisioning Manager 1.3.1

Cisco Unified Provisioning Manager adds the following:

- **Set-only Provisioning Attributes**—Provisioning attributes that can only be set. You can provision their settings, but they are not stored once they are set, and they are not retrieved from the Call Processor during a synchronization.

Following is a list of the new set-only provisioning attributes:

- BLF Directed Call Park
- Device Mobility Mode
- DND Incoming Call Alert
- DND Option
- Do Not Disturb
- Call Pickup Group Audio Alert Setting (Phone Active)
- Call Pickup Group Audio Alert Setting (Phone Idle)
- Ignore Presentation Indicators (Internal Calls Only)
- Presence Group
- Primary Phone
- Rerouting Calling Search Space
- Secondary Calling Search Space for Forward All

- SIP Profile
- Subscribe Calling Search Space
- The following provisioning attributes:
 - Busy Lampfield Info
 - Enable ResyncMWI
- The following provisioning attributes for Extension Mobility Line:
 - Alerting Name
 - ASCII Alerting Name
 - ASCII Display (Internal Caller ID)
 - ASCII Line Text Label
 - Line Groups
- The following business rules:
 - AssociateUsersByDevicePool
 - AssociateUsersByLocation
- Enhancements to the Call Pickup Group configuration template.
- Ability to unlock voicemail accounts.
- Ability for users to have privileges for multiple Domains.
- Ability to add external AAA servers (LDAP servers) for user authentication.
- Support for third-party SIP phones.
- Support for Cisco Unified Communications Manager 6.1(3).
- Support for Cisco Unified Communications Manager Express 7.0(1).
- Support for Cisco Unity Express 7.0.1.
- Support for Third-party SIP Device (Advanced and Basic).
- Support for VMware.

Product Documentation



Note

The originally published printed and electronic documentation is included with your product. Any changes after original publication are reflected on Cisco.com, where you will find the most up-to-date documentation.

[Table 1](#) describes the product documentation that is available.

Table 1 **Product Documentation**

Document Title	Available Formats
<i>Supported Devices Table for Cisco Unified Provisioning Manager 1.3.1</i>	On Cisco.com at the following URL: http://www.cisco.com/en/US/products/ps7125/products_device_support_tables_list.html
<i>Release Notes for Cisco Unified Provisioning Manager 1.3.1</i>	<ul style="list-style-type: none"> • In PDF on the product CD-ROM • On Cisco.com at the following URL: http://www.cisco.com/en/US/products/ps7125/prod_release_notes_list.html
<i>Installation Guide for Cisco Unified Provisioning Manager 1.3.1</i>	<ul style="list-style-type: none"> • In PDF on the product CD-ROM • On Cisco.com at the following URL: http://www.cisco.com/en/US/products/ps7125/prod_installation_guides_list.html
<i>User Guide for Cisco Unified Provisioning Manager 1.3.1</i>	<ul style="list-style-type: none"> • In PDF on the product CD-ROM • On Cisco.com at the following URL: http://www.cisco.com/en/US/products/ps7125/products_user_guide_list.html

Known Problems

[Table 2](#) describes problems known to exist in this release.



Note

To obtain more information about known problems, access the Cisco Software Bug Toolkit at <http://tools.cisco.com/Support/BugToolKit/action.do?hdnAction=searchBugs>. (You will be prompted to log into Cisco.com).

Table 2 **Known Problems in Provisioning Manager**

Bug ID	Summary	Explanation
CSCsq88154	Searches do not recognize the underscore character.	<p>The underscore (_) character is not recognized by the search tool.</p> <p>For example, if you perform a search using *User* or *User_*, the results are the same.</p> <p>Workaround:</p> <p>You can add an escape character (\) in front of the underscore (_) character in the search query string. The search results will then be correct.</p> <p>For example, if you change the search string from *User_* to *User**, the correct search result is returned.</p>

Table 2 Known Problems in Provisioning Manager (continued)

Bug ID	Summary	Explanation
CSCsv22073	Cannot create Domains with similar names, where the only difference in the names is that underscores replace spaces.	If a Domain is created with a name which contains a space (for example, Test Domain), and then another Domain is created with the same name but uses an underscore (_) instead of spaces (for example, Test_Domain), an error occurs and the second Domain cannot be created. Workaround: Do not create Domains that have similar names, where the only difference is that spaces are replaced by underscores.
CSCsw35871	An error occurs if an ampersand character is part of the batch filename.	If a batch filename contains an ampersand (&), an error occurs when you upload the batch action file. Workaround: Do not enter an ampersand in the filename of a batch file.
CSCsx15433	Cannot view the Domain if an ampersand character is part of the Service Area ID.	When you create a Service Area, if you enter an ampersand (&) as part of the Service Area ID, you cannot view the Domain. Workaround: Do not use an ampersand in the Service Area ID.
CSCsx19449	Domain synchronization fails if the Call Processor name contains a colon.	When you create a Call Processor, if you enter a colon (:) as part of its name, and the Domain synchronization rule AssociateUsersByDevicePool is enabled, the Domain synchronization fails. Workaround: Do not use a colon in the name of a Call Processor.
CSCso79103	Cannot configure transformation CSS for outbound calls in H323 gateways.	Provisioning Manager does not provision the following H323 gateway fields in Cisco Unified Communications Manager: <ul style="list-style-type: none"> • Called Party Transformation CSS • Use Device Pool Called Party Transformation CSS • Calling Party Transformation CSS • Use Device Pool Calling Party Transformation CSS This problem applies to all versions of Cisco Unified Communications Manager. Workaround: None.

In Provisioning Manager, you create Call Processors and Unified Message Processors. Call Processors are proxies for each instance of a Cisco Unified Communications Manager or Cisco Unified Communications Manager Express. Unified Message Processors are proxies for each instance of Cisco Unity, Cisco Unity Express, or Cisco Unity Connection.

Problems can occur while obtaining the data from these devices, due to known problems in certain versions of these devices.

[Table 3](#) lists the known problems and the related device bug IDs. When a related bug is fixed, the problem will no longer exist in Provisioning Manager.

Table 3 Known Problems in Call Processor and Unified Message Processor Devices

Summary	Explanation
<p>Cannot set a Directed Call Park without a partition in Cisco Unified Communications Manager.</p>	<p>If you have two BLF Directed Call Parks with the same number (for example, 100) but with different partitions, when you try to set the value as 100 in the device, it will be set as <i>100 in RP</i> instead of <i>100</i>.</p> <p>If you create a BLF Directed Call Park without a partition and then try to configure this value, you will get the following error:</p> <pre>The specified Directed Call Park is not found.</pre> <p>This problem applies to Cisco Unified Communications Manager 6.x and 7.x. The related Cisco Unified Communications Manager bug ID is CSCsu79343.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 6.1.2 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
<p>The Label ASCII field is not set in Cisco Unified Communications Manager.</p>	<p>The Label ASCII field of the BLF Directed Call Park provisioning attribute is not set properly in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 6.x and 7.x. The related Cisco Unified Communications Manager bug ID is CSCsu79308.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 6.1.2 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
<p>The BLF Directed Call Park set-only provisioning attribute does not work correctly with Cisco Unified Communications Manager.</p>	<p>The BLF Directed Call Park set-only provisioning attribute does not work correctly with Cisco Unified Communications Manager. This is due to a Cisco Unified Communications Manager user interface issue.</p> <p>This problem applies to Cisco Unified Communications Manager 6.0.1.</p> <p>Workaround: None.</p>
<p>Device Mobility Mode is not set on Cisco Unified Communications Manager.</p>	<p>The Device Mobility Mode set-only provisioning attribute is not set on Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.3.2. The related Cisco Unified Communications Manager bug ID is CSCsw39524.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 4.3.2 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
The Label ASCII field is not set in Cisco Unified Communications Manager.	<p>The Label ASCII field of the Busy Lampfield Info provisioning attribute is not set properly in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 7.0.1. The related Cisco Unified Communications Manager bug ID is CSCsw48333.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 7.0.1 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
An infrastructure synchronization is shown as completed, even though the wrong credentials were entered for Cisco Unified Communications Manager.	<p>An infrastructure synchronization completes, and instead of getting an error when the wrong credentials are entered for Cisco Unified Communications Manager in Provisioning Manager, you get a message telling you that synchronization has completed successfully. However none of the infrastructure products are synchronized.</p> <p>This problem applies to Cisco Unified Communications Manager 6.1.2. The related Cisco Unified Communications Manager bug ID is CSCsw51375.</p> <p>Workaround: None.</p>
The Retry Video Call as Audio value is selected in Cisco Unified Communications Manager, even though the setting was not selected in Provisioning Manager.	<p>When configuring the Retry Video Call as Audio value of an H323 Gateway to false in Provisioning Manager, the value is set to true in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.3.2. The related Cisco Unified Communications Manager bug ID is CSCsq88437.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 4.3.2 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
Users are not added to the User Group, and setting the Cisco Unified Communications Manager password for the users fails.	<p>During a Phone Service order, the user is not added to the corresponding User Group (End User Group). As a result, the user cannot log into Cisco Unified Communications Manager using his password.</p> <p>This problem applies to Cisco Unified Communications Manager 7.0.1. The related Cisco Unified Communications Manager bug ID is CSCsw37163.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 7.0.1 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>

Table 3 *Known Problems in Call Processor and Unified Message Processor Devices (continued)*

Summary	Explanation
<p>Cannot synchronize phones for Cisco Unified Communications Manager.</p>	<p>In Cisco Unified Communications Manager, if you create a phone with a MAC address (for example, SEP555555555555) and try to update the MAC with the same address (for example, 555555555555), you will receive a duplicate error. If you try to update the phone with a new MAC address, the new MAC address will not be reflected in the Cisco Unified Communications Manager database. As a result, synchronizing the phone is not successful.</p> <p>This problem applies to all supported versions of Cisco Unified Communications Manager. The related Cisco Unified Communications Manager bug ID is CSCsk93459.</p> <p>Workaround:</p> <p>Delete the phone in Cisco Unified Communications Manager and then recreate the phone. Then perform a subscriber synchronization in Provisioning Manager.</p>
<p>A duplicate MAC address error may occur.</p>	<p>Sometimes when placing an order for a phone service, you will get a duplicate MAC address error. This happens when a phone is ordered, cancelled, and then reordered.</p> <p>This problem applies to Cisco Unified Communications Manager 4.x and 5.x. The related Cisco Unified Communications Manager bug ID is CSCsq69085.</p> <p>Workaround: None.</p>
<p>Orders fail if the phone description field contains UTF-8 characters.</p>	<p>If you enter UTF-8 characters (for example, Danish or German characters) in the phone description field when adding a phone, the order fails. This occurs because Cisco Unified Communications Manager does not support these special characters in the phone description field.</p> <p>This problem applies to all supported versions of Cisco Unified Communications Manager. The related Cisco Unified Communications Manager bug ID is CSCsr69414.</p> <p>Workaround:</p> <p>Do not use special characters in the phone description field.</p>
<p>Extension Mobility Access, Extension Mobility Access with Line, and Phone Service with Extension Mobility enabled orders fail.</p>	<p>The following orders placed on Cisco Unified Communications Manager fail:</p> <ul style="list-style-type: none"> • Extension Mobility Access • Extension Mobility Access with Line • Phone Service with Extension Mobility enabled <p>This problem applies to Cisco Unified Communications Manager 4.3(2). The related Cisco Unified Communications Manager bug ID is CSCsq52523.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 4.3 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
Subscribers and their associated products do not appear in Provisioning Manager after a subscriber synchronization if Extension Mobility is enabled.	<p>The products; Extension Mobility Access, Extension Mobility Access with Line, and Phone Service with Extension Mobility enabled are not synchronized during a subscriber synchronization on Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.3(2). The related Cisco Unified Communications Manager bug ID is CSCsq52523.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 4.3 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
Cannot retrieve a subscriber from Cisco Unity Connection if the subscriber's ID contains uppercase characters.	<p>If a subscriber ID with uppercase characters is created in Provisioning Manager, and then Provisioning Manager creates the same subscriber in a Cisco Unity Connection device, the subscriber cannot be retrieved from the Cisco Unity Connection device when Provisioning Manager queries for the subscriber.</p> <p>Cisco Unity Connection converts mixed-case subscriber IDs into all lowercase before saving to its database. Retrieved subscriber IDs will not match the original subscriber IDs that contain uppercase characters.</p> <p>This problem applies to Cisco Unity Connection 7.0. The related Cisco Unity Connection bug ID is CSCsr05155.</p> <p>Workaround:</p> <p>This problem has been fixed in Cisco Unified Communications Manager, Business Edition Engineering Special 7.0(1.21006.1) with Cisco Unity Connection version 7.0(1)ES12. (For details, see http://ipcbu-cap.cisco.com/loads/readme/UCSInstall_UCOS_7.0.1.21006-1_readme.html.)</p>
The description for Call Pickup Group is not displayed in Cisco Unified Communications Manager.	<p>When configuring the Call Pickup Group in Cisco Unified Communications Manager through Provisioning Manager, the description field for the Call Pickup group cannot be set in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.3(2). The related Cisco Unified Communications Manager bug ID is CSCsq88429.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 4.3.2 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>

Table 3 **Known Problems in Call Processor and Unified Message Processor Devices (continued)**

Summary	Explanation
<p>The MLPP Domain field does not accept alphabetic characters.</p>	<p>When configuring Cisco Unified Communications Manager devices, you can enter alphabetic characters in the MLPP Domain field for common device configuration or device pool. But if you configure the common device configuration or device pool through Provisioning Manager, the MLPP Domain field cannot contain alphabetic characters.</p> <p>This problem applies to Cisco Unified Communications Manager 5.x, 6.x, and 7.x. The related Cisco Unified Communications Manager bug ID is CSCsl01858 and CSCsr43379.</p> <p>Workaround: None.</p>
<p>AAR Group is a required field in H323 gateways for Cisco Unified Communications Manager.</p>	<p>If the AAR Group field is set to None, H323 gateways cannot be configured in Cisco Unified Communications Manager. This occurs even though the AAR Group is not a mandatory field in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.3(2). The related Cisco Unified Communications Manager bug ID is CSCsm90656.</p> <p>Workaround: None.</p>
<p>Ordering Phone Service with Extension Mobility enabled results in an error.</p>	<p>When using batch ordering to order Phone Service (or Unified Messaging Service) with Extension Mobility enabled, a recoverable error occurs. The following error message appears:</p> <p>You cannot add a line to an extension mobility enabled phone while a user is logged on to that phone.</p> <p>This problem applies to Cisco Unified Communications Manager 5.1(2) and 5.1(3). The related Cisco Unified Communications Manager bug ID is CSCsk41840.</p> <p>Workaround:</p> <p>In Provisioning Manager, do the following:</p> <ol style="list-style-type: none"> 1. Go to Infrastructure Configuration > Set Up Devices > Call Processors > View Call Processor. 2. Select the Call Processor on which the order was placed, and perform a subscriber synchronization. 3. Go to Provisioning Dashboard > Manage Activities > My Activities > All Activities. 4. Select the Handle Recoverable Error Activity for the failed order and continue the order.

Table 3 **Known Problems in Call Processor and Unified Message Processor Devices (continued)**

Summary	Explanation
<p>A Change Line order cannot unset some provisioning attributes.</p>	<p>The following provisioning attributes cannot be unset (clearing the value of an attribute or setting the value to its default) in a Change Line order:</p> <ul style="list-style-type: none"> • Busy Trigger • Maximum Number of Calls • MLPP No Answer Ring Duration <p>Also, all call forwarding provisioning attributes can be unset to false.</p> <p>This problem applies to all supported versions of Cisco Unified Communications Manager. The related Cisco Unified Communications Manager bug IDs are CSCsi93796 and CSCsj55139.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 5.x build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
<p>For CTI Route Points, infrastructure synchronization does not synchronize the Common Device Config value.</p>	<p>After adding a CTI Route Point in a Call Processor and performing an infrastructure synchronization, the Common Device Config value set in Cisco Unified Communications Manager is not synchronized with Provisioning Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 6.0.1. The related Cisco Unified Communications Manager bug ID is CSCsj24568.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 6.0.1 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
<p><i>Not set</i> is displayed in Provisioning Manager for Phone provisioning attributes set through Provisioning Manager.</p>	<p>After synchronization, Phones provisioned through Provisioning Manager have their provisioning attributes set to <i>Not set</i>.</p> <p>Following are the affected provisioning attributes.</p> <ul style="list-style-type: none"> • Auto Line Select • Gratuitous ARP • PC Port • PC Voice VLAN Access • Settings Access • Video Capabilities • Web Access <p>This problem applies to all supported versions of Cisco Unified Communications Manager. The related Cisco Unified Communications Manager bug ID is CSCsh61703.</p> <p>Workaround: None.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
The MLPP Domain provisioning attribute does not accept special characters.	<p>The MLPP Domain provisioning attribute setting in Provisioning Manager only supports hexadecimal values (0-9 and A-F), as originally supported in Cisco Unified Communications Manager 4.x. Cisco Unified Communications Manager 5.x and later supports ASCII characters. Provisioning Manager 1.3 does not allow ASCII characters in the attribute setting.</p> <p>This problem applies to Cisco Unified Communications Manager 5.x and later. The related Cisco Unified Communications Manager bug IDs are CSCsl01858 and CSCsl01858.</p> <p>Workaround: None.</p>
Canceling a line does not set the telephone number to a blank (empty) value on Cisco Unified Communications Manager when the directory number of the line is set as the phone number for the user.	<p>When canceling a line, where the phone number and primary extension number are set for a user, the phone number and primary extension number of the user are not set to an empty value on Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 5.1(2). The related Cisco Unified Communications Manager bug ID is CSCsl09935.</p> <p>Workaround: None.</p>
You cannot unset the No Answer Ring Duration provisioning attributes.	<p>You cannot unset some Line provisioning attributes either through batch provisioning (using the keyword CUPM_BLANK) or through the Provisioning Manager user interface.</p> <p>You cannot set the following Line provisioning attributes to the default value (no value):</p> <ul style="list-style-type: none"> • No Answer Ring Duration • MLPP No Answer Ring Duration <p>This problem applies to Cisco Unified Communications Manager 4.1(3) and 4.2(3). The related Cisco Unified Communications Manager bug ID is CSCsj55139.</p> <p>Workaround: None.</p>
Subscriber synchronization and batch ordering for Cisco Unified Communications Manager 6.0(1) takes a long time to process when compared to the Provisioning Manager-supported versions of Cisco Unified Communications Manager 4.x and 5.x.	<p>The time it takes for subscriber synchronization and batch order processing for a large number of users is longer for 6.0(1) when compared to the Provisioning Manager-supported versions of Cisco Unified Communications Manager 4.x and 5.x. This is due to the reduced AXL performance on Cisco Unified Communications Manager 6.0(1) when compared to the Provisioning Manager-supported versions of Cisco Unified Communications Manager 4.x and 5.x.</p> <p>This problem applies to Cisco Unified Communications Manager 6.0(1). The related Cisco Unified Communications Manager bug ID is CSCsi41499.</p> <p>Workaround: None.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
<p>When a phone has two lines and line 1 is canceled and recreated using a new number, the new number is not applied.</p>	<p>This problem occurs on a phone with two lines. If line 1 is canceled and then recreated with a different number, the first number for line 1 is still listed as the telephone number in the user information.</p> <p>This problem applies to Cisco Unified Communications Manager 5.1(1) and 6.0(1). The related Cisco Unified Communications Manager bug ID is CSCsi93796.</p> <p>Workaround:</p> <p>This problem has been fixed in an interim Cisco Unified Communications Manager 5.1.3 build. To get the interim build, contact the Cisco Technical Assistance Center (TAC), at: http://www.cisco.com/en/US/support/tsd_cisco_worldwide_contacts.html.</p>
<p>SIP phones provisioned through Provisioning Manager cannot register to Cisco Unified Communications Manager.</p>	<p>Cisco Unified Communications Manager does not provide sufficient support to provision SIP phones from an external provisioning tool (Provisioning Manager).</p> <p>This problem applies to Cisco Unified Communications Manager 5.0(4) and 5.1(1). The related Cisco Unified Communications Manager bug ID is CSCsi28204.</p> <p>Workaround:</p> <p>To register with Cisco Unified Communications Manager, you must go to the Cisco Unified Communications Manager interface and set the SIP profile field.</p>
<p>In the Voice Region Configuration Template, for Cisco Unified Communications Manager 5.1(1) and 6.0(1), the Default Codec cannot be set with the values Use System Default or Keep Current Setting.</p>	<p>When creating a Voice Region Configuration Template, the Default Codec field does not list Use System Default or Keep Current Setting. These selections are available on Cisco Unified Communications Manager 5.1(1) and 6.0(1), but are not supported in Provisioning Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 5.1(1) and 6.0(1). The related Cisco Unified Communications Manager bug ID is CSCsi82847.</p> <p>Workaround:</p> <p>After the voice region is created, make updates to the voice region using the Cisco Unified Communications Manager user interface.</p>
<p>A blank Translation Pattern cannot be created for Cisco Unified Communications Manager 5.0(4) and 5.1(1).</p>	<p>A Translation Pattern with a blank pattern cannot be created using the Configuration Templates. If you try to create a blank translation pattern you will get an error message similar to the following:</p> <pre>Dial Plan is required for non-SIP Route and Translation Patterns that have @ in the pattern.</pre> <p>This problem applies to Cisco Unified Communications Manager 5.0(4) and 5.1(1). The related Cisco Unified Communications Manager bug ID is CSCsi59634.</p> <p>Workaround: None.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
Removing the number from the Contact Number field on the subscriber wizard does not remove the number from the Cisco Unified Communications Manager End User Telephone Number field.	<p>When updating a subscriber's information, if you remove the number from the Contact Number field on the subscriber wizard, the Cisco Unified Communications Manager End User Telephone Number field displays the previous value. The expected behavior would be for the End User Telephone Number field to be blank.</p> <p>This problem applies to Cisco Unified Communications Manager 5.1(1) and 6.0(1). The related Cisco Unified Communications Manager bug ID is CSCsi93796.</p> <p>Workaround: None.</p>
MLPP Domain objects are created on Cisco Unified Communications Manager if a nonexistent MLPP Domain ID is specified when creating a Common Device Configuration.	<p>If you specify a nonexistent MLPP Domain ID when adding a Common Device Configuration object from Provisioning Manager using the Configuration Templates, the Cisco Unified Communications Manager creates a new MLPP Domain object using the provided ID instead of returning an error message stating that the MLPP Domain does not exist.</p> <p>This problem applies to Cisco Unified Communications Manager versions 5.0.4 and 5.1.1. The related Cisco Unified Communications Manager bug ID is CSCsj10137.</p> <p>Workaround:</p> <p>Specify the correct MLPP Domain ID in Provisioning Manager.</p> <p>The MLPP Domain ID is considered a hexadecimal value on Cisco Unified Communications Manager, whereas it is considered a decimal value in Provisioning Manager. You can convert the hexadecimal MLPP Domain ID in Cisco Unified Communications Manager to a decimal value and use that value in Provisioning Manager.</p>
Members of the CallPickupGroup and the LineGroup are not saved in the Provisioning Manager database.	<p>Provisioning Manager cannot obtain values for the members of the CallPickupGroup and LineGroup objects during synchronization with Cisco Unified Communications Manager. However, these objects can be configured on Cisco Unified Communications Manager using Provisioning Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 4.1(3), 4.2(1), and 5.0(4). The related Cisco Unified Communications Manager bug IDs are CSCsf07468 and CSCsf07560.</p> <p>Workaround: None.</p>
Synchronizing Cisco Unified Communications Manager 5.0(4) is sometimes unsuccessful.	<p>There are two issues causing this problem:</p> <ul style="list-style-type: none"> • Provisioning Manager cannot support Route Patterns that are configured to use a gateway as the destination. The related Cisco Unified Communications Manager bug ID is CSCsh36013. • Provisioning Manager cannot support Route Patterns whose configured Route Lists are deleted manually from Cisco Unified Communications Manager. The related Cisco Unified Communications Manager bug ID is CSCsh29825. <p>This problem applies to Cisco Unified Communications Manager 5.0(4).</p> <p>Workaround: None.</p>

Table 3 Known Problems in Call Processor and Unified Message Processor Devices (continued)

Summary	Explanation
<p>In some cases, a change phone order changes the phone load name on Cisco Unified Communications Manager.</p>	<p>When performing a change phone order, a phone load name is set on the phone. This problem occurs if the phone load name was originally not set (which means that Cisco Unified Communications Manager is using the default phone load).</p> <p>Also, the problem results in different situations for the Provisioning Manager supported versions of Cisco Unified Communications Manager 4.x and 5.x:</p> <ul style="list-style-type: none"> • In the Provisioning Manager supported versions of Cisco Unified Communications Manager 4.x, a change phone order sets the phone load name with the default phone load name. • In the Provisioning Manager supported versions of Cisco Unified Communications Manager 5.x, only when a module load name is present does performing a change phone order set the phone's load name with the module load name. <p>This problem applies to all supported versions of Cisco Unified Communications Manager 4.x and 5.x.</p> <p>The related Cisco Unified Communications Manager bug IDs are CSCsh26744 and CSCsh58736.</p> <p>Workaround: None.</p>
<p>Canceling a shared phone for a subscriber does not disassociate the phone in Cisco Unified Communications Manager.</p>	<p>A canceled shared phone remains associated in the user's account on the Cisco Unified Communications Manager, if the subscriber has only one phone in Cisco Unified Communications Manager.</p> <p>This problem applies to Cisco Unified Communications Manager 5.0(4) and 5.1(1). The related Cisco Unified Communications Manager bug ID is CSCsh48876.</p> <p>Workaround: None.</p>
<p>Change phone orders fail on Cisco Unified Communications Manager 5.0(4) when Extension Mobility is on and using the same MAC address.</p>	<p>If you perform a change phone order on a phone that has Extension Mobility set and keep the same MAC address, the order fails.</p> <p>This occurs because Cisco Unified Communications Manager does not delete the autogenerated profile on Cisco Unified Communications Manager. Therefore it is attempting to regenerate the same autogenerated profile.</p> <p>This problem applies to Cisco Unified Communications Manager 4.2(1) and 5.0(4). The related Cisco Unified Communications Manager bug ID is CSCsd60519.</p> <p>Workaround:</p> <p>Before placing the change order, remove the autogenerated device profile from Cisco Unified Communications Manager.</p>

Table 3 *Known Problems in Call Processor and Unified Message Processor Devices (continued)*

Summary	Explanation
<p>When ordering Phone Service, the primary extension is set to None.</p>	<p>When ordering Phone Service for a new subscriber (which creates a user, phone, and line in Cisco Unified Communications Manager), the user's primary extension should be set as the line's directory number. Instead, the primary extension is set to None.</p> <p>This problem applies to Cisco Unified Communications Manager 5.0(4) and 5.1(1). The related Cisco Unified Communications Manager bug ID is CSCsh77973.</p> <p>Workaround: None.</p>
<p>The default value is not set to True for the following:</p> <ul style="list-style-type: none"> • Forwarded Call Info - Caller Name • Forwarded Call Info - Dialed Number <p>Because of this, call forwarding does not occur.</p>	<p>In Cisco Unified Communications Manager, the following provisioning attributes are set to False:</p> <ul style="list-style-type: none"> • Forwarded Call Information - Caller Name • Forwarded Call Information - Dialed Number <p>These attributes must be set to True for call forwarding to occur.</p> <p>This problem applies to all Provisioning Manager supported versions of Cisco Unified Communications Manager 4.x. The related Cisco Unified Communications Manager bug ID is CSCsg37872.</p> <p>Workaround:</p> <p>After creating a Service Area, set these provisioning attributes to True.</p>
<p>The MLPP Domain ID is not set on the Cisco Unified Communications Manager when an H323 gateway is created through Configuration Templates.</p>	<p>The MLPP Domain ID is not set for Cisco Unified Communications Manager.</p> <p>This problem applies to all Provisioning Manager supported versions of Cisco Unified Communications Manager 4.x. The related Cisco Unified Communications Manager bug ID is CSCsh56843.</p> <p>Workaround: None</p>

Resolved Problems

Table 4 describes problems that were fixed in this release.


Note

To obtain more information about resolved problems, access the Cisco Software Bug Toolkit at <http://tools.cisco.com/Support/BugToolKit/action.do?hdnAction=searchBugs>. (You will be prompted to log into Cisco.com).

Table 4 *Problems Resolved in Provisioning Manager 1.3.1*

Bug ID	Summary	Explanation
CSCso79201	Could not specify a codec when outbound fast start was enabled on H323 gateways.	When configuring an H323 gateway in Cisco Unified Communications Manager, you can enable fast start for outbound calls (by selecting the Enable Outbound FastStart field), and then you can select a codec for the outbound fast start in Cisco Unified Communications Manager. But in the Provisioning Manager Template Configuration page, if you selected the Enable Outbound FastStart field, you could not choose a codec for outbound fast start. Now you can choose a codec for outbound fast start.
CSCsr13259	Provisioning attributes were not set for the new owner after performing a change owner operation.	If you used the keyword \${USERID}, \${FIRSTNAME}, or \${LASTNAME} in a provisioning attribute at the Service Area level, when you performed a change owner operation, the new user ID, first name, or last name (respectively) was not set for the new owner. Now the settings are set.
CSCsr14246	The number of characters allowed in the provisioning attributes fields might not have been sufficient when keywords were used.	The number of characters allowed in the provisioning attribute fields did not account for keywords. Now the field takes keywords into account.
CSCsr68344	After running a Domain synchronization, Extension Mobility Access for SCCP phones would appear in a SIP Service Area.	Sometimes after a Domain synchronization ran, Extension Mobility Access products appeared in SIP Service Areas. This problem is fixed.

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

This document is to be used in conjunction with the documents listed in the “[Product Documentation](#)” section.

CCDE, CCENT, Cisco Eos, Cisco HealthPresence, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0812R)

Copyright © 2009 Cisco Systems, Inc. All rights reserved.