



Release Notes for Cisco NAC Appliance, Version 4.8

Document Number OL-19675-01 Revised: September 28, 2011

Contents

These release notes provide the latest cumulative release information for Cisco® NAC Appliance, Release 4.8. This document describes new features, changes to existing features, limitations and restrictions (“caveats”), upgrade instructions, and related information. These release notes supplement the Cisco NAC Appliance documentation included with the distribution. Read these release notes carefully and refer to the upgrade instructions prior to installing the software.

- [Cisco NAC Appliance Releases, page 2](#)
- [System and Hardware Requirements, page 2](#)
- [Software Compatibility, page 11](#)
- [New and Changed Information, page 15](#)
- [Cisco NAC Appliance Supported AV/AS Products, page 19](#)
- [Caveats, page 21](#)
- [New Installation of Release 4.8, page 60](#)
- [Upgrading to Release 4.8, page 62](#)
- [Known Issues for Cisco NAC Appliance, page 81](#)
- [Troubleshooting, page 88](#)
- [Documentation Updates, page 93](#)
- [Obtaining Documentation and Submitting a Service Request, page 94](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Cisco NAC Appliance Releases

Cisco NAC Appliance Version	Availability
4.8 ED	July 26, 2010


Note

Cisco recommends you deploy Cisco NAC Appliance Release 4.8 in test network before deploying in a production network.

System and Hardware Requirements

This section describes the following:

- [Licensing](#)
- [Hardware Support](#)
- [Supported Switches for Cisco NAC Appliance](#)
- [VPN and Wireless Components Supported for Single Sign-On \(SSO\)](#)
- [Additional Support Information](#)

Licensing

You must obtain and install Cisco NAC Appliance product licenses for the Clean Access Manager (CAM) and Clean Access Server (CAS) in order for your deployment to function. Install the CAM product license in the CAM License Form to initially access the CAM web admin console. Once you can access the CAM web console, upload the additional CAM HA license or CAS license(s) into the CAM (under **Administration > CCA Manager > Licensing**) in order to add CASs to the CAM. An OOB CAS license must be present to access the “OOB Management” module of the CAM. The **Licensing** page displays the types of licenses present after they are added.

Note that both CAM and CAS product licenses are generated based on the eth0 MAC address of the CAM. For High Availability (HA) pairs, you must generate an additional CAM HA license based on the eth0 MAC addresses of both Primary and Secondary CAMs and install it on the CAM whether you are adding a CAM HA pair or CAS HA pair.

For complete details on service contract support, obtaining new and evaluation licenses, legacy licenses and RMA, refer to [Cisco NAC Appliance Service Contract / Licensing Support](#).

Hardware Support

This section contains the following topics:

- [Release 4.8 and Hardware Platform Support](#)
- [Release 4.8 and Cisco NAC Profiler](#)
- [Supported Switches for Cisco NAC Appliance](#)

Release 4.8 and Hardware Platform Support

FIPS Compliant

You can install or upgrade to Cisco NAC Appliance Release 4.8 on the following FIPS-compliant Cisco NAC Appliance platforms:

- NAC-3315, NAC-3355, and NAC-3395



Note

Release 4.8 and 4.7(0) are the only certified FIPS-compliant Cisco NAC Appliance releases.

Non-FIPS

You can install or upgrade to Cisco NAC Appliance Release 4.8 on the following Cisco NAC Appliance platforms:

- NAC-3315, NAC-3355, and NAC-3395
- CCA-3140 (EOL), NAC-3310, NAC-3350, NAC-3390



Note

Next generation Cisco NAC Appliance platforms (FIPS or non-FIPS Cisco NAC-3315, NAC-3355, NAC-3395) support fresh installation of Release 4.8 or upgrade from Release 4.7(0), 4.7(1), or 4.7(2) to Release 4.8 only.

Due to limited hardware resources on the CCA-3140, some combinations of Release 4.8 features may cause undesirable system behavior. If you are experiencing problems with Release 4.8 on the CCA-3140, please contact the Cisco Technical Assistance Center (TAC).

- If the FIPS card in a CAM/CAS ceases to work correctly, make sure the card operation switch is set to “O” (for operational mode), as described in [FIPS and SSH, page 8](#). If the card is still not operational, you will need to RMA the appliance with Cisco Systems and replace it with a new Cisco NAC-3315/3355/3395 platform. Refer to the “[Cisco NAC Appliance RMA and Licensing](#)” section of [Cisco NAC Appliance Service Contract/Licensing Support](#) for details.

NME-NAC-K9

- See [Cisco NAC Network Module, page 4](#)

Additionally, Cisco NAC Appliance Release 4.8 provides substantial changes and enhancements for product hardware support, installation, and upgrade:

- A single product installation CD (.ISO) provides the option to perform CD installation on all supported appliance platforms. The installation package detects whether a CAS, CAM or SuperCAM was previously installed along with the software version.
- To upgrade your CAM and CAS from Release 4.6(1), or 4.7(x), insert the same Cisco NAC Appliance Release 4.8 installation CD-ROM (.ISO) into an existing Cisco NAC Appliance CAM or CAS and perform a “clean” or “graceful” shutdown and reboot for the system. The upgrade option from the CD-ROM automatically prompts you to choose whether you want to do a fresh Install or Upgrade to Release 4.8. For more information, see [Upgrading to Release 4.8, page 62](#) and [Known Issues with Web Upgrade in Release 4.1\(3\), 4.1\(6\), and 4.1\(8\), page 84](#).
- The installation/upgrade CD does not execute if attempting to launch it on a non-supported platform. Refer to [Changes for 4.8 Upgrade, page 65](#) for additional details.

- Legacy customers on non-appliance platforms who wish to upgrade to Release 4.8 will need to purchase a supported platform to install the Release 4.8 software. Refer to [Migrating from Customer-Supplied Hardware to Release 4.8 on a NAC-3310/3350/3390 Platform, page 63](#) for additional details.

See also [Features Optimized/Removed in Release 4.8, page 19](#) for additional information.

**Note**

You must run the same software version on all CAM/CAS appliances in your network.

Cisco NAC Network Module

The Cisco NAC Network Module for Integrated Services Routers (NME-NAC-K9) is a next generation service module for the Cisco 2811, 2821, 2851, 3825, and 3845 Integrated Services Routers (ISRs) that is supported starting from Cisco NAC Appliance, Release 4.1(2) and later.

In addition to the Cisco 2811, 2821, 2851, 3825, and 3845 Integrated Services Routers (ISRs), Cisco NAC Appliance Release 4.8 supports Cisco 2911, 2921, 2951, 3925, and 3945 Integrated Services Routers (ISRs).

The Cisco NAC network module has the same software features as the Clean Access Server on a NAC-3300 series appliance, with the exception of high availability. NME-NAC-K9 does not support failover from one module to another.

**Note**

NME-NAC-K9 supports fresh installation of Cisco NAC Appliance Release 4.8 or upgrade from Release 4.6(1) to Release 4.8 only.

**Note**

Cisco NAC Network Module does not support Wireless Out-of-Band (OOB). The Wireless OOB feature introduced in Release 4.5 only supports Layer 2 OOB Virtual Gateway deployments that require no IP change. The NAC Network Module does not support this topology.

For further details, including software installation instructions, refer to [Getting Started with Cisco NAC Network Modules in Cisco Access Routers](#).

**Note**

You must run the same software version (e.g. 4.8) on all CAM/CAS appliances and CAS network modules in your network.

Release 4.8 and Cisco NAC Profiler

All Cisco NAC Appliance releases are shipped with a default version of the Cisco NAC Profiler Collector component. Cisco NAC Appliance 4.8 release is shipped with Collector version 3.1.0.24 by default. When upgrading the NAC Server to a newer Cisco NAC Appliance release, the current version of the Collector is replaced with the default version of the Collector shipped with the Cisco NAC Appliance release. For example, if you are running Release 4.7(2) and Collector 3.1.1, and you upgrade to NAC 4.8, the Collector version will be downgraded to 3.1.0.24. You need to manually upgrade the 3.1.0.24 Collector to 3.1.1 again and configure it after the NAC Server upgrade.

Refer to the [Release Notes for Cisco NAC Profiler](#) for software compatibility matrixes and additional upgrade and product information.

**Note**

Cisco NAC Profiler and Cisco NAC Guest Server are not supported in FIPS-compliant deployments in Release 4.7(0) and Release 4.8.

FIPS 140-2 Compliance

**Note**

Release 4.8 and 4.7(0) are the only certified FIPS-compliant Cisco NAC Appliance releases.

This section describes the following topics:

- [Overview, page 5](#)
- [Capabilities, Dependencies, and Restrictions, page 6](#)
- [FIPS Compliance in HA Deployments, page 7](#)
- [Trusted Certificates and Private Key Management with FIPS, page 8](#)
- [FIPS and SSH, page 8](#)
- [FIPS and the Cisco NAC Appliance SWISS Protocol, page 8](#)
- [IPSec Considerations with FIPS, page 9](#)
- [FIPS and SNMP Configuration, page 9](#)
- [FIPS and Cisco Secure ACS as RADIUS Authentication Provider, page 9](#)
- [FIPS with VPN SSO, page 9](#)
- [FIPS with AD SSO, page 9](#)

Overview

Cisco NAC Appliance Release 4.7(0) introduced Federal Information Processing Standard (FIPS) 140-2 Common Criteria EAL2 compliance for new installations on new Cisco NAC-3315, NAC-3355, and NAC-3395 hardware appliance platforms. Release 4.8 now also offers a field-replaceable FIPS card upgrade for Cisco NAC-3310, NAC-3350, and NAC-3390 platforms. In order to provide FIPS compliance in your Cisco NAC Appliance network, both CAM(s) and CAS(s) must be FIPS compliant.

**Note**

Cisco NAC Profiler and Cisco NAC Guest Server are not supported in FIPS-compliant deployments in Release 4.7(0) and Release 4.8.

To enable FIPS 140-2 compliance in Cisco NAC Appliance, CAMs and CASs must have an encryption card that handles the primary FIPS “level 2” compliance functions and manages private keys for the system.

In Release 4.8 and 4.7(0), if the FIPS card in a Cisco NAC-3315/3355/3395 CAM/CAS ceases to work correctly, make sure the card operation switch is set to “O” (for operational mode), as described in [FIPS and SSH, page 8](#). If the card is still not operational, you will need to RMA the appliance with Cisco Systems and replace it with a new Cisco NAC-3315/3355/3395 platform. Refer to the “[Cisco NAC Appliance RMA and Licensing](#)” section of *Cisco NAC Appliance Service Contract/Licensing Support* for details. When you configure the replacement appliance, you must also ensure you configure it with the same master password and have imported any required third-party certificates before connecting the appliance to the network. For more information, see [Release 4.8 and Hardware Platform Support, page 3](#).

**Note**

Once the FIPS card is Operational on the CAM/CAS, the position of the electromagnetic switch (“O,” “M,” or “I”) on the FIPS card does not impact the performance of the card again until you reboot either the FIPS card or the appliance.

In addition, in order to ensure FIPS compliance across the entire Cisco NAC Appliance network, users must use the latest Cisco NAC Agent version 4.8.0.35 or 4.7.1.15 on client machines connecting to the Cisco NAC Appliance network. Although Cisco NAC Appliance Releases 4.8 and 4.7(0) support other Cisco NAC Appliance Agent versions, users logging in with a different version of the Agent are not FIPS compliant. For more information on the latest Cisco NAC Agent, see [Cisco NAC Windows Agent Version 4.8.0.35](#), page 19.

**Note**

Cisco NAC Appliance network administrators managing the CAM/CAS via web console *and* client machine browsers accessing a FIPS-compliant Cisco NAC Appliance Releases 4.8 and 4.7(0) network require TLSv1 in order to “talk” to the network, which is disabled by default in Microsoft Internet Explorer Version 6. This option is enabled by default in Microsoft Internet Explorer versions 7 and 8 and Mozilla Firefox has not shown this limitation. For details, see [Enabling TLSv1 on Internet Explorer Version 6](#), page 88.

Capabilities, Dependencies, and Restrictions

FIPS 140-2 compliance in Release 4.7(0) introduced the following capabilities, dependencies, and restrictions:

1. Key management in Release 4.7(0) and Release 4.8 is different than in non-FIPS Releases. Both CAM and CAS store their private keys in the FIPS card. This private key is used for all Cisco NAC Appliance PKI-based security solutions (i.e. SSL, SSH, and IPSec). In addition, both the CAM and CAS store a master secret in the card. The master secret is used to secure important data, (like other system passwords) stored in the database or on file systems. For more information, see [Trusted Certificates and Private Key Management with FIPS](#), page 8.
2. JSSE (the equivalent of OpenSSL in Java) is used:
 - a. On the CAM and CAS during JMX publishing
 - b. On the CAS to send HTTP requests to the CAM when users are logging in
 - c. On the CAM when using LDAP over SSL for authentication/lookup providers

**Note**

JSSE uses the FIPS card for SSL handshakes and data security.

3. APACHE/MOD_SSL handles HTTP/HTTPS requests from:
 - a. User client machines to the CAS
 - b. Administrators when using both the CAM and CAS web consoles
 - c. The CAS to the CAM when users are logging in

**Note**

MOD_SSL uses the FIPS card during SSL handshakes only. That is, data security is performed outside of the card.

4. IPsec secures:
 - a. CAM and CAS HA configurations
 - b. RADIUS authentication calls
 - c. VPN establishment and maintenance tasks



Note IPsec uses the FIPS card for handshakes only. That is, data security is performed outside of the card.

For more information, see [IPsec Considerations with FIPS, page 9](#).

5. SSH—Just like APACHE and IPsec, SSH uses the FIPS card during SSL handshakes only. For more information, see [FIPS and SSH, page 8](#).



Note When a FIPS card goes down, existing SSH web sessions still work; however, you cannot initiate any new sessions. You are also unable to initiate new SSH sessions if the FIPS card goes into error mode and/or has been erroneously left in Initialization state. In this case, the CAM/CAS console port is the only access method.

6. JGSS—JGSS is used for Kerberos and ADSSO. JGSS uses the FIPS card for securing data.
7. SNMP V3—SNMP V3 uses the FIPS card for securing data. For more information, see [FIPS and SNMP Configuration, page 9](#).
8. SWISS—SWISS uses the FIPS card for securing data. For more information, see [FIPS and the Cisco NAC Appliance SWISS Protocol, page 8](#).
9. Cisco WLCs support RADIUS accounting over IPsec using pre-shared-keys (which are not FIPS compliant) for IKE authentication, and do not support Certificate-based IKE authentication (which *is* FIPS compliant).
10. When AD SSO is configured in the network, Windows XP client machines are not FIPS 140-2 compliant due to XP limitations. You cannot use AES for XP Kerberos, and 3DES encryption is not supported on Windows XP client machines.



Note Windows 2008 Server and the Windows Vista or Windows 7 operating systems are required to support AD SSO in a FIPS-compliant Cisco NAC Appliance deployment.

11. LDAP—You must use Windows 2008 when performing LDAP lookups using GSSAPI in a FIPS 140-2 compliant deployment.
12. NTP server authentication—The CAM and CAS both use MD5 authentication to verify and authenticate Network Time Protocol (NTP) servers in Cisco NAC Appliance Release 4.8. MD5 is not a FIPS 140-2 compliant protocol, therefore you must disable the NTP authentication feature in Cisco NAC Appliance to ensure your network remains FIPS compliant.

FIPS Compliance in HA Deployments

To support FIPS 140-2 compliance, HA CAMs/CASs automatically establish an IPsec tunnel to ensure all communications between the HA pair appliances remains secure across the network.

Trusted Certificates and Private Key Management with FIPS

In Cisco NAC Appliance Release 4.7(0) and Release 4.8, you can no longer export private keys and you cannot generate CSRs using a FIPS compliant CAM/CAS. To adhere to strict FIPS compliance guidelines, you can only import certificates from trusted third-party resources.

Cisco NAC Appliance uses two types of keys to support FIPS compliance: Private Keys and Shared Master Keys. Both of these key types are managed and stored using the FIPS card installed in the CAM/CAS. During installation, keys are created using the CAM/CAS setup utilities, the keys are then *moved* to the card for security, and key-generation files and/or directories are then removed from the CAM/CAS.

This enhancement affects the following pages of the CAM web console:

- **Administration > Clean Access Manager > SSL > x509 Certificate**
- **Administration > Clean Access Manager > SSL > Trusted Certificate Authorities**
- **Administration > Clean Access Manager > SSL > x509 Certification Request**

FIPS and SSH

SSH connections between FIPS and non-FIPS CAMs/CASs are supported in Cisco NAC Appliance Release 4.7(0) or Release 4.8. However, if the FIPS card in a CAM/CAS fails (or is inadvertently set to the incorrect operational mode), you cannot use SSH to or from that appliance until the issue with the card is resolved.

You can verify FIPS functionality on a CAM/CAS as follows:

- Ensure the FIPS card operation switch is set to “O” (for operational mode).
- Log into the CAM console interface as `root`.
- Navigate to the `/perfigo/common/bin/` directory.
- Enter `./test_fips.sh info` and verify the following output:

```
Installed FIPS card is nCipher
Info-FIPS file exists
Info-card is in operational mode
Info-httpd worker is in FIPS mode
Info-sshd up
```



Note

You can also verify whether or not the FIPS card is properly installed and enabled in the Clean Access Manager by looking at the CAM **Monitoring > Summary** web console page. When FIPS is operational, the following status is displayed:

Installed card in the system: nCipher
System is running in FIPS mode

FIPS and the Cisco NAC Appliance SWISS Protocol

To enhance network security and adhere to FIPS 140-2 compliance, Cisco NAC Appliance encapsulates SWISS communications between client machines and CASs, including Discovery Packet transmission/acknowledgement, authentication, and posture assessment results using the HTTPS protocol.

In addition, the CAS SWISS mechanism has been enhanced to feature a new handler that uses 3DES encryption for SWISS protocol functions. Because of these changes, older versions of Cisco NAC Appliance Agents are not compatible with FIPS-compliant CAMs/CASs in Releases 4.8 and 4.7(0).

IPSec Considerations with FIPS

Cisco NAC Appliance Releases 4.8 and 4.7(0) use IPSec for the following purposes:

- CAM and CAS HA pairs (both FIPS and non-FIPS modes)
- CAS file synchronization between HA-Primary and HA-Secondary nodes
- CAM and CAS RADIUS server authentication calls in FIPS mode
- ASA (Adaptive Security Appliance)-CAS in FIPS mode

When setting up your Cisco NAC Appliance to use IPSec, you must ensure you can set up and import certificates and configure IPSec tunnels between Cisco NAC Appliance and your external authentication resources.

For Active Directory, LDAP, and Kerberos functions with FIPS-compliant CAMs/CASs, you must ensure that hosts are running Windows 2008 Server to support secure authentication sessions between external resources and FIPS-compliant appliances.

FIPS and SNMP Configuration

Cisco NAC Appliance Release 4.7(0) and Release 4.8 provide support for SHA-1 and 3DES encryption when configuring SNMP management on a FIPS-compliant CAM.

This enhancement affects the following page of the CAM web console:

- **OOB Management > Profiles > SNMP Receiver > SNMP Trap**

FIPS and Cisco Secure ACS as RADIUS Authentication Provider

You can configure a FIPS 140-2 compliant external RADIUS Authentication Provider type by setting up a secure IPSec tunnel between your Cisco NAC Appliance system and Cisco ACS 4.x in a Windows environment running Windows Server 2003 or 2008.

For specific configuration instructions, see “Add a FIPS 140-2 Compliant RADIUS Auth Provider Using an ACS Server” section of the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#).

FIPS with VPN SSO

You can configure Cisco NAC Appliance to connect to and manage a Cisco ASA VPN Concentrator in a FIPS 140-2 compliant deployment.

For specific configuration instructions, see the “Configure VPN SSO in a FIPS 140-2 Compliant Deployment” section of the [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

FIPS with AD SSO

To maintain FIPS 140-2 compliance and support AD SSO, you *must* use 32-bit Windows Server 2008 with KTPass version 6.0.6001.18000, and client machines must run Windows Vista or Windows 7 with Cisco NAC Agent version 4.7.1.15 or version 4.8.0.35 installed. For specific configuration instructions, see the “Configure Active Directory for FIPS 140-2 Compliant AD SSO” section of the [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

You cannot perform AD SSO in a FIPS-compliant network using Cisco Wireless LAN Controllers because the WLCs do not support IPSec communication with the Cisco NAC Appliance network, so you cannot provide RADIUS SSO capability to users in your FIPS 140-2 compliant environment.

Supported Switches for Cisco NAC Appliance

See [Switch Support for Cisco NAC Appliance](#) for complete details on:

- Cisco switch models and Wireless LAN Controllers supported in a Cisco NAC Appliance Wireless OOB environment
- All switch models and NME service modules that support Out-of-Band (OOB) deployment
- Switches/NMEs that support VGW VLAN mapping
- Known issues with switches/WLCs
- Troubleshooting information

VPN and Wireless Components Supported for Single Sign-On (SSO)

[Table 1](#) lists VPN and wireless components supported for Single Sign-On (SSO) with Cisco NAC Appliance. Elements in the same row are compatible with each other.

Table 1 VPN and Wireless Components Supported By Cisco NAC Appliance For SSO

Cisco NAC Appliance Version	VPN Concentrator/Wireless Controller	VPN Clients
4.5 and later	Cisco WiSM Wireless Service Module for the Cisco Catalyst 6500 Series Switches	N/A
	Cisco 2200/4400 Wireless LAN Controllers (Airespace WLCs) ¹	N/A
	Cisco ASA 5500 Series Adaptive Security Appliances, Version 8.0(3)7 or later ²	AnyConnect
	Cisco ASA 5500 Series Adaptive Security Appliances, Version 8.0(3)7 or later	<ul style="list-style-type: none"> • Cisco SSL VPN Client (Full Tunnel)
	Cisco WebVPN Service Modules for Cisco Catalyst 6500 Series Switches and Cisco 7600 Series Routers	<ul style="list-style-type: none"> • Cisco VPN Client (IPSec)
	Cisco VPN 3000 Series Concentrators, Release 4.7	
	Cisco PIX Firewall	

1. For additional details, see also [Known Issues with Cisco 2200/4400 Wireless LAN Controllers \(Airespace WLCs\)](#), page 86.
2. Release 4.5 and later supports existing AnyConnect clients accessing the network via Cisco ASA 5500 Series devices running release 8.0(3)7 or later. For more information, see the [Release Notes for Cisco NAC Appliance, Version 4.1\(3\)](#), and [CSCsi75507](#).



Note

Only the SSL Tunnel Client mode of the Cisco WebVPN Services Module is currently supported.

Cisco WLCs do not support IPSec communication with the Cisco NAC Appliance network, so you cannot provide RADIUS SSO capability to users in your FIPS 140-2 compliant environment.

For further details, see the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#) and the [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

Additional Support Information

Refer to [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#) for additional details related to Windows/Mac OS X/Web Agent support.

Refer to [Supported Hardware and System Requirements for Cisco NAC Appliance](#) for additional information on Cisco NAC Appliance hardware platforms and support information for Cisco NAC Appliance 4.1(x) and earlier releases.

Software Compatibility

This section describes software compatibility for releases of Cisco NAC Appliance:

- [Release 4.8 CAM/CAS Upgrade Compatibility Matrix](#)
- [Release 4.8 CAM/CAS/Agent Compatibility Matrix](#)
- [Release 4.8 Agent Upgrade Compatibility Matrix](#)

Release 4.8 CAM/CAS Upgrade Compatibility Matrix

[Table 2](#) shows CAM/CAS upgrade compatibility. You can upgrade/migrate your CAM/CAS from the previous release(s) specified to the latest release shown in the same row. When you upgrade your system software, Cisco recommends you upgrade to the most current release available whenever possible.

Table 2 Release 4.8 CAM/CAS Upgrade Compatibility Matrix

Clean Access Manager ^{1,2}		Clean Access Server ^{1,2,3}	
Upgrade From:	To:	Upgrade From:	To:
4.7(2)	4.8	4.7(2)	4.8
4.7(1)		4.7(1)	
4.7(0)		4.7(0)	
4.6(1)		4.6(1)	

1. Next generation Cisco NAC Appliance platforms (FIPS or non-FIPS Cisco NAC-3315, NAC-3355, NAC-3395) support fresh installation of Release 4.8 or upgrade from Release 4.7(0), 4.7(1), or 4.7(2) to Release 4.8 only. You can also install or upgrade to Release 4.8 on the NAC-3310, NAC-3350, NAC-3390, and CCA-3140 (EOL) platforms, but they operate in non-FIPS mode only. See [Hardware Support, page 2](#) and [Changes for 4.8 Upgrade, page 65](#) for additional details.
2. You cannot upgrade your Cisco NAC Appliance deployment from maintenance Release 4.7(3) to Release 4.8 directly. Refer to caveat [CSCtj02066, page 54](#) for more information.
3. The Clean Access Server is shipped with a default version of the Cisco NAC Profiler Collector. See [Release 4.8 and Cisco NAC Profiler, page 4](#) for details.

Release 4.8 CAM/CAS/Agent Compatibility Matrix

[Table 3](#) lists Cisco NAC Appliance Manager/Server/Agent compatibility per supported release. CAM/CAS/Agent versions displayed in the same row are compatible with one another. Cisco recommends that you synchronize your software images to match those shown as compatible in [Table 3](#).

For complete support information, including specific client machine operating systems supported with specific Agent versions, refer to the [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#).

Table 3 Release 4.8 CAM/CAS/Agent Compatibility Matrix

Clean Access Manager ^{1,2}	Clean Access Server ^{1,2}	Cisco NAC Appliance Agents ³		
		Windows	Mac OS X	Web Agent
FIPS 140-2 Compliant ⁴				
4.8 4.7(0)	4.8 4.7(0)	4.8.0.35 4.7.1.15	N/A	N/A
English-Only Server		English-Only Agent		
4.8 ⁵	4.8	4.8.0.35 4.7.2.10 4.7.1.511 4.7.1.15 4.6.2.113	4.8.0.569 4.7.2.507 4.7.1.506 4.7.0.2 4.6.0.3	4.8.0.4
4.7(2)	4.7(2)	4.7.2.10 4.7.1.511 4.7.1.15 4.6.2.113 4.5.2.0 ⁶ 4.5.1.0 4.5.0.0 4.1.8.0 ⁷ 4.1.6.0 4.1.3.2	4.7.2.507 4.7.1.506 4.7.0.2 4.6.0.3 4.5.0.0 ⁷	4.7.2.5
4.7(1) ⁷	4.7(1)	4.7.2.10 4.7.1.511 4.7.1.15 4.6.2.113 4.5.2.0 ⁴ 4.5.1.0 4.5.0.0 4.1.8.0 ⁷ 4.1.6.0 4.1.3.2	4.7.2.507 4.7.1.506 4.7.0.2 4.6.0.3 4.5.0.0 ⁷ 4.1.3.0 ⁷	4.7.1.504 ⁸
4.7(0)	4.7(0)	4.7.2.10 4.7.1.511 4.7.1.15 4.6.2.113 4.5.2.0 ⁷ 4.5.1.0 4.5.0.0 4.1.8.0 ⁷ 4.1.6.0 4.1.3.2	4.7.2.507 4.7.1.506 4.7.0.2 4.6.0.3 4.5.0.0 ⁷ 4.1.3.0 ⁷	4.7.0

Table 3 Release 4.8 CAM/CAS/Agent Compatibility Matrix (continued)

Clean Access Manager ^{1,2}	Clean Access Server ^{1,2}	Cisco NAC Appliance Agents ³		
		Windows	Mac OS X	Web Agent
English-Only Server		English-Only Agent		
4.6(1)	4.6(1)	4.7.2.10 4.7.1.511 4.7.1.15 ^{9,10}	4.7.2.507 4.7.1.506 4.7.0.2	N/A
		4.6.2.113	4.6.0.3	

- Next generation Cisco NAC Appliance platforms (FIPS or non-FIPS Cisco NAC-3315, NAC-3355, NAC-3395) support fresh installation of Release 4.8 or upgrade from Release 4.7(0), 4.7(1), or 4.7(2) to Release 4.8 only. You can also install or upgrade to Release 4.8 on the NAC-3310, NAC-3350, NAC-3390, and CCA-3140 (EOL) platforms, but they operate in non-FIPS mode only. See [Hardware Support, page 2](#) and [Changes for 4.8 Upgrade, page 65](#) for additional details.
- Make sure that both CAM and CAS are of same version.
- See [Enhancements in Release 4.8, page 15](#) for details on each version of the Windows/Mac OS X/Web Agents.
- Release 4.8 and 4.7(0) are the only certified FIPS-compliant Cisco NAC Appliance releases.
- When upgrading the CAM from version 4.1(3) and later to Release 4.8, Agent files are automatically upgraded to the latest Agent version packaged with the CAM software image (e.g. Windows version 4.8.0.35 and Mac OS X version 4.8.0.569).
- CAM/CAS Release 4.8 and 4.7(x) support 4.1.3.2 and later Agents for basic compatibility (login/logout) and AV/AS product support. The maximum available AV/AS support is based on the maximum version of the Agent file uploaded to the CAM as well as the maximum version of the Agent on the client. See [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#) for details. For full 4.5 and later features (including Mac OS X posture assessment), the 4.5.0.0 or later Agent must be run with the appropriate 4.5 or later CAM/CAS.
- When upgrading the CAM from version 4.5(x) and later to Release 4.8, Agent files are automatically upgraded to the latest Agent version packaged with the CAM software image (e.g. Windows version 4.7.1.511 and Mac OS X version 4.7.1.506).
- Cisco NAC Web Agent version 4.7.1.504 does not support Windows 7 Starter Edition. Client machines with the Windows 7 Starter Edition operating system can only perform web login to verify user credentials when accessing the network via Cisco NAC Appliance Release 4.7(1). For specific information on enabling web login for client machines running Windows 7 Starter Edition, see [Known Issue with Enabling Web Login for Windows 7 Starter Edition Clients, page 83](#).
- 4.6.x.x and 4.7.1.x Windows Agents and 4.6.x.x and 4.7.x.y Mac OS X Agents are supported on 4.1(3) and later CAM/CAS releases for basic compatibility (login/logout) and AV/AS product support. The maximum available AV/AS support is based on the maximum version of the Agent file uploaded to the CAM as well as the maximum version of the Agent on the client. See [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#) for details. For full 4.5 and later features (including Mac OS X posture assessment), the 4.5.0.0 or later Agent must be run with the appropriate 4.5 or later CAM/CAS.
- If you only upgrade to the latest version of the Cisco NAC Agent, and leave your CAM/CAS at Release 4.5(1) or earlier, the Agent operates as an English-only entity—you cannot take advantage of the native operating system localization support available to Cisco NAC Agent users who are logging in to a 4.7(x) CAM/CAS network.

Release 4.8 Agent Upgrade Compatibility Matrix

Table 4 shows Cisco NAC Appliance Agent upgrade compatibility when upgrading existing versions of the persistent Agents on clients after CAM/CAS upgrade.



Note

Auto-upgrade does not apply to the temporal Cisco NAC Web Agent, since it is updated on the CAM under **Device Management > Clean Access > Updates > Update**.

For complete support information, including specific client machine operating systems supported with specific Agent versions, refer to the [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#).

Table 4 Release 4.8 Agent Upgrade Compatibility Matrix

Clean Access Manager ¹	Clean Access Server ¹	Cisco NAC Appliance Agent ²			
		Upgrade From Cisco NAC Windows Agent:	To Latest Compatible Cisco NAC Windows Agent:	Upgrade From Cisco Mac OS X Agent	To Latest Compatible Mac OS X Agent
4.8	4.8	4.7.2.10 ^{3,4} 4.7.1.511 ^{3, 4} 4.7.1.15 ⁵ 4.6.2.113	4.8.0.35 ^{3,4}	4.7.2.507 4.7.1.506 4.7.0.2 4.6.0.3	4.8.0.569

1. Next generation Cisco NAC Appliance platforms (FIPS or non-FIPS Cisco NAC-3315, NAC-3355, NAC-3395) support fresh installation of Release 4.8 or upgrade from Release 4.7(0), 4.7(1), or 4.7(2) to Release 4.8 only. You can also install or upgrade to Release 4.8 on the NAC-3310, NAC-3350, NAC-3390, and CCA-3140 (EOL) platforms, but they operate in non-FIPS mode only. See [Hardware Support, page 2](#) and [Changes for 4.8 Upgrade, page 65](#) for additional details.
2. See [Enhancements in Release 4.8, page 15](#) for details on each version of the Windows/Mac OS X/Web Agent.
3. Cisco NAC Agent versions 4.7.1.511, 4.7.2.10, and 4.8.0.35 are the only Cisco NAC Appliance Agents that support Windows 7 operating systems. (Cisco NAC Agent version 4.7.1.511 does not support the Windows 7 Starter Edition operating system.)
4. For checks/rules/requirements, version 4.1.1.0 and later Windows Agents can detect “N” (European) versions of the Windows Vista operating system, but the CAM/CAS treat “N” versions of Vista as their US counterpart.
5. To remain FIPS-compliant, users logging into Cisco NAC Appliance via AD SSO must run Windows Vista or Windows 7 and have Cisco NAC Agent version 4.7.1.15 or 4.8.0.35 installed on their client machine. Windows XP clients cannot perform AD SSO in a FIPS 140-2 compliant network. See [FIPS with AD SSO, page 9](#) for details.

Determining the Software Version

Clean Access Manager (CAM) Version

- SSH or console to the machine and type: `cat /perfigo/build`
- CAM web console: **Administration > CCA Manager > Software Upload | Current Version**

Clean Access Server (CAS) Version

- SSH or console to the machine and type `cat /perfigo/build`
- CAS web console (https://<CAS_eth0_IP_address>/admin): **Administration > Software Upload | Current Version**
- CAM web console: **Device Management > CCA Servers > List of Servers > Manage [CAS_IP] > Misc > Upgrade Logs | Current Version**

Cisco NAC Appliance Agent Version (Windows, Mac OS X, Web Agent)

- CAM web console: **Monitoring > Summary**
- Agent taskbar menu: right-click **About** for Agent version; right-click **Properties** for AV/AS software installed and Discovery Host (used for L3 deployments).

Cisco Clean Access Updates

- CAM web console: **Device Management > Clean Access > Updates > Summary**

New and Changed Information

This section describes enhancements added to the following releases of Cisco NAC Appliance for the Clean Access Manager and Clean Access Server.

Enhancements in Release 4.8

- [Support for Cisco NME-NAC Platforms, page 15](#)
- [Administrator Access Restriction, page 15](#)
- [Out-of-Band Logoff, page 16](#)
- [In-Band and Out-of-Band Filter Behavior Enhancements, page 16](#)
- [Compliance Module, page 16](#)
- [RADIUS Session Timeout, page 17](#)
- [Passive Re-assessment, page 17](#)
- [Reporting Enhancements, page 17](#)
- [Agent Customization, page 18](#)
- [Agent Authorizes CAS, page 18](#)
- [Field-Replaceable FIPS Card for HP-Based Cisco NAC Appliances, page 18](#)
- [Cisco NAC Windows Agent Version 4.8.0.35, page 19](#)
- [Mac OS X Agent Version 4.8.0.569, page 19](#)
- [Cisco NAC Web Agent Version 4.8.0.4, page 19](#)
- [Features Optimized/Removed in Release 4.8, page 19](#)
- [Supported AV/AS Product List Enhancements \(Windows Version 83, Mac OS X Version 7\), page 19](#)

Support for Cisco NME-NAC Platforms

Cisco NAC Appliance Release 4.8 supports Cisco NAC Network Module (NME-NAC-K9) platforms. NME-NAC-K9 supports fresh installation of Cisco NAC Appliance Release 4.8 or upgrade from Release 4.6(1) to Release 4.8 only.

In addition to the Cisco 2811, 2821, 2851, 3825, and 3845 Integrated Services Routers (ISRs), Cisco NAC Appliance Release 4.8 supports Cisco 2911, 2921, 2951, 3925, and 3945 Integrated Services Routers (ISRs).

See [Cisco NAC Network Module, page 4](#) for more information.

Administrator Access Restriction

Cisco NAC Appliance Release 4.8 enables the admin users to block access to CAM and CAS web console for a set of configured IP Addresses. The information of IP addresses to be blocked are published by the CAM to the CAS connected to the CAM. If the CAS is not connected to the CAM, then the CAS cannot be restricted to block access.

This feature affects the following page in the CAM web console:

- **Administration > Admin Users > new Access Restrictions.**

Out-of-Band Logoff

In Cisco NAC Appliance Release 4.8, client session management has been enhanced to ensure that users who log off of their client machines in an Out-of-Band deployment are promptly removed from the Out-of-Band Online Users list when their respective client machines are simultaneously removed from the Certified Devices List.

In previous releases of Cisco NAC Appliance, scenarios could occur where Out-of-Band users would terminate their session or shut down (either deliberately or unintentionally) the client machine, thus removing the client machine from the Certified Devices List, but keeping the user “logged in” to Cisco NAC Appliance and present in the Out-of-Band Online Users list. This situation could potentially lead to a network security issue where the switch port through which the user is connecting to the network remains available for other client machines to sign on and gain access to the internal network without having to go through authentication and posture assessment.

This feature affects the following page in the CAM web console:

- **Device Management > Clean Access > General Setup > Agent Login**—new **Enable OOB logoff for Windows NAC Agent and Mac OS X Agent** option
- **Device Management > Clean Access > General Setup > Agent Login > Logoff NAC Agent users from network on their machine logoff or shutdown after <x> secs** affects OOB Logoff.
- **User Management > User Roles > Schedule > new OOB Heartbeat Timer** tab
- This feature has introduced a new parameter **EnableVlanDetectWithoutUI** in the **NACAgentCFG.xml** file

In-Band and Out-of-Band Filter Behavior Enhancements

In Cisco NAC Appliance Release 4.8, Cisco has improved Online Users list and Certified Devices List login status updates based on global vs. local device filter options. This enhancement is related to the improvements introduced in Release 4.8 for [Out-of-Band Logoff](#) enhancement.

Two basic recommendations stem from this enhancement:

- Cisco recommends always turning on the “Change VLAN according to global device filter list” option in the **OOB Management > Profiles > Port Profile** page for that particular switch port
- Cisco recommends that you do not configure any local (CAS-level) device filters for Out-of-Band deployments, as they would not serve any purpose beyond a global device filter option

Compliance Module

Cisco NAC Appliance Release 4.8 introduces the Compliance Module feature to help administrators keep client machines as up-to-date with imposed security policies as possible. Traditionally, administrators would need to wait for a new version of the Cisco NAC Agent and/or Mac OS X Agent to provide the most up-to-date AV/AS support for client machines logging into the network. Now, with the Compliance Module feature, the AV/AS support updates have been “decoupled” from the Agent package and can be made available to users’ client machines more frequently, thus providing greater support for up-to-date AV/AS vendor applications.

This feature affects the following page in the CAM web console:

- **Device Management > Clean Access > Clean Access Agent > Distribution**—new **Windows Compliance Module Current Version** field and three new options: **Current Compliance Module is a mandatory upgrade**, **Do not offer current Compliance Module to users for upgrade**, and **Allow downgrade of Compliance Module**
- **Device Management > Clean Access > Clean Access Agent > Rules > AV/AS Support Info**—Support tables now specify both the minimum Agent version and Compliance Module version for the specified vendor application
- **Device Management > Clean Access > Clean Access Agent > Reports**—Individual Agent report windows now specify the current Compliance Module version associated with the Agent in question.

Refer to [Downloading Compliance Module, page 20](#) for details on how to download the latest Compliance Module file.

RADIUS Session Timeout

Cisco NAC Appliance Release 4.8 features a RADIUS Session Timeout that is enabled when the RADIUS server is configured. Usually, the Session Timeout is set for a role. RADIUS Session Timeout occurs per user session, irrespective of the user role.

Passive Re-assessment

Cisco NAC Appliance Release 4.8 features the Passive Re-assessment client posture verification enhancement that allows you to periodically check to see that client machines remain compliant with imposed network security policies while users remain online and logged in to the network.

With earlier deployments of Cisco NAC Appliance, client machines would only be required to go through posture assessment during user login authentication. As a result, client machines that remained logged in to the Cisco NAC Appliance system for very long periods of time could actually become inadvertently non-compliant with imposed network security policies, thus posing a potential threat to the protected internal network until the next posture assessment (login) opportunity.

This feature affects the following pages in the CAM web console:

- **User Management > User Roles New/Edit Role**—new **Enable Passive Re-assessment** checkbox and three additional configuration options: **Re-assessment Interval**, **Grace Timer**, and **Default action on failure**
- **Device Management > Clean Access > Clean Access Agent > Role-Requirements**—new **Passive** check box to enable Passive Re-assessment for individual user roles
- **Device Management > Clean Access > Clean Access Agent > Reports > Report Viewer**—new column **Type** to indicate whether the report has been generated due to Login posture or Passive Re-assessment.



Note

Passive Re-assessment has been implemented for Cisco NAC Agent only.

Reporting Enhancements

In Cisco NAC Appliance Release 4.8, reports have been enhanced. The new Reporting tab can be used to enable/disable the reporting settings. Once enabled, the Reporting tab displays the current system information and preset reports.

This feature adds the following pages to the CAM web console:

- **Monitoring > Reporting**
- **Monitoring > Reporting > Settings**
- **Monitoring > Reporting > Current Status**
- **Monitoring > Reporting > Canned Reports**

Agent Customization

Cisco NAC Appliance Release 4.8 contains the new Agent Customization Settings. You can customize the NAC Agent UI on Windows client machines with Cisco NAC Agent that is compatible with CAM Release 4.8 installed.

This feature affects the following page in the CAM web console:

- **Device Management > Clean Access > Clean Access Agent > Installation**—new **Agent customization file upload** checkbox.

Agent Authorizes CAS

This feature enhancement has been implemented for Cisco NAC Appliance Release 4.8 as well as Release 4.7(2).

The Agent discovery process (where the persistent Agent on the client machine searches for a CAS through which the user can login via Cisco NAC Appliance) has been enhanced so that the Agent verifies the CAS via a combination of certificate, hostname, and domain name matching criteria before trusting the CAS and initiating the client login session.

This feature has introduced a new parameter **ServerNameRules** in the **NACAgentCFG.xml** file.

The Agent compares the CN (canonical name) in the certificate provided by the CAS/Agent SSL communication with the ServerNameRules parameters in the NACAgentCFG.xml file. The CN contains information like host name and domain name. The Agent pops up only when these names match.

Refer to the “Specify Server Rule Names” table under the “Cisco NAC Agent XML Configuration File Settings” section in the *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8* for more information.

Field-Replaceable FIPS Card for HP-Based Cisco NAC Appliances

Cisco NAC Appliance Release 4.8 supports adding field-replaceable FIPS cards to existing HP-based CAMs/CASs to help support FIPS 140-2 compliant operations in your Cisco NAC Appliance deployment.

For more information and installation instructions, see the following resources:

- [FIPS 140-2 Compliance, page 5](#)
- [Cisco NAC Appliance FIPS Card Field-Replaceable Unit Installation Guide](#)
- [Cisco NAC Appliance Hardware Installation Guide, Release 4.8](#)
- [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#)
- [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#)

Cisco NAC Windows Agent Version 4.8.0.35

Cisco NAC Appliance Release 4.8 introduces Cisco NAC Agent version 4.8.0.35.

Refer to [Release 4.8 CAM/CAS/Agent Compatibility Matrix, page 11](#) for additional compatibility details.

For details on Agent functionality, refer to the “Cisco NAC Appliance Agents” chapter of the *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8*.

Mac OS X Agent Version 4.8.0.569

Cisco NAC Appliance Release 4.8 introduces Mac OS X Agent version 4.8.0.569, which supports Out-of-Band Logoff feature. See [Out-of-Band Logoff, page 16](#) for details.

Cisco Mac OS X Agent version 4.8.0.569 provides updated AV/AS support capabilities on Macintosh client machines as described in [Cisco NAC Appliance Supported AV/AS Products, page 19](#).

Cisco NAC Web Agent Version 4.8.0.4

Cisco NAC Appliance Release 4.8 introduces Cisco NAC Web Agent version 4.8.0.4.

For details on Agent functionality, refer to the “Cisco NAC Appliance Agents” chapter of the *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8*.

Features Optimized/Removed in Release 4.8

In Cisco NAC Appliance release 4.8, you can now use a .tar.gz upgrade process similar to that used for upgrading CAM/CAS appliances in earlier releases of Cisco NAC Appliance (like the process used in Release 4.5(x), 4.6(1), and 4.7(2)) instead of having to perform “in-place” upgrades via an .ISO image on a CD-ROM, as is required to upgrade to Cisco NAC Appliance release 4.7(0) and 4.7(1). For more information, see [Upgrading to Release 4.8, page 62](#).



Note

You cannot use the Release 4.8 .ISO CD-ROM to perform an upgrade. You must use the .tar.gz upgrade file method.

Supported AV/AS Product List Enhancements (Windows Version 83, Mac OS X Version 7)

See [Cisco NAC Appliance Supported AV/AS Products, page 19](#) for the latest AV/AS product charts.

Cisco NAC Appliance Supported AV/AS Products

The Cisco NAC Appliance Supported AV/AS Product List is a versioned XML file distributed from a centralized update server and downloaded to the Clean Access Manager via **Device Management > Clean Access > Updates > Update**. It provides the most current matrix of supported antivirus (AV) and anti-spyware (AS) vendors and products per version of the Agent, and is used to populate AV/AS Rules and AV/AS Definition Update requirements for Agents that support posture assessment/remediation.

You can access AV and AS product support information from the CAM web console under **Device Management > Clean Access > Clean Access Agent > Rules > AV/AS Support Info**. For convenience, this section also provides the following summary and product charts. The charts list which product versions support virus or spyware definition checks and automatic update of client virus/spyware definition files via the user clicking the **Update** button on the Agent.

**Note**

In some cases, the specific AV/AS vendor software requires the user to have administrator privileges on the client machine to enable updates.

Windows 7/Vista/XP

For Windows 7/Vista/XP AV/AS support information on the Cisco NAC Agent (version 4.8.0.32) and Cisco NAC Web Agent (version 4.8.0.4), see the [Cisco NAC Appliance Release 4.8 Supported Windows AV/AS Products](#) document optimized for UTF-8 character display.

Mac OS X

For Mac OS X AV/AS support information on the Cisco Mac OS X Agent (version 4.8.0.569), see the [Cisco NAC Appliance Release 4.8 Supported Mac OS X AV/AS Products](#) document optimized for UTF-8 character display.

**Note**

Cisco recommends keeping your Supported AV/AS Product List up-to-date on your CAM (particularly if you have updated the Windows Agent Setup/Patch version or Mac OS Agent) by configuring the **Update Settings** under **Device Management > Clean Access > Updates > Update** to **Automatically check for updates starting from <x> every <y> hours**.

**Note**

Where possible, Cisco recommends using AV Rules mapped to AV Definition Update Requirements when checking antivirus software on clients, and AS Rules mapped to AS Definition Update Requirements when checking anti-spyware software on clients. In the case of non-supported AV or AS products, or if an AV/AS product/version is not available through AV Rules/AS Rules, administrators always have the option of creating their own custom checks, rules, and requirements for the AV/AS vendor (and/or using Cisco provided pc_checks and pr_rules) through **Device Management > Clean Access > Clean Access Agent** (use New Check, New Rule, and New File/Link/Local Check Requirement). See the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#) for configuration details.

Note that Clean Access works in tandem with the installation schemes and mechanisms provided by supported AV/AS vendors. In the case of unforeseen changes to underlying mechanisms for AV/AS products by vendors, the Cisco NAC Appliance team will update the Supported AV/AS Product List and/or Agent in the timeliest manner possible in order to support the new AV/AS product changes. In the meantime, administrators can always use the “custom” rule workaround for the AV/AS product (such as pc_checks/pr_rules) and configure the requirement for “Any selected rule succeeds.”

Downloading Compliance Module

Refer to [Compliance Module, page 16](#) for more details.

You can download the Compliance Module file as follows:

-
- Step 1** Log in to the Cisco Software Download Site at <http://www.cisco.com/public/sw-center/index.shtml>. You will likely be required to provide your CCO credentials.
- Step 2** Navigate to **Security > Endpoint Security > Cisco Network Access Control > Cisco NAC Appliance > Cisco NAC Appliance 4.8 > Network Admission Control (NAC) Compliance Module Software**.
- Step 3** Download the latest compliance module file (for example, **av-posture-pack-win-3.4.16.1.tar.gz**).
- Step 4** In the CAM web console, navigate to **Device Management > Clean Access > Clean Access Agent > Distribution**.
- Step 5** In the **Upload Agent/Compliance Module File** field, use the **Browse** button and navigate to the folder where the appropriate compliance module file is located. Select the file and click **Upload** to manually upload the Windows AV/AS Posture pack in this field.
-

Refer to the "Setting Up Agent Distribution/Installation" section in *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8* for more information on enabling the Compliance Module.

For Windows 7/Vista/XP, AV/AS support information on the Cisco NAC Agent (version 4.8.0.35), Cisco NAC Web Agent (version 4.8.0.4), and Compliance Module version 3.4.16.1, see the *Cisco NAC Appliance Release 4.8 Supported Windows AV/AS Products* document optimized for UTF-8 character display.

Refer to [Enhancements in Release 4.8, page 15](#) for additional details on Agent versions in this release.

Caveats

This section describes the following caveats:

- [Open Caveats - Release 4.8, page 22](#)
- [Resolved Caveats - Release 4.8, page 55](#)
- [Resolved Caveats - Cisco NAC Agent Vers 4.8.0.35/Mac OS X Vers 4.8.0.569, page 59](#)



Note

If you are a registered cisco.com user, you can view Bug Toolkit on cisco.com at the following website:
<http://www.cisco.com/cgi-bin/Support/Bugtool/home.pl>

To become a registered cisco.com user, go to the following website:
<http://tools.cisco.com/RPF/register/register.do>

Open Caveats - Release 4.8

Table 5 List of Open Caveats (Sheet 1 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsd03509	No	<p>The Time Servers setting is not updated in HA-Standby CAM web console</p> <p>After updating the “Time Servers” setting in HA-Primary CAM, the counterpart “Time Servers” setting for the HA-Standby CAM does not get updated in the web console even though the “Time Servers” setting is updated in the HA-Standby CAM database.</p> <p>Workaround Reboot the HA-Standby CAM or perform a HA-CAM failover to make the HA-Standby CAM become HA-Active.</p>
CSCsg07369	No	<p>Incorrect “IP lease total” displayed on editing manually created subnets</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Add a Managed Subnet having at least 2500+ IP addresses (for example 10.101.0.1/255.255.240.0) using CAM web page Device Management > Clean Access Servers > Manage [IP Address] > Advanced > Managed Subnet. 2. Create a DHCP subnet with 2500+ hosts using CAM web page Device Management > Clean Access Servers > Manage [IP Address] > Network > DHCP > Subnet List > New. 3. Edit the newly created subnet using CAM web page Device Management > Clean Access Servers > Manage [IP Address] > Network > DHCP > Subnet List > Edit. 4. Click Update. The CAM displays a warning informing the administrator that the current IP Range brings IP lease total up to a number that is incorrect. The CAM counts the IP address in the subnet twice, creating the incorrect count. <p>The issue is judged to be cosmetic and does not affect DHCP functionality.</p>
CSCsg66511	No	<p>Configuring HA-failover synchronization settings on Secondary CAS takes an extremely long time</p> <p>Once you have configured the Secondary CAS HA attributes and click Update, it can take around 3 minutes for the browser to get the response from the server. (Configuring HA-failover synchronization on the Primary CAS is nearly instantaneous.)</p>

Table 5 List of Open Caveats (Sheet 2 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsh77730	No	<p>Agent locks up when greyed out OK button is pressed</p> <p>The Agent locks up when the client machine refreshes its IP address. This only occurs when doing an IP release/renew, so the CAS must be in an OOB setup.</p> <p>If the Automatically close login success screen after <x> secs option is enabled and the duration set to 0 (instantaneous) in the Clean Access > General Setup > Agent Login page and the user clicks on the greyed out OK button while the IP address is refreshing, the Agent locks up after refreshing the IP address. The IP address is refreshed and everything else on the client machine works, but the user cannot close the Agent without exiting via the system tray icon, thus “killing” the Agent process.</p> <p>Workaround Either uncheck the box or set that timer to a non-zero value. If it is set to anything else, and the user hits the greyed out OK button while the IP is refreshing, then the Agent window closes successfully.</p>
CSCsi07595	No	<p>DST fix will not take effect if generic MST, EST, HST, etc. options are specified</p> <p>Due to a Java runtime implementation, the DST 2007 fix does not take effect for Cisco NAC Appliances that are using generic time zone options such as “EST,” “HST,” or “MST” on the CAM/CAS UI time settings.</p> <p>Workaround If your CAM/CAS machine time zone setting is currently specified via the UI using a generic option such as “EST,” “HST,” or “MST.” change this to a location/city combination, such as “America/Denver.”</p> <p>Note CAM/CAS machines using time zone settings specified by the “service perfigo config” script or specified as location/city combinations in the UI, such as “America/Denver” are not affected by this issue.</p>
CSCsj46232	No	<p>Agent should NOT pop-up during CAS HA failover</p> <p>Agent pops up during CAS HA failover. The user ISD still appears in the Online User List and the client machine still appears in the Certified Devices List.</p> <p>Workaround The user simply needs to close the Agent dialog and it does not pop up again.</p>

Table 5 List of Open Caveats (Sheet 3 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsk55292	No	<p>Agent not added to system tray during boot up</p> <p>When the Agent is installed on a Windows client, the Start menu is updated and Windows tries to contact AD (in some cases where the AD credentials are expired) to refresh the Start menu.</p> <p>Due to the fact that the client machine is still in the Unauthenticated role, AD cannot be contacted and an approximately 60 second timeout ensues, during which the Windows taskbar elements (Start menu, System Tray, and Task Bar) are locked. As a result, the Agent displays a “Failed to add Clean Access Agent icon to taskbar status area” error message.</p> <p>Workaround There are two methods to work around this issue:</p> <ul style="list-style-type: none"> • Allow AD traffic through the CAS for clients in the Unauthenticated role. • Try to start the Agent manually after the install and auto load process fails.
CSCsl13782	No	<p>Microsoft Internet Explorer 7.0 browser pop-ups on Windows Vista launched from the Summary Report appear behind the Summary Report window</p> <p>This is also seen when you click on the Policy link in the Policy window. This issue appears on Vista Ultimate and Vista Home, but is not seen with Firefox or on Internet Explorer versions running in Windows 2000 or Windows XP.</p> <p>Workaround You can click on the new item on the Windows status bar to bring the new dialog box or window in front of the Cisco NAC Web Agent Summary report.</p> <p>Note This problem only happens when a Google tool bar is installed and enabled in Internet Explorer.</p>
CSCsl17379	No	<p>Multiple Agent pop-ups with Multi NIC in L2 Virtual Gateway OOB role-based VLAN</p> <p>The user sees multiple Agent login dialogs with two or more active NICs on the same client machine pointing to the Unauthenticated network access point (eth1 IP address).</p> <p>After the first Agent pops up and the user logs in, a second Agent login dialog pops up. If the user logs in to this additional Agent instantiation there are now two entries for the same system with both MAC addresses in the CAM’s Certified Device List and Online Users List.</p> <p>Workaround The user can manually Disable Agent login pop-up after authentication.</p>

Table 5 List of Open Caveats (Sheet 4 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsl40812	No	<p>The Refresh Windows domain group policy after login option is not functioning for Cisco NAC Web Agent</p> <p>(It is working fine with the Clean Access Agent.)</p> <p>This scenario was tested configuring a GPO policy for a Microsoft Internet Explorer browser title. The browser was not refreshed as expected after login in using the Web Agent.</p>
CSCsl75403	No	<p>Mac OS X Agent does not detect VPN interface-fails MAC filters/L3 strict mode</p> <p>This caveat addresses two issues:</p> <ol style="list-style-type: none"> 1. MAC filter does not work for Mac OS X client machines connected to the network in a VPN environment. 2. L3 Strict mode does not allow Mac OS X users to log in and users see a “Access to network is blocked by the administrator” message. <p>With MacOS X client machines, there are no separate interfaces created once the client machine successfully connects to the VPN concentrator. The implementation is different on Windows where a separate interface gets created having an IP address assigned by the VPN concentrator.</p> <p>Workaround To work around these issues:</p> <ul style="list-style-type: none"> • For issue 1, use IP based filters for Mac OS X client machines in VPN environment. • For issue 2, Disable L3 strict mode on the CAS. <p>Note This issue does not affect Windows client machines in VPN environment.</p>
CSCsl88429	No	<p>User sees Invalid session after pressing [F5] following Temporary role time-out</p> <p>When a user presses [F5] or [Refresh] to refresh the web page after the Agent Temporary role access timer has expired, the user sees an “Invalid” session message. If the user then attempts to navigate to the originally requested web address, they are prompted with the web login page again and are able to log in.</p>
CSCsl88627	No	<p>Description of removesubnet has “updatesubnet” in op field</p> <p>The removesubnet API function description has “updatesubnet” listed in its operations field. The description should read “removesubnet.”</p>

Table 5 List of Open Caveats (Sheet 5 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsm20254	No	<p>CAS duplicates HSRP packets with Cisco NAC Profiler Collector Modules enabled.</p> <p>Symptom HSRP duplicate frames are sent by CAS in Real-IP Gateway with Collector modules enabled. This causes HSRP issues and the default gateway to go down.</p> <p>Conditions Real-IP Gateway and Collector modules enabled on a CAS with ETH0 and or ETH1 configured for NetWatch.</p> <p>Workaround Do not configure the CAS' ETH0 trusted interface or ETH1 untrusted interface in the NetWatch configuration settings for the CAS Collector. It is not a supported configuration.</p>
CSCsm61077	No	<p>ActiveX/Java applet fails to refresh the IP address on Vista with User Account Control (UAC) turned on</p> <p>When logged in as a machine admin on Vista and using web login with IP refresh configured, IP address refresh/renew via ActiveX or Java will fail due to the fact that IE does not run as an elevated application and Vista requires elevated privileges to release and renew an IP address.</p> <p>Workaround In order to use the IP refresh feature, you will need to:</p> <ol style="list-style-type: none"> 1. Log into the Windows Vista client as an administrator. 2. Create a shortcut for IE on your desktop. 3. Launch it by right-clicking the shortcut and running it as administrator. This will allow the application to complete the IP Refresh/Renew. Otherwise, the user will need to do it manually via Command Prompt running as administrator. <p>Note This is a limitation of the Windows Vista OS.</p> <p>Alternatively, the Cisco NAC Web Agent can be used with no posture requirements enabled.</p> <p>See also Known Issue for Windows Vista and IP Refresh/Renew, page 86.</p>

Table 5 List of Open Caveats (Sheet 6 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCso15754	No	<p>The ClamXAV live update feature may not work the first time if a “failed” ClamXAV installation requirement immediately precedes the live update in the Mac OS X Assessment Report remediation window</p> <p>If both a ClamXAV Link Distribution and a ClamXAV live update requirement are configured for Mac OS X client remediation, and the installation requirement appears right before the live definition update, then the ClamXAV live update may fail because as the installation process completes, the live update process begins and does not have a chance to read the updated ClamXAV version before launching. Therefore, if the timing is not right, users may have already started the live update while the actual ClamXAV application update tool is still copying onto the client machine.</p> <p>Workaround The user needs to perform the remediation process again because it requires a little extra time for the live update tool to be ready following ClamXAV installation. If the user clicks the Remediate button again after seeing the requirement fail in the first round of remediation tasks, it works just fine.</p>
CSCso49473	No	<p>“javax.naming.CommunicationException” causes no provider list ADSSO with LDAP Lookup</p> <p>If the LDAP connection to Active Directory fails during the lookup process (because the lookup takes a long time or the connection is suddenly lost), the Agent does not receive the list of authentication providers from the CAS. As a result, the user is presented with a blank provider list.</p> <p>LDAP server fails to respond due to network connectivity failure or a long directory search. The failure must occur after communication to the LDAP server has begun.</p> <p>Note There is no known workaround for this issue.</p>

Table 5 List of Open Caveats (Sheet 7 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCso50613	No	<p>Mac OS X Agent DHCP refresh fails if dhcp_refresh file does not exist</p> <p>DHCP refresh will fail with no notice (to the user or to the logs) if the dhcp_refresh file does not exist. The dhcp_refresh tool is required for all versions of Mac OS X Agents, so it always fails if the dhcp_refresh tool is missing regardless the Mac OS version.</p> <p>Workaround There are three ways to work around this issue:</p> <ol style="list-style-type: none"> 1. Reinstalling the Mac OS X Agent automatically reinstalls the missing dhcp_refresh file. 2. Users can sign on to Cisco NAC Appliance via web login. The Java applet installs the dhcp_refresh tool if the Install DHCP Refresh tool into Linux/MacOS system directory option is checked under User Page > Login Page > Edit > General. 3. When using the Apple Migration Assistant, the user can try to include /sbin/dhcp_refresh in the migration list.
CSCsr52953	No	<p>RMI error messages periodically appear for deleted and/or unauthorized CASs in CAM event logs</p> <p>Clean Access Servers connected to a CAM can periodically appear as “deleted” or “unauthorized” in the CAM event logs even though the CAS is functioning properly and has not experienced any connection issues with the Clean Access Manager. Error message examples are:</p> <ul style="list-style-type: none"> • “SSL Communication 2008-07-23 00:31:29 SSLManager:authorizing server failed CN=10.201.217.201, OU=Perfigo, O=Cisco Systems, L=San Jose, ST=California, C=US” • “SSL Communication 2008-07-23 00:31:29 RMISocketFactory:Creating RMI socket failed to host 10.201.217.201:java.security.cert.CertificateException: Unauthorized server CN=10.201.217.201, OU=Perfigo, O=Cisco Systems, L=San Jose, ST=California, C=US” <p>Workaround</p> <ul style="list-style-type: none"> • Reboot the CAS and wait for the CAM to re-establish connection. • Reboot the CAM after deleting and removing the CAS from the Authorized CCA Server list using the CAM Device Management > CCA Servers > Authorization admin web console page.

Table 5 List of Open Caveats (Sheet 8 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsu47350	No	Invalid version number displayed in CAM backup snapshot web page When the administrator navigates to another page in the CAM web console during the backup snapshot process, the resulting snapshot version number is invalid.
CSCsu63247	No	DHCP IP refresh not working for some Fedora core 8 client machines DHCP IP refresh does not work on Fedora core 8 clients logging in to a Layer 3 Real-IP Gateway CAS using the current version of the Java applet. As a result, Fedora core8 clients must use web login to gain access to the Cisco NAC Appliance network. Note There is no known workaround for this issue
CSCsu78379	No	Bandwidth settings for Receiver CAM roles should not change after Policy Sync Steps to reproduce: <ol style="list-style-type: none"> 1. Create role on Master CAM, r1 2. Edit Upstream and Downstream Bandwidth fields of r1 to equal 1Kbps 3. Create role on Receiver CAM, r2 4. Edit Upstream and Downstream Bandwidth fields of r2 to equal 2 Kbps 5. Select role-based Master Policies to Export and perform manual sync 6. Upstream and Downstream Bandwidth fields for role r1 on Receiver CAM are changed to -1 (not 2 Kbps and not 1 Kbps). Note Receiver's Up/Down Kbps, Mode, Burst should either not change or should be the same as the Master.
CSCsu84848	No	CAM should set the switch port to Authentication VLAN before removing from OUL and DCL The CAM should set the switch port to the Authentication VLAN before removing the user from Online Users List and Discovered Client List when the Switch or WLC entry is deleted from the CAM. Workaround Bounce the switch port to clear the OUL and DCL.

Table 5 List of Open Caveats (Sheet 9 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsv18261	No	<p>HA Failover database sync times out in event log after reboot</p> <p>In Cisco NAC Appliance Release 4.5, the CAM HA database copy function times out when the active CAM fails over and becomes the standby CAM. (Event log entries show that the database copy function times out.) This situation arises when the inactive CAM comes up and attempts to copy the database from the active CAM, but the database is still locked by the [now standby] CAM. This issue is not seen during normal operation and database sync because the entries are copied in real time.</p> <p>Note In Cisco NAC Appliance releases prior to 4.5, there is no timeout function, and the database sync takes less time to complete because the CAM does not lock the database or verify the copy function.</p>
CSCsv18995	No	<p>Three requirement types allow administrators to select single Windows XP/Vista operating systems when “All” is checked</p> <p>When creating a new Windows Update, Launch programs, and/or Windows Server Update Services (WSUS) requirement type, and checking the “Windows XP (All)” or “Windows Vista (All)” options, the individual OS options are also still selectable (although they should not be).</p> <p>Note This issue is not seen on the other requirement types.</p> <p>There is no known workaround for this issue</p>
CSCsv20270	No	<p>Conflicting CAM’s eth1 HA heartbeat address with Release 4.5.0 after upgrade</p> <p>The perfigo service cannot be started on the standby CAM because both the eth1 interface of HA CAMs have the same IP address: either 192.168.0.253 or 192.168.0.254.</p> <p>This happens in an HA setup when one of the CAMs is upgraded from Release 4.0(x) to 4.5 and the other CAM is fresh CD installed.</p> <p>Workaround Change to use the manual setting for eth1 on the fresh CD installed node or re-apply the HA config on the upgraded node.</p>

Table 5 List of Open Caveats (Sheet 10 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsv22418	No	<p>CAS service IP not reachable after standby reboot due to race condition</p> <p>The Active CAS's service IP become unreachable after standby CAS reboot.</p> <p>In a rare race condition, the standby CAS temporarily becomes active for very short period of time after reboot.</p> <p>Workaround</p> <ol style="list-style-type: none"> 1. Increase the “Heartbeat Timeout” value from the recommended 15 seconds to 30 seconds. 2. Or, run the heartbeat interface on Interface 3 (eth2 or eth3).
CSCsv78301	No	<p>VPN SSO login does not work with VPN in managed subnet after upgrade to Cisco NAC Appliance Release 4.5</p> <p>Prior to Release 4.5, the Clean Access Server associates the client with the VPN IP address and VPN Concentrator’s MAC address after the first login. From there, the SWISS protocol only checks the IP address from the Agent and reports back to the Agent that the client is logged in (regardless of whether the client is connected via Layer 2 or Layer 3).</p> <p>In Release 4.5, the SWISS protocol checks the MAC address for Layer 2 clients, but the MAC address reported by the Agent (which is the real client MAC address) is different from the one the CAS gets for the client (the VPN concentrator MAC address). As a result, the SWISS protocol tells the Agent that the client machine is not logged in (due to the different MAC addresses recorded) and the Agent launches the login dialog repeatedly, never able to complete login.</p> <p>Workaround Remove the subnet making up the client machine address pool from the collection of managed subnets and create a Layer 3 static route on the CAS untrusted interface (eth1) with VPN concentrator’s IP address as the gateway for the VPN subnet using the CAM web console Device Management > CCA Servers > Manage [CAS_IP] > Advanced > Static Routes page.</p>

Table 5 List of Open Caveats (Sheet 11 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsv92867	No	<p>DB conversion tool (Latin1 to UTF8)-iconv cannot work with &#8224; format</p> <p>Release 4.5 and earlier Clean Access Managers with foreign characters in the database cannot be upgraded to Release 4.6(1) and later.</p> <p>Workaround To upgrade from Release 4.1(6) or 4.5:</p> <ul style="list-style-type: none"> • Perform a fresh install of Release 4.6(1) or later (recommend). • Remove any foreign characters from the database prior to upgrade.
CSCsw39262	No	<p>Agent cannot be launched when switching between users in Vista</p> <p>The Cisco NAC Agent does not support Windows Fast User Switching. The effect is that the primary user is the only user that:</p> <ul style="list-style-type: none"> • Can log into the Clean Access Server and based on the level of authentication will dictate the system's access to the network. • Will see the NAC Agent tray icon. • Will be able to re-authenticate if kicked off the network via the Clean Access Server. <p>Note This does not impact client machines that are part of a Windows Domain. It also does not impact users who log out before logging in as another user.</p> <p>Workaround Logging out the first user or closing the Cisco NAC Agent before Fast Switching eliminates this problem.</p>
CSCsw45596	No	<p>Username text box should be restricted with max no of characters</p> <p>The Username text box is presently taking the characters such that the total size is ~5kb. It is better to have the upper bound for the Username text box to hold the number of characters that it can take.</p>
CSCsw67476	No	<p>Mac OS X Agent upgrade cannot be restarted once stopped</p> <p>User is not able to log in again (no agent screen or icon available) when they cancel the Mac OS X Agent upgrade process.</p> <p>Note This issue has been observed when upgrading from Release 4.5 to 4.6(1) and later.</p> <p>Workaround Manually start the agent which then started the upgrade portion.</p>

Table 5 List of Open Caveats (Sheet 12 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsw88911	No	<p>Mac Agent freezes on login dialog, but remains operational</p> <p>The tray icon of a Mac OS X Agent logged into a Cisco NAC Appliance OOB deployment shows Click - Focus then Click again and is hung (looks like logging in).</p> <p>Workaround Operationally, everything is running normally (the machine is OOB and logged in per CAM and client) just the user interface is locked up.</p>
CSCsx05054	No	<p>DHCP does not work with IGNORE fallback policy and CAS Failover</p> <p>If CAS Fallback policy is set to IGNORE and the CAM becomes unreachable from CAS, the CAS blocks all traffic and CAS DHCP stops working.</p> <p>Workaround Setting the CAS Fallback policy to “Allow All” or “Block All” solves the issue. Also, if you can ensure that the active CAS does not fail over when CAM is unreachable, this situation should not happen.</p>
CSCsx18496	No	<p>Cisco Log Packager crashes on XP Tablet PC with Restricted User credentials</p>
CSCsx29191	No	<p>Mac OS X Agent has no ‘APPLE’+TAB presence</p> <p>When using the Mac OS X Agent, the GUI focus can get lost and is hard to regain. This issue was observed during upgrade.</p> <p>Workaround Using hot corners to show all applications. With this tool, users can find the Agent and continue the process.</p>
CSCsx35438	No	<p>Clean Access Manager read timeout reached when deleting many DHCP IPs at once</p> <p>After upgrading to or installing Release 4.1(8) and deleting hundreds of DHCP IPs at once, the Clean Access Server becomes unmanageable. This issue affects Clean Access Servers configured as a DHCP server on which the administrator tries to delete more than 800 DHCP IPs at once.</p> <p>Workaround Please see Known Issue with Mass DHCP Address Deletion, page 83.</p>

Table 5 List of Open Caveats (Sheet 13 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsx35911	No	<p>Mac OS X Agent does not pop up for login and click-focus does not get user's attention</p> <p>When the user moves from a non-Cisco NAC Appliance network to a Cisco NAC Appliance network, the Agent login dialog does not automatically appear. Click-focus can resolve the issue, but the is not generally obvious to the user. The result of this issue is that users would likely be stuck in the authentication network and/or assigned to a restricted role for the duration of their session.</p> <p>Workaround Click on the upper right icon that is saying click focus and then login.</p>
CSCsx37073	No	<p>Cisco NAC Agent does not pop-up if authentication server name is \\</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Create a Kerberos authentication server named \\ in addition to Local DB. 2. Go to Login Page > Content and check Provider Label, Local DB, \\ (def provider). 3. Let the Cisco NAC Agent pop-up. User sees \\ and Local DB as Server options. (This is as expected.) 4. Go to Login Page > Content and uncheck Local DB. 5. Let the Cisco NAC Agent pop-up again. This time, user sees only the \\ Server option. (This is also as expected.) 6. Go to User Management > Auth Servers and delete \\. 7. Close the Cisco NAC Agent window, which does not pop-up again. <p>Repeat the above steps with authentication server named "myKerberos" instead of \\. The CAM returns a "Clean Access Server is not properly configured. Please contact your administrator if the problem persists" error message.</p> <p>Workaround Avoid non-alphabetic naming conventions when configuring authentication servers in Cisco NAC Appliance.</p>

Table 5 List of Open Caveats (Sheet 14 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsx45051	No	<p>Agent may proceed with AV/AS auto remediation while it's not supported</p> <p>For an AV/AS Definition Update Requirement Type with Automatic Remediation Type and Antivirus/Anti-Spyware Vendor Name configured as ANY, when the client fails the requirement, the Agent should automatically launch the AV (or AS) update on the AV product for which the Agent supports live update. If live update is not supported, the Agent should prompt the user to perform manual remediation. With this issue, the Agent may proceed with auto remediation on a product for which the Agent does not support live update. As a result, auto remediation will fail, and the agent will prompt user to do manual remediation.</p> <p>Note This issue is observed with MS Live One 2.x. Auto Remediation fails when configured for MS Live One 2.x.</p> <p>Workaround Remediate AV manually while in the temporary role.</p>
CSCsx49160	No	<p>Cisco NAC Agent shows one less authentication provider if one of the provider names is \</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Create a Kerberos authentication server called my_krbr. 2. Create a login page and check the Local DB and my_krbr (def provider) Provider Labels. 3. Let the Cisco NAC Agent pop-up. Both my_krbr (def provider) and the Local DB provider options are available. 4. Go to the list of Authentication Servers and rename my_krbr to \. 5. Go to the Login page. \ appears as the new Kerberos name. 6. Close the Cisco NAC Agent and let it automatically pop-up again. <p>This time, the authentication provider list only shows Local DB—\ is missing.</p> <p>Workaround Avoid non-alphabetic naming conventions when configuring authentication servers in Cisco NAC Appliance.</p>
CSCsx52263	No	<p>NAC Appliances always assume USA keyboard layout</p> <p>When connected via Keyboard and Monitor, if a keyboard with layout other than US layout is used, the Cisco NAC Appliances do not recognize the keyboard and it is possible to erroneously enter different characters.</p> <p>Workaround Use a US layout keyboard or ensure that you know the key mapping if you are connecting a keyboard of different layout.</p>

Table 5 **List of Open Caveats (Sheet 15 of 33)**

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsx81395	No	<p>Sophos AV Definition rule fails even if Mac OS Agent has the latest definition</p> <p>The remediation window pops up for updating the Sophos definition files on the Mac OS Agent even though Sophos is updated.</p> <p>This occurs if Sophos is installed on the Mac OS client and an AV definition check for Sophos is configured on the CAM.</p> <p>Workaround There is no workaround at this time.</p>
CSCsx95230	No	<p>Length of token is not printed in the ADSSO logs</p> <p>When ADSSO logging is changed to DEBUG for troubleshooting purposes, the ADSSO logs display the token but not the token size.</p> <p>Workaround None.</p>
CSCsy32119	No	<p>Cisco NAC Appliance CAM/CAS need ability to set port speed/duplex manually</p> <p>There have been instances where switch ports are not negotiating the same as other ports on the same appliance. This is inefficient since the ports in question do not necessarily use the highest possible speed. In addition, there could be collisions, FEC, and errors on a port if there is a mismatch.</p> <p>Note There is no known workaround for this issue.</p>
CSCsy45807	No	<p>Mac OS X Agent does not pop up using Sprint Wireless</p> <p>This issue has been encountered using Sprint Wireless Novatel U727 on 2 different Mac OS X client machines.</p>
CSCsz19346	No	<p>Korean log packager GUI translations/buttons are garbled & some missing</p> <p>Workaround Some of the buttons are still readable. Click Collect Data > Locate File and then click Exit.</p>

Table 5 List of Open Caveats (Sheet 17 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsz55538	No	<p>IP refresh message shows up in L3OOBRIP with IP Un-numbered scenario</p> <p>When L3OOBRIP with IP un-numbered is configured, the IP refresh message shows up even if IP refresh does not happen.</p> <p>Workaround In the CAM web console, go to Profiles > SNMP Receiver > Advanced Settings. Enter “0” in the DHCP Release Delay and DHCP Renew Delay fields.</p>
CSCsz80035	No	<p>“ANY” AV remediation for Trend Micro 17.1 fails</p> <p>The AV update for Trend Micro version 17.1.1250 shows a failure in the Cisco NAC Agent window, but the update is successful.</p> <p>Workaround Click OK on the error display. The AV update is actually successful.</p>
CSCsz83270	No	<p>Agent file download fails at lower speed WAN links between CAS and CAM</p> <p>When the Agent is uploaded to the CAM, the .tar file gets partially downloaded and removed several times on CAS before it is successfully downloaded and its contents unpacked. As a result the client does not pop-up for a long time for upgrade or fresh install from the Cisco NAC Appliance web login page.</p> <p>This happens during agent upgrade or download from web page when CAS and CAM are separated by a WAN link (512kbps/256kbps).</p> <p>Workaround If agent does not get downloaded for a long time, remove the contents of /perfigo/access/apache/www/perfigo_download to start the download of the file.</p> <p>Note Problem usually corrects itself after a while, but if it does not, Cisco recommends following this workaround.</p>
CSCsz85892	No	<p>Web login display Guest ID instead of Username</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Add a Kerberos auth server named “k1.” 2. Enable the Local DB and “k1” providers on the Login Page, and make “k1” the default provider. 3. Open a browser and check that Username is there and “k1” is the default provider. 4. Delete “k1” from the roster of Auth Servers. 5. Open another browser and note that the user name is now “Guest ID.”

Table 5 *List of Open Caveats (Sheet 18 of 33)*

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsz92761	No	<p>CAM GUI and publishing behavior during DB restore</p> <p>When a CAM snapshot is restored from a database, the CAM web console times out, and once refreshed, shows the associated CAS is offline as a result of triggering a database restoration.</p> <p>This issue occurs when the CAM and CAS are connected via WAN links (T1/256k/512k) with several CASs experiencing at least 400ms delay.</p> <p>Note After the CAM completes its parallel connection at the end of the database restoration, it starts to publish to many of the CASs via serial connection.</p> <p>Workaround DBrestore happens and CAS do get connected and publishing completed.</p>
CSCsz97199	No	<p>McAfee AV_TotalProtectionforSmallBusiness_4_7_x upgrade to 5.0 issues</p> <p>When auto-upgrading the McAfee AV_TotalProtectionforSmallBusiness_4_7_x to version 5.0 via the Cisco NAC Agent, all updates are downloaded and installed for 4.7, but then an automatic upgrade to 5.0 fails.</p> <p>Note There is no known workaround for this issue.</p>
CSCta12544	No	<p>Server communication error upon web and Agent login</p> <p>This issue can occur when a brand new Release 4.5 or later CAS is connected to a CAM pair that has been upgraded from an older release of Cisco NAC Appliance to Release 4.5 or later, resulting in unreliable communication between the CAM HA pair and the new CAS.</p>
CSCta19323	No	<p>Memory for crash kernel message seen during 4.7.0 CD install</p> <p>The message is benign, it is displayed when memory is not configured/allocated for a crash kernel to aid in crash dump. This is displayed by Red Hat and CentOS 5 releases while booting on any system.</p>
CSCta35732	No	<p>Deleting subnet filters causes CASs to disconnect</p> <p>When you delete the subnet filter one after another from the CAM, the web console slows down and loses connection to the associated CAS.</p> <p>The CAM connects to all the CASs every few minutes via serial interface and checks for heartbeats. If a CAS goes offline, the CAM tries to connect to the CAS to resume connection. However, the wait time depends on the number of CASs attached to the CAM.</p> <p>Note After a few minutes, CASs come back online.</p>

Table 5 List of Open Caveats (Sheet 19 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCta35741	No	<p>Agent not Popping up for First time for TLS not enabled on IE 6.0 If TLS 1.0 is not enabled on Microsoft Internet Explorer browsers when the user launches the Cisco NAC Agent in a FIPS 140-2 compliant network, the Agent dialog/login screen does not appear.</p> <p>Workaround The user must Exit the Cisco NAC Agent using the Windows Systray icon and launch the Agent again.</p>
CSCta97229	No	<p>Collector Modules show “Stopping” instead of “Stopped” in Profiler UI</p> <p>This issue happens when the administrator manually stops the Profiler Collector.</p> <p>Workaround Services are actually stopped. You can enter service collector status in the CAS CLI to verify the current state.</p>
CSCtb30587	No	<p>Clearing CAM CDL upon intra-subnet roaming keeps client in Access VLAN</p> <p>This issue has been seen on WLC1 managing AP1 and WLC2 managing AP2 have same SSID with WLANs on both the controllers mapped to interface which are on the same subnet. (Both controllers are running version 6.0.182.0.)</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Client is initially associated to AP1. Do a posture validation on the client and client entry is shown on WLC1. 2. Now disable AP1. The client machine is associated to AP2, the client entry is deleted from WLC1, and the client entry is now available only on WLC2. Client is now in Access VLAN and client entry shown on WLC2. <p>However, the CAM still lists WLC1 IP address with client entry.</p> <ol style="list-style-type: none"> 3. Clear the CDL and OUL from the CAM. The client still appears in the Access VLAN, has complete access to the internet, and an error appears in the CAM’s nac-manager.log file after clearing the CDL and OUL on the CAM.

Table 5 List of Open Caveats (Sheet 20 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCtb30691	No	<p>Agent pops up from and active wired NIC after user is already authenticated via a wireless NIC in the same client machine</p> <p>After authenticating using the wireless NIC with a higher preference than the wired NIC on the same client machine, the Agent pops up again, prompting the user to enter authentication credentials. This happens on Windows XP SP3 client machines. (This issue has not been observed in Windows XP SP2.)</p> <p>Workaround The problem is caused by a Windows TCP/IP feature called “Dead Gateway Detection.” To disable this feature, set the “EnableDeadGWDetect” registry value under HKEY_LOCAL_MACHINE\System\CurrentControlSet\Services\Tcpip\Parameters to 0, then reboot the client machine.</p>
CSCtb32797	No	<p>LDAP GSSAPI with SSL lookup and authentication fails</p> <p>The Cisco NAC Appliance network returns the following message: “Unsupported Ldap Operation ([LDAP: error code 53 - 00002029: LdapErr: DSID-0C09048A, comment: Cannot bind using sign/seal on a connection on which TLS or SSL is in effect, data 0, v1771])” or “Naming Error (dcchild.child.2k8.com:636; socket closed)”</p> <p>Note Microsoft has documented this error on its support site at http://support.microsoft.com/kb/957072. Unfortunately, Windows 2008 server SP2 with the latest Windows updates as of 8/20/09 did not resolve this problem.</p> <p>Note There is no known workaround for this issue.</p>
CSCtb38026	No	<p>Scripting error with database restore with modified DB snapshot name</p> <p>If the database snapshot name is altered to include some string after the version number and before the .gz suffix like the following: 08_12_09-23-48_snapshot_VER_4_7_0_A23_upgraded_from_4-1-3 .gz the database restoration process returns a scripting error. This issue is only cosmetic and does not affect the database restore functionality.</p> <p>Workaround Do not rename the database snapshot (for identification purposes, for example) after it has been created.</p>

Table 5 List of Open Caveats (Sheet 21 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCtb43264	No	<p>Both HA-CAS nodes stuck in active-active state</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Do a fresh install of both CAS nodes and the CAM. 2. Configure high availability for the CAS HA-pair. 3. Reboot both the HA-CAS nodes at the same time. 4. Add the primary CAS to the CAM. The CAM reports the CAS to be disconnected. 5. Click Manage where the CAM web console reports “SSKEY on server does not match the value in database.” 6. Click Advanced > Managed Subnet and add a managed subnet. Both CASs appear to be active-active. <p>This is a dangerous scenario creating a Layer 2 broadcast loop that almost immediately brings down the network.</p> <p>Workaround There are two possible remedies for this issue:</p> <ul style="list-style-type: none"> • Configure a longer heartbeat timeout interval for the HA-pair. • Add an additional heartbeat Ethernet interface link (eth2, eth3).
CSCtb44223	No	<p>Mac OS X Agent gets presented with incorrect login page and providers</p> <p>The Mac OS X Agent is presented with providers from a configured “MAC_ALL” OS login page rather than the intended “MAC_OSX” login page.</p> <p>This issue has been observed on Mac OS X 10.4 and 10.5 running Agent version 4.6.0.3 in a Cisco NAC Appliance Release 4.6(1) deployment.</p> <p>Workaround Configure MAC_ALL page identically to MAC_OSX page.</p>
CSCtb55184	No	<p>Web Agent download fails if the CAS IP address in the trusted certificate is different from the CAS domain IP address.</p> <p>This situation can occur when the CAS is in Layer 2 In-Band Real-IP gateway mode, and IP used for initial SSL cert during install is different from that imported using the web console.</p> <p>Workaround Enter <code>service perfigo restart</code> on the CAS to resolve this issue.</p>

Table 5 List of Open Caveats (Sheet 22 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCtb92910	No	<p>Need to reflect all the states of FIPS card in the UI and CLI</p> <p>Currently, the web console page only reflects whether or not the FIPS card is operational, but states like maintenance or initialization are not reflected.</p> <p>Workaround If the CAM Monitoring > Summary page does not show that the FIPS card is operational, assume it is in one of the other states (Maintenance or Initialization). You can also manually verify the electromagnetic switch position (“O,” “M,” or “I”) on the FIPS card, itself when you look at the back of the NAC-3315/3355/3395 chassis.</p> <p>Note Once the FIPS card is Operational on the CAM/CAS, the position of the electromagnetic switch on the FIPS card does not come into play again until you reboot either the FIPS card or the appliance.</p>
CSCtb98457	No	<p>Posture Assessment requirements for Vista machines results in the user being placed in the temporary role.</p> <p>This has been observed in Windows Vista Home operating systems running version 4.6.2.113 of the Cisco NAC Agent.</p> <p>Workaround Disable compatibility mode for Nacagent.exe. Compatibility mode can be disabled by un-checking (disabling) the “Run this program in compatibility mode for” option in the file properties for NACagent.exe.</p>
CSCtc00668	No	<p>Mac Agent trying to update Avast even though application is up-to-date</p> <p>Following login, the Mac Agent pops up prompting user to update “ANY” AV.</p> <p>Workaround Use one of the following options:</p> <ul style="list-style-type: none"> • Stop and restart the Mac OS X Agent after installation. • Reboot the client machine. • Make the requirement optional (opens the network up to an old AV definition file version).
CSCtc01957	No	<p>Firefox 3.5.2 Freezes and user cannot enter user credentials</p> <p>After the applet loads in the Firefox browser, the user login page locks up and the user is unable to enter login credentials. This situation can occur when a user is attempting web login with a FireFox 3.5.2 browser for the very First time.</p> <p>Workaround The workaround for this issue is to minimize the Browser or open a new browser window.</p>

Table 5 List of Open Caveats (Sheet 23 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCtc41408	No	<p>Windows 7 tray icon default should be show icon and notifications</p> <p>According to Microsoft, there is no way for a program to promote itself by setting the “Show Icon and Notifications” option. This can be done only by the user and only manually. Default behavior is to hide all icons.</p> <p>Workaround The Windows 7 client machine user can change this behavior by either drag-and-dropping the hidden icon or by changing the “Show Icon and Notifications” setting.</p>
CSCtc46376	No	<p>Windows WSUS update (Microsoft rules) is not working for KB890830</p> <p>When a WSUS update is performed on a new installation of Windows 7 (where no updates have been applied), and the No UI option is selected for the requirement, the WSUS update can fail.</p> <p>The portion of the Windows update that fails to install is the KB890830 update (Windows Malicious Software Removal Tool, http://support.microsoft.com/?kbid=890830). This upgrade must be installed with admin privileges and there is a one time EULA that the user must accept during installation.</p> <p>After KB890830 is installed, there are monthly updates that are pushed out from Microsoft on patch Tuesday. The subsequent updates of KB890830 do not require admin privileges and they work fine on a client where the user is not a member of the admin group.</p> <p>If users manually install KB890830 on a client system as a non-admin user using Windows Update, they are prompted for the administrator password and then get the EULA.</p> <p>Workaround Ensure new installations of Windows are brought up to date by a user with administrator privileges prior to turning the client machine over to users without administrator privileges.</p>
CSCtc52252	No	<p>Cannot uninstall the Agent using MSI executable with full quiet mode selected</p> <p>If you open a Command Prompt window and run the MSI install/uninstall commands using the quiet option, the command fails.</p> <p>Workaround You must open the Command Prompt window using the “Run as Administrator” option, even if you are administrator on the system.</p>

Table 5 List of Open Caveats (Sheet 24 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCtc59248	No	<p>The Agent does not launch if IE has never been launched or the CA certificate is not installed</p> <p>The Cisco NAC Agent login window does not pop up (or takes a long time to pop up) during initial login because:</p> <ul style="list-style-type: none"> • The CA cert that signs the CAS server cert has not been installed • IE has never been launched before by the user <p>This problem could also occur when the administrator kicks the user out of the NAC Appliance network after logging in via an OOB session.</p> <p>Workaround - Deploy the CA cert that signs the CAS server cert before user logs in and instruct the user to start IE after experiencing this problem.</p> <p>Note The Cisco NAC Agent running in a Windows 7 environment allows the user to install the CA certificate at initial login.</p>
CSCtc66277	No	<p>IP refresh takes a minute and Agent vanishes after that</p> <p>This issue can come up in a network where spanning tree merge has been configured on the switch. Configuring portfast minimizes the IP refresh time.</p> <p>Note Cisco recommends enabling port-fast switch configuration whenever appropriate to do so.</p>
CSCtc68565	No	<p>Web Agent does not launch using ActiveX on a client machine where the administrator UAC is “default”</p> <p>When using Windows 7 as a local machine administrator and a proxy server, Internet Explorer places the CAS into the intranet settings category, which automatically disables “Protected Mode.”</p> <p>Workaround Enable “Protected Mode” in Internet Explorer for intranet sites.</p>
CSCtc86765	No	<p>The Cisco NAC Agent does not pop up in a VPN environment upon re-connecting to the VPN server</p> <p>This issue has been observed when power cycling a SOHO (Small office home office) DSL/Cable modem router, thus terminating the VPN connection.</p> <p>Workaround Exit and re-launch the Cisco NAC Agent.</p>

Table 5 List of Open Caveats (Sheet 25 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCtc90896	No	<p>For McAfee Total Protection 5.0, you need to change firewall setting AV definition file update for McAfee Total Protection 5.0 does not work with the default McAfee firewall settings.</p> <p>Workaround For AV definition file update to work for McAfee Total Protection 5.0, you need to change the McAfee firewall setting from “Untrusted Network” to “Trusted Network” or “Custom” and allow the McAfee program to access the update site.</p>
CSCtc90964	No	<p>Inaccuracy in AV/AS support info</p> <p>Latest Virus Definition version/date for Selected Vendor under AV/AS support info does not display the updated version/date for some AV/AS vendors.</p>
CSCtc91616	No	<p>Inconsistent support for Internationalized characters in usernames</p> <p>It is unclear if Internationalized characters are supported for uncommon user names in Cisco NAC Appliance. For example, some internationalized characters (like è) are allowed when creating a username on the CAM, but user login fails. Other character sets (like Japanese) also fail when attempting to create the user in the Local DB.</p>
CSCtc92037	No	<p>Mac agent in L2 non-strict mode does not pop up behind NAT router.</p> <p>With L2 non-strict mode and Mac client behind NAT router, Mac agent does not pop up.</p> <p>Note There is no known workaround for this issue.</p>
CSCtd04881	No	<p>Serbian web install shows error and installer is English</p> <p>A popup window appears with an error message in Serbian, which approximately translates to, “Writing error in applied transformation. Recommend to use a valid transformation path.”</p> <p>After clicking OK the installer launches in English, yet the application launches and is fully functional in Serbian.</p> <p>Note There is no known workaround for this issue.</p>
CSCtd39544	No	<p>In certain cases, root CA certificate is categorized as CCA cert in SSL user interface</p> <p>The SSL user interface for an X509 certificate chain is used with a multi-tier hierarchy may not display the Root CA cert.</p> <p>Note This issue is only cosmetic and does not impact SSL functionality.</p>

Table 5 **List of Open Caveats (Sheet 26 of 33)**

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCte55522	No	<p>The Cisco NAC Agent for Release 4.7(2) does not update ZoneAlarm 7.1.078.000 in Windows Vista Ultimate</p> <p>This particular update works in Windows Vista Ultimate SP0.</p> <p>Workaround The user can upgrade to ZoneAlarm Version 8 when running Windows Vista Ultimate SP1.</p>
CSCte64337	No	<p>Unexpected switch to UDP discovery mechanism</p> <p>There are unexpected SSM events found in the Agent log. These events are caused by unexpected switch to UDP discovery after SwissUdpExchange starts sending Swiss requests.</p>
CSCte76636	No	<p>L3 MAC unable to refresh on Vista (32-bit/64-bit) w/ UAC w/o port bounce</p> <p>Windows Vista users are not able to get an IP address from the DHCP pool for the access VLAN with web login or web agent.</p> <p>Workaround Run the browser (Internet Explorer or Firefox) as administrator.</p>
CSCtf02702	No	<p>After deleting and re-adding a CAS, the CAM web console displays that AD SSO is started</p> <p>This issue does not impact Cisco NAC Appliance functionality. After deleting and re-adding a CAS, the administrator must also reboot the CAS. Once you reboot the CAS (or perform “service perfigo restart”), everything works as designed.</p> <p>Workaround Restart the CAS to avoid this symptom appearing.</p>
CSCtf10973	No	<p>For every single login/logout, CAM sends two accounting packets</p> <p>This issue was not observed running the same test on a Cisco NAC Appliance Release 4.7(2) CAM, and this issue has not been observed in an In-Band deployment.</p>

Table 5 List of Open Caveats (Sheet 27 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCtf69345	No	<p>Agent reports incorrect update details for McAfee 8.7.0i on Win7 x64</p> <p>NAC Agent reports incorrect McAfee virus definition update date and version, while McAfee shows the right date.</p> <p>This occurs because Windows registry is blocked with permissions issue and prevents McAfee from overwriting the appropriate date and version information to registry.</p> <p>Workaround Perform the following steps:</p> <ol style="list-style-type: none"> 1. Uninstall McAfee. 2. Delete the following key and sub keys from registry: HKEY_LOCAL_MACHINE\SOFTWARE\McAfee 3. Re-install McAfee and confirm that the entry is recorded in the registry with proper details. 4. Perform updates in McAfee. 5. Verify that both NAC Agent and McAfee show the same dates and definition versions.
CSCtf99294	No	<p>RSA RADIUS Server Connection Fails</p> <p>When adding a new RSA token-based RADIUS server to a Clean Access Manager, the web interface returns a large Java error.</p>
CSCtf99678	No	<p>Enable OOB logoff msg for Windows not grayed out in Firefox browser</p> <p>The Enable OOB logoff for Windows NAC Agent and Mac OS X Agent checkbox is not grayed out in Mozilla Firefox version 3.5.8, even with the “Use 'WINDOWS_ALL' settings for this OS version” option checked.</p> <p>Note This issue appears in Mozilla Firefox and has not been observed in other browser types.</p>
CSCtg01263	No	<p>Invalid provider name seen between multi-NIC transition with OOB Logoff</p> <p>This problem is happening because while the role based (with IP refresh) wired NIC is transition from logged in, through IP refresh on logout, then the wireless NIC has the better metric so the wireless side responds, once the ip is refreshed on the wired side an invalid provider is seen and then wired login continues normally.</p>

Table 5 List of Open Caveats (Sheet 28 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCtg06599	No	<p>IP refresh on Win 7 after successful auth is very slow</p> <p>After a successful login, it takes 1-4 minutes for a machine to complete the IP refresh. This happens with Windows 7 and Vista machines moving from authentication to access networks (with an IP address change).</p> <p>This occurs because the Network Connectivity Status Indicator, which is part of the Network Location Awareness in Windows, tries to reach the msftncsi.com web page while performing IP refresh. If it is not able to reach this website, then Microsoft takes longer to sense the machine's status and results in slower applications that require internet access.</p> <p>For more information, see Known Issue with Delayed IP Address Refresh for Windows 7/Vista Clients Running Cisco NAC Agent, page 82.</p>
CSCtg39044	No	<p>Running Internet Explorer in offline mode effects Cisco NAC Agent auto-upgrade function</p> <p>When users access the network via Internet Explorer in offline mode, the Cisco NAC Agent auto-upgrade function does not work correctly for Agent versions 4.7.2.10 and earlier. The login session appropriately prompts the user to upgrade the Agent, but clicking OK brings up the login screen instead of launching the Agent installer.</p>
CSCtg45522	No	<p>Delay in Agent logging out in Vista 64-bit</p> <p>Found that after authentication when click logout on a Vista 64bit machine, it takes a while before CAM receives the logout message and hence client takes a while to switch back from access to auth.</p>
CSCtg45741	No	<p>IP address release takes a while in Windows 7 32-bit using taskbar logout option</p> <p>IP release takes a long time to complete on Windows 7 32-bit clients for Cisco NAC Agent. As a result, the delay between release and renew is around 50sec.</p>
CSCtg45753	No	<p>Cisco NAC Agent won't pop-up with multi-NIC same metric /auth/discovery 404</p> <p>This issue can occur when Agent runs on a client machine with two NICs using the same metric. (For example, the wired interface has NAC, while the wireless interface has no NAC.)</p> <p>Note This was observed on 100MB wired and 300MB wireless interfaces where the wireless speed signal dropped close to 100 resulting in two NICs with the same metric.</p>
CSCtg57758	No	Error in Mac OS X Agent while editing Filters

Table 5 List of Open Caveats (Sheet 29 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCth61503	No	Duplicate kernel status message appears during CD installation The “Memory for crash kernel (0x0 to 0x0) not within permissible range” message appears twice in a row during CD installation.
CSCth61543	No	Catalyst 2975 MAC address appears incorrectly in CAM When a Cisco 2975GS switch is added to a CAM for OOB switch management, the CAM UI does not display the MAC address of the switch.
CSCtg61995	No	Mac OS X Agent SWISS discovery back-off algorithm When Mac Agent is not connected to a NAC network, the Agent will never give up on trying to contact the last known CASes. It will continuously send UDP SWISS packet every ~17 seconds forever.
CSCtg69836	No	HTML Canned Report Missing AV gives blank report, but is ok for PDF
CSCtf08917	No	Kaspersky 6.0.4.1217 is not recognized by the NAC Agent on Japanese client machines This issue has been observed on a Windows XP system with Japanese locale. Note There is no known workaround for this issue.
CSCtg36630	No	Need Mac OS X Agent support for Intego VirusBarrier X6 in Cisco NAC Appliance to match that of the Cisco NAC Agent
CSCtg65859	No	The Cisco NAC Agent is not able to logout in an OOB deployment Cisco NAC Appliance generates a “Rogue Client Agent Report” after the user performs web login and then launches the NAC Agent (or closes the NAC Agent dialog window if already launched), and then tries to log out using the NAC Agent in an OOB environment. Workaround Use the Cisco NAC Agent to log in to such networks.
CSCtg90535	No	Cisco NAC Agent fails to pop up on remote site Cisco NAC Agents (version 4.7.1.511) in a remote site fail to display the login dialog and, following restart, the client machine stays in the authentication VLAN. Workaround Downgrading the Agents on remote site from version 4.7.x.y to 4.5.x.y seems to act as a workaround for this issue.
CSCth17804	No	VPN SSO presents a blank Cisco NAC Agent login dialog Following a VPN disconnect, the client machine renegotiates for VPN to connect through the network and the user is presented with a blank Agent login dialog.

Table 5 List of Open Caveats (Sheet 30 of 33)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCth60233	No	<p>Windows IP Refresh not working properly after user logoff</p> <p>This issue has been observed on both Windows XP and Vista client machines—the Agent is not releasing the IP address.</p> <p>Workaround Manually refresh the IP address on the client machine.</p>
CSCth73166	No	<p>Remediation and login screens are still displayed after network change</p> <p>The Agent displays these screens indefinitely (or until the remediation timer expires) after removing the network cable or changing networks while the Agent login or remediation screens are active.</p> <p>Workaround Click Cancel on the login page or click Complete on the remediation screen.</p>
CSCth73774	No	<p>McAfee Virus scan 14.0 remediation fails</p> <p>This issue has been observed during client remediation of McAfee VirusScan 14.0.</p> <p>Workaround Set McAfee to automatically update during the time the user is logged in. (The user can also manually update while logged in or while in the Agent Temporary role.)</p>
CSCth81638	No	<p>The Cisco NAC Agent gets stuck in logout loop if remediation times out</p> <p>When the client machine has no AV installed and is failing requirement for AV, the Agent loops, asking for login while sending logout messages to the CAS.</p> <p>Workaround There are two possible workarounds for this issue:</p> <ul style="list-style-type: none"> • Manually restart the Cisco NAC Agent. • Install and update an AV so that the Agent no longer prompts the user to remediate.
CSCth83522	No	<p>Clicking Yes clicked on a certificate revocation dialog displays an internal error message</p> <p>When logging in with the Web agent where the root certificate is not trusted and certificate revocation checking is enabled in Internet Explorer, an internal error message appears when the user clicks Yes on the revocation check dialog.</p> <p>Workaround There are two workarounds for this issue:</p> <ul style="list-style-type: none"> • Ensure the certificates are trusted. • Disable Server Certificate revocation checking in Internet Explorer's Advanced settings.


Table 5 List of Open Caveats (Sheet 31 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCth85390	No	<p>Certificate dialog appears multiple times when certificate is not valid</p> <p>Workaround Ensure valid certificates are available on the client machine.</p>
CSCth85833	No	<p>The Cisco NAC Agent tool-tip indicates logged-in long after VPN disconnect</p> <p>This issue has been observed performing VPN SSO via the Cisco NAC Agent on Windows 7 client machines.</p> <p>Note This issue has no impact on system functionality.</p>
CSCth88009	No	<p>The Mac OS X Agent's Popup Login Window option does not work during SSO</p>
CSCth93201	No	<p>Uploading Agent file without a version should not be allowed</p> <p>Uploading a new Agent onto the CAM without specifying a version prevents the Agent login dialog from appearing on client machines where a version of the Agent already exists, and does not allow new Agent installation on client machines where no Agent yet exists.</p> <p>Workaround There are two possible workarounds for this issue:</p> <ul style="list-style-type: none"> • Upload the Agent file to the CAM again specifying the correct Agent version information using the Device Management > Clean Access > Clean Access Agent > Distribution web console page. • Download the agent files from Cisco update servers by going to the CAM Device Management > Clean Access > Updates > Update web console page, enable (check) the Check for Windows NAC Agent updates and Check for Macintosh Clean Access Agent updates options, and click Update. <p>After performing either of the above, verify that the Agent has been uploaded correctly by viewing the CAM Monitoring > Summary web console page to ensure the agent version information for both the Cisco NAC Agent and Mac OS X Agent appears as specified.</p>
CSCth95243	No	<p>VPN connection to non-NAC Appliance networks may disconnect</p> <p>This issue has been observed in deployments where the Cisco NAC Appliance VPN connection tunnels all traffic, the Access to Authentication VLAN Change Detection feature is enabled, and the NACAgentCfg.xml PingArp parameter is set to 0 (default).</p> <p>Workaround Disable the Access to Authentication VLAN Change Detection feature or change the PingArp value in NACAgentCfg.xml to 1 or 2.</p>

Table 5 List of Open Caveats (Sheet 32 of 33)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCth98219	No	<p>Agent appears when user is logged in via restricted network access role</p> <p>When a user logs into an Out-of-Band network and accepts Restricted network access after failing a mandatory requirement, the Cisco NAC Agent appears a second time (and continues to appear each time) when the user either logs in again without remediating, or closes the Agent login dialog.</p> <p>Workaround The Cisco NAC Appliance administrator can manually add text to the Restricted Access dialog box advising the user to iconize the Agent and must perform manual remediation. Once the user remediates the client machine, they can double-click the Agent icon and log in again.</p>
CSCti35086	No	<p>Disable Fast SSID change for NAC Wireless OOB setup</p> <p>Wireless clients without the Cisco NAC Agent installed can associate to a “guest” WLAN where NAC is not enabled.</p> <p>When FAST SSID Change is enabled globally on a Wireless LAN Controller, wireless clients (without the Cisco NAC Agent installed) can then disassociate from the “guest” WLAN and immediately associate to the corporate WLAN (where NAC functionality is enabled), resulting in the client machine being placed directly into the network Access VLAN without being redirected to the Quarantine role.</p> <p>Workaround Disable the Fast SSID function on the Wireless LAN Controller.</p>
CSCti03955	No	<p>The Agent login dialog becomes unresponsive when the Temporary role timer runs out</p> <p>This situation can occur if the Temporary role timer expires during a long remediation like WSUS or AV/AS update.</p> <p>Workaround To avoid this issue, make sure the Temporary role timer is set to a value that will not expire during “worst case” remediations.</p> <p>Note If this problem occurs, users can clear the NAC Agent login dialog by selecting Exit from the Cisco NAC Agent systray icon or rebooting the client machine. If the user chooses to Exit, the user must also then manually launch the Cisco NAC Agent again.</p>

Table 5 List of Open Caveats (Sheet 33 of 33)

DTS Number	Software Release 4.8	
	Corrected	Caveat
CSCti78938	No	<p>HA configurations are not updated when hostname is modified</p> <p>When hostname is modified from the CAM web console Administration > CCA Manager > Network or by using service perfigo config, the hostname settings in HA configuration files are not updated.</p> <p>Workaround Go to Administration > CCA Manager > Failover, enter appropriate values, and click Update before rebooting the CAM.</p>
CSCtj02066	No	<p>Upgrade from 4.7.3 to 4.8.0 Release is not allowed</p> <p>You cannot upgrade your Cisco NAC Appliance deployment from Release 4.7(3) to Release 4.8 directly. The upgrade option is not allowed.</p>
CSCtj81255	No	<p>Two MAC addresses detected on neighboring switch of ACS 1121 Appliance.</p> <p>Symptom Two MAC addresses are detected on the switch interface connected to an ACS 1121 Appliance although only one interface is connected on the ACS 1121 Server eth 0.</p> <p>Conditions Only one Ethernet interface, eth 0 is connected between ACS and Switch.</p> <p>Workaround Disable BMC (Baseboard Management Controller) feature using BIOS setup.</p> <p> Caution To help prevent a potential network security threat, Cisco strongly recommends physically disconnecting from the Cisco NAC console management port when you are not using it. For more details, see http://seclists.org/fulldisclosure/2011/Apr/55, which applies to the Cisco ISE, Cisco NAC Appliance, and Cisco Secure ACS hardware platforms.</p>

Resolved Caveats - Release 4.8

Refer to [Enhancements in Release 4.8, page 15](#) for additional information.

Table 6 List of Resolved Caveats (Sheet 1 of 4)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCsx07592	Yes	<p>Syslogging of CAM/CAS system logs</p> <p>There is no method to send the CAM or CAS support logs to a syslog server.</p> <p>The syslog file has been updated at the CAM/CAS end so that the remote host receives system logs.</p>
CSCtb66010	Yes	<p>NACAgentCFG.xml file is not preserved after CAM upgrade</p> <p>The Agent configuration XML file packaged with the Cisco NAC Agent is not preserved after upgrading from Release 4.6(1) to 4.7.</p> <p>The Upgrade now retains the Agent configuration XML file.</p>
CSCsw89027	Yes	<p>Mac OS X Agent logs can grow too large in debug and do not clean up</p> <p>When Agent logging is set to “Defect”, Mac OS X Agent logs grow too large.</p> <p>Workaround Do not compile Mac OS X Agent logs in debug mode for extended periods of time.</p>
CSCsx03338	Yes	<p>HTTP packet to a host using reversed IP address after connection on Mac OS X client</p> <p>The Mac Agent sends a packet to UDP port 80 to the reversed IP address of the client’s default gateway every 5 seconds.</p> <p>Note This occurs only on the Mac Agent, and is a side effect of the Vlan Change Detection feature added in Cisco NAC Appliance Release 4.1(3).</p> <p>Workaround Disable the access-to-auth vlan-detection by following the instructions at http://www.cisco.com/en/US/docs/security/nac/appliance/configuration_guide/461/cam/m_oob.html.</p>
CSCsx27857	Yes	<p>With session timer disabled for the Agent Temporary role, version 4.6.0.3 of the Mac OS X Agent times out</p> <p>If the Temporary role timer disabled on the CAM, the Mac Agent times out right away.</p>
CSCsx78577	Yes	<p>ClamAV not showing def date</p> <p>ClamAV does not provide the definition date to the Agent.</p>

Table 6 List of Resolved Caveats (Sheet 2 of 4)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCsz48766	Yes	<p>MAC Agent VLAN change detection logic causes AnyConnect to disconnect</p> <p>Anyconnect client constantly loses connection to VPN network when using the Mac OS X Agent with the VlanDetectInterval set to 5 seconds.</p> <p>Workaround The settings.plist file does not contain the VlanDetectInterval value by default, so Mac users must add a “VlanDetectInterval value 0” child string and then restart the Agent to address the AnyConnect connection issues.</p>
CSCta43634	Yes	<p>JSF library throws duplicated ID in faces tree exception occasionally</p> <p>This condition can occur if the user inadvertently double-clicks a hyperlink, resulting in the CAM web console returning an exception error.</p> <p>Workaround Log out and log back into the CAM web console.</p>
CSCta85491	Yes	<p>addmac API is susceptible to XSS on the CAS when using local device filter</p> <p>Steps to reproduce:</p> <ol style="list-style-type: none"> 1. Call addmac for a global device filter where the description contains <code><script>alert('CAS specific XSS'); </script></code>. No pop-up alert box is observed. 2. Call addmac for a CAS-specific local device filter where the description contains <code><script>alert('CAS specific XSS'); </script></code>. 3. Go to the CAM web console and click the manage icon for the CAS in question and then go to Filter > Devices, You should see a pop-up alert box with a CAS-specific XSS message. <p>Note This is not an issue for global device filters calling addmac.</p>
CSCtb58837	Yes	<p>Database write to HA-Secondary CAM fails</p> <p>Standby CAM can occasionally fall out of sync with Active under stress load condition where there is a lot of very rapid individual update to the HA-Standby appliance for a very long period of time (i.e. users logging on and off and many changes to the device filter list, for example).</p> <p>Workaround Restart the Standby node to bring it back in sync with Active.</p>

Table 6 List of Resolved Caveats (Sheet 3 of 4)

Software Release 4.8		
DDTS Number	Corrected	Caveat
CSCtb95381	Yes	<p>Cisco NAC Appliance certificates not signed and/or expiring soon</p> <p>Cisco NAC Appliance Release 4.7.0 comes with the following files that are either not signed or expire in March 2010:</p> <ul style="list-style-type: none"> • CCALogin.cab Cisco certs expires 3/10 versign 6/12 (CCAWebLogin.ocx 2.3.0.0 not signed) • CiscoNACLoginFacilitator Java signature expiring in march/2010 (taweb.jar expires 3/10 please see attached file) • CCALogin.jar entry was signed on 10/3/08 1:10 PM (X.509, CN=Cisco Systems, OU=INFORMATION SECURITY, O=Cisco Systems, L=San Jose, ST=California, C=US [certificate is valid from 2/25/08 7:00 PM to 3/31/10 7:59 PM]) <p>Note Fixed in Cisco NAC Appliance Release 4.8</p>
CSCtd23998	Yes	<p>Uploading large distribution files should not corrupt the database</p> <p>When files larger than 50MB are uploaded to the CAM for File Distribution requirement types, the database snapshot could become corrupted. This issue has been observed on NAC-3140 CAMs where a distribution file larger than 50MB has been uploaded.</p> <p>Workaround Remove the large distribution file from the CAM and use a Link Distribution requirement type to point users to a download domain where they can retrieve the file.</p>
CSCtd14712	Yes	<p>CAS info missing from new Active CAM when master secret different</p> <p>When the master secret is different on two CAMs in an HA deployment, some critical CAS information may be missing on the secondary (standby) node.</p> <p>Workaround Restore the correct master secret on the incorrect CAM.</p>
CSCtd37076	Yes	<p>Missing “Referral” option for LDAP type</p> <p>Under User Management > Auth Servers for LDAP authentication type, the “Referral” option is missing in the web console for a pull-down menu with options “Manage(Ignore)” and “Handle(Follow)”.</p> <p>Note There is no known workaround for this issue.</p>
CSCtd78468	Yes	<p>Cisco NAC Agent fails to posture WSUS on 64-bit Windows OS</p> <p>When trying to posture assess WSUS on a 64-bit Windows OS, the posture assessment fails and the Agent report displays a “Windows Update Agent is not the correct version” message.</p> <p>This issue has been observed on client machines running 64-bit versions of the Windows Vista or Windows 7 operating system with Cisco NAC Agent version 4.7.1.511 installed.</p> <p>Workaround Use Cisco Rules to posture assess the client machine rather than the WSUS updates.</p>

Table 6 List of Resolved Caveats (Sheet 4 of 4)

DDTS Number	Software Release 4.8	
	Corrected	Caveat
CSCth82967	Yes	<p>AD SSO doesn't start with a redundant AD server</p> <p>When one AD server is down, trying to enable AD SSO with the secondary AD Sever fails and the service is not enabled.</p> <p>The primary reason for this issue is the RMI_READ_TIME_OUT parameter in CAM. This parameter contains the time value for which the CAM waits for a reply from the CAS after a remote method invocation. The current setting for this parameter is 30 seconds. The CAM times out after 30 seconds when there is no reply from the CAS.</p> <p>Workaround Change the timeout value so that the CAM waits for a longer time.</p> <ol style="list-style-type: none"> 1. In the CAM, go to the file /perfigo/control/bin/starttomcat and modify the value of CATALINA_OPTS. 2. Add -D RMI_READ_TIME_OUT=180000 at the end of CATALINA_OPTS. This resets the parameter to 3 minutes. <p>Note This parameter is dependent on the number of KDCS.</p> <ol style="list-style-type: none"> 3. Restart the perfigo service. This change has to be performed on each of the nodes for HA setup.

Resolved Caveats - Cisco NAC Agent Vers 4.8.0.35/Mac OS X Vers 4.8.0.569

Refer to [Enhancements in Release 4.8, page 15](#) for additional information.

Table 7 List of Resolved Caveats (Sheet 1 of 2)

Cisco NAC Agent Version 4.8.0.35/Mac OS X Version 4.8.0.569		
DDTS Number	Corrected	Caveat
CSCs140626	Yes	<p>Cisco NAC Web Agent should handle certificate revocation dialogs similar to persistent Agent</p> <p>Upon logging in via the Cisco NAC Web Agent (with certificate revocation turned on or with Norton 360 installed), the user is presented with a “Revocation information for the security certificate for this site is not available. Do you want to proceed?” dialog box approximately 40 to 50 times. If the user clicks Yes to proceed enough times, the Web Agent fails to login and displays a “You will not be allowed to access the network due to internal error. Please contact your administrator.” message to the user.</p> <p>Workaround There are two potential workarounds for this issue:</p> <ol style="list-style-type: none"> 1. Export the CAS’s root CA certificate and install it in the trusted store on the client machine. 2. Try selecting Yes. If this does not work you can turn off the security certificates revocation check by changing the options in Internet Explorer: <ol style="list-style-type: none"> a. Launch Internet Explorer. b. Select Tools > Internet Options from the menu bar. c. Click the Advanced tab. d. In the Security section, un-check (disable) the “Check for server certificate revocation” option. e. Click Apply. f. Click OK. g. Close the browser window and try web login again.
CSCtd12250	Yes	<p>Incorrect AntiVirus def date is displayed in CAM reports</p> <p>This issue has been observed on client machines with an iAntiVirus def date of 11/05, but the CAM report displays some day in August.</p> <p>Note There is no known workaround for this issue.</p>

Table 7 List of Resolved Caveats (Sheet 2 of 2)

Cisco NAC Agent Version 4.8.0.35/Mac OS X Version 4.8.0.569		
DDTS Number	Corrected	Caveat
CSCte44041	Yes	Microsoft Forefront definition date only detected if user is an Admin The Cisco NAC Agent supports Microsoft Forefront date checking starting from version 4.5.0.0 (and was supposed to be fixed as a result of CSCtb54272 in 4.7.1). However, now the def date is only detected if the user logged into the PC is a local Admin user (or if the agent is run as an Administrator). If the user is not an administrator, the agent shows (and reports to the CAM) a blank date field for the definitions. This causes any date based requirements to fail for those users.
CSCtg73799	Yes	Cisco NAC Agent: Login delay with Microsoft Security Essential
CSCsw49588	Yes	Vista Ultimate: Client pop-up "Cisco NAC Agent UI has stopped working" When Collect Data of Cisco Log Packager is clicked, NAC Agent pops up. When login credentials are entered in the Agent window, an error message is displayed as "Cisco NAC Agent UI has stopped working".
CSCti03452	Yes	NAC Agent fails to restart DHCP Client service
CSCti37690	Yes	JAWS: table summary attribute not read by JAWS while using CTRL+INS+T
CSCth94319	Yes	Agent does not respond during "File Distribution" check if the filename contains "&" character
CSCti96921	Yes	4.8.0 NAC Agent interoperability with pre 4.8 CAM/CAS (PRA packet issue) When client sends PRA packets to CAS with version earlier than 4.8, the Agent throws an error as "Agent user operating system is not supported".
CSCtj05004	Yes	Remove HTTP timer incremental as it causes an increasing timeout loop.
CSCte44041	Yes	Microsoft Forefront definition date is detected only if the user is an admin. If the user is not an admin, the Agent reports a blank date field for the definitions. This causes any date based requirements to fail for those users.

New Installation of Release 4.8

The following steps summarize how to perform new CD software installation of Release 4.8 on supported Cisco NAC Appliance hardware platforms (see [Release 4.8 and Hardware Platform Support, page 3](#) for additional support details).

To upgrade on an existing Cisco NAC Appliance, refer to the instructions in [Upgrading to Release 4.8, page 62](#).

**Note**

The click in the NAC is configured with default settings like default priority, CPU usage etc. The driver loop of the click thread uses the full CPU whenever other processes are idle. The CPU usage of click can reach 99% . As the thread runs with default priority, other processes like tomcat can take over whenever requests come for them. The high CPU usage of click will not lead to any performance issues.

For New Installation:

With Release 4.8, installation occurs in two phases:

1. The software is installed from the CD, and when complete, the CD is ejected from the appliance.
2. The admin logs in and performs the initial configuration.

-
- Step 1** If you are going to perform a new installation but are running a previous version of Cisco NAC Appliance, Cisco recommends backing up your current Clean Access Manager installation and saving the snapshot on your local computer, as described in [General Preparation for Upgrade, page 68](#).
- Step 2** Follow the instructions on your welcome letter to obtain product license files for your installation. See [Licensing, page 2](#) for details. (If you are evaluating Cisco Clean Access, visit <http://www.cisco.com/go/license/public> to obtain an evaluation license.)
- Step 3** Install the latest version of Release 4.8 on each Clean Access Server and Clean Access Manager, as follows:
- a. Log in to the Cisco Software Download Site at <http://www.cisco.com/public/sw-center/index.shtml>. You will likely be required to provide your CCO credentials.
 - b. Navigate to **Security > Endpoint Security > Cisco Network Access Control > Cisco NAC Appliance > Cisco NAC Appliance 4.8**.
 - c. Download the latest Release 4.8 .ISO image (e.g. **nac-4.8-K9.iso**) and burn the image as a bootable disk to a CD-R.

**Note**

Cisco recommends burning the .ISO image to a CD-R using speeds 10x or lower. Higher speeds can result in corrupted/unbootable installation CDs.

- d. Insert the CD into the CD-ROM drive of each installation server, and follow the instructions in the auto-run installer.

- Step 4** After software installation, access the Clean Access Manager web admin console by opening a web browser and typing the IP address of the CAM as the URL. The Clean Access Manager License Form will appear the first time you do this to prompt you to install your FlexLM license files.
- Step 5** Install a valid FlexLM product license file for the Clean Access Manager (either evaluation, starter kit, or individual license).
- Step 6** At the admin login prompt, login with the web console username and password you configured when you installed the Clean Access Manager.
- Step 7** In the web console, navigate to **Administration > CCA Manager > Licensing** to install any additional license files for your CASs, CAM HA pairs or CAS HA pairs. You must install the CAS license to add the CASs to the CAM and an OOB CAS license to enable OOB features on the CAM.
- Step 8** Perform initial configuration of your CAM/CAS according to the instructions in the [Cisco NAC Appliance Hardware Installation Guide, Release 4.8](#).

For additional information on configuring your deployment, including adding the CAS(s) to the CAM, refer to the following guides:

- [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#)
- [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#)



Note

As of Release 4.7(0), Cisco NAC Appliance no longer contains the “www.perfigo.com” Certificate Authority in the .ISO or upgrade image. Administrators requiring the “www.perfigo.com” CA in the network must manually import the CA from a local machine following installation or upgrade to Release 4.8.

In order to establish the initial secure communication channel between a CAM and CAS, you must import the root certificate from each appliance into the other appliance’s trusted store so that the CAM can trust the CAS’s certificate and vice-versa.



Note

Clean Access Manager 4.8 is bundled with version 4.8.0.35 of the Cisco NAC Agent and version 4.8.0.569 of the Mac OS X Agent.



Note

Cisco NAC Appliances assume the keyboard connected to be of US layout for both direct and IP-KVM connections. Use a US layout keyboard or ensure that you know the key mapping if you are connecting a keyboard of different layout.

Upgrading to Release 4.8



Note

To upgrade from Cisco NAC Appliance Release 4.1(8) or earlier to Release 4.8, you must first upgrade your system to Release 4.6(1), 4.7(0), 4.7(1), or 4.7(2) and then upgrade to Release 4.8.



Note

You cannot upgrade your Cisco NAC Appliance deployment from maintenance Release 4.7(3) to Release 4.8 directly. Refer to caveat [CSCtj02066](#), page 54 for more information.



Note

You must upgrade the CAM first prior to upgrading the CAS. Otherwise, you will end up in a situation in which CAS has been upgraded but not the CAM.

This section provides instructions for how to upgrade your existing supported Cisco NAC Appliance platform to Release 4.8. If you need to perform a new CD software installation, refer instead to [New Installation of Release 4.8](#), page 60.

Refer to the following information prior to upgrade:

- [Paths for Upgrading to Release 4.8](#)
- [Changes for 4.8 Upgrade](#)
- [General Preparation for Upgrade](#)

- [Upgrade Instructions for Standalone Machines](#)
- [Upgrade Instructions for HA Pairs](#)

**Caution**

During the upgrade process, new users will not be able to log in or authenticate with Cisco NAC Appliance until the Clean Access Server reestablishes connectivity with the Clean Access Manager.

**Note**

Cisco NAC Appliance 4.8 release includes Cisco NAC Profiler Collector version 3.1.0.24 by default. When upgrading the CAS to a newer Cisco NAC Appliance release, the current version of the Collector is replaced with the default version of the Collector shipped with the Cisco NAC Appliance release. For example, if you are running Release 4.7(2) and Collector 3.1.1, and you upgrade to NAC 4.8, the Collector version will be downgraded to 3.1.0.24. Refer to the [Release Notes for Cisco NAC Profiler](#) for software compatibility matrixes and additional upgrade and product information.

Paths for Upgrading to Release 4.8

Depending on the type of upgrade you are performing, use one of the following sets of guidelines to successfully upgrade your Cisco NAC Appliance release image, Cisco NAC Appliance hardware, or both:

- [Migrating from Customer-Supplied Hardware to Release 4.8 on a NAC-3310/3350/3390 Platform](#)
- [Upgrading an Existing NAC-3310/3350/3390 Platform to Release 4.8](#)
- [Migrating from a NAC-3310/3350/3390 Platform to Release 4.8 on a NAC-3315/3355/3395 Platform](#)

**Note**

If you are upgrading from an earlier Cisco NAC Appliance release on non-Cisco hardware to a next generation Cisco NAC-3315/2255/3395 platform, you must use the new Cisco Migration Utility available on CCO and follow the migration instructions in [Cisco NAC Appliance Migration Guide - Release 4.1\(8\) to Release 4.7\(0\)](#) and then upgrade your system(s) to Release 4.8 according to the guidelines in [Upgrade Instructions for Standalone Machines, page 69](#).

Migrating from Customer-Supplied Hardware to Release 4.8 on a NAC-3310/3350/3390 Platform

**Note**

This procedure only applies to customers upgrading non-Cisco hardware to NAC-3310/3350/3390 platforms.

If you are running the Cisco NAC Appliance software (Release 4.1(x) or earlier) on a non-Cisco NAC Appliance platform, you must purchase Cisco NAC Appliance hardware before you can upgrade your system to Release 4.6(1) or later. You may additionally need to obtain proper FlexLM product licenses. Once you obtain your new Cisco NAC Appliance hardware, Cisco recommends that you:

- Step 1** Create a backup snapshot for the current software version you are running (e.g. 4.1(x) or earlier).
- Step 2** Download and install the same software version on your new Cisco NAC-3310/3350/3390 platform.
- Step 3** Restore the snapshot to your new Cisco NAC Appliance.

- Step 4** If necessary (depending on your existing release version), upgrade your appliance to 4.0(x) or 4.1(x) and then to Release 4.6(1) or 4.7(x).



Note If you are upgrading from a much older version of Cisco Clean Access, you may need to perform an interim upgrade to a version that is supported for upgrade to Release 4.8. In this case, refer to the applicable [Release Notes](#) for upgrade instructions for the interim release. Cisco recommends to always test new releases on a different system before upgrading your production system.

- Step 5** Follow the guidelines in [Upgrade Instructions for Standalone Machines, page 69](#) or [Upgrade Instructions for HA Pairs, page 78](#) (depending on your deployment) to upgrade Cisco NAC Appliance from Release 4.6(1) or 4.7(x) to Release 4.8.

- Step 6** Create a backup snapshot of your upgraded system.

Upgrading an Existing NAC-3310/3350/3390 Platform to Release 4.8



Note This procedure only applies to customers upgrading their existing NAC-3310/3350/3390 platforms to Release 4.8.

The Release 4.8 .ISO installation/upgrade image only supports upgrade from Release 4.6(1), 4.7(0), 4.7(1), and 4.7(2). If you are running an older software version (e.g. Release 4.1(8) or earlier), you must first upgrade your system to one of the supported base releases for Release 4.8 upgrade.

- Step 1** Ensure you have upgraded to Release 4.6(1) or 4.7(x) and create a backup snapshot for your system.
- Step 2** Follow the guidelines in [Upgrade Instructions for Standalone Machines, page 69](#) or [Upgrade Instructions for HA Pairs, page 78](#) (depending on your deployment) to upgrade Cisco NAC Appliance from Release 4.6(1) or 4.7(x) to Release 4.8.
- Step 3** Create a backup snapshot of your upgraded system.

Migrating from a NAC-3310/3350/3390 Platform to Release 4.8 on a NAC-3315/3355/3395 Platform



Note This procedure only applies to customers upgrading from NAC-3310/3350/3390 (non-FIPS) platforms to a next generation (NAC-3315/3355/3395) platform and assumes you are upgrading from Release 4.6(1) or 4.7(x) to Release 4.8.

If you are running the Cisco NAC Appliance software (Release 4.1(x) or earlier) on a NAC-3310/3350/3390 platform and are planning to upgrade to next generation NAC-3315/3355/3395 hardware you must first upgrade your existing system to Release 4.6(1) or later before shifting to a new hardware platform. You may additionally need to obtain proper FlexLM product licenses for your new hardware before upgrading, as well. Once you obtain your next generation NAC-3315/3355/3395 hardware, Cisco recommends that you:

- Step 1** Ensure you have upgraded to Release 4.7(0) and create a backup snapshot for your system.

- Step 2** Download and install the same (Release 4.7(0)) software version on your new NAC-3315/3355/3395 platform.
 - Step 3** Restore the snapshot from your existing NAC-3310/3350/3390 to your new NAC-3315/3355/3395 hardware.
 - Step 4** Follow the guidelines in [Upgrade Instructions for Standalone Machines, page 69](#) or [Upgrade Instructions for HA Pairs, page 78](#) (depending on your deployment) to upgrade Cisco NAC Appliance from Release 4.7(0) to Release 4.8.
 - Step 5** Create a backup snapshot of your upgraded system.
-

Changes for 4.8 Upgrade

Cisco NAC Appliance Release 4.8 is an Early Deployment software maintenance release. Cisco strongly recommends to test new releases on a pilot system prior to upgrading your production system.

If planning to upgrade to Cisco NAC Appliance Release 4.8, note the following:

- [Hardware Considerations](#)
- [Upgrade Changes](#)
- [Features That May Change With Upgrade](#)
- [Password Changes](#)

Hardware Considerations

- You can install Cisco NAC Appliance Release 4.8 on the following Cisco NAC Appliance platforms:
 - NAC-3315, NAC-3355, and NAC-3395 (FIPS or non-FIPS mode)



Note Next generation Cisco NAC Appliance platforms (FIPS or non-FIPS Cisco NAC-3315, NAC-3355, NAC-3395) support fresh installation of Release 4.8 or upgrade from Release 4.7(0), 4.7(1), or 4.7(2) to Release 4.8 only.

- CCA-3140 (EOL), NAC-3310, NAC-3350, and NAC-3390 (non-FIPS mode only)



Note

Due to limited hardware resources on the CCA-3140, some combinations of Release 4.8 features may cause undesirable system behavior. If you are experiencing problems with Release 4.8 on the CCA-3140, please contact the Cisco Technical Assistance Center (TAC).

You cannot install any Cisco NAC Appliance release other than Release 4.7(0) or later on the NAC-3315, NAC-3355, and NAC-3395. You cannot upgrade to or install Release 4.6(1) and later on any non-Cisco platform. See [Hardware Support, page 2](#) for additional details.

- If performing CD software installation on a NAC-3310 based appliance which is not reading the software on the CD ROM drive, refer to [Known Issue with Cisco NAC Appliance CAM/CAS Boot Settings](#).

Upgrade Changes



Warning

If your previous deployment uses a chain of SSL certificates that is incomplete, incorrect, or out of order, CAM/CAS communication may fail after upgrade to Release 4.6(1) and later. You must correct your certificate chain to successfully upgrade. For details on how to fix certificate errors on the CAM/CAS after upgrade to Release 4.6(1) and later, refer to the [How to Fix Certificate Errors on the CAM/CAS After Upgrade](#) Troubleshooting Tech Note.

- Starting from Release 4.7(1), the upgrade process now warns the administrator if the uploaded file for a “File Distribution” requirement type in the CAM database exceeds 50MB. If file size is too large, the upgrade process returns a warning to the administrator, aborts, ejects the Release 4.8 .ISO CD-ROM, and reboots the appliance. Before attempting to perform the upgrade again, the administrator must manually purge “File Distribution” files larger than 50MB from the database using the **CAM Device Management > Clean Access > Clean Access Agent > Requirements > Requirement List** web console page, or move the uploaded file to a network server and create a “Link Distribution” requirement to replace the oversized “File Distribution” requirement. (This issue only affects the CAM, thus there are no changes in upgrade behavior on the CAS.)
- Starting from Release 4.7(1), the upgrade process now warns the administrator if the total compressed size of the CAM database cannot fit in available memory. If the compressed file size is too large, the upgrade process returns a warning to the administrator, aborts, ejects the Release 4.8 .ISO CD-ROM, and reboots the appliance. Before attempting to perform the upgrade again, the administrator must manually purge large files (like large collections of Agent Reports or Event Logs) from the CAM database. Before attempting to perform the upgrade again, the administrator must manually purge large database stores like Agent reports and Event Logs from the database using the **CAM Device Management > Clean Access > Clean Access Agent > Reports > Report Viewer** and **Monitoring > Event Logs > Log Viewer** web console pages, respectively. (This issue only affects the CAM, thus there are no changes in upgrade behavior on the CAS.)
- The **NACAgentCFG.xml** Agent configuration XML file packaged with the Cisco NAC Agent is not preserved after upgrading from Release 4.6(1) to 4.8. You must manually re-import the Agent configuration XML file to maintain client machine login behavior.
- The Cisco NAC Agent does not support Nessus-based network scanning. Nessus-based network scanning capabilities only apply to web login users and Clean Access Agent (Agent version 4.5.2.0 and earlier) users for whom a combination of client network scanning and Agent login functionality has been configured.
- Starting from Release 4.6(1), the CAM no longer manages Clean Access Agent Patch/Upgrade files (CCAAgentUpgrade-4.x.y.z.tar.gz). If you are downgrading or replacing the current version of the Agent on the CAM, be sure you only upload Clean Access Agent installation files (CCAAgentSetup-4.x.y.z.tar.gz or CCAAgentMacOSX-4.x.y.z-k9.tar.gz) from the Cisco Software Download site.
- Users without administrator privileges upgrading their Windows client machine from an earlier version of the Clean Access Agent (version 4.5.2.0 and earlier or version 4.1.10.0 and earlier) to the Cisco NAC Agent must have the **CCAAgentStub.exe** Agent Stub installed on the client machine to facilitate upgrade. (Users with administrator privileges do not need this file.) After successful Cisco NAC Agent installation, the user is not required to have administrator privileges on the client machine, nor is the **CCAAgentStub.exe** Agent Stub file needed. For more information on Agent Stub installers and requirements/prerequisites, see the appropriate [Release Notes](#) for the specific previous version of Cisco NAC Appliance.

- Macintosh client machines require the CAS to have a name-based SSL certificate in order to communicate with Cisco NAC Appliance. Note that if you generate or import a new name-based certificate, you must reboot the CAS using the **service perfigo reboot** or **reboot** command from the CAS CLI.
- When you upgrade the CAM to Release 4.8, the installation process prompts you to upgrade the Agent files to the latest Windows Cisco NAC Agent and Mac OS X Agent versions packaged with the CAM software image (e.g. Cisco NAC Agent version 4.8.0.35, and Mac OS X Agent version 4.8.0.569).
- Release 4.8 includes version 3.1.0 of the Cisco NAC Profiler Collector component that resides on the CAS installations. When upgrading CAS appliances (standalone or HA) to Release 4.8, the upgrade script will check the version of the Collector and only upgrade it if version 3.1.0 is not already installed. Refer to the [Release Notes for Cisco NAC Profiler](#) for software compatibility matrixes and additional upgrade and product information.



Note Cisco NAC Profiler and Cisco NAC Guest Server are not supported in FIPS-compliant deployments in Release 4.7(0) and Release 4.8.

Features That May Change With Upgrade

- If you employed any of the previous Windows registry settings to adjust Windows Clean Access Agent behavior on client machines, you must specify the same settings in the XML Agent configuration file to preserve Agent behavior using the Cisco NAC Agent. For more information, see the “Cisco NAC Agent XML Configuration File Settings” section of the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#).
- For new installations of Cisco NAC Appliance Release 4.5(1) and later, the CAS Fallback behavior enhancement introduces new default values for the **Detect Interval** and **Detect Timeout** settings (20 and 300 seconds, respectively) and requires that the **Detect Timeout** value be at least 15 times the specified **Detect Interval**. You can find these settings at **Device Management > CCA Servers > Manage [CAS_IP] > Filter > Fallback**.
If you are upgrading to Release 4.5(1) and later, however, your existing values for these settings are preserved and you must specify new values for these settings to take advantage of the enhanced CAS Fallback capabilities available in Release 4.5(1).
- When upgrading a VPN SSO Cisco NAC Appliance network to Release 4.8, user login does not work properly **when the user VPN is part of a managed subnet on the CAS**. For more information, see [Known Issue for VPN SSO Following Upgrade to Release 4.5 and Later, page 84](#).

Password Changes

- To offer increased security against potential unauthorized access to Cisco NAC Appliance, the CAM and CAS root admin password you specify during initial system configuration (when performing fresh install or Release 4.8 or reconfiguring the appliance via **service perfigo config**) must now meet strong password standards. However, any existing CAM/CAS root passwords are preserved during upgrade.
- For new installations of Cisco NAC Appliance, there is no longer a default **cisco123** CAM web console password. Administrators must specify a unique password for the CAM web console. However, any existing CAM web console passwords (including the old default **cisco123**) are preserved during upgrade.

For additional details, see also:

- [Hardware Support, page 2](#)
- [Known Issues for Cisco NAC Appliance, page 81](#)

General Preparation for Upgrade

Cisco strongly recommends you review this section carefully before commencing any Cisco NAC Appliance upgrade.



Caution

During the upgrade process, new users will not be able to log in or authenticate with Cisco NAC Appliance until the Clean Access Server reestablishes connectivity with the Clean Access Manager.

- **Homogenous Clean Access Server Software Support**

You must upgrade your Clean Access Manager and all your Clean Access Servers concurrently. The Cisco NAC Appliance architecture is not designed for heterogeneous support (i.e., some Clean Access Servers running 4.8 software and some running 4.6(1) or 4.7(x) software).

- **Upgrade Downtime Window**

Depending on the number of Clean Access Servers you have, the upgrade process should be scheduled as downtime. For minor release upgrades, our estimates suggest that it takes approximately 10 to 20 minutes for the Clean Access Manager upgrade and 10 minutes for each Clean Access Server upgrade. Use this approximation to estimate your downtime window.

- **Upgrade Clean Access Servers Before Clean Access Manager**

Starting with Cisco NAC Appliance Release 4.1(6), the Clean Access Manager and Clean Access Server require encrypted communication. Therefore, you must upgrade CASs *before* the CAM that manages them to ensure the CASs have the same (upgraded) release when the CAM comes back online and attempts to reconnect to the managed CASs.

If you upgrade the Clean Access Manager by itself, the Clean Access Server (which loses connectivity to the CAM during Clean Access Manager restart or reboot) continues to pass authenticated user traffic only if the CAS Fallback Policy specifies that Cisco NAC Appliance should “ignore” traffic from client machines.

- **High Availability (Failover) Via Serial Cable Connection**

When connecting high availability (failover) pairs via serial cable, BIOS redirection to the serial port must be disabled for Cisco NAC Appliance CAMs/CASs, and for any other server hardware platform that supports the BIOS redirection to serial port functionality.



Note If you are upgrading from a Cisco NAC Appliance release older than Release 4.6(1), this upgrade preparation step does not apply.

- **Database Backup (Before and After Upgrade)**

Cisco recommends creating a manual backup snapshot before and after upgrade of your CAM database. The snapshot contains CAM database configuration and CAS configuration for all CASs added to the CAM's domain. Pre- and post-upgrade snapshots allow you to revert to your previous database should you encounter problems during upgrade and preserves your upgraded database as a

baseline after upgrade. Make sure to download the snapshots to another machine for safekeeping. After upgrade, delete all earlier snapshots from the CAM web console as they are no longer compatible.



Warning

You cannot restore a CAM database from a snapshot created using a different release. For example, you cannot restore a 4.5(x), 4.6(1), or 4.7(x) database snapshot to a 4.8 CAM.

- **Backup of necessary files**

Cisco recommends to backup all the necessary files that are not related to the database configuration from the system before running upgrade. For example, any previous database backups and CAM/CAS log files can be backed up.

- **Software Downgrade**

Once you have upgraded your software to Release 4.8, if you wish to revert to your previous version of software, you will need to reinstall the previous version from the CD and recover your configuration based on the backup you performed prior to upgrading to 4.8. See [Upgrade Instructions for Standalone Machines, page 69](#) for additional details.

- **Passwords**

For upgrade via console/SSH, you will need your CAM and CAS `root` user password.

Upgrade Instructions for Standalone Machines

This section describes how to upgrade standalone (i.e. non-HA) CAM/CAS machines from Release 4.6(1) or 4.7(x) to Release 4.8, and only applies to Cisco NAC-3310/3350/3390 or Cisco NAC-3315/3355/3395 platforms. If you have HA CAM/CAS pairs, refer instead to [Upgrade Instructions for HA Pairs, page 78](#).

In Cisco NAC Appliance release 4.8, you can now use a .tar.gz upgrade process similar to that used for upgrading CAM/CAS appliances in earlier releases of Cisco NAC Appliance (like the process used in Release 4.6(1) and Release 4.7(2)) instead of having to perform “in-place” upgrades via an .ISO image on a CD-ROM, as is required to upgrade to Cisco NAC Appliance release 4.7(0) and 4.7(1).

After you have downloaded and copied the upgrade file to the CAM/CAS, you must use the CAM/CAS CLI to extract the upgrade image files and perform the upgrade procedure as described in:

- [Run the Upgrade Script on a Release 4.7\(x\) CAM/CAS, page 72](#)
- [Run the Upgrade Script on a Release 4.6\(1\) CAM/CAS, page 74](#)



Note

You cannot use the Release 4.8 .ISO CD-ROM to perform an upgrade. You must use the .tar.gz upgrade file method.

Review [Changes for 4.8 Upgrade, page 65](#) and [General Preparation for Upgrade, page 68](#) before proceeding with these upgrade instructions.

Summary of Steps for Standalone Upgrade

The steps to upgrade standalone 4.8 systems are as follows:

1. [Create CAM DB Backup Snapshot, page 70](#)
2. [Download the Upgrade File, page 70](#)

3. [Copy the Upgrade File to the CAS/CAM, page 71](#)
4. [Run the Upgrade Script on a Release 4.7\(x\) CAM/CAS, page 72](#) or [Run the Upgrade Script on a Release 4.6\(1\) CAM/CAS, page 74](#)

Create CAM DB Backup Snapshot

This section describes how to back up your current system so that you can retrieve your previous configuration in case there is an issue with the upgrade process.



Note

Release 4.8 upgrades rewrite the appliance's hard-disk. Therefore, Cisco recommends backing up any non-essential data you may have manually archived (like syslog messages, event logs, etc.) onto another machine before beginning the upgrade process.

- Step 1** From the CAM web console, go to the **Administration > Backup** page.
- Step 2** The **Snapshot Tag Name** field automatically populates with a name incorporating the current time and date (e.g. 05_11_10-15-47_snapshot). You can also either accept the default name or type another.
- Step 3** Click **Create Snapshot**. The CAM generates a snapshot file and adds it to the snapshot list at the bottom of the page. The file physically resides on the CAM machine for archiving purposes. The Version field and the filename display the software version of the snapshot for convenience (e.g. **05_11_10-15-47_snapshot_VER_4_7_2.gz**).
- Step 4** For backup, download the snapshot to another computer by clicking the **Tag Name** or the **Download** button for the snapshot to be downloaded.
- Step 5** In the file download dialog, select the **Save File to Disk** option to save the file to your local computer.
- Step 6** After upgrade, delete all earlier snapshots from the CAM web console as they will no longer be compatible.



Note

Cisco NAC Appliance creates automatic snapshots before and after software upgrades and failover events, and preserves the last five entries. For further details, see “Database Recovery Tool” in the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#).

Download the Upgrade File

This section describes how to access and download the upgrade file to your local machine.

- Step 1** Log in to the Cisco Software Download Site at <http://www.cisco.com/public/sw-center/index.shtml>. You will likely be required to provide your CCO credentials.
- Step 2** Navigate to **Security > Endpoint Security > Cisco Network Access Control > Cisco NAC Appliance > Cisco NAC Appliance 4.8**.
- Step 3** Navigate to the Cisco NAC Appliance 4.8 subdirectory, download the latest 4.8 upgrade file (depending on the Cisco NAC Appliance release from which you are upgrading), and save this file to the local computer from which you are accessing the CAM web console.:
 - If upgrading from Release 4.6(1)—download the **cca_upgrade-4.8.0-from-4.6.x.tar.gz** upgrade file

- If upgrading from Release 4.7(x)—download the **cca_upgrade-4.8.0-from-4.7.x.tar.gz** upgrade file

Copy the Upgrade File to the CAS/CAM

This section describes how to copy the upgrade file to the Clean Access Manager and Clean Access Server(s) respectively using [WinSCP](#), [SSH File Transfer](#), or [PSCP](#) as described below.

If Using the Release 4.7(2) or Release 4.6(1) CAM/CAS Web Console

-
- Step 1** Access the CAM software update web console page by navigating to **Administration > CCA Manager > Software Upload** and/or the CAS software upgrade web console page by navigating to **Administration > Software Upload**.
- Step 2** Click **Browse** to navigate to the directory on your local machine where you have stored the Release 4.8 .tar.gz upgrade file. Depending on the Cisco NAC Appliance release from which you are upgrading, the upgrade image name is one of the following:
- If upgrading from Release 4.7(x)—download the **cca_upgrade-4.8.0-from-4.7.x.tar.gz** upgrade file
 - If upgrading from Release 4.6(1)—download the **cca_upgrade-4.8.0-from-4.6.x.tar.gz** upgrade file
- Step 3** Click **Upload**. After a brief time, the web console screen automatically refreshes, displaying the newly uploaded Release 4.8 upgrade image and the date/time when it was uploaded to the CAM/CAS.
-

If Using WinSCP or SSH File Transfer

-
- Step 1** Access the CAM via WinSCP or SSH File Transfer.
- Step 2** Copy the **cca_upgrade-4.8.0-from-4.6.x.tar.gz** or **cca_upgrade-4.8.0-from-4.7.x.tar.gz** file from your local machine to the **/store** directory on the Clean Access Manager.
- Step 3** Access each CAS via WinSCP or SSH File Transfer.
- Step 4** Copy the **cca_upgrade-4.8.0-from-4.6.x.tar.gz** or **cca_upgrade-4.8.0-from-4.7.x.tar.gz** file from your local machine to the **/store** directory on *each* Clean Access Server.
-

If Using PSCP

-
- Step 1** Open a command prompt on your Windows computer.
- Step 2** Cd to the path where your PSCP resides (e.g, C:\Documents and Settings\desktop).
- Step 3** Enter the following command to copy the file to the **/store** directory on the CAM:
- ```
pscp cca_upgrade-4.8.0-from-4.6.x.tar.gz root@<ipaddress_manager>:/store
```
- or
- ```
pscp cca_upgrade-4.8.0-from-4.7.x.tar.gz root@<ipaddress_manager>:/store
```
- Step 4** Enter the following command to copy the file to the **/store** directory on the CAS (copy to each CAS):
- ```
pscp cca_upgrade-4.8.0-from-4.6.x.tar.gz root@<ipaddress_server>:/store
```

or

```
pscp cca_upgrade-4.8.0-from-4.7.x.tar.gz root@<ipaddress_server>:/store
```

## Run the Upgrade Script on a Release 4.7(x) CAM/CAS

This section describes how to untar the upgrade file and run the script to upgrade standalone CAM/CAS machines from release 4.6(1) or 4.7(x) to release 4.8. You will need to login with your CAM and CAS `root` user passwords and access the command line of the CAM or CAS machine using one of the following methods:

- Direct console connection using KVM or keyboard/monitor connected directly to the machine
- SSH connection
- Serial console connection (e.g. HyperTerminal or SecureCRT) from an external workstation connected to the machine via serial cable

When run, the upgrade script automatically determines whether the machine is a Clean Access Manager (CAM) or Clean Access Server (CAS) and executes accordingly.



### Note

The 4.8 upgrade script only executes if the current system is a supported Cisco NAC Appliance platform. Otherwise, the script exits with message “Unable to upgrade, not a recommended hardware platform for 4.8”.

## Step 1: Upgrade the Release 4.7(x) CAS

**Step 1** Connect to the Clean Access Server to upgrade using a console connection, or [Putty](#) or [SSH](#).

**Step 2** Log in as user `root` with root password.

**Step 3** Change directory to `/store`:

```
cd /store
```

**Step 4** Locate the upgrade file. If you used WinSCP, SSH File Transfer, or PSCP, the upgrade filename is `cca_upgrade-4.8.0-from-4.7.x.tar.gz`.

```
ls -l
```

**Step 5** Extract the contents of the downloaded upgrade file:

```
tar xzvf cca_upgrade-4.8.0-from-4.7.x.tar.gz
```

The extraction process automatically places the upgrade files and necessary upgrade script in the `/cca_upgrade-4.8.0` directory.

**Step 6** Change to the `/cca_upgrade-4.8.0` directory and execute the upgrade process:

```
cd cca_upgrade-4.8.0
./UPGRADE.sh
```

**Step 7** Wait for the upgrade to complete. This will take several minutes.

```
Finished upgrading the system to 4.8.0
Upgrade is complete.
Changes require a REBOOT
```

**Step 8** When upgrade is done, reboot the CAS at the prompt:

```
reboot
```

**Step 9** Verify whether or not the upgrade was successful by logging into the CAS CLI and entering the following commands:

```
cd /perfigo/common/bin/
./showstate.sh | grep INCORRECT
```

If you do not see any output from the “grep INCORRECT” portion of the command, then your appliance has been upgraded successfully.

If your system returns any “INCORRECT” statements from the upgrade process, enter `./showstate.sh` again to capture the entire upgrade process output (including all CORRECT and INCORRECT entries) and save it to an easily accessible location on your local machine along with your backup snapshot you created in [Create CAM DB Backup Snapshot, page 70](#) to help debug any upgrade issues.

**Step 10** Repeat steps 1 through 9 for each CAS managed by the CAM.



**Tip**

You can run `cat /perfigo/build` to verify the software version before and after upgrade.

## Step 2: Upgrade the Release 4.7(x) CAM

**Step 1** Connect to the Clean Access Manager to upgrade using a console connection, or [Putty](#) or [SSH](#).

**Step 2** Log in as user `root` with root password.

**Step 3** Change directory to `/store`:

```
cd /store
```

**Step 4** Locate the upgrade file. If you used WinSCP, SSH File Transfer, or PSCP, the upgrade filename is `cca_upgrade-4.8.0-from-4.7.x.tar.gz`.

```
ls -l
```

**Step 5** Extract the contents of the downloaded upgrade file:

```
tar xzvf cca_upgrade-4.8.0-from-4.7.x.tar.gz
```

The extraction process automatically places the upgrade files and necessary upgrade script in the `/cca_upgrade-4.8.0` directory.

**Step 6** Change to the `/cca_upgrade-4.8.0` directory and execute the upgrade process:

```
cd cca_upgrade-4.8.0
./UPGRADE.sh
```

**Step 7** When prompted to update the Windows Agent, specify `y` or `n` to upgrade the Agent or retain the current Agent version.

```
Stopping the perfigo service...
```

```
Currently installed Windows NAC Agent version is 4.7.1.15. Do you want to change the
Windows NAC Agent to version 4.8.0.35 (y/n)? [y] y
```

```
Currently installed Mac Agent version is 4.7.0.2. Do you want to change the Mac Agent to
version 4.8.0.569 (y/n)? [y] y
```

```
Going to upgrade the manager rpm
```

Windows NAC Agent version updated to 4.8.0.35.  
 Mac Agent version updated to 4.8.0.569.

**Step 8** Wait for the upgrade to complete. This will take several minutes.

```
Finished upgrading the system to 4.8.0
Upgrade is complete.
Changes require a REBOOT
```

**Step 9** When upgrade is done, reboot the CAM at the prompt:

```
reboot
```

**Step 10** Verify whether or not the upgrade was successful by logging into the CAM CLI and entering the following commands:

```
cd /perfigo/common/bin/
./showstate.sh | grep INCORRECT
```

If you do not see any output from the “grep INCORRECT” portion of the command, then your appliance has been upgraded successfully.

If your system returns any “INCORRECT” statements from the upgrade process, enter `./showstate.sh` again to capture the entire upgrade process output (including all CORRECT and INCORRECT entries) and save it to an easily accessible location on your local machine along with your backup snapshot you created in [Create CAM DB Backup Snapshot, page 70](#) to help debug any upgrade issues.



**Tip**

You can run `cat /perfigo/build` to verify the software version before and after upgrade.

## Run the Upgrade Script on a Release 4.6(1) CAM/CAS

This section describes how to untar the upgrade file and run the script to upgrade standalone CAM/CAS machines from Release 4.6(1) to Release 4.8. If you are upgrading an existing Release 4.7(x) CAM/CAS, see [Run the Upgrade Script on a Release 4.7\(x\) CAM/CAS, page 72](#). You will need to login with your CAM and CAS `root` user passwords and access the command line of the CAM or CAS machine using one of the following methods:

- Direct console connection using KVM or keyboard/monitor connected directly to the machine
- Serial console connection (e.g. HyperTerminal or SecureCRT) from an external workstation connected to the machine via serial cable

When run, the upgrade script automatically determines whether the machine is a Clean Access Manager (CAM) or Clean Access Server (CAS) and executes accordingly.



**Note**

The 4.8 upgrade script only executes if the current system is a supported Cisco NAC Appliance platform. Otherwise, the script exits with message “Unable to upgrade, not a recommended hardware platform for 4.8”.

### Step 1: Upgrade the Release 4.6(1) CAS

**Step 1** Connect to each machine in the failover pair via console connection (keyboard/monitor/KVM).

**Step 2** Log in as user `root` with root password.

**Step 3** Change directory to `/store`:

```
cd /store
```

**Step 4** Locate the upgrade file. If you used WinSCP, SSH File Transfer, or PSCP, the upgrade filename is `cca_upgrade-4.8.0-from-4.6.x.tar.gz`.

```
ls -l
```

**Step 5** Extract the contents of the downloaded upgrade file:

```
tar xzvf cca_upgrade-4.8.0-from-4.6.x.tar.gz
```

The extraction process automatically places the upgrade files and necessary upgrade script in the `/cca_upgrade-4.8.0` directory.

**Step 6** Change to the `/cca_upgrade-4.8.0` directory and execute the upgrade process:

```
cd cca_upgrade-4.8.0
./UPGRADE.sh
```

**Step 7** Specify whether you want to run the upgrade session via direct console connection or over a serial console line.

After setting up the system for upgrade, upgrade will run in Standard or Serial console as per selection below. Please choose one of the following actions:

- 1) Upgrade over Standard console (monitor and keyboard).
- 2) Upgrade over Serial console.
- 3) Upgrade without user interaction.
- 4) Exit upgrade.

```
3
```



**Note**

When you perform this upgrade on a Cisco NME-NAC network module, the option to perform the upgrade over the serial console connection is not available.

**Step 8** When prompted, enter the Master Secret for the CAS.

The master secret is used to encrypt sensitive data. Remember to configure all HA pairs with the same secret. Please enter the master secret:  
Please confirm the master secret:

After reboot, upgrade will proceed without user interaction. Upgrade will take 20-30 minutes to complete. Once upgrade completes, machine is rebooted and will be available for ssh login.

After logging back in, please check the log at `/root/nac-install.log`. If the upgrade is successful, the log file should contain "Upgrade completed successfully."

```
nac-upgrade: ready to reboot. Press <ENTER> to reboot
```



**Note**

The above text is displayed when you have selected the "Upgrade without user interaction" option in Step 7. For the other options in Step 7, the text may be different. Follow the instructions that appear on the screen to proceed.

**Step 9** Press **Enter** and wait for the upgrade to complete. The time taken for an upgrade depends on both the appliance configuration and database size.

**Step 10** After the upgrade is complete, make sure that the appliance is up. Use the **ping** command to make sure that the appliance is reachable.

```
ping <appliance IP address>
```

Once the appliance is reachable, SSH into the appliance to verify connectivity before proceeding with the set up for the CAM.

**Step 11** Verify whether or not the upgrade was successful by logging into the CAS CLI and entering the following commands:

```
cd /perfigo/common/bin/
./showstate.sh | grep INCORRECT
```

If you do not see any output from the “grep INCORRECT” portion of the command, then your appliance has been upgraded successfully.

If your system returns any “INCORRECT” statements from the upgrade process, enter `./showstate.sh` again to capture the entire upgrade process output (including all CORRECT and INCORRECT entries) and save it to an easily accessible location on your local machine along with your backup snapshot you created in [Create CAM DB Backup Snapshot, page 70](#) to help debug any upgrade issues.

**Step 12** Repeat steps 1 through 11 for each CAS managed by the CAM.



**Tip** You can run `cat /perfigo/build` to verify the software version before and after upgrade.

## Step 2: Upgrade the Release 4.6(1) CAM



**Note** This upgrade procedure automatically updates the Cisco NAC Agent and Mac OS X Agent to the latest versions packaged with the Release 4.8 .tar.gz upgrade image.

**Step 1** Connect to each machine in the failover pair via console connection (keyboard/monitor/KVM).

**Step 2** Log in as user `root` with root password.

**Step 3** Change directory to `/store`:

```
cd /store
```

**Step 4** Locate the upgrade file. If you used WinSCP, SSH File Transfer, or PSCP, the upgrade filename is `cca_upgrade-4.8.0-from-4.6.x.tar.gz`.

```
ls -l
```

**Step 5** Extract the contents of the downloaded upgrade file:

```
tar xzvf cca_upgrade-4.8.0-from-4.6.x.tar.gz
```

The extraction process automatically places the upgrade files and necessary upgrade script in the `/cca_upgrade-4.8.0` directory.

**Step 6** Change to the `/cca_upgrade-4.8.0` directory and execute the upgrade process:

```
cd cca_upgrade-4.8.0
```

```
./UPGRADE.sh
```

- Step 7** Specify whether you want to run the upgrade session via direct console connection or over a serial console line.

After setting up the system for upgrade, upgrade will run in Standard or Serial console as per selection below. Please choose one of the following actions:

- 1) Upgrade over Standard console (monitor and keyboard).
- 2) Upgrade over Serial console.
- 3) Upgrade without user interaction.
- 4) Exit upgrade.

```
3
```



- Note** When you perform this upgrade on a Cisco NME-NAC network module, the option to perform the upgrade over the serial console connection is not available.

- Step 8** When prompted, enter the Master Secret for the CAM.

The master secret is used to encrypt sensitive data. Remember to configure all HA pairs with the same secret. Please enter the master secret:  
Please confirm the master secret:

After reboot, upgrade will proceed without user interaction. Upgrade will take 20-30 minutes to complete. Once upgrade completes, machine is rebooted and will be available for ssh login.

After logging back in, please check the log at /root/nac-install.log. If the upgrade is successful, the log file should contain "Upgrade completed successfully."

```
nac-upgrade: ready to reboot. Press <ENTER> to reboot
```

- Step 9** Press **Enter** and wait for the upgrade to complete. The time taken for an upgrade depends on both the appliance configuration and database size.

- Step 10** After the upgrade is complete, make sure that the appliance is up. Use the **ping** command to make sure that the appliance is reachable.

```
ping <appliance IP address>
```

Once the appliance is reachable, SSH into the appliance to verify connectivity.

- Step 11** Verify whether or not the upgrade was successful by logging into the CAM CLI and entering the following commands:

```
cd /perfigo/common/bin/
./showstate.sh | grep INCORRECT
```

If you do not see any output from the “grep INCORRECT” portion of the command, then your appliance has been upgraded successfully.

If your system returns any “INCORRECT” statements from the upgrade process, enter `./showstate.sh` again to capture the entire upgrade process output (including all CORRECT and INCORRECT entries) and save it to an easily accessible location on your local machine along with your backup snapshot you created in [Create CAM DB Backup Snapshot, page 70](#) to help debug any upgrade issues.

**Tip**


---

You can run `cat /perfigo/build` to verify the software version before and after upgrade.

---

## Upgrade Instructions for HA Pairs

In Cisco NAC Appliance release 4.8, you can now use a .tar.gz upgrade process similar to that used for upgrading CAM/CAS appliances in earlier releases of Cisco NAC Appliance (like the process used in Release 4.6(1) and Release 4.7(2)) instead of having to perform “in-place” upgrades via an .ISO image on a CD-ROM, as is required to upgrade to Cisco NAC Appliance release 4.7(0) and 4.7(1).

See [Release 4.8 Upgrade Instructions for HA Pairs, page 78](#) to upgrade your HA Pair CAM/CAS appliances.

### Release 4.8 Upgrade Instructions for HA Pairs

This section describes how to upgrade high-availability (HA) pairs of CAM or CAS servers from Release 4.6(1) or 4.7(x) to Release 4.8, and only applies to Cisco NAC-3310/3350/3390 or Cisco NAC-3315/3355/3395 platforms. If you have standalone CAM/CAS servers, refer instead to [Upgrade Instructions for Standalone Machines, page 69](#).

**Note**


---

You cannot use the Release 4.8 .ISO CD-ROM to perform an upgrade. You must use the .tar.gz upgrade file method.

---

**Note**


---

To support FIPS 140-2 compliance, HA CAMs/CASs automatically establish an IPsec tunnel to ensure all communications between the HA pair appliances remains secure across the network.

---

**Warning**


---

**If you are using serial connection for HA, do not attempt to connect serially to the CAS during the upgrade procedure. When serial connection is used for HA, serial console/login will be disabled and serial connection cannot be used for installation/upgrade.**

---

**If you are using serial connection for HA, BIOS redirection to the serial port must be disabled for Cisco NAC Appliance CAMs/CASs, and for any other server hardware platform that supports the BIOS redirection to serial port functionality.**

---

**Note**


---

If you are changing the master secret for the CAM, ensure that both the CAMs are configured with the same master secret. If the master secret is different, when the standby CAM tries to come up, the perfigo service is stopped. Refer to [CSCtd14712, page 57](#) for more details.

---

**Note**


---

For additional details on CAS HA requirements, see also [Supported Hardware and System Requirements for Cisco NAC Appliance \(Cisco Clean Access\)](#).

---

Review [Changes for 4.8 Upgrade, page 65](#) and [General Preparation for Upgrade, page 68](#) before proceeding with these upgrade instructions.

## Upgrading HA-CAM and HA-CAS Pairs

The following steps show the recommended way to upgrade an existing high-availability (failover) pair of Clean Access Managers or Clean Access Servers.



### Warning

**Make sure to carefully execute the following procedure to prevent the CAM database from getting out of sync.**

- Step 1** Download and save the upgrade file to your local PC, as described in [Download the Upgrade File, page 70](#). Be sure you download the correct file, depending upon the existing Cisco NAC Appliance release from which you are upgrading:
- If upgrading from Release 4.7(x)—download the **cca\_upgrade-4.8.0-from-4.7.x.tar.gz** upgrade file
  - If upgrading from Release 4.6(1)—download the **cca\_upgrade-4.8.0-from-4.6.x.tar.gz** upgrade file
- Step 2** From either a console connection (keyboard/monitor/KVM) or via SSH, connect to the individual IP address of each machine in the failover pair.



**Note** Do not connect to the Service IP of the pair, as you will lose connection during the upgrade.

- Step 3** Copy the upgrade image to each CAM/CAS machines' **/store** directory as described in [Copy the Upgrade File to the CAS/CAM, page 71](#).
- Step 4** Login as the **root** user with the root password.
- Step 5** Change directory to **/store**:
- ```
cd /store
```
- Step 6** Locate the upgrade file. If you used WinSCP, SSH File Transfer, or PSCP, the upgrade filename is **cca_upgrade-4.8.0-from-4.6.x.tar.gz** or **cca_upgrade-4.8.0-from-4.7.x.tar.gz**, depending on the Cisco NAC Appliance release from which you are upgrading.
- ```
ls -l
```
- Step 7** Extract the contents of the downloaded upgrade file:
- ```
tar xzvf cca_upgrade-4.8.0-from-4.7.x.tar.gz
```
- or
- ```
tar xzvf cca_upgrade-4.8.0-from-4.6.x.tar.gz
```

The extraction process automatically places the upgrade files and necessary upgrade script in the **/cca\_upgrade-4.8.0** directory.

- Step 8** Before proceeding, determine the failover state on each machine by changing directory and running the **fostate.sh** command on each machine:
- ```
cd /perfigo/common/bin/
./fostate.sh
```

The results should be either “My node is active, peer node is standby” or “My node is standby, peer node is active”. No nodes should be dead. This should be done on both appliances, and the results should be that one appliance considers itself active and the other appliance considers itself in standby mode. Future references in these instructions that specify “active” or “standby” refer to the results of this test as performed at this time.

**Note**

The `fostate.sh` command is part of the upgrade script. You can also determine which appliance is active or standby as follows:

- Access the web console as described in “Accessing Web Consoles in High Availability Pairs” sections of the “Configuring High Availability” chapter in the *Cisco NAC Appliance Hardware Installation Guide, Release 4.8*.
- SSH to the Service IP of the CAM/CAS pair, and type `ifconfig eth0`. The Service IP will always access the active CAM or CAS, with the other pair member acting as standby.

Step 9 Stop services on the standby appliance by entering the following command via the console/SSH terminal:

For CAM—`service perfigo stop`

For CAS—`service perfigo maintenance`

Step 10 Wait until the standby appliance has suspended services.

Step 11 Change directory and run the `fostate.sh` command on the active appliance:

```
cd /perfigo/common/bin/
./fostate.sh
```

Make sure this returns “My node is active, peer node is dead” before continuing.

Step 12 Upgrade the active appliance as follows:

- Make sure the upgrade package is untarred in the `/store` directory on the active appliance.
- From the untarred upgrade directory created on the active appliance (for example `cca_upgrade-4.8.0`), run the upgrade script on the active appliance:

```
./UPGRADE.sh
```

- For the CAM only, when prompted to update the Windows Agent, specify `y` or `n` to upgrade the Agent or retain the current Agent version.

```
Please choose whether to upgrade Windows Agent to 4.8.0.35 (It's highly recommended to
upgrade) (y/n)? [y]
```

```
Please choose whether to upgrade Mac Agent to 4.8.0.569 (It's highly recommended to
upgrade) (y/n)? [y]
```

Step 13 After the upgrade is completed, stop services on the active appliance by entering the following command via the console/SSH terminal:

```
service perfigo stop
```

Wait until the active appliance has suspended services.

Step 14 Restart services on the standby appliance by entering the following command via the console/SSH terminal:

```
service perfigo start
```

Step 15 Upgrade the standby appliance as follows:

- Make sure the upgrade package is untarred in the `/store` directory on the standby appliance.
- Change to the untarred upgrade directory created on the standby appliance:

```
cd cca_upgrade-4.8.0
```

c. Run the upgrade script on the standby appliance:

```
./UPGRADE.sh
```

d. For the CAM only, when prompted to update the Windows Agent, specify **y** or **n** to upgrade the Agent or retain the current Agent version.

```
Please choose whether to upgrade Windows Agent to 4.8.0.35 (It's highly recommended to upgrade) (y/n)? [y]
```

```
Please choose whether to upgrade Mac Agent to 4.8.0.569 (It's highly recommended to upgrade) (y/n)? [y]
```

Step 16 Verify whether or not the upgrade was successful by logging into the CLI of each CAM/CAS upgraded in the HA pair and entering the following commands:

```
cd /perfigo/common/bin/  
./showstate.sh | grep INCORRECT
```

If you do not see any output from the “grep INCORRECT” portion of the command, then your appliance has been upgraded successfully.

If your system returns any “INCORRECT” statements from the upgrade process, enter `./showstate.sh` again to capture the entire upgrade process output (including all CORRECT and INCORRECT entries) and save it to an easily accessible location on your local machine along with your backup snapshot you created in [Create CAM DB Backup Snapshot, page 70](#) to help debug any upgrade issues.

Step 17 After the upgrade is completed, stop services on the standby appliance by entering the following command via the console/SSH terminal:

```
service perfigo stop
```

Step 18 Reboot the active appliance by entering the following command via the console/SSH terminal:

```
reboot
```

Wait until it is running normally and you are able to connect to the web console.

Step 19 Reboot the standby appliance by entering the following command via the console/SSH terminal:

```
reboot
```



Note

There will be approximately 2-5 minutes of downtime while the appliances reboot.

Known Issues for Cisco NAC Appliance

This section describes known issues when integrating Cisco NAC Appliance:

- [Known Issue with CAS-to-CAM Certificate Verification in Internet Explorer](#)
- [Known Issue with Delayed IP Address Refresh for Windows 7/Vista Clients Running Cisco NAC Agent](#)
- [Known Issue with Enabling Web Login for Windows 7 Starter Edition Clients](#)
- [Known Issue with Mass DHCP Address Deletion](#)
- [Known Issue for VPN SSO Following Upgrade to Release 4.5 and Later](#)

- [Known Issues with Web Upgrade in Release 4.1\(3\), 4.1\(6\), and 4.1\(8\)](#)
- [Known Issue with Active HA CAM Web Console Following Failover](#)
- [Known Issue with Cisco NAC Appliance CAM/CAS Boot Settings](#)
- [Known Issue with IP Packet Fragmentation Leading to Disconnect Between CAS and Agent](#)
- [Known Issues with Switches](#)
- [Known Issues with Cisco 2200/4400 Wireless LAN Controllers \(Airespace WLCs\)](#)
- [Known Issue for Windows Vista and IP Refresh/Renew](#)

Known Issue with CAS-to-CAM Certificate Verification in Internet Explorer

When launching the CAM web console in Release 4.8 using Internet Explorer, you may see a “Choose a digital certificate” pop-up dialog with no options available in the selection window. This pop-up is a result of the way the CAM verifies CAS-to-CAM certificates for communication. If you click **OK** or **Cancel**, the dialog disappears and you can continue the web console session normally. If you want to ensure this pop-up does not appear in the future, you can apply the following custom security setting in Internet Explorer:

1. Go to **Tools > Internet Options**, click on the **Security** tab, and click **Custom Level**.
2. Scroll down and enable the **Don't prompt for client certificate selection when no certificate or only one certificate exists** option.
3. Click **OK**.



Note

This issue has not been observed when accessing the CAM with Mozilla Firefox or Google Chrome browsers.

Known Issue with Delayed IP Address Refresh for Windows 7/Vista Clients Running Cisco NAC Agent

The IP address release/renew process for Windows 7 and Windows Vista client machines running Cisco NAC Agent version 4.8.0.x that move from the authentication to access VLAN can take as long as 4 minutes to complete.

This situation can occur when the Network Connectivity Status Indicator, which is part of the Network Location Awareness in Windows, tries to reach the **msftncsi.com** web page while refreshing the client machines IP address. When the client machine cannot reach this page, Windows 7 and Windows Vista take longer to sense the machine's status, thus slowing down applications requiring internet access.

For reference, see:

- [http://technet.microsoft.com/en-us/library/cc766017\(WS.10\).aspx](http://technet.microsoft.com/en-us/library/cc766017(WS.10).aspx)
- [http://technet.microsoft.com/en-us/library/ee126135\(WS.10\).aspx](http://technet.microsoft.com/en-us/library/ee126135(WS.10).aspx)

To resolve this issue, open the following sites using host traffic policies in any user roles associated with the client login session (Unauthenticated/Quarantine, Temporary, and standard user login roles):

- `ncsi.glb dns.microsoft.com equals Microsoft NCSI check`
- `.msftncsi.com ends Microsoft NCSI check`

The administrator can also use a utility like Microsoft SMS to pass a registry update disabling this option in the Windows registry on client machines.

See [CSCtg06599](#) for more information.

Known Issue with Enabling Web Login for Windows 7 Starter Edition Clients



Note

This known issue applies only to Cisco NAC Agent version 4.7.1.511 and Cisco NAC Web Agent version 4.7.1.504. The latest versions of the Cisco NAC Agent (version 4.7.2.10 and later) and Cisco NAC Web Agent (version 4.7.2.5 and later) support Windows 7 Starter Edition.

Cisco NAC Agent version 4.7.1.511 and Cisco NAC Web Agent version 4.7.1.504 do not support Windows 7 Starter Edition. Client machines with the Windows 7 Starter Edition operating system can only perform web login to verify user credentials when logging into the network via Cisco NAC Appliance Release 4.7(1). The solution to simultaneously provide Cisco NAC Appliance support for web login on Windows 7 Starter Edition client machines as well as Agent login for other Windows operating systems requires the administrator to add a web login page that classifies Windows 7 Starter Edition in a “WINDOWS_ALL” operating system context. To enable web login functions for client machines running Windows 7 Starter Edition:

- Users must perform web login using Internet Explorer version 8.0 with ActiveX only (Java Applet is not supported)
- The Cisco NAC Appliance administrator must use the **CAM Administration > User Pages > Login Page** web console page to create a login page for the “WINDOWS_ALL” operating system that:
 - Requires the “ActiveX Only” Web Client setting
 - Enables the “Use web client to detect MAC address and Operating System” option to appropriately reflect the Windows 7 Starter Edition operating system on the client machine

Known Issue with Mass DHCP Address Deletion

An issue exists in Release 4.5(1) and later where a Clean Access Server configured to be a DHCP server can become unmanageable if the administrator attempts to delete more than 800 DHCP addresses from the appliance using the Clean Access Manager web console. If you have more than 800 DHCP addresses, Cisco recommends deleting addresses in smaller blocks of no more than 800 addresses at a time.

In addition to ensuring you do not delete more than 800 DHCP addresses at a time, there are two methods to work around this potential issue.

Workaround 1

The DHCP IP delete can be done manually by connecting to the CLI and executing the following commands:

```
service perfigo stop
rm -f /var/state/dhcp/dhcpd.leases
touch /var/state/dhcp/dhcpd.leases
service perfigo start
```

If on an HA system, Cisco strongly recommends taking the CASs offline and performing the commands on both machines simultaneously, taking particular care to issue the **service perfigo start** on the two appliances at roughly the same time.

Workaround 2

If you experience this problem more than once, Cisco recommends changing the Clean Access Manager timeout value by editing the `/perfigo/control/bin/starttomcat` file and adding “-DRMI_READ_TIME_OUT=<new value>” to the end of the CATALINA_OPTS options string. (The current default value is 60 seconds, and Cisco does not recommend increasing the timeout value to any more than 300 seconds.) Please note that increasing the read time out value can likely lower the resiliency of WAN deployments, thus reversing the CAM/CAS connectivity improvements introduced when Cisco addressed caveat CSCsw20607 in the [Release Notes for Cisco NAC Appliance, Version 4.5\(1\)](#).

**Note**

In Release 4.6(1) and later, the CAM only allows 60 seconds for a response on remote calls to the CAS. This impacts deleting hundreds of DHCP IPs at once, particularly on slower CAS hardware platforms. Cisco recommends that you do not delete any more than 3 class C address segments at once.

For more information, see [CSCsx35438](#), page 33.

Known Issue for VPN SSO Following Upgrade to Release 4.5 and Later

When you upgrade your Cisco NAC Appliance network employing VPN SSO to Release 4.5 and later, user login does not work properly **when the user VPN is part of a managed subnet on the CAS**.

In Release 4.5 and later, the SWISS protocol checks the MAC address for Layer 2 clients, but the MAC address reported by the Agent (which is the real client MAC address) is different from the one the CAS gets for the client (the VPN concentrator MAC address). As a result, the SWISS protocol tells the Agent that the client machine is not logged in (due to the different MAC addresses recorded) and the Agent launches the login dialog repeatedly, never able to complete login. Prior to Release 4.5, the Clean Access Server associates the client with the VPN IP address and VPN Concentrator’s MAC address after the first login. From there, the SWISS protocol only checks the IP address from the Agent and reports back to the Agent that the client is logged in (regardless of whether the client is connected via Layer 2 or Layer 3).

To work around this issue, remove the subnet making up the client machine address pool from the collection of managed subnets and create a Layer 3 static route on the CAS untrusted interface (eth1) with VPN concentrator’s IP address as the gateway for the VPN subnet using the CAM web console **Device Management > CCA Servers > Manage [CAS_IP] > Advanced > Static Routes** page.

Known Issues with Web Upgrade in Release 4.1(3), 4.1(6), and 4.1(8)

In Cisco NAC Appliance Release 4.8, web upgrade is no longer supported and cannot be used to upgrade Cisco NAC Appliances on Release 4.1(3) and later. To upgrade your Cisco NAC Appliances from Release 4.1(3) and later, you must run the upgrade script via the in-place Install/Upgrade CD method, as described in [Upgrading to Release 4.8](#), page 62.

**Note**

To upgrade from Cisco NAC Appliance Release 4.1(8) or earlier to Release 4.8, you must first upgrade your system to Release 4.6(1), 4.7(0), 4.7(1), or 4.7(2) and then upgrade to Release 4.8.

Known Issue with Active HA CAM Web Console Following Failover

For a brief period following a failover event, the administrator web console for the newly “active” CAM retains the limited menu/submenu options previously available while the machine was still the “standby” CAM.

To manually reproduce this scenario:

1. Configure the HA-CAM failover pair.
2. Issue the `service perfigo stop` CLI command on both HA-CAMs to stop services.
3. Issue the `service perfigo start` CLI command on the HA-Standby CAM to restart services.
4. As soon as the `service perfigo start` command finishes, access the HA-Service IP address in a browser for the administrator web console, enter authentication credentials, and click **Login**.
5. The CAM HA-Service IP administrator web console displays the limited menu/submenu options previously available while the machine was still the “standby” CAM.

To get the administrator web console to display properly, simply reload (Ctrl-refresh) the CAM HA-Service IP/hostname web page to display the full GUI for the now “active” CAM.

Known Issue with Cisco NAC Appliance CAM/CAS Boot Settings

When performing CD software installation, if a Cisco NAC Appliance CAM/CAS does not read the software on the CD ROM drive, and instead attempts to boot from the hard disk, you will need to configure the appliance BIOS settings to boot from CD ROM before attempting to re-image or upgrade the appliance from CD. For detailed steps, refer to the “Configuring Boot Settings on the Cisco NAC Appliance CAM/CAS” section of the *Cisco NAC Appliance Hardware Installation Guide, Release 4.8*.

Client machines going across a GRE tunnel in the network are unable to authenticate and the agent doesn't popup.

Known Issue with IP Packet Fragmentation Leading to Disconnect Between CAS and Agent

TCP traffic between the Agent and CAS can break down if the overall network path MTU is smaller than the MTU needed for the CAS to send unfragmented packets and the packet coming from the CAS to the Agent has the “do not fragment” setting enabled.



Note

This scenario has been observed with TCP SSL packets and generally only applies to authentication, posture, and discovery host traffic. This issue does not apply to traffic that is not directed specifically to the CAS/Discovery Host.

To address this issue, apply one of the following solutions to your network:

- Set the IP TCP adjust-mss for the GRE tunnel according to the guidelines at http://www.cisco.com/en/US/docs/ios/12_2t/12_2t4/feature/guide/ft_admss.html.
- Remove the “do not fragment” setting from the packet using a route map, as described in http://www.cisco.com/en/US/tech/tk827/tk369/technologies_white_paper09186a00800d6979.shtml

Example configuration:

```

interface FastEthernet0/0
 ip address 10.32.32.101 255.255.255.0
 ip policy route-map removedontfrag
 duplex auto
 speed auto
!
access-list 101 permit tcp host 10.255.253.152 any
access-list 101 permit tcp host 10.255.252.152 any
access-list 101 permit tcp host 1.1.1.1 any
!
route-map removedontfrag permit 10
 match ip address 101
 set ip df 0

```

NOTE: 10.255.253.152 is the trusted IP Address of the CAS

NOTE: 10.255.252.152 is the trusted IP Address of the CAS

NOTE: 1.1.1.1 is the discovery host resolved IP Address.

Known Issues with Switches

For complete details, see [Switch Support for Cisco NAC Appliance](#).

Known Issues with Cisco 2200/4400 Wireless LAN Controllers (Airespace WLCs)

Due to changes in DHCP server operation with Cisco NAC Appliance Release 4.0(2) and later, networks with Cisco 2200/4400 Wireless LAN Controllers (also known as Airespace WLCs) which relay requests to the Clean Access Server (operating as a DHCP server) may have issues. Client machines may be unable to obtain DHCP addresses. Refer to the “Cisco 2200/4400 Wireless LAN Controllers (Airespace WLCs) and DHCP” section of [Switch Support for Cisco NAC Appliance](#) for detailed instructions.

**Note**

For further details on configuring DHCP options, refer to the applicable version of the [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

**Note**

This known issue does not affect Wireless Out-of-Band deployments because CASs are only deployed in Virtual Gateway mode, thus the CAS is not configured to perform any DHCP functions.

Known Issue for Windows Vista and IP Refresh/Renew

When logged in as a machine admin on Windows Vista and using web login with IP refresh configured, IP address refresh/renew via ActiveX or Java will fail due to the fact that Internet Explorer does not run as an elevated application and Vista requires elevated privileges to release and renew an IP address.

Workaround

In order to use the IP refresh feature, you will need to:

1. Log into the Windows Vista client as an administrator.

2. Create a shortcut for IE on your desktop.
3. Launch it by right-clicking the shortcut and running it as administrator. This will allow the application to complete the IP Refresh/Renew. Otherwise, the user will need to do it manually via Command Prompt running as administrator. This is a limitation of the Windows Vista OS.

See also [CSCsm61077](#), page 26.

Troubleshooting

This section provides troubleshooting information for the following topics:

- [Enabling TLSv1 on Internet Explorer Version 6](#)
- [Windows Vista and Windows 7—IE 7 and IE 8 Certificate Revocation List](#)
- [HA Active-Active Situation Due to Expired SSL Certificates](#)
- [Agent AV/AS Rule Troubleshooting](#)
- [Debug Logging for Cisco NAC Appliance Agents](#)
- [Creating CAM/CAS Support Logs](#)
- [Recovering Root Password for CAM/CAS](#)
- [Troubleshooting CAM/CAS Certificate Issues](#)
- [Troubleshooting Switch Support Issues](#)
- [Other Troubleshooting Information](#)



Note

For additional troubleshooting information, see also [New Installation of Release 4.8, page 60](#).

Enabling TLSv1 on Internet Explorer Version 6

Cisco NAC Appliance network administrators managing the CAM/CAS via web console *and* client machine browsers accessing a FIPS-compliant Cisco NAC Appliance Release 4.7(0) network require TLSv1 in order to “talk” to the network, which is disabled by default in Microsoft Internet Explorer Version 6.

To locate and enable this setting in IE version 6:

-
- Step 1** Got to **Tools > Internet Options**.
 - Step 2** Select the **Advanced** tab.
 - Step 3** Scroll down to locate the **Use TLS 1.0** option under **Security**.
 - Step 4** Click on the checkbox to enable the **Use TLS 1.0** option and click **Apply**.
 - Step 5** If necessary, close the browser and open a new one where the TLS 1.0 option should now be automatically enabled.
-



Note

This option is enabled by default in Microsoft Internet Explorer versions 7 and 8 and Mozilla Firefox has not shown this limitation.

Windows Vista and Windows 7—IE 7 and IE 8 Certificate Revocation List



Note

In Internet Explorer versions 7 and 8, the “Check for server certificate revocation (requires restart)” checkbox is enabled **by default** under IE's Tools > Internet Options > Advanced | Security settings.

In Release 4.6(1) and later, you can use the “AllowCRLChecks” attribute in the **NACAgentCFG.xml** file to turn off Certificate Revocation List (CRL) checking for the Cisco NAC Agent during discovery and negotiation with the CAS. For details, see the “Cisco NAC Agent XML Configuration File Settings” section in the *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8*.

The “Network error: SSL certificate rev failed 12057” error can occur and prevent login for Clean Access Agent or Cisco NAC Web Agent users in either of the following cases:

1. The client system is using Microsoft Internet Explorer version 7 or 8 and/or the Windows Vista or Windows 7 operating system, and the certificate issued for the CAS is not properly configured with a CRL (Certificate Revocation List).
2. A temporary SSL certificate is being used for the CAS and:
 - The user has not imported this certificate to the trusted root store.
 - The user has not disabled the “Check for server certificate revocation (requires restart)” checkbox in IE.

To resolve this issue, perform the following actions:

-
- Step 1** (**Preferred**) When using a CA-signed CAS SSL certificate, check the “CRL Distribution Points” field of the certificate (including intermediate or root CA), and add the URL hosts to the allowed Host Policy of the Unauthenticated/Temporary/Quarantine Roles. This will allow the Agent to fetch the CRLs when logging in.
- Step 2** Or, if continuing to use temporary certificates for the CAS, the user will need to perform ONE of the following actions:
- a. Import the certificate to the client system's trusted root store.
 - b. Disable the “Check for server certificate revocation (requires restart)” checkbox under IE's Tools > Internet Options > Advanced | Security settings.
-

HA Active-Active Situation Due to Expired SSL Certificates

HA communication for both HA-CAMs and HA-CASs is handled over IPSec tunnels to secure all communications between the two HA pair appliances. This IPSec tunnel is negotiated based on the SSL certificates uploaded to the HA pairs for both CAM and CAS. In case the SSL certificates are not trusted by the two HA peers, have expired, or are no longer valid, the HA heartbeat communication between the two HA pairs breaks down, leading both HA pair appliances to assume the Active HA-Primary) role.

For CASs deployed in VGW mode, this can potentially create a Layer 2 loop that could bring down the network. HA-CAMs with expired or invalid SSL certificates could lead to an Active-Active situation where the database is not synced between the two HA-CAM appliances. Eventually, this situation leads to the CAMs losing all recent configuration changes and/or all recent user login information following an HA-CAM failover event.

As HA communication over IPSec tunnels requires valid SSL certificates on both the CAM and CAS, the CAM-CAS communication also breaks down if the SSL certificate expires on either the CAM or CAS. This situation leads to end user authentications failures and the CAS reverting to fallback mode per CAS configuration.

Administrators can minimize HA appliance Active-Active situations due to expired SSL certificates by using SSL certificates with longer validity periods and/or using serial port connection (if available and not used to control another CAM or CAS) for HA heartbeat. However, when you configure HA-CAMs to perform heartbeat functions over the serial link and the primary eth1 interface fails because of SSL certificate expiration, the CAM returns a database error indicating that it cannot sync with its HA peer and the administrator receives a “WARNING! Closed connections to peer [standby IP] database! Please restart peer node to bring databases in sync!!” error message in the CAM web console.



Note

Starting with Cisco NAC Appliance Release 4.7(0), the CAM or CAS generates event log messages to indicate the certificate expiry in addition to the message displayed in the CAM/CAS web console.



Note

The self-signed SSL certificate expires after 90 days from the date of generation.

Agent AV/AS Rule Troubleshooting

When troubleshooting AV/AS Rules:

- View administrator reports for the Agent from **Device Management > Clean Access > Clean Access Agent > Reports**
- Or, to view information from the client, right-click the Agent taskbar icon and select **Properties**.

When troubleshooting AV/AS Rules, please provide the following information:

1. Version of CAS, CAM, and Agent (see [page 14](#)).
2. Version of client OS (e.g. Windows XP SP2).
3. Version of Cisco Updates ruleset
4. Product name and version of AV/AS software from the Add/Remove Program dialog box.
5. What is failing—AV/AS installation check or AV/AS update checks? What is the error message?
6. What is the current value of the AV/AS def date/version on the failing client machine?
7. What is the corresponding value of the AV/AS def date/version being checked for on the CAM? (See **Device Management > Clean Access > Clean Access Agent > Rules > AV/AS Support Info.**)
8. If necessary, provide Agent debug logs as described in [Debug Logging for Cisco NAC Appliance Agents, page 90](#).
9. If necessary, provide CAM support logs as described in [Creating CAM/CAS Support Logs, page 92](#).

Debug Logging for Cisco NAC Appliance Agents

This section describes how to view and/or enable debug logging for Cisco NAC Appliance Agents. Refer to the following sections for steps for each Agent type:

- [Generate Cisco NAC Agent Debug Logs](#)

- [Cisco NAC Web Agent Logs](#)
- [Generate Mac OS X Agent Debug Log](#)

Copy these event logs to include them in a customer support case.

Generate Cisco NAC Agent Debug Logs

To generate Cisco NAC Agent logs using the Cisco Log Packager utility, refer to the “Create Agent Log Files Using the Cisco Log Packager” section of the *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8*.

Cisco NAC Web Agent Logs

The Cisco NAC Web Agent version 4.1.3.9 and later can generate logs when downloaded and executed. By default, the Cisco NAC Web Agent writes the log file upon startup with debugging turned on. The Cisco NAC Web Agent generates the following log files for troubleshooting purposes: **webagent.log** and **webagentsetup.log**. These files should be included in any TAC support case for the Web Agent. Typically, these files are located in the user's temp directory, in the form:

C:\Document and Settings*user*\Local Settings\Temp\webagent.log

C:\Document and Settings*user*\Local Settings\Temp\webagentsetup.log

If these files are not visible, check the TEMP environment variable setting. From a command-prompt, type “echo %TEMP%” or “cd %TEMP%”.

When the client uses Microsoft Internet Explorer, the Cisco NAC Web Agent is downloaded to the **C:\Documents and Settings*user*\Local Settings\Temporary internet files** directory.

Generate Mac OS X Agent Debug Log

For Mac OS X Agents, the Agent **event.log** file and **preference.plist** user preferences file are available under *<username>* > **Library** > **Application Support** > **Cisco Systems** > **CCAagent.app**. To change or specify the LogLevel setting, however, you must access the global **setting.plist** file (which is *different* from the user-level **preference.plist** file).

Because Cisco does not recommend allowing individual users to change the LogLevel value on the client machine, you must be a superuser or root user to alter the global **setting.plist** system preferences file and specify a different Agent LogLevel.



Note

For versions prior to 4.1.3.0, debug logging for the Mac OS X Agent is enabled under *<local drive ID>* > **Library** > **Application Support** > **Cisco Systems** | **CCAagent.app** > **Show Package Contents** > **setting.plist**.

To view and/or change the Agent LogLevel:

- Step 1** Open the navigator pane and navigate to *<local drive ID>* > **Applications**.
- Step 2** Highlight and right-click the **CCAagent.app** icon to bring up the selection menu.
- Step 3** Choose **Show Package Contents** > **Resources**.
- Step 4** Choose **setting.plist**.

- Step 5** If you want to change the current LogLevel setting using Mac **Property Editor** (for Mac OS 10.4 and later) or any standard text editor (for Mac OS X releases earlier than 10.4), find the current LogLevel Key and replace the exiting value with one of the following:
- **Info**—Include only informational messages in the event log
 - **Warn**—Include informational and warning messages in the event log
 - **Error**—Include informational, warning, and error messages in the event log
 - **Debug**—Include all Agent messages (including informational, warning, and error) in the event log



Note The **Info** and **Warn** entry types only feature a few messages pertaining to very specific Agent events. Therefore, you will probably only need either the **Error** or **Debug** Agent event log level when troubleshooting Agent connection issues.



Note Because Apple, Inc. introduced a binary-format .plist implementation in Mac OS 10.4, the .plist file may not be editable by using a common text editor such as vi. If the .plist file is not editable (displayed as binary characters), you either need to use the Mac **Property List Editor** utility from the Mac OS X CD-ROM or acquire another similar tool to edit the **setting.plist** file.

Property List Editor is an application included in the Apple Developer Tools for editing .plist files. You can find it at <CD-ROM>/Developer/Applications/Utilities/Property List Editor.app.

If the **setting.plist** file *is* editable, you can use a standard text editor like vi to edit the LogLevel value in the file.

You must be the root user to edit the file.

Creating CAM/CAS Support Logs

The **Support Logs** web console pages for the CAM and CAS allow administrators to combine a variety of system logs (such as information on open files, open handles, and packages) into one tarball that can be sent to TAC to be included in the support case. Refer to “Support Logs” sections of the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#) or [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

Recovering Root Password for CAM/CAS

Refer to the “Password Recovery” chapter of the [Cisco NAC Appliance Hardware Installation Guide, Release 4.8](#).

Troubleshooting CAM/CAS Certificate Issues

Refer to the “Troubleshooting Certificate Issues” sections of the [Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8](#) or [Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8](#).

Troubleshooting Switch Support Issues

To troubleshoot switch issues, see *Switch Support for Cisco NAC Appliance*.

Other Troubleshooting Information

For general troubleshooting tips, see the following Technical Support webpage:

http://www.cisco.com/en/US/products/ps6128/tsd_products_support_series_home.html

Documentation Updates

Table 8 Updates to Release Notes for Cisco NAC Appliance, Release 4.8

Date	Description
9/28/11	Added HA Active-Active Situation Due to Expired SSL Certificates , page 89
6/2/11	Added CSCtj81255 to Open Caveats - Release 4.8 , page 22
12/16/10	Added link to Accessibility Guide in the Related Documentation , page 93
12/9/10	<ul style="list-style-type: none"> Updated Cisco NAC Agent version 4.8.0.35 Added Downloading Compliance Module, page 20 Added AV/AS support information for the Cisco NAC Agent version 4.8.0.35 and Compliance Module version 3.4.16.1
12/3/10	<ul style="list-style-type: none"> Modified CSCtj02066 in Open Caveats - Release 4.8, page 22
10/21/10	Added caveat CSCth82967 to Resolved Caveats - Release 4.8 , page 55
10/11/10	<ul style="list-style-type: none"> Added caveats CSCti35086 and CSCtj02066 to Open Caveats - Release 4.8, page 22 Added notes about upgrading from Release 4.7(3) to Release 4.8
9/17/10	Added caveat CSCti78938 to Open Caveats - Release 4.8 , page 22
9/9/10	Added notes regarding running Release 4.8 on CCA-3140 platform
7/28/10	<ul style="list-style-type: none"> Added caveat CSCti03955 to Open Caveats - Release 4.8, page 22 Added caveat CSCtd78468 to Resolved Caveats - Release 4.8, page 55
7/26/10	Release 4.8

Related Documentation

For the latest updates to Cisco NAC Appliance documentation on Cisco.com see:

http://www.cisco.com/en/US/products/ps6128/tsd_products_support_series_home.html or simply <http://www.cisco.com/go/cca>.

- *Cisco NAC Appliance Hardware Installation Guide, Release 4.8*
- *Cisco NAC Appliance - Clean Access Manager Configuration Guide, Release 4.8*
- *Cisco NAC Appliance - Clean Access Server Configuration Guide, Release 4.8*
- *Getting Started with Cisco NAC Network Modules in Cisco Access Routers*

- [Cisco NAC Appliance FIPS Card Field-Replaceable Unit Installation Guide](#)
- [Support Information for Cisco NAC Appliance Agents, Release 4.5 and Later](#)
- [Switch Support for Cisco NAC Appliance](#)
- [Cisco NAC Appliance Service Contract / Licensing Support](#)
- [Accessibility Features in Cisco NAC Agent- Keyboard Navigation](#)

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as an RSS feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service. Cisco currently supports RSS Version 2.0.

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

© 2010 Cisco Systems, Inc. All rights reserved.