

Working With Configuration Files

This chapter describes how to work with switch configuration files on the Catalyst 5000, 4000, 2948G, 2926G, and 2926 series switches switch configuration files.

Note For complete syntax and usage information for the commands used in this chapter, refer to the *Command Reference* for your switch.

This chapter consists of these sections:

- Guidelines for Creating and Using Configuration Files on page 20-1
- Creating a Configuration File on page 20-2
- Downloading Configuration Files to the Switch on page 20-2
- Uploading Configuration Files to a TFTP Server on page 20-5
- Clearing the Configuration on page 20-7

Note For more information on working with configuration files on the Flash file system, see Chapter 18, “Working With the Flash File System.”

Guidelines for Creating and Using Configuration Files

Creating configuration files can aid in the configuration of your switch. Configuration files can contain some or all the commands needed to configure one or more switches. For example, you might want to download the same configuration file to several switches that have the same hardware configuration so that they have identical module and port configurations.

Use the following guidelines when creating a configuration file:

- We recommend that you connect through the console port when using configuration files to configure the switch. If you configure the switch from a Telnet session, IP addresses are not changed, and ports and modules are not disabled.
- If no passwords have been set on the switch, you must set them on each switch by entering the **set password** and **set enablepass** commands. Enter a blank line after the **set password** and **set enablepass** commands. The passwords are saved in the configuration file as clear text.

If passwords already exist, you cannot enter the **set password** and **set enablepass** commands because the password verification will fail. If you enter passwords in the configuration file, the switch mistakenly attempts to execute the passwords as commands as it executes the file.

- Certain commands must be followed by a blank line in the configuration file. The blank line is necessary; without the blank line, these commands might disconnect your Telnet session. Before disconnecting a session, the switch prompts you for confirmation. The blank line acts as a carriage return, which indicates a negative response to the prompt and thus retains the Telnet session.

Include a blank line after each occurrence of these commands in a configuration file:

- **set interface sc0** *ip_addr netmask*
- **set interface sc0** **disable**
- **set module disable** *mod_num*
- **set port disable** *mod_num/port_num*

Creating a Configuration File

When creating a configuration file, you must list commands in a logical way so that the system can respond appropriately. One method of creating a configuration file is as follows:

- Step 1** Download an existing configuration from a switch.
- Step 2** Open the configuration file in a text editor, such as vi or emacs on UNIX or Notepad on a PC.
- Step 3** Extract the portion of the configuration file with the desired commands and save it in a new file. Make sure the file begins with the word **begin** on a line by itself and ends with the word **end** on a line by itself.
- Step 4** Copy the configuration file to the appropriate TFTP directory on the workstation (usually /tftpboot on a UNIX workstation).
- Step 5** Make sure the permissions on the file are set to world-read.

This example shows an example configuration file. This file could be used to set the DNS configuration on multiple switches.

```
begin

!
#dns
set ip dns server 172.16.10.70 primary
set ip dns server 172.16.10.140
set ip dns enable
set ip dns domain corp.com
end
```

Downloading Configuration Files to the Switch

You can configure the switch using configuration files you create or download from another switch. In addition, you can store configuration files on Flash devices on hardware that supports the Flash file system, and you can configure the switch using a configuration stored on a Flash device.

These sections describe how to configure the switch using configuration files downloaded from a TFTP server or stored on a Flash device:

- Preparing to Download a Configuration File Using TFTP on page 20-3
- Configuring the Switch Using a File on a TFTP Server on page 20-3
- Configuring the Switch Using a File on a Flash Device (Catalyst 5000 Series Supervisor Engine III, III FSX, III FLX or Catalyst 4000, 2948G, or 2926G Series Switches) on page 20-4

Preparing to Download a Configuration File Using TFTP

Before you begin downloading a configuration file using TFTP, do the following:

- Ensure that the workstation acting as the TFTP server is configured properly. On a Sun workstation, make sure that the `/etc/inetd.conf` file contains this line:

```
tftp dgram udp wait root /usr/etc/in.tftpd in.tftpd -p -s /tftpboot
```

Make sure that the `/etc/services` file contains this line:

```
tftp 69/udp
```

Note You must restart the `inetd` daemon after modifying the `/etc/inetd.conf` and `/etc/services` files. To restart the daemon, either stop the `inetd` process and restart it, or enter a **fastboot** command (on the SunOS 4.x) or a **reboot** command (on Solaris 2.x or SunOS 5.x). Refer to the documentation for your workstation for more information on using the TFTP daemon.

- Ensure that the switch has a route to the TFTP server. The switch and the TFTP server must be in the same subnetwork if you do not have a router to route traffic between subnets. Check connectivity to the TFTP server using the **ping** command.
- Ensure that the configuration file to be downloaded is in the correct directory on the TFTP server (usually `/tftpboot` on a UNIX workstation).
- Ensure that the permissions on the file are set correctly. Permissions on the file should be world-read.

Configuring the Switch Using a File on a TFTP Server

Use this procedure to configure a Catalyst 5000 series switch with a Supervisor Engine I or II or a Catalyst 2926 series switch using a configuration file downloaded from a TFTP server:

- Step 1** Copy the configuration file to the appropriate TFTP directory on the workstation.
- Step 2** Log into the switch through the console port or a Telnet session.
- Step 3** Configure the switch using the configuration file downloaded from the TFTP server using the command appropriate for your switch and supervisor engine:
- **Catalyst 5000 series Supervisor Engine I or II, and Catalyst 2926 series switches**—Use the **configure network** command. Specify the IP address or host name of the TFTP server and the name of the file to download.
 - **Catalyst 5000 series Supervisor Engine III, III FSX, and III FLX, and Catalyst 4000, 2948G, and 2926G series switches**—Use the **copy tftp config** command. Specify the IP address or host name of the TFTP server and the name of the file to download.

The configuration file downloads and the commands are executed as the file is parsed line-by-line.

This example shows how to configure a Catalyst 5000 series switch with a Supervisor Engine I or II, or a Catalyst 2926 series switch, using a configuration file downloaded from a TFTP server:

```
Console> (enable) configure network
IP address or name of remote host? 172.20.52.3
Name of configuration file? dns-config.cfg
Configure using dns-config.cfg from 172.20.52.3 (y/n) [n]? y
/
Finished network download. (134 bytes)
>>
>> set ip dns server 172.16.10.70 primary
172.16.10.70 added to DNS server table as primary server.
>> set ip dns server 172.16.10.140
172.16.10.140 added to DNS server table as backup server.
>> set ip dns enable
DNS is enabled
>> set ip dns domain corp.com
Default DNS domain name set to corp.com
Console> (enable)
```

This example shows how to configure a Catalyst 5000 series switch with a Supervisor Engine III, III FSX, or III FLX, or a Catalyst 4000, 2948G, or 2926G series switch using a configuration file downloaded from a TFTP server:

```
Console> (enable) copy tftp config
IP address or name of remote host []? 172.20.52.3
Name of file to copy from []? dns-config.cfg

Configure using tftp:dns-config.cfg (y/n) [n]? y
/
Finished network download. (134 bytes)
>>
>> set ip dns server 172.16.10.70 primary
172.16.10.70 added to DNS server table as primary server.
>> set ip dns server 172.16.10.140
172.16.10.140 added to DNS server table as backup server.
>> set ip dns enable
DNS is enabled
>> set ip dns domain corp.com
Default DNS domain name set to corp.com
Console> (enable)
```

Configuring the Switch Using a File on a Flash Device (Catalyst 5000 Series Supervisor Engine III, III FSX, III FLX or Catalyst 4000, 2948G, or 2926G Series Switches)

Use this procedure to configure a Catalyst 5000 series switch with a Supervisor Engine III, III FSX, or III FLX, or a Catalyst 4000, 2948G, or 2926G series switch using a configuration file stored on a Flash device in the Flash file system:

- Step 1** Log into the switch through the console port or a Telnet session.
- Step 2** Locate the configuration file using the **cd** and **dir** commands (for more information, see Chapter 18, “Working With the Flash File System”).

- Step 3** Configure the switch using the configuration file stored on the Flash device using the `copy file-id config` command.

The commands are executed as the file is parsed line-by-line.

This example shows how to configure the switch using a configuration file stored on a Flash device:

```

Console> (enable) copy slot0:dns-config.cfg config

Configure using slot0:dns-config.cfg (y/n) [n]? y

Finished network download. (134 bytes)
>>
>> set ip dns server 172.16.10.70 primary
172.16.10.70 added to DNS server table as primary server.
>> set ip dns server 172.16.10.140
172.16.10.140 added to DNS server table as backup server.
>> set ip dns enable
DNS is enabled
>> set ip dns domain corp.com
Default DNS domain name set to corp.com
Console> (enable)
Console> (enable)

```

Uploading Configuration Files to a TFTP Server

These sections describe how to upload the running configuration or a configuration file stored on a Flash device to a TFTP server:

- Preparing to Upload a Configuration File to a TFTP Server on page 20-5
- Uploading a Configuration File to a TFTP Server on page 20-6

Preparing to Upload a Configuration File to a TFTP Server

Before you attempt to upload a configuration file to a TFTP server, do the following:

- Ensure that the workstation acting as the TFTP server is configured properly. On a Sun workstation, make sure that the `/etc/inetd.conf` file contains this line:

```
tftp dgram udp wait root /usr/etc/in.tftpd in.tftpd -p -s /tftpboot
```

Make sure that the `/etc/services` file contains this line:

```
tftp 69/udp
```

Note You must restart the `inetd` daemon after modifying the `/etc/inetd.conf` and `/etc/services` files. To restart the daemon, either stop the `inetd` process and restart it, or enter a **fastboot** command (on the SunOS 4.x) or a **reboot** command (on Solaris 2.x or SunOS 5.x). Refer to the documentation for your workstation for more information on using the TFTP daemon.

- Ensure that the switch has a route to the TFTP server. The switch and the TFTP server must be in the same subnetwork if you do not have a router to route traffic between subnets. Check connectivity to the TFTP server using the **ping** command.

- You might need to create an empty file on the TFTP server before uploading the configuration file. To create an empty file, enter the **touch filename** command, where *filename* is the name of the file you will use when uploading the configuration to the server.
- If you are overwriting an existing file (including an empty file, if you had to create one), ensure that the permissions on the file are set correctly. Permissions on the file should be world-write.

Uploading a Configuration File to a TFTP Server

Use this procedure to upload a configuration file from a switch to a TFTP server for storage:

- Step 1** Log into the switch through the console port or a Telnet session.
- Step 2** Upload the switch configuration to the TFTP server using the command appropriate for your switch and supervisor engine:
- **Catalyst 5000 series Supervisor Engine I or II, and Catalyst 2926 series switches**—Use the **write network** command. Specify the IP address or host name of the TFTP server and the destination filename.
 - **Catalyst 5000 series Supervisor Engine III, III FSX, and III FLX, and Catalyst 4000, 2948G, and 2926G series switches**—Use the **copy config tftp** command. Specify the IP address or host name of the TFTP server and the destination filename.

The file is uploaded to the TFTP server.

This example shows how to upload the running configuration on a Catalyst 5000 series switch with a Supervisor Engine I or II, or on a Catalyst 2926 series switch, to a TFTP server:

```
Console> (enable) write network
IP address or name of remote host? 172.20.52.3
Name of configuration file? cat5002_config.cfg
Upload configuration to cat5002_config.cfg on 172.20.52.3 (y/n) [n]? y
.....
.....
.....
..
/
Finished network upload. (8534 bytes)
Console> (enable)
```

This example shows how to upload the running configuration on a Catalyst 5000 series switch with a Supervisor Engine III, III FSX, or III FLX, or on a Catalyst 4000, 2948G, or 2926G series switch, to a TFTP server for storage:

```
Console> (enable) copy config tftp
IP address or name of remote host []? 172.20.52.3
Name of file to copy to []? cat5000_config.cfg

Upload configuration to tftp:cat5000_config.cfg, (y/n) [n]? y
.....
.....
.....
.....
..
/
Configuration has been copied successfully.
Console> (enable)
Console> (enable)
```

Clearing the Configuration

To clear the configuration on the entire switch, perform this task in privileged mode:

Task	Command
Clear the switch configuration.	clear config all

This example shows how to clear the configuration for the entire switch:

```

Console> (enable) clear config all
This command will clear all configuration in NVRAM.
This command will cause ifIndex to be reassigned on the next system startup.
Do you want to continue (y/n) [n]? y
.....
.....

System configuration cleared.
Console> (enable)

```

To clear the configuration on an individual module, perform this task in privileged mode:

Task	Command
Clear the configuration for a specific module.	clear config mod_num

Note If you remove a module and replace it with a module of another type (for example, if you remove a Fast Ethernet module and insert a Token Ring module), the module configuration is inconsistent. The output of the **show module** command indicates this problem. To resolve the inconsistency, clear the configuration on the problem module.

This example shows how to clear the configuration on a specific module:

```

Console> (enable) clear config 2
This command will clear module 2 configuration.
Do you want to continue (y/n) [n]? y
.....
Module 2 configuration cleared.
Console> (enable)

```

