



Meet-Me Number/Pattern Configuration

Meet-Me conferences require an allocation of directory numbers. The Cisco CallManager Administration provides the Meet-Me conference directory number range to users so they can access the feature.

Adding a Meet-Me Number/Pattern

This section describes how to add a Meet-Me Number/Pattern.

Before You Begin

Make sure the following prerequisites are met before proceeding with the steps:

- Configure the servers. See the [“Server Configuration”](#) section on page 2-1.
- Configure the device pools. See the [“Device Pool Configuration”](#) section on page 8-1.

Procedure

- Step 1** Choose **Service > Media Resource > Conference Bridge**.
- Step 2** Click **Meet-Me Number/Pattern Configuration**, from the top, right corner of the window.

The window refreshes and the Meet-Me Number/Pattern Configuration window appears.

Step 3 Enter the appropriate settings as described in [Table 37-1](#).

Step 4 Click **Insert**.

The window refreshes, and the new Meet-Me Number/Pattern appears in the list on the left side of the window.

Related Topics

- [Updating a Meet-Me Number/Pattern, page 37-2](#)
- [Deleting a Meet-Me Number/Pattern, page 37-4](#)
- [Adding a Software Conference Device, page 25-2](#)
- [Adding a Hardware Conference Device, page 25-5](#)
- [Adding a Cisco IOS Conference Bridge Device, page 25-7](#)
- [Updating a Conference Device, page 25-9](#)
- [Deleting a Conference Device, page 25-10](#)
- [Updating Conference Bridge Parameters, page 25-12](#)
- [Partition Configuration, page 12-1](#)
- [Conference Bridges, *Cisco CallManager System Guide*](#)

Updating a Meet-Me Number/Pattern

This section describes how to update a Meet-Me Number/Pattern.

Before You Begin

Make sure the following prerequisites are met before proceeding with the steps:

- Configure the servers. See the “[Server Configuration](#)” section on [page 2-1](#).
- Configure the device pools. See the “[Device Pool Configuration](#)” section on [page 8-1](#).
- Configure the meet-me number/pattern. See the “[Adding a Meet-Me Number/Pattern](#)” section on [page 37-1](#).

Procedure

- Step 1** Choose **Service > Media Resource > Conference Bridge**.
- Step 2** Click **Meet-Me Number/Pattern Configuration** from the top, right corner of the window.
- The Meet-Me Number/Pattern Configuration window appears.
- Step 3** Choose the Meet-Me Number/Pattern you want to update from the Meet-Me Numbers/Patterns list.
- The pattern you chose appears in the pattern field.
- Step 4** Update the appropriate settings as described in [Table 37-1](#).



Note You can change the number or pattern as needed (example, changing 5000 to 500X).

- Step 5** Click **Update**.
- The window refreshes, and the pattern is updated with the new route partition information.
-

Related Topics

- [Adding a Software Conference Device, page 25-2](#)
- [Adding a Hardware Conference Device, page 25-5](#)
- [Adding a Cisco IOS Conference Bridge Device, page 25-7](#)
- [Updating a Conference Device, page 25-9](#)
- [Deleting a Conference Device, page 25-10](#)
- [Updating Conference Bridge Parameters, page 25-12](#)
- [Adding a Meet-Me Number/Pattern, page 37-1](#)
- [Deleting a Meet-Me Number/Pattern, page 37-4](#)
- [Partition Configuration, page 12-1](#)
- [Conference Bridges, *Cisco CallManager System Guide*](#)

Deleting a Meet-Me Number/Pattern

This section describes how to delete a Meet-Me Number/Pattern.

Before You Begin

Make sure the following prerequisites are met before proceeding with the steps:

- Configure the servers.
- Configure the device pools.
- Configure the meet-me number/pattern.

Procedure

-
- Step 1** Choose **Service > Media Resource > Conference Bridge**.
- Step 2** Click **Meet-Me Number/Pattern Configuration** from the top, right corner of the window.
- The Meet-Me Number/Pattern Configuration window appears.
- Step 3** Choose the Meet-Me Number/Pattern you want to delete from the Meet-Me Numbers/Patterns list.
- Step 4** Click **Delete**.
- A message displays stating that you are about to permanently delete this pattern and that this action cannot be undone.
- Step 5** Click **OK** to continue, or **Cancel** to cancel the deletion.
-

Related Topics

- [Adding a Software Conference Device, page 25-2](#)
- [Adding a Hardware Conference Device, page 25-5](#)
- [Adding a Cisco IOS Conference Bridge Device, page 25-7](#)
- [Updating a Conference Device, page 25-9](#)
- [Deleting a Conference Device, page 25-10](#)
- [Updating Conference Bridge Parameters, page 25-12](#)
- [Adding a Meet-Me Number/Pattern, page 37-1](#)

- [Updating a Meet-Me Number/Pattern, page 37-2](#)
- [Conference Bridges, Cisco CallManager System Guide](#)

Meet-Me Number/Pattern Configuration Settings

[Table 37-1](#) describes the meet-me number/pattern configuration settings.

Table 37-1 Meet-Me Number/Pattern Configuration Settings

Field	Description
Directory Number or Pattern	Enter a Meet-Me Numbers/pattern or a range of numbers (such as 8000 to 8009).
Partition	Select a partition. See the “Partition Configuration” section on page 12-1 for more information.

Related Topics

- [Adding a Meet-Me Number/Pattern, page 37-1](#)
- [Updating a Meet-Me Number/Pattern, page 37-2](#)

