

Firepower 2100 Series ل رورملا ةملك دادرتسإ

تاوت حمل

[قم دق م ل ا](#)

[ةيساس ال ا تابل ط م ل ا](#)

[تابل ط م ل ا](#)

[ةمدختس م ل ا تانوك م ل ا](#)

[ةيساس ا تامول عم](#)

[عارجالا](#)

ةمدق م ل ا

لوؤس م ل ا رورم ةملك نادق ف دن ع ه عابتا ب جي ي ذل ا دادرتس ال ا عارجالا دن تنس م ل ا اذه فص ي

ةيساس ال ا تابل ط م ل ا

تابل ط م ل ا

ةيلال ا عيضاوم ل ا ب ةفرعم ك ي دل نوك ت ن ا ب Cisco ي صوت

- Cisco Firepower FXOS
- لى ع ةردق ل ا و ةيساس ل س ل س ت ل ا م ك ح ت ل ا ةدحو ل ا ل و ص و ل ا رورم ل ا ةملك دادرتس ا ب ل ط ت ي
FPR 2100 زا ه ل ل ي غ ش ت

ةمدختس م ل ا تانوك م ل ا

و ا FPR 2100 ةلس ل س ل ا ن م 1.0.00 رادص ال ا ل ا دن تنس م ل ا اذه ي ف ةدراول ا تامول عم ل ا دن تنس ت
ل ا ع ا

ةصاخ ةي لم عم ةئ ي ب ي ف ةدوچوم ل ا ةزه ال ا ن م دن تنس م ل ا اذه ي ف ةدراول ا تامول عم ل ا عاشن ا م ت
تن ا ك ا ذ ا . (يضا رت ف ا) حوس م م ن ي و ك ت ب دن تنس م ل ا اذه ي ف ةمدختس م ل ا ةزه ال ا عي م ج ت ا د ب
رم ا ي ا ل م ت ح م ل ا ر ي ث ا ت ل ل ك م ه ف ن م د ك ا ت ف ، ل ي غ ش ت ل ا د ي ق ك ت ك ب ش

ةيساس ا تامول عم

اذه ا ع ا د ت س ا دن ع ب ر م ل ا ر ي و ص ت ي ل ا ح ل ا (FXOS) ع س و ت م ل ا ل ي غ ش ت ل ا م ا ظ ن ر ا د ص ا د ي ع ي
ل ا ص ت ا ل ا ب م ق ، ع ن ص م ل ا ي ف زا ه ل ل ا ط ب ص ة د ا ع ا ل . ن ي و ك ت ل ا ت ا ن ا ي ب ع ي م ج د ق ف ن ك م ي . ق ف د ت ل ا
ب [erase](#) ن ي و ك ت ر د ص ا و ة ي ل ح م ل ا ة ر ا د ا ل ا و FXOS ب

عارجالا

ل ي ض ا ر ت ف ا ل ا د ي ه م ت ل ا ل س ل س ت ة ع ط ا ق م ل ن ا و ت 10 ك م ا م ا . Firepower21xx زا ه ر ي و د ت 1. ة و ط خ ل ا

ROMMON ESC حاتفم ىلع ةطغض مادختساب

```
*****
Cisco System ROMMON, Version 1.0.00, RELEASE SOFTWARE
Copyright (c) 1994-2017 by Cisco Systems, Inc.
Compiled Tue 01/03/2017 23:55:11.41 by builder
*****
```

```
Current image running: Boot ROM0
Last reset cause: ResetRequest
DIMM_1/1 : Present
DIMM_2/1 : Present
```

```
Platform FPR-2130 with 32768 MBytes of main memory
BIOS has been successfully locked !!
MAC Address: 0c:75:bd:08:c8:00
```

```
Use BREAK or ESC to interrupt boot.
Use SPACE to begin boot immediately.
Boot interrupted.
```

```
rommon 1 >
```

ROMMON password_reset رمأ ءاعدتساب مق 2. ةوطخلا



لشكشا ASA ل وحمي و، ةادا FirePOWER 21xx ل ىلع reimage رمأ اذه رجن ي: ريذحت

```
rommon 1 > password_reset
WARNING: User configurations can be lost with this operation
Are you sure ? yes/no [no]: yes
```

```
Enabling password reset..
Please continue to boot the image !
rommon 2 >
```




م ت password_reset رمأ مدختسأ، مدقأل تارادصل او 1.0.04 رادصلال ROMMON ل: حيملت
ثدأل تارادصلال ي فنصملا طبض ةداعل ىل رمأل اذه ريغت

رمأل اذه مدختسأ، ىلعفل ROMMON رادصل ةحص نم ققحتلل

```
rommon 1 > show info
Cisco System ROMMON, Version 1.0.06, RELEASE SOFTWARE
Copyright (c) 1994-2018 by Cisco Systems, Inc.
Compiled Wed 11/01/2018 18:38:59.66 by builder
```

وأية ضارته فالأهروصلها مادختس إك نكمي boot. رمألأهأعدتس او زاهجلا ليمحتب مق 3. ةوطخلأهديهمتلل ةفلتخم ةروص ديحت.

 (جذوم نلل اق فو) ةق يق د 40 و 20 ني ب ام ةي لم عل لامك إ قرغت سي دق: ةظحالم

<#root>

```
rommon 3 > boot
Located '.boot_string' @ cluster 648129.
```

```
#
Located 'installables/switch/fxos-k8-fp2k-1fbff.2.2.1.29.SPA' @ cluster 404198.
```

```
#####
#####
```

<skipped>

```
INIT: version 2.88 booting
Starting udev
Configuring network interfaces... done.
Populating dev cache
Starting Power Off Shutdown Handler (poshd)
poshd: using FPGA version 1.0.00 and PSEQ version 2.11
Primary SSD discovered
eMMC Flash not detected; retrying
eMMC Flash not detected; retrying
eMMC Flash not detected; retrying
Rommon requested SSD reformat
```

Formating SSD...

Creating config partition: START: 1MB END: 1001MB

```
mke2fs 1.42.8 (20-Jun-2013)
Discarding device blocks: done
Filesystem label=
OS type: Linux
Block size=4096 (log=2)
Fragment size=4096 (log=2)
Stride=0 blocks, Stripe width=0 blocks
61056 inodes, 244224 blocks
12211 blocks (5.00%) reserved for the super user
First data block=0
Maximum filesystem blocks=251658240
8 block groups
32768 blocks per group, 32768 fragments per group
7632 inodes per group
Superblock backups stored on blocks:
    32768, 98304, 163840, 229376
```

.
.
.
.
.
.
.

```
[/sbin/fsck.vfat (1) -- /dev/sdc1] fsck.vfat -a /dev/sdc1
dosfsck 2.11, 12 Mar 2005, FAT32, LFN
/dev/sdc1: 47 files, 616932/1937459 clusters
fsck(/dev/sdc1) returned 0
Running postinst /etc/rpm-postinsts/100-apache2...
Running postinst /etc/rpm-postinsts/101-syslog-ng...
Running postinst /etc/rpm-postinsts/102-bind...
INIT: Entering runlevel: 3un-postinsts exists during rc.d purge
Starting system message bus: dbus.
Starting OpenBSD Secure Shell server: sshd
done.
Starting rpcbind daemon...done.
starting statd: done
Starting Advanced Configuration and Power Interface daemon: acpid.
acpid: starting up
```

لاصتال admin/Admin123 ةيضا رتفالال دامتعالال تانايب مدختسا، زاهال ديهمت ةداعإ دعب
حبصت نأ درجمب دامتعالال تانايب س فن مادختسا نكمي. لوخدلا ليجست رما هجوم رفوت درجمب
Firepower Device Manager (FDM) م ساب اراصتخا فورعلمال) و Firepower Chassis Manager (FCM)
نيتزهاج.

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذہ Cisco تچرت
ملاعلاء انءمچي فني مدختسمل معدى وتحم مي دقتل ةيرشبل او
امك ةقيقد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچري. ةصاغل مهتغب
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه
ىلإ أمئاد ةوچرلاب ي صؤتو تامچرتل هذه ةقدنع اهتيلوئسم Cisco
Systems (رفوتم طبارل) ي لصلأل يزي لچنل دن تسمل