



## RADIUS

RADIUS Accounting for Management Access can only be enabled when TACACS+ Accounting is disabled. TACACS+ Accounting is currently disabled.

RADIUS Accounting:  Port Based Access Control (802.1X, MAC Based, Web Authentication)  
 Management Access  
 Both Port Based Access Control and Management Access  
 None

### Use Default Parameters

Retries:  (Range: 1 - 10, Default: 3)  
Timeout for Reply:  sec (Range: 1 - 30, Default: 3)  
Dead Time:  min (Range: 0 - 2000, Default: 0)  
Key String:  Encrypted   
 Plaintext  (0/128 characters used)  
Source IPv4 Interface:   
Source IPv6 Interface:

Apply

Cancel

### RADIUS Table

<input type="checkbox"/>	Server	Priority	Key String (Encrypted)	Timeout for Reply	Authentication Port	Accounting Port	Retries	Dead Time	Usage Type
0 results found.									
<input type="button" value="Add..."/>	<input type="button" value="Edit..."/>	<input type="button" value="Delete"/>							

ةبساحملا تامولعم عون ديدحتل رايخا رز رتخا، RADIUS ةبساحم لقح يف 2. ةوطخلال  
يلع ظفاحت ةبساحم تامولعم RADIUS مداخ حنم نكمي. اهل RADIUS مداخ يطعيسي يتلا  
رثوي نل. رخا ايشا، اهمدختسي يتلا دراوملاو، مدختسملا لمع ةسلج تقو بقعت  
802.1X اءا اىل عل انه ددحملا رايخالا.

RADIUS Accounting:  Port Based Access Control (802.1X, MAC Based, Web Authentication)  
 Management Access  
 Both Port Based Access Control and Management Access  
 None

### Use Default Parameters

Retries:  (Range: 1 - 10, Default: 3)  
Timeout for Reply:  sec (Range: 1 - 30, Default: 3)  
Dead Time:  min (Range: 0 - 2000, Default: 0)  
Key String:  Encrypted   
 Plaintext  (0/128 characters used)  
Source IPv4 Interface:   
Source IPv6 Interface:

Apply

Cancel

يه تارايخالا:

لوح ةبساحملا تامولعم رايخالا اذه لسري - ذفنملا اىل دنتمسمل لوصولا يف مكحتلا:  
RADIUS مداخ اىل ذفنملا ةطساوب اهيلع قدصملا تاسلجلا.

اىل لوحملا ةرادا تاسلج لوح ةبساحملا تامولعم رايخالا اذه لسري - ةرادالا اىل لوصولا.

## RADIUS مداخل.

اذه لسري - ةرادإلإ ىلإ لوصولو اذفانملا ىلإ دننتمسمل لوصولو يف مكحتلا نم الك .  
RADIUS مداخل ىلإ ةبساحملا تامولعم نم نيعونلا الك رايلخلا

RADIUS مداخل ىلإ ةبساحملا تامولعم لاسرا مدع - الب .

يتلا تادادعإلإ نيوكتب مق ، ةيضارتفالا تامولعملا مداخلتسإ ةقطنم يف 3. ةوطخل  
هتادادعإب فاضم RADIUS مداخل نيوكتب متي مل ام ييضارتفالا لكشب اهمادختسإ متيس  
تادادعإلإ ام مداخلتسي نا نكمي لولحمل ىلإ هيفيضة يدرف مداخل لاخذل لك ؛ ةصاخلا  
تادادعإلإ مداخلتسنس ، ةلاقملا هذهل . ةلصفنملا ةديرفلا تادادعإلإ وأ ةيضارتفالا  
مسللا اذه يف ةدحمل ةيضارتفالا

RADIUS Accounting:  Port Based Access Control (802.1X, MAC Based, Web Authentication)  
 Management Access  
 Both Port Based Access Control and Management Access  
 None

Use Default Parameters

Retries: 3 (Range: 1 - 10, Default: 3)  
Timeout for Reply: 3 sec (Range: 1 - 30, Default: 3)  
Dead Time: 0 min (Range: 0 - 2000, Default: 0)

Key String:  Encrypted  Plaintext radius (6/128 characters used)

Source IPv4 Interface: Auto  
Source IPv6 Interface: Auto

Apply Cancel

ةيولاتلا تادادعإلإ نيوكتب مق :

مدخب لاصتالا لولحمل اهيف لولحييس يتلا تارملا ددع لخدا - ةلولحمل ةداعإ تايلمع .  
3. وه ييضارتفالا . يولاتلا مداخل ىلإ لاقنتالا لبق RADIUS

ذاختإ لبق RADIUS مداخل نم ادر لولحمل اهيف رظتنيس يتلا يئاوثل ددع لخدا - درلا ةلهم .  
3. وه ييضارتفالا . (مالستسالا وأ ىرخأ ةرم ةلولحمل) يفاضإ ءارجإ

رېغ RADIUS مداخل ريرمت لبق ييضقنت يتلا قئاقدل ددع لخدا - فقوتلا تقو .  
ال مداخل نا ةميقلا هذه ينعنو ، 0 يه ةيضارتفالا ةميقل . ةمدخل تابلطل بيحتمسلا  
هزواجت متي .

مدخو لولحمل نيب ةقداصم لل مداخلتسمل يرسل حاتفملا لخدا - حيتافملا ةلسلس .  
الاو ، رشفملا وي دارلا رز مداخلتساب حاتفملا لخدا ، رشفم حاتفم كيدل ناك اذا . RADIUS  
يداعلا صنلل يكلسالا رزلا مداخلتساب يداعلا صنلا حاتفملا لخدا .

ردصم ةهجاو رايتخال ةلدسنملا مئاوقلا هذه مداخلتسأ - ردصملا IPv4/IPv6 ةهجاو .  
يئاقلت وه ييضارتفالا دادعإلإ . RADIUS مداخل لاصتالا دننتمسمل اهمادختسإ متيس يتلا  
ةرداصلا ةهجاو ىلإ فرعمل ييضارتفالا ردصملا IP ناونع مداخلتسيس يذلاو .

ة.يضارتفالا تادادعالا قيبطت متيس .قبطي ةقطق ط. 4 ةوطخلا

RADIUS Accounting:  Port Based Access Control (802.1X, MAC Based, Web Authentication)  
 Management Access  
 Both Port Based Access Control and Management Access  
 None

---

**Use Default Parameters**

Retries:  (Range: 1 - 10, Default: 3)  
 Timeout for Reply:  sec (Range: 1 - 30, Default: 3)  
 Dead Time:  min (Range: 0 - 2000, Default: 0)

Key String:  Encrypted   
 Plaintext  (6/128 characters used)

Source IPv4 Interface:    
 Source IPv6 Interface:

ىلع ايلاح اهنويوكت متي التا RADIUS مداخل تا لادخا RADIUS لودج رهظي س. 5 ةوطخلا  
 مداخل ةفاضل ةذفان حتف متيس ...ةفاضل رزلا قوف رونا ،ديج لادخا ةفاضل .لوجملا  
 RADIUS.

**RADIUS Table**

<input type="checkbox"/>	Server	Priority	Key String (Encrypted)	Timeout for Reply	Authentication Port	Accounting Port	Retries	Dead Time	Usage Type
0 results found.									
<input checked="" type="button" value="Add..."/> <input type="button" value="Edit..."/> <input type="button" value="Delete"/>									

An \* indicates that the parameter is using the default global value.

بسح RADIUS مداخل لاصتالا ديرت تنك اذا ام رتخأ ،مداخل فيرعت لقح ي ف. 6 ةوطخلا  
 IPv6 مادختسا ددح ، IP ناووع ةطساوب تددح اذا . (hostname) مسالا بسح و IP ناووع  
 ةهجوو IPv6 ناووع عون مدختساف ، 6 رادصالا تددح اذا . (4 رادصالا) IPv4 و (6 رادصالا)  
 همادختسا متيس يذلا IPv6 ناووع ديدحتل ةيلحمل طابترالا

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

RADIUS مداخل فيض الما مس ا و IP ناوع لخد ا ،مداخل ل IP مس ا/ناوع ل قح ي ف . 7 ة واخل

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

لواجهت سو؛ مداخل اذهل اهنه يعت دتت لة لة ولوالا لخدأ، ة ولوالا ل قح ف 8. ة وطلال  
 ع رة مداخل ي قتل لة تحت ة مئاق لة عبات مة ولوالا ل عاب مداخل ل لاصت ال ل وحم ل  
 لة ولوالا ل وه 0 نوك عم، 0 - 65535 وه قاطن لة. ة باحت س ال

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

درل رختلاو، جيتافملا ةلسلس يف يضارتفالا رايفالا مادختسا لوقح ددح 9 ةوطخلا  
 ءحفص يف اقبسما هنيوكت مت يتلا تادادعلا مادختسا لقطعلا تقوو، ءلواحملا ءداعا  
 نيوكتل مدختسملا لبق نم ءفرعملا رايفالا رارزا ديدحت اضيا كنكمي RADIUS.  
 متيس، كلذب كمايق ءلاح يف، ءيضارتفالا تادادعلا نع فلخت يتلا تادادعلا  
 طقف ددحملا RADIUS مداخل تادادعلا هذم مادختسا.

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

لاصتال هم ادختسا متيس يذلا ذفنملا ددح، ةقداصملا ذفنم لقح يف 10 ةوطخلا  
 ، يضارتفالا ذفنملا يلع كلذ يقبى نأ نسحتسملا نم. RADIUS مداخ عم ةقداصملا  
 1812.

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

تالاصتال همادختسا متيس يذلا ذفنملا ددح، ةبساحملا ذفنم لقح ي ف 11 ةوطخلا  
ريصقت ءانيملا يلع اذه يقبي نأ نسحتسملا نم. RADIUS مداخ عم ةبساحملا  
1813.



Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

ةقداصم نيكم تل *RADIUS* لودج ىلإ مداخال ةفاضل متتس .قبطي ةقطق . 13 ةوطخال  
يلال مسقل ىلإ ةعباتم لىجري ،ذفنم لىلإ ةدنتسم ل 802.1X

Server Definition:  By IP address  By name

IP Version:  Version 6  Version 4

IPv6 Address Type:  Link Local  Global

Link Local Interface:

Server IP Address/Name:

Priority:  (Range: 0 - 65535)

Key String:  Use Default  
 User Defined (Encrypted)   
 User Defined (Plaintext)  (0/128 characters used)

Timeout for Reply:  Use Default  
 User Defined  sec (Range: 1 - 30, Default: 3)

Authentication Port:  (Range: 0 - 65535, Default: 1812)

Accounting Port:  (Range: 0 - 65535, Default: 1813)

Retries:  Use Default  
 User Defined  (Range: 1 - 10, Default: 3)

Dead Time:  Use Default  
 User Defined  min (Range: 0 - 2000, Default: 0)

Usage Type:  Login  
 802.1x  
 All

## ذفنم لایلا ةدنن سملل ةقدا صملل نیکمت

ةقدا صملل/802.1X/MAC > نیکم الل لایلا لقتنا ، ةدعاسم لایلا بیولل نیوکت ةادأ یف 1. ةوطخلل صئاصخلل ةحفص حتف متی . صئاصخلل > بیولل

## Properties

Port-Based Authentication:  Enable

Authentication Method:  RADIUS, None  
 RADIUS  
 None

Guest VLAN:  Enable

Guest VLAN ID:

Guest VLAN Timeout:  Immediate  
 User Defined  sec (Range: 30 - 180)

### Trap Settings

802.1x Authentication Failure Traps:  Enable

802.1x Authentication Success Traps:  Enable

MAC Authentication Failure Traps:  Enable

MAC Authentication Success Traps:  Enable

Web Authentication Failure Traps:  Enable

Web Authentication Success Traps:  Enable

Web Authentication Quiet Traps:  Enable

Apply

Cancel

### VLAN Authentication Table

VLAN ID	VLAN Name	Authentication
---------	-----------	----------------

0 results found.

Edit...

نېكمت راي تڅالا ډناخ ددح، ذفنم لاي لاي ډدنن سمل ا ډقدا صمل لاي لاي قح يي ف. 2 ډوطځالا ايضارت فا اذه تننكم. ذفنم لاي لاي ډدنن سمل ا ډقدا صمل لاي نېكمت لاي

Port-Based Authentication:  Enable

Authentication Method:  RADIUS, None  
 RADIUS  
 None

Guest VLAN:  Enable

Guest VLAN ID: 1

Guest VLAN Timeout:  Immediate  
 User Defined  sec (Range: 30 - 180)

**Trap Settings**

802.1x Authentication Failure Traps:  Enable

802.1x Authentication Success Traps:  Enable

MAC Authentication Failure Traps:  Enable

MAC Authentication Success Traps:  Enable

Web Authentication Failure Traps:  Enable

Web Authentication Success Traps:  Enable

Web Authentication Quiet Traps:  Enable

Apply Cancel

تقوم بإعداد الإعدادات لمعوية في كديحتل عاقتنا رزرتخأ، ةقداصملا قويرط لقح في 3. ةوطخل  
 ذفنملا إلى ةدنتسملا

Port-Based Authentication:  Enable

Authentication Method:  RADIUS, None  
 RADIUS  
 None

Guest VLAN:  Enable

Guest VLAN ID: 1

Guest VLAN Timeout:  Immediate  
 User Defined  sec (Range: 30 - 180)

**Trap Settings**

802.1x Authentication Failure Traps:  Enable

802.1x Authentication Success Traps:  Enable

MAC Authentication Failure Traps:  Enable

MAC Authentication Success Traps:  Enable

Web Authentication Failure Traps:  Enable

Web Authentication Success Traps:  Enable

Web Authentication Quiet Traps:  Enable

Apply Cancel

ه تارايل:

ةحفص في ةفرعملا RADIUS (مداوخ) مداخ لاصتال لوجملا لواحي س - نوب، RADIUS.  
 ةقداصم ةيأ عارج متي ال، (مداوخال) مداخال نم ةباجتس! يقلت مدع ةلاح في RADIUS.

ة، حص ريغ دامتعالا تانايب تنانكو، بيجتسم مداخل ناك اذا. ةسلجلاب حامسلا متي و  
لمعلا ةسلج صفر متي.

·RADIUS ةحفص ي ف ةفرعملل RADIUS (مداوخ) مداخ ل لاصلال لوجملا لواحيس - RADIUS  
ذيفنتل. لمعلا ةسلج صفر متي، (مداوخلا) مداخال نم ةباجتسا يقلت مدع ةلاح ي ف .  
802.1X رايل اذهب ي صوي، انام رثكال ال 802.1X.

·اذه موق ي نل. لمعلا تاسلج عيمجب حامسلا متيس. ةقداصم ةيأ عارجا متي ال - ال ب .  
802.1X ذيفنتب رايلال.

ق.ب.ط ي ةق.ط.ق 4. ةوطخلال

Port-Based Authentication:  Enable

Authentication Method:  RADIUS, None  
 RADIUS  
 None

Guest VLAN:  Enable

Guest VLAN ID:

Guest VLAN Timeout:  Immediate  
 User Defined  sec (Range: 30 - 180)

**Trap Settings**

802.1x Authentication Failure Traps:  Enable

802.1x Authentication Success Traps:  Enable

MAC Authentication Failure Traps:  Enable

MAC Authentication Success Traps:  Enable

Web Authentication Failure Traps:  Enable

Web Authentication Success Traps:  Enable

Web Authentication Quiet Traps:  Enable

رهظت. ذفنملا ةقداصم > 802.1X/MAC/Web ةقداصم > نامألا ي لإ لقتنا 5. ةوطخلال  
ذفنملا ةقداصم ةحفص

Port Authentication Table									
	Entry No.	Port	Current Port Control	Administrative Port Control	RADIUS VLAN Assignment	Guest VLAN	Open Access	802.1x Based Authentication	MAC Based Authentication
<input type="radio"/>	1	FE1	Authorized	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	2	FE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	3	FE3	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	4	FE4	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	5	FE5	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	6	FE6	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	7	FE7	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	8	FE8	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	9	GE1	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled
<input type="radio"/>	10	GE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled

تقداصم لودج يف هب صاخلا وي دارلا رز ديدحتب هنيوكت ديرت يذلا ذفنملا ددح 6. ةوطخلا  
 ذفنملا ةقداصم ريرحت ةذفان رهظي.... ريرحت رز يلعل رقنا مث ذفنملا

Port Authentication										
Port Authentication Table										
Entry No.	Port	Current Port Control	Administrative Port Control	RADIUS VLAN Assignment	Guest VLAN	Open Access	802.1x Based Authentication	MAC Based Authentication	Web Based Authentication	
<input checked="" type="radio"/>	1	FE1	Authorized	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	2	FE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	3	FE3	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	4	FE4	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	5	FE5	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	6	FE6	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	7	FE7	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	8	FE8	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	9	GE1	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	10	GE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled

Copy Settings... Edit...

ليوخت ةيفيك ديدحتل ةاقتنا رز رتخأ، يرادإلا ذفنملا يف مكحتلا لقح يف 7. ةوطخلا  
 ةيلال ليوختلا ةلاح يلال ذفنملا يف مكحتلا لقح ضرعي. تاسلجلل ذفنملا  
 ددحلا ذفنملا

Interface: FE1

Current Port Control: Authorized

Administrative Port Control:  Force Unauthorized  Auto  Force Authorized

RADIUS VLAN Assignment:  Disable  Reject  Static

Guest VLAN:  Enable

Open Access:  Enable

802.1x Based Authentication:  Enable

MAC Based Authentication:  Enable

Web Based Authentication:  Enable

Periodic Reauthentication:  Enable

Reauthentication Period: 3600 sec (Range: 300 - 4294967295, Default: 3600)

Reauthenticate Now:

Authenticator State: Force Authorized

Time Range:  Enable

Time Range Name: Edit

يه تارايل:

زاهال رفوي ال. اهب حرصم ريغ ةلاح يلال ةهجالو لقلع لمعي - هب حرصم ريغ ضرعي.  
 لوصول ضرعيو، ذفنملا اذهب لصتم ليمع يال ةقداصم

ةهجالو لقلعي. ددحلا ذفنملا ذفانملا يلال ةدنتسملا ةقداصملا نيكمتم - ئياقت.  
 رايلال اذرتخأ. ةقداصملا ةارجا ةجيتن يلال ةانب هب حرصم ريغو هب حرصم نيبي  
 802.1X ذيفنتل.

لوصولنا زاهجلا رفوييس .اهب حرصم ةلاح ىلا ةهجاوولا لقن ىلع لمعت - اهب حرصملا ةوقلا .  
ةقداصم نود ذفنملا اذهب لصتي لي مع يى ىلا

نكي متل 802.1X ىلا ةدنتسملا ةقداصملا لقح يى ف نكي مت راي تخالال ةناخ ددح .8 ةوطخلا  
ددحملل ذفنملا ل 802.1X ةقداصم

Interface:	FE1
Current Port Control:	Authorized
Administrative Port Control:	<input type="radio"/> Force Unauthorized <input checked="" type="radio"/> Auto <input type="radio"/> Force Authorized
RADIUS VLAN Assignment:	<input checked="" type="radio"/> Disable <input type="radio"/> Reject <input type="radio"/> Static
Guest VLAN:	<input type="checkbox"/> Enable
Open Access:	<input type="checkbox"/> Enable
802.1x Based Authentication:	<input checked="" type="checkbox"/> Enable
MAC Based Authentication:	<input type="checkbox"/> Enable
Web Based Authentication:	<input type="checkbox"/> Enable
Periodic Reauthentication:	<input type="checkbox"/> Enable
Reauthentication Period:	3600 sec (Range: 300 - 4294967295, Default: 3600)
Reauthenticate Now:	<input type="checkbox"/>
Authenticator State:	Force Authorized
Time Range:	<input type="checkbox"/> Enable
Time Range Name:	<input type="text"/> Edit

802.1X ةقداصملا لمالكلا ب انوكم نآلا ذفنملا نوكي نأ بجي .قبطي ةقطق .9 ةوطخلا  
لقح مدختسا .هب نيلصتم عال مع يى ةقداصم ادبل زهاج وهو ،ذفنملا ىلا ةدنتسملا  
ذفنملا ةقداصم ةحفص ىلا عوجرلا نود نيوكتل لل فلتخم ذفنم دي دحتل ةهجاوولا

802.1x Based Authentication:  Enable

MAC Based Authentication:  Enable

Web Based Authentication:  Enable

Periodic Reauthentication:  Enable

Reauthentication Period:  sec (Range: 300 - 4294967295, Default: 3600)

Reauthenticate Now:

Authenticator State: Force Authorized

Time Range:  Enable

Time Range Name:  [Edit](#)

Maximum WBA Login Attempts:  Infinite  
 User Defined  (Range: 3 - 10)

Maximum WBA Silence Period:  Infinite  
 User Defined  sec (Range: 60 - 65535)

Max Hosts:  Infinite  
 User Defined  sec (Range: 1 - 4294967295)

Quiet Period:  sec (Range: 10 - 65535, Default: 60)

Resending EAP:  sec (Range: 30 - 65535, Default: 30)

Max EAP Requests:  (Range: 1 - 10, Default: 2)

Supplicant Timeout:  sec (Range: 1 - 65535, Default: 30)

Server Timeout:  sec (Range: 1 - 65535, Default: 30)

[Apply](#) [Close](#)

ذفانم لآ نم قاطن وأ رخآ ذفنم ىلإ ةعرسب ذفنم لآ تادادع|خسن دىرت تنك اذا 10. ةوطخل رقناو ذفنم لآ ةقداصم لودج يف هخسن دىرت يذلا ذفنم لآ صاخلا ويدارلآ رز قوف رقنا خسن لآ تادادع| ةذفان رهظي .رز...خسن لآ تادادع| قوف

### Port Authentication

Port Authentication Table										
	Entry No.	Port	Current Port Control	Administrative Port Control	RADIUS VLAN Assignment	Guest VLAN	Open Access	802.1x Based Authentication	MAC Based Authentication	Web Based Authentication
<input checked="" type="radio"/>	1	FE1	Authorized	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	2	FE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	3	FE3	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	4	FE4	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	5	FE5	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	6	FE6	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	7	FE7	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	8	FE8	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	9	GE1	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled
<input type="radio"/>	10	GE2	N/A	Force Authorized	Disabled	Disabled	Disabled	Enabled	Disabled	Disabled

[Copy Settings...](#) [Edit...](#)

دىرت يتلآ (تالصافب ةلوصفم) ذفانم لآ وأ ذفنم لآ لخدأ، صن لآ ل قح يف 11. ةوطخل قىببط رقنا، كلذ دعب .ءانم لآ ىدم تنيع اضيأ عىطتسي تنأ .اهىلآ تادادع لآ خسن تادادع لآ خسن لآ

Copy configuration from entry 1 (FE1)

to:  (Example: 1,3,5-10 or: FE1,FE3-FE5)

عرض فيديو متعلق بهذه المقالة...

[انقر هنا لعرض المحادثات التقنية الأخرى من Cisco](#)

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت  
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او  
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب  
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او  
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco  
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل