

ىل ا دي هم ت Catalyst 9000 switches ل و ح م ل ا Stack 1+1 ري غ ت م ب ب س ب ة ب ل ا ط م : ل و ح م ل ا

ت ا ي و ت ح م ل ا

[ة م د ق م ل ا](#)

[ة ل ك ش م ل ا](#)

[ل ح ل ا](#)

[ة ل ص ت ا ذ ت ا م و ل ع م](#)

ة م د ق م ل ا

دهم ي ن ا ل ش ف ي ن ا ح ا ت ف م 9000 sery ة ز ا ف ح ة د ا م ل و ح ل و ح و ة ر د ا ن ة ل ك ش م ة ق ي ث و ا ذ ه ف ص ي
ش ح ة ل ا س ر (ح ا ت ف م) bootloder ف ي ط ق س ي و ي ع ي ب ط ل ك ش ب

ة ل ك ش م ل ا

1+1 ع ض و ي ف د ا د ع ت س ا ل ا / ط ا ش ن ل ا د ي د ح ت ل ش ف - ب ب س ل ا ، ل ي ح م ت ل ا ة د ا ع | 2 ل ك ي ه ل ا

```
switch: boot
attempting to boot from [flash:packages.conf]
```

```
Located file packages.conf
```

```
#
```

```
#####
#####
```

```
Validate packages: SHA-1 hash:
```

```
calculated 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA
```

```
expected 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA
```

```
Both links down, not waiting for other switches
```

```
Switch number is 2
```

```
Chassis 2 reloading, reason - Active/standby selection failed in 1+1 Mode <<<<<<
```

```
Feb 19 20:06:55.572 FP0/0: %PMAN-5-EXITACTION: Process manager is exiting: reload fp action requested
```

```
Feb 19 20:06:57
```

```
Initializing Hardware...
```

```
System Bootstrap, Version 16.6.1r [FC1], RELEASE SOFTWARE (P)
```

```
Compiled Sat 07/15/2017 8:31:57.39 by rel
```

```
Current image running:
```

```
Primary Rommon Image
```

```
Last reset cause: SoftwareReload
```

```
C9300-48U platform with 8388608 Kbytes of main memory
```

```
attempting to boot from [flash:packages.conf]
```

```
Located file packages.conf
```

```
#
```

```
#####  
#####
```

```
Validate packages: SHA-1 hash:
```

```
calculated 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA
```

```
expected 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA
```

1+1 س د ك م ل ل د ي ه م ت ل ل ل ي م ح ت ة ا د ا ر ي غ ت م ي ل ا ر ظ ن ل ل ي ه ة ل ك ش م ل ا ه ز ه د ي د ح ت ل ي ر خ ا ة ق ي ر ط ل ي م ح ت ة ا د ا ع ض و ي ف ل و ح م ل ا ل ع ل و ص ح ل ل . د ي ه م ت ل ل ل ي م ح ت ة ا د ا ع ض و ي ف s e t م ا د خ ت س ا ب د ي ه م ت ل ل ي ف ل و ح م ل ا ل ي غ ش ت ع د ب ا ن ا ث ا m o d e ق و ف ر ق ن ا ، د ي ه م ت ل ل

```
switch: set
```

```
ABNORMAL_RESET_COUNT=0
```

```
AUTOREBOOT_RESTORE=1
```

```
BOARDID=20569
```

```
BOOT=flash:packages.conf
```

```
BSI=0
```

```
MAC_ADDR=00:ab:cd:ef:01
```

```
MANUAL_BOOT=yes
```

```
MODEL_NUM=C9300-48UXM
```

```
MODEL_REVISION_NUM=D0
```

```
MOTHERBOARD_ASSEMBLY_NUM=73-17959-06
```

```
MOTHERBOARD_REVISION_NUM=A0
```

```
MOTHERBOARD_SERIAL_NUM=XXXXXXXXXXXX
```

```
RANDOM_NUM=1901228755
```

```
RET_2_RCALTS=
```

```
ROMMON_AUTOBOOT_ATTEMPT=3
```

```
STACK_1_1=2_0 <<<<<<
```

```
SWITCH_IGNORE_STARTUP_CFG=1
```

```
SWITCH_NUMBER=2
```

```
SYSTEM_SERIAL_NUM=XXXXXXXXXXXX
```

```
TEMPLATE=access
```

```
VERSION_ID=V01
```

```
switch:
```

لحل

ل ك ش ب د ي ه م ت ل ل ل ع ر د ا ق ح ا ت ف م ل ا ا ز ه ن و ك ي ن ا د ع ب . 1+1 س د ك م ل ا ر ي غ ت م ن ي ي ع ت ع ا غ ل ا ب م ق ي ع ي ط

```
switch:unset STACK_1_1
```

```
switch: set
```

```
ABNORMAL_RESET_COUNT=0
```

```
AUTOREBOOT_RESTORE=1
```

```
BOARDID=20569
```

```
BOOT=flash:packages.conf
```

```
BSI=0
```

```
MAC_ADDR=00:ab:cd:ef:01
```

```
MANUAL_BOOT=yes
```

```
MODEL_NUM=C9300-48UXM
MODEL_REVISION_NUM=D0
MOTHERBOARD_ASSEMBLY_NUM=73-17959-06
MOTHERBOARD_REVISION_NUM=A0
MOTHERBOARD_SERIAL_NUM=XXXXXXXXXXXX
RANDOM_NUM=1901228755
RET_2_RCALTS=
ROMMON_AUTOBOOT_ATTEMPT=3
SWITCH_IGNORE_STARTUP_CFG=1
SWITCH_NUMBER=2
SYSTEM_SERIAL_NUM=XXXXXXXXXXXX
TEMPLATE=access
VERSION_ID=V01
```

switch:

نأثيحب رمأ boot رادصإب مق م ث، 1+1 سدكملل ديهمتلا لي محت ةأدا ريغت م ني عت ةاغلا درجب
حاتفملا لىل ع ةومجم ريغت م ةمزجالا نم تدهم عي طتسي حاتفم

```
switch: boot
attempting to boot from [flash:packages.conf]
```

Located file packages.conf

#

```
#####
```

```
#####
```

Validate packages: SHA-1 hash:

calculated 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA

expected 550C9730:667B2788:DD6F6B06:D0FFA819:01A315DA

Both links down, not waiting for other switches

Switch number is 2

ةلص تاذا تامولعم

1:1 راركتلا لىل ع جرا، 1+1 سدكمللا عضولوح تامولعم لىل ع لوصحلل

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إلمءءاد ءوچرلاب ةصوء و تاملرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةلصلأل ةزىلچنل دن تسمل