

BroadWorks switchDeviceType ةزيم مادختسا

تايوتحمل

[ةمدقمل](#)

[ةيساسأل تابلطتم](#)

[تابلطتم](#)

[ةمدختسم تانوكمل](#)

[ةيساسأ تامولعم](#)

[مادختسال تاراخي](#)

[يلكوب](#)

[رمأ OCI-P](#)

[طاطخم XML](#)

[يلمعم لاثم](#)

[لاثم BWCLI](#)

[لجسال يلعل لاثم](#)

[ةلص تاذ تامولعم](#)

ةمدقمل

BroadWorks switchDeviceType ةزيم مادختسا دننتمسما اذه فصوي.

ةيساسأل تابلطتم

تابلطتم

دننتمسما اذهل ةصاخ تابلطتم دجوت ال.

ةمدختسم تانوكمل

ةنيم ةيدام تانوكم وجمارب تارادصا يلعل دننتمسما اذه رصتقي ال.

ةصاخ ةيلمعم ةئيبي يف ةدوجوملا ةزهجال نم دننتمسما اذه يف ةدراول تامولعمل عاشنإ مت تناك اذا. (يضا رتفا) حوسمم نيوكتب دننتمسما اذه يف ةمدختسملا ةزهجال عيمج تادب رما يال لمتمحمل ريثاتلل كمهف نم دكاتف، ليغشتلا ديقتك تكبش.

ةيساسأ تامولعم

نم زاهجال فيرعت فلم عون ليوحتل ةيلال لادام مت، دعب اميفو 23.0 رادصال، BroadWorks، نم رخاا دل دحاو.

مادختسال تاراخي

رمأ OCI-p و BWCLI رمأ نم ام اذيفنتل نكمي switchDeviceType رمأ ال ضرعي.

ي ل ك و ب

AS_CLI/System/Device/IpDeviceMgmt> help switchDeviceType

This command is used to switch device profiles from one device type to another.

Parameters description:

- attribute : The name of the attribute that scopes the command.
- system : This parameter specifies the switch command is issued at the system level.
- fromDeviceType : This parameter specifies the original device type.
- toDeviceType : This parameter specifies the destination device type.
- serviceProvider : This parameter specifies the switch command is issued at the service provider level.
- svcProviderId : This parameter specifies the ID of the service provider.
- group : This parameter specifies the switch command is issued at the group level.
- groupId : This parameter specifies the valid group within the service provider.
- systemDeviceProfile : This parameter specifies the switch command is issued for a single device profile at the system level.
- deviceName : This parameter specifies the name of the device profile.
- svcProvDeviceProfile: This parameter specifies the switch command is issued for a single device profile at the service provider level.
- groupDeviceProfile : This parameter specifies the switch command is issued for a single device profile at the group level.

```

=====
switchDeviceType
<attribute>, Choice = {system, serviceProvider, group, systemDeviceProfile,
svcProvDeviceProfile, groupDeviceProfile}
system:
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
serviceProvider:
<svcProviderId>, String {1 to 30 characters}
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
group:
<svcProviderId>, String {1 to 30 characters}
<groupId>, String {1 to 30 characters}
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
systemDeviceProfile:
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
svcProvDeviceProfile:
<svcProviderId>, String {1 to 30 characters}
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
groupDeviceProfile:
<svcProviderId>, String {1 to 30 characters}
<groupId>, String {1 to 30 characters}
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}

```

أ م أ OCI-P

```

<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
instance">

```

```

<sessionId xmlns="">SESSIONID</sessionId>
<command xsi:type="SystemDeviceManagementSwitchDeviceTypeDeviceRequest" xmlns="">
<svcProviderId>YOUR ENT/SP</svcProviderId>
<groupId>YOUR GROUP</groupId>
<deviceName>ORIGINAL DEVICE TYPE</deviceName>
<toDeviceType>NEW DEVICE TYPE</toDeviceType>
</command>
</BroadsoftDocument>

```

ط XML

```

<xs:complexType name="SystemDeviceManagementSwitchDeviceTypeDeviceRequest">
<xs:annotation>
<xs:appinfo>
<bwAppInfo bwtag="_1843b06e76464254bf146a91622df7b4" />
<asDataModeSupported>true</asDataModeSupported>
<amplifyDataModeSupported>true</amplifyDataModeSupported>
<xsDataModeSupported>true</xsDataModeSupported>
</xs:appinfo>
<xs:documentation>
Switch the device type for a specified device.
To switch a system level device profile, serviceProviderId and groupId should not be present.
To switch a service provider level device profile, only serviceProviderId should be specified.
To switch a group level device profile, serviceProviderId and groupId should specified.
The response is either a SuccessResponse or an ErrorResponse.
</xs:documentation>
</xs:annotation>
<xs:complexContent>
<xs:extension base="core:OCIRequest">
<xs:sequence>
<xs:choice minOccurs="0">
<xs:element name="serviceProviderId" type="ServiceProviderId"/>
<xs:sequence>
<xs:element name="svcProviderId" type="ServiceProviderId"/>
<xs:element name="groupId" type="GroupId"/>
</xs:sequence>
</xs:choice>
<xs:element name="deviceName" type="AccessDeviceName"/>
<xs:element name="toDeviceType" type="AccessDeviceType"/>
</xs:sequence>
</xs:extension>
</xs:complexContent>
</xs:complexType>

```

ي لم عم ل اثم

ل اثم BWCLI

ل اثم اذه ل cisco-CP-78xx-88xx-68xx-3PCC ل ل عون ة ادا Poly_VVX_D230 نم DeviceProfile ة وم جم تن ل ل وحي، ل اثم اذه ل عون ة ادا

- زاه ل ل Poly_VVX_D230 ن ي عت و Poly_VVX_D230_Switch ة وم جم زاه ل في رعت فلم ة فاضا ل

```

AS_CLI/System/Device/IpDeviceMgmt> add pws_ent pws_grp Poly_VVX_D230_Switch Poly_VVX_D230
macAddress 678678678678

```

- ل ل Cisco-CP-78xx-88xx-68xx-3PCC ل ل في صوت ل ل نم حات فلم ل ل تن جن أ 3PCC:

```
AS_CLI/System/Device/IpDeviceMgmt> switchDeviceType groupDeviceProfile pws_ent pws_grp
Poly_VVX_D230_Switch Cisco-CP-78xx-88xx-68xx-3PCC
...Done
[Request for switch is being processed; Rebuild triggered for device type: Cisco-CP-78xx-88xx-
68xx-3PCC,
please refer to DMEventQueues for completion status.]
```

لجسلا ىلع لاثم

PSLog. نم هتدهاشم مت يذلا اذه بلطلال عون لجسل لاثم اذه

2022.05.26 09:34:57:686 EDT | Info | OCI-P | BCCT Worker #0

```
Received the following request from: 127.0.0.1:56212
<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
instance">
<sessionId xmlns="">16535720065220.14787900206648874</sessionId>
<command xsi:type="SystemDeviceManagementSwitchDeviceTypeDeviceRequest" xmlns="">
<svcProviderId>pws_ent</svcProviderId>
<groupId>pws_grp</groupId>
<deviceName>Poly_VVX_D230_Switch</deviceName>
<toDeviceType>Cisco-CP-78xx-88xx-68xx-3PCC</toDeviceType>
</command>
</BroadsoftDocument>
```

2022.05.26 09:34:57:711 EDT | FieldDebug | Generic | BCCT Worker #0

```
OCI Transaction
com.broadsoft.oci.transactions.system.SystemDeviceManagementSwitchDeviceTypeDeviceTransaction
write5193 executed.
User: Default Administrator (admin) Authorization Level: System
Start Time: 2022.05.26 09:34:57:687 EDT
End Time: 2022.05.26 09:34:57:711 EDT
Duration: 24 ms
```

2022.05.26 09:34:57:711 EDT | Info | OCI-P | BCCT Worker #0 | admin

```
TO 127.0.0.1:56212
<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
instance">
<sessionId xmlns="">16535720065220.14787900206648874</sessionId>
<command echo="" xsi:type="c:SuccessResponse" xmlns:c="C" xmlns=""/>
</BroadsoftDocument>
```

ةلص تاذا تامول عم

- [DeviceProfileTypeCustomizationEnhanced-AS-FD](#)
- [Cisco نم تاليزن تالواو ينق تال مرعدلا](#)

ةمچرتل هذه ل و ح

ةلأل تاي نقتل ن م ة و مچ م ادخت ساب دن تسمل اذ ه Cisco ت مچرت
ملاعلاء ان ا عي مچ ي ف ن ي م دخت سمل ل معد ي و تح م مي دقت ل ة ي رش ب ل و
امك ة ق ي قد ن و ك ت ن ل ة ي ل ة مچرت ل ض ف ا ن ا ة ظ حال م ي ج ر ي . ة ص ا خ ل م ه ت غ ل ب
Cisco ي ل خ ت . ف ر ت ح م مچرت م ا ه م د ق ي ي ت ل ا ة ي ف ا ر ت ح ا ل ا ة مچرت ل ا ع م ل ا ح ل ا و ه
ي ل ا م ا د ع و ج ر ل ا ب ي ص و ت و ت ا مچرت ل ا ه ذ ه ة ق د ن ع ا ه ت ي ل و ئ س م Cisco
Systems (رف و ت م ط بار ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا دن تسمل ا