

ىلع تازيمل او طيشنتلا حياتافم تيبتت TelePresence ماظنل ISDN (ISDN GW) ةباوب نم Cisco

تايوتحمل

[ةمدقمل](#)

[ةيساسأل تابلطمل](#)

[ةمدختسمل تانوكمل](#)

[نيوكتلا](#)

[بيولا ةهجاو ربع ةزيملا حياتافم وأجتنملا طيشنت ةفاضلا](#)

[نيوكتلا](#)

[ةحصللا نم ققحتلا](#)

[اهجالص او ءاطخال افاشكتسا](#)

ةمدقمل

ماظنل ISDN (ISDN GW) ةباوبل ةزيم حياتافم و طيشنت حياتافم تيبتت دنتملا اذه فصوي
بيولا ةهجاو ربع Cisco نم TelePresence.

ةيساسأل تابلطمل

تابلطمل

ةيلالل عيضاوملاب ةفرعم كيديل نوكت نأب Cisco ي صوت:

ةهجاو ربع هيلل لوصوللا نكمي حل اص IP ناو نع تقب طو ح اجنب ISDN GW تيبتت تمق دقل
بيولا.

مقرلل حل اصللا ةزيملا حياتافم و طيشنتلا حياتافم ىلع لوصولل بلط مي دقت مت
همالتساو ISDN GW يلسلسلا

بيولا ةهجاو ةطساوب لوؤسم باسح مادختساب ISDN GW ىل لوصولاب عتمت

Cisco TelePresence MSE و ISDN GW 3241 ل ةفلتخملا ةيساسأل ةمظنألاب ةفرعم ىلع نك
بيولا ةهجاو مادختساب ISDN GW 8321.

Chrome و Internet Explorer و Firefox لثم بيو ضرعتسم مادختسا

انه ISDN GW تيبتت ةلدأ ىلع روثعلا نكمي: **ةظالم**

<http://www.cisco.com/c/en/us/support/conferencing/telepresence-isdn-gateway/products-installation-guides-list.html>

ةمدختسمل تانوكمل

ةةلللالل اءماربلال اراراصلإ إلى دنلسملا اذه في ةءراولال اامولعملال دنلسل:

Cisco ISDN GW 8321 راراصلإال 2.2(1.114)

ءزيملا اءافم وأ طيشنللال اءافم ماءءلساب ينورللالل الءرل الء عيمء

ءزيملا اءافم وأ طيشنللال اءافم ماءءلساب ينورللالل الءرل الء عيمء

Chrome وأ Internet Explorer وأ Firefox لءم بيوضرعللسم

ءصاوءلللمعم ةئبب في ةءووءولل ةزهألل نم دنلسملا اذه في ةءراولال اامولعملال ءاشنإمء
لنالك اءا (يضرارللال). ءوسمم نبوكلب دنلسملا اذه في ةمءءلسملا ةزهألل عيمءلءب
رملال لللمءءلملال رلءاللل كمهل نم ءكأءل ءءرءابم كءكبلبش

نلوكلل

ببولل ةهءاو ربل ةزيملا اءافم وأ ءلنملا طلشنل ءافاصلإ

ءنلسملا اذه لامكلساب وللءلفلاب اذه ببولل ةهءاو لءم موقل

نلوكلل

مءءءو ولسلسللسللال مقررلال لعل لولصلالو ءب صاأل ISDN GW لبلبءلء ءرءمب 1. ةوطللال
كنكمل ءلسلسللسللال مقررلال و PAK مقررلال ماءءلساب كلءل ةزيملا اءافم وأ طلشنللال اءافم
Cisco صلءرل ءلرف نم صلءرللاب صاأل ينورللالل الءرل ببلل

ءنلسملا اذه قاطن ءراء PAK لعل ةلءمأ ءءو: ءظءالم

ءرللال لعل لءم
لنورللالل

*** IMPORTANT - DO NOT DISCARD THIS E-MAIL ***

You have received this email because your email address was provided to Cisco Systems during the Serial Number Lookup process for software license activation key/file. Please read this email carefully and forward it with any attachments to the proper system administrator if you are not the correct person.

System Serial Number : SM011A5A
Hardware Serial Number : SM011A5A
MAC Address : 000D7C0234B4
Service Contract : 3630730
SC End Date : 09/27/2017

Software Part Name : LIC-TB-198321SW:
Tandberg Item No : 198321SW:SW, MSE8321 ISDN GW Blade Software
Shipped Version : 2.0(1.51)P
Shipped Version Key : MVR55-Y7M23-UWK91-R7YRT
Shipped Image URL : -
Upgrade To : 2.1(1.49)
Upgrade To Key : MVR55-Y7M23-UWK91-R7YRT
Upgrade To Image URL : -

Activation Key

Options
Cisco Option Name : LIC-AESCDN-K9:
Tandberg Option Name : 194200AES:KEY, Encryption Option Key
Option Key : VX8G5-Y09U5-2UF5M-BG3FR

Feature Key

CAUTION: If the Unified Messaging for Exchange and Domino license file is misplaced or lost, it can take up to one business day to get another copy.

PLEASE READ THIS SOFTWARE LICENSE AGREEMENT CAREFULLY BEFORE DOWNLOADING, INSTALLING OR USING CISCO OR CISCO-SUPPLIED SOFTWARE.

BY DOWNLOADING OR INSTALLING THE SOFTWARE, OR USING THE EQUIPMENT THAT CONTAINS THIS SOFTWARE, YOU ARE BINDING THE BUSINESS ENTITY THAT YOU REPRESENT ("CUSTOMER") TO THIS AGREEMENT. IF YOU DO NOT AGREE TO ALL OF THE TERMS OF THIS AGREEMENT, THEN (A) DO NOT DOWNLOAD, INSTALL OR USE THE SOFTWARE, AND (B) YOU MAY RETURN THE SOFTWARE FOR A FULL REFUND, OR, IF THE SOFTWARE IS SUPPLIED AS PART OF ANOTHER PRODUCT, YOU MAY RETURN THE ENTIRE PRODUCT FOR A FULL REFUND. YOUR RIGHT TO RETURN AND REFUND EXPIRES 30 DAYS AFTER PURCHASE FROM CISCO OR AN AUTHORIZED CISCO RESELLER, AND APPLIES ONLY IF CUSTOMER IS THE ORIGINAL END USER PURCHASER.

The following terms of this Software License Agreement ("Agreement") govern Customer's access and use of the Software, except to the extent (a) there is a separate signed agreement between Customer and Cisco governing Customer's use of the Software or (b) the Software includes a separate "click-accept" license

إلى لوخذل لچسو و ك ب صراخل بيولا ضرعتسم في ISDN GW ب صراخل IP ناووع لخدأ 2. ةوطخل
> تادادعالإ إلى لقتنا. لوؤسم باسح مادختساب ISDN GW بيولا ةهواو
ةيقرتلا:

The screenshot shows the Cisco ISDN GW 8321 web interface. The top navigation bar includes 'Home', 'Status', 'Network', 'Settings', 'Gatekeeper', 'Dial plan', 'Users', and 'ISDN'. The 'Settings' menu item is highlighted with a red box and an arrow. Below the navigation bar, the 'Upgrade' tab is selected and highlighted with a red box and an arrow. The main content area is divided into several sections: 'Firmware updates' (Main software image and Loader software), 'Back up and restore' (Back up configuration and Restore configuration), and 'Feature management'. The 'Main software image' section shows the current version as 2.2(1.114)P and a 'Browse...' button for selecting a new image file. The 'Loader software' section shows the current version as 1.0(0.1) and a 'Browse...' button for selecting a new image file. The 'Back up configuration' section has a 'Save backup file' button. The 'Restore configuration' section has 'Overwrite settings' checkboxes for 'Network settings' and 'User settings', a 'Browse...' button for selecting a backup file, and a 'Restore backup file' button.

وأطيشتننللاتم ةمي ق لخدأ. ةيقرتلا ةحفص في تازيملا ةرادإ مسق ةقوم ددح 3. ةوطخل
طيشننللا زمر ل قح في ةزيملا ةحاتم ةمي ق:

Home Status Network Settings Gatekeeper Dial plan Users ISDN Logout Logs Help

Home > Settings > Upgrade

ISDN ISDN ports H.323 SIP Encryption Time Security User interface Auto attendant Upgrade Shutdown

Firmware updates

Main software image
Current version 2.2(1.11-4)P
New image file No file selected.
 For normal upgrades.

Loader software
Current version 1.0(0.1)
New image file No file selected.
 Only for use with upgrades under the guidance of Cisco customer support.

Back up and restore

Back up configuration
 Warning: backup file may contain sensitive information about your system.

Restore configuration
Overwrite settings Network settings User settings
Backup file to be restored No file selected.
 Warning: back up current system configuration prior to attempting a restore operation.

Feature management

Feature management
Activated features: MSE 8321 activation (M/R/S5-Y7M23-UWK91-R7YRT)
Encryption (VY9G5-Y09U5-2LFSM-8G3FR)
License keys: PRI port licenses x 8 (LNK7FM5-4M66GJGJ3BQ6P8U8)
Activation code:

Activation and Feature Keys take effect immediately. A reboot is NOT required.

اهحال صإو ءاطخأل فاشكتسا

هنا نم دكاتو ،همالتسا مت يذلا طيشنتل حاتفم وأ ءزيملا حاتفم نم ققحت 1 ةوطخلال ISDN ل ححصلا ل سلسلتا مقررلا ل لوصحلل هرادصا مت و ححصلا (PID) حتنملا فرعمل GW.

ISDN GW ل ححصلا ل سلسلتا مقررل ححصلا حاتفملا تيبثت نم دكات 2 ةوطخلال

يف تازيملا ءراد مسق نم طيشنتلا زمر ل قح يف حاتفملا ءمي ق لاخذإ نم دكات 3 ةوطخلال ءة ققرتلا > تاداعإلا ءحفص.

مقف ،ححصلا ل ل ناك اذا . ىرخأ ءرم ثالث ىلإ ءحواو نم تاوطخلال مبيقتب مق 4 ةوطخلال يتلا ءمي قلا يف ءة فاضا فورح وأ تافاسم دوجو مدع نم دكات . ىرخأ ءرم حءة افملا ءفاضاب طرش ياً ني مضا نم دكات و اهلل اءم

مسق يف ءة برأ ىلإ ءحواو نم تاوطخلال وليلدلا اءه يف تاوطخلال ءبتا نا ءعب اءخ ياً تنأ ءءاوي نا م Cisco TAC ب لصتا ، لىلدلا اءه نم اءحال صإو ءاطخأل فاشكتسا

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةلخت. فرتمة مچرت مء دقء ةل ةل ةفارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةلصلأل ةزءل ءنل دن تسمل