

CUCM PLAR نيوكت لاثم

تايوت حمل

[قمدق مل](#)

[تاب ل ط م ل](#)

[قمدخت س م ل تانوك م ل](#)

[نيوكت ل ت اوطخ](#)

[SCCP PLAR نيوكت](#)

[SIP PLAR نيوكت](#)

[قحص ل ا نم ق قحت ل](#)

قمدق مل:

Auto صاخ ل طخل ل يئاق ل ل ل قان ل ل Cisco IP فتاه نيوكت ةي ف ي ك دن ت س م ل اذه ش قان ي
Cisco Unified Communications Manager م ادخت س اب ن خاس ل ل ل اص تال ا و (PLAR) Ring-Down (CUCM).

م ادخت س اب ددحم طخب ل اص تال ا نع فتاه ل ا ع طق درجم ب موقت ش ي ح ب Plar ةزيم م ي م ص ت م ت ي
اقب س م ه نيوكت م ت م ق ر .

Cisco. TAC س دن ه م ، س و ب و ل ا ل ي ف ه ي س و خ ل ب ق ن م ة م ه اس م ل ا ت م ت

Cisco. TAC س دن ه م ، ز ي ر ي م ا ر س ي و ل ر ي ر ح ت

تاب ل ط م ل

ةي ل ل ا ل ع ي ض ا و م ل ا ب ة فر ع م ك ي د ل نو ك ت ن ا ب Cisco ي ص و ت

- Cisco Unified Communications Manager (CUCM) جم ان رب
- ل و ح م ل ا ة ح اس م ا ع ا د ت س ا (CSS)
- م س ق ل ل (PT)
- ة م ج ر ت ل ا ط ا م ن ا
- ل م ع ة س ل ج ا د ب ل و ك و ت و ر ب ب ل ط د ع ا و ق (SIP)

قمدخت س م ل تانوك م ل

ةي ل ل ا ل ا ة ي د ا م ل ا تانوك م ل ا و ج م ا ر ب ل ا ت ا ر ا د ص ا ل ا دن ت س م ل ا اذه ي ف ة د ر ا و ل ا ت ا م و ل ع م ل ا دن ت س ت

- CUCM 10.5
 - CUCM ع م SIP فتاه و ه Skinny Client Control Protocol (SCCP) ل و ك و ت و ر ب ل ي ج س ت م ت ي
- ة ص ا خ ة ي ل م ع م ة ي ب ي ف ة د و ج و م ل ا ة ز ه ا ل ا ن م دن ت س م ل ا اذه ي ف ة د ر ا و ل ا ت ا م و ل ع م ل ا ا ش ن ا م ت
ت ن ا ك ا ذ ا . (ي ض ا ر ت ف ا) ح و س م م نيوكت ب دن ت س م ل ا اذه ي ف ة م د خ ت س م ل ا ة ز ه ا ل ا ع ي م ج ت ا د ب
ر ي ي غ ت ي ا ل ل م ت ح م ل ا ر ي ث ا ت ل ل ك م ه ف ن م د ك ا ت ف ، ة ر ش ا ب م ك ت ك ب ش

ةلصللا تاذا تاجت نمللا

ةغصي صةيج مرربو زاهج اذة عم تللمعتسا تنك اضيأ عيطتسي ةقيثو اذة

- CUCM 8.X/9.X/11.X

ننيوكتلا تاوطخ

ننيوكت SCCP PLAR

نع IP فتاه جورخ دنع ايئاقلت اقبس م هنيوكت مت فتاه مقرر بلطب فتاه لل حامسلل ةغراف ةمچرت طمن ةلسلسب ةمچرت طمن ىلع يوتحي ميسقتب CSS ننيوكت متي، راسملا طمن موقبي كلذ دعب. طمنلا اذة عم ةرشابم Cisco نم تاملكملا ريديم قباطت ىلإ يدؤي اذو ميست متي ثيح (Hotdial) ةهوللا مقرر ىلإ (ءيش ال يأ) ىعدتسملا مقررلا ليوحتب ةمچرتلا ةملاكملا.

مت امقرر صخللي PLAR ماقرال هنيوكت مت يذلا (DN) ليلدلا مقرر نأل ارظن: **ةظالم** ماقرا ةيأ بلطل PLAR DN مادختسا كنكمي ال، راسملا نع هجورخ دنع اقبس م هنيوكت قدانفلا يف طغضلا تاعامج يفي يجذومن ننيوكت اذو، لاثملا ليبس ىلع. ىرخأ

PLAR ةهول مسق 1. Crete ةوطخلا

لخدأ. ديديج مسقة فاضاب مقرر م مسقلا >ةئفلا يفي مكحتلا >تاملكملا هيچوت ىلإ لقتنا جاردل قوف رقتنا مثة بولطملا لىصافتلا



Save

Status

Status: Ready

Partition Information

To enter multiple partitions, use one line for each partition entry. You can enter up to 75 partitions; the names and descriptions can have up to a total of 1475 characters. The partition name cannot exceed 50 characters. Use a comma (',') to separate the partition name and description on each line. If a description is not entered, Cisco Unified Communications Manager uses the partition name as the description. For example:

<< partitionName >> , << description >>

CiscoPartition, Cisco employee partition

DallasPartition

Name*

ديج CSS عاشن | 2. ةوطخل

ةفاض | رقنا م ث شحب لة حاسم | ءاعدتس | > ءائفال | ف م كحتال | > تاملالكم لاهي جوت | ل لقتنا
ة. ديج ءاعدتس | شحب ءحاسم

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management

Calling Search Space Configuration

Save  Delete  Copy  Add New

Status

 Status: Ready

Calling Search Space Information

Name*

Description

Route Partitions for this Calling Search Space

Available Partitions**

- Directory URI
- Global Learned E164 Numbers
- Global Learned E164 Patterns
- Global Learned Enterprise Numbers
- Global Learned Enterprise Patterns

Selected Partitions

- to1161

ةمچرت طمن ءاشنإ. 3 ةوطخلإ

مسا ددح. ددج ةمچرت طمن ةفاضإ قوف رقنا مث >لاصتالآ هچوت ةمچرت طمن ىلإ لقتنا ةیناثلا ةوطخلآو ىلوالآ ةوطخلآ یف اقبس م امه ءاشنإ مت نیذلل CSS و بولطمل مسقلا جاردا قوف رقنا. PLAR فده مقررلخدا، فرطلا لېوت عانق یمسې تحت، اریخأ

اغراف ةمچرتلا طمن ل قح كرت نم دكأت: ةطحال م

Cisco

- هلې مېحت دي رت ي ذل ا DN رت خ او، Plar ف تاه ددح
- ل ج ا ن م DN ل ل CSS ع م ج ت

Phone Configuration Related Links: Back To Find/List

Save Delete Copy Reset Apply Config Add New

Status: Ready

Association

- 1 Line [1] - 1054 (no partition)
- 2 Line [2] - Add a new DN
- 3 Add a new SURF
- 4 Add a new BLF SD
- 5 Add a new SD
- 6 Add a new BLF Directed Call Park
- 7 CallBack
- 8 Call Park
- 9 Call Pickup
- 10 Conference List
- 11 Conference
- 12 Do Not Disturb
- 13 End Call
- 14 Forward All
- 15 Group Call Pickup

Phone Type

Product Type: Cisco 7942
Device Protocol: SCCP

Real-time Device Status

Registration: Registered with Cisco Unified Communications Manager josevil-105
IPv4 Address: 10.201.192.57
Active Load ID: SCCP42.9-4-2-15
Download Status: None

Device Information

Device is Active
Device is trusted
MAC Address*: 108CCFE06150
Description: Auto 1054
Device Pool*: Default
Common Device Configuration: < None >
Phone Button Template*: Universal Device Template Button Layout
Softkey Template: < None >
Common Phone Profile*: Standard Common Phone Profile
Calling Search Space: < None >

Directory Number Configuration

Save Delete Reset Apply Config Add New

Status: Ready

Directory Number Information

Directory Number*: 1054 Urgent Priority

Route Partition: < None >

Description:

Alerting Name:

ASCII Alerting Name:

External Call Control Profile: < None >

Allow Control of Device from CTI

Associated Devices: SEP108CCFE06150

Dissociate Devices:

Edit Device
Edit Line Appearance

Directory Number Settings

Voice Mail Profile: < None > (Choose <None> to use system default)

Calling Search Space: PlarTo1161

BLF Presence Group*: Standard Presence group

User Hold MOH Audio Source: < None >

Network Hold MOH Audio Source: < None >

Auto Answer*: Auto Answer Off

Reject Anonymous Calls

م ت CSS ن كل و، 1161 ل ل 1054 DN ل ل ع PLAR ءاش ن ا ب اذه ن ي و ك ت ل ل ا ل ا م م و ق ي : ة ط ح ا ل م
ل ل ع ف ل ت خ م ر ز ل ل ا ر خ ا DN ن ي ع ت ة ي ن ا ك م ا ر ف و ي ي ذ ل ا، DN ل و ت س م ل ل ا ه ن ي و ك ت

ةزيم ىلع ريثأتلا نود IP فتاه س فن نم ةيداع تاملكم ءارج اب حم سي امم ، فتاهلا PLAR.

SIP PLAR نيوكت

SIP PLAR ب ل ط دع اوق ءاشن ا 1. ةوطخل

- SIP ب ل ط دع اوق > ب ل ط لا دع اوق > تاملكم لا هي جوتى ل ا ثحن N
- دي دج ةفاض ا .

The screenshot shows the 'SIP Dial Rule Configuration' interface. At the top, there are buttons for Save, Delete, Reset, Apply Config, and Add New. Below this is a 'Status' section with an 'Update successful' message. The main configuration area is divided into three sections: 'SIP Dial Rule Information', 'Pattern Information', and 'Pattern Addition'. 'SIP Dial Rule Information' contains fields for Name (PlarTo1161), Description (Plar for Button 2), and Dial Pattern (7940_7960_OTHER). 'Pattern Information' is a table with columns for Description, Delete Pattern Dial Parameter, Value, and Delete Parameter. It shows a row for '1161' with a dropdown for 'Button' and a value of '2'. 'Pattern Addition' has a 'Pattern Description' field and 'Add Pattern' and 'Add Plar' buttons. At the bottom, there are buttons for Save, Delete, Reset, Apply Config, and Add New.

ي راي تخ ا فصولا لقح : ةظحالم

زاهجل طقف 1 DN ىلع PLAR ةزيم رابجل ، رز ىلع ب ل ط لا ةم لعم ني عت مت : ةظحالم

ىرخ ا PLAR ةدعاق ءاشن ا مزلي ، IP فتاه و ا ر خ ر ز ي ف ابولطم PLAR ناك اذ ا : ةظحالم

SIP فتاهو ىل ا ةدعاقلا ني عت ب مق . 2. ةوطخل

SIP فتاهو ىلع طقف بولطم اذه

The screenshot shows the 'Protocol Specific Information' interface. It contains several configuration options: Packet Capture Mode (None), Packet Capture Duration (0), BLF Presence Group (Standard Presence group), SIP Dial Rules (PlarTo1161), MTP Preferred Originating Codec (711ulaw), Device Security Profile (Cisco 7942 - Standard SIP Non-Secure Profile), Rerouting Calling Search Space (< None >), SUBSCRIBE Calling Search Space (< None >), SIP Profile (Standard SIP Profile), and Digest User (< None >). There are also checkboxes for Media Termination Point Required, Unattended Port, and Require DTMF Reception. A 'View Details' link is next to the SIP Profile field.

ةحصللا نم ققحتلا

فتاهل مقرر. فاطخلال نم فتاهل اةلازاب مق، ححص لكشب نيوكتلا ذيفنت نم ققحتلل
ايئاقلت 1161.

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إلمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل