



Release Notes for Cisco Business 220 Series Switches - Software Version 2.0.0.17

First Published: 2021-04-13

Introduction

April 2021

This Release Note describes the recommended practices and known issues that apply to software version 2.0.0.17 for the Cisco Business 220 Series Switches that include the following models:

Model	Product Label
CBS220-8T-E-2G	10-Port Gigabit Smart Switch
CBS220-8P-E-2G	10-Port Gigabit PoE Smart Switch
CBS220-8FP-E-2G	10-Port Gigabit PoE Smart Switch
CBS220-16T-2G	18-Port Gigabit Smart Switch
CBS220-16P-2G	18-Port Gigabit PoE Smart Switch
CBS220-24T-4X	24-Port Gigabit Smart Switch
CBS220-24FP-4G	24-Port Gigabit PoE Smart Switch
CBS220-24P-4X	24-Port Gigabit PoE Smart Switch
CBS220-24FP-4X	24-Port Gigabit PoE Smart Switch
CBS220-48T-4X	48-Port Gigabit Smart Switch
CBS220-48P-4X	48-Port Gigabit PoE Smart Switch
CBS220-48FP-4X	48-Port Gigabit PoE Smart Switch
CBS220-24T-4G	24-Port Gigabit Smart Switch
CBS220-24P-4G	24-Port Gigabit PoE Smart Switch
CBS220-48T-4G	48-Port Gigabit Smart Switch
CBS220-48P-4G	48-Port Gigabit PoE Smart Switch

Resolved Issues

Table 1: Caveats Resolved in Release V2.0.0.17

Number	Description
CSCvx44876	Symptom Light memory leak when running PnP for a long time.
CSCvx44877	Symptom STP Loopback Guard functionality is missing on WEB GUI.
CSCvx44878	Symptom ACL fails to block DHCP packets if DHCP snooping is enabled.
CSCvx99239	Symptom Memory leak on CBD subscription actions.
CSCvx99245	Symptom PnP configuration template function is not working correctly.
CSCvx99248	Symptom Import configuration with user account which contain quote will add extra quotes.

Introduction

February 2021

This Release Note describes the recommended practices and known issues that apply to software version 2.0.0.13 for the Cisco Business 220 Series Switches that include the following models:

Model	Product Label
CBS220-8T-E-2G	10-Port Gigabit Smart Switch
CBS220-8P-E-2G	10-Port Gigabit PoE Smart Switch
CBS220-8FP-E-2G	10-Port Gigabit PoE Smart Switch
CBS220-16T-2G	18-Port Gigabit Smart Switch
CBS220-16P-2G	18-Port Gigabit PoE Smart Switch
CBS220-24T-4X	24-Port Gigabit Smart Switch
CBS220-24P-4X	24-Port Gigabit PoE Smart Switch
CBS220-24FP-4X	24-Port Gigabit PoE Smart Switch
CBS220-48T-4X	48-Port Gigabit Smart Switch

Model	Product Label
CBS220-48P-4X	48-Port Gigabit PoE Smart Switch
CBS220-48FP-4X	48-Port Gigabit PoE Smart Switch
CBS220-24T-4G	24-Port Gigabit Smart Switch
CBS220-24P-4G	24-Port Gigabit PoE Smart Switch
CBS220-48T-4G	48-Port Gigabit Smart Switch
CBS220-48P-4G	48-Port Gigabit PoE Smart Switch

What's New

1.1 Browser and OS Support

The device web UI supports the following browsers and OS system:

- Supported OS – MS Windows 7 (32 & 64 bit), MS Windows 10 (32 & 64 bit), MAC OS (not supported: MS Windows 8, 8.1, XP and Vista; Linux).
- Supported Browsers – Chrome, Firefox and Microsoft Edge (Microsoft Internet Explorer not supported) – both for Windows and for MAC OS; Safari – MAC OS only.

1.2 Web GUI Style

Cisco Business Switches support a new modern web UI style which provides better user experience compared to the web UI implemented on the Sx220 switches.

1.3 Password Complexity

For enhanced security, the user does not have the option to disable the password complexity setting. The password complexity is supported with the following default and ranges:

- Minimum length – range 8-64, default = 8
- Minimum class – range 1-4, default = 3
- Number of repeat characters– range 1-16, default = 3
- New passwords cannot match the current password.
- Passwords cannot reverse or repeat the username nor Cisco.

1.4 SSL Cipher Support

For enhanced security, support following Ciphers:

- TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384 (secp256r1)
- TLS_ECDHE_RSA_WITH_AES_128_GCM_SHA256 (secp256r1)
- TLS_DHE_RSA_WITH_AES_256_GCM_SHA384 (dh 1024)

- TLS_DHE_RSA_WITH_AES_128_GCM_SHA256 (dh 1024)
- TLS_RSA_WITH_AES_256_GCM_SHA384 (rsa 2048)
- TLS_ECDHE_RSA_WITH_CHACHA20_POLY1305_SHA256 (secp256r1)
- TLS_DHE_RSA_WITH_AES_128_CBC_SHA256 (dh 1024)
- TLS_DHE_RSA_WITH_AES_128_CBC_SHA (dh 1024)
- TLS_RSA_WITH_AES_128_GCM_SHA256 (rsa 2048)
- TLS_AES_256_GCM_SHA384
- TLS_CHACHA20_POLY1305_SHA256
- TLS_AES_128_GCM_SHA256

1.5 SSL Cipher Support

OpenSSL version 1.1.0l.

1.6 Password Encryption

In the current release, the user's credentials are salted and hashed using PBKDF2 based on HMAC-SHA-256 hash. This adds additional security to the credentials and protects them from various attacks.

Relevant credentials:

- Local database Password
- Enable password

1.7 Self-Signed Certificate Lifetime

- Default: 3652 days (i.e., 10 years)

1.8 PNP Client

The Cisco Plug-n-Play (PnP) solution reduces the costs associated with deployment/installation of network devices, increase the speed of their installation and reduce the complexity of deployments without compromising the security. User can perform Zero Touch Installs of the CBS220 in various deployment scenarios and deployment locations.

1.9 CBD Call Home Agent

With Cisco Business Dashboard (CBD) Call home agent, CBS 220 can be monitored and managed by CBD manager.

1.10 Tech Support

Through WEB GUI or CLI user can generate the diagnostic information from switch for troubleshooting.

1.11 Locate device

Through WEB GUI user can blink all ports' LEDs in front panel to locate device.

Known Issues

Table 2: Caveats Acknowledged in Release V2.0.0.13

Number	Description
CSCvx44873	<p>Symptom</p> <p>Packet loss occurs in RFC 2889 Back Pressure test when sending jumbo frame. Issue happens when packet size is greater than 6144 bytes in 100Mbps speed or 5120 bytes in 1Gbps speed.</p> <p>Workaround</p> <p>None.</p>
CSCvx44875	<p>Symptom</p> <p>RSPAN destination port always receives double broadcast/multicast packets if source port send broadcast/multicast packets.</p> <p>Workaround</p> <p>None.</p>
CSCvx44876	<p>Symptom</p> <p>Light memory leak when running PnP for a long time.</p> <p>Workaround</p> <p>Disable PnP agent.</p>
CSCvx44877	<p>Symptom</p> <p>STP Loopback Guard functionality is missing on WEB GUI.</p> <p>Workaround</p> <p>Configure it via CLI.</p>
CSCvx44878	<p>Symptom</p> <p>ACL fails to block DHCP packets if DHCP snooping is enabled.</p> <p>Workaround</p> <p>None.</p>
CSCvx44879	<p>Symptom</p> <p>PNP agent cannot connect manager via ipv6 link-local address.</p> <p>Workaround</p> <p>Use IPv4 unicast or IPv6 global unicast address.</p>

Cisco Business Online Support

For current support information, visit the pages given below:

Cisco Business	
Cisco Business Home	http://www.cisco.com/go/ciscobusiness
Support	
Cisco Business Support Community	http://www.cisco.com/go/cbcommunity
Cisco Business Support and Resources	http://www.cisco.com/go/smallbizhelp
Cisco Business Phone Support	http://www.cisco.com/go/cbphone
Cisco Business Chat Support	http://www.cisco.com/go/cbchat
Cisco Business Firmware Downloads	http://www.cisco.com/go/smallbizfirmware Select a link to download the firmware for your Cisco product. No login is required.
Cisco Business Open Source Requests	If you wish to receive a copy of the source code to which you are entitled under the applicable free/open source license(s) (such as the GNU Lesser/General Public License), please send your request to: external-opensource-requests@cisco.com . In your request, please include the Cisco product name, version, and the 18 digit reference number (for example: 7XEEX17D99-3X49X08 1) found in the product open source documentation.

