

Smart Call Home Quick Start Configuration Guide

Smart Call Home offers proactive diagnostics and real-time alerts on select Cisco devices, which provides higher network availability and increased operational efficiency. Smart Call is a secure connected service of Cisco SMARTnet for the Cisco 7600.

This document provides information to configure and register a Cisco 7600 for Smart Call Home using four options. It is assumed that the device has the necessary DNS configuration (ip domain-name and ip name-server for DNS look-ups or ip host for static entries) in order to resolve host-names that may appear in destination addresses.

1. [HTTPS transport from the Cisco 7600 to Cisco](#)
2. [Email transport from the Cisco 7600 to Cisco](#)
3. [HTTP from the Cisco 7600 to a Transport Gateway \(TG\) - HTTPS transport to Cisco](#)
4. [Email from the Cisco 7600 to a Transport Gateway \(TG\) - HTTPS transport to Cisco](#)

Note: For security reasons, Cisco recommends customers make use of one of the HTTPS transport options, due to the additional payload encryption that HTTPS offers. The [Transport Gateway software](#) is downloadable from Cisco and is available for customers that require an aggregation point or a proxy for connection to the internet.

Requirements for Smart Call Home:

- IOS version 12.2(33)SRC or later is required to support Call Home.
- A CCO ID associated with an appropriate Cisco SMARTnet Service contract for your company.
- Cisco SMARTnet Service for the device to be registered.
- An image with cryptographic support is required to encrypt messages on the Cisco 7600 for HTTPS transport.

Resources for Smart Call Home:

Different resources are available for Smart Call Home at www.cisco.com/go/smartcall.

The complete Call-Home configuration guide is available at <http://www.cisco.com/en/US/docs/routers/7600/ios/12.2SR/configuration/guide/callhome.html>.

The Smart Call-Home User Guide is available at http://www.cisco.com/en/US/docs/switches/lan/smart_call_home/user_guides/Book.html.

The Smart Call Home server certificate for HTTPS is available at - http://www.cisco.com/en/US/docs/switches/lan/smart_call_home/user_guides/SCH_Ch6.pdf#G1039385.

Call Home Configuration - HTTPS to Cisco

The following is a sample configuration showing the minimum steps required to configure Call Home on a Cisco 7600 to communicate securely with the Smart Call Home System using HTTPS and a command to start the registration process. All commands are in blue.

1. **Enable Call Home** - In global configuration mode enter the service call-home command to activate the call-home feature and enter the call-home configuration command to enter call-home configuration mode.

```
7600#configure terminal
7600 (config)#service call-home
7600 (config)#call-home
```

2. **Configure the mandatory contact email address -**

```
7600 (cfg-call-home)#contact-email-addr username@domain-name
```

3. **Activate the default CiscoTAC-1 Profile and set the transport option to HTTP-**

```
7600 (cfg-call-home)#profile CiscoTAC-1
7600 (cfg-call-home-profile)#active
7600 (cfg-call-home-profile)#destination transport-method http
```

4. **Install a security certificate** - Copy the Cisco server certificate from http://www.cisco.com/en/US/docs/switches/lan/smart_call_home/user_guides/SCH_Ch6.pdf#G1039385. The security certificate can be copied from the previous URL, which is from the Smart Call Home User's Guide. Configure a trust-point and prepare to enroll the certificate via the terminal using copy and paste when prompted.

```
7600 (config)#crypto pki trustpoint cisco
7600 (ca-trustpoint)#enroll terminal
7600 (ca-trustpoint)#revocation-check crl none
7600 (ca-trustpoint)#exit
7600 (config)#crypto pki authenticate cisco

Enter the base 64 encoded CA certificate.
End with a blank line or the word "quit" on a line by itself

[paste the certificate here and accept it]

% Do you accept this certificate? [yes/no]: yes
Trustpoint CA certificate accepted.
% Certificate successfully imported
```

5. **Exit and Save the configuration -**

```
7600 (config)#end
7600#copy running-config startup-config
```

6. **Send a Call Home Inventory message to start the registration process -**

```
7600#call-home send alert-group inventory profile CiscoTAC-1
Sending inventory info call-home message ...
Please wait. This may take some time ...
```

7. **Receive an email from Cisco and follow the link to complete registration for Smart Call home -**

Call Home Configuration - Email to Cisco

The following is a sample configuration showing the minimum steps required to configure Call Home on a Cisco 7600 to communicate using email with the Smart Call Home System and a command to start the registration process. All commands are in blue.

1. **Enable Call Home** - In global configuration mode enter the service call-home command to activate the call-home feature and enter the call-home configuration command to enter call-home configuration mode.

```
7600#configure terminal
7600 (config)#service call-home
7600 (config)#call-home
```

2. **Configure the mandatory contact email address** -

```
7600 (cfg-call-home)#contact-email-addr username@domain-name
```

3. **Configure the mandatory email server information** - The `mail-server` address is an IP address or domain-name of a SMTP server that Call Home will send email messages to. If more than one `mail-server` address is configured for redundancy the `mail-server priority` is used to determine which server is the active primary server. Call Home will send messages to the active server with the lowest priority number.

```
7600 (cfg-call-home)#mail-server <address> priority <server_priority_number>
```

4. **Activate the default CiscoTAC-1 Profile and set the transport option to Email** -

```
7600 (cfg-call-home)#profile CiscoTAC-1
7600 (cfg-call-home-profile)#active
7600 (cfg-call-home-profile)#destination transport-method email
```

5. **Exit and Save the configuration** -

```
7600 (cfg-call-home-profile)#end
7600#copy running-config startup-config
```

6. **Send a Call Home Inventory message to start the registration process** -

```
7600#call-home send alert-group inventory profile CiscoTAC-1
Sending inventory info call-home message ...
Please wait. This may take some time ...
```

7. **Receive an email from Cisco and follow the link to complete registration for Smart Call home** -

Call Home Configuration - HTTP to Transport Gateway and HTTPS to Cisco

The following is a sample configuration showing the minimum steps required to configure Call Home on a Cisco 7600 to use HTTP to send to a Transport Gateway which will use HTTPS to communicate with the Smart Call Home System, and a command to start the registration process. This assumes that the [Transport Gateway software](#) has been installed, configured and registered with Smart Call. All commands are in blue.

1. **Enable Call Home** - In global configuration mode enter the service call-home command to activate the call-home feature and enter the call-home configuration command to enter call-home configuration mode.

```
7600#configure terminal
7600 (config)#service call-home
7600 (config)#call-home
```

2. **Configure the mandatory contact email address** -

```
7600 (cfg-call-home)#contact-email-addr username@domain-name
```

3. **De-activate the default CiscoTAC-1 Profile if it is active** -

```
7600 (cfg-call-home)#profile CiscoTAC-1
7600 (cfg-call-home-profile)#no active
```

4. **Configure a user profile** - The profile's alert-group subscriptions will be similar to the default CiscoTAC-1 profile with the destination HTTP transport-method and with a destination HTTP address provided by the Transport Gateway (Refer to [Configure the HTTP Server](#) section). Some versions of the IOS have a problem parsing the URL if it contains an IP address followed by a port number (refer to bug CSCsv52025). The work-around is to replace the IP address with the domain/host name of the TG or use port 80 and remove the port number from the URL.

```
7600 (cfg-call-home-profile)#profile Your_profile_name
7600 (cfg-call-home-profile)#active
7600 (cfg-call-home-profile)#destination transport-method http
7600 (cfg-call-home-profile)#destination address http http://url_from_TG
7600 (cfg-call-home-profile)#subscribe-to-alert-group diagnostic severity minor
7600 (cfg-call-home-profile)#subscribe-to-alert-group environment severity minor
7600 (cfg-call-home-profile)#subscribe-to-alert-group syslog severity major pattern ".*"
7600 (cfg-call-home-profile)#subscribe-to-alert-group configuration periodic monthly 23 15:00
7600 (cfg-call-home-profile)#subscribe-to-alert-group inventory periodic monthly 23 15:00
```

5. **Exit and Save the configuration** -

```
7600 (cfg-call-home-profile)#end
7600#copy running-config startup-config
```

6. **Send a Call Home Inventory message to start the registration process** -

```
7600#call-home send alert-group inventory profile Your_profile_name
Sending inventory info call-home message ...
Please wait. This may take some time ...
```

7. **Receive the email from Cisco and follow the link to complete registration for Smart Call home.**

Call Home Configuration - Email to Transport Gateway and HTTPS to Cisco

The following is a sample configuration showing the minimum steps required to configure Call Home on a Cisco 7600 to send Email to a Transport Gateway which will use HTTPS to communicate with the Smart Call Home System, and a command to start the registration process. This assumes that the [Transport Gateway software](#) has been installed, configured and registered with Smart Call Home. All commands are in blue.

1. **Enable Call Home** - In global configuration mode enter the service call-home command to activate the call-home feature and enter the call-home configuration command to enter call-home configuration mode.

```
7600#configure terminal
7600 (config)#service call-home
7600 (config)#call-home
```

2. **Configure the mandatory contact email address** -

```
7600 (cfg-call-home)#contact-email-addr username@domain-name
```

3. **Configure the mandatory email server information** - The [mail-server](#) address is an IP address or domain-name of a SMTP server that Call Home will send email messages to.

```
7600 (cfg-call-home)#mail-server <address> priority <server_priority_number>
```

4. **De-activate the default CiscoTAC-1 Profile if it is active** -

```
7600 (cfg-call-home)#profile CiscoTAC-1
7600 (cfg-call-home-profile)#no active
```

5. **Configure a user profile** - The profile's alert-group subscriptions will be similar to the default CiscoTAC-1 profile with the destination email transport-method and with a destination email address which is for the email account used by the Transport Gateway.

```
7600 (cfg-call-home-profile)#profile Your_profile_name
7600 (cfg-call-home-profile)#active
7600 (cfg-call-home-profile)#destination transport-method email
7600 (cfg-call-home-profile)#destination address email account_for_TG@yourCompany.com
7600 (cfg-call-home-profile)#subscribe-to-alert-group diagnostic severity minor
7600 (cfg-call-home-profile)#subscribe-to-alert-group environment severity minor
7600 (cfg-call-home-profile)#subscribe-to-alert-group syslog severity major pattern ".*"
7600 (cfg-call-home-profile)#subscribe-to-alert-group configuration periodic monthly 23 15:00
7600 (cfg-call-home-profile)#subscribe-to-alert-group inventory periodic monthly 23 15:00
```

6. **Exit and Save the configuration** -

```
7600 (cfg-call-home-profile)#end
7600#copy running-config startup-config
```

7. **Send a Call Home Inventory message to start the registration process** -

```
7600#call-home send alert-group inventory profile Your_profile_name
Sending inventory info call-home message ...
Please wait. This may take some time ...
```

8. **Receive the email from Cisco and follow the link to complete registration for Smart Call home.**

Downloading Cisco Transport Gateway Software

To download Cisco Transport Gateway software, go to the [Download Software](#) web page. On that page the Related Information section on the right lists the different OS versions (Linux, Solaris, Windows) of Transport Gateway software. Find the correct OS version of Transport Gateway software in the list and then click either **Download Now** or **Add to cart**.

After you have downloaded the correct OS version of Transport Gateway software, then refer to the [Transport Gateway Installation/Configuration/Registration sections of the Smart Call Home Users' Guide](#) for information on how to install the downloaded code then configure and register the Transport Gateway.