



First Hop Security

This chapter contains the following sections:

- [About First Hop Security, on page 1](#)
- [ACI FHS Deployment, on page 2](#)
- [Guidelines and Limitations, on page 2](#)
- [Configuring FHS Using the APIC GUI, on page 3](#)
- [Configuring FHS Using the NX-OS CLI, on page 3](#)
- [FHS Switch iBASH Commands, on page 9](#)
- [Configuring FHS in APIC Using REST API, on page 14](#)

About First Hop Security

First-Hop Security (FHS) features enable a better IPv4 and IPv6 link security and management over the layer 2 links. In a service provider environment, these features closely control address assignment and derived operations, such as Duplicate Address Detection (DAD) and Address Resolution (AR).

The following supported FHS features secure the protocols and help build a secure endpoint database on the fabric leaf switches, that are used to mitigate security threats such as MIM attacks and IP thefts:

- ARP Inspection—allows a network administrator to intercept, log, and discard ARP packets with invalid MAC address to IP address bindings.
- ND Inspection—learns and secures bindings for stateless autoconfiguration addresses in Layer 2 neighbor tables.
- DHCP Inspection—validates DHCP messages received from untrusted sources and filters out invalid messages.
- RA Guard—allows the network administrator to block or reject unwanted or rogue router advertisement (RA) guard messages.
- IPv4 and IPv6 Source Guard—blocks any data traffic from an unknown source.
- Trust Control—a trusted source is a device that is under your administrative control. These devices include the switches, routers, and servers in the Fabric. Any device beyond the firewall or outside the network is an untrusted source. Generally, host ports are treated as untrusted sources.

FHS features provide the following security measures:

- **Role Enforcement**—Prevents untrusted hosts from sending messages that are out the scope of their role.
- **Binding Enforcement**—Prevents address theft.
- **DoS Attack Mitigations**—Prevents malicious end-points to grow the end-point database to the point where the database could stop providing operation services.
- **Proxy Services**—Provides some proxy-services to increase the efficiency of address resolution.

FHS features are enabled on a per tenant bridge domain (BD) basis. As the bridge domain, may be deployed on a single or across multiple leaf switches, the FHS threat control and mitigation mechanisms cater to a single switch and multiple switch scenarios.

ACI FHS Deployment

Most FHS features are configured in a two-step fashion: firstly you define a policy which describes the behavior of the feature, secondly you apply this policy to a "domain" (being the Tenant Bridge Domain or the Tenant Endpoint Group). Different policies that define different behaviors can be applied to different intersecting domains. The decision to use a specific policy is taken by the most specific domain to which the policy is applied.

The policy options can be defined from the Cisco APIC GUI found under the `Tenant_name>Networking>Protocol Policies>First Hop Security tab`.

Guidelines and Limitations

Follow these guidelines and limitations:

- Starting with release 3.1(1), FHS is supported with virtual Endpoints (AVS only).
- FHS is supported with both VLAN and VXLAN encapsulation.
- Any secured endpoint entry in the FHS Binding Table Database in **DOWN** state will get cleared after **18 Hours** of timeout. The entry moves to **DOWN** state when the front panel port where the entry is learned is link down. During this window of **18 Hours**, if the endpoint is moved to a different location and is seen on a different port, the entry will be gracefully moved out of **DOWN** state to **REACHABLE/STALE** as long as the endpoint is reachable from the other port it is moved from.
- When IP Source Guard is enabled, the IPv6 traffic that is sourced using IPv6 Link Local address as IP source address is not subject to the IP Source Guard enforcement (i.e. Enforcement of Source Mac <=> Source IP Bindings secured by IP Inspect Feature). This traffic is permitted by default irrespective of binding check failures.
- FHS is not supported on L3Out interfaces.
- FHS is not supported N9K-M12PQ based TORs.
- FHS in ACI Multi-Site is a site local capability therefore it can only be enabled in a site from the APIC cluster. Also, FHS in ACI Multi-Site only works when the BD and EPG is site local and not stretched across sites. FHS security cannot be enabled for stretched BD or EPGs.
- FHS is not supported on a Layer 2 only bridge domain.

- Enabling FHS feature can disrupt traffic for 50 seconds because the EP in the BD are flushed and EP Learning in the BD is disabled for 50 seconds.

Configuring FHS Using the APIC GUI

Before you begin

- The tenant and Bridge Domain configured.

-
- Step 1** On the menu bar, click **Tenants > Tenant_name**. In the **Navigation** pane, click **Policies > Protocol > First Hop Security**. Right click on **First Hop Security** to open **Create Feature Policy** and perform the following actions:
- In the **Name** field, enter a name for the First Hop Security policy.
 - Verify that the **IP Inspection**, **Source Guard**, and **Router Advertisement** fields are enabled and click **Submit**.
- Step 2** In the **Navigation** pane, expand **First Hop Security** and right click on **Trust Control Policies** to open **Create Trust Control Policy** and perform the following actions:
- In the **Name** field, enter a name for the Trust Control policy.
 - Select the desired features to be allowed on the policy and click **Submit**.
- Step 3** (Optional) To apply the Trust Control policy to an EPG, in the **Navigation** pane, expand **Application Profiles > Application Profile_name > Application EPGs** and click on **Application EPG_name** and perform the following actions:
- In the **Work** pane, click on the **General** tab.
 - Click on the down-arrow for **FHS Trust Control Policy** and select the policy you previously created and click **Submit**.
- Step 4** In the **Navigation** pane, expand **Bridge Domains > Bridge Domain_name** and click on the **Advanced/Troubleshooting** tab and perform the following action:
- In the **First Hop Security Policy** field, select the policy you just created and click **Submit**. This completes FHS configuration.

Configuring FHS Using the NX-OS CLI

Before you begin

- The tenant and Bridge Domain configured.

-
- Step 1** **configure**

Enters configuration mode.

Example:

```
apic1# configure
```

- Step 2** Configure FHS policy.

Example:

```

apic1(config)# tenant coke
apic1(config-tenant)# first-hop-security
apic1(config-tenant-fhs)# security-policy pol1
apic1(config-tenant-fhs-secpol)#
apic1(config-tenant-fhs-secpol)# ip-inspection-admin-status enabled-both
apic1(config-tenant-fhs-secpol)# source-guard-admin-status enabled-both
apic1(config-tenant-fhs-secpol)# router-advertisement-guard-admin-status enabled
apic1(config-tenant-fhs-secpol)# router-advertisement-guard
apic1(config-tenant-fhs-raguard)#
apic1(config-tenant-fhs-raguard)# managed-config-check
apic1(config-tenant-fhs-raguard)# managed-config-flag
apic1(config-tenant-fhs-raguard)# other-config-check
apic1(config-tenant-fhs-raguard)# other-config-flag
apic1(config-tenant-fhs-raguard)# maximum-router-preference low
apic1(config-tenant-fhs-raguard)# minimum-hop-limit 10
apic1(config-tenant-fhs-raguard)# maximum-hop-limit 100
apic1(config-tenant-fhs-raguard)# exit
apic1(config-tenant-fhs-secpol)# exit
apic1(config-tenant-fhs)# trust-control tcpol1
picl(config-tenant-fhs-trustctrl)# arp
apic1(config-tenant-fhs-trustctrl)# dhcipv4-server
apic1(config-tenant-fhs-trustctrl)# dhcipv6-server
apic1(config-tenant-fhs-trustctrl)# ipv6-router
apic1(config-tenant-fhs-trustctrl)# router-advertisement
apic1(config-tenant-fhs-trustctrl)# neighbor-discovery
apic1(config-tenant-fhs-trustctrl)# exit
apic1(config-tenant-fhs)# exit
apic1(config-tenant)# bridge-domain bd1
apic1(config-tenant-bd)# first-hop-security security-policy pol1
apic1(config-tenant-bd)# exit
apic1(config-tenant)# application ap1
apic1(config-tenant-app)# epg epg1
apic1(config-tenant-app-epg)# first-hop-security trust-control tcpol1

```

Step 3 Show FHS configuration example:**Example:**

```

leaf4# show fhs bt all

Legend:
    TR      : trusted-access          UNRES : unresolved          Age   : Age since
    creation
    UNTR    : untrusted-access       UNDTR : undetermined-trust  CRTNG : creating
    UNKNW   : unknown               TENTV : tentative           INV   : invalid
    NDP     : Neighbor Discovery Protocol STA   : static-authenticated REACH : reachable
    INCMP   : incomplete            VERIFY : verify             INTF  : Interface
    TimeLeft : Remaining time since last refresh LM    : lla-mac-match DHCP  :
    dhcp-assigned

    EPG-Mode:
        U : unknown      M : mac       V : vlan      I : ip
        BD-VNID        BD-Vlan       BD-Name
        15630220        3           t0:bd200

-----
| Origin | IP          | MAC          | INTF | EPG(sclass) (mode) | Trust-lvl | State |
-----
```

Age		TimeLeft						
ARP	192.0.200.12	D0:72:DC:A0:3D:4F	eth1/1	epg300(49154) (V)	LM,TR	STALE		
00:04:49	18:08:13							
ARP	172.29.205.232	D0:72:DC:A0:3D:4F	eth1/1	epg300(49154) (V)	LM,TR	STALE		
00:03:55	18:08:21							
ARP	192.0.200.21	D0:72:DC:A0:3D:4F	eth1/1	epg300(49154) (V)	LM,TR	REACH		
00:03:36	00:00:02							
LOCAL	192.0.200.1	00:22:BD:F8:19:FF	vlan3	LOCAL(16387) (I)	STA	REACH		
04:49:41	N/A							
LOCAL	fe80::200	00:22:BD:F8:19:FF	vlan3	LOCAL(16387) (I)	STA	REACH		
04:49:40	N/A							
LOCAL	2001:0:0:200::1	00:22:BD:F8:19:FF	vlan3	LOCAL(16387) (I)	STA	REACH		
04:49:39	N/A							

The trust levels are:

- **TR**— Trusted. Displayed when the endpoint is learned from an EPG where the trust configuration is enabled.
- **UNTR**— Untrusted. Displayed when the endpoint is learned from an EPG where the trust configuration is not enabled.
- **UNDTR**— Undetermined. Displayed in the case of a DHCP relay topology where the DHCP server bridge domain (BD) is on a remote leaf and the DHCP clients are on a local leaf. In this situation, the local leaf will not know whether the DHCP server BD has trust DHCP enabled.

Step 4 Show violations with the different types and reasons example:

Example:

```
leaf4# show fhs violations all

Violation-Type:
    POL : policy      THR : address-theft-remote
    ROLE : role        TH : address-theft
    INT  : internal

Violation-Reason:
    IP-MAC-TH : ip-mac-theft          OCFG_CHK : ra-other-cfg-check-fail   ANC-COL
    : anchor-collision                : internal-error                    TRUST-CHK
    PRF-LVL-CHK : ra-rtr-pref-level-check-fail  INT-ERR : internal-error
    : trust-check-fail               ST-EP-COL : static-ep-collision     LCL-EP-COL
    SRV-ROL-CHK : srv-role-check-fail  MAC-LIM  : ep-limit-reached       MCFG-CHK
    : local-ep-collision            : mac-theft                      : ra-managed-cfg-check-fail
    : rtr-role-check-fail           : ip-theft                      HOP-LMT-CHK : ra-hoplimit-check-fail  MOV-COL : competing-move-collision RTR-ROL-CHK
    IP-TH : ip-theft

EPG-Mode:
    U : unknown      M : mac      V : vlan      I : ip

BD-VNID          BD-Vlan          BD-Name
15630220         3              t0:bd200

-----| Type | Last-Reason | Proto | IP                  | MAC                         | Port | EPG(sclass) (mode) | Count |
-----| THR  | IP-TH       | ARP   | 192.0.200.21 | D0:72:DC:A0:3D:4F | tunnel15 | epg300(49154) (V) | 21  |

-----Table Count: 1
```

Step 5

Show FHS configuration:

Example:

```
swtb23-ifc1# show tenant t0 bridge-domain bd200 first-hop-security binding-table
```

Pod/Node State	Type	Family	IP Address	MAC Address	Interface	Level
-----	-----	-----	-----	-----	-----	-----
1/102 reach	local	ipv4	192.0.200.1	00:22:BD:F8:19:FF	vlan3	static-
able 1/102 reach	local	ipv6	fe80::200	00:22:BD:F8:19:FF	vlan3	static-
able 1/102 reach	local	ipv6	2001:0:0:200::1	00:22:BD:F8:19:FF	vlan3	static-
able 1/101 stale	arp	ipv4	192.0.200.23	D0:72:DC:A0:02:61	eth1/2	lla-mac-match
1/101 reach	local	ipv4	192.0.200.1	00:22:BD:F8:19:FF	vlan3	static-
able 1/101 reach	nd	ipv6	fe80::d272:dcff:fea0:261	D0:72:DC:A0:02:61	eth1/2	lla-mac-match
able 1/101 stale	nd	ipv6	2001:0:0:200::20	D0:72:DC:A0:02:61	eth1/2	lla-mac-match
1/101 stale	nd	ipv6	2001::200:d272:dcff:fea0:261	D0:72:DC:A0:02:61	eth1/2	lla-mac-match
1/101 reach	local	ipv6	fe80::200	00:22:BD:F8:19:FF	vlan3	static-
able 1/101 reach	local	ipv6	2001:0:0:200::1	00:22:BD:F8:19:FF	vlan3	static-
able 1/103 reach	local	ipv4	192.0.200.1	00:22:BD:F8:19:FF	vlan4	static-
able 1/103 reach	local	ipv6	fe80::200	00:22:BD:F8:19:FF	vlan4	static-
able 1/103 reach	local	ipv6	2001:0:0:200::1	00:22:BD:F8:19:FF	vlan4	static-
able 1/104 stale	arp	ipv4	192.0.200.10	F8:72:EA:AD:C4:7C	eth1/1	lla-mac-match

```

1/104    arp     ipv4      172.29.207.222          D0:72:DC:A0:3D:4C  eth1/1      ,trusted-access
stale

1/104    local   ipv4      192.0.200.1           00:22:BD:F8:19:FF  vlan4      ,trusted-access
reach

able
1/104    nd      ipv6      fe80::fa72:eaff:fead  F8:72:EA:AD:C4:7C  eth1/1      lla-mac-match
stale

1/104    nd      ipv6      2001:0:0:200::10        F8:72:EA:AD:C4:7C  eth1/1      ,trusted-access
stale

1/104    local   ipv6      fe80::200             00:22:BD:F8:19:FF  vlan4      ,trusted-access
reach

able
1/104    local   ipv6      2001:0:0:200::1          00:22:BD:F8:19:FF  vlan4      static-
reach

able
1/104    local   ipv6      2001:0:0:200::1          00:22:BD:F8:19:FF  vlan4      authenticated
able

```

Pod/Node	Type	IP Address	Creation TS	Last Refresh TS
Lease Period				
<hr/>				
1/102	local	192.0.200.1	2017-07-20T04:22:38.000+00:00	2017-07-20T04:22:38.000+00:00
1/102	local	fe80::200	2017-07-20T04:22:56.000+00:00	2017-07-20T04:22:56.000+00:00
1/102	local	2001:0:0:200::1	2017-07-20T04:22:57.000+00:00	2017-07-20T04:22:57.000+00:00
1/101	arp	192.0.200.23	2017-07-27T10:55:20.000+00:00	2017-07-27T16:07:24.000+00:00
1/101	local	192.0.200.1	2017-07-27T10:48:09.000+00:00	2017-07-27T10:48:09.000+00:00
1/101	nd	fe80::d272:dcff:fea0	2017-07-27T10:52:16.000+00:00	2017-07-27T16:04:29.000+00:00
		:261		
1/101	nd	2001:0:0:200::20	2017-07-27T10:57:32.000+00:00	2017-07-27T16:07:24.000+00:00
1/101	nd	2001::200:d272:dcff:	2017-07-27T11:21:45.000+00:00	2017-07-27T16:07:24.000+00:00
		fea0:261		
1/101	local	fe80::200	2017-07-27T10:48:10.000+00:00	2017-07-27T10:48:10.000+00:00
1/101	local	2001:0:0:200::1	2017-07-27T10:48:11.000+00:00	2017-07-27T10:48:11.000+00:00
1/103	local	192.0.200.1	2017-07-26T22:03:56.000+00:00	2017-07-26T22:03:56.000+00:00
1/103	local	fe80::200	2017-07-26T22:03:57.000+00:00	2017-07-26T22:03:57.000+00:00
1/103	local	2001:0:0:200::1	2017-07-26T22:03:58.000+00:00	2017-07-26T22:03:58.000+00:00
1/104	arp	192.0.200.10	2017-07-27T11:21:13.000+00:00	2017-07-27T16:05:48.000+00:00
1/104	arp	172.29.207.222	2017-07-27T11:54:48.000+00:00	2017-07-27T16:06:38.000+00:00
1/104	local	192.0.200.1	2017-07-27T10:49:13.000+00:00	2017-07-27T10:49:13.000+00:00
1/104	nd	fe80::fa72:eaff:fead	2017-07-27T11:21:13.000+00:00	2017-07-27T16:06:43.000+00:00
		:c47c		
1/104	nd	2001:0:0:200::10	2017-07-27T11:21:13.000+00:00	2017-07-27T16:06:19.000+00:00
1/104	local	fe80::200	2017-07-27T10:49:14.000+00:00	2017-07-27T10:49:14.000+00:00
1/104	local	2001:0:0:200::1	2017-07-27T10:49:15.000+00:00	2017-07-27T10:49:15.000+00:00

swtb23-ifc1#

```

swtb23-ifc1# show tenant t0 bridge-domain bd200 first-hop-security statistics arp
Pod/Node      : 1/101
Request Received : 4
Request Switched : 2
Request Dropped : 2
Reply Received : 257

```

Configuring FHS Using the NX-OS CLI

```

Reply Switched      : 257
Reply Dropped      : 0

Pod/Node           : 1/104
Request Received   : 6
Request Switched   : 6
Request Dropped    : 0
Reply Received     : 954
Reply Switched     : 954
Reply Dropped      : 0

swtb23-ifc1# show tenant t0 bridge-domain bd200 first-hop-security statistics dhcpv4
Pod/Node           : 1/102
Discovery Received : 5
Discovery Switched : 5
Discovery Dropped  : 0
Offer Received     : 0
Offer Switched     : 0
Offer Dropped      : 0
Request Received   : 0
Request Switched   : 0
Request Dropped    : 0
Ack Received       : 0
Ack Switched       : 0
Ack Dropped        : 0
Nack Received      : 0
Nack Switched      : 0
Nack Dropped       : 0
Decline Received   : 0
Decline Switched   : 0
Decline Dropped    : 0
Release Received   : 0
Release Switched   : 0
Release Dropped    : 0
Information Received : 0
Information Switched : 0
Information Dropped : 0
Lease Query Received : 0
Lease Query Switched : 0
Lease Query Dropped : 0
Lease Active Received : 0
Lease Active Switched : 0
Lease Active Dropped : 0
Lease Unassignment Received : 0
Lease Unassignment Switched : 0
Lease Unassignment Dropped : 0
Lease Unknown Received : 0
Lease Unknown Switched : 0
Lease Unknown Dropped : 0

swtb23-ifc1# show tenant t0 bridge-domain bd200 first-hop-security statistics neighbor-discovery
Pod/Node           : 1/101
Neighbor Solicitation Received : 125
Neighbor Solicitation Switched : 121
Neighbor Solicitation Dropped  : 4
Neighbor Advertisement Received : 519
Neighbor Advertisement Switched : 519
Neighbor Advertisement Drop    : 0
Router Solicitation Received   : 4
Router Solicitation Switched   : 4
Router Solicitation Dropped    : 0
Router Adv Received          : 0
Router Adv Switched          : 0

```

```

Router Adv Dropped          : 0
Redirect Received          : 0
Redirect Switched          : 0
Redirect Dropped           : 0

Pod/Node                   : 1/104
Neighbor Solicitation Received : 123
Neighbor Solicitation Switched : 47
Neighbor Solicitation Dropped : 76
Neighbor Advertisement Received : 252
Neighbor Advertisement Switched : 228
Neighbor Advertisement Drop   : 24
Router Solicitation Received : 0
Router Solicitation Switched : 0
Router Solicitation Dropped  : 0
Router Adv Received         : 53
Router Adv Switched         : 6
Router Adv Dropped          : 47
Redirect Received           : 0
Redirect Switched          : 0
Redirect Dropped            : 0

```

FHS Switch iBASH Commands

- Step 1** Show command to display the FHS feature configuration on the BD and the Trust control policy configuration on the EPG:

Example:

```

leaf4# show fhs features all

BD-VNID      BD-Vlan      BD-Name
15630220     4           t0:bd200
Feature Policy:
  Feature    Family    Protocol  Operational-State  Options
  ipinspect  IPV4      ARP        UP                stalelifetime: 180s
  ipinspect  IPV4      DHCP       UP                -
  ipinspect  IPV4      LOCAL      UP                -
  ipinspect  IPV4      STATIC     UP                -
  ipinspect  IPV6      ND         UP                stalelifetime: 180s
  ipinspect  IPV6      DHCP       UP                -
  ipinspect  IPV6      LOCAL      UP                -
  ipinspect  IPV6      STATIC     UP                -
  raguard    IPV6      -          UP                ManagedCfgFlag: on
                                         OtherCfgFlag: on
                                         maxHopLimit: 15
                                         minHopLimit: 3
                                         routerPref: medium
-----
Trust Policy:
Epg-id      Epg-type      Epg-name
49154       Ckt-Vlan      epg300
  Trust-Attribute  Operational-State
  PROTO-ARP       UP
  PROTO-ND        UP
  DHCPV4-SERVER   UP
  DHCPV6-SERVER   UP
  ROUTER          UP

```

Step 2 Show commands to display the FHS secured endpoint database:

Example:

```

leaf1# show fhs bt
all      data      dhcipv4    local      static
arp      detailed  dhcipv6    nd        summary

leaf1# show fhs bt all

Legend:
DHCP     : dhcp-assigned                      TR      : trusted-access          UNRES   : unresolved
Age       : Age since creation                 CRTNG   : creating              TENTV   : tentative
VERIFY    : verify                            UNDTR   : undetermined-trust      INV     : invalid
NDP      : Neighbor Discovery Protocol        STA     : static-authenticated    REACH   : reachable
LM       : lla-mac-match                      UNKNW   : unknown               INTF    : Interface
TimeLeft : Remaining time since last refresh  INCMP   : incomplete            UNTR    :
untrusted-access

EPG-Mode:
U : unknown   M : mac      V : vlan     I : ip

BD-VNID           BD-Vlan           BD-Name
15630220          3                t0:bd200

-----| Origin | IP                                | MAC                         | INTF | EPG(sclass) (mode) | Trust-lvl |
-----| State  | Age      | TimeLeft |                               |       |                         |           |
-----| ARP    | 192.0.200.23          | D0:72:DC:A0:02:61 | eth1/2 | epg200(32770) (V) | LM,UNTR |
-----| STALE  | 00:07:47 | 00:01:33 |                               |       |                         |           |
-----| LOCAL  | 192.0.200.1           | 00:22:BD:F8:19:FF | vlan3  | LOCAL(16387) (I) | STA    |
-----| REACH  | 00:14:58 | N/A      |                               |       |                         |           |
-----| NDP    | fe80::d272:dcff:fea0:261 | D0:72:DC:A0:02:61 | eth1/2 | epg200(32770) (V) | LM,UNTR |
-----| STALE  | 00:10:51 | 00:00:47 |                               |       |                         |           |
-----| NDP    | 2001:0:0:200::20        | D0:72:DC:A0:02:61 | eth1/2 | epg200(32770) (V) | LM,UNTR |
-----| STALE  | 00:05:35 | 00:00:42 |                               |       |                         |           |
-----| LOCAL  | fe80::200             | 00:22:BD:F8:19:FF | vlan3  | LOCAL(16387) (I) | STA    |
-----| REACH  | 00:14:58 | N/A      |                               |       |                         |           |
-----| LOCAL  | 2001:0:0:200::1         | 00:22:BD:F8:19:FF | vlan3  | LOCAL(16387) (I) | STA    |
-----| REACH  | 00:14:57 | N/A      |                               |       |                         |           |

```

```
leaf1# show fhs bt summary all
```

FHS Binding Table Summary

BD-Vlan: 3	BD-Name: t0:bd200	
Total number of ARP entries	: 1	
Total number of DHCPv4 entries	: 0	
Total number of ND entries	: 2	
Total number of DHCPv6 entries	: 0	
Total number of Data entries	: 0	
Total number of Static entries	: 0	
Total number of Local entries	: 3	
Total number of entries	: 6	

Total entries across all BDs matching given filters

```
Total number of ARP entries      : 1
Total number of DHCPv4 entries   : 0
Total number of ND entries       : 2
Total number of DHCPv6 entries   : 0
Total number of Data entries     : 0
Total number of Static entries   : 0
Total number of Local entries    : 3
Total number of entries          : 6
```

Step 3 Show command to display FHS endpoint violations:

Example:

```
leaf1# show fhs violations all

Violation-Type:
  POL : policy      THR : address-theft-remote
  ROLE : role        TH : address-theft
  INT  : internal

Violation-Reason:
  IP-MAC-TH : ip-mac-theft           OCFG_CHK : ra-other-cfg-check-fail      ANC-COL
  : anchor-collision
  PRF-LVL-CHK : ra-rtr-pref-level-check-fail   INT-ERR : internal-error            TRUST-CHK
  : trust-check-fail
  SRV-ROL-CHK : srv-role-check-fail         ST-EP-COL : static-ep-collision      LCL-EP-COL
  : local-ep-collision
  MAC-TH : mac-theft                   EP-LIM : ep-limit-reached            MCFG-CHK
  : ra-managed-cfg-check-fail
  HOP-LMT-CHK : ra-hoplimit-check-fail      MOV-COL : competing-move-collision   RTR-ROL-CHK
  : rtr-role-check-fail
  IP-TH : ip-theft

Trust-Level:
  TR : trusted-access    UNTR : untrusted-access      UNDTR : undetermined-trust
  INV : invalid           STA : static-authenticated   LM : lla-mac-match
  DHCP : dhcp-assigned

EPG-Mode:
  U : unknown      M : mac      V : vlan      I : ip

BD-VNID          BD-Vlan          BD-Name
15630220         4                t0:bd200

| Type | Last-Reason | Proto | IP                                | MAC                         | Port |
| EPG(sclass) (mode) | Trust-lvl | Count |
```

```
| TH | IP-TH | ND | 2001:0:0:200::20 | D0:72:DC:A0:3D:4F | eth1/1 | epg300(49154) (V)
| LM,UNTR | 2 |          |
| POL | HOP-LMT-CHK | RD | fe80::fa72:eaff:fead:c47c | F8:72:EA:AD:C4:7C | eth1/1 | epg300(49154) (V)
| LM,TR | 2 |          |
```

Table Count: 2

Step 4 Show command to display FHS control packet forwarding counters:

Example:

```
leaf1# show fhs counters
all    arp    dhcpv4  dhcpv6  nd
leaf4# show fhs counters all

BD-VNID          BD-Vlan          BD-Name
15630220         4                t0:bd200
```

Counter Type	Received	Switched	Dropped
Arp Request	6	6	0
Arp Reply	94	94	0
Dhcpv4 Ack	0	0	0
Dhcpv4 Decline	0	0	0
Dhcpv4 Discover	0	0	0
Dhcpv4 Inform	0	0	0
Dhcpv4 Leaseactive	0	0	0
Dhcpv4 Leasequery	0	0	0
Dhcpv4 Leaseunassigned	0	0	0
Dhcpv4 Leaseunknown	0	0	0
Dhcpv4 Nack	0	0	0
Dhcpv4 Offer	0	0	0
Dhcpv4 Release	0	0	0
Dhcpv4 Request	0	0	0
Dhcpv6 Advertise	0	0	0
Dhcpv6 Confirm	0	0	0
Dhcpv6 Decline	0	0	0
Dhcpv6 Informationreq	0	0	0
Dhcpv6 Rebind	0	0	0
Dhcpv6 Reconfigure	0	0	0
Dhcpv6 Relayforw	0	0	0
Dhcpv6 Relayreply	0	0	0
Dhcpv6 Release	0	0	0
Dhcpv6 Renew	0	0	0
Dhcpv6 Reply	0	0	0
Dhcpv6 Request	0	0	0
Dhcpv6 Solicit	0	0	0
Nd Na	18	18	0
Nd Ns	26	22	4
Nd Ra	11	6	5
Nd Redirect	0	0	0
Nd Rs	0	0	0

Step 5 Display FHS secured endpoint database from the NxOS memory:**Example:**

```
leaf1# vsh -c 'show system internal fhs bt'

Binding Table has 7 entries, 4 dynamic

Codes:
L - Local      S - Static      ND - Neighbor Discovery    ARP - Address Resolution Protocol
DH4 - IPv4 DHCP  DH6 - IPv6 DHCP  PKT - Other Packet      API - API created

Preflevel flags (prlvl):
0001: MAC and LLA match   0002: Orig trunk           0004: Orig access
0008: Orig trusted trunk   0010: Orig trusted access  0020: DHCP assigned
0040: Cga authenticated    0080: Cert authenticated   0100: Statically assigned

EPG types:
V - Vlan Based EPG       M - MAC Based EPG        I - IP Based EPG
```

Code	Network Layer Address prlvl Age	Link Layer Address State	Interface Time left	Vlan	Epg
------	--	-------------------------------	--------------------------	------	-----

ARP 172.29.207.222			d0:72:dc:a0:3d:4c	Eth1/1	4
0x40000c002 (V)	0011 29 s	STALE	157 s		
L 192.0.200.1			00:22:bd:f8:19:ff	Vlan4	4
0x400004003 (I)	0100 55 mn	REACHABLE			
ARP 192.0.200.10			f8:72:ea:ad:c4:7c	Eth1/1	4
0x40000c002 (V)	0011 156 s	STALE	30 s		
L 2001:0:0:200::1			00:22:bd:f8:19:ff	Vlan4	4
0x400004003 (I)	0100 55 mn	REACHABLE			
ND 2001:0:0:200::10			f8:72:ea:ad:c4:7c	Eth1/1	4
0x40000c002 (V)	0011 143 s	STALE	47 s		
L fe80::200			00:22:bd:f8:19:ff	Vlan4	4
0x400004003 (I)	0100 55 mn	REACHABLE			
ND fe80::fa72:eaff:fead:c47c			f8:72:ea:ad:c4:7c	Eth1/1	4
0x40000c002 (V)	0011 176 s	STALE	11 s		

Step 6 Display FHS feature configuration from the NX-OS FHS process internal memory:**Example:**

```
leaf4# vsh -c 'show system internal fhs pol'
```

Target	Type	Policy	Feature	Target-Range	Sub-Feature
epg 0x40000c002	EPG	epg 0x40000c002	Trustctrl	vlan 4	Device-Roles: DHCPv4-Server, DHCPv6-Server, Router
vlan 4	VLAN	vlan 4	IP inspect	vlan all	Protocols: ARP ND
vlan 4	VLAN	vlan 4	RA guard	vlan all	Protocols: ARP, DHCPv4, ND, DHCPv6, Min-HL:3, Max-HL:15,
M-Config-flag:Enable,On					O-Config-flag:Enable,On,
Router-Pref:medium					

Step 7 Display FHS secured endpoint database from the NX-OS shared database:**Example:**

```
leaf1# vsh -c 'show system internal fhs sdb bt'
```

Preflevel flags (preflvl):				
0001: MAC and LLA match	0002: Orig trunk	0004: Orig access		
0008: Orig trusted trunk	0010: Orig trusted access	0020: DHCP assigned		
0040: Cga authenticated	0080: Cert authenticated	0100: Statically assigned		
Origin	Zone ID	L3 Address	MAC Address	VLAN ID EPG ID
	If-name	Preflvl State		
-----	-----	-----	-----	-----
ARP 0x4		172.29.207.222	d0:72:dc:a0:3d:4c	4
0x40000c002	Eth1/1	0011 STALE		
L 0x4		192.0.200.1	00:22:bd:f8:19:ff	4
0x400004003	Vlan4	0100 REACHABLE		
ARP 0x4		192.0.200.10	f8:72:ea:ad:c4:7c	4
0x40000c002	Eth1/1	0011 REACHABLE		
L 0x4		2001:0:0:200::1	00:22:bd:f8:19:ff	4
0x400004003	Vlan4	0100 REACHABLE		
ND 0x4		2001:0:0:200::10	f8:72:ea:ad:c4:7c	4
0x40000c002	Eth1/1	0011 STALE		
L 0x80000004		fe80::200	00:22:bd:f8:19:ff	4
0x400004003	Vlan4	0100 REACHABLE		
ND 0x80000004		fe80::fa72:eaff:fead:c47c	f8:72:ea:ad:c4:7c	4
0x40000c002	Eth1/1	0011 STALE		

Step 8 Display FHS feature configurations from the NxOS shared database:**Example:**

Configuring FHS in APIC Using REST API

```
leaf1# vsh -c 'show system internal fhs sdb pol'
Policies:

IP inspect      Vlan 4          Protocols:ARP DHCPv4 ND DHCPv6
RA guard        Vlan 4          Min-HL:3 Max-HL:15 M-Config-Flag:enable,on
O-Config-Flag:enable,on Router-Pref:medium
Trustctrl       Epg 0x40000c002  Vlan:4
                                         Device-Roles:DHCPv4-Server DHCPv6-Server Router
                                         Protocols:ARP ND
```

Step 9 Show command to clear a secured database endpoint entry:

Example:

```
leaf1# vsh -c 'clear system internal fhs bt ipv4 172.29.207.222'
```

Configuring FHS in APIC Using REST API

Before you begin

- The tenant and bridge domain must be configured.
-

Configure the FHS and Trust Control policies.

Example:

```
<polUni>
  <fvTenant name="Coke">
    <fhsBDPol name="bdpol5" ipInspectAdminSt="enabled-ipv6" srcGuardAdminSt="enabled-both"
raGuardAdminSt="enabled" status="">
      <fhsRaGuardPol name="raguard5" managedConfigCheck="true" managedConfigFlag="true"
otherConfigCheck="true" otherConfigFlag="true" maxRouterPref="medium" minHopLimit="3" maxHopLimit="15"
status="" />
    </fhsBDPol>
    <fvBD name="bd3">
      <fvRsBDToFhs tnFhsBDPolName="bdpol5" status="" />
    </fvBD>
  </fvTenant>
</polUni>

<polUni>
  <fvTenant name="Coke">
    <fhsTrustCtrlPol name="trustctrl5" hasDhcpv4Server="true" hasDhcpv6Server="true"
hasIpv6Router="true" trustRa="true" trustArp="true" trustNd="true" />
    <fvAp name="wwwCokecom3">
      <fvAEPg name="test966">
        <fvRsTrustCtrl tnFhsTrustCtrlPolName="trustctrl5" status="" />
      </fvAEPg>
    </fvAp>
  </fvTenant>
</polUni>
```
