



Understanding NDB Fabrics and Switches, Release 4.2.1

Table of Contents

New and changed information	1
Overview	1
Inventory	2
Switches	3
Controllers	6
Connectivity	7
Configuration policies	8
Anomalies	8
History	9
Monitor individual switches	10
Statistics	10
Copyright	14

New and changed information

The following table provides an overview of the significant changes up to this current release. The table does not provide an exhaustive list of all changes or of the new features up to this release.

Release Version	Feature	Description
Nexus Dashboard 4.2.1	Nexus Data Broker integration	Beginning with release 4.2.1, Nexus Dashboard supports a new fabric type dedicated to Data Broker networks. You can also configure and manage SPAN settings for Data Broker switches directly within Nexus Dashboard, which enhances connectivity and monitoring capabilities.

The **Fabrics** page provides a centralized view of Nexus Data Broker (NDB) operations, inventory health, connectivity metrics, configuration, and operational status of the network monitoring infrastructure.

The **Fabrics** page includes the following tabs.

- [Overview](#)
- [Inventory](#)
- [Connectivity](#)
- [Configuration policies](#)
- [Anomalies](#)
- [History](#)

Overview

The **Overview** tab provides a summary of the health and status of the NDB fabric. You can also view the anomaly level, general fabric details (such as software versions and license tier), inventory summaries, and real-time status of input ports, monitoring tools, and packet filters. It also tracks data throughput and recent administrative activity.

Follow these steps to navigate to the **Overview** tab.


1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. Click the **Overview** tab.



Inventory

The **Inventory** tab lists all hardware assets managed within the NDB fabric including switches and controllers. It allows you to monitor hardware resources, view capacity, and verify the operational status of each device in the network.

Follow these steps to navigate to the **Inventory** tab.


1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. In the **Fabrics** page, click the **Inventory** tab.



The **Inventory** tab displays the following tabs.

- **Switches**
- **Controllers**

Switches

Cisco Nexus series devices act as programmable packet brokers within the network monitoring infrastructure in the NDB fabric. These switches aggregate, filter, replicate, and forward copies of production traffic from TAP or SPAN sources to monitoring and security tools. Switches enable scalable TAP and SPAN aggregation, redirect inline traffic, and provide advanced traffic management features such as packet truncation, time stamping, and tag stripping.

The **Switches** table provides the following information.

Field	Description
Name	Specifies the name of the switch.
Anomaly level	Displays the anomaly level of the switch, classified as Critical , Major , or Warning based on operational issues.
IP address	Specifies the IP address of the switch.
Model	Specifies the switch model.
Configuration sync status	Indicates whether the switch configuration is In-Sync or Out of sync .
Serial number	Specifies the serial number of the switch.
Discovery status	Indicates the discovery status of the switch, such as Discovering , Ok , Rediscovering , Unreachable , or Paused . The status is set to Paused when you enable Pause mode (Go to Actions > Pause).
Mode	Specifies whether the switch is in Normal , Migration , or Maintenance mode.
Software version	Specifies the software version running on the switch.

Field	Description
Uptime	Specifies the time the switch has been operational since last reboot.

Configure switches

Follow these steps to configure the switches.

1. Navigate to the **Fabrics** page.

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. In the **Fabrics** page, click the **Inventory** tab.

4. Click the **Switches** tab.

5. Choose a switch.

6. From the **Actions** drop-down list, choose one of the following options.

- **Add switches**—allows you to add switches to the fabric. For more information, see [Add switches](#).
- **Configuration**—allows you to preview generated configurations or deploy configurations to the switch.
- **Discovery**—allows you to trigger discovery processes for the chosen device.
- **Maintenance**—provides options for operational tasks such as reboots or firmware management.
- **Pause/Resume**—temporarily stops or restarts management/monitoring of the switch.
- **Delete switch(s)**—removes the device from the fabric inventory.

The screenshot shows the Cisco Nexus Dashboard interface. The top navigation bar includes the Cisco logo, 'Nexus Dashboard', and user information 'admin'. The main content area is titled 'sri-ndb' and has tabs for Overview, Inventory, Connectivity, Configuration policies, Anomalies, and History. The 'Inventory' tab is active, and the 'Switches' sub-tab is selected. A table lists switches with columns for Name, Anomaly level, IP address, Model, and Config status. One switch is listed: 'N9K-C9336C-FX2-156' with a 'Major' anomaly level and IP address '172.22.30.156'. An 'Actions' dropdown menu is open over the table, showing options: Add switches, Configuration, Discovery, Maintenance, Pause, Resume, and Delete switch(es).

For more information, see [Working with Inventory in Your Nexus Dashboard](#).

Add switches

The **Add switches** option allows you to add switches to the NDB fabric using a discovery mechanism. Ensure that you have the management IP addresses and the necessary administrative credentials (username and password) for the switches you intend to add. You can add multiple switches simultaneously.

Follow these steps to add switches to the NDB fabrics.

1. Navigate to the **Fabrics** page.

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. In the **Fabrics** page, click the **Inventory** tab.

4. Click the **Switches** tab.

5. From the **Actions** drop-down list, choose **Add switches**.

The **Add switches** page displays.

The screenshot shows the 'Add switches' configuration page in the Nexus Dashboard. The page is titled 'Add switches - Fabric: default'. The 'Switch addition mechanism' is set to 'Discover'. Under 'Seed switch details', there is a text input for 'IP*' with a placeholder 'IP' and a hint 'Ex: "2.2.2.20" or "2.2.2.20, 2.2.2.21"'. Below that is a dropdown for 'Authentication / Privacy*' set to 'MD5'. There are text inputs for 'Username*' and 'Password*' with a 'Show' button. A checkbox 'Set as individual device write credential' is present. At the bottom right are 'Close' and 'Discover switches' buttons.



You can also access the **Add switches** page from the **Inventory** page. Go to **Manage > Inventory** and choose **Add switches** from the **Actions** drop-down list.

6. The **Switch addition mechanism** defaults to **Discover**.

7. Under **Seed switch details**, provide the following information.

- **IP**—provide the management IP address of the switch. You can provide multiple IP addresses separated by commas.

- **Authentication / Privacy** – choose the authentication protocol from the drop-down list.
- **Username** – enter the administrative username for the switch.
- **Password** – enter the password for the specified username.
- **Set as individual device write credential** – check this option if you want to use these credentials specifically for write operations on these devices.

8. Click **Discover switches** to initiate the process.

Nexus Dashboard attempts to communicate with the switches. After Nexus Dashboard discovers the switches, they appear in the **Switches** table with a **Discovering** or **Ok** status.



By default, Nexus Dashboard sets the device TCAM (specialized hardware memory used for high-speed traffic matching) scale to 2048 entries. This memory allows the switch to store and process your traffic filtering and forwarding rules.

Controllers

The **Controllers** tab is used to manage and monitor the controller instances associated with a specific NDB fabric.

The **Controllers** table provides the following information.

Field	Description
Active IP	Displays the IP address Nexus Dashboard currently uses to communicate with the controller.
Username	Specifies the username.
Name	Identifies the unique name assigned to the controller.
Fabric name	Identifies the specific NDB fabric associated with the controller.
Device type	Specifies the model or software version assigned to the controller.
Primary IP address	Specifies the main IP address assigned to the controller.
Secondary IP address	Specifies the backup IP address for high-availability configurations
Tertiary IP address	Specifies a third IP address for additional redundancy, if applicable.
Status description	Provides real-time details regarding the operational state or connection health.

Configure controllers

Follow these steps to configure the switches.

1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. In the **Fabrics** page, click the **Inventory** tab.
4. Click the **Controllers** tab.
5. Choose a switch.
6. From the **Actions** drop-down list, choose one of the following options.
 - **Onboard controller**-- allows you to add a new controller.
 - **Reconnect controller**—allows you to restore communication between NDB and a controller that is offline or lost its connection.
 - **Delete controller**—allows you to remove a controller from the inventory.

Connectivity

The **Connectivity** tab provides a centralized location to manage and monitor the physical and logical connections within your NDB fabric. It allows you to verify that interfaces function correctly and traffic follows your defined policies.

Follow these steps to navigate to the **Connectivity** tab.


1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. Click the **Connectivity** tab.



Input ports	Interface	Switch	Admin status	Operational status	Reason	Policy
Monitoring tools	Ethernet1/1	N9K-C9336C-FX2-156	↑ Up	↑ Up	ok	Data-I
	Ethernet1/2	N9K-C9336C-FX2-156	↑ Up	↑ Up	ok	Data-I
	Ethernet1/3	N9K-C9336C-FX2-156	↑ Up	↓ Down	XCVR not inserted	Data-I
	Ethernet1/4	N9K-C9336C-FX2-156	↑ Up	↓ Down	XCVR not inserted	Data-I
	Ethernet1/5	N9K-C9336C-FX2-156	↑ Up	↓ Down	XCVR not inserted	Data-I

For more information, see [Working with Connectivity in Your Nexus Dashboard NDB fabrics](#).

Configuration policies

The **Configuration policies** tab allows you to manage and deploy CLI-based configuration templates to the switches within the NDB fabric. It applies settings such as interface breakouts and system features directly to the hardware.

Follow these steps to navigate to the **Configuration policies** tab.


1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the Fabrics table, click an NDB fabric.

The **Fabrics** page displays.

3. Click the **Configuration policies** tab.



The screenshot shows the Cisco Nexus Dashboard interface. The top navigation bar includes the Cisco logo, 'Nexus Dashboard', a search icon, a notification bell with '3', a refresh icon, and a user profile 'admin'. The main content area is titled 'sri-ndb' and has a navigation menu with 'Overview', 'Inventory', 'Connectivity', 'Configuration policies' (selected), 'Anomalies', and 'History'. Below the navigation menu, there are tabs for 'Policies' and 'Resources'. A search bar 'Filter by attributes' and an 'Actions' dropdown are present. The main table lists configuration policies with columns: Template, Description, Content type, Switch, Entity name, Entity type, Source, Priority, Editable, and Actions. The table contains several rows of data, including 'feature_tacacs', 'host_11_1', 'int_eth', 'int_mgmt', and 'int_ndb_routed_host'. At the bottom, it indicates '61 items found' and 'Rows per page 100'.

Template	Description	Content type	Switch	Entity name	Entity type	Source	Priority	Editable	Actions	
<input type="checkbox"/>	feature_tacacs	-	TEMPLATE_CLI	N9K-C9336C-FX2-156	SWITCH	switch	-	100	true	fi
<input type="checkbox"/>	host_11_1	-	TEMPLATE_CLI	N9K-C9336C-FX2-156	SWITCH	switch	-	100	true	fi
<input type="checkbox"/>	int_eth	-	TEMPLATE_CLI	N9K-C9336C-FX2-156	mgmt0	interface	mgmt0	910	false	fi
<input type="checkbox"/>	int_mgmt	-	PYTHON	N9K-C9336C-FX2-156	mgmt0	interface	-	900	true	fi
<input type="checkbox"/>	int_ndb_routed_host	loopback7	PYTHON_CLI	N9K-C9336C-FX2-156	loopback7	interface	Data Broker Configuration	500	false	fi

For more information, see [Working with Configuration Policies](#).

Anomalies

The **Anomalies** tab displays all detected anomalies within the NDB fabric. It organizes the anomalies by severity level and category, allowing you to filter and group events to identify and troubleshoot specific problems like hardware health issues.

Follow these steps to navigate to the **Anomalies** tab.


1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.

The **Fabrics** page displays.

3. Click the **Anomalies** tab.



For more information, see [Anomalies](#).

History


The **History** tab provides a comprehensive activity log of all actions taken within the NDB fabric. It provides details about audit logs, deployment history, policy change history, and system events in chronological order, which is essential for compliance, auditing, and tracking the root cause of configuration changes.

Follow these steps to navigate to the **History** tab.

1. Navigate to the **Fabrics** page .

Go to **Manage > Fabrics**.

2. From the **Fabrics** table, click an NDB fabric.
3. The **Fabrics** page displays.
4. Click the **History** tab.



For more information, see [Reviewing History and Logs in Your Nexus Dashboard](#).

Monitor individual switches

The **Switch overview** page provides detailed visibility into the health, traffic flows, and hardware components of an individual switch.

Follow these steps to navigate to the **Switch overview** page of an NDB fabric.

1. Navigate to the **Inventory** page.

Go to **Manage > Inventory**.

2. Click an NDB switch

The **Switch overview** page displays.

The **Switch overview** page includes the following tabs.

- Overview
- Hardware
- Connectivity
- Statistics
- Configuration policies
- Anomalies
- History

For more information on each tab, see [View information on a single switch](#).

Statistics

The **Statistics** tab provides real-time traffic telemetry and performance data for the chosen switch.

The **Statistics** tab is specific to NDB fabrics and allows you to monitor how traffic moves through the hardware to ensure your monitoring policies are active.

Follow these steps to navigate to the **Statistics** page.

1. Navigate to the **Inventory** page.

Go to **Manage > Inventory**.

2. Click an NDB switch

The **Switch overview** page displays.


3. Click the **Statistics** tab.

The **Statistics** page displays the following subtabs.

- o **Flows**
- o **Ports**

Flows

The **Flows** tab shows device flows for NDB devices.



The **Flows** table provides the following information.

Field	Description
In port	Indicates the input port(s) that match the traffic.
DL src	Shows the source MAC address that matches the incoming traffic.
DL dst	Shows the destination MAC address that matches the incoming traffic.
DL type	Displays the Ethertype that matches the incoming traffic. For example, IPv4 or IPv6.

Field	Description
DL VLAN	Displays the VLAN ID that matches the incoming traffic.
VLAN PCP	Shows the VLAN priority that matches the incoming traffic.
NW src	Displays the IPv4 or IPv6 source address for the incoming traffic.
NW dst	Displays the IPv4 or IPv6 destination address for the incoming traffic.
NW proto	Shows the network protocol that matches the incoming traffic, such as "6" for TCP.
TP src	Indicates the source port associated with the network protocol for the incoming traffic.
TP dst	Indicates the destination port associated with the network protocol for the incoming traffic.
Packet count	Shows the aggregate traffic volume, in packets, that match the specified flow connection.

Ports

The **Ports** tab shows statistics for the ports of an NDB device.

The screenshot shows the Cisco Nexus Dashboard interface. The main content area displays the 'Ports' tab for a switch (N9K-C9336C-FX2-156). The table below represents the data shown in the screenshot:

Port	RX pkts	TX pkts	RX bytes	TX bytes	RX pkts (Kbps)	TX pkts (Kbps)	RX drops	TX c
Ethernet1/1	961	961	292144	311277	0	0	0	0
Ethernet1/2	961	961	246977	311277	0	0	0	0
Ethernet1/3	0	0	0	0	0	0	0	0
Ethernet1/4	0	0	0	0	0	0	0	0
Ethernet1/5	0	0	0	0	0	0	0	0
Ethernet1/6	0	0	0	0	0	0	0	0
Ethernet1/7	0	0	0	0	0	0	0	0
Ethernet1/8	0	0	0	0	0	0	0	0
Ethernet1/9	0	0	0	0	0	0	0	0

The **Ports** table provides the following information.

Field	Description
Port	Shows the device interface for which statistics appear.
RX pkts	Shows the number of packets the port received.
TX pkts	Shows the number of packets the port transmitted.
RX bytes	Shows the number of bytes the port received.
TX bytes	Shows the number of bytes the port transmitted.

Field	Description
RX pkts (Kbps)	Displays the rate at which the port receives packets.
TX pkts (Kbps)	Displays the rate at which the port transmits packets.
RX drops	Shows the rate at which the port drops packets while receiving.
TX drops	Shows the rate at which the port drops packets while transmitting.
RX errs	Indicates errors that occur while the port receives packets.
TX errs	Indicates errors that occur while the port transmits packets.
RX frame errs	Shows frame errors that occur while the port receives packets.
RX overRu	Shows overrun errors that occur while the port receives packets.

Copyright

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2017–2026 Cisco Systems, Inc. All rights reserved.

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706

USA

<https://www.cisco.com>

Tel: 408 526-4000

800 553-NETS (6387)

Fax: 408 527-0883