

Cisco Nexus 9000 Series NX-OS Release Notes

Release 10.4(5)M

Note: The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Introduction

This document describes the features, issues, and limitations of Cisco NX-OS software Release 10.4(5)M for use on the Cisco Nexus 9000 Series switches.

Date	Description
March 04, 2025	Release 10.4(5)M became available.

Software Features

There are no new software features introduced in Cisco NX-OS Release 10.4(5)M.

Hardware Features

There are no new hardware features introduced in Cisco NX-OS Release 10.4(5)M.

Release Image

In Cisco NX-OS Release 10.4(5)M, the following two 64-bit images are supported:

- The 64-bit Cisco NX-OS image filename with “nxos64-cs” as the prefix (for example, nxos64-cs.10.4.4.M.bin) is supported on all Cisco Nexus 9000 series switches except Cisco Nexus 9500 -R and -R2 switches and cards.
- The 64-bit Cisco NX-OS image filename with “nxos64-msll” as the prefix (for example, nxos64-msll.10.4.4.M.bin) is supported on Cisco Nexus 9000 Series -R and -R2 modular switches.

Note: The 32-bit image is no longer supported.

Open Issues

Click the bug ID to access the Bug Search Tool and see additional information about the bug.

Bug ID	Headline
CSCwj58944	IPV6 RNH is not updated after ipv6 neighbors are cleared

Resolved Issues

Click the bug ID to access the Bug Search Tool and see additional information about the bug.

Bug ID	Headline
CSCwi53829	N9K - Micron 5300 & 5100 Read-Only Bootflash
CSCwi76297	Ctrl +C is not stopping immediately for " show tech-sup module all" on multiple platforms, vsh crash
CSCwi95363	debug service-core module <i>module</i> sap <i>sap-id</i> frame-count <i>num</i> doesn't work
CSCwj30700	VSH Crash when tunnel-encryption show command is used
CSCwj68609	All dom supported xcvrs show DOMs as N/A on post ND ISSU
CSCwj79746	Seeing tahusd core on sanity129-tor2/N9K-C93600CD-GX
CSCwk09955	syslogd MTS build up leading to copy run start / show cli failure
CSCwk11115	Vulnerabilities in rpcbind 0.2.4
CSCwk24875	svi is taking longer to come up on GIR/vpc domain no shut on primary
CSCwk49611	Delayed linkup seen with 40g or 100g on specific retimer ports
CSCwk49982	NLB Source traffic failed to forward and gets flooded within nlb vlan
CSCwk76266	IGMP proxy reports not generated for L2TRM
CSCwm04351	N9K: 'show system internal access-list globals' contains unexpected output
CSCwm40478	N9K-X9636C-RX: Traffic Punt with default route + uRPF
CSCwm40487	Dispute detected with Peer-switch enabled on non-root
CSCwm45424	MTM Crash after touching scale of 270K mac in L2 heavy mode
CSCwm47438	Cisco NX-OS Software Image Verification Bypass Vulnerability
CSCwm48014	Nexus 9500 mgmt0 interface reverts to 100m after upgrade
CSCwm49373	EVPN prefix fails to advertise when dup paths with same GWIPs are shared between RR via iBGP
CSCwm55371	n9k/vpc - VPC MAC table may have out of sync with high mac scale after peer link flap
CSCwm59420	VLAN Tag on GRE tunneled traffic is changed to Native VLAN for broadcast traffic on N9K
CSCwm61956	n9k: Incorrect static route after NH move between VPC peers in VPC fabric peering
CSCwm63165	under router ospf, no redistribute < proto > without route-map is not working
CSCwm63174	under ospfv3 address-family ipv6, no redistribute <i>proto</i> without route-map is not working
CSCwm72260	Implement recovery mechanism for traffic going over same incoming interface
CSCwm78254	N9K/OSPF route was not installed in route table
CSCwm78875	SNMP trap not generated on MGMT port using IPv6 address

Bug ID	Headline
CSCwmm80669	Proactive IP SLA not able to be configured
CSCwmm80791	Retimer show commands hog CSUSD main thread, client apps could get killed.
CSCwmm83889	TCAM exhaustion caused by ACL configuration pushed through NETCONF results in DME sync issues
CSCwmm84389	New L3VNID config automatically gets added to the running and startup post upgrade to 10.2 code
CSCwmm89006	N9K: Modification failed for NBM flow policy name with the character '/'
CSCwmm89617	On FX3-based N9K switches, SFP-10G-T-X not coming back up after link down
CSCwmm97982	IPv4 policy route-map (PRM) cannot be removed from SVIs If TCAM reaches high utilization
CSCwmm98382	Traffic not forwarded in LACP port-channel with 2 active FEX HIF interfaces
CSCwmm99621	Incorrect command "show logging log file" included in "show tech ngoam"
CSCwmo13546	Incorrect CR patch for bmp-server initial-refresh delay <>
CSCwn01856	LACP/ETHPM REINIT Flap Brings Down All Interfaces of a 400G Breakout
CSCwn03443	DLC is not triggered after SMU installation NXOS.
CSCwn62246	Docker file filling up /var/volatile/log causing logging stops
CSCwn06288	Routes for which RNH is covered by the route's prefix are "pending ufdm" after RNH is lost.
CSCwn07611	Not possible to remove "license smart proxy" from starting-configuration
CSCwn81911	N9K "copy bootflash:<X.ncf> run" of "conf sess vty-acl" results in "Failed to complete Verification"
CSCwn09685	Service "port-profile" crashes due to a memory leak
CSCwn10211	Disclosure of local user password in AAA server logs
CSCwn10332	IPv6 ACL Miss Programmed Blocking ICMP Echo-Reply Type 129
CSCwn11753	Memory leak in SNMP due to libutils.so
CSCwn14266	MPLS Labeled destination traffic dropped on N9k EOR with RX line card
CSCwn21950	Not able to delete a numeric user from the commandline.
CSCwn22843	N9K/TRM/new L3VNI mode - The secondary vPC does not forward multicast traffic in a failover scenario
CSCwn27011	NxOS IPv6 Static Route remains valid when interface to reach next-hop is down
CSCwn29296	N9500-R hardware application counters may get corrupted
CSCwn31806	N9K-GX2/HX Links fail to come up
CSCwn33500	BGP sends out updates 20+ sec after BGP session is up in peer scale setup

Bug ID	Headline
CSCwn36477	N9K-R Stale MPLS Labels attached to URIB even after LDP flushed labels for prefixes
CSCwn36599	N9K-GX2 - CSUSD HAP Reset with no core or stack-trace
CSCwn39482	Need remove the 44B trailer from IPv6 BFD control packets
CSCwn39790	L3 MTU misprogramming on Nexus 9500 after upgrading to 10.3(6)M
CSCwn41310	N9K - " ip pim rp-candidate" command shows as " ip pim bsr rp-candidate" in running-config
CSCwn43902	root command polling data after customer enabling Suzieq poller
CSCwn45253	N9K experiences an unexpected reload with tahusd hap reset
CSCwn46406	NX-OS PIM Bidir DF loser on both sides due to Nexus sending the wrong metric.
CSCwn47474	EBGP peering between vPC Border Leaf VTEP and an external Layer3 fails during failover scenario
CSCwn50809	ALL BFD neighbors down after upgrading from 10.4.2 to 10.4.4(M)
CSCwn51357	vPC LACP Lag-ID mis matched issues when reconfiguration vPC domain.
CSCwn53389	The 'class-map' configuration differs between the show run all and show startup commands
CSCwn55171	Policy based routing not applied after configure replace
CSCwn58536	Auto-negotiation is not supported on C93180YC-FX3 with 100G DAC cable on port with macsec enabled
CSCwn60569	network-operator execute commands for admin after removing VSA on Radius-server
CSCwn64379	N9K-X9716D-GX - Sensor/MTM/Port-Client crash when faulty QSFP-DD is present.
CSCwn78958	Silent Failure Issuing Factory-Reset of FM-G Module
CSCwn80023	" Show flow tracer" command stops working after upgrade to 10.3(x) and above.
CSCwn80317	ospf configuration mismatch in 10.3(5)
CSCwn81661	Broadcast Traffic is Blackholed When the Primary Parent Switch is in Maintenance Mode
CSCwn85089	Traffic destined for IP ending in 136.204 do not reach the 9K SW FEX, not in ELAM
CSCwn87179	NBM interfaces attributes missing in telemetry data streamed from N9K in 10.3(6)
CSCwn89255	Nexus removing IPv4 address from CDP details after IPv6 is configured
CSCwn89433	Upgrade fails from 9.3.14 to 10.3.6 when cli alias name command present
CSCwn90502	ERROR: Failed to write VSH commands.
CSCwn90671	Nexus 9500 floods LSA type 7 for default route with Max age post switchover
CSCwn97983	When performing a config replace statement under router OSPF not applied

Bug ID	Headline
CSCwo00475	Unable to enable "feature netflow"
CSCwo22044	YANG models distributed for NX-OS 10.4.4 are not getting through validation
CSCwo02525	"switchport mac-learn disable" doesn't work in EX platform
CSCwo06777	system vrf-member-change retain-l3-config fails to create new VRF with "vrf member"
CSCwo08645	Crash on C9364D-GX2A while printing transceiver information
CSCwo08994	ERROR: Cannot apply config on a port that is already a member of a port channel

General/Known Issues

Click the bug ID to access the Bug Search Tool and see additional information about the bug.

Bug ID	Description
CSCwi95977	DME CC failure for multisite virtual rmac
CSCwi95768	Loopback Ping is not working after enabling MPLS LDP at Interface
CSCwh36396	Third Party 40G SWDM4 transceiver may take between 40-60 secs to link up
CSCwh88451	URIB crashed on urib_chlist_segv_handler after restarting bgp and urib together
CSCwi57646	ESG_SGACL: Source of MAC detail is not seen in json output of MAC table
CSCwm55263	queue-limit dynamic 0 drops packets with minimal traffic on interface
CSCwi87175	slight drop in L2 multicast performance in N9K-C9364C-H1 switch
CSCwi24238	With NDFC/auto-config, VPC peer-link stays down on disable 'feature tunnel-encryption'
CSCvt37624	'The BGP instance is not in expected state' after quick bgp unconfig / reconfig with 700K ipv4 pfx
CSCwi22304	TTL is not decremented for decap L3 VPN traffic on N9K-C9800.

Bug ID	Description
CSCwh44244	DME inconsistency in sys/mplsta-[eth1/7/1] object after some CLI sequence

Device Hardware

The following tables list the Cisco Nexus 9000 Series hardware that Cisco NX-OS Release 10.4(5)M supports. For additional information about the supported hardware, see the Hardware Installation Guide for your Cisco Nexus 9000 Series device.

Table 1. Cisco Nexus 9800 Switches

Product ID	Description
N9K-C9808	16-RU modular switch with slots for up to 8 Line Cards in addition to 2 supervisors, 8 fabric modules, 4 fan trays, and 3 power trays.
N9K-C9804	10-RU modular switch with slots for up to 4 Line Cards in addition to 2 supervisors, 8 fabric modules, 4 fan trays, and 2 power trays.

Table 2. Cisco Nexus 9800 Series Line Cards

Product ID	Description
N9K-X9836DM-A	Cisco Nexus 9800 36-port 400G QSFP-DD Line Card with MACsec.
N9K-X98900CD-A	Cisco Nexus 9800 14-port 400G QSFP-DD + 34-port 100G QSFP28 Line Card.

Table 3. Cisco Nexus 9800 Series Fabric Modules

Product ID	Description
N9K-C9808-FM-A	Cisco Nexus 9800 Fabric Module for 8-slot Chassis
N9K-C9804-FM-A	Cisco Nexus 9800 Fabric Module for 4-slot Chassis

Table 4. Cisco Nexus 9800 Supervisor Module

Product ID	Description
N9K-C9800-SUP-A	Cisco Nexus 9800 Platform Supervisor Module

Table 5. Cisco Nexus 9800 Fans and Fan Trays

Product ID	Description
N9K-C9808-FAN-A	Cisco Nexus 9800 8-slot chassis fan tray (1 st Generation)
N9K-C9804-FAN-A	Cisco Nexus 9800 4-slot chassis fan tray (1 st Generation)

Table 6. Cisco Nexus 9800 Power Supplies

Product ID	Description
NXK-HV6.3KW20A-A	Cisco Nexus 9800 6,300W 20A AC and HV Power Supply

Table 7. Cisco Nexus 9500 Switches

Product ID	Description
N9K-C9504	7-RU modular switch with slots for up to 4 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 4 power supplies.
N9K-C9508	13-RU modular switch with slots for up to 8 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 8 power supplies.
N9K-C9516	21-RU modular switch with slots for up to 16 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 10 power supplies.

Table 8. Cisco Nexus 9500 Cloud Scale Line Cards

Product ID	Description	Maximum Quantity		
		Cisco Nexus 9504	Cisco Nexus 9508	Cisco Nexus 9516
N9K-X9716D-GX	Cisco Nexus 9500 16-port 400G QSFP-DD Line Card	4	8	N/A
N9K-X9736C-FX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9788TC-FX	Cisco Nexus 9500 48-port 1/10-G BASE-T Ethernet and 4-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X97160YC-EX	Cisco Nexus 9500 48-port 10/25-Gigabit Ethernet SFP28 and 4-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9732C-FX	Cisco Nexus 9500 32-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9732C-EX	Cisco Nexus 9500 32-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9736C-EX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16

Table 9. Cisco Nexus 9500 R-Series Line Cards

Product ID	Description	Maximum Quantity	
		Cisco Nexus 9504	Cisco Nexus 9508
N9K-X9636C-R	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8
N9K-X9636C-RX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8
N9K-X9636Q-R	Cisco Nexus 9500 36-port 40-Gigabit Ethernet QSFP Line Card	4	8
N9K-X96136YC-R	Cisco Nexus 9500 16-port 1/10 Gigabit, 32-port 10/25 Gigabit, and 4-port 40/100 Gigabit Ethernet Line Card	4	8
N9K-X9624D-R2	Cisco Nexus 9500 24-port 400-Gigabit QDD Line Card	Not supported	8

Table 10. Cisco Nexus 9500 Cloud Scale Fabric Modules

Product ID	Description	Minimum	Maximum
N9K-C9504-FM-E	Cisco Nexus 9504 100-Gigabit cloud scale fabric module	4	5
N9K-C9504-FM-G	Cisco Nexus 9500 4-slot 1.6Tbps cloud scale fabric module	4	5
N9K-C9508-FM-E	Cisco Nexus 9508 100-Gigabit cloud scale fabric module	4	5
N9K-C9508-FM-E2	Cisco Nexus 9508 100-Gigabit cloud scale fabric module	4	5
N9K-C9508-FM-G	Cisco Nexus 9500 8-slot 1.6Tbps cloud-scale fabric module	4	5
N9K-C9516-FM-E2	Cisco Nexus 9516 100-Gigabit cloud scale fabric module	4	5

Table 11. Cisco Nexus 9500 R-Series Fabric Modules

Product ID	Description	Minimum	Maximum
N9K-C9504-FM-R	Cisco Nexus 9504 100-Gigabit R-Series fabric module	4	6
N9K-C9508-FM-R	Cisco Nexus 9508 100-Gigabit R-Series fabric module	4	6
N9K-C9508-FM-R2	Cisco Nexus 9508 400-Gigabit R-Series fabric module	4	6

Table 12. Cisco Nexus 9500 Supervisor Modules

Supervisor	Description	Maximum
N9K-SUP-A	1.8-GHz supervisor module with 4 cores, 4 threads, and 16 GB of memory	2
N9K-SUP-A+	1.8-GHz supervisor module with 4 cores, 8 threads, and 16 GB of memory	2

Supervisor	Description	Maximum
N9K-SUP-B	2.2-GHz supervisor module with 6 cores, 12 threads, and 24 GB of memory	2
N9K-SUP-B+	1.9-GHz supervisor module with 6 cores, 12 threads, and 32 GB of memory	2

Note: N9K-SUP-A and N9K-SUP-A+ are not supported on Cisco Nexus 9504 and 9508 switches with -R and -R2 Line Cards.

Table 13. Cisco Nexus 9500 System Controller

Product ID	Description	Quantity
N9K-SC-A	Cisco Nexus 9500 Platform System Controller Module	2

Table 14. Cisco Nexus 9500 Fans and Fan Trays

Product ID	Description	Quantity
N9K-C9504-FAN	Fan tray for 4-slot modular chassis	3
N9K-C9504-FAN2	Fan tray that supports the Cisco N9K-C9504-FM-G fabric module	3
N9K-C9508-FAN	Fan tray for 8-slot modular chassis	3
N9K-C9508-FAN2	Fan tray that supports the Cisco N9K-C9508-FM-G fabric module	3
N9K-C9516-FAN	Fan tray for 16-slot modular chassis	3

Table 15. Cisco Nexus 9500 Fabric Module Blanks with Power Connector

Product ID	Description	Minimum	Maximum
N9K-C9504-FAN-PWR	Cisco Nexus 9500 4-slot chassis 400G cloud scale fan tray power connector	1	2
N9K-C9508-FAN-PWR	Cisco Nexus 9500 4-slot chassis 400G cloud scale fan tray power connector	1	2

Table 16. Cisco Nexus 9500 Power Supplies

Product ID	Description	Quantity	Cisco Nexus Switches
N9K-PAC-3000W-B	3-KW AC power supply	Up to 4	Cisco Nexus 9504
		Up to 8	Cisco Nexus 9508
		Up to 10	Cisco Nexus 9516
N9K-PDC-3000W-B	3-KW DC power supply	Up to 4	Cisco Nexus 9504
		Up to 8	Cisco Nexus 9508
		Up to 10	Cisco Nexus 9516

Product ID	Description	Quantity	Cisco Nexus Switches
N9K-PUV-3000W-B	3-KW Universal AC/DC power supply	Up to 4	Cisco Nexus 9504
		Up to 8	Cisco Nexus 9508
		Up to 10	Cisco Nexus 9516
N9K-PUV2-3000W-B	3.15-KW Dual Input Universal AC/DC Power Supply	Up to 4	Cisco Nexus 9504
		Up to 8	Cisco Nexus 9508
		Up to 10	Cisco Nexus 9516

Table 17. Cisco Nexus 9400 Switches

Product ID	Description
N9K-C9408	4-RU, 8-slot centralized modular chassis switch, which is configurable with up to 128 200-Gigabit QSFP56 (256 100 Gigabit by breakout) ports or 64 400-Gigabit ports.
N9K-C9400-SUP-A	Cisco Nexus 9400 Supervisor Card
N9K-C9400-SW-GX2A	Cisco Nexus 9400 25.6Tbps Switch Card
N9K-X9400-8D	Cisco Nexus 9400 8p 400G QSFP-DD LEM
N9K-X9400-16W	Cisco Nexus 9400 16p 200G QSFP56 LEM
N9K-X9400-22L	Cisco Nexus 9400 LEM with 22 10G/25G/50G ports.

Table 18. Cisco Nexus 9200 and 9300 Switches

Cisco Nexus Switch	Description
N9K-C92348GC-X	The Cisco Nexus 92348GC-X switch (N9K-C92348GC-X) is a 1-RU switch that supports 696 Gbps of bandwidth and over 250 mpps. The 1GBASE-T downlink ports on the 92348GC-X can be configured to work as 100 Mbps, 1-Gbps ports. The 4 ports of SFP28 can be configured as 1/10/25-Gbps and the two-ports of QSFP28 can be configured as 40- and 100-Gbps ports. The Cisco Nexus 92348GC-X is ideal for Big Data customers that require a Gigabit Ethernet ToR switch with local switching.
N9K-C93400LD-H1	1-RU fixed-port, L2/L3 switch with 48 50G SFP56 ports and 4 400G QSFP-DD uplink ports.
N9K-C93108TC-FX3	1 RU fixed-port switch Forty-eight 100M/1G/10GBASE-T ports (ports 1-48), Six 40/100-Gigabit ports QSFP28 (ports 49-54), Two management ports (one 10/100/1000BASE-T port and one SFP port), One console port (RS-232), and one USB port.
N9K-C9332D-H2R	1-RU fixed-port switch with 400-Gigabit QSFP-DD ports (32), 10-Gigabit SFP+ ports (2), Management ports (one 10/100/1000BASE-T port and one SFP port), console port (RS-232), and USB port.

Cisco Nexus Switch	Description
N9K-C9348GC-FX3	1 RU fixed-port switch 48 10/100/1000M copper RJ-45 downlink ports, 4 10-/25G SFP28 uplink ports, and 2 40-/100G QSFP28 uplink ports.
N9K-C9348GC-FX3PH	1-RU fixed-port switch 40 10M/100M/1G copper RJ-45 downlink ports that support PoE/PoE+/PoE++ and 8 10M/100M copper RJ-45 downlink ports that support PoE/PoE+/PoE++, 4 10-/25G SFP28 uplink ports, and 2 40-/100G QSFP28 uplink ports.
N9K-C93180YC-FX3H	1-RU fixed-port switch with 24 100M/1/10/25-Gigabit Ethernet SFP28 ports (ports 1-24), 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54), One management port (one 10/100/1000BASE-T port), and One console port (RS-232)
N9K-C9316D-GX	1-RU switch with 16x400/100/40-Gbps ports.
N9K-C9364C-GX	2-RU fixed-port switch with 64 100-Gigabit SFP28 ports.
N9K-C93600CD-GX	1-RU fixed-port switch with 28 10/40/100-Gigabit QSFP28 ports (ports 1-28), 8 10/40/100/400-Gigabit QSFP-DD ports (ports 29-36)
N9K-C9364C	2-RU Top-of-Rack switch with 64 40-/100-Gigabit QSFP28 ports and 2 1-/10-Gigabit SFP+ ports. • Ports 1 to 64 support 40/100-Gigabit speeds. • Ports 49-64 support MACsec encryption. • Ports 651-64and66 support 1/10 Gigabit speeds.
N9K-C9364C-H1	2-RU fixed-port switch with 64 100G SFP28 ports.
N9K-C9332C	1-RU fixed switch with 32 40/100-Gigabit QSFP28 ports and 2 fixed 1/10-Gigabit SFP+ ports.
N9K-C9332D-GX2B	1-Rack-unit (1-RU) spine switch with 32p 400/100-Gbps QSFP-DD ports and 2p 1/10 SFP+ ports.
N9K-C9348D-GX2A	48p 40/100/400-Gigabit QSFP-DD ports and 2p 1/10G/10G SFP+ ports
N9K-C9364D-GX2A	64p 400/100-Gigabit QSFP-DD ports and 2p 1/10 SFP+ ports
N9K-C93180YC-FX3	48 1/10/25 Gigabit Ethernet SFP28 ports (ports 1-48) 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54)
N9K-C93180YC-FX3S	48 1/10/25 Gigabit Ethernet SFP28 ports (ports 1-48) 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54)
N9K-C9336C-FX2-E	1-RU switch with 36 40-/100-Gb QSFP28 ports
N9K-C9336C-FX2	1-RU switch with 36 40-/100-Gb Ethernet QSFP28 ports
N9K-C93360YC-FX2	2-RU switch with 96 10-/25-Gigabit SFP28 ports and 12 40/100-Gigabit QSFP28 ports
N9K-C93240YC-FX2	1.2-RU Top-of-Rack switch with 48 10-/25-Gigabit SFP28 fiber ports and 12 40-/100-Gigabit Ethernet QSFP28 ports.

Cisco Nexus Switch	Description
N9K-C93216TC-FX2	2-RU switch with 96 100M/1G/10G RJ-45 ports, 12 40/100-Gigabit QSFP28 ports, 2 management ports (one RJ-45 and one SFP port), 1 console port, and 1 USB port.
N9K-C93180YC-FX	1-RU Top-of-Rack switch with 10-/25-/32-Gigabit Ethernet/FC ports and 6 40-/100-Gigabit QSFP28 ports. You can configure the 48 ports as 1/10/25-Gigabit Ethernet ports or as FCoE ports or as 8-/16-/32-Gigabit Fibre Channel ports.
N9K-C93180YC-FX-24	1 RU 24 1/10/25-Gigabit Ethernet SFP28 front panel ports and 6 fixed 40/100-Gigabit Ethernet QSFP28 spine-facing ports. The SFP28 ports support 1-, 10-, and 25-Gigabit Ethernet connections and 8-, 16-, and 32-Gigabit Fibre Channel connections.
N9K-C93108TC-FX	1-RU Top-of-Rack switch with 48 100M/1/10GBASE-T (copper) ports and 6 40-/100-Gigabit QSFP28 ports
N9K-C93108TC-FX-24	1 RU 24 1/10GBASE-T (copper) front panel ports and 6 fixed 40/100-Gigabit Ethernet QSFP28 spine-facing ports.
N9K-C93108TC-FX3P	1-RU fixed-port switch with 48 100M/1/2.5/5/10GBASE-T ports and 6 40-/100-Gigabit QSFP28 ports
N9K-C9348GC-FXP ¹	Cisco Nexus 9300 with 48p 100M/1 G, 4p 10/25 G SFP+ and 2p 100 G QSFP

Table 19. Cisco Nexus 9200 and 9300 Fans and Fan Trays

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-SFAN-30CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9348GC-FX3
NXA-SFAN-30CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	3	9348GC-FX3
NXA-SFAN-30CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9348GC-FX3PH
NXA-SFAN-30CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	3	9348GC-FX3PH
NXA-SFAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	6	9332D-H2R
		5	93400LD-H1
		4	93108TC-FX3

¹ For N9K-C9348GC-FXP the PSU SPROM is not readable when the PSU is not connected. The model displays as "UNKNOWN" and status of the module displays as "shutdown."

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-SFAN-35CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	6	9332D-GX2B
		5	93400LD-H1
		4	93108TC-FX3
NXA-SFAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	6	9332D-GX2B
NXA-FAN-160CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9364C ^[2] 93360YC-FX2
NXA-FAN-160CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	3	9364C ^[1] 93360YC-FX2
NXA-FAN-160CFM2-PE	Fan module with port-side exhaust airflow (blue coloring)	4	9364C-GX
NXA-FAN-160CFM2-PI	Fan module with port-side intake airflow (burgundy coloring)	4	9364C-GX
NXA-FAN-30CFM-B	Fan module with port-side intake airflow (burgundy coloring)	3	93108TC-FX ^[1] 93180YC-FX ^[1] 9348GC-FXP ^[1]
NXA-FAN-30CFM-F	Fan module with port-side exhaust airflow (blue coloring)	3	93108TC-FX ^[1] 93180YC-FX ^[1] 9348GC-FXP
NXA-FAN-35CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	4	92300YC ^[1] 9332C ^[1] 93180YC-FX3S ^[3] 93180YC-FX3 93108TC-FX3P 93180YC-FX3H
		6	9336C-FX2-E 9316D-GX 93600CD-GX

² For specific fan speeds see the Overview section of the Hardware Installation Guide.

³ This switch runs with +1 redundancy mode so that if one fan fails, the switch can sustain operation. But if a second fan fails, this switch is not designed to sustain operation. Hence before waiting for the major threshold temperature to be hit, the switch will power down due to entering the fan policy trigger command.

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-FAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	4	92300YC [1] 9332C [1] 93180YC-FX3S [2] 93180YC-FX3 93108TC-FX3P 93180YC-FX3H
		6	9316D-GX 93600CD-GX
	Fan module with port-side exhaust airflow (blue coloring)	6	9336C-FX2-E
NXA-FAN-65CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	93240YC-FX2 [1] 9336C-FX2 [1]
NXA-FAN-65CFM-PI	Fan module with port-side exhaust airflow (burgundy coloring)	3	93240YC-FX2 9336C-FX2 [1]

Table 20. Cisco Nexus 9200 and 9300 Power Supplies

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PDC-715W-PI	715-W DC power supply with port-side intake airflow (blue coloring)	2	93108TC-FX3P
NXA-PDC-440W-PE	440-W DC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PDC-440W-PI	440-W DC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PHV-350W-PE	350-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PHV-350W-PI	350-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-350W-PE2	350-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-350W-PI2	350-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-1900W-PE	1900-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-1900W-PI	1900-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PHV-2KW-PI	2000-W HVDC power supply with port-side intake airflow (burgundy coloring)	2	9332D-H2R 93400LD-H1
NXA-PAC-1500W-PE	1500-W AC power supply with port-side exhaust airflow (blue coloring)	2	9332D-GX2B
NXA-PAC-1500W-PI	1500-W AC power supply with port-side intake airflow (burgundy coloring)	2	9332D-GX2B
NXA-PAC-500W-PE	500-W AC power supply with port-side exhaust airflow (blue coloring)	2	93180YC-FX 93108TC-FX3
NXA-PAC-500W-PI	500-W AC power supply with port-side intake airflow (burgundy coloring)	2	93180YC-FX 93108TC-FX3
NXA-PAC-650W-PE	650-W AC power supply with port-side exhaust (blue coloring)	2	92300YC 93180YC-FX3S 93180YC-FX3 93180YC-FX3H
NXA-PAC-650W-PI	650-W AC power supply with port-side intake (burgundy coloring)	2	92300YC 93180YC-FX3S 93180YC-FX3 93180YC-FX3H
NXA-PAC-750W-PE	750-W AC power supply with port-side exhaust airflow (blue coloring) 1	2	9336C-FX2 9336C-FX2-E 9332C 93240YC-FX2
NXA-PAC-750W-PI	750-W AC power supply with port-side intake airflow (burgundy coloring) 1	2	9336C-FX2 9336C-FX2-E 9332C 93240YC-FX2
NXA-PAC-1100W-PE2	1100-W AC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 9332C 9316D-GX 9336C-FX2 9336C-FX2-E 93600CD-GX
NXA-PAC-1100W-PI2	1100-W AC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 9332C 9316D-GX 9336C-FX2 9336C-FX2-E 93600CD-GX
NXA-PAC-1100W-PI	Cisco Nexus 9000 PoE 1100W AC PS, port-side intake	2	93108TC-FX3P
NXA-PAC-1100W-PE	Cisco Nexus 9000 PoE 1100W AC PS, port-side exhaust	2	93108TC-FX3P
NXA-PAC-1900W-PI	Cisco Nexus 9000 PoE 1900W AC PS, port-side intake	2	93108TC-FX3P

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PAC-1200W-PE	1200-W AC power supply with port-side exhaust airflow (blue coloring)	2	93360YC-FX2 9364C
NXA-PAC-1200W-PI	1200-W AC power supply with port-side intake airflow (burgundy coloring)	2	93360YC-FX2 9364C
NXA-PAC-1400W-PE	1400-W AC power supply with port-side exhaust airflow (blue coloring)	2	93400LD-H1
NXA-PAC-1400W-PI	1400-W AC power supply with port-side intake airflow (burgundy coloring)	2	93400LD-H1
N9K-PUV-1200W	1200-W Universal AC/DC power supply with bidirectional airflow (white coloring)	2	92300YC 93108TC-FX 93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93108TC-FX3
NXA-PDC-930W-PE	930-W DC power supply with port-side exhaust airflow (blue coloring)	2	93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93180YC-FX3H 93108TC-FX3
NXA-PDC-930W-PI	930-W DC power supply with port-side intake airflow (burgundy coloring)	2	93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93180YC-FX3H 93108TC-FX3
NXA-PDC-1100W-PE	1100-W DC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 93600CD-GX 9316D-GX 9332C 9336C-FX2 9336C-FX2-E
NXA-PDC-1100W-PI	1100-W DC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 93600CD-GX 9316D-GX 9332C 9336C-FX2 9336C-FX2-E
NXA-PHV-1100W-PE	1100-W AC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 9336C-FX2
NXA-PHV-1100W-PI	1100-W AC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 9336C-FX2
NXA-PAC-2KW-PE	2000-W AC power supply with port-side exhaust airflow (blue coloring)	2	9364C-GX

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PAC-2KW-PI	2000-W AC power supply with port-side intake airflow (burgundy coloring)	2	9364C-GX 9332D-H2R
NXA-PDC-2KW-PE	2000-W DC power supply with port-side exhaust airflow (blue coloring)	2	9364C-GX 93400LD-H1
NXA-PDC-2KW-PI	2000-W DC power supply with port-side intake airflow (burgundy coloring)	2	9364C-GX 9332D-H2R 93400LD-H1
N2200-PAC-400W	400-W AC power supply with port-side exhaust airflow (blue coloring)	2	92348GC-X
N2200-PAC-400W-B	400-W AC power supply with port-side intake airflow (burgundy coloring)	2	92348GC-X
N2200-PDC-350W-B	350-W DC power supply with port-side intake airflow	2	92348GC-X
N2200-PDC-400W	400-W DC power supply with port-side exhaust airflow (blue coloring)	2	92348GC-X

Compatibility Information

Fabric Module and Line Card compatibility details are listed below:

Table 21. Cisco Nexus 9500 Cloud Scale Line Cards

Product ID	N9K-C9504-FM-G	N9K-C9508-FM-G	N9K-C9504-FM-E	N9K-C9508-FM-E	N9K-C9508-FM-E2	N9K-C9516-FM-E2
N9K-X9716D-GX	4	4	No	No	No	No
N9K-X9736C-FX	5	5	5	5	5	5
N9K-X97160YC-EX	4	4	4	4	4	4
N9K-X9788TC-FX	4	4	4	4	4	4
N9K-X9732C-EX	4	4	4	4	4	4
N9K-X9732C-FX	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)

Table 22. Cisco Nexus 9500 R-Series Line Cards

Product ID	N9K-C9504-FM-R	N9K-C9508-FM-R
N9K-X9636C-RX	6	6

Product ID	N9K-C9504-FM-R	N9K-C9508-FM-R
N9K-X9636Q-R	4 6 (n+2 redundancy)	4 6 (n+2 redundancy)
N9K-X9636C-R	5 6 (n+1 redundancy)	5 6 (n+1 redundancy)
N9K-X96136YC-R	6	6

Table 23. Cisco Nexus 9500 R2-Series Line Cards

Product ID	N9K-C9508-FM-R2
N9K-X9624D-R2	6

Optics

For information about transceivers and cables supported on a switch, see the [Transceiver Module \(TMG\) Compatibility Matrix](#). For the transceiver specifications and installation information, see the [Install and Upgrade Guides](#).

Cisco Nexus Dashboard Insights for Data Center

Cisco NX-OS Release 10.4(5)M supports the Cisco Nexus Dashboard Insights on Cisco Nexus 9300-FX, 9300-FX2, 9300-FX3, 9300-GX, 9300-GX2, 9400, and 9800 platform switches and 9500 platform switches with -EX/FX/GX Line Cards. See the [Cisco Nexus Insights documentation](#).

Upgrade and Downgrade

To perform a software upgrade or downgrade, follow the instructions in the Cisco Nexus 9000 Series NX-OS Software Upgrade and Downgrade Guide, Release 10.4(x). For information about an In Service Software Upgrade (ISSU), see the [Cisco NX-OS ISSU Support Matrix](#).

Related Content

Document Title	Description
Cisco Nexus 9000 Series Switches	Cisco Nexus 9000 Series Switches documentation
Cisco NX-OS Software Strategy and Lifecycle Guide	Cisco NX-OS Software Release and Image-naming Convention
Cisco Nexus 3000 and 9000 Series NXAPI REST SDK User Guide and API Reference	Cisco Nexus 3000 and 9000 Series NX-NX-API REST SDK User Guide and API Reference

Document Title	Description
Cisco NX-OS Licensing Guide Cisco Nexus 9000 and 3000 Series NX-OS Switch License Navigator Cisco Nexus Smart Licensing Using Policy User Guide	Licensing Information Note: When you downgrade from Cisco NX-OS Release 10.4(5)M to an earlier release, the features that use the ACI+NX-OS Essentials, Advantage, and add-on licenses or the Hardware Streaming Telemetry license continue to work in honor mode in the downgraded version. In addition, the output of the show license usage command continues to include entries for these unsupported licenses.
Cisco Nexus 9000 Series NX-OS Software Upgrade and Downgrade Guide	Cisco Nexus 9000 Series Software Upgrade and Downgrade Guide, Release 10.4(x)
Cisco Nexus 9000 Series FPGA/EPLD Upgrade Release Notes	Cisco Nexus 9000 Series FPGA/EPLD Upgrade Release Notes, Release 10.4(5)M
https://cisco.github.io/cisco-mibs/supportlists/nexus9000/Nexus9000MIBSupportList.html	Cisco NX-OS Supported MIBs
Cisco Nexus 9000 Series Switch FEX Support Matrix	Supported FEX modules
Cisco Nexus 9000 Series Hardware Installation Guides	Cisco Nexus 9000 Series Hardware Installation Guides

Documentation Feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to nexus9k-docfeedback@cisco.com. We appreciate your feedback.

Legal Information

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL:

<https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2025 Cisco Systems, Inc. All rights reserved.