

Cisco Nexus 9000 Series NX-OS Release Notes

Release 10.5(6)M

Note: The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Introduction

This document describes the features, issues, and limitations of Cisco NX-OS software Release 10.5(6)M for use on the Cisco Nexus 9000 Series switches.

Date	Description
July 17, 2026	Release 10.5(6)M became available.

Software features

There are no new software features introduced in Cisco NX-OS Release 10.5(6)M.

Hardware features

There are no new hardware features introduced in Cisco NX-OS Release 10.5(6)M.

Release image

In Cisco NX-OS Release 10.5(6)M, the following four 64-bit images are supported:

- The 64-bit Cisco NX-OS image filename with “nxos64-cs” as the prefix (for example, nxos64-cs.10.5.6.M.bin) is supported on all Cisco Nexus 9000 series switches except Cisco Nexus 9500 series -R and -R2 modular switches, Cisco Nexus 9800 switches, and N9364E-SG2 switches.
- The 64-bit Cisco NX-OS image filename with “nxos64-s1” as the prefix (for example, nxos64-s1.10.5.6.M.bin) is supported and mandatory on all Cisco Nexus 9800 and N9364E-SG2 switches.
- The 64-bit Cisco NX-OS image filename with “nxos64-msll” as the prefix (for example, nxos64-msll.10.5.6.M.bin) is supported on Cisco Nexus 9500 Series -R and -R2 modular switches.

Note: The 32-bit image is no longer supported.

Open issues

There are no open issues in Cisco NX-OS Release 10.5(6)M.

Resolved issues

Click the bug ID to access the Bug Search Tool and see additional information about the bug.

Identifier	Headline
CSCwt59437	RPF not updated properly for PIM Bidir with phantom RP when route for RP is updated

Identifier	Headline
CSCwt49540	Ingress-NAT flows leave switch without NAT for few milliseconds during OIF addition/deletion
CSCwu10926	Slow Memory leak on Multisite BGW switches during Overlay Mroute deletion
CSCwt38794	Presence of faulty hardware can cause segmentation fault in a 9500 system
CSCwt30826	VLAN mapping configuration stuck in ethernet port configuration
CSCwt81214	Exported flow-record duration is negative, StartTime more than EndTime
CSCwt71807	Potential memory leak in IPFM NBM process on Nexus 9000 running 10.5(4) or later
CSCwt57234	ECMP IPv6 Route learnt over VXLAN EVPN as Type-5 Route programmed incorrectly in FIB
CSCwt93795	Multi-port VLAN disable filtering does not prevent probes on specified interfaces causing blocking in NGOAM SLD
CSCws91873	Nexus 9000 gRPC Telemetry Stuck in "Transmit Error" State After InfluxDB Collector Outage (No Auto-Recovery)
CSCwt43290	nginx_dme crashes after changing the "clock summer-time" setting
CSCwu05367	PBR Is not bypassing FIB result when default route is present via VPC

Device hardware

The following tables list the Cisco Nexus 9000 Series hardware that Cisco NX-OS Release 10.5(6)M supports. For additional information about the supported hardware, see the Hardware Installation Guide for your Cisco Nexus 9000 Series device.

Table 1. Cisco Nexus 9800 Switches

Product ID	Description
N9K-C9808	16-RU modular switch with slots for up to 8 Line Cards in addition to 2 supervisors, 8 fabric modules, 4 fan trays, and 3 power trays.
N9K-C9804	10-RU modular switch with slots for up to 4 Line Cards in addition to 2 supervisors, 8 fabric modules, 4 fan trays, and 2 power trays.

Table 2. Cisco Nexus 9800 Series Line Cards

Product ID	Description
N9K-X9836DM-A	Cisco Nexus 9800 36-port 400G QSFP-DD Line Card with MACsec.
N9K-X98900CD-A	Cisco Nexus 9800 14-port 400G QSFP-DD + 34-port 100G QSFP28 Line Card.

Table 3. Cisco Nexus 9800 Series Fabric Modules

Product ID	Description
N9K-C9808-FM-A	Cisco Nexus 9800 Fabric Module for 8-slot Chassis
N9K-C9804-FM-A	Cisco Nexus 9800 Fabric Module for 4-slot Chassis

Table 4. Cisco Nexus 9800 Supervisor Module

Product ID	Description
N9K-C9800-SUP-A	Cisco Nexus 9800 Platform Supervisor Module

Table 5. Cisco Nexus 9800 Fans and Fan Trays

Product ID	Description
N9K-C9808-FAN-A	Cisco Nexus 9800 8-slot chassis fan tray (1 st Generation)
N9K-C9804-FAN-A	Cisco Nexus 9800 4-slot chassis fan tray (1 st Generation)

Table 6. Cisco Nexus 9800 Power Supplies

Product ID	Description
N9K-HV 6.3KW 20A-A	Cisco Nexus 9800 6,300W 20A AC and HV Power Supply

Table 7. Cisco Nexus 9500 Switches

Product ID	Description
N9K-C9504	7-RU modular switch with slots for up to 4 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 4 power supplies.
N9K-C9508	13-RU modular switch with slots for up to 8 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 8 power supplies.
N9K-C9516	21-RU modular switch with slots for up to 16 Line Cards in addition to two supervisors, 2 system controllers, 3-6 fabric modules, 3 fan trays, and up to 10 power supplies.

Table 8. Cisco Nexus 9500 Cloud Scale Line Cards

Product ID	Description	Maximum Quantity		
		Cisco Nexus 9504	Cisco Nexus 9508	Cisco Nexus 9516
N9K-X9716D-GX	Cisco Nexus 9500 16-port 400G QSFP-DD Line Card	4	8	N/A
N9K-X9736C-FX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16

Product ID	Description	Maximum Quantity		
		Cisco Nexus 9504	Cisco Nexus 9508	Cisco Nexus 9516
N9K-X9736C-FX3	Cisco Nexus 9500 36-port 40GE/100GE line card	4	8	16
N9K-X9788TC-FX	Cisco Nexus 9500 48-port 1/10-G BASE-T Ethernet and 4-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X97160YC-EX	Cisco Nexus 9500 48-port 10/25-Gigabit Ethernet SFP28 and 4-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9732C-FX	Cisco Nexus 9500 32-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9732C-EX	Cisco Nexus 9500 32-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16
N9K-X9736C-EX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8	16

Table 9. Cisco Nexus 9500 R-Series Line Cards

Product ID	Description	Maximum Quantity	
		Cisco Nexus 9504	Cisco Nexus 9508
N9K-X9636C-R	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8
N9K-X9636C-RX	Cisco Nexus 9500 36-port 40/100 Gigabit Ethernet QSFP28 Line Card	4	8
N9K-X9636Q-R	Cisco Nexus 9500 36-port 40-Gigabit Ethernet QSFP Line Card	4	8
N9K-X96136YC-R	Cisco Nexus 9500 16-port 1/10 Gigabit, 32-port 10/25 Gigabit, and 4-port 40/100 Gigabit Ethernet Line Card	4	8
N9K-X9624D-R2	Cisco Nexus 9500 24-port 400-Gigabit QDD Line Card	Not supported	8

Table 10. Cisco Nexus 9500 Cloud Scale Fabric Modules

Product ID	Description	Minimum	Maximum
N9K-C9504-FM-E	Cisco Nexus 9504 100-Gigabit cloud scale fabric module	4	5
N9K-C9504-FM-G	Cisco Nexus 9500 4-slot 1.6Tbps cloud scale fabric module	4	5
N9K-C9508-FM-E	Cisco Nexus 9508 100-Gigabit cloud scale fabric module	4	5

Product ID	Description	Minimum	Maximum
N9K-C9508-FM-E2	Cisco Nexus 9508 100-Gigabit cloud scale fabric module	4	5
N9K-C9508-FM-G	Cisco Nexus 9500 8-slot 1.6Tbps cloud-scale fabric module	4	5
N9K-C9516-FM-E2	Cisco Nexus 9516 100-Gigabit cloud scale fabric module	4	5

Table 11. Cisco Nexus 9500 R-Series Fabric Modules

Product ID	Description	Minimum	Maximum
N9K-C9504-FM-R	Cisco Nexus 9504 100-Gigabit R-Series fabric module	4	6
N9K-C9508-FM-R	Cisco Nexus 9508 100-Gigabit R-Series fabric module	4	6
N9K-C9508-FM-R2	Cisco Nexus 9508 400-Gigabit R-Series fabric module	4	6

Table 12. Cisco Nexus 9500 Supervisor Modules

Supervisor	Description	Maximum
N9K-SUP-A	1.8-GHz supervisor module with 4 cores, 4 threads, and 16 GB of memory	2
N9K-SUP-A+	1.8-GHz supervisor module with 4 cores, 8 threads, and 16 GB of memory	2
N9K-SUP-B	2.2-GHz supervisor module with 6 cores, 12 threads, and 24 GB of memory	2
N9K-SUP-B+	1.9-GHz supervisor module with 6 cores, 12 threads, and 32 GB of memory	2

Note: N9K-SUP-A and N9K-SUP-A+ are not supported on Cisco Nexus 9504 and 9508 switches with -R and -R2 Line Cards.

Table 13. Cisco Nexus 9500 System Controller

Product ID	Description	Quantity
N9K-SC-A	Cisco Nexus 9500 Platform System Controller Module	2

Table 14. Cisco Nexus 9500 Fans and Fan Trays

Product ID	Description	Quantity
N9K-C9504-FAN	Fan tray for 4-slot modular chassis	3
N9K-C9504-FAN2	Fan tray that supports the Cisco N9K-C9504-FM-G fabric module	3
N9K-C9508-FAN	Fan tray for 8-slot modular chassis	3
N9K-C9508-FAN2	Fan tray that supports the Cisco N9K-C9508-FM-G fabric module	3
N9K-C9516-FAN	Fan tray for 16-slot modular chassis	3

Table 15. Cisco Nexus 9500 Fabric Module Blanks with Power Connector

Product ID	Description	Minimum	Maximum
N9K-C9504-FAN-PWR	Cisco Nexus 9500 4-slot chassis 400G cloud scale fan tray power connector	1	2
N9K-C9508-FAN-PWR	Cisco Nexus 9500 4-slot chassis 400G cloud scale fan tray power connector	1	2

Table 16. Cisco Nexus 9500 Power Supplies

Product ID	Description	Quantity	Cisco Nexus Switches
N9K-PAC-3000W-B	3-KW AC power supply	Up to 4 Up to 8 Up to 10	Cisco Nexus 9504 Cisco Nexus 9508 Cisco Nexus 9516
N9K-PDC-3000W-B	3-KW DC power supply	Up to 4 Up to 8 Up to 10	Cisco Nexus 9504 Cisco Nexus 9508 Cisco Nexus 9516
N9K-PUV-3000W-B	3-KW Universal AC/DC power supply	Up to 4 Up to 8 Up to 10	Cisco Nexus 9504 Cisco Nexus 9508 Cisco Nexus 9516
N9K-PUV2-3000W-B	3.15-KW Dual Input Universal AC/DC Power Supply	Up to 4 Up to 8 Up to 10	Cisco Nexus 9504 Cisco Nexus 9508 Cisco Nexus 9516

Table 17. Cisco Nexus 9400 Switches

Product ID	Description
N9K-C9408	4-RU, 8-slot centralized modular chassis switch, which is configurable with up to 128 200-Gigabit QSFP56 (256 100 Gigabit by breakout) ports or 64 400-Gigabit ports.
N9K-C9400-SUP-A	Cisco Nexus 9400 Supervisor Card
N9K-C9400-SW-GX2A	Cisco Nexus 9400 25.6Tbps Switch Card
N9K-X9400-8D	Cisco Nexus 9400 8p 400G QSFP-DD LEM
N9K-X9400-16W	Cisco Nexus 9400 16p 200G QSFP56 LEM
N9K-X9400-22L	Cisco Nexus 9400 LEM with 22 10G/25G/50G ports.

Table 18. Cisco Nexus 9200 and 9300 Switches

Cisco Nexus Switch	Description
N9364E-SG2-Q	The Cisco Nexus 9364E-SG2-Q switch is a 2-rack unit (RU), fixed-port, high-density switch designed to support high-density 800G fabrics for next generation leaf and spine designs.
N9364E-SG2-O	The Cisco Nexus 9364E-SG2-O Switch is a 2-rack unit (RU), fixed-port, high-density switch designed to support high-density 800G fabrics for next generation leaf and spine designs.
N9K-C92348GC-X	The Cisco Nexus 92348GC-X switch (N9K-C92348GC-X) is a 1-RU switch that supports 696 Gbps of bandwidth and over 250 mpps. The 1GBASE-T downlink ports on the 92348GC-X can be configured to work as 100 Mbps, 1-Gbps ports. The 4 ports of SFP28 can be configured as 1/10/25-Gbps and the two-ports of QSFP28 can be configured as 40- and 100-Gbps ports. The Cisco Nexus 92348GC-X is ideal for Big Data customers that require a Gigabit Ethernet ToR switch with local switching.
N9K-C93400LD-H1	1-RU fixed-port, L2/L3 switch with 48 50G SFP56 ports and 4 400G QSFP-DD uplink ports.
N9K-C93108TC-FX3	1 RU fixed-port switch Forty-eight 100M/1G/10GBASE-T ports (ports 1-48), Six 40/100-Gigabit ports QSFP28 (ports 49-54), Two management ports (one 10/100/1000BASE-T port and one SFP port), One console port (RS-232), and one USB port.
N9K-C9332D-H2R	1-RU fixed-port switch with 400-Gigabit QSFP-DD ports (32), 10-Gigabit SFP+ ports (2), Management ports (one 10/100/1000BASE-T port and one SFP port), console port (RS-232), and USB port.
N9K-C9348GC-FX3	1 RU fixed-port switch 48 10/100/1000M copper RJ-45 downlink ports, 4 10-/25G SFP28 uplink ports, and 2 40-/100G QSFP28 uplink ports.
N9K-C9348GC-FX3PH	1-RU fixed-port switch 40 10M/100M/1G copper RJ-45 downlink ports that support PoE/PoE+/PoE++ and 8 10M/100M copper RJ-45 downlink ports that support PoE/PoE+/PoE++, 4 10-/25G SFP28 uplink ports, and 2 40-/100G QSFP28 uplink ports.
N9K-C93180YC-FX3H	1-RU fixed-port switch with 24 100M/1/10/25-Gigabit Ethernet SFP28 ports (ports 1-24), 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54), One management port (one 10/100/1000BASE-T port), and One console port (RS-232)
N9K-C9316D-GX	1-RU switch with 16x400/100/40-Gbps ports.
N9K-C9364C-GX	2-RU fixed-port switch with 64 100-Gigabit SFP28 ports.
N9K-C93600CD-GX	1-RU fixed-port switch with 28 10/40/100-Gigabit QSFP28 ports (ports 1-28), 8 10/40/100/400-Gigabit QSFP-DD ports (ports 29-36)

Cisco Nexus Switch	Description
N9K-C9364C	2-RU Top-of-Rack switch with 64 40-/100-Gigabit QSFP28 ports and 2 1-/10-Gigabit SFP+ ports. • Ports 1 to 64 support 40/100-Gigabit speeds. • Ports 49-64 support MACsec encryption. • Ports 651-64and66 support 1/10 Gigabit speeds.
N9K-C9364C-H1	2-RU fixed-port switch with 64 100G SFP28 ports.
N9K-C9332C	1-RU fixed switch with 32 40/100-Gigabit QSFP28 ports and 2 fixed 1/10-Gigabit SFP+ ports.
N9K-C9332D-GX2B	1-Rack-unit (1-RU) spine switch with 32p 400/100-Gbps QSFP-DD ports and 2p 1/10 SFP+ ports.
N9K-C9348D-GX2A	48p 40/100/400-Gigabit QSFP-DD ports and 2p 1/10G/10G SFP+ ports
N9K-C9364D-GX2A	64p 400/100-Gigabit QSFP-DD ports and 2p 1/10 SFP+ ports
N9K-C93180YC-FX3	48 1/10/25 Gigabit Ethernet SFP28 ports (ports 1-48) 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54)
N9K-C93180YC-FX3S	48 1/10/25 Gigabit Ethernet SFP28 ports (ports 1-48) 6 10/25/40/50/100-Gigabit QSFP28 ports (ports 49-54)
N9K-C9336C-FX2-E	1-RU switch with 36 40-/100-Gb QSFP28 ports
N9K-C9336C-FX2	1-RU switch with 36 40-/100-Gb Ethernet QSFP28 ports
N9K-C93360YC-FX2	2-RU switch with 96 10-/25-Gigabit SFP28 ports and 12 40/100-Gigabit QSFP28 ports
N9K-C93240YC-FX2	1.2-RU Top-of-Rack switch with 48 10-/25-Gigabit SFP28 fiber ports and 12 40-/100-Gigabit Ethernet QSFP28 ports.
N9K-C93216TC-FX2	2-RU switch with 96 100M/1G/10G RJ-45 ports, 12 40/100-Gigabit QSFP28 ports, 2 management ports (one RJ-45 and one SFP port), 1 console port, and 1 USB port.
N9K-C93180YC-FX	1-RU Top-of-Rack switch with 10-/25-/32-Gigabit Ethernet/FC ports and 6 40-/100-Gigabit QSFP28 ports. You can configure the 48 ports as 1/10/25-Gigabit Ethernet ports or as FCoE ports or as 8-/16-/32-Gigabit Fibre Channel ports.
N9K-C93180YC-FX-24	1 RU 24 1/10/25-Gigabit Ethernet SFP28 front panel ports and 6 fixed 40/100-Gigabit Ethernet QSFP28 spine-facing ports. The SFP28 ports support 1-, 10-, and 25-Gigabit Ethernet connections and 8-, 16-, and 32-Gigabit Fibre Channel connections.
N9K-C93108TC-FX	1-RU Top-of-Rack switch with 48 100M/1/10GBASE-T (copper) ports and 6 40-/100-Gigabit QSFP28 ports
N9K-C93108TC-FX-24	1 RU 24 1/10GBASE-T (copper) front panel ports and 6 fixed 40/100-Gigabit Ethernet QSFP28 spine-facing ports.
N9K-C93108TC-FX3P	1-RU fixed-port switch with 48 100M/1/2.5/5/10GBASE-T ports and 6 40-/100-Gigabit QSFP28 ports

Cisco Nexus Switch	Description
N9K-C9348GC-FXP ¹	Cisco Nexus 9300 with 48p 100M/1 G, 4p 10/25 G SFP+ and 2p 100 G QSFP

Table 19. Cisco Nexus 9200 and 9300 Fans and Fan Trays

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-SFAN-30CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9348GC-FX3
NXA-SFAN-30CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	3	9348GC-FX3
NXA-SFAN-30CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9348GC-FX3PH
NXA-SFAN-30CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	3	9348GC-FX3PH
NXA-SFAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	6	9332D-H2R
		5	93400LD-H1
		4	93108TC-FX3
NXA-SFAN-35CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	6	9332D-GX2B
		5	93400LD-H1
		4	93108TC-FX3
NXA-SFAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	6	9332D-GX2B
NXA-FAN-160CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	9364C ^[2] 93360YC-FX2

¹ For N9K-C9348GC-FXP the PSU SPROM is not readable when the PSU is not connected. The model displays as "UNKNOWN" and status of the module displays as "shutdown."

² For specific fan speeds see the Overview section of the Hardware Installation Guide.

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-FAN-35CFM-PI	Fan module with port-side intake airflow (burgundy coloring)	4	92300YC [1] 9332C [1] 93180YC-FX3S [2] 93180YC-FX3 93108TC-FX3P 93180YC-FX3H
		6	9316D-GX 93600CD-GX
	Fan module with port-side exhaust airflow (blue coloring)	6	9336C-FX2-E
NXA-FAN-65CFM-PE	Fan module with port-side exhaust airflow (blue coloring)	3	93240YC-FX2 [1] 9336C-FX2 [1]
NXA-FAN-65CFM-PI	Fan module with port-side exhaust airflow (burgundy coloring)	3	93240YC-FX2 9336C-FX2 [1]

Table 20. Cisco Nexus 9200 and 9300 Power Supplies

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PDC-715W-PI	715-W DC power supply with port-side intake airflow (blue coloring)	2	93108TC-FX3P
NXA-PDC-440W-PE	440-W DC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PDC-440W-PI	440-W DC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PHV-350W-PE	350-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PHV-350W-PI	350-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-350W-PE2	350-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-350W-PI2	350-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-1900W-PE	1900-W AC power supply with port-side exhaust airflow (blue coloring)	2	9348GC-FX3 9348GC-FX3PH
NXA-PAC-1900W-PI	1900-W AC power supply with port-side intake airflow (burgundy coloring)	2	9348GC-FX3 9348GC-FX3PH

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PHV-2KW-PI	2000-W HVDC power supply with port-side intake airflow (burgundy coloring)	2	9332D-H2R 93400LD-H1
NXA-PAC-1500W-PE	1500-W AC power supply with port-side exhaust airflow (blue coloring)	2	9332D-GX2B
NXA-PAC-1500W-PI	1500-W AC power supply with port-side intake airflow (burgundy coloring)	2	9332D-GX2B
NXA-PAC-500W-PE	500-W AC power supply with port-side exhaust airflow (blue coloring)	2	93180YC-FX 93108TC-FX3
NXA-PAC-500W-PI	500-W AC power supply with port-side intake airflow (burgundy coloring)	2	93180YC-FX 93108TC-FX3
NXA-PAC-650W-PE	650-W AC power supply with port-side exhaust (blue coloring)	2	92300YC 93180YC-FX3S 93180YC-FX3 93180YC-FX3H
NXA-PAC-650W-PI	650-W AC power supply with port-side intake (burgundy coloring)	2	92300YC 93180YC-FX3S 93180YC-FX3 93180YC-FX3H
NXA-PAC-750W-PE	750-W AC power supply with port-side exhaust airflow (blue coloring) 1	2	9336C-FX2 9336C-FX2-E 9332C 93240YC-FX2
NXA-PAC-750W-PI	750-W AC power supply with port-side intake airflow (burgundy coloring) 1	2	9336C-FX2 9336C-FX2-E 9332C 93240YC-FX2
NXA-PAC-1100W-PE2	1100-W AC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 9332C 9316D-GX 9336C-FX2 9336C-FX2-E 93600CD-GX
NXA-PAC-1100W-PI2	1100-W AC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 9332C 9316D-GX 9336C-FX2 9336C-FX2-E 93600CD-GX
NXA-PAC-1100W-PI	Cisco Nexus 9000 PoE 1100W AC PS, port-side intake	2	93108TC-FX3P
NXA-PAC-1100W-PE	Cisco Nexus 9000 PoE 1100W AC PS, port-side exhaust	2	93108TC-FX3P
NXA-PAC-1900W-PI	Cisco Nexus 9000 PoE 1900W AC PS, port-side intake	2	93108TC-FX3P

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PAC-1200W-PE	1200-W AC power supply with port-side exhaust airflow (blue coloring)	2	93360YC-FX2 9364C
NXA-PAC-1200W-PI	1200-W AC power supply with port-side intake airflow (burgundy coloring)	2	93360YC-FX2 9364C
NXA-PAC-1400W-PE	1400-W AC power supply with port-side exhaust airflow (blue coloring)	2	93400LD-H1
NXA-PAC-1400W-PI	1400-W AC power supply with port-side intake airflow (burgundy coloring)	2	93400LD-H1
N9K-PUV-1200W	1200-W Universal AC/DC power supply with bidirectional airflow (white coloring)	2	92300YC 93108TC-FX 93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93108TC-FX3
NXA-PDC-930W-PE	930-W DC power supply with port-side exhaust airflow (blue coloring)	2	93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93180YC-FX3H 93108TC-FX3
NXA-PDC-930W-PI	930-W DC power supply with port-side intake airflow (burgundy coloring)	2	93360YC-FX2 93180YC-FX3S 93180YC-FX 9364C 93180YC-FX3H 93108TC-FX3
NXA-PDC-1100W-PE	1100-W DC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 93600CD-GX 9316D-GX 9332C 9336C-FX2 9336C-FX2-E
NXA-PDC-1100W-PI	1100-W DC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 93600CD-GX 9316D-GX 9332C 9336C-FX2 9336C-FX2-E
NXA-PHV-1100W-PE	1100-W AC power supply with port-side exhaust airflow (blue coloring)	2	93240YC-FX2 9336C-FX2
NXA-PHV-1100W-PI	1100-W AC power supply with port-side intake airflow (burgundy coloring)	2	93240YC-FX2 9336C-FX2
NXA-PAC-2KW-PE	2000-W AC power supply with port-side exhaust airflow (blue coloring)	2	9364C-GX

Product ID	Description	Quantity	Cisco Nexus Switches
NXA-PAC-2KW-PI	2000-W AC power supply with port-side intake airflow (burgundy coloring)	2	9364C-GX 9332D-H2R
NXA-PDC-2KW-PE	2000-W DC power supply with port-side exhaust airflow (blue coloring)	2	9364C-GX 93400LD-H1
NXA-PDC-2KW-PI	2000-W DC power supply with port-side intake airflow (burgundy coloring)	2	9364C-GX 9332D-H2R 93400LD-H1
N2200-PAC-400W	400-W AC power supply with port-side exhaust airflow (blue coloring)	2	92348GC-X
N2200-PAC-400W-B	400-W AC power supply with port-side intake airflow (burgundy coloring)	2	92348GC-X
N2200-PDC-350W-B	350-W DC power supply with port-side intake airflow	2	92348GC-X
N2200-PDC-400W	400-W DC power supply with port-side exhaust airflow (blue coloring)	2	92348GC-X

Compatibility information

Fabric Module and Line Card compatibility details are listed below:

Table 21. Cisco Nexus 9500 Cloud Scale Line Cards

Product ID	N9K-C9504-FM-G	N9K-C9508-FM-G	N9K-C9504-FM-E	N9K-C9508-FM-E	N9K-C9508-FM-E2	N9K-C9516-FM-E2
N9K-X9716D-GX	4	4	No	No	No	No
N9K-X9736C-FX	5	5	5	5	5	5
N9K-X97160YC-EX	4	4	4	4	4	4
N9K-X9788TC-FX	4	4	4	4	4	4
N9K-X9732C-EX	4	4	4	4	4	4
N9K-X9732C-FX	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)	4 5 (n+1 redundancy)

Table 22. Cisco Nexus 9500 R-Series Line Cards

Product ID	N9K-C9504-FM-R	N9K-C9508-FM-R
N9K-X9636C-RX	6	6

Product ID	N9K-C9504-FM-R	N9K-C9508-FM-R
N9K-X9636Q-R	4 6 (n+2 redundancy)	4 6 (n+2 redundancy)
N9K-X9636C-R	5 6 (n+1 redundancy)	5 6 (n+1 redundancy)
N9K-X96136YC-R	6	6

Table 23. Cisco Nexus 9500 R2-Series Line Cards

Product ID	N9K-C9508-FM-R2
N9K-X9624D-R2	6

Optics

For information about transceivers and cables supported on a switch, see the [Transceiver Module \(TMG\) Compatibility Matrix](#). For the transceiver specifications and installation information, see the [Install and Upgrade Guides](#).

Cisco Nexus Dashboard Insights for Data Center

Cisco NX-OS Release 10.5(6)M supports the Cisco Nexus Dashboard Insights on Cisco Nexus 9300-FX, 9300-FX2, 9300-FX3, 9300-GX, 9300-GX2, 9400, and 9800 platform switches and 9500 platform switches with -EX/FX/GX Line Cards. See the [Cisco Nexus Insights documentation](#).

Upgrade and downgrade

To perform a software upgrade or downgrade, follow the instructions in the Cisco Nexus 9000 Series NX-OS Software Upgrade and Downgrade Guide, Release 10.5(x). For information about an In Service Software Upgrade (ISSU), see the [Cisco NX-OS ISSU Support Matrix](#).

Related content

Document Title	Description
Cisco Nexus 9000 Series Switches	Cisco Nexus 9000 Series Switches documentation
Cisco NX-OS Software Strategy and Lifecycle Guide	Cisco NX-OS Software Release and Image-naming Convention
Cisco Nexus 3000 and 9000 Series NXhttps://developer.cisco.com/site/nx-os/docs/n3k-n9k-api-ref/API REST SDK User Guide and API Reference	Cisco Nexus 3000 and 9000 Series NX-NX-API REST SDK User Guide and API Reference

Document Title	Description
Cisco NX-OS Licensing Guide Cisco Nexus 9000 and 3000 Series NX-OS Switch License Navigator Cisco Nexus Smart Licensing Using Policy User Guide	Licensing Information Note: When you downgrade from Cisco NX-OS Release 10.5(6)M to an earlier release, the features that use the ACI+NX-OS Essentials, Advantage, and add-on licenses or the Hardware Streaming Telemetry license continue to work in honor mode in the downgraded version. In addition, the output of the show license usage command continues to include entries for these unsupported licenses.
Cisco Nexus 9000 Series NX-OS Software Upgrade and Downgrade Guide	Cisco Nexus 9000 Series Software Upgrade and Downgrade Guide, Release 10.5(x)
Cisco Nexus 9000 Series FPGA/EPLD Upgrade Release Notes	Cisco Nexus 9000 Series FPGA/EPLD Upgrade Release Notes, Release 10.5(6)M
https://cisco.github.io/cisco-mibs/supportlists/nexus9000/Nexus9000MIBSupportList.html	Cisco NX-OS Supported MIBs
Cisco Nexus 9000 Series Switch FEX Support Matrix	Supported FEX modules
Cisco Nexus 9000 Series Hardware Installation Guides	Cisco Nexus 9000 Series Hardware Installation Guides

Documentation feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to nexus9k-docfeedback@cisco.com. We appreciate your feedback.

Legal information

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL:

<https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2026 Cisco Systems, Inc. All rights reserved.