



Cisco Nexus 9000 Series NX-OS Verified Scalability Guide, Release 10.6(3)F

[List of Tables.....cv](#)

| | |
|---|----------|
| Introduction | 5 |
| Verified Scalability Limits - Unidimensional | 5 |
| Verified Scalability Limits - Multidimensional - 9500 R-Series | 95 |
| Deployment Case Studies | 101 |

[List of Tables.....cv](#)

LIST OF TABLES

| | |
|---|-----|
| Table 1: eBGP/IS-IS Profile Verified Scalability Limits (Multidimensional)..... | 95 |
| Table 2: iBGP/OSPF Profile Verified Scalability Limits (Multidimensional)..... | 96 |
| Table 3: iBGP/EIGRP Profile Verified Scalability Limits (Multidimensional)..... | 97 |
| Table 4: MPLS Verified Scalability Limits (Multidimensional)..... | 98 |
| Table 5: Layer 2/Layer 3 Boundary Verified Scalability Limits (Multidimensional)..... | 98 |
| Table 6: Segment Routing Verified Scalability Limits (Multidimensional)..... | 99 |
| Table 7: VXLAN Profile Verified Scalability Limits (Multidimensional)..... | 100 |
| Table 8: VXLAN BGP/eVPN iBGP Centric Topology..... | 101 |
| Table 9: FEX System Topology..... | 104 |



Preface

Audience

This publication is for network administrators who configure and maintain Cisco Nexus devices.

Document Conventions



Note As part of our constant endeavor to remodel our documents to meet our customers' requirements, we have modified the manner in which we document configuration tasks. As a result of this, you may find a deviation in the style used to describe these tasks, with the newly included sections of the document following the new format.

Command descriptions use the following conventions:

| Convention | Description |
|-----------------|---|
| bold | Bold text indicates the commands and keywords that you enter literally as shown. |
| <i>Italic</i> | Italic text indicates arguments for which the user supplies the values. |
| [x] | Square brackets enclose an optional element (keyword or argument). |
| [x y] | Square brackets enclosing keywords or arguments separated by a vertical bar indicate an optional choice. |
| {x y} | Braces enclosing keywords or arguments separated by a vertical bar indicate a required choice. |
| [x {y z}] | Nested set of square brackets or braces indicate optional or required choices within optional or required elements. Braces and a vertical bar within square brackets indicate a required choice within an optional element. |
| <i>variable</i> | Indicates a variable for which you supply values, in context where italics cannot be used. |
| string | A nonquoted set of characters. Do not use quotation marks around the string or the string will include the quotation marks. |

Examples use the following conventions:

| Convention | Description |
|-----------------------------|---|
| screen font | Terminal sessions and information the switch displays are in screen font. |
| boldface screen font | Information you must enter is in boldface screen font. |
| <i>italic screen font</i> | Arguments for which you supply values are in italic screen font. |
| < > | Nonprinting characters, such as passwords, are in angle brackets. |
| [] | Default responses to system prompts are in square brackets. |
| !, # | An exclamation point (!) or a pound sign (#) at the beginning of a line of code indicates a comment line. |

This document uses the following conventions:



Note Means *reader take note*. Notes contain helpful suggestions or references to material not covered in the manual.



Caution Means *reader be careful*. In this situation, you might do something that could result in equipment damage or loss of data.

Documentation Feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to: .

We appreciate your feedback.

Introduction

This document describes the Cisco NX-OS configuration limits for Cisco Nexus 9000 Series switches.

The values provided in this guide should not be interpreted as theoretical system limits for Cisco NX-OS hardware or Cisco NX-OS software. These limits refer to values that have been validated by Cisco. They can increase over time as more testing and validation is done.

Verified Scalability Limits - Unidimensional

The following tables in this section list the verified scalability limits of the Cisco Nexus 9000 Series switches for Cisco NX-OS Release 10.6(3)F.

- [Cisco Nexus 2000 Series Fabric Extenders \(FEX\) Straight Through Mode Verified Scalability Limits, on page 6](#)
- [ePBR Verified Scalability Limits, on page 6](#)
- [FC and FCoE Switch Level Configuration Limits, on page 7](#)
- [FC and FCoE Fabric Level Configuration Limits, on page 8](#)
- [Intelligent Traffic Director Verified Scalability Limits, on page 8](#)
- [Interfaces Verified Scalability Limits, on page 9](#)
- [Label Switching Verified Scalability Limits, on page 13](#)
- [Private VLANs \(PVLANS\) Verified Scalability Limits, on page 18](#)
- [Layer 2 Switching Verified Scalability Limits, on page 19](#)
- [Multicast Routing Verified Scalability Limits, on page 23](#)
- [IP Fabric for Media Solution Verified Scalability Limits, on page 28](#)
- [IP Fabric for Media Solution Policer Verified Scalability Limits, on page 30](#)
- [Programmability Verified Scalability Limits, on page 30](#)
- [QoS Verified Scalability Limits, on page 32](#)
- [Security Verified Scalability Limits, on page 33](#)
- [SRv6 Verified Scalability Limits, on page 41](#)
- [Egress NetFlow Verified Scalability Limits, on page 42](#)
- [System Management Verified Scalability Limits, on page 43](#)
- [NetFlow Scalability Support \(Flows\) for Cisco Nexus 9500 Family Switches, on page 52](#)
- [NetFlow SVI Verified Scalability Limits, on page 53](#)
- [Unicast Routing Verified Scalability Limits, on page 54](#)
- [RIPng Verified Scalability Limits, on page 76](#)
- [PVLAN VXLAN Verified Scalability Limits, on page 76](#)

- [VXLAN Verified Scalability Limits, on page 77](#)
- [Tetration Verified Scalability Limits, on page 93](#)

These limits are validated with a unidimensional configuration. The values provided in these tables focus on the scalability of one particular feature at a time.

Each number is the absolute maximum that is currently supported by this Cisco NX-OS release for the corresponding feature. If the hardware is capable of a higher scale, future software releases could increase this verified maximum limit. Results might differ from the values that are listed in this guide when you try to achieve maximum scalability with multiple features enabled.



-
- Note**
1. If only one number is provided, the verified limit applies to all supported platforms and line cards.
 2. Verified limits are provided only for supported platforms.
 3. If a feature is not supported for a particular platform, the verified limit is not provided.
-



Note You can deploy up to 500 commands under config-profile.

Cisco Nexus 2000 Series Fabric Extenders (FEX) Straight Through Mode Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| Fabric Extenders ¹ and Fabric Extender server interfaces | Nexus 9300-FX/FX2/FX3 ² /GX switches | 16 and 768 |
| VLANs across all Fabric Extenders | Nexus 9300-FX/FX2/FX3 ² /GX switches | 562 |
| VLANs per Fabric Extender server interface ³ | Nexus 9300-FX/FX2/FX3 ² /GX switches | 75 |
| Port channels | Nexus 9300-FX/FX2/FX3 ² /GX switches + FEX | 511 |

¹ When FEX configured using "AA" mode, then the maximum number of 6 FEX on the NFE base ToR and 16 FEX for the LSE base ToR are supported.

² FEX is not supported on Nexus 9348GC-FX3, and 9348GC-FX3PH, 93108TC-FX3, 9332D-H2R, 93400LD-H1, 9364C-H1, and 92348GC-FX3 switches.

³ For FEX HIF port channels, Cisco recommends that you enable STP port type edge using the **spanning tree port type edge [trunk]** command.

ePBR Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|-----------------------------|------------------------------|------------------|
| Maximum services per switch | Nexus 9300 and 9500 switches | 150 ⁴ |
| Endpoints per service | Nexus 9300 and 9500 switches | 64 |

| Feature | Supported Platforms | Verified Limits |
|--------------------------|------------------------------|-----------------|
| ePBR policies per switch | Nexus 9300 and 9500 switches | 150 |
| Policies per VRF | Nexus 9300 and 9500 switches | 16 |
| Services per chain | Nexus 9300 and 9500 switches | 6 |
| Match per policy | Nexus 9300 and 9500 switches | 16 |
| Aces per match | Nexus 9300 and 9500 switches | 256 |

⁴ Only 62 unique ACLs can be configured per slice of ASIC. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62. In order to achieve 150 services per switch with the limitation of 62 ACLs per slice, the ingress interfaces should be spread across multiple slices of ASIC.



-
- Note**
1. For a list of platforms on which ePBR is supported, see the [Nexus Switch Platform Support Matrix](#).
 2. For the ACL limitations, see the [Cisco Nexus 9000 Series NX-OS Security Configuration Guide](#).
-

FC and FCoE Switch Level Configuration Limits

| Feature | Supported Platforms | Verified Limits |
|--|---|------------------|
| FLOGI per port | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 256 |
| FLOGI per switch | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 1000 |
| Port channels | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 8 ⁵ |
| Maximum number of member ports in a port channel | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 16 |
| NPV switches per NPIV core switch | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 8 ⁶ |
| Maximum number of FC ports supported | Nexus 93180YC-FX switches | 48 |
| | Nexus 93360YC-FX2 switches | 96 |
| | Nexus 9336C-FX2-E switches | 112 |
| VFCs | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 512 ⁷ |
| VSANs | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 32 |

- ⁵ The number of SAN port channels and virtual FC port channels, together, can be only 8 on the Cisco Nexus 9000 Series switch.
- ⁶ Tested with FC NPV.
- ⁷ This is applicable only for the NPV mode.

FC and FCoE Fabric Level Configuration Limits

| Feature | Supported Platforms | Verified Limits |
|------------------------------------|---|-----------------|
| Zones | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 8000 |
| Zone members | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 16,000 |
| Zone sets | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 32 |
| Zone database size | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 2 MB |
| FCNS entries in the fabric | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 10,000 |
| Device Alias | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 8000 |
| Switch hops from server to storage | Nexus 93180YC-FX, 93360YC-FX2, and 9336C-FX2-E switches | 7 |

Intelligent Traffic Director Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|-------------------------|--|------------------|
| Nodes per device group | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 64 |
| | Nexus X96136YC-R, X9636Q-R, X9636C-R, and X9636C-RX line cards | 16 |
| ITD services per switch | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 150 ⁸ |
| Buckets per ITD service | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 256 |
| | Nexus X96136YC-R, X9636Q-R, X9636C-R, and X9636C-RX line cards | 64 |

- ⁸ Only 62 unique ACLs can be configured per slice of ASIC. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62. In order to achieve 150 ITD services per switch with the limitation of 62 ACLs per slice, the ingress interfaces should be spread across multiple slices of ASIC.

**Note**

- For a list of platforms on which ITD is supported, see the *Cisco Nexus 9000 Series NX-OS Intelligent Traffic Director Configuration Guide*.
- For the ACL limitations, see the *Cisco Nexus 9000 Series NX-OS Security Configuration Guide*.

Interfaces Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| DHCP clients per switch | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 10 (IPv4) + 10 (IPv6) |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | |
| Flex link | Nexus 9300-FX/FX2 switches | 12 pairs One pair consists of one each of active and backup interface. The active and backup interface can be either a physical port or port channel. |
| IP DHCP relay addresses (helper addresses) per interface | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, Nexus 9808, 9364E-SG2-Q and 9364E-SG2-O switches | 32 (IPv4) + 32 (IPv6) |
| | Nexus 9164E-NS4-O switches | |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches | |
| | N9324C-SE1U and N9348Y2C6D-SE1U switches | |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | |
| Generic routing encapsulation (GRE) tunnels | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and 9804 switches | 16 |
| | Nexus X9716D-GX, Nexus X97160YC-EX, 9700-FX/FX3, Nexus X9836DM-A and X98900CD-A line cards | |
| LACP rate fast support during system switchover | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 606 ports in total with 16 line cards |

| Feature | Supported Platforms | Verified Limits |
|---|--|---|
| Port channel links | Nexus 9300-FX/FX2/FX3 ⁹ /GX2/H2R/H1, 9804, 9364E-SG2-Q and 9364E-SG2-O switches | 32 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches | |
| | N9324C-SE1U and N9348Y2C6D-SE1U switches | |
| | Nexus 9600-R, 9600-RX, X97160YC-EX, 9700-FX/FX3, Nexus X9836DM-A and X98900CD-A line cards | |
| Selective Q-in-Q with Multiprovider tag | Nexus 9300-FX/FX2/FX3/H2R/H1 switches | Per port: 4000 mappings, 10 provider VLANs; System wide: 48,000 mappings, 512 Provider VLANs |
| SVIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 1000 (with HSRP) 1000 HSRP groups |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches 10 | |
| | N9324C-SE1U and N9348Y2C6D-SE1U switches | |
| | Nexus 9300-FX3 switches | 510 |
| | Nexus 92348GC-FX3 switches | 128 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 1000 (with HSRP), 1500 (without HSRP) |
| | Nexus 9600-R and 9600-RX line cards | 3967 |
| Nexus X9636C-R, X9636Q-R, X9636C-RX and X96136YC-R line cards | 350 (with HSRP), 3967 (without HSRP) | |
| SVI Unnumbered | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | Primary (50); Secondary (450), 1 primary SVI can have a maximum of 50 secondary SVIs |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX line cards | |

| Feature | Supported Platforms | Verified Limits |
|---|--|---|
| vPCs | Nexus 9300-FX/FX3 ⁹ switches N9348Y2C6D-SE1U switches | 80 |
| | Nexus 9300-FX2 switches N9324C-SE1U switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches | 96 |
| | Nexus 92348GC-FX3 switches | 48 |
| | Nexus N9K-C9332D-H2R switches | 112 (breakout mode) ¹¹ 28 (non-breakout mode) |
| | Nexus N9K-C9364C-H1 switches | 60 (non-breakout port/ physical port) |
| | Nexus 9300-GX2, Nexus 9408 switches | 128 |
| | N9K-C9364D-GX2A switches | 250 ¹² |
| | Nexus 9300-GX switches | 60 (for flat Layer 2 Network) 56 (for L2/L3 Network) |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX line cards | 300 |
| | Nexus 9600-R/RX line cards | 255 |
| | Nexus X9636C-R, X9636Q-R, X9636C-RX and X96136YC-R line cards | 110 |
| | Static Network Address Translation (NAT) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches |
| Dynamic Network Address Translation (NAT) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | Non-Atomic mode: 1023 Atomic mode: 60% of Non-Atomic scale number is supported. |
| Static twice Network Address Translation (NAT) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | Non-Atomic mode: 580 Atomic mode: 60% of Non-Atomic scale number is supported. |
| Dynamic twice Network Address Translation (NAT) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | Non-Atomic mode: 875 Atomic mode: 60% of Non-Atomic scale number is supported. |

| Feature | Supported Platforms | Verified Limits |
|---|--|--|
| Sub-interfaces | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 3900 Note It is recommended to configure 60% of the mentioned limits with higher route scale deployments. |
| | Nexus 92348GC-FX3 switches | 128 |
| | Nexus 9300-FX and 9300C switches | 1900 Note It is recommended to configure 60% of the mentioned limits with higher route scale deployments. |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| | Nexus 9808/9804 switches | 2000 |
| | Nexus X9836DM-A and X98900CD-A line cards | |
| Port VLAN translations under an interface | Nexus 9300-FX/FX2/FX3 ⁹ /GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 3967 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 100 |
| Port VLAN translations in a switch | Nexus 9300-FX/FX2/FX3 ⁹ /GX/GX2/H2R/H1, Nexus 9408 switches | 24,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 2000 |

⁹ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Interfaces Configuration Guide, Release 10.4\(x\)](#).

¹⁰ For Nexus 9300-SE1 switches, of the total Router MAC scale, the number of unique 32 bit MSBs allowed for user-defined MAC addresses is 11.

¹¹ The scale of vPC on the N9K-C9332D-H2R switch has been tested in breakout mode (4x25G) across 28 physical ports.

¹² The total number of available links are 256. When scaling, ensure that uplinks and MCT links are planned accordingly to avoid exceeding this limit.



Note

- The scale for vPC convergence is tested with an LACP supported device connected to the vPC pair link.
- For **interface port-channel** configuration, LACP vPC convergence must be enabled. For more details, see the **Configuring vPCs** section of the *Cisco Nexus 9000 Series NX-OS Interfaces Configuration Guide*.
- For **vPC domain** configuration, the tested time for the delay restore is 150 seconds, the delay restore for interface VLAN is 150 seconds, and the delay restore for orphan ports is 140 seconds. For more details, see the **Configuring vPCs** section of the *Cisco Nexus 9000 Series NX-OS Interfaces Configuration Guide*.
- Above NAT scale numbers are supported provided that enough TCAM resources configured and allocated.

Label Switching Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--|--|---|
| Forwarding Equivalence Classes (FECs) (Node/Prefix/Adj/Binding SID) | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2 switches | MPLS Heavy Template: 4096 Default Template: 1024 |
| | Nexus 9332D-H2R, 9300-H1 switches | Default Template: 1024 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | MPLS Heavy Template: 4096 Default Template: 1024 |
| | Nexus 9600-R and 9600-RX line cards | 1000 |
| Equal-cost multipaths (ECMPs) | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 32 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 32 |
| | Nexus 9600-R and 9600-RX line cards | 8 - way |

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| Equal-cost multipaths Groups (ECMPs) | Nexus 9300-FX2/FX3 ¹³ switches | MPLS Heavy Template: 12,288 (with 4-way ECMP) and 4096 (with 8-way ECMP) Default: 1024 Note After the ECMP objects are exhausted, there is a fallback to the adjacency for all further routes. |
| | Nexus 9300-FX/GX/GX2 switches | MPLS Heavy Template and Default Routing Mode: 12,288 (with a 4-way ECMP) and 4096 (with 8-way ECMP) Note After the ECMP objects are exhausted, there is a fallback to the adjacency for all further routes. |
| | Nexus 9332D-H2R/H1 switches | MPLS Heavy Template: 12,288 (with 4-way ECMP) |
| | Nexus 9600-RX line cards | 24,000 ECMP Groups 2 paths per ECMP Note Supported only on Cisco NX-OS Release 9.2(4). |
| FECs * ECMPs | Nexus 9600-R and 9600-RX line cards | 8000 |
| Flex counters for segment-routing in ingress direction | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 and 9300C switches | Total ingress label stats: 4000; VRF ingress label stats: 1000; (MPLS Heavy Template) |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | Total ingress label stats: 4000; VRF ingress label stats: 1000; (MPLS Heavy Template) |
| Flex counters for segment-routing in Egress direction | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 and 9300C switches | Total ingress label stats: 48,000 (MPLS Heavy Template) |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | Total ingress label stats: 48,000 (MPLS Heavy Template) |
| Egress Peer Engineering | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 and 9300C switches | 64 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 64 |
| IAS option B labels | Nexus 9600-R and 9600-RX line cards | 450,000 |

| Feature | Supported Platforms | Verified Limits |
|--|--|---|
| Label-switched paths (LSPs) for label stack imposition ¹⁴ | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 256 (with 32 - way ECMP and 5 label stack push) |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 256 (with 32 - way ECMP and 5 label stack push) |
| Layer 3 VPN routes | Nexus 9300-GX2/H2R/H1 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches Nexus N9K-X9736C-FX3 line cards | 400,000 (IPv4 routes) 90,000 (IPv6 routes) |
| | Nexus 9600-R and 9600-RX line cards | 450,000 |
| Layer 3 EVPN Labels | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 1000 (With MPLS Heavy Template) |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 (With MPLS Heavy Template) |
| LDP session | Nexus 9600-R and 9600-RX line cards ¹⁵ | 200 |
| Node Sid/Prefix SID | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 4000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 4000 |
| Adjacency SID | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 112 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 112 |
| Binding SID | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| SRTE Policy | | |

| Feature | Supported Platforms | Verified Limits |
|---|---|--|
| SRTE policy with PBR | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2 switches | 512 per slice with 4 way ECMP/1024 per slice with 2 way ECMP |
| | Nexus 9332D-H2R/H1 switches | 512 |
| | Nexus N9K-X9736C-FX3 line cards | 512 |
| Number of route-maps with SRTE policy (IPv4/IPv6) | Nexus 9300-FX/FX2/FX3 ¹³ /GX/GX2/H2R/H1 switches | 256 (IPv4) + 256 (IPv6) per slice with 4 way ECMP |
| | and N9K-X9736C-FX3 line cards | 256 (IPv4) + 256 (IPv6) per slice with 4 way ECMP |
| Hierarchical ECMP 16 | | |
| Node SID | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 4000 |
| Adjacency SID | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8 |
| VRF | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| VPN label | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |

| Feature | Supported Platforms | Verified Limits |
|----------------------|---|-----------------|
| Level 1 ECMP groups | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 12 |
| Level 2 ECMP groups | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 10 |
| Level 2 ECMP members | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8 |
| VPN decap statistics | Cisco N9K-C9804 switches and N9K-C9804-FM-A Modular switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 VRF |

¹³ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Label Switching Configuration Guide Release 10.4\(x\)](#).

¹⁴ For Cisco Nexus 9300 and 9500 Series switches, LSPs *ECMP* label stack push cannot exceed 1500.

¹⁵ Nexus X9636C-RX, X9636C-R, X9636Q-R, and 96136YC-R

¹⁶ Hierarchical ECMP provides enhanced ECMP scale and convergence, with two level route resolution.



Note For network scalability, Cisco recommends using a hierarchical routing design with multi-hop BGP for advertising the attached prefixes from a top-of-rack (ToR) or border leaf switch.

ECMP group creation will be limited if the next-hop adjacency space is exhausted.

Private VLANs (PVLANS) Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--|---|-----------------|
| Primary VLANs Note The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port. | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 400 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 16 |
| Secondary VLANs Note The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port. | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 400 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 20 |
| Ports in Community host mode | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 40 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | |
| Ports in isolated host mode | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 40 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | |
| Ports in isolated trunk host mode | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 40 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | |
| Ports in promiscuous mode | Nexus 9300-FX switches | 10 |
| | Nexus 9300-FX2/FX3/GX/H2R/H1 switches | 5 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 5 |
| Ports in promiscuous trunk mode | Nexus 9300-FX switches | 10 |
| | Nexus 9300-FX2/FX3/GX/H2R/H1 switches | 5 |
| | Nexus -X9716D-GX, and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 5 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| PVLANS allowed on a PVLAN port Note The 400 PVLAN-mapping scale per PVLAN port is only applicable when port is configured as promiscuous trunk port. | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | 400 |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 16 |

Layer 2 Switching Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--------------------------------------|---|--|
| MAC addresses | Nexus 9300-FX/FX2/FX3 ¹⁷ /GX/GX2/H2R/H1, Nexus 92348GC-FX3 and Nexus 9408 switches | 92,000 (default system routing mode) |
| | Nexus 9300-FX/FX2/FX3 ¹⁷ /GX/GX2/H2R/H1 and Nexus 9408 switches | 200,000 (system routing mode L2-heavy) 18 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 8,000 (including control plane MACs) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 120,000 (including control plane MACs) |
| | Nexus X9716D-GX and Nexus X97160YC-EX, 9700-FX/FX3 line cards | 92,000 |
| | Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 120,000 |
| | Nexus 9600-R and 9600-RX line cards | 192,000 |
| MST PV count with single instances 0 | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 190,000 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| MST instances | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408, Nexus 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 64 |
| | Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 64 |
| | Nexus 9600-R, 9600-RX, Nexus X9716D-GX, and X97160YC-EX, 9700-FX/FX3 line cards | 64 |
| MST virtual ports with more than 1 MST instance | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches | 48,000 |
| | Nexus X9716D-GX and X97160YC-EX, 9700-FX/FX3 line cards | 85,000 |
| | Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 150,000 |
| | Nexus 9600-R and 9600-RX line cards | 236,000 |
| RPVST virtual ports (physical ports * VLANs) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 48,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 5000 |
| | Nexus X9716D-GX and X97160YC-EX, 9700-FX/FX3 line cards | 65,000 |
| | Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 150,000 |
| | Nexus 9600-R and 9600-RX line cards | 13,750 |

| Feature | Supported Platforms | Verified Limits |
|---|---|---|
| RPVST logical ports (logical ports * VLANs) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 22,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 1200 |
| | Nexus X9716D-GX and X97160YC-EX, 9700-FX/FX3 line cards | 45,000 |
| | Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 33,000 |
| | Nexus 9600-R and 9600-RX line cards | 13,750 |
| VLANs in MST mode | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 3967 (the remaining 127 VLANs are reserved) |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 |
| | Nexus X9716D-GX, 9600-R/RX, and X97160YC-EX, 9700-FX/FX3 line cards Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 3967 (the remaining 127 VLANs are reserved) |

| Feature | Supported Platforms | Verified Limits |
|---|---|--------------------|
| VLANs in RPVST mode | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3 and Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 3967 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards Nexus N9K-X9836DM-A, N9K-X98900CD-A line cards | 3967 ¹⁹ |
| | Nexus 9600-R2 line cards | 123 |
| | Nexus 9600-R and 9600-RX line cards | 250 |
| Total number of VLANs × ports with switch port isolated (3967 VLANs x 48 ports) ²⁰ | Nexus 9300-FX/FX2/FX3 ¹⁷ /GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 190,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3, and Nexus X9716D-GX line cards | 190,000 |
| Total number of VLANs × ports with switch port isolated (3967 VLANs x 144 ports) | Nexus X9636C-R, X9636Q-R, X9636C-RX, and X96136YC-R line cards | 571,248 |

¹⁷ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Layer 2 Switching Configuration Guide, Release 10.4\(x\)](#).

¹⁸ Layer 2 unidimensional scale only. SVI, Layer 3 interface, and VXLAN VLANs are not supported. 200K MAC is enabled only when " system routing template-l2-heavy" is configured and the system is reloaded.

¹⁹ On EOR, support is for 12,000 PV count with 3967 vlans and RPVST with default timers. If 22,000 PV count is needed with 3968 vlans and RPVST, recommended hello timer value is 4 or higher. It is also recommended to tune forward delay and max age accordingly.

²⁰ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Layer 2 Switching Configuration Guide, Release 10.4\(x\)](#).

**Note**

- For more information on STP scale considerations, see [Spanning Tree Protocol scale considerations, on page 94](#) section.
- The number of supported VLANs per vPC should be within the MST or RPVST virtual port count that is specified in this table, depending on the topology.
- The number of supported STP VLAN port instances, for Fabric Extender host interface ports, should be less than 13000.
- The ports with switch port isolated are only supported on Layer 2 ports. However, on Layer 2 the following port types are not supported:
 - FEX host interfaces
 - FEX host interface port channels
 - PVLAN ports

Multicast Routing Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|-----------------------------------|--|-----------------|
| Egress NAT | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 2000 |
| Ingress NAT | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 2000 |
| Egress and Ingress NAT | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 2000 |
| Unicast to Multicast NAT (UM NAT) | Nexus 9300-FX/FX2 switches | 1760 |
| | Nexus 9300-FX3/GX/GX2/H2R/H1 switches | 2000 |

| Feature | Supported Platforms | Verified Limits |
|---|---|--|
| Note The limits are for a combination of IPv4 and IPv6 multicast routes. Layer 2 multicast entries are a part of the total 120K limits. For example, 110K IPv4 + 2K IPv6 multicast routes + 8K Layer 2 multicast entries. | Nexus 9348GC-FXP switches | 8192 (Layer 2 + Layer 3) |
| | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 | 32,768 (Layer 2 + Layer 3 with system routing template - default, multicast-heavy mode); 131,072 (with system routing template - multicast - ext - heavy mode) |
| | Nexus 9300-FX2 switches | 8192 (Layer 2 + Layer 3); 32,768 (Layer 2 + Layer 3 with system routing template -multicast-heavy mode); 131,072 (with system routing template -multicast - ext - heavy mode) |
| | Nexus 9408 switches | 8192 (Layer 2 + Layer 3); 32,768 (Layer 2 + Layer 3 with system routing template - multicast-heavy mode); 131,072 (with system routing template - multicast - ext - heavy mode) |
| | Nexus 9800 switches | 131,072 (with system routing template - multicast - ext - heavy mode) Note Only Layer 3 multicast is supported. Layer 2 multicast is not supported. |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 131,072 (Layer 2 + Layer 3 with system routing template -multicast -ext - heavy mode) |
| | Nexus N9K-X97160YC-EX line cards | 8192 (Layer 2 + Layer 3); 32,768 (Layer 2 + Layer 3 with system routing template - multicast-heavy mode); 8192 (with system routing template - lpm - heavy mode) |
| | Nexus 9700-FX/FX3 line cards | 8192 (Layer 2 + Layer 3); 32,768 (Layer 2 + Layer 3 with system routing template - multicast-heavy mode); 131,072 (with system routing template - multicast - ext - heavy mode) 21 |
| | Nexus X9716D-GX line card | 131,072 (65,536 *,G + 65,536 S,G) |
| | Nexus 9600-R and 9600-line cards | 32,768 (Layer 3) |

| Feature | Supported Platforms | Verified Limits |
|-----------------------|---|--|
| MLD snooping groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 8192 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8192 |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX/FX3 line cards | 8192 |
| IPv6 multicast routes | Nexus 9300-FX, and 9500 switches | 8192 (Layer 3 with system routing template - default, multicast - heavy, multicast - ext - heavy and multicast - heavy, multicast - ext - heavy, dual - stack - multicast) |
| | Nexus 9348GC-FXP switches | 8192 (Layer 2 + Layer 3 with system routing template - multicast - heavy - multicast - ext - heavy mode) |
| | Nexus 9300-FX2 switches | 8192 (Layer 3 with system routing template - multicast - heavy mode) |
| | Nexus 9300-FX3 switches | 8192 (4096 - *, G + 4096 - S,G) |
| | Nexus 9300-GX/GX2/H2R/H1, Nexus 92348GC-FX3, Nexus 9408 switches | 8192 |
| | Nexus 9800 switches | 8192 (Layer 3) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8192 (Layer 2 + Layer 3) |
| | Nexus X9716D-GX/FX3 line card | 8192 (4096 - *, G + 4096 - S,G) |
| Multicast FPV | Nexus 9300-FX/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | IPv4 32,000 (Layer 2 + Layer 3) multicast routes |
| | Nexus 9300-FX2 switches | 8000 (with system routing template - default), 32,000 (with system routing template - multicast-heavy - multicast - ext - heavy mode) |

| Feature | Supported Platforms | Verified Limits |
|----------------------------|--|--|
| Outgoing interfaces (OIFs) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 40 (SVI + physical Layer 3) or 256 (physical Layer 3) |
| | Nexus 9808 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 256 (physical Layer 3) |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX/FX3 line cards | 40 (SVI + physical Layer 3) or 256 (physical Layer 3) |
| | Nexus 9600-R and 9600-RX line cards | 16 OIFs for 32K mroutes or 287 OIFs for 1000 mroutes |
| IGMP snooping groups | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 32,000 (with default template, multicast-heavy template, and multicast-ext-heavy template 22) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 16,000 |
| | Nexus 9300-FX2 switches | 8000 (with system routing template - default), 32,000 (Multicast-heavy, Multicast-ext-heavy templates) |
| | Nexus 92348GC-FX3 switches | 8000 |
| | Nexus 9700-FX line cards | 8000 (with system routing template - default), 16000 (with system routing template - multicast - heavy - multicast - ext - heavy mode) |
| | Nexus X9716D-GX line card | 16,000 |
| | Nexus 9600-R, 9600-RX, and 9600-R2 line cards | 8000 |
| PIM neighbors | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3 switches | 250 |
| | Nexus 9808 switches | 500 |
| | Nexus 9600-R, 9600-RX, X97160YC-EX and 9700-FX/FX3 line cards | 500 |

| Feature | Supported Platforms | Verified Limits |
|---|--|---|
| PIM Bidir IPv6 | Nexus 9300-FX2 | 2048 with default template (Maximum number of IPv6 bidirectional multicast routes) |
| | Nexus 9300-FX/FX3/GX/GX2/HX switches Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 8192 with default template (Maximum number of IPv6 bidirectional multicast routes) |
| | Nexus 9300-FX/FX2/FX3/GX/GX2/HX switches and Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 8192 with multicast-heavy and multicast-ext-heavy templates (Maximum number of IPv6 bidirectional multicast routes) |
| | Nexus 9300-FX/FX2/FX3/GX/GX2/HX switches and Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 64 (Maximum number of /m (prefix) IPv6 bidirectional routes) |
| | Nexus 9300-FX/FX2/FX3/GX/GX2/HX switches and Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 8 (Maximum number of rendezvous points) |
| MVPN - unidimensional | | |
| Multicast VRFs | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 300 |
| Default MDT groups | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 300 |
| MVPN Peers (PIM neighbors) per device | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 900 |
| Maximum number of PEs per VRF | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 200 PEs per VRF with up to 3 VRFs (600 PIM neighbors) |
| Maximum number of Data MDT groups per VRF on a PE | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 1000 |
| Maximum number of Data MDT groups across all VRFs on a PE | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 10,000 |
| Maximum number of MDT groups across all VRFs on PE | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 10,300 (10,000 Data + 300 default DMT) |
| Maximum number of Multicast routes on a PE node | Nexus 9600-R and 9600-RX line cards (except the Nexus X96136YC-R line card) | 32,000 |

²¹ All line cards must have the FX type.

²² The 32,000 IGMPv3 (S,G) snooping entries are supported only with the multicast-ext-heavy template.



- Note**
- The IPv4 multicast routes and the IPv4/IPv6 host routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
 - High availability (graceful restart and stateful switchover) is not supported when unicast or multicast aggressive timers are configured at any scale.
 - The hash table is subject to collisions. Depending on the host route pattern, collisions might occur with an expected hashing efficiency of about 80%.

IP Fabric for Media Solution Verified Scalability Limits

| Description | Verified Limit | | | |
|--|----------------------|-----------------------|----------------|-----------------|
| | NBM-Active Mode Only | NBM-Passive Mode Only | Mixed Mode | |
| | | | NBM-Active VRF | NBM-Passive VRF |
| Switches | 120 | 32 | 32 | |
| Number of flows | 32000 | 32000 | 32000 | |
| VRFs | 16 | 16 | 16 | |
| Host Policy - Sender | 16000 | N/A | 16000 | N/A |
| Host Policy - Receiver | 16000 | N/A | 16000 | N/A |
| Host Policy - PIM | 2000 | N/A | 2000 | N/A |
| Flow Policy | 32000 | N/A | 32000 | N/A |
| ASM group-range | 20 | N/A | 20 | N/A |
| NBM Static Receiver | | | | |
| Per Switch Maximum (receiver leaf where the static OIF will be programmed) | 1500 | 8000 | 1500 | |
| Per Fabric Maximum | 8000 | 32000 | 8000 | |
| NBM IGMP Receivers | | | | |
| Per Switch Maximum | 8000 | N/A | 8000 | N/A |
| Per Fabric Maximum | 24000 | N/A | 24000 | N/A |
| NBM NAT Flows | | | | |
| Egress-NAT (E-NAT) | 2000 | 2000 | 1000 | 1000 |
| Ingress-NAT (I-NAT) | 2000 | 2000 | 1000 | 1000 |

| Description | Verified Limit | | | |
|--|--|-----------------------|----------------|-----------------|
| | NBM-Active Mode Only | NBM-Passive Mode Only | Mixed Mode | |
| | | | NBM-Active VRF | NBM-Passive VRF |
| Multicast-Unicast NAT (MU-NAT) | 2000 | 2000 | 1000 | 1000 |
| Unicast-Multicast NAT (UM-NAT) | 2000 | 2000 | 1000 | 1000 |
| Mixed Mode (E-NAT, I-NAT, MU-NAT, UM-NAT together) | 2000 | 2000 | 1000 | 1000 |
| RTP Flow Monitoring with ACL | | | | |
| ACL | 128 IPv4 ACL entries or 64 IPv6 ACL entries (total 128 TCAM spaces) | | | |
| | Note With combined IPv4 and IPv6 ACL entries, the scale limit cannot exceed 128 TCAM spaces. | | | |
| RTP Flow Loss Monitoring | | | | |
| Feature | Supported platforms | | | Verified limits |
| RTP flows | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | | | 24,000 |

IP Fabric for Media Solution Policer Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|----------------------------------|--|-----------------|
| NBM Flow Policers (Slice/System) | Nexus 9300-FX/FX3 switches | 1536/1536 |
| | Nexus 9300-FX2 switches | 1536/3072 |
| | Nexus 9348GC-FX3 switches | 1536/1536 |
| | Nexus 9300-GX/GX2B switches | 1536/6144 |
| | Nexus 9300-GX2A switches | 1536/12288 |
| | Nexus 9332D-H2R switches | 1536/6144 |
| | Nexus 93400LD-H1, and 9364C-H1 switches | 1536/3072 |
| | Nexus 9336C-SE1 switches N9324C-SE1U switches | 1792/3584 |
| | Nexus X9636C-R line cards | 2048/12288 |
| | Nexus X9636Q-R line cards | 2048/6144 |
| | Nexus X9636C-RX line cards | 2048/8192 |
| | Nexus X9624D-R2 line cards | 2048/8192 |
| | Nexus X9836DM-A line cards | 700/6300 |
| | Nexus X98900CD-A line cards | 700/4200 |



Note When storm control is enabled on Nexus 9300-FX3/GX/GX2/H2R/H1 Platform Series switches, the maximum supported scale for NBM flow policers is limited to 1534.

For a list of supported platforms, see [Cisco Nexus 9000 Series NX-OS IP Fabric for Media Solution Guide](#).

Programmability Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|------------------|--|-----------------------------|
| gNMI | | |
| VRF - Default | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | 16 concurrent subscriptions |
| VRF - Management | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | 16 concurrent subscriptions |

| Feature | Supported Platforms | Verified Limits |
|---|--|--|
| VRF - Default and Management | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | 32 concurrent subscriptions |
| Paths | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | 48 paths in a single subscription |
| Message size | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | Less than 12 MB |
| Aggregate MO's | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R switches and Nexus 9700-FX line cards | 150,000 |
| NX-API | | |
| See Guidelines and Limitations for NX-API limitations. | | |
| Maximum Number of concurrent VSH session | Nexus 9000 switches and line cards | 5 concurrent VSH sessions and 5 persistent VSH sessions per worker process. |
| Number of worker processes in Nginx | Nexus 9000 switches and line cards | 4 worker processes |
| Number of VSH sessions per worker process | Nexus 9000 switches and line cards | A maximum of 5 persistent VSH sessions are supported for each worker process |
| Maximum response size supported in output | Nexus 9000 switches and line cards | 10 MB |
| Maximum number of concurrent session supported for chunk mode. See Configuring the Message Format and Command Type to know more about chunk mode | Nexus 9000 switches and line cards | 2 |
| Maximum size of response supported in chunk mode | Nexus 9000 switches and line cards | After 10.3(1) release, the maximum size supported in chunk mode is the same as the amount of space available in volatile. |
| DME | | |
| Note | | |
| <ul style="list-style-type: none"> • If all the DME features are configured together, it may cause performance issues. • Model to CLI Conversion of payload is not supported. | | |
| Telemetry | Nexus 9000 switches and line cards | Telemetry data can be streamed to 4 receivers in parallel |
| Hardware Telemetry (SSX) | | |
| SSX | N9K-X9736C-FX3 line cards | <ul style="list-style-type: none"> • Number of records: 24 • Number of exporters: 24 • Number of monitors: 24 |

QoS Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|---------------------------|---|---|
| Class maps per policy map | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, Nexus 9408, Nexus 9808/9804, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches Nexus 9164E-NS4-O switches | 128 |
| AFD | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, and Nexus 9408 switches | 30 profiles |
| WRED | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, and Nexus 9408 switches | 30 profiles |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9164E-NS4-O switches | 10 Profiles |
| | Nexus 9808/9804 switches | 14 Profiles |
| Ingress 1R2C | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, Nexus 9408, and Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | 1280 per ASIC |
| Ingress | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | <ul style="list-style-type: none"> • 6300 Policer / LC – PMN use case • QoS on physical or SI – Limited by 128 unique ACLs / ASIC |
| Egress 1R2C | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, and Nexus 9408 switches | 256 |
| Ingress 2R3C | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, and Nexus 9408 switches | 766 |
| Total policy maps | Nexus 9300-GX/GX2/FX2/FX3 ²³ /H2R/H1, Nexus 9408, Nexus 9808/9804, 9364E-SG2-Q and 9364E-SG2-O switches | 4000 |
| | Nexus 9164E-NS4-O switches | 128 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 127 |

| Feature | Supported Platforms | Verified Limits |
|---------------------------|---|-----------------|
| QoS unique burst profiles | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | 4/ASIC |
| TCAM label | Nexus 9300-FX3 ²³ switches | 64 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 14 |
| | Nexus 9164E-NS4-O switches | |

²³ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Quality of Service Configuration Guide, Release 10.4\(x\)](#).

Security Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|-------------|--|---|
| Egress ACLs | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | <ul style="list-style-type: none"> • 1022 per slice for IPv4 • 511 per slice for IPv6 |
| | Nexus 9600-R line cards | 20,000 |
| System ACLs | Nexus 9600-R line cards | 4000 TCAM entries in internal TCAM 64,000 TCAM entries in external TCAM |

| Feature | Supported Platforms | Verified Limits |
|---------|--|---|
| ACL | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | IPv4 Ingress - 3584 IPv6 Ingress - 1792 |
| | Nexus 9332D-H2R switches | Total TCAM region size is 14,336 (Default TCAM carving: 10,240 Ingress and 4096 Egress) <ul style="list-style-type: none"> • 4 slice with 8 interface • 510 Ingress - RACL per slice • 254 Egress - RACL per slice • 30 PACL and Egress PACL per slice Note The maximum TCAM region size that can be carved as ingress or egress is 13056, as ing-sup/egr-sup cannot be carved size=0. |
| | Nexus 93400LD-H1 and 9364C-H1 switches | Total TCAM region size is 14,336 (Default TCAM carving: 10,240 Ingress and 4096 Egress) 2 Slices 0 and 1 Slice 1: interface 1-32 Slice 0: interface 33-52 <ul style="list-style-type: none"> • 510 Ingress - RACL per slice • 254 Egress - RACL per slice • 30 PACL and Egress PACL per slice Optionally, you can carve a flexible TCAM region. However, you can carve it as either ingress or egress only, with a maximum size of 13568. |
| | Nexus 9336C-SE1 switches | |

| Feature | Supported Platforms | Verified Limits |
|---------|---|---|
| | | <ul style="list-style-type: none"> • Ingress RACLv4 - 7168 per slice • Ingress RACLv6 - 3584 per slice • Egress RACLv4 - 7168 per slice • Egress RACLv6 - 3584 per slice • 126 Unique labels Ingress IPv4 per ASIC • 126 Unique labels Ingress IPv6 per ASIC • 14 Unique labels for Egress IPv4 per ASIC • 14 Unique labels for Egress IPv6 per ASIC |
| | <p>Nexus 9396Y12C-SE1, 9396T12C-SE1 switches</p> <p>N9324C-SE1U, N9348Y2C6D-SE1U switches</p> | <ul style="list-style-type: none"> • Ingress RACLv4 - 7168 Access Control Entries (ACE) per slice • Ingress RACLv6 - 3584 ACE per slice • Egress RACLv4 - 7168 ACE per slice • Egress RACLv6 - 3584 ACE per slice • Ingress PACLv4 - 7168 ACE per slice • Ingress PACLv6 - 3584 ACE per slice • Ingress SVI RACLv4 - 7168 ACE per slice • Ingress SVI RACLv6 - 3584 ACE per slice • Egress SVI RACLv4 - 7168 ACE per slice • Egress SVI RACLv6 - 3584 ACE per slice |
| | Nexus 9164E-NS4-O switches | |

| Feature | Supported Platforms | Verified Limits |
|---------|---|---|
| | | <p>There is no slice concept in this switch and the following are system scales.</p> <p>The switch provides 1536 TCAM entries each for IPv4 ACL, IPv6 ACL, QoS IPv4 ACL, and QoS IPv6 ACL, for a total capacity of 6144 entries.</p> <p>Supported only ingress RACL and ingress QOS for both IPv4 and IPv6</p> <ul style="list-style-type: none"> • Ingress RACL IPv4 = 1536 • Ingress RACL IPv6 = 1536 • Ingress QOS IPv4 = 1536 • Ingress QOS IPv6 = 1536 • Total TCAM spaces = 6144 |
| | Nexus 9348Y12C-SE1 switches | <ul style="list-style-type: none"> • Ingress PACLv4 - 14,336 ACE per slice • Ingress PACLv6 - 7168 ACE per slice • Ingress RACLv4 - 14,336 ACE per slice • Ingress RACLv6 - 7168 ACE per slice • Egress RACLv4 - 7168 ACE per slice • Egress RACLv6 - 3584 ACE per slice • Ingress SVI RACLv4 - 7168 ACE per slice • Ingress SVI RACLv6 - 3584 ACE per slice |
| | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | |

| Feature | Supported Platforms | Verified Limits |
|-----------------------|--------------------------------|--|
| | | <ul style="list-style-type: none"> • Ingress RACLv4 - 14,336 per slice • Ingress RACLv6 - 7168 per slice • Egress RACLv4 - 9216 per slice • Egress RACLv6 - 4608 per slice • RACL on physical or sub-interfaces – Limited by 128 unique ACLs / ASIC • 126 Unique labels Ingress IPv4 per ASIC • 126 Unique labels Ingress IPv6 per ASIC • 14 Unique labels for Egress IPv4 per ASIC • 14 Unique labels for Egress IPv6 per ASIC • Ingress ACL Group (QOS + RACL) 252 per ASIC • Egress ACL Group (RACL) 60 per ASIC |
| | Nexus N9K-X9736C-FX3 line card | <p>Line card has 4 instances with 9 port per instance</p> <ul style="list-style-type: none"> • Default TCAM carving: 4096 ingress and 2048 Egress • 62 Unique labels Ingress RACL per instance • 254 Unique labels Egress RACL per instance • 30 Unique labels Ingress PACL per instance • Egress PACL : Not supported |
| RACL Labels (maximum) | Nexus 9504 and 9508 switches | 4000 |

| Feature | Supported Platforms | Verified Limits |
|--|--|--|
| ACL Labels | Nexus 9396Y12C-SE1, 9396T12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | <ul style="list-style-type: none"> • Ingress IPv4 - 126 unique labels • Ingress IPv6 - 126 unique labels • Egress IPv4 - 14 unique labels • Egress IPv6 - 14 unique labels |
| | Nexus 9164E-NS4-O switches | <ul style="list-style-type: none"> • Ingress IPv4 - 14 unique labels • Ingress IPv6 - 14 unique labels |
| | Nexus 9348Y12C-SE1 switches | <ul style="list-style-type: none"> • RACL/PACL Ingress IPv4 -124 unique labels • RACL Egress IPv4 - 14 unique labels |
| ACL LOU Threshold Support | Nexus 9500-R line cards | 24 LOUs per line card |
| IPv4 ingress access control entries (ACEs) | Nexus 9600-R and 9600-RX line cards | <ul style="list-style-type: none"> • RACL on LC Nexus X9636C-RX: 100,000 • PACL on LC Nexus X9636C-RX: 12,000 • RACL-2048, PACL-1024 (without TCAM Carving) IPv4 52,640 ACEs per system • PACL IPv4: 1024 TCAM entries in internal TCAM • PACL MAC: 2048 TCAM entries in internal TCAM • RACL IPv4: 2048 TCAM entries in internal TCAM |
| IPv6 ingress access control entries (ACEs) | Nexus 9600-R and 9600-RX line cards | <ul style="list-style-type: none"> • RACL-1024, PACL-1024 (without TCAM Carving) IPv6 25,200 ACEs per system • PACL IPv6: 1024 TCAM entries in internal TCAM • RACL IPv6: 1024 TCAM entries in internal TCAM |

| Feature | Supported Platforms | Verified Limits |
|-------------------------------|---|---|
| IPv4 ingress TCAM entries | Nexus 9300-FX/FX2/FX3 ²⁴ switches | 3582 (per slice of the forwarding engine) |
| | Nexus 9300-GX/GX2 switches | 4608 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 1450 (per slice of the forwarding engine) |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX line cards | 3582 (per slice of the forwarding engine) |
| IPv4 egress TCAM entries | Nexus 9300-FX/FX2/FX3 ²⁴ /GX/GX2 switches | 1792 (per slice of the forwarding engine) |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 1022 (per slice of the forwarding engine) |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX line cards | 1792 (per slice of the forwarding engine) |
| IPv6 ingress TCAM entries | Nexus 9300-FX/FX2/FX3 ²⁴ /GX/GX2 switches | 1792 (per slice of the forwarding engine) |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 725 (per slice of the forwarding engine) |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX line cards | 1792 (per slice of the forwarding engine) |
| IPv6 egress TCAM entries | Nexus 9300-FX/FX2/FX3 ²⁴ /GX/GX2 switches | 896 (per slice of the forwarding engine) |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 511 (per slice of the forwarding engine) |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX line cards | 896 (per slice of the forwarding engine) |
| Ingress SUP IPv4 TCAM entries | Nexus 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 360 |

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| Ingress SUP IPv6 TCAM entries | Nexus 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 180 |
| Ingress QoSv4 | Nexus 9808 switches | 9216 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 1450 |
| | Nexus 9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | <ul style="list-style-type: none"> • Physical: 9000 per slice • Port-Channel: 5000 |
| Ingress SPAN filter v4 | Nexus 9808 switches | 9216 |
| | Nexus 9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | Physical: 14,000 per slice |
| Ingress QoSv6 | Nexus 9808 switches | 4608 ²⁵ |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 725 |
| | Nexus 9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | <ul style="list-style-type: none"> • Physical: 7000 per slice • Port-Channel: 2500 |
| Ingress SPAN filter v6 | Nexus 9808 switches | 4608 ²⁵ |
| | Nexus 9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | Physical: 7000 per slice |
| Number of unique ACLs each for RACLv4, RACLv6, QoS, ACL SPAN ²⁶ | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | <ul style="list-style-type: none"> • 127 (per unit) each for ingress and QoS • 15 (per unit) each for egress (IPv4 and IPv6 RACL) |

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| Number of unique ACL combinations | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | <ul style="list-style-type: none"> • 14 (per unit) for ingress label (IPv4 and IPv6) • 7 (per unit) for egress label (IPv4 and IPv6) |
| | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | <ul style="list-style-type: none"> • 252 (per unit) for ingress • 60 (per unit) for egress |
| DHCP snooping bindings | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 2048 |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX/FX3 line cards | 2048 |
| 802.1x | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 1024 hosts |
| Key Chain Keys Verified Scalability Limits (Unidimensional) | | |
| Type-6 Keys | Nexus 9000 Series switches | 5000 |
| Type 7 keys | Nexus 9000 Series switches | 20,000 |

²⁴ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS Security Configuration Guide, Release 10.4\(x\)](#).

²⁵ Each IPv6 ACL is limited to 1000 ACEs. This applies to all IPv6 ACLs (RACL, QoS or SPAN filter). No such limitation applies for IPv4 ACL.

²⁶ ACL SPAN is not supported on Nexus 9364E-SG2-Q and 9364E-SG2-O switches.



Note

- The TCAM entries scalability limits also apply to policy-based TCAM entries (PBACLs).
- Only 62 unique ACLs can be configured. Each ACL takes one label. If the same ACL is configured on multiple interfaces, the same label is shared. If each ACL has unique entries, the ACL labels are not shared, and the label limit is 62.

SRv6 Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--------------------------|---|-----------------|
| ARP | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 48,000 |
| Host and LPM IPv4 routes | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 470,000 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| Host and LPM IPv6 routes | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 256,000 |
| Leaf | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 256 |
| SID DB | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 2000 |
| SRv6 and VXLAN Peer | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 256 |
| VRF | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 1000 |
| ND | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 24,000 |
| SRv6 Traffic Engineering policies | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 1000 |
| Number of prefixes (IPv4 and IPv6) that use SRv6 Traffic Engineering policies | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 50,000 |
| Maximum number of preferences per policy | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 3 |
| Maximum number of segment lists | Nexus 9300-GX/GX2/H2R/H1, and Nexus 9408 switches | 3000 |

Egress NetFlow Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--|--|---|
| Flow monitors | Nexus 9300-FX/FX2/GX/GX2/H2R/H1 switches and 9500 with 9700-FX/GX line cards | 30 IPv4 flow monitor and each flow monitor with two exporters 28 IPv6 flow monitor and each flow monitor with two exporters 32 Layer 2 Flow monitor and each flow monitor with two exporters Maximum number of exporters supported per flow monitor is 2 |
| Maximum number of flows in the software table (IPv4 or CE flows) | Nexus 9000 switches | 100,000 flows using the show flow cache command on 9500 modular chassis per line card 1,000,000 flows (1 Million) using the show flow cache command on 9300 switches |

System Management Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|---------|---------------------|-----------------|
| PTP | | |

| Feature | Supported Platforms | Verified Limits |
|---------------------|---|---|
| PTP ports | Nexus 9300-FX/GX, and 9364C-H1 switches | 64 per system |
| | Nexus 93180YC-FX3 and 93180YC-FX3S switches | 68 per system Note Speed: Mixed Speed: 10G/25G/40G/100G - includes soft/physical break-out |
| | Nexus 93108TC-FX3 | 48 per system Note Speed: All 1G ports |
| | Nexus 93108TC-FX3P switches | 48 per system Note Speed: All 1G ports |
| | Nexus 9348GC-FX3 switches | 48 per system Note Speed: All 1G ports |
| | Nexus 9332D-H2R switches | 128 per system Note Speed: 4x100G - Only Soft break-out |
| | Nexus 9300-FX2/GX2 switches | 144 per system |
| | Nexus 93400LD-H1 switches | 60 per system Note Speed: 10G/25G/40G/100G - includes soft/physical break-out ; 50G - Only Soft-breakout |
| | Nexus 9808 switches | 64 per line card 512 per chassis |
| | Nexus 9336C-SE1 switches | 144 per system |
| | N9324C-SE1U switches | 96 per system |
| | N9348Y2C6D-SE1U switches | 80 per system |
| Nexus 9408 switches | 144 per system 32 per LEM | |

| Feature | Supported Platforms | Verified Limits |
|------------------------|---|---|
| | Nexus 9500 switches with X97160YC-EX, 9700-FX line cards | 1305 per chassis The per line card limit is based on the maximum physical ports supported. Note PTP Offload is supported on Nexus X97160YC-EX and 9700-FX line cards. |
| | Nexus 9508 switches with -R line cards | 64 per line card 300 per chassis Note PTP Offload is supported on 9508-R line cards. |
| | N9K-X9736C-FX3 line cards | 36 per line card Note PTP Offload is supported on N9K-X9736C-FX3 line cards. |
| | Nexus 9500 switches with 9600-RX line cards | 128 per line card 512 per chassis |
| PTP clients per port | Nexus 9300-FX/FX2/FX3 ²⁷ /GX/GX2, 9408 and 9808 switches Nexus 9500 switches with X97160YC-EX, 9700-FX, 9508-R and 9600-RX line cards | 4 |
| sFlow | | |
| sFlow ports | Nexus 9300-FX/FX2/GX/H1 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 64 |
| | Nexus 9300-FX3 ²⁷ switches | 30 |
| | Nexus X97160YC-EX, 9700-FX line cards | 256 |
| | Nexus X9716D-GX line card | 16 |
| SPAN and ERSPAN | | |

| Feature | Supported Platforms | Verified Limits |
|--------------------------------------|---|--|
| Configurable SPAN or ERSPAN sessions | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 32 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 4 Note Session ID 4 reserved for SOD (Span On Drop) |
| | Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards | 10 |
| | Nexus 9600-R, 9600-RX, Nexus X9716D-GX/FX/FX3 line cards | 32 |

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| Active SPAN or ERSPAN sessions ²⁸ | Nexus 9300-FX/FX2/FX3/GX/H2R/H1 switches | <p>4 sessions (per chassis/ToR or based on the number of the line cards in the EoR).</p> <p>Note If the source interface configured for a monitor session is on the same line card, the maximum supported active SPAN sessions are 4. Based on the number of line cards in the EoR, the total number of active SPAN sessions are 4 x n, where n is the number of line cards on EoR, provided the source and destination interface are on the same line module.</p> <p>Port-channels count against all linecards when considering 4 x n scale of SPAN sessions when configured as a SPAN source, regardless of port-channel member interfaces.</p> |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | <p>4</p> <p>Note Session ID 4 reserved for SOD (Span On Drop)</p> |
| | <p>Nexus 9808/9804 switches, and Nexus X9836DM-A and X98900CD-A line cards</p> <p>Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches</p> <p>N9324C-SE1U, N9348Y2C6D-SE1U switches</p> | 10 |
| | Nexus 9600-R, 9600-RX, X97160YC-EX and 9700-FX/GX/FX3 line cards | |

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| | | <p>4 sessions (per chassis/ToR or based on the number of the line cards in the EoR).</p> <p>Note If the source interface configured for a monitor session is on the same line card, the maximum supported active SPAN sessions are 4. Based on the number of line cards in the EoR, the total number of active SPAN sessions are 4 x n, where n is the number of line cards on EoR, provided the source and destination interface are on the same line module.</p> <p>Port-channels count against all linecards when considering 4 x n scale of SPAN sessions when configured as a SPAN source, regardless of port-channel member interfaces.</p> |
| Active localized SPAN or ERSPAN sessions per line card ²⁹ | Nexus 9300-FX/FX2/FX3 ²⁷ switches | 4 |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX/GX/FX3 line cards | 4 |
| | Nexus 9600-R and 9600-RX line cards | 32 sessions across ports on single-line card |
| Active localized SPAN or ERSPAN session (Rx and Tx, Rx, or Tx) | Nexus 9600-R and 9600-RX line cards | 32 sessions, 128 sources, and 1 destination |
| Source interfaces per SPAN or ERSPAN session (Rx and Tx, Rx, or Tx) | <p>Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9808/9804, 9364E-SG2-Q and 9364E-SG2-O switches</p> <p>Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches</p> <p>N9324C-SE1U, N9348Y2C6D-SE1U switches</p> | 48 |
| | Nexus X97160YC-EX, 9700-/FX/FX3, X9716D-GX, X9836DM-A and X98900CD-A line cards | 48 |

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| Destination interfaces per SPAN session | Nexus 9300-FX/FX2/FX3 ²⁷ /GX/GX2, 9364E-SG2-Q and 9364E-SG2-O switches | 1 (physical/PO interface) Note Destination as PO interface is not supported for Nexus X9716D-GX line card. |
| | Nexus 9808/9804 switches | 1 Physical only (no PO support). |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1 Physical only (no PO support). |
| | Nexus 9600-R, 9600-RX, X9716D-GX, X97160YC-EX, and 9700-FX/FX3 line cards | 1 (physical/PO interface) Note Destination as PO interface is not supported for Nexus X9716D-GX line card. |
| | Nexus X9836DM-A and X98900CD-A line cards | 1 Physical only (no PO support). |
| Source VLANs per SPAN or ERSPAN session | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 32 |
| | Nexus 9600-R, 9600-RX, X9716D-GX, X97160YC-EX, and 9700-FX/FX3 line cards | 32 |
| Tap Aggregation | | |
| Redirect interfaces in the redirect port list | Nexus 9300-FX/FX2/FX3/GX/H2R | 32 |
| | Nexus 93400LD-H1, and 9364C-H1 switches | 12 |
| | Nexus 9500 Merchant Silicon platform switches | 12 |
| | Nexus X9716D-GX/N9K-X9736C-FX3 line cards | 12 |
| Redirect port lists per system Note This denotes every unique redirect port list across ACLs/ACEs in the system | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 100 |

| Feature | Supported Platforms | Verified Limits |
|----------------------------------|---|---|
| Deduplication | Nexus 9300-GX/GX2B/FX3/H1 switches | 240,000 (maximum supported flows) |
| | Nexus 9300-FX2/GX2A switches | 120,000 (maximum supported flows) |
| NetFlow | | |
| Flow monitors 30 | Nexus 9300-FX/FX2/GX/GX2/FX3/H2R/H1 switches | 30 IPv4 flow monitor and each flow monitor with two exporters 28 IPv6 flow monitor and each flow monitor with two exporters 30 Layer 2 Flow monitor and each flow monitor with two exporters Maximum number of exporters supported per flow monitor is 2 |
| | Nexus N9364E-SG2-O and N9364E-SG2-Q switches | 2 flow monitors per type (2 IPv4 or 2 IPv6 or one IPv4 and one IPv6). 1,000,000 flows (1 Million) using the show flow cache command on switches 250 per slice for SVI |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 15 flow monitors per type (15 IPv4 flow monitors, 15 IPv6 flow monitors, and 15 flow monitor for CE flows) 1,000,000 flows (1 Million) using the show flow cache command on switches 1000 per slice for SVI |
| | Nexus 9500 switches with 9700-FX/GX line cards | 30 IPv4 flow monitor and each flow monitor with two exporters 28 IPv6 flow monitor and each flow monitor with two exporters 30 Layer 2 Flow monitor and each flow monitor with two exporters Maximum number of exporters supported per flow monitor is 2 |
| | Nexus 9500 switches with X97160YC-EX, and FM-E fabric line cards | 2 flow monitors per type (2 IPv4 flow monitors and 2 IPv6 flow monitors). 1 flow monitor for CE flows 2 exporters for each flow monitor. Hence, a total of 4 different exporters can be configured. |

| Feature | Supported Platforms | Verified Limits |
|--|---|--|
| Maximum number of flows in the software table (IPv4 or IPv6 or CE flows) | Nexus 9000 switches | 100,000 flows using the show flow cache command on 9500 modular chassis per line card 1,000,000 flows (1 Million) using the show flow cache command on switches |
| Maximum number of concurrent flows supported (IPv4 or IPv6 or CE flows) | Nexus 9300-FX/FX2 switches | 6000 traffic flows. By increasing LCPUG-SIZE using the following command one can achieve Max 18000 concurrent flows, after modifying LCPUG-SIZE, the switch needs reboot after saving configuration <pre>switch(config)# hardware qos lcpu-pg-size ? <200-10000> Pool Group size switch(config)# hard qos lcpu-pg-size 5000 Warning:Reload required for configured PG size to take effect. Save configuration and reload the system. switch(config)# copy running-config startup-config</pre> <p>In Cisco Nexus Release 9.3(3), the hardware qos command is not supported.</p> |
| | Nexus 9300-GX/GX2/FX3/H2R/H1 switches | 100,000 traffic flows |
| Netflow ingress VRF-id export support | Nexus 9300-FX/FX2/FX3 ²⁷ /GX/GX2/H1/H2R, Nexus 9300C and 9408 switches | 500 different VRFs |
| | Nexus 9500 switches with X97160YC-EX/FX/GX line cards | 500 different VRFs |
| Flow visibility in Nexus Dashboard Insights and NetFlow | | |
| Flow monitors | Nexus 9300-FX/FX2/GX/GX2, Nexus 9408 switches | 28 IPv4 flow monitor and each flow monitor with two exporters 26 IPv6 flow monitor and each flow monitor with two exporters |
| | 9500 switches with FX/GX line cards | 28 IPv4 flow monitor and each flow monitor with two exporters 26 IPv6 flow monitor and each flow monitor with two exporters |

| Feature | Supported Platforms | Verified Limits |
|--|--|--|
| Maximum number of flows in the software table (IPv4 or IPv6 flows) | Nexus 9000 switches | 20,000 flows using the show flow cache command |
| Traffic Analytics | | |
| Netflow Monitor | Cisco Nexus 9300-FX/FX2/FX3/GX/GX2/H1 switches | 30 IPv4 flow monitor and each flow monitor with two exporters 28 IPv6 flow monitor and each flow monitor with two exporters |
| Interface Filter | Cisco Nexus 9300-FX/FX2/FX3/GX/GX2/H1 switches | 32 |
| VRF Filter | Cisco Nexus 9300-FX/FX2/FX3/GX/GX2/H1 switches | 100 |
| Maximum number of flows in the software table (IPv4 or IPv6 flows) | Cisco Nexus 9300-FX/FX2/FX3/GX/GX2/H1 switches | 400,000 |

²⁷ Nexus 9348GC-FX3PH switch has feature limitations due to Half Duplex only ports, see [Cisco Nexus 9000 Series NX-OS System Management Configuration Guide, Release 10.4\(x\)](#).

²⁸ A single forwarding engine instance supports four SPAN or ERSPAN sessions. For Cisco Nexus 9300 Series switches, if the first three sessions have bidirectional sources, the fourth session has hardware resources only for Rx sources. This limitation might also apply to Cisco Nexus 9500 Series switches, depending on the SPAN or ERSPAN source's forwarding engine instance mappings.

²⁹ The number of SPAN or ERSPAN sessions per line card reduces to two if the same interface is configured as the bidirectional source in more than one session.

³⁰ When configuring a NetFlow flow monitor on a range of VLAN interfaces, the process can be time-consuming (approximately 30 minutes) depending on the range of VLANs specified in the command. To reduce wait time, limit the number of VLANs or specify the VLANs in chunks. Note: On a 9500 modular chassis with 9700-FX or 9700-GX modules, the configuration takes significantly longer time compared to other switches.

NetFlow Scalability Support (Flows) for Cisco Nexus 9500 Family Switches

| Feature | Platform | Scale Limit per Slice (Flows) |
|---|--------------------------|-------------------------------|
| IP flow monitor | Nexus 9500-EX Line cards | 2 |
| IPv6 flow monitor | | 2 |
| Layer 2 Flow monitor | | 1 |
| Maximum number of exporters per each flow monitor | | 2 |
| Flow Scale | | 24,000 per ASIC slice |

| Feature | Platform | Scale Limit per Slice (Flows) |
|---|--------------------------|-------------------------------|
| IP flow monitor | Nexus 9500-FX Line cards | 30 |
| IPv6 flow monitor | | 28 |
| Layer 2 Flow monitor | | 1 |
| Maximum number of exporters per each flow monitor | | 2 |
| Flow Scale | | 24,000 per ASIC slice |



Note NetFlow scale limits are determined based on the interfaces of the line cards where the NetFlow configurations are attached in the modular switches.

NetFlow SVI Verified Scalability Limits

| Platform (VLAN Ports) | SVI | | | VLAN | | | SVI + VLAN | | |
|--|--|------|----------------|------|------|----------------|------------|------|----------------|
| | IPv4 | IPv6 | IPv4 + IPv6 | IPv4 | IPv6 | IPv4 + IPv6 | IPv4 | IPv6 | IPv4 + IPv6 |
| Member ports from Cisco Nexus 9300-FX switches | Total interfaces supported in the system | | | | | | | | |
| Member ports from Nexus 9300-FX switches (EOR chassis) | 474 | 118 | 94 | 474 | 118 | 94 | 237 | 61 | 38 |



Note The scale numbers are based on the TCAM space available on the Cisco Nexus 9300-FX switches. A IPv4 flow monitor uses 4 TCAM space for the Cisco Nexus 9300-FX switches. Similarly, a IPv6 flow monitor uses 2 TCAM space for the Cisco Nexus 9300-FX switches.

For port channels, SVIs, and VLANs that have port from both 9300-FX switches, the lower common denominator limit of the 9300-FX switches is applied.

Unicast Routing Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|---|---|---|
| IPv4 ARP and IPv6 ND | | |
| IPv4 ARP (Default routing template) | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 98,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP) |
| | Nexus 9300-FX2 switches | 48,000 (without URPF) 32,000 (with URPF enabled) |
| | Nexus 9408 switches | 49,152 |
| | Nexus 92348GC-FX3 switches | 32,000 |
| | Nexus 9808 switches | 4000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 2000 |
| | Nexus 9164E-NS4-O switches | 16,384 Default DLB mode: 2000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 98,304 |
| Nexus 9600-R, 9600-RX, X97160YC-EX, Nexus X9716D-GX, and 9700-FX/FX3 line cards | 48,000 | |

| Feature | Supported Platforms | Verified Limits |
|------------------------------------|---|---|
| IPv6 ND (Default routing template) | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 98,000 (in default routing mode, Hash Table: Shared between IPv6 ND, IPv4 ARP) |
| | Nexus 9300-FX2 switches | 32,000 (default), 16,000 (lpm heavy) |
| | Nexus 92348GC-FX3 switches | 32,000 |
| | Nexus 9408 switches | 32,768 |
| | Nexus 9808 switches | 4000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 2000 |
| | Nexus 9164E-NS4-O switches | 16,384 Default DLB mode: 2000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 98,304 |
| | Nexus 9600-R, 9600-RX, X97160YC-EX, and 9700-FX/FX3 line cards | 32,000 |
| IPv4 ARP (Internet peering mode) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 32,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16,000 over a SVI/VLAN (as the upper limit of the dynamic learned MAC address in the "internet peering" mode is 16,000) |
| | Nexus 9408 switches | 32,768 |
| | Nexus X9716D-GX, X97160YC-EX and Nexus 9700-FX/FX3 line cards | 32,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16,000 over a SVI/VLAN (as the upper limit of the dynamic learned MAC address in the "internet peering" mode is 16,000) |

| Feature | Supported Platforms | Verified Limits |
|---------------------------------|--|---|
| IPv6 ND (Internet-peering mode) | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 32,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16,000 over a SVI/VLAN (as the upper limit of the dynamic learned MAC address in the "internet Peering" mode is 16,000) |
| | Nexus 9300-FX2 switches | 16,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) |
| | Nexus 9408 switches | 16,384 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 16,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) |
| | Nexus X9716D-GX/FX3 line cards | 32,000 (Hash Table: Shared between IPv6 ND, IPv4 ARP, and protocol learned IPv6 host) over L3 interface and 16,000 over a SVI/VLAN (as the upper limit of the dynamic learned MAC address in the "internet Peering" mode is 16,000) |
| IPv4 ARP (Dual-host mode) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 98,000 |
| IPv6 ND (Dual-host mode) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 98,000 |
| IPv4 and IPv6 Routes | | |
| Default Routing Template | | |

| Feature | Supported Platforms | Verified Limits |
|-------------------------------------|---|--|
| IPv4 host routes 31 | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 1,153,000 |
| | Nexus 9300-FX2 switches | 524,000 / 471,000 (without / with URPF enabled) |
| | Nexus 92348GC-FX3 switches | 96,000 |
| | Nexus 9408 switches | 734,003 |
| | Nexus 9808 switches | 256,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 512,000 |
| | Nexus 9164E-NS4-O switches | 126,976 - This scale value is shared with IPv4 LPM routes. |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1,146,880 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | FM-E: 589,000 FM-E2: 589,000 FM-G: 1,000,000 |
| | Nexus 9600-R/RX and Nexus X9716D-GX line cards | 1,000,000 (default routing template) |

| Feature | Supported Platforms | Verified Limits |
|--------------------------------|---|--|
| IPv6 host routes ³² | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 628,000 |
| | Nexus 9300-FX2 switches | 265,000 |
| | Nexus 92348GC-FX3 switches | 48,000 |
| | Nexus 9408 switches | 412,876 |
| | Nexus 9808 switches | 64,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 130,000 |
| | Nexus 9164E-NS4-O switches | 32,768 (Shared with LPM with prefix length ≥ 64) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 212,992 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | FM-E: 32,000 FM-E2: 235,000 FM-G: 235,000 |
| | Nexus X9716D-GX line card | 235,000 |
| Nexus 9600-RX line cards | 256,000 | |

| Feature | Supported Platforms | Verified Limits |
|--------------------------|---|---|
| IPv4 LPM routes | Nexus 9300-FX switches | 1,153,000 / 996,000 (without / with URPF enabled) |
| | Nexus 9300-FX2 switches | 524,000 / 471,000 (without / with URPF enabled) |
| | Nexus 9300-FX3/GX/GX2/H2R/H1 switches | 1,153,000 |
| | Nexus 92348GC-FX3 switches | 6000 |
| | Nexus 9408 switches | 734,003 |
| | Nexus 9808, 9364E-SG2-Q and 9364E-SG2-O switches | 512,000 |
| | Nexus 9164E-NS4-O switches | 126,976 - This scale value is shared with IPv4 host routes. |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1,048,576 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 589,000 |
| | Nexus 9600-R line cards | 192,000 |
| Nexus 9600-RX line cards | 1,000,000 | |

| Feature | Supported Platforms | Verified Limits |
|-----------------------|---|---|
| IPv6 LPM routes | Nexus 9300-FX switches | 628,000 / 560,000 (without / with URPF enabled) |
| | Nexus 9300-FX2 switches | 294,000 / 265,000 (without / with URPF enabled) |
| | Nexus 9300-FX3/GX/GX2/H2R/H1 switches | 628,000 / 628,000 (without/with URPF enabled) |
| | Nexus 9408 switches | 412,876 |
| | Nexus 9808 switches | 250,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 204,800 |
| | Nexus 9164E-NS4-O switches | 126976 (Prefix length 0-63) 32768 (Prefix length 64-128 , Shared with V6 Host routes) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 524,288 |
| | Nexus 9500 switches | 20,000 (default system routing mode) 4000 (max-host routing mode) 80,000 with no IPv4 routes (64-bit ALPM routing mode) |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | FM-E: 176,000 (/64 prefix length); 3900 (non /64 prefix length) FM-E2: 235,000 (any prefix length) FM-G: 235,000 |
| | Nexus 9600-R line cards | 62,000 |
| | Nexus 9600-RX line cards | 256,000 |
| LPM Heavy Mode | | |

| Feature | Supported Platforms | Verified Limits |
|-----------------------|---|---|
| IPv4 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 786,000 / 734,000 (with out/with URPF enabled) |
| | Nexus 9408 switches | 1,048,576 |
| | Nexus 9808 switches | 256,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 786,000 |
| IPv6 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 442,000 / 412,000 (with out/with URPF enabled) |
| | Nexus 9408 switches | 589,824 |
| | Nexus 9808 switches | 64,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | FM-E: 32,000 (shared between IPv6 ND and protocol learned host) FM-E2: 235,000 FM-G: 235,000 |
| | Nexus X9716D-GX line card | 235,000 |
| IPv4 LPM routes | Nexus 9300-FX/FX3/FX2/GX/GX2/H2R/H1 switches | 786,000 / 734,000 (with out/with URPF enabled) |
| | Nexus 9408 switches | 1,048,576 |
| | Nexus 9808 switches | 900,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 786,000 |
| IPv6 LPM routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 442,000 / 412,000 (with out/with URPF enabled) |
| | Nexus 9408 switches | 589,824 |
| | Nexus 9808 switches | 250,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | FM-E: 235,000 (/64 prefix length); 3900 (non /64 prefix length) FM-E2: 235,000 (any prefix len) FM-G: 235,000 |
| Dual Host Mode | | |

| Feature | Supported Platforms | Verified Limits |
|------------------------------|--|--|
| IPv4 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 262,000 |
| | Nexus 9808 switches | 256,000 |
| IPv6 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 131,000 |
| | Nexus 9808 switches | 64,000 |
| IPv4 LPM routes | Nexus 9300-FX switches | 8000 |
| | Nexus 9300-FX2/GX/GX2/H2R/H1, and Nexus 9408 switches | 10,000 |
| | Nexus 9300-FX3 switches | 7000 |
| IPv6 LPM routes | Nexus 9300-FX/FX3 switches | 1900 |
| | Nexus 9300-FX2/GX/GX2/H2R/H1, and Nexus 9408 switches | 3900 |
| Internet Peering Mode | | |
| IPv4 host routes | Nexus 9300-FX2 switches | 1,000,000 |
| | Nexus 9300-FX switches | 1,256,000 |
| | Nexus 9300-FX3/H2R/H1/GX/GX2 switches | 2,000,000 |
| | Nexus 9408 switches | 1,468,006 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and 9700-GX line cards | 1,000,000 |
| IPv6 host routes | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 628,224 |
| | Nexus 9300-FX2 switches | 500,000 |
| | Nexus 9408 switches | 412,876 |
| | Nexus X97160YC-EX line cards | 16,000 (Hash Table: Shared between IPv6 ND and protocol learned IPv6 host) |
| | Nexus 9700-FX/GX/FX3 line cards | 500,000 |

| Feature | Supported Platforms | Verified Limits |
|---------------------------------|--|--|
| IPv4 LPM routes | Nexus 9300-FX2 switches | 1,000,000 |
| | Nexus 9300-FX switches | 1,256,000 |
| | Nexus 9300-FX3/GX/GX2/H2R/H1 switches and Nexus 9700 GX line cards | 2,000,000 |
| | Nexus 9408 switches | 1,468,006 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 1,000,000 |
| IPv6 LPM routes | Nexus 9300-FX/FX3/GX/GX2/H2R/H1 switches | 628,224 |
| | Nexus 9300-FX2 switches | 500,000 |
| | Nexus 9408 switches | 412,876 |
| | Nexus X97160YC-EX line cards | 500,000 (Prefix length 48-83) protocol learned 1900 (Prefix length /84-127) |
| | Nexus 9700-FX/GX/FX3 line cards | 500,000 (Prefix length 48-128) protocol learned |
| | Nexus 9500 switches with the FM-E2 fabric line cards | 176,000 (Prefix length 0–47) protocol learned host |
| | Nexus 9500 switches with the FM-G fabric line cards | 500,000 |
| Routes | Nexus 9600-R and 9600-RX line cards | 1 Million ³³ |
| IPv4 routes | Nexus 9600-R and 9600-RX line cards | 852,000 ³⁴ |
| IPv6 routes | Nexus 9600-R line cards | 175,000 ³⁵ |
| Routes | Nexus 9600-R line cards | 852,000 |
| IPv4 routes | Nexus 9600-R line cards | 781,000 |
| IPv6 routes | Nexus 9600-R line cards | 71,000 |
| L3 Heavy Mode | | |
| IPv4 LPM routes | Nexus 9600-RX line cards | 1,800,000 |
| IPv6 LPM routes (13-heavy mode) | Nexus 9600-RX line cards | 750,000 |
| L3 Host Heavy Template | | |

| Feature | Supported Platforms | Verified Limits |
|---|----------------------------|------------------------|
| IPv4 host routes | Nexus 9300-FX2 switches | 367,000 |
| | Nexus 9300-H2R/H1 switches | 550,000 |
| IPv6 host routes | Nexus 9300-FX2 switches | 183,000 |
| | Nexus 9300-H2R/H1 switches | 275,000 |
| IPv4 LPM routes | Nexus 9300-FX2 switches | 5800 |
| | Nexus 9300-H2R/H1 switches | 262,144 |
| IPv6 LPM routes | Nexus 9300-FX2 switches | 5800 |
| | Nexus 9300-H2R/H1 switches | 150,000 |
| Unicast Protocols | | |
| Bidirectional Forwarding Detection (BFD) | | |

| Feature | Supported Platforms | Verified Limits |
|---------------------------------|---|--|
| BFD sessions (echo mode) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 128 when the BFD intervals are set to default, which is 50 ms 2048 sessions when the BFD intervals are relaxed to 300 ms |
| | Nexus 92348GC-FX3 switches | 256 |
| | Nexus 9164E-NS4-O switches | 128 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 sessions (IPv4 and IPv6) |
| | Nexus 9800 switches (single hop) Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 128 when the BFD intervals are set to default, which is 50 ms 1000 (IPv4 and IPv6) sessions when the BFD intervals are relaxed to 300 ms Note For Nexus 9800 switches, the maximum session limit per L3 port channel and its subinterfaces is 128. |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 128 when the BFD intervals are set to default, which is 50 ms 2048 sessions when the BFD intervals are relaxed to 300 ms Note On EoR, per line card session limit will be 256. |
| | Nexus X9716D-GX line card | 512 when the BFD intervals are set to default, which is 50 ms 1024 when the BFD intervals are relaxed to 300 ms Note On EoR, per line card session limit will be 256. |
| | Nexus 9600-R and 9600-RX line cards | 288 |
| | Nexus N9K-X9836DM-A line cards | 768 |
| Nexus N9K-X98900CD-A line cards | 512 | |
| Border Gateway Protocol | | |

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| BGP neighbors (IPv4 and IPv6 combined) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1024 |
| | Nexus 92348GC-FX3 switches | 256 |
| | Nexus 9164E-NS4-O switches | 128 |
| | Nexus 9808, 9364E-SG2-Q and 9364E-SG2-O switches | 1000 (IPv4 and IPv6) |
| | Nexus X97160YC-EX, 9700-FX and Nexus X9716D-GX line cards | 2000 |
| | Nexus 9600-R, 9600-RX and 9600-R2 line cards | 1024 |
| HSRP | | |
| HSRP groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 1000 ³⁶ |
| | Nexus 92348GC-FX3 switches | 255 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 - IPv4 and IPv6 (virtual MAC address support) |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches ³⁷ N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 (virtual MAC address support) ³⁸ |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 1000 (virtual MAC address support) ³⁹ |
| | Nexus 9600-R and 9600-RX line cards | 16 ⁴⁰ |
| EIGRP | | |

| Feature | Supported Platforms | Verified Limits |
|---|--|------------------------|
| EIGRP routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, 9808, 9364E-SG2-Q and 9364E-SG2-O switches | 20,000 |
| | Nexus 92348GC-FX3 switches | 20,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 50,000 |
| EIGRP neighbors | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, 9808, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches | 256 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 2000 |
| IS-IS | | |
| IS-ISv4 adjacencies (either L1, L2, or sum of L1 and L2 with default timers) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 255 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 255 |
| IS-ISv4 BFD sessions (with default timers) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 255 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 255 |

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| IS-ISv4 routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 10,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 10,000 |
| Groups | | |
| Groups with default timers (3s/10s) and multiple group optimizations. [There are 2 primary, one for IPv4 and the other for IPv6, and 7926 secondary] | Nexus X9636C-R/RX and X9636Q-R line cards | 7928 |
| Groups with aggressive timers (1s/3s) and multiple groups optimization. [There are 2 primary, one for IPv4 and the other for IPv6, and 7926 secondary] ⁴¹ | Nexus X9636C-R/RX and X9636Q-R line cards | 7928 |
| Groups per interface or I/ module | Nexus X9636C-R/RX and X9636Q-R line cards | Maximum 16 (Because 16 is the unique virtual MAC address limit) |
| OSPFv2 and OSPFv3 | | |
| OSPFv2/OSPFv3 LSA/LSDB size | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9808, 9364E-SG2-Q and 9364E-SG2-O switches, Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 100,000 |
| | Nexus 9600-R and 9600-RX line cards | 250,000 |

| Feature | Supported Platforms | Verified Limits |
|-------------------------|---|-----------------|
| OSPFv2/OSPFv3 areas | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9808, 9364E-SG2-Q and 9364E-SG2-O switches, Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 100 |
| | Nexus 9600-R and 9600-RX line cards | 200 |
| OSPFv2/OSPFv3 neighbors | Nexus 9300-FX/FX2/GX | 650 |
| | Nexus 9300-FX3/GX2/H2R/H1, Nexus 92348GC-FX3, 9808, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 256 |
| | Nexus 9600-R, 9600-RX, Nexus X9716D-GX, X97160YC-EX, and 9700-FX line cards | 1000 |
| Static Routes | | |
| IPv4 Static routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9808, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 8000 |

| Feature | Supported Platforms | Verified Limits |
|---------------------------------------|---|-----------------|
| IPv6 Static routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9808, 9364E-SG2-Q and 9364E-SG2-O switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 8000 |
| Virtual Routing and Forwarding | | |
| VRFs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and 9808 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| | Nexus 92348GC-FX3 switches | 256 |
| | Nexus 9164E-NS4-O switches | 128 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 200 (IPv4/IPv6) |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 1000 |
| | Nexus 9600-R and 9600-RX line cards | 3967 |
| Policy Based Routing | | |
| Configured sequences per policy | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408, 9800, Nexus 92348GC-FX3 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 128 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 128 |

| Feature | Supported Platforms | Verified Limits |
|-------------------------------|--|--|
| Next-hop addresses per policy | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408, 9800, Nexus 92348GC-FX3 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 32 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 32 |
| IPv4 ACEs (unidimensional) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408, Nexus 92348GC-FX3 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 3582 (per network forwarding engine) |
| | N9K-C9508 switches with N9K-X9636C-RX line card | 20,000 (per network forwarding engine) |
| | Nexus 9800 switches | 14,000 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 3582 (per network forwarding engine) |
| IPv6 ACEs (unidimensional) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408, Nexus 92348GC-FX3 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1792 (per network forwarding engine) |
| | Nexus 9800 switches | 7000 |
| IPv4 and IPv6 ACEs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and 9408 switches | 1024 IPv4 + 128 IPv6 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1024 IPv4 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| Interfaces with PBR policy 42 | Nexus 9300-FX3/GX/GX2/H2R/H1 switches | 510 |
| | Nexus 92348GC-FX3 switches | 256 |
| | Nexus 9300-FX/FX2, 9408, 9800 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 512 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 512 |
| | Nexus X9716D-GX line card | 256 |
| | | |
| VRRP | | |
| VRRP groups per interface or I/O module | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 and Nexus X9716D-GX line cards | 250 |
| VRRPv3 groups per interface | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches | 255 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 255 |
| | Nexus X9716D-GX line card | 250 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| VRRPv3 groups with default timers (1 s) | Nexus 9300-FX/FX2/FX3 switches | 255 |
| | Nexus 9300-GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches and Nexus 9700-GX line cards Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 490 |
| VRRPv3 groups with relaxed timers (3 s) | Nexus 9300-FX/FX2/FX3 switches | 255 |
| | Nexus 9300-GX/GX2/H2R/H1, Nexus 92348GC-FX3, 9364E-SG2-Q and 9364E-SG2-O switches and Nexus 9700-GX line cards Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 490 |
| Pathways with one VRRPv3 group with default timer (1 s) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3 switches | 489 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 489 |
| VRRPv3 groups and pathways combined | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 92348GC-FX3 switches | 490 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 250 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 490 |
| | Nexus X9716D-GX line card | 250 |

| Feature | Supported Platforms | Verified Limits |
|---|---|--|
| ECMP Scale | | |
| ECMP Paths - IPv4 (internet-peering mode) | Nexus 9300-FX/FX3/GX/GX2, and Nexus 9408 switches | 16 |
| ECMP Paths - IPv6 (internet-peering mode) | Nexus 9300-FX/FX3/GX/GX2, and Nexus 9408 switches | 16 |
| ECMP Paths (IPv4 and IPv6 Unicast Address-family) | Nexus 9300-FX/FX2/FX3/FXP/GX/GX2/H2R/H1, 9408, and 9808 switches | 128 ⁴³ |
| | Nexus 9396Y12C-SE1, 9396T12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 64 |
| | Nexus 9300-FX3/GX/GX2 switches | 512 |
| | Nexus 9804/9808 switches | 511 |
| | Nexus 9336C-SE1, 9348Y12C-SE1 switches | 511 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 128 for regular ECMP 127 for DLB enabled ECMP |
| | Nexus 9164E-NS4-O switches | 256 |
| | Nexus 9504/9508 switches with -R/RX line cards and | 64 |
| | Nexus X9716D-GX and N9K-X9736C-FX3 line cards | 128 ⁴⁴ |
| ECMP Groups | Nexus 9804/9808 switches | 16,384 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 8192 |
| | Nexus 9164E-NS4-O switches | Default DLB mode: 512 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 512 256 for DLB enabled ECMP |
| Dynamic Load Balancing Enabled ECMP | | |

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| Maximum DLB Enabled ECMP Groups | Nexus 9300-FX3/GX/GX2/H2R/H1 | 128 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | Default DLB mode: 512 Policy-driven mixed DLB mode: 256 |
| Internet Peering ECMP | | |
| Maximum ECMP paths (Route scale: 1,800,000 million IPv4 + 200,000 IPv6 LPM routes) | Nexus 9300-GX/GX2/H2R/H1 Note Required RAM 64 GB | 32 |
| | Nexus 9300-FX3/GX/GX2/H2R/H1 Note Required RAM 32 GB | 16 |
| Mixed path | | |
| Total VRFs | Nexus 9300-FX/FX2/FX3/GX/GX2 switches and 9500 switches with 9700-FX line cards | 250 (125 Internal/External VRFs) 2 Service VRFs that all VRFs leak into |
| Total VM routes ⁴⁵ | Nexus 9300-FX/FX2/FX3/GX/GX2 switches and 9500 switches with 9700-FX line cards | 10000 IPv4 (5000 Internal and 5000 External) 5000 IPv6 (2500 Internal and 2500 External) |
| Max number of VNF per VM route | Nexus 9300-FX/FX2/FX3/GX/GX2 switches and 9500 switches with 9700-FX line cards | 32 |

³¹ The hash table is subject to collisions. Depending on the host route pattern, collisions might occur.

³² The hash table is subject to collisions. Depending on the host route pattern, collisions might occur.

³³ Contains internet peering profile with additional IPv4 and IPv6 routes.

³⁴ Internet profile with additional IPv4 routes (total of 914K routes consisting of IPv4 and 62K of IPv6)

³⁵ Internet profile with additional IPv6 routes (total of 871K routes consisting of IPv6 and 696K of IPv4)

³⁶ If you have more than 490 groups, then only one group per SVI. SVIs cannot have a user defined MAC or any VRRP group with it.

³⁷ For Nexus 9300-SE1 switches, of the total Router MAC scale, the number of unique 32 bit MSBs allowed for user-defined MAC addresses is 11.

³⁸ If you have more than 490 groups, then only one group per SVI. SVIs cannot have a user defined MAC or any VRRP group with it.

³⁹ If you have more than 490 groups, then only one group per SVI. SVIs cannot have a user defined MAC or any VRRP group with it.

⁴⁰ For vPC configuration, HSRP maximum scale is 16 groups, 15 groups with vPC peer-gateway configured.

⁴¹ If the user has Multi-protocol configuration, user should configure appropriate CoPP policies to avoid any control plane traffic drops.

- ⁴² When using PBR with the "set vrf" option, if the user attempts to shut down the recircular port, it will trigger a modify PPF session from RPM. If the maximum labels (510) have already been consumed and atomic update is enabled, a "label allocation failure" will occur. To avoid this, the user needs to disable atomic update.
- ⁴³ 128-way ECMP paths are not supported for MPLS, VXLAN, and L3 tunnels. Resilient hashing is not supported on Cisco Nexus 9808 switch for routing, PBR and Port-channel.
- ⁴⁴ 128-way ECMP paths are not supported for MPLS, VXLAN, and L3 tunnels. Resilient hashing is not supported on Cisco Nexus 9808 switch for routing, PBR and Port-channel.
- ⁴⁵ VM Routes are service routes which are recursively resolved over its Gateway IP/VNF.



Note

- With IPv6 scale, traffic loss could be there for a few seconds during switchover.
- The maximum number of PBR next-hops based on 4 FM-E supported is 192 per slice of the forwarding engine
 - The IPv4/IPv6 host routes and the IPv4 multicast routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
 - The IPv4 and IPv6 unicast routes share the same hardware table. Limits are provided for both the default line card mode and the max host line card mode.
 - High availability (graceful restart and stateful switchover) is not supported when unicast or multicast aggressive timers are configured at any scale.

Guidelines and Limitations for OSPF Verified Scalability Limits

- To achieve the highest scale, we recommend that you use a single OSPF instance instead of multiple instances.
- Each OSPFv2 and OSPFv3 scale value might vary when combined with other parameters.
- The graceful restart timeout value might be increased in multidimensional scenarios.

RIPng Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|-----------------|------------------------------|-----------------|
| RIPng Neighbors | Nexus 9300 and 9500 switches | 250 |
| RIPng Routes | Nexus 9300 and 9500 switches | 1500 |

PVLAN VXLAN Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|------------------------------|------------------------------------|-----------------|
| Primary VLANs | Nexus 9300-FX/FX2/FX3/H2R switches | 16 |
| Secondary VLANs | Nexus 9300-FX/FX2/FX3/H2R switches | 20 |
| Ports in community host mode | Nexus 9300-FX/FX2/FX3/H2R switches | 40 |
| Port in Isolated host mode | Nexus 9300-FX/FX2/FX3/H2R switches | 40 |
| Ports in isolated trunk mode | Nexus 9300-FX/FX2/FX3/H2R switches | 40 |

| Feature | Supported Platforms | Verified Limits |
|--------------------------------|------------------------------------|-----------------|
| Ports in promiscuous mode | Nexus 9300-FX/FX2/FX3/H2R switches | 5 |
| PVLANS allowed on a PVLAN port | Nexus 9300-FX/FX2/FX3/H2R switches | 16 |



Note The above scale numbers are applicable for both IPv4 and IPv6 Underlay. However, for Nexus 9300-H2R switches the above scale is applicable only for IPv4 Underlay.

VXLAN Verified Scalability Limits

| Feature | Supported Platforms | Verified Limits |
|--|---|---|
| VXLAN BGP eVPN and Ingress Replication | | |
| Note Scale limit are with default system routing template. | | |
| Layer 2 VNIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 3900 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 250 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 3900 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 3900 |
| | Nexus 9600-R and 9600-RX line cards | 2000 |
| Xconnect VLANs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 40 |
| Selective Qinqni with multiprovider tag (IPv4 and IPv6 Underlay) | Nexus 93180YC-FX, 9336C-FX2, Nexus 9300-FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | Port level: 4000 mappings, 512 provider VLANs System wide: 48,000 mappings, 512 provider VLANs |

| Feature | Supported Platforms | Verified Limits |
|---|---|-----------------|
| SVI with Distributed Anycast Gateway; Layer 2 VNI extended | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 3900 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| Layer 3 VNIs / VRFs ⁴⁶ | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 2000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 64 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 2000 |
| | Nexus 9600-R and 9600-RX line cards | 900 |
| | Nexus X97160YC-EX, 9700-FX/FX3 line cards | 750 |
| | Nexus X9716D-GX line cards | 2000 |

| Feature | Supported Platforms | Verified Limits |
|--------------------------|---|---|
| VTEP Peers ⁴⁷ | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 350 vPC pairs or 1000 standalone VTEPs with IR ⁴⁸ 512 standalone VTEPs with multicast underlay |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 256 (Leaf Role) 800 (Multi-Site Anycast BGW) |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 350 vPC pairs or 1000 standalone VTEPs with IR ⁴⁸ 512 standalone VTEPs with multicast underlay |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 350 vPC pairs or 1000 standalone VTEPs with IR ⁴⁸ 512 standalone VTEPs with multicast underlay |
| | Nexus 9600-R, 9600-RX line cards | 256 |
| ARP | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches | 96,000 Note In default system routing template, ARP and ND share the same resource table. To scale ARP to 96K and ND to 96K independently, use the command system routing template dual-stack-host-scale and reload the switch. |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 2000 |
| ND | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches | 96,000 Note In default system routing template, ARP and ND share the same resource table. To scale ARP to 96K and ND to 96K independently, use the command system routing template dual-stack-host-scale and reload the switch. |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 2000 |

| Feature | Supported Platforms | Verified Limits |
|---|---|--|
| MAC addresses | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | Default template: 90,000 dual-stack-host-scale template: 96,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 32,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | Default template: 90,000 dual-stack-host-scale template: 96,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | Default template: 90,000 dual-stack-host-scale template: 96,000 |
| Port VLAN translations under an interface | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches | 3967 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 100 |
| Port VLAN translations in a switch | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches | 24,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 2000 |
| IPv4 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 471,000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 512,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 512,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 128,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 656,000 |

| Feature | Supported Platforms | Verified Limits |
|-------------------------|---|------------------------|
| IPv6 host routes | Nexus 9300-FX/FX2/GX/GX2/H2R/H1, and Nexus 9408 switches | 265,000 |
| | Nexus 9300-FX3 switches | 500,000 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 128,000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 112,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 64,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 34,000 |
| Overlay IPv4 LPM routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 471,500 |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 512,000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 1,000,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 440,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 656,000 |

| Feature | Supported Platforms | Verified Limits |
|---------------------------|---|------------------------|
| Overlay IPv6 LPM routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 265,000 ⁴⁹ |
| | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 128,000 |
| | Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 512,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 206,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 174,000 ⁴⁹ |
| IGMP groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 8192 |
| ECMP group (L3) | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 512 |
| Overlay ECMP | Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 128 |
| Underlay multicast groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 512 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 512 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 512 |

| Feature | Supported Platforms | Verified Limits |
|---|---|--|
| Maximum policy scale or number of VNIs to which a policy can be applied | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 switches, and Nexus 9408 switches | 510 Note The default scale is 60 on Nexus 9300-FX2 ToR switches. To increase the scale to 510, use the <code>hardware access-list tcam label ing-racl 9</code> command. |
| | Nexus 9300-FX switches | 60 |
| | Nexus 9700-FX/GX/FX3 line cards | 60 |
| IGMP snooping over VXLAN | | |
| VXLAN VLANs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| Overlay EVPN ECMP | | |
| ECMP Paths Note An ECMP entry is created for each tunnel. (There may be multiple tunnels for each VXLAN peer). | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 128 |
| | Nexus 9364E-SG2 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 64 |
| | Nexus 9500 switches with Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 128 |
| | Nexus 9800 switches with N9K-X9836DM-A, and N9K-X98900CD-A line cards | 64 |
| | | |
| Underlay EVPN ECMP | | |

| Feature | Supported Platforms | Verified Limits |
|--------------------------------------|--|------------------------|
| ECMP Paths | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 64 |
| | Nexus 9364E-SG2 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 64 |
| | Nexus 9500 switches with Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 64 |
| | Nexus 9800 switches with N9K-X9836DM-A, and N9K-X98900CD-A line cards | 64 |
| Multi-Site 50 | | |
| Asymmetric VNIs per peer | Nexus 9300-FX/FX2/FX3/FXP/GX/GX2/H2R/H1, Nexus 9408 switches | 3900 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 3900 |
| Number of Tunnel Encryption sessions | Nexus 9300, 9336C-FX2, 93240YC-FX2, 93360YC-FX2, 93216TC-FX2, 93180YC-FX3, and 93108TC-FX3P switches ⁵⁵ | 128 51 |
| Number of sites | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches. Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 128 |
| | 9500 switches, and Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 128 |

| Feature | Supported Platforms | Verified Limits |
|--|---|---------------------------|
| Number of sites for TRM | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 16 sites |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 16 sites |
| Number of BGWs per site ⁵² | Nexus 9300-FX/FX2/FX3/GX/H2R/H1, and Nexus 9408 switches | 6 (Anycast) or 2 (vPC) |
| | Nexus 9300-GX2 switches Nexus 9364E-SG2-Q and 9364E-SG2-O switches | 32 (Anycast BGW) |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 4 (Anycast) or 2(vPC) |
| Number of BGWs per site with TRM enabled | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 6 (Anycast), 2 (vPC) |
| | Nexus 9500 switches with Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 2 (Anycast), 2 (vPC) |
| Multisite-PIP ECMP | Nexus 9300-FX2/FX3 ⁵⁵ /GX/GX2 switches | 1000 ⁵³ |
| VTEPs per Site | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 512 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 512 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 512 |
| Multi-Site with PIP (Anycast BGWs) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | L2VNI: 2000 L3VNI: 900 |
| | Nexus X97160YC-EX, 9700-FX/FX3/GX line cards | L2VNI: 2000 L3VNI: 900 |

| Feature | Supported Platforms | Verified Limits |
|---|---|---------------------------|
| Multi-Site with PIP (vPC BGWs) | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | L2VNI: 2000 L3VNI: 900 |
| | Nexus 9700-GX/FX3 ⁵⁴ line cards | L2VNI: 2000 L3VNI: 900 |
| CloudSec | | |
| Number of sites for Secure VXLAN EVPN Multi-Site using CloudSec | Nexus 9300-FX2/FX3 ⁵⁵ /GX2, and Nexus 9408 switches | 10 sites |
| Number of BGWs per site for Secure VXLAN EVPN Multi-Site using CloudSec | Nexus 9336C-FX2/FX3, 93240YC-FX2/FX3, 93360YC-FX2/FX3, 93216TC-FX2/FX3, 9332D-GX2B switches ⁵⁵ | 6 per 10 sites |
| Number of Cloudsec Security Associations for Secure VXLAN EVPN Multi-Site using CloudSec sessions | Nexus 9300-FX2/FX3 ⁵⁵ /GX2, and Nexus 9408 switches | 128 ⁵⁶ |
| Tenant Route Multicast Layer 3 Mode with VXLAN BGP eVPN | | |
| VXLAN Layer 2 VNI | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| VXLAN Layer 3 VNI/VRFs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 250 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 250 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 and X9836DM-A and X98900CD-A line cards | 250 |
| VTEP Peers | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 254 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 254 |

| Feature | Supported Platforms | Verified Limits |
|--|---|-------------------|
| Underlay Multicast Group (PIM ASM Underlay) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 512 ⁵⁷ |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 512 ⁵⁷ |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 512 ⁵⁷ |
| Total Multicast routes (PIM ASM & PIM SSM) | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 32,000 |
| | Nexus 9808/9804 switches with X9836DM-A and X98900CD-A line cards | 32,000 |
| | Nexus X97160YC-EX line card | 8000 |
| | Nexus 9700-FX/GX/FX3 line cards | 32,000 |
| VXLAN Flood and Learn | | |
| Virtual network identifiers (VNIs) or VXLAN-mapped VLANs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 3900 |
| | Nexus 9600-R and 9600-RX line cards | 2000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 3900 |
| Underlay multicast groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 512 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | |
| Overlay MAC addresses | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 60,000 |
| | Nexus 9300-FX switches | 90,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 90,000 |

| Feature | Supported Platforms | Verified Limits |
|--|---|-----------------|
| Ingress replication peers 58 | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 512 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 512 |
| Ingress replication Layer 2 VNIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| MAC addresses for ingress replication | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 90,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 1000 |
| Port VLAN translations under an interface | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches Nexus 9336C-SE1, 9396Y12C-SE1, 9396T12C-SE1, 9348Y12C-SE1 switches N9324C-SE1U, N9348Y2C6D-SE1U switches | 3967 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 100 |
| Port VLAN translations in a switch | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 and Nexus 9408 switches | 24,000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 2000 |
| Static MAC addresses pointing to a remote VTEP | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 1000 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 2000 |

| Feature | Supported Platforms | Verified Limits |
|---|---|-------------------|
| VXLAN VLANs per FEX port (host interface) | Nexus 9300-FX2/FX3 ⁵⁵ /GX/GX2, and Nexus 9408 switches | 75 |
| Layer 2 routed VNIs for vPC-centralized gateway | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 450 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | |
| IGMP groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 8192 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 8192 |
| BGP sessions at BGW | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, and Nexus 9408 switches | 4000 |
| Port Multi-VLAN Mapping ⁵⁹ | Nexus 9300-FX2/GX/GX2/H2R/H1 switches | 510 ⁶⁰ |
| | Nexus 9300-FX switches | 368 ⁶¹ |
| VXLAN and IP-in-IP Tunneling | | |
| IP-in-IP tunnels | Nexus 9300-FX2 switches | 16 |
| VXLAN Static Tunnels | | |
| VNIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 100 |
| VRFs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 100 |
| VTEP peers | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 254 |
| V4 routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, Nexus 9408 switches | 10,000 |
| First Hop Security | | |

| Feature | Supported Platforms | Verified Limits |
|---|--|-----------------|
| DHCP snooping bindings | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 2048 |
| | Nexus X97160YC-EX, 9700-FX/GX/FX3 line cards | 2048 |
| Security Groups (Micro-Segmentation with VXLAN GPO) | | |
| Note This feature is supported only with security-groups template. | | |
| Endpoint Security Group (ESG) selectors | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1 switches | 8000 |
| Total Security Group ACL Entries | Nexus 9300-FX ⁶² /FX3/GX/GX2B/H2R/H1 switches | 64,000 |
| | Nexus 9300-FX2/GX2A, 9408 switches | 32,000 |
| IPv4/IPv6 Trie (Shared) | Nexus 9300-FX/FX3/GX switches | 160,000 |
| | Nexus N9K-9332D-GX2B switches | 224,000 |
| | Nexus 9300-GX2A switches | 110,000 |
| | Nexus 9300-FX2 switches | 60,000 |
| IPv4 host routes | Nexus 9300-FX/FX3/GX switches | 56,000 |
| | Nexus N9K-9332D-GX2B switches | 67,000 |
| | Nexus 9300-GX2A switches | 33,000 |
| | Nexus 9300-FX2 switches | 32,000 |
| IPv6 host routes | Nexus 9300-FX/FX3/GX switches | 24,000 |
| | Nexus N9K-9332D-GX2B switches | 28,000 |
| | Nexus 9300-GX2A/FX2 switches | 12,000 |
| MAC addresses | Nexus 9300-FX/FX3/GX switches | 56,000 |
| | Nexus N9K-9332D-GX2B switches | 44,000 |
| | Nexus 9300-FX2/GX2A switches | 22,000 |
| IPv4 Multicast | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 32,000 |
| IPv6 Multicast | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 8000 |

| Feature | Supported Platforms | Verified Limits |
|-------------------------|--|---|
| MPLS Labels | Nexus 9300-FX/FX3/GX/GX2 switches | 16,000 |
| ECMP Groups | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 24,000 |
| ECMP Members | Nexus 9300-FX/FX3/GX/GX2B switches | 128,000 |
| | Nexus 9300-FX2/GX2A switches | 64,000 |
| Next Hops | Nexus 9300-FX/FX3/GX/GX2B switches | 96,000 |
| | Nexus 9300-FX2/GX2A switches | 48,000 |
| Multicast RPF | Nexus 9300-FX/FX2/FX3/GX/GX2 switches | 32,000 |
| Policy | Nexus 9300-FX/FX3/GX/GX2B switches | 64,000 |
| | Nexus 9300-FX2/GX2A switches | 32,000 |
| ESI Multi-Homing | | |
| Number of ESI in Fabric | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 511 BD/Modulo DF: 511 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 511 BD/Modulo DF: 511 |
| Overlay-ECMP | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 24,000 BD/Modulo DF: 24,000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 24,000 BD/Modulo DF: 24,000 |
| L3 Adjacency | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 96,000 BD/Modulo DF: 96,000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 96,000 BD/Modulo DF: 96,000 |
| L2VNI | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 3900 BD/Modulo DF: 1000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 3900 BD/Modulo DF: 1000 |

| Feature | Supported Platforms | Verified Limits |
|---|--|--|
| L3VNI | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 2000 BD/Modulo DF: 512 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 2000 BD/Modulo DF: 512 |
| VTEP scale in the fabric | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | Per-Flow DF: 512 BD/Modulo DF: 512 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | Per-Flow DF: 512 BD/Modulo DF: 512 |
| Number of supported ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 4 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 4 |
| Number of VLANs supported in ESI port-channel | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 3900 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 3900 |
| Number of MAC's behind ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 96,000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 96,000 |
| Number of IPv4 host routes behind ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 60,000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 60,000 |
| Number of IPv6 host routes behind ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | IPv6: 30,000 Dual stack (IPv4 + IPv6): 6000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | IPv6: 30,000 Dual stack (IPv4 + IPv6): 6000 |
| IGMP Snooping scale behind ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 8000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 8000 |

| Feature | Supported Platforms | Verified Limits |
|-------------------------------------|--|-----------------|
| MLD Snooping scale behind ESI pairs | Nexus 9300-FX2/FX3/GX/GX2/H2R/H1 Series switches | 8000 |
| | Nexus 9500 Series switches with 9700-GX/FX3 line cards ⁶³ | 8000 |

⁴⁶ ECMP objects are not shared across multiple VRFs.

⁴⁷ In case of IR, each VNI can have a max of 64 peers.

⁴⁸ Beginning with Cisco NX-OS Release 10.4(3)F, 1000 VTEP Scale is supported. However, a minimum of 32 GB of memory is required on the device to support this scale.

⁴⁹ All /64 routes + 4000 for non /64 routes.

⁵⁰ All the other BGW numbers (number of supported L2VNIs, L3VNIs, MAC addresses, IP addresses, and so on) match the values supported on a generic VXLAN EVPN VTEP node.

⁵¹ Total number of Cloudsec Security Associations in hardware = 128 (M *N*L) where (M = no. of Cloudsec peers, N = no. of uplinks on each Cloudsec endpoint, L is number of border gateway nodes)

⁵² Multi-Site enabled with TRM supported number of L2VNIs –1000 and L3VNIs –100. Maximum supported multicast underlay and overlay route is 8000. From Cisco NX-OS Release 10.2(3), Multi-Site enabled with TRM supported number of L3VNIs –250. Maximum supported multicast underlay and overlay route is 32000 for Nexus 9300-FX/FX3/GX/GX2 and 8000 for Nexus 9300-FX2 and Nexus 9508.

⁵³ Number of vrfs * number of sites = 1000

⁵⁴ IPv6 unicast traffic is supported only with 9500-FM-G Fabric Modules.

⁵⁵ This feature is not supported on Nexus 9348GC-FX3, 9348GC-FX3PH, 9332D-H2R and 93108TC-FX3 switches.

⁵⁶ Total number of Cloudsec Security Associations in hardware = 128 (M *N*L) where (M = no. of Cloudsec peers, N = no. of uplinks on each Cloudsec endpoint, L is number of border gateway nodes)

⁵⁷ VXLAN underlay and overlay multicast routes shares the same hardware table. Maximum Multicast routes is 8000 in the default mode. If you want more overlay route scale, reduce the underlay multicast control group.

⁵⁸ In case of IR, each VNI can have a maximum number of 64 peers; 512 peers supported on 100 VNIs only.

⁵⁹ Only one provider VLAN is supported.

⁶⁰ The maximum number of Layer-2 subinterfaces is based on the available entries allocated for ing-pacl-sb team region.

⁶¹ Since Nexus 9300-FX have only one slice, the maximum number of Layer-2 subinterfaces that can be created is lower than the limit for Nexus 9300-FX2.

⁶² ACL TCAM region for ing-sup should be carved to a minimum of 768 using 'hardware access-list team region ing-sup <size>' on Cisco Nexus 9300-FX switches.

⁶³ Cisco Nexus 9700-FX line cards support only core links on the ESI fabric.

Tetration Verified Scalability Limits

| Feature | Supported Platforms | Verified Limit |
|-----------|------------------------|--|
| TCAM size | 9300-FX switches | 1024 entries IPv4 –2 entries per rule (ICMP and IP) IPv6 –8 entries per rule (4 entries per ICMP and IPv6 for a total of 8 entries) 24 entries out of 1000 is consumed for default. |
| TCAM | Nexus 9300-FX switches | 500 (IPv4) or 125 (IPv6) |

The entire Cisco Tetration Analytics documentation set is available at the following URL:
<https://www.cisco.com/c/en/us/support/data-center-analytics/tetration-analytics/tsd-products-support-series-home.html>

Spanning Tree Protocol scale considerations

Spanning Tree Protocol (STP) scalability is assessed using two main metrics, each representing a different dimension of scale:

1. STP Virtual Port Scale

Definition: Represents the total number of STP entities managed, considering both internal STP data structures and port-level MAC programming/VLAN allow lists.

Calculation: Virtual Port Scale = (Number of physical STP-managed ports) × (Number of VLANs carried by those ports)

Example (RPVST):

- 100 VLANs
- 4 individual L2 interfaces
- 2 L2 port-channels (each with 8 member interfaces)
- Calculation:
(4 individual interfaces + 2 port-channels × 8 members each) × 100 VLANs
= (4 + 16) × 100 = 2000 Virtual Ports



Note All port-channel members are included in this calculation.

MST Scenario:

For Multiple Spanning Tree (MST), multiply the number of physical interfaces by the number of VLANs in the carried MST instances. If all 100 VLANs are in the same instance, the result is the same (2000 Virtual Ports).

2. STP Logical Port Scale

Definition: Measures the maximum STP BPDU load per hello interval, especially relevant for RPVST, which generates a BPDU per VLAN. This metric helps evaluate control plane scalability. Hence, MST is recommended for large-scale environments, as it reduces Logical Port Scale concerns.

Calculation: Logical Port Scale = (Number of individual L2 interfaces + Number of port-channels) × (Number of VLANs carried)

Example:

- 100 VLANs
- 4 individual L2 interfaces
- 2 L2 port-channels
- Calculation:
(4 interfaces + 2 port-channels) × 100 VLANs
= 6 × 100 = 600 Logical Ports



Note Port-channel members are not included in this calculation.



Note

- All computation will vary if interfaces have unique VLAN pruning lists or have different MST instances with unique VLAN counts. Always review STP scalability against actual hardware/software limits.
- For large deployments, prefer MST to minimize BPDU processing overhead.

Verified Scalability Limits - Multidimensional - 9500 R-Series

The tables in this section list the verified scalability limits for the Cisco Nexus 9508 switch with an X9636C-R, X9636C-RX, or X9636Q-R line card or a C9508-FM-R fabric module and Cisco Nexus 9504 with -R line cards. These limits are validated with a multidimensional configuration. The values provided in these tables focus on the scalability of all listed features at the same time.



Note These numbers are not the maximum verified values if each feature is viewed in isolation. For these numbers, see the corresponding "Verified Scalability Limits" section.

Table 1: eBGP/IS-IS Profile Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|--------------------------------|-------------------|
| Number of 100G ports | 288 |
| ECMP | 16-way (Upstream) |
| BGP neighbors | 960 |
| BGP IPv4 /32 unicast routes | 30,000 |
| BGP IPv4 VLSM unicast routes | 18,000 |
| BGP IPv6 /128 unicast routes | 16,000 |
| BGP IPv6 VLSM unicast routes | 1000 |
| IS-IS v2 neighbors | 255 |
| IS-IS v3 neighbors | 255 |
| IS-IS Layer 2 adjacency | 16 |
| IS-IS IPv4 /32 unicast routes | 20,000 |
| IS-IS IPv4 VLSM unicast routes | 1000 |

| Feature | Verified Limits |
|--------------------------------|----------------------|
| IS-IS IPv6 /128 unicast routes | 20,000 |
| IS-IS IPv6 VLSM unicast routes | 1000 |
| BFD sessions | 272 |
| PIM neighbors | 256 |
| ACL ACEs | 15,000 500 |
| Sub-interfaces | 712 |
| SPAN sessions | 1 local SPAN session |
| Multicast SSM | 20,000 |

Table 2: iBGP/OSPF Profile Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|---------------------------------|------------------|
| Number of 100G ports | 180 |
| Number of 40G ports | 108 |
| ECMP | 8-way (Upstream) |
| BGP neighbors | 8 |
| BGP IPv4 VLSM unicast routes | 40,000 |
| BGP IPv6 VLSM unicast routes | 10,000 |
| OSPFv2 neighbors | 108 |
| OSPFv3 neighbors | 30 |
| OSPF IPv4 /32 unicast routes | 100,000 |
| OSPF IPv4 VLSM unicast routes | 155,000 |
| OSPFv3 IPv6 /128 unicast routes | 1000 |
| OSPFv3 IPv6 VLSM unicast routes | 9000 |
| BFD sessions | 108 |
| VRF | 250 |
| PIM neighbors | 108 |
| IPv4 (*,G) multicast routes | 2000 |

| Feature | Verified Limits |
|-----------------------------|--------------------------|
| IPv4 (S,G) multicast routes | 10,000 |
| ACL ACEs | 500 (IPv4) 500 (IPv6) |
| SPAN sessions | 1 local SPAN session |

Table 3: iBGP/EIGRP Profile Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|--------------------------------|--------------------------|
| Number of 100G ports | 180 |
| Number of 40G ports | 108 |
| ECMP | 16-way (Upstream) |
| BGP neighbors | 8 |
| BGP IPv4 VLSM unicast routes | 40,000 |
| BGP IPv6 VLSM unicast routes | 10,000 |
| EIGRP v4 neighbors | 276 |
| EIGRP v6 neighbors | 276 |
| EIGRP IPv4 /32 unicast routes | 30,000 |
| EIGRP IPv4 VLSM unicast routes | 1000 |
| EIGRP IPv6 /128 unicast routes | 30,000 |
| EIGRP IPv6 VLSM unicast routes | 1000 |
| BFD sessions | 276 |
| VRF | 250 |
| PIM neighbors | 276 |
| IPv4 (*,G) multicast routes | 6000 |
| IPv4 (S,G) multicast routes | 16,000 |
| ACL ACEs | 500 (IPv4) 500 (IPv6) |
| SPAN sessions | 1 local SPAN session |

Table 4: MPLS Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|-------------------------------------|-------------------------------|
| MPLS L3VPN | 3967 |
| VPE | 3967 |
| PE nodes | 3 |
| PE routes | 20,000 |
| X9636C-RX line card: ACL scale-IPv4 | 95,000 |
| X9636C-RX line card: ACL scale-IPv6 | 20,000 |
| HSRP, HSRP VIP | 3967 each for v4 and v6 |
| vPC uRPF | 3967 |
| Strict uRPF | Yes |
| VRF | 3967 |
| MPLS VPN VRFs | 2000 (combined IPv4 and IPv6) |
| SVI | 3967 |
| Layer 3 VPN routes IP ECMP | 2000 |
| MPLS LSR ECMP | 2000 |
| VPNv4 routes | 400,000 |
| VPNv6 routes | 90,000 |
| EBGP neighbors | 750 |

Table 5: Layer 2/Layer 3 Boundary Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|-------------------------------|------------------------|
| MAC addresses | 19,000 |
| vPC Port channels | 46 |
| ECMP | 16-way (Upstream) |
| OSPFv2 neighbors | 47 |
| OSPFv3 neighbors | 47 |
| OSPF IPv4 /32 unicast routes | 45,000 |
| OSPF IPv4 VLSM unicast routes | 1000 |

| Feature | Verified Limits |
|--------------------------------|--|
| OSPF IPv6 /128 unicast routes | 20,000 |
| OSPF IPv6 VLSM unicast routes | 1000 |
| BFD sessions | 49 |
| VRF | 250 |
| VLAN | 3750 |
| SVI | 3750 |
| VRRP v4 groups | 1996 VRRS / 4 VRRPv3 |
| VRRP v6 groups | 1996 VRRS / 4 VRRPv3 |
| HSRP IPv4 | 1743 Secondary groups / 7 Primary groups |
| HSRP IPv6 | 1743 Secondary groups / 7 Primary groups |
| PIM neighbors | 396 |
| IPv4 (*,G) multicast routes | 3080 |
| IPv4 (S,G) multicast routes | 26,600 |
| IGMP snooping database entries | 6400 |
| sFlow enabled interfaces | 83 |
| UDLD enabled interfaces | 93 |
| SPAN sessions | 1 local SPAN session |

Table 6: Segment Routing Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|----------------|------------------------|
| VLAN | 100 |
| SVI | 100 |
| MAC entries | 10,000 |
| ARP entries | 70 |
| HSRPv4 VIPs | 100 |
| HSRpv6 VIPs | 100 |
| LACP | 11 |
| LACP members | 4 |

| Feature | Verified Limits |
|------------------------|------------------------|
| eBGP IPv6 neighbors | 9 |
| eBGP IPv4 LU neighbors | 9 |
| IPv4 (LU) routes | 6888 |
| IPv4 (LU) paths | 17580 |
| IPv6 routes | 6663 |
| 6PE routes | 17,338 |
| SR ECMP | 18 (dual-homed) |
| MPLS HW entries | 11,957 |

Table 7: VXLAN Profile Verified Scalability Limits (Multidimensional)

| Feature | Verified Limits |
|--|------------------------|
| Ports | 16 |
| ECMP | 8-way (Upstream) |
| BGP neighbors | 200 |
| BGP EVPN Layer 2 VPN host routes | 64,000 |
| BGP IPv4 VLSM unicast routes or OSPF | 10,000 |
| BGP IPv6 VLSM unicast routes or OSPF | 6000 |
| BFD sessions | 20 |
| PIM neighbors | 20 |
| IPv4 (*, G) multicast routes (co-existing) | 4000 |
| IPv4 (S,G) multicast routes (co-existing) | 2000 |
| Layer 3 VNI | 900 |
| Layer 2 VNI | 2000 |
| Local VTEP | 1 |
| Remote VTEPs | 256 |
| VLAN | 3600 |
| SVI | 900 |
| MAC | 90,000 |

Deployment Case Studies

This section provides sample topologies for some common deployments. For each topology, the scalability numbers are the limits with all of the listed features enabled at the same time.



Attention These numbers are not the maximum verified values if each feature is viewed in isolation. For these numbers, see the "Verified Scalability Limits" section.

VXLAN BGP/eVPN iBGP Centric Topology

This VXLAN BGP/eVPN iBGP centric topology consists of Cisco Nexus 9300 and 9500 Platform switches acting as VXLAN vPC tunnel endpoints (VTEPs) and VXLAN non-vPC VTEPs. VXLAN VTEPs establish iBGP sessions to a Cisco Nexus 9508 switch (route reflector) acting as a spine node. VXLAN-distributed anycast gateway SVIs are configured for dual stack, and the traffic is dual stack.

The focus of this topology is to test VXLAN overlay network scale and underlay Layer 2 switching and other routing, multicast, and Layer 4 through Layer 7 features for management and operations. Underlay PIM neighbors and IS-IS adjacency were tested with the default timer and Bidirectional Forwarding Detection (BFD) enabled on all links.

In the following table, the Verified Limit column lists the verified scaling capabilities with all listed features enabled at the same time. These numbers are not the maximum verified values if each feature is viewed in isolation.

Table 8: VXLAN BGP/eVPN iBGP Centric Topology

| Feature | Supported Platform | Verified Limit |
|-------------------------|---|----------------|
| System Routing Template | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | default |
| VXLAN VTEPs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 128 |
| VXLAN Layer 2 VNIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 2000 |
| VXLAN Layer 3 VNIs/VRFs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX line cards | 500 |

| Feature | Supported Platform | Verified Limit |
|------------------------------------|---|---|
| VXLAN multicast groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 128 |
| VXLAN overlay MAC addresses | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX line cards | 64,000 |
| VXLAN overlay IPv4 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 60,000 |
| VXLAN overlay IPv6 host routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 16,000 |
| VXLAN overlay IGMP Snooping groups | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 1000 |
| VXLAN IPv4 LPM routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 5120 |
| VXLAN IPv6 LPM routes | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 1500 |
| VLANs on VTEP node | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 1700 (total VLANs) 1500 (VXLAN VLANs) 200 (non-VXLAN VLANs) |

| Feature | Supported Platform | Verified Limit |
|--|---|----------------|
| MST instances | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 20 |
| STP logical ports For more information on STP scale considerations, see Spanning Tree Protocol scale considerations, on page 94 section. | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 3500 |
| vPC port channels | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 40 |
| Underlay IS-IS neighbors | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 32 |
| Underlay PIM neighbors | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 12 |
| Underlay vPC SVIs | Nexus 9300-FX/FX2/FX3/GX/GX2/H2R/H1, 9408 switches, and 9500 switches with Nexus X97160YC-EX, 9700-FX/GX line cards | 200 |

FEX System Topology

The FEX 9300 multi-dimensional scale topology consists of two Cisco Nexus N9K-C93180YC-FX and another pair has N9K-C9336C-FX2 switches used in vPC mode along with 12 FEX uplinks connected to each switch.

- Multiple FEXs of type Nexus 2248TP-E, C2348TQ, C2332TQ are used.
- The switches are used at the Layer 2 and Layer 3 boundary and are also configured as VXLAN VTEPs. The FEX host ports are operating as Layer 2 ports. The switches are configured as gateways with the use of SVI interfaces.
- In the following table, the Platform Verified Limit column lists the verified scaling capabilities with all listed features enabled at the same time. The scale numbers listed here exceed those used by most customers in their topologies. These numbers are not the maximum verified values if each feature is viewed in isolation.

Table 9: FEX System Topology

| Feature | 9300 Platform Verified Limit |
|-------------------------|-------------------------------------|
| Fabric Extenders | 12 |
| Port channels | 372 |
| vPC members | 360 |
| VLANs | 624 |
| MAC addresses | 14515 |
| HSRP | 365 |
| ARP | 9727 |
| Neighbor discovery (ND) | 10911 |
| Multicast (*,G) | 2250 |
| Multicast (S,G) | 2250 |

LIST OF TABLES

Table 1: eBGP/IS-IS Profile Verified Scalability Limits (Multidimensional).....95

Table 2: iBGP/OSPF Profile Verified Scalability Limits (Multidimensional).....96

Table 3: iBGP/EIGRP Profile Verified Scalability Limits (Multidimensional).....97

Table 4: MPLS Verified Scalability Limits (Multidimensional).....98

Table 5: Layer 2/Layer 3 Boundary Verified Scalability Limits (Multidimensional).....98

Table 6: Segment Routing Verified Scalability Limits (Multidimensional).....99

Table 7: VXLAN Profile Verified Scalability Limits (Multidimensional).....100

Table 8: VXLAN BGP/eVPN iBGP Centric Topology.....101

Table 9: FEX System Topology.....104

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS REFERENCED IN THIS DOCUMENTATION ARE SUBJECT TO CHANGE WITHOUT NOTICE. EXCEPT AS MAY OTHERWISE BE AGREED BY CISCO IN WRITING, ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS DOCUMENTATION ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED.

The Cisco End User License Agreement and any supplemental license terms govern your use of any Cisco software, including this product documentation, and are located at <https://www.cisco.com/c/en/us/about/legal/cloud-and-software/software-terms.html>. Cisco product warranty information is available at <https://www.cisco.com/c/en/us/products/warranty-listing.html>. US Federal Communications Commission Notices are found here <https://www.cisco.com/c/en/us/products/us-fcc-notice.html>.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any products and features described herein as in development or available at a future date remain in varying stages of development and will be offered on a when-and if-available basis. Any such product or feature roadmaps are subject to change at the sole discretion of Cisco and Cisco will have no liability for delay in the delivery or failure to deliver any products or feature roadmap items that may be set forth in this document.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2026 Cisco Systems, Inc. All rights reserved.



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA 95134-1706
USA

Asia Pacific Headquarters
CiscoSystems(USA)Pte.Ltd.
Singapore

Europe Headquarters
CiscoSystemsInternationalBV
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.