



## SD-AVC Notes and Limitations

- [General](#), on page 1
- [Setup](#), on page 1
- [Classification](#), on page 2
- [High Availability](#), on page 3
- [Protocol Pack](#), on page 3
- [REST API](#), on page 3

### General

Note/Limitation	Description
Maximum number of participating network devices	Maximum number of network devices participating with SD-AVC (running the SD-AVC agent): 6000

### Setup

Note/Limitation	Description
MD5 checksum of OVA download	When installing or upgrading the SD-AVC network service, download the OVA package, copy it to the device that will host the network service, then verify the MD5 checksum of the package before installing. The correct MD5 checksum value appears on the <a href="#">Download Software</a> page when downloading the package.
Network Service gateway interface attached to VRF	For the SD-AVC Network Service, running on a host device, if the host interface that is used as a gateway interface is attached to a VRF, see <a href="#">Operating the SD-AVC Network Service with Host Interface Attached to a VRF</a> for configuration details.

Note/Limitation	Description
Running and startup configurations of participating devices	<p>SD-AVC adds two lines to the running and startup configurations of participating devices:</p> <ul style="list-style-type: none"> <li>To enable the MS Office 365 Web Service, which improves classification of Microsoft Office traffic: <pre>ip nbar protocol-pack bootflash:sdavc/sdavc_ppdk.pack force</pre> </li> <li>When SD-AVC deploys Protocol Packs to a device: <pre>ip nbar protocol-pack harddisk:sdavc/protocol-pack-name.pack</pre> </li> </ul>

## Classification

Note/Limitation	Description
Interval before sending application data	SD-AVC requires a few minutes to learn from the network traffic before the application data is sent to the SD-AVC Network Service and compiled at the network level. See <a href="#">SD-AVC and Application Recognition</a> .
SD-AVC application rules pack less relevant for client-to-client traffic	SD-AVC provides application classification for server-based applications. The SD-AVC application rules pack is less relevant for client-to-client traffic, which is more granular and dynamic. Client-to-client traffic is classified by NBAR2 running on each network element.
Proxy or CDN	In the case of a proxy or content delivery network (CDN), multiple applications may use the same IP/port combination. The network devices themselves classify such traffic fully. However, for these applications, the SD-AVC agent operating on a device may report application data to the SD-AVC network service with a lesser degree of detail: they may be reported with less detailed classification granularity or not at all.
Reported bandwidth of Unclassified Traffic Discovery	For traffic that appears in the Unclassified Traffic view, the reported bandwidth is based on samples and may not be accurate in some cases. See <a href="#">Unclassified Traffic Analysis and Discovery</a> .
High-stress flows may not be discovered by the Unclassified Traffic Discovery feature	High-stress flows that require a large amount of system resources may be excluded from the traffic reported in the <b>Unclassified Traffic</b> view. For example, the Timeline may show a high-bandwidth of unknown/generic traffic that is not reported in the table. This is done to minimize the utilization of resources in case of high stress flows and skip the discovery mechanism. See <a href="#">Unclassified Traffic Analysis and Discovery</a> .

## High Availability

Note/Limitation	Description
Error status and Protocol Pack deployment during high availability switchover and switchback	<p>In SD-AVC high availability configurations, if the primary SD-AVC network service becomes unavailable, network devices switch to the secondary SD-AVC network service. When the primary SD-AVC network service becomes available again, the devices switch back to primary.</p> <p>The <b>switchover</b> and <b>switchback</b> processes require approximately 30 minutes. During this time:</p> <ul style="list-style-type: none"> <li>• Service in the network continues normally without interruption.</li> <li>• The <b>SD-AVC Dashboard &gt; Application Visibility</b> page shows an error status for the devices.</li> <li>• The <b>SD-AVC Dashboard &gt; Protocol Packs</b> page shows that the devices are not active. During this brief period, SD-AVC does not deploy Protocol Packs to the devices.</li> </ul> <p>See <a href="#">SD-AVC High Availability</a>.</p>

## Protocol Pack

Note/Limitation	Description
Cisco ISR4000 Series: hard disk limitation	Protocol Pack files must be loaded on the boot flash. For ISR4000 routers operating with SD-AVC, it is not recommended to install a hard disk. Doing so will cause Protocol Pack deployment by SD-AVC to fail.
Protocol Pack deployment during high availability switchover and switchback	See <a href="#">High Availability, on page 3</a> .

## REST API

Note/Limitation	Description
User-defined application source	In the initial release of the REST API, only one source is supported.

Note/Limitation	Description
Total number of user-defined applications available	For each network segment: <ul style="list-style-type: none"><li>• Maximum user-defined applications: 1100</li><li>• Maximum L3L4 rules: 20000</li><li>• Maximum serverNames: 50000</li></ul>
High-availability SD-AVC configurations	High-availability SD-AVC configurations are supported. On the primary and secondary SD-AVC network services, configure the same REST API-based user-defined application configuration.
L3/L4 subnet limitations	IPv4: Subnet prefix length limited to: 24 to 32 IPv6: Not supported.