



## **IP Switching: Configuring Multicast Distributed Switching Configuration Guide, Cisco IOS Release 12.2SR**

### **Americas Headquarters**

Cisco Systems, Inc.  
170 West Tasman Drive  
San Jose, CA 95134-1706  
USA  
<http://www.cisco.com>  
Tel: 408 526-4000  
800 553-NETS (6387)  
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2011 Cisco Systems, Inc. All rights reserved.



## **CONTENTS**

### **Configuring Multicast Distributed Switching 1**

Finding Feature Information 1

Information About Multicast Distributed Switching 1

Advantages of Multicast Distributed Switching 1

Multicast Distributed Switching Is Disabled by Default 2

How to Configure Multicast Distributed Switching 2

Configuring Multicast Distributed Switching 2

Maintaining Multicast Distributed Switching 4

Maintaining Multicast Distributed Switching on the Line Card 4

Maintaining Multicast Distributed Switching on the Route Processor 5

Monitoring Multicast Distributed Switching 6

Monitoring Multicast Distributed Switching on the Line Card 6

Monitoring Multicast Distributed Switching on the Route Processor 8

Configuration Examples for Multicast Distributed Switching 10

Example Configuring Multicast Distributed Switching 10

Example Maintaining Multicast Distributed Switching 10

Example Maintaining Multicast Distributed Switching on the Line Card 10

Example Maintaining Multicast Distributed Switching on the Route Processor 10

Additional References 10

Feature Information for Multicast Distributed Switching 12

Glossary 12





# Configuring Multicast Distributed Switching

---

This module describes the required and optional tasks for configuring Multicast Distributed Switching (MDS).

- [Finding Feature Information, page 1](#)
- [Information About Multicast Distributed Switching, page 1](#)
- [How to Configure Multicast Distributed Switching, page 2](#)
- [Configuration Examples for Multicast Distributed Switching, page 10](#)
- [Additional References, page 10](#)
- [Feature Information for Multicast Distributed Switching, page 12](#)
- [Glossary, page 12](#)

## Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the Feature Information Table at the end of this document.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

## Information About Multicast Distributed Switching

- [Advantages of Multicast Distributed Switching, page 1](#)
- [Multicast Distributed Switching Is Disabled by Default, page 2](#)

## Advantages of Multicast Distributed Switching

Prior to MDS, IP multicast traffic was always switched at the Route Processor (RP) in the Route Switch Processor (RSP)-based platforms.

Switching multicast traffic at the RP had the following disadvantages:

- The load on the RP increased. This affected important route updates and calculations (for Border Gateway Protocol (BGP), among others) and could stall the router if the multicast load was substantial.
- The net multicast performance was limited to what a single RP could switch.

MDS solves these problems by performing distributed switching of multicast packets received at the line cards (Versatile Interface Processors [VIPs] in the case of RSP, and line cards in the case of Cisco 12000 series router). The line card is the interface card that houses the VIPs (in the case of RSP) and the line card (in the case of Cisco 12000 series router). MDS is accomplished using a forwarding data structure called a Multicast Forwarding Information Base (MFIB), which is a subset of the routing table. A copy of MFIB runs on each line card and is always kept up to date with the MFIB table of the RP.

MDS can work in conjunction with Cisco Express Forwarding or unicast distributed fast switching (DFS).

Starting with Cisco IOS Release 11.2GS, IP multicast traffic can be distributed switched on RSP-based platforms with VIPs. MDS is the only multicast switching method on the Cisco 12000 series router starting with Cisco IOS Release 11.2(11)GS.

## Multicast Distributed Switching Is Disabled by Default

On the Cisco 7500 series router, the default is IP multicast fast switching. MDS is an option that is available and is disabled by default.

On the Cisco 12000 series routers, MDS is also disabled by default. To switch multicast packets on the Cisco 12000 series router, you need to configure all interfaces for MDS. MDS is the only multicast switching mode for the Cisco 12000 series router.

If MDS is not enabled on an incoming interface that is capable of MDS, incoming multicast packets are not distributed switched; the multicast packets are fast switched at the RP. Also, if the incoming interface is not capable of MDS, packets are fast switched or process-switched at the RP.

If MDS is enabled on the incoming interface, but at least one of the outgoing interfaces cannot fast switch, packets are process switched.

**Note**

---

We recommend that you disable fast switching on any interface when MDS is enabled.

---

## How to Configure Multicast Distributed Switching

- [Configuring Multicast Distributed Switching, page 2](#)
- [Maintaining Multicast Distributed Switching, page 4](#)
- [Monitoring Multicast Distributed Switching, page 6](#)

## Configuring Multicast Distributed Switching

Perform the following task to configure MDS. To configure MDS, you must enable it globally and on at least one interface because MDS is an attribute of the interface.

**Note**

---

When you enable an interface to perform distributed switching of incoming multicast packets, you are configuring the physical interface, not the logical interface (subinterface). All subinterfaces are included in the physical interface.

---

**SUMMARY STEPS**

1. **enable**
2. **configure terminal**
3. **ip multicast-routing distributed**
4. **interface *type number***
5. **ip route-cache distributed**
6. **ip mroute-cache distributed**
7. Repeat Steps 4 through 6 for each interface that you want to perform MDS.
8. **end**

**DETAILED STEPS**

Command or Action	Purpose
<p><b>Step 1 enable</b></p> <p><b>Example:</b></p> <pre>Router&gt; enable</pre>	<p>Enables privileged EXEC mode.</p> <ul style="list-style-type: none"> <li>• Enter your password if prompted.</li> </ul>
<p><b>Step 2 configure terminal</b></p> <p><b>Example:</b></p> <pre>Router# configure terminal</pre>	<p>Enters global configuration mode.</p>
<p><b>Step 3 ip multicast-routing distributed</b></p> <p><b>Example:</b></p> <pre>Router(config)# ip multicast-routing distributed</pre>	<p>Enables IP multicast routing.</p> <ul style="list-style-type: none"> <li>• The <b>distributed</b> keyword enables MDS globally.</li> </ul>
<p><b>Step 4 interface <i>type number</i></b></p> <p><b>Example:</b></p> <pre>Router(config)# interface ethernet 0</pre>	<p>Configures an interface type and enters interface configuration mode.</p> <ul style="list-style-type: none"> <li>• The <i>type</i> argument is the type of interface to be configured.</li> <li>• The <i>number</i> argument is the port, connector, or interface card number. The numbers are assigned at the factory at the time of installation or when added to a system, and can be displayed with the <b>show interfaces</b> command.</li> </ul>

Command or Action	Purpose
<b>Step 5</b> <code>ip route-cache distributed</code>  <b>Example:</b>  <pre>Router(config-if)# ip route-cache distributed</pre>	Enables distributed switching on the RSP.  <b>Note</b> This step is required on the RSP platform only.
<b>Step 6</b> <code>ip mroute-cache distributed</code>  <b>Example:</b>  <pre>Router(config-if)# ip mroute-cache distributed</pre>	Enables MDS on the interface.  For Cisco 7500 series routers, this keyword is optional; if it is omitted, fast switching occurs. For Cisco 12000 series, this keyword is required because the Cisco 12000 series does only distributed switching.
<b>Step 7</b> Repeat Steps 4 through 6 for each interface that you want to perform MDS.	--
<b>Step 8</b> <code>end</code>  <b>Example:</b>  <pre>Router(config-if)# end</pre>	Exits to privileged EXEC mode.

## Maintaining Multicast Distributed Switching

- [Maintaining Multicast Distributed Switching on the Line Card, page 4](#)
- [Maintaining Multicast Distributed Switching on the Route Processor, page 5](#)

### Maintaining Multicast Distributed Switching on the Line Card

Perform the following task to maintain MDS on the line card.

#### SUMMARY STEPS

1. `enable`
2. `clear ip mds forwarding`
3. `exit`



**DETAILED STEPS**

Command or Action	Purpose
<b>Step 1 enable</b>  <b>Example:</b> Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>Enter your password if prompted.</li> </ul>
<b>Step 2 clear ip mds forwarding</b>  <b>Example:</b> Router# clear ip mds forwarding	Clears MDS information from the router, <ul style="list-style-type: none"> <li>Clears the Multicast Forwarding Information Base (MFIB) table of the line card and resynchronizes it with the RP.</li> </ul>
<b>Step 3 exit</b>  <b>Example:</b> Router# exit	Exits to user EXEC mode.

**Maintaining Multicast Distributed Switching on the Route Processor**

Perform the following task to maintain MDS on the RP.

**SUMMARY STEPS**

- enable
- clear ip mroute {\* | group [source]}
- clear ip pim interface count
- exit

**DETAILED STEPS**

Command or Action	Purpose
<b>Step 1 enable</b>  <b>Example:</b> Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>Enter your password if prompted.</li> </ul>

Command or Action	Purpose
<p><b>Step 2</b> <code>clear ip mroute [*   group [source]]</code></p> <p><b>Example:</b></p> <pre>Router# clear ip mroute *</pre>	<p>Deletes entries from the IP multicast routing table.</p> <ul style="list-style-type: none"> <li>The <i>*</i>(asterisk) keyword deletes all entries from the IP multicast routing table.</li> <li>The <i>group</i> argument is either of the following: <ul style="list-style-type: none"> <li>Name of the multicast group, as defined in the Domain Name System (DNS) hosts table or with the <b>ip host</b> command.</li> <li>IP address of the multicast group. This is a multicast IP address in four-part dotted-decimal notation.</li> </ul> </li> <li>The <i>source</i> argument is a name or address of a multicast source that is sending to the group. A source need not be a member of the group. If you specify a group name or address, you can also specify a source name or address.</li> </ul>
<p><b>Step 3</b> <code>clear ip pim interface count</code></p> <p><b>Example:</b></p> <pre>Router# clear ip pim interface count</pre>	<p>Clears all line card counts or packet counts.</p>
<p><b>Step 4</b> <code>exit</code></p> <p><b>Example:</b></p> <pre>Router# exit</pre>	<p>Exits to user EXEC mode.</p>

## Monitoring Multicast Distributed Switching

- [Monitoring Multicast Distributed Switching on the Line Card, page 6](#)
- [Monitoring Multicast Distributed Switching on the Route Processor, page 8](#)

### Monitoring Multicast Distributed Switching on the Line Card

Perform the following task to monitor MDS on the line cards.

Remember that to reach a line card's console, enter the **attach slot#** command, using the slot number where the line card resides.

```
Router> attach 1
LC-Slot1> enable
LC-Slot1#
```

#### SUMMARY STEPS

- enable**
- show ip mds forwarding [group-address]**
- show ip mds summary**
- exit**

## DETAILED STEPS

### Step 1

#### enable

Use this command to enable privileged EXEC mode. Enter a password, if prompted. For example:

#### Example:

```
Router> enable
Router#
```

### Step 2

#### show ip mds forwarding [group-address]

Use this command to display the MFIB table, forwarding information, related flags, and counts. For example:

#### Example:

```
Router# show ip mds forwarding

IP multicast MDFS forwarding information and statistics:
Flags: N - Not MDFS switchable, F - Not all MDFS switchable, O - OIF Null
      R - In-ratelimit, A - In-access, M - MTU mismatch, P - Register set
Interface state: Interface, Next-Hop, Mac header
(*, 224.2.170.73),
  Incoming interface: Null
  Pkts: 0, last used: never, Kbps: 0, fast-flags: N
  Outgoing interface list: Null
(192.168.62.86, 224.2.170.73) [31]
  Incoming interface: Fddi3/0/0
  Pkts: 3034, last used: 00:00:00, Kbps: 0, fast-flags: M
  Outgoing interface list:
```

### Step 3

#### show ip mds summary

Use this command to display a summary of the MFIB. For example:

#### Example:

```
Router# show ip mds summary

IP multicast MDFS forwarding information and statistics:
Flags: N - Not MDFS switchable, F - Not all MDFS switchable, O - OIF Null
      R - In-ratelimit, A - In-access, M - MTU mismatch, P - Register set
Interface state: Interface, Next-Hop, Mac header
(*, 224.2.170.73),
  Incoming interface: Null
  Pkts: 0, last used: never, Kbps: 0, fast-flags: N
(192.168.62.86, 224.2.170.73) [31]
  Incoming interface: Fddi3/0/0
  Pkts: 3045, last used: 00:00:03, Kbps: 0, fast-flags: M
(192.168.3.7, 224.2.170.73) [334]
  Incoming interface: Fddi3/0/0
  Pkts: 0, last used: never, Kbps: 0, fast-flags: M
```

### Step 4

#### exit

Use this command to exit to user EXEC mode. For example:

#### Example:

```
Router# exit
Router>
```

## Monitoring Multicast Distributed Switching on the Route Processor

Perform the following task to monitor MDS on the RP.

### SUMMARY STEPS

1. **enable**
2. **show ip mds stats [switching | linecard]**
3. **show mds interface**
4. **show interface stats**
5. **exit**

### DETAILED STEPS

#### Step 1

##### **enable**

Use this command to enable privileged EXEC mode. Enter a password, if prompted. For example:

##### Example:

```
Router> enable
Router#
```

#### Step 2

##### **show ip mds stats [switching | linecard]**

Use this command to display switching statistics or line card statistics for MDS. This example displays switching statistics:

##### Example:

```
Router# show ip mds stats switching
Slot Total      Switched      Drops      RPF      Punts      Failures
              (switch/clone)
 1      0            0            0            0            4            0/0
 3  20260925    18014717    253          93          2247454     1/0
```

This example displays linecard statistics:

##### Example:

```
Router# show ip mds linecard
Slot      Status      IPC(seq/max)  Q(high/route)  Reloads
 1        active     10560/10596   0/0            9
 3        active     11055/11091   0/0            9
```

#### Step 3

##### **show mds interface**

Use this command to display MDS interfaces. For example:

##### Example:

```
Router# show mds interface
```

Interface	SW-Index	HW-Index	HW IDB	FS Vector	VRF
Ethernet1/0/0	2	1	0x60C2DB40	0x602FB7A4	default
Ethernet1/0/1	3	2	0x60C32280	0x603D52B8	default
Ethernet1/0/2	4	3	0x60C35E40	0x602FB7A4	default
Ethernet1/0/3	5	4	0x60C39E60	0x603D52B8	default
Ethernet1/0/4	6	5	0x60C3D780	0x602FB7A4	default
Ethernet1/0/5	7	6	0x60C41140	0x602FB7A4	default
Ethernet1/0/6	8	7	0x60C453A0	0x602FB7A4	default
Ethernet1/0/7	9	8	0x60C48DC0	0x602FB7A4	default
POS2/0/0	10	9	0x0		default
POS3/0/0	11	10	0x0		default
Virtual-Access1	13	11	0x0		default
Loopback0	14	12	0x0		default
Tunnel0	15	23	0x61C2E480	0x603D52B8	vrf1
Tunnel1	16	24	0x61C267E0	0x603D52B8	vrf2
Ethernet1/0/3.1	17	4	0x60C39E60	0x603D52B8	vrf1
Ethernet1/0/3.2	18	4	0x60C39E60	0x603D52B8	vrf2

**Step 4** **show interface stats**

Use this command to display numbers of packet that were process switched, fast switched, and distributed switched. For example:

**Example:**

```
Router# show interface stats
GigabitEthernet0/0
  Switching path   Pkts In   Chars In   Pkts Out   Chars Out
    Processor           0         0         225       77625
    Route cache         0         0           0           0
  Multi-Processor Fwding   950      221250    500       57000
    Total              950      221250    725      134625
GigabitEthernet0/1
  Switching path   Pkts In   Chars In   Pkts Out   Chars Out
    Processor           1         60        226       77685
    Route cache         0         0           0           0
  Multi-Processor Fwding   500      57000    500       57000
    Total              501      57060    726      134685
GigabitEthernet0/2
  Switching path   Pkts In   Chars In   Pkts Out   Chars Out
    Processor           1         60        226       77685
    Route cache         0         0           0           0
  Multi-Processor Fwding   0         0           0           0
    Total              1         60        226       77685
FastEthernet1/0
  Switching path   Pkts In   Chars In   Pkts Out   Chars Out
    Processor      34015    5331012    1579     158190
    Route cache     0         0           0           0
  Total           34015    5331012    1579     158190
```

**Step 5** **exit**

Use this command to exit to user EXEC mode. For example:

**Example:**

```
Router# exit
Router>
```

# Configuration Examples for Multicast Distributed Switching

- [Example Configuring Multicast Distributed Switching, page 10](#)
- [Example Maintaining Multicast Distributed Switching, page 10](#)

## Example Configuring Multicast Distributed Switching

The following example show how to enables MDS:

```
configure terminal
ip multicast-routing distributed
interface pos 1/0/0
 ip route-cache distributed
 ip mroute-cache distributed
end
```

The **ip route-cache distributed** command is needed on the RSP only, not on the GSR.

## Example Maintaining Multicast Distributed Switching

This section contains the following examples for maintaining MDS:

- [Example Maintaining Multicast Distributed Switching on the Line Card, page 10](#)
- [Example Maintaining Multicast Distributed Switching on the Route Processor, page 10](#)

### Example Maintaining Multicast Distributed Switching on the Line Card

The following example shows how to maintain MDS on the line card:

```
enable
clear ip mds forwarding
exit
```

In this example, the MFIB table of the line card is cleared of entries and resynchronized with the RP.

### Example Maintaining Multicast Distributed Switching on the Route Processor

The following example shows how to maintain MDS on the RP:

```
enable
clear ip mroute *
clear ip pim interface count
exit
```

In this example, all entries are deleted from the IP multicast routing table and all line card counts or packet counts are cleared.

## Additional References

**Related Documents**

Related Topic	Document Title
Cisco IOS commands	<a href="#">Cisco IOS Master Commands List, All Releases</a>
IP switching commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples.	<i>Cisco IOS IP Switching Command Reference</i>
Overview of switching paths available on Cisco IOS devices	Cisco IOS Switching Paths Overview

**Standards**

Standard	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	--

**MIBs**

MIB	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: <a href="http://www.cisco.com/go/mibs">http://www.cisco.com/go/mibs</a>

**RFCs**

RFC	Title
No new or modified RFCs are supported by this feature, and support for existing RFCs has not been modified by this feature.	--

**Technical Assistance**

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	<a href="http://www.cisco.com/cisco/web/support/index.html">http://www.cisco.com/cisco/web/support/index.html</a>

## Feature Information for Multicast Distributed Switching

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

**Table 1** *Feature Information for Configuring Multicast Distributed Switching*

Feature Name	Releases	Feature Information
This table is intentionally left blank because no features were introduced or modified in Cisco IOS Release 12.2(1) or later. This table will be updated when feature information is added to this module.	--	--

## Glossary

**Cisco Express Forwarding** --A Layer 3 switching technology. Cisco Express Forwarding can also refer to central Cisco Express Forwarding mode, one of two modes of Cisco Express Forwarding operation. Cisco Express Forwarding enables a Route Processor (RP) to perform express forwarding. Distributed Cisco Express Forwarding is the other mode of Cisco Express Forwarding operation

**line card** --A general term for an interface processor that can be used in various Cisco products. For example, a Versatile Interface Processor (VIP) is a line card for the Cisco 7500 series router.

**MFIB** --Multicast Forwarding Information Base. A protocol-independent multicast forwarding system that contains unique multicast forwarding entries for each source or group pair known in a given network. There is a separate MFIB for every logical network (VPN) in which the router is configured. Each MFIB entry resolves a given source or group pair to an incoming interface (IIF) for reverse forwarding (RPF) checking and an outgoing interface list (olist) for multicast forwarding.

**RP** --Route Processor. The processor module in the Cisco 7000 series routers that contains the CPU, system software, and most of the memory components that are used in the router. It is sometimes called a supervisory processor.

**RSP** --Route Switch Processor. Processor module in the Cisco 7000 series routers that integrates the functions of the Route Processor (RP) and the Switch processor (SP).

**VIP** --Versatile Interface Processor. An interface card used in Cisco 7000 and Cisco 7500 series routers. The VIP provides multilayer switching and runs Cisco IOS.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third party



trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

