



# Multilink Frame Relay over L2TPv3 AToM

---

**Last Updated: November 22, 2011**

This feature enables Multilink Frame Relay switching over Layer 2 Tunnel Protocol Version 3 (L2TPv3) and Any Transport over MPLS (AToM). The feature works with like-to-like interfaces and disparate interfaces (L2VPN interworking).

Multilink Frame Relay is the logical grouping of one or more physical interfaces between two devices of the User-to-Network Interface/Network-to-Network Interface (UNI/NNI) as one single Frame Relay data link.

- [Finding Feature Information, page 1](#)
- [Prerequisites for Configuring Multilink Frame Relay over L2TPv3 AToM, page 2](#)
- [Restrictions for Configuring Multilink Frame Relay over L2TPv3 AToM, page 2](#)
- [Information About Configuring Multilink Frame Relay over L2TPv3 AToM, page 2](#)
- [How to Configure Multilink Frame Relay over L2TPv3 AToM, page 4](#)
- [Configuration Examples for Multilink Frame Relay over L2TPv3 AToM, page 9](#)
- [Additional References, page 16](#)
- [Command Reference, page 17](#)
- [Feature Information for Multilink Frame Relay over L2TPv3 AToM, page 17](#)

## Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the Feature Information Table at the end of this document.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.



---

**Americas Headquarters:**  
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

## Prerequisites for Configuring Multilink Frame Relay over L2TPv3 AToM

Before configuring Multilink Frame Relay over L2TPv3/AToM, you should understand how to configure Layer 2 virtual private networks (VPNs) and Multilink Frame Relay. See the [Additional References, page 16](#) for pointers to the feature modules that explain how to configure and use those features.

## Restrictions for Configuring Multilink Frame Relay over L2TPv3 AToM

- Only data-link connection identifier (DLCI)-to-DLCI switching, where each DLCI maps to its own pseudowire, is supported. Port-port mode (also known as HDLC mode), where the entire content of the port, including the Local Management Interface (LMI), is carried across a single pseudowire, is not supported.
- The following functionality is not supported:
  - UNI/NNI or end-to-end fragmentation
  - Nonstop forwarding/stateful switchover
  - Four-byte DLCIs
- On the Cisco 7500 series routers, all bundle links must reside on the same port adapter (PA) of the Versatile Interface Processor (VIP). Links spreading across PAs are not supported.
- Cisco 7500 series routers support the VIP6-80, VIP4-80, VIP4-50, VIP2-50, CH-STM1, CT3/CE3, CT1/CE1, PA-4T+, and PA-8T port adapters.
- On the Cisco 12000 series routers, Multilink Frame Relay is supported only on the following pluggable modules: Cisco 4-port channelized T3 (DSO) shared port adapter, Cisco 8-port channelized T1/E1 shared port adapter, and the Cisco 1-port channelize OC-3/STM-1 shared port adapter.

## Information About Configuring Multilink Frame Relay over L2TPv3 AToM

- [Multilink Frame Relay over L2TPv3 AToM, page 2](#)
- [Internetworking Support for Multilink Frame Relay, page 3](#)
- [Quality of Service Support for Multilink Frame Relay over L2TPv3 AToM, page 3](#)

## Multilink Frame Relay over L2TPv3 AToM

Multilink Frame Relay over L2TPv3/AToM supports the following functionality:

- Permanent virtual circuit (PVC) status signaling
- LMI types cisco, q933a, and ANSI
- Sequencing
- Frame Relay policing (nondistributed)
- Type of service (ToS) marking for L2TPv3

## Internetworking Support for Multilink Frame Relay

Interworking support for Multilink Frame Relay interfaces supports the following functionality:

- Frame Relay to Ethernet/VLAN (Ethernet and IP interworking)
- Frame Relay to PPP and ATM (IP interworking)
- Cisco and Internet Engineering Task Force (IETF) encapsulation on the customer-edge (CE) router
- Sequencing
- LMI interworking to notify CE routers of PVC status changes

## Quality of Service Support for Multilink Frame Relay over L2TPv3 AToM

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

L2VPN quality of service (QoS) features supported for Frame Relay are also supported with the Multilink Frame Relay over L2TPv3/AToM feature. You can attach an input service policy to the Multilink Frame Relay interface or individual DLCIs on the interface using the map-class mechanism to police or mark the traffic. You can attach an output policy to the Multilink Frame Relay (MFR) interface to perform class-based queueing, including per-DLCI queueing using the **match fr-dlci** command.

The following ingress QoS features are supported with the Multilink Frame Relay over L2TPv3/AToM feature:

- Interface input policy matching on the discard eligibility (DE) bit to set Multiprotocol Label Switching (MPLS) EXP or tunnel differentiated services code point (DSCP).
- Virtual circuit (VC) input policy configured with a color-aware, two-rate, three-color policer using the DE bit as input color and setting the MPLS EXP bit or tunnel DSCP bit based on color.

**Note**

You cannot use the VC-level and interface-level input policies at the same time on the same interface.

The following egress QoS features are supported with the Multilink Frame Relay over L2TPv3/AToM feature:

- Egress queueing using tail drop or discard class-based weighted random early detection (WRED). You can use the latter with a core interface input policy to set the discard class based on the MPLS EXP or tunnel DSCP.
- Interface output policy matching on QoS group (selected by MPLS EXP or tunnel DSCP).
- Interface aggregate shaping policy with queueing policy.
- VC output shaping policy with tail drop or discard class-based WRED.
- Forward explicit congestion notification (FECN)/backward explicit congestion notification (BECN) marking.

**Note**

You cannot use VC-level and interface-level output policies at the same time on the same interface.

**Note**

Egress queueing and shaping policies are not supported with Multilink Frame Relay on the Cisco 7200 series routers.

## How to Configure Multilink Frame Relay over L2TPv3 ATOM

- [Configuring a Multilink Frame Relay Bundle Interface, page 4](#)
- [Configuring a Multilink Frame Relay Bundle Link Interface, page 5](#)
- [Connecting Frame Relay PVCs Between Routers, page 7](#)
- [Verifying Multilink Frame Relay over L2TPv3 ATOM, page 8](#)

### Configuring a Multilink Frame Relay Bundle Interface

Configure a bundle interface to aggregate bandwidth of multiple member links under a single interface to one virtual pipe. To configure a bundle interface for Multilink Frame Relay, perform the following steps.

#### SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface mfr *number***
4. **frame-relay multilink bid *name***

#### DETAILED STEPS

Command or Action	Purpose
<b>Step 1 enable</b>  <b>Example:</b> <pre>Router&gt; enable</pre>	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>• Enter your password if prompted.</li> </ul>
<b>Step 2 configure terminal</b>  <b>Example:</b> <pre>Router# configure terminal</pre>	Enters global configuration mode.

Command or Action	Purpose
<b>Step 3</b> <code>interface mfr <i>number</i></code>  <b>Example:</b>  <b>Example:</b> <pre>Router(config)# interface mfr 1</pre>	Configures a multilink Frame Relay bundle interface and enters interface configuration mode.
<b>Step 4</b> <code>frame-relay multilink bid <i>name</i></code>  <b>Example:</b>  <b>Example:</b> <pre>Router(config-if)# frame-relay multilink bid int1</pre> <b>Example:</b>	(Optional) Assigns a bundle identification name to a multilink Frame Relay bundle.  <b>Note</b> The bundle identification (BID) will not go into effect until the interface has gone from the down state to the up state. One way to bring the interface down and back up again is by using the <b>shutdown</b> and <b>no shutdown</b> commands in interface configuration mode.

## Configuring a Multilink Frame Relay Bundle Link Interface

Configuring a Multilink Frame Relay bundle link interface allows you to combine bandwidth of multiple lower-speed serial links into a single large pipe and avoid the need of upgrading or purchasing new hardware. To configure a bundle link interface for Multilink Frame Relay, perform the following steps.

### SUMMARY STEPS

1. `enable`
2. `configure terminal`
3. `interface serial number`
4. `encapsulation frame-relay mfr number [name]`
5. `frame-relay multilink lid name`
6. `frame-relay multilink hello seconds`
7. `frame-relay multilink ack seconds`
8. `frame-relay multilink retry number`

## DETAILED STEPS

Command or Action	Purpose
<b>Step 1</b> <code>enable</code>  <b>Example:</b> <pre>Router&gt; enable</pre>	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>Enter your password if prompted.</li> </ul>
<b>Step 2</b> <code>configure terminal</code>  <b>Example:</b> <pre>Router# configure terminal</pre>	Enters global configuration mode.
<b>Step 3</b> <code>interface serial <i>number</i></code>  <b>Example:</b> <pre>Router(config)# interface serial 1/1</pre>	Configures an interface and enters interface configuration mode.
<b>Step 4</b> <code>encapsulation frame-relay mfr <i>number</i> [<i>name</i>]</code>  <b>Example:</b> <pre>Router(config-if)# encapsulation frame-relay mfr 1</pre>	Creates a multilink Frame Relay bundle link and associates the link with a bundle.  <b>Tip</b> To minimize latency that results from the arrival order of packets, we recommend bundling physical links of the same line speed in one bundle.
<b>Step 5</b> <code>frame-relay multilink lid <i>name</i></code>  <b>Example:</b> <pre>Router(config-if)# frame-relay multilink lid four</pre>	(Optional) Assigns a bundle link identification name with a multilink Frame Relay bundle link.  <b>Note</b> The bundle link identification (LID) will not go into effect until the interface has gone from the down state to the up state. One way to bring the interface down and back up again is by using the <b>shutdown</b> and <b>no shutdown</b> commands in interface configuration mode.
<b>Step 6</b> <code>frame-relay multilink hello <i>seconds</i></code>  <b>Example:</b> <pre>Router(config-if)# frame-relay multilink hello 20</pre>	(Optional) Configures the interval at which a bundle link will send out hello messages. The default value is 10 seconds.

Command or Action	Purpose
<b>Step 7</b> <b>frame-relay multilink ack <i>seconds</i></b>  <b>Example:</b>  <pre>Router(config-if)# frame-relay multilink ack 10</pre>	(Optional) Configures the number of seconds that a bundle link will wait for a hello message acknowledgment before resending the hello message. The default value is 4 seconds.
<b>Step 8</b> <b>frame-relay multilink retry <i>number</i></b>  <b>Example:</b>  <pre>Router(config-if)# frame-relay multilink retry 5</pre>	(Optional) Configures the maximum number of times a bundle link will resend a hello message while waiting for an acknowledgment. The default value is 2 tries.

## Connecting Frame Relay PVCs Between Routers

By connecting Frame Relay PVCs between routers, you can integrate Frame Relay over a Level 2 VPN backbone, which allows you to use your existing Frame Relay network without upgrading. To connect Frame Relay PVCs between routers, perform the following steps.

### SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **connect *connection-name* mfr *number dlc* l2transport**
4. **xconnect *peer-router-id vcid* encapsulation mpls**

### DETAILED STEPS

Command or Action	Purpose
<b>Step 1</b> <b>enable</b>  <b>Example:</b>  <pre>Router&gt; enable</pre>	Enables privileged EXEC mode. <ul style="list-style-type: none"> <li>• Enter your password if prompted.</li> </ul>
<b>Step 2</b> <b>configure terminal</b>  <b>Example:</b>  <pre>Router# configure terminal</pre>	Enters global configuration mode.

Command or Action	Purpose
<b>Step 3</b> <code>connect connection-name mfr number dlci l2transport</code>  <b>Example:</b>  <pre>Router(config)# connect fr1 mfr 1 100 l2transport</pre>	Defines connections between Frame Relay PVCs. <ul style="list-style-type: none"> <li>Using the <b>l2transport</b> keyword specifies that the PVC will not be a locally switched PVC, but will be tunneled over the backbone network.</li> <li>The <i>connection-name</i> argument is a text string that you provide.</li> <li>The <i>dlci</i> argument is the DLCI number of the PVC that will be connected.</li> </ul> Enters connect configuration submode.
<b>Step 4</b> <code>xconnect peer-router-id vcid encapsulation mpls</code>  <b>Example:</b>  <b>Example:</b>  <b>Example:</b>  <pre>Router(config-fr-pw-switching)# xconnect 10.0.0.1 123 encapsulation mpls</pre>	Creates the VC to transport the Layer 2 packets. In a DLCI-to-DLCI connection type, Frame Relay over MPLS uses the <b>xconnect</b> command in connect configuration submode.

## Verifying Multilink Frame Relay over L2TPv3 AToM

To verify the configuration of Multilink Frame Relay, perform the following steps. The tunnel and session should be in the established (est) state.

### SUMMARY STEPS

1. `show l2tunnel`
2. `show mpls forwarding`

### DETAILED STEPS

#### Step 1 `show l2tunnel`

On both PE routers, use the following command to verify the configuration of Multilink Frame Relay over L2TPv3:

##### Example:

```
PE1# show l2tunnel
```

```
Tunnel and Session Information Total tunnels 1 sessions 1
LocID RemID Remote Name State Remote Address Port Sessions L2TPclass
35788 41451 FRWI1 est 10.9.9.9 0 1 l2tp_default_cl
LocID RemID TunID Username, Intf/ State
```



```

8161          54072          35788          Vcid, Circuit          est
PE2# show l2tunnel
Tunnel and Session Information Total tunnels 1 sessions 1
LocID RemID Remote Name State Remote Address Port Sessions L2TPclass
41451 35788 FRWI3 est 10.8.8.8 0 1
LocID RemID TunID Username, Intf/ State
Vcid, Circuit
54072 8161 41451 6, Fa0/1.6:6 est

```

**Step 2****show mpls forwarding**

On both PE routers, use the following command to verify the configuration of Multilink Frame Relay over MPLS:

**Example:**

PE1# show mpls forwarding

Local tag	Outgoing tag or VC	Prefix or Tunnel Id	Bytes tag switched	Outgoing interface	Next Hop
16	Pop tag	10.0.0.0/24	0	PO4/1/0	point2point
17	Untagged	12ckt(5)	0	MF1	point2point
18	Untagged	12ckt(6)	0	MF1	point2point
19	17	10.9.9.9/32	0	PO4/1/0	point2point

PE2# show mpls forwarding

Local tag	Outgoing tag or VC	Prefix or Tunnel Id	Bytes tag switched	Outgoing interface	Next Hop
16	16	10.8.8.8/32	0	PO2/0	point2point
17	Pop tag	10.13.0.0/24	0	PO2/0	point2point
18	Untagged	12ckt(5)	2244	MF2	point2point
19	Untagged	12ckt(6)	510	MF2	point2point

## Configuration Examples for Multilink Frame Relay over L2TPv3 AToM

- [Frame Relay-to-Frame Relay over L2TPv3 on Multilink Frame Relay Interfaces Example, page 10](#)
- [Frame Relay-to-Ethernet VLAN Interworking over L2TPv3 on Multilink Frame Relay Interfaces Example, page 11](#)
- [Frame Relay-to-Ethernet Interworking over MPLS on Multilink Frame Relay Interfaces Example, page 11](#)
- [MQC Color-Aware Policing Example, page 12](#)
- [DE Bit Matching Example, page 13](#)
- [DLCI-Based queueing Example, page 13](#)
- [Discard Class-Based WRED Example, page 13](#)
- [Aggregate Shaping Example, page 14](#)
- [VC Shaping Example, page 15](#)
- [FECN BECN Marking Example, page 15](#)

## Frame Relay-to-Frame Relay over L2TPv3 on Multilink Frame Relay Interfaces Example

The following example sets up Multilink Frame Relay interfaces to transport Frame Relay data between PE routers:

PE1	PE2
<pre> configure terminal ip cef distributed frame-relay switching ! interface loopback 0  ip address 10.8.8.8 255.255.255.255  no shutdown ! pseudowire-class fr-xconnect  encapsulation l2tp  protocol l2tpv3  ip local interface loopback0 ! controller T3 1/1/1 t1 1 framing esf t1 1 clock source internal t1 1 channel-group 1 timeslots 1-24 speed 64 ! t1 2 framing esf t1 2 clock source inter t1 2 channel-group 1 timeslots 1-24 speed 64 ! interface mfr 1  encapsulation frame-relay  logging event dlci-status-change  frame-relay intf-type nni  no shutdown ! interface Serial1/1/1:1  encapsulation frame-relay mfr1 interface Serial1/1/1:2:1  encapsulation frame-relay mfr1 ! interface POS4/1/0  clock source internal  ip address 10.13.0.0 255.255.255.0  no shutdown  no fair-queue ! connect fr-fr mfr1 206 12 xconnect 10.9.9.9 6 pw-class fr-xconnect ! router ospf 10  network 10.13.0.0 0.0.0.0 area 0  network 10.8.8.8 0.0.0.0 area 0 end </pre>	<pre> configure terminal ip routing ip cef frame-relay switching ! interface loopback 0  ip address 10.9.9.9 255.255.255.255  no shutdown ! interface p2/0  clock source internal  ip address 10.14.0.2 255.255.255.0  no shutdown  no fair-queue ! controller T3 3/1 t1 1 framing esf t1 1 clock source internal t1 1 channel-group 1 timeslots 1-24 speed 64 ! t1 2 framing esf t1 2 clock source internal t1 2 channel-group 1 timeslots 1-24 speed 64 ! interface mfr2  encapsulation frame-relay  logging event dlci-status-change  frame-relay intf-type dce  no shutdown ! interface serial3/1/1:1  encapsulation frame-relay mfr2 ! interface s3/1/2:1  encapsulation frame-relay mfr2 ! pseudowire-class fr-xconnect  encapsulation l2tpv3  protocol l2tpv3  ip local interface loopback0 ! connect fr-fr mfr2 306 12transport xconnect 10.8.8.8 6 pw-class fr-xconnect ! router ospf 10  network 10.14.0.2 0.0.0.0 area 0  network 10.9.9.9 0.0.0.0 area 0 end </pre>

## Frame Relay-to-Ethernet VLAN Interworking over L2TPv3 on Multilink Frame Relay Interfaces Example

The following example sets up Multilink Frame Relay interfaces to perform Frame Relay-to-Ethernet VLAN interworking between PE routers. The example uses IP interworking, also referred to as routed interworking.

PE1	PE2
<pre> configure terminal ip cef distributed frame-relay switching ! interface loopback 0 ip address 10.8.8.8 255.255.255.255 no shutdown ! pseudowire-class ip encapsulation l2tp interworking ip ip local interface loopback0 ! interface mfr 1 encapsulation frame-relay logging event dlci-status-change no shutdown frame-relay intf-type nni ! interface Serial1/1/1/1:1 encapsulation frame-relay mfr1 interface Serial1/1/1/2:1 encapsulation frame-relay mfr1 ! interface POS4/1/0 clock source internal ip address 13.0.0.2 255.255.255.0 no shutdown no fair-queue ! connect fr-vlan mfr1 206 l2 xconnect 9.9.9.913.0.0.2 6 pw-class ip ! router ospf 10 network 10.13.0.2 0.0.0.0 area 0 network 10.8.8.8 0.0.0.0 area 0 end </pre>	<pre> configure terminal ip routing ip cef frame-relay switching ! interface loopback 0 ip address 10.9.9.9 255.255.255.255 no shutdown ! pseudowire-class ip encapsulation l2tp interworking ip ip local interface loopback0 ! interface p2/0 clock source internal ip address 10.14.0.2 255.255.255.0 no shutdown no fair-queue ! interface FastEthernet0/1 no shutdown ! interface FastEthernet0/1.6 encapsulation dot1Q 6 xconnect 10.8.8.8 6 pw-class ip no shutdown ! router ospf 10 network 10.14.0.2 0.0.0.0 area 0 network 10.9.9.9 0.0.0.0 area 0 ! end </pre>

## Frame Relay-to-Ethernet Interworking over MPLS on Multilink Frame Relay Interfaces Example

The following example sets up Multilink Frame Relay interfaces to perform Frame Relay-to-Ethernet interworking between PE routers. The example uses IP interworking, also referred to as routed interworking.

## PE1

```

configure terminal
ip cef distributed
frame-relay switching
!
interface loopback 0
 ip address 10.8.8.8 255.255.255.255
 no shutdown
!
interface mfr 1
 encapsulation frame-relay
 logging event dlci-status-change
 no shutdown
 frame-relay intf-type nni
!
interface Serial1/1/1:1
 encapsulation frame-relay mfr1
interface Serial1/1/1:2:1
 encapsulation frame-relay mfr2
!
interface POS4/1/0
 clock source internal
 ip address 10.13.0.2 255.255.255.0
 no shutdown
 mpls ip
!
router ospf 10
 network 10.13.0.2 0.0.0.0 area 0
 network 10.8.8.8 0.0.0.0 area 0
!
mpls label protocol ldp
mpls ldp router-id loopback0
mpls ip
!
pseudowire-class atom
 encapsulation mpls
 interworking ip
!
connect fr-eth mfr1 207 12
 xconnect 10.9.9.9 7 pw-class atom
!
end

```

## PE2

```

configure terminal
ip routing
ip cef
frame-relay switching
!
interface loopback 0
 ip address 10.9.9.9 255.255.255.255
 no shutdown
!
interface POS2/0
 clock source internal
 ip address 10.14.0.2 255.255.255.0
 no shutdown
 no fair-queue
 mpls ip
!
router ospf 10
 network 10.14.0.2 0.0.0.0 area 0
 network 10.9.9.9 0.0.0.0 area 0
!
mpls label protocol ldp
mpls ldp router-id loopback0
mpls ip
!
pseudowire-class atom
 encapsulation mpls
 interworking ip
!
interface FastEthernet0/1
 xconnect 10.8.8.8 7 pw-class atom
 no shutdown
!
end

```

## MQC Color-Aware Policing Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example configures a VC input policy with a color-aware, two-rate, three-color policing method using a DE bit as input color and setting the tunnel Differentiated Services Code Point (DSCP) based on color. Packets in excess of peak rates are discarded.

```

class-map not-fr-de
match not fr-de
!
policy-map police
class class-default
 police cir 64000 pir 256000
 conform-color not-fr-de
 conform-action set-dscp-tunnel-transmit af31
 exceed-action set-dscp-tunnel-transmit af32
 violate-action drop
!

```

```
interface MFR1
frame-relay interface-dlci 206 switched
class police
!
connect fr-vlan mfr1 206 12
xconnect 10.9.9.9 6 pw-class ip
!
map-class frame-relay police
service-policy input police
```

## DE Bit Matching Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of an interface input policy matching on the DE bit to set the tunnel DSCP:

```
class-map de
match fr-de
!
policy-map de
class de
set ip dscp tunnel af32
class class-default
set ip dscp tunnel af31
!
interface MFR1
service-policy input de
```

## DLCI-Based queueing Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of an interface output policy matching on a QoS group based on the DLCI:

```
class-map dlci100
match fr-dlci 100
class-map dlci200
match fr-dlci 200
!
policy-map dlci
class dlci100
bandwidth percent 10
class dlci200
bandwidth percent 20
!
interface MFR1
service-policy output dlci
```

## Discard Class-Based WRED Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of an interface output policy matching on a QoS group based on the tunnel DSCP:

```
class-map conform
  match ip dscp af31
  match mpls experimental 4
class-map exceed
  match ip dscp af32
  match mpls experimental 3
class-map cos1
  match qos-group 1
!
policy-map core
  class conform
    set qos-group 1
    set discard-class 1
  class exceed
    set qos-group 1
    set discard-class 2
!
policy-map wred
  class cos1
    bandwidth percent 40
    random-detect discard-class-based
    random-detect discard-class 1 20 30 10
    random-detect discard-class 2 1 9 10
!
interface POS1/0
  service-policy input core
!
interface MFR1
  service-policy output wred
```

## Aggregate Shaping Example



### Note

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of an interface aggregate shaping policy with a DLCI-based queueing policy:

```
class-map dlci205
  match fr-dlci 205
class-map dlci206
  match fr-dlci 206
!
policy-map dlci
  class dlci205
    bandwidth 128
  class dlci206
    bandwidth 256
!
policy-map shape
  class class-default
    shape average 512000 2048 2048
  service-policy dlci
!
interface MFR1
  service-policy output shape
```

## VC Shaping Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of a VC output shaping policy with discard class-based WRED:

```
class-map conform
match mpls experimental 4
class-map exceed
match mpls experimental 3
class-map cos1
match qos-group 1
!
policy-map core
class conform
set qos-group 1
set discard-class 1
class exceed
set qos-group 1
set discard-class 2
!
policy-map vc-wred
class class-default
bandwidth percent 40
random-detect discard-class-based
random-detect discard-class 1 20 30 10
random-detect discard-class 2 1 9 10
!
policy-map shape
class class-default
shape average 512000 2048 2048
service-policy vc-wred
!
interface POS4/1/0
service-policy input core
!
interface MFR1
frame-relay interface-dlci 206 switched
class shape
!
map-class frame-relay shape
service-policy output shape
```

## FECN BECN Marking Example

**Note**

Quality of Service features are not supported in Cisco IOS Release 12.4(11)T.

The following example shows the configuration of an output policy that configures BECN and FECN bits:

```
policy-map dlci
class dlci100
bandwidth percent 10
class dlci200
bandwidth percent 20
set fr-fecn-becn 1
interface MFR1
service-policy output dlci
frame-relay congestion-management
threshold ecn 20
```

## Additional References

The following sections provide references related to the Multilink Frame Relay over L2TPv3/AToM feature.

### Related Documents

Related Topic	Document Title
Multilink Frame Relay	<ul style="list-style-type: none"> <li>For the Cisco 7500 series routers: <a href="#">Distributed Multilink Frame Relay (FRF.16)</a></li> <li>For the Cisco 7200 series routers: <a href="#">Multilink Frame Relay (FRF.16)</a></li> </ul>
L2VPN interworking	<a href="#">L2VPN Interworking</a>
Layer 2 Tunneling Protocol, Version 3	L2TPV3
Layer 2 local switching	Layer 2 Local Switching

### Standards

Standard	Title
draft-martini-l2circuit-trans-mpls-08.txt	Transport of Layer 2 Frames Over MPLS
draft-martini-l2circuit-encap-mpls-04.txt	Encapsulation Methods for Transport of Layer 2 Frames Over MPLS
draft-ietf-l2tpext-l2tp-base-03.txt	Layer Two Tunneling Protocol (Version 3)

### MIBs

MIB	MIBs Link
<ul style="list-style-type: none"> <li>Cisco Frame Relay MIB (CISCO-FRAME-RELAY-MIB.my)</li> <li>Interfaces MIB (IF-MIB.my)</li> <li>MPLS LDP MIB (MPLS-LDP-MIB.my)</li> </ul>	<p>To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL:</p> <p><a href="http://www.cisco.com/go/mibs">http://www.cisco.com/go/mibs</a></p>

### RFCs

RFC	Title
RFC 2661	<i>Layer Two Tunneling Protocol</i>



### Technical Assistance

Description	Link
The Cisco Technical Support & Documentation website contains thousands of pages of searchable technical content, including links to products, technologies, solutions, technical tips, and tools. Registered Cisco.com users can log in from this page to access even more content.	<a href="http://www.cisco.com/techsupport">http://www.cisco.com/techsupport</a>

## Command Reference

The following commands are introduced or modified in the feature or features documented in this module. For information about these commands, see the *Cisco IOS Multiprotocol Label Switching Command Reference* at [http://www.cisco.com/en/US/docs/ios/mppls/command/reference/mp\\_book.html](http://www.cisco.com/en/US/docs/ios/mppls/command/reference/mp_book.html). For information about all Cisco IOS commands, go to the Command Lookup Tool at <http://tools.cisco.com/Support/CLILookup> or to the *Cisco IOS Master Commands List*.

- **xconnect**

## Feature Information for Multilink Frame Relay over L2TPv3 AToM

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

**Table 1**      **Feature Information for Multilink Frame Relay over L2TPv3/AToM**

Feature Name	Releases	Feature Information
Multilink Frame Relay over L2TPv3/AToM	12.0(28)S 12.2(25)S 12.0(32)S 12.4(11)T	<p>This feature was introduced in Cisco IOS Release 12.0(28)S for the Cisco 7200 and 7500 series routers.</p> <p>This feature was integrated into Cisco IOS Release 12.2(25)S.</p> <p>In Cisco IOS Release 12.0(32)S, this feature added support for the following pluggable modules for the Cisco 12000 series router: Cisco 4-port channelized T3 (DSO) shared port adapter, Cisco 8-port channelized T1/E1 shared port adapter, and the Cisco 1-port channelized OC-3/ STM-1 shared port adapter.</p> <p>This feature was integrated into Cisco IOS Release 12.4(11)T.</p>

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2011 Cisco Systems, Inc. All rights reserved.