



BECN and FECN Marking for Frame Relay over MPLS

This feature explains the how to configure backward explicit congestion notification (BECN) and forward explicit congestion notification (FECN) bits on packets for Frame Relay over MPLS.

History for the BECN and FECN Marking for Frame Relay over MPLS Feature

Release	Modification
12.0(26)S	This feature was introduced on the Cisco 7200 and 7500 series routers.
12.2(27)SBA	This feature was integrated into Cisco IOS Release 12.2(27)SBA.

Finding Support Information for Platforms and Cisco IOS Software Images

Use Cisco Feature Navigator to find information about platform support and Cisco IOS software image support. Access Cisco Feature Navigator at <http://www.cisco.com/go/fn>. You must have an account on Cisco.com. If you do not have an account or have forgotten your username or password, click **Cancel** at the login dialog box and follow the instructions that appear.

Contents

- [Prerequisites for BECN and FECN Marking for Frame Relay over MPLS, page 2](#)
- [Restrictions for BECN and FECN Marking for Frame Relay over MPLS, page 2](#)
- [Prerequisites for BECN and FECN Marking for Frame Relay over MPLS, page 2](#)
- [How to Configure BECN and FECN Marking for Frame Relay over MPLS, page 3](#)
- [Configuration Examples for BECN and FECN Marking for Frame Relay over MPLS, page 8](#)
- [Additional References, page 8](#)
- [Command Reference, page 10](#)



Corporate Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Copyright © 2005 Cisco Systems, Inc. All rights reserved.

Prerequisites for BECN and FECN Marking for Frame Relay over MPLS

The following prerequisites apply to the Cisco 7500 series router:

- Enable distributed IP CEF globally.
- Use VIP modules for both ingress and egress interfaces.

Restrictions for BECN and FECN Marking for Frame Relay over MPLS

- FECN and BECN marking does not work with L2VPN Interworking. FECN and BECN marking works only with Frame Relay over MPLS in like-to-like configurations.
- FECN and BECN marking does not work with Frame Relay over MPLS with port-to-port connections.
- If you configure the ECN thresholds at the interface level and also configure shaping, unpredictable behavior can occur. The software cannot differentiate between packets that are shaped and packets that experienced interface congestion.
- If you configure ECN thresholds at both the interface level and the class level, only the class-level ECN threshold is used.
- If you do not configure ECN thresholds at the class level, the software inherits the interface-level ECN threshold.
- You cannot configure priority or bandwidth after configuring the class ECN threshold. If you attempt to configure priority or bandwidth when ECN thresholds have been configured, you receive the following error:

```
Please remove set fr-fecn-becn from this class first
```

Information About BECN and FECN Marking for Frame Relay over MPLS

This feature provides congestion management on a provider edge (PE) router's egress interface when Frame Relay traffic is being tunneled across an MPLS cloud. When the congestion queue thresholds configured at the interface or class level of the PE router are exceeded, PE router does the following:

- Sets the FECN bit to 1 on the outgoing packets.
- Sets the BECN bit to 1 for all traffic destined for the originating CE router, which decreases its traffic based on the number of BECN packets it received.

You can configure FECN and BECN marking at the class level with the `command`. You can set up FECN and BECN marking at the interface level with the **threshold ecn** command.

How to Configure BECN and FECN Marking for Frame Relay over MPLS

You can configure BECN and FECN marking at either the class level or the interface level. This section shows both methods and includes the following sections:

- [Configuring BECN and FECN Marking at the Class Level, page 3](#) (Optional)
- [Configuring BECN and FECN Marking at the Interface Level, page 5](#) (Optional)
- [Verifying the Configuration, page 7](#) (Optional)

Configuring BECN and FECN Marking at the Class Level

Use the following steps to enable BECN and FECN marking at the class level, using the `enable` command.

SUMMARY STEPS

1. `enable`
2. `configure terminal`
3. `class-map class-map-name`
4. `match fr-dlci dlci-number`
5. `exit`
6. `policy-map policy-map-name`
7. `class class-name`
8. `priority {kbps | percent percent} [bytes]`
9. `set fr-fecn-becn percent`
10. `exit`
11. `interface type number`
12. `service-policy {input | output} policy-map-name`

DETAILED STEPS

	Command or Action	Purpose
Step 1	<code>enable</code>	Enables privileged EXEC mode. • Enter your password if prompted.
	Example: Router> <code>enable</code>	
Step 2	<code>configure terminal</code>	Enters global configuration mode.
	Example: Router# <code>configure terminal</code>	

How to Configure BECN and FECN Marking for Frame Relay over MPLS

	Command or Action	Purpose
Step 3	class-map <i>class-map-name</i> Example: Router (config)# class-map dcli-100	Specifies the name of the class map to be created and enters class-map configuration mode.
Step 4	match fr-dlci <i>dlci-number</i> Example: Router(config-cmap)# match fr-dlci 100	(Optional) Configures the class map created above to match traffic based on the Frame Relay DLCI number associated with the packet.
Step 5	exit Example: Router(config-cmap)# exit	Exits class-map configuration mode.
Step 6	policy-map <i>policy-map-name</i> Example: Router(config)# policy-map output-policy	Specifies the name of the traffic policy to configure. Names can be a maximum of 40 alphanumeric characters.
Step 7	class <i>class-name</i> Example: (config-pmap)# class dlci-100	Specifies the name of a predefined traffic class, which was configured with the class-map command, used to classify traffic to the traffic policy.
Step 8	priority { <i>kbps</i> percent <i>percent</i> } [<i>bytes</i>] Example: Router(config-pmap-c)# priority 250	(Optional) Specifies the guaranteed allowed bandwidth, in kbps or percentage, for priority (time-sensitive) traffic. The optional <i>bytes</i> argument controls the size of the burst allowed to pass through the system without being considered in excess of the configured kbps rate.
Step 9	set fr-fecn-becn <i>percent</i> Example: Router(config-pmap-c)# set fr-fecn-becn 30	Specifies the allowed maximum class queue size, in percentage. If the class queue depth matches or exceeds the percentage, the software initiates BECN and FECN marking.
Step 10	exit Example: Router(config-pmap-c)# exit	Exits policy-map configuration mode.
Step 11	interface <i>type number</i> Example: Router(config-if)# interface s4/0	Configures an interface (or subinterface) type and enters interface configuration mode.
Step 12	service-policy { input output } <i>policy-map-name</i> Example: Router(config-if)# service-policy output output-policy	Specifies the name of the policy map to be attached to the input or output direction of the interface.

Configuring BECN and FECN Marking at the Interface Level

Use the following steps to enable BECN and FECN marking at the class level, using the **threshold ecn** command.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **class-map** *class-map-name*
4. **match fr-dlci** *dlci-number*
5. **exit**
6. **policy-map** *policy-map-name*
7. **class** *class-name*
8. **priority** {*kbps* | **percent** *percent*} [*bytes*]
9. **exit**
10. **interface** *type number*
11. **service-policy** {**input** | **output**} *policy-map-name*
12. **frame-relay congestion-management**
13. **threshold ecn** *percentage*

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	class-map <i>class-map-name</i> Example: Router (config)# class-map dcli-100	Specifies the name of the class map to be created and enters class-map configuration mode.
Step 4	match fr-dlci <i>dlci-number</i> Example: Router(config-cmap)# match fr-dlci 100	(Optional) Configures the class map created above to match traffic based on the Frame Relay DLCI number associated with the packet.

	Command or Action	Purpose
Step 5	exit Example: Router(config-cmap)# exit	Exits class-map configuration mode.
Step 6	policy-map <i>policy-map-name</i> Example: Router(config)# policy-map output-policy	Specifies the name of the traffic policy to configure. Names can be a maximum of 40 alphanumeric characters.
Step 7	class <i>class-name</i> Example: Router(config-pmap)# class dlci-100	Specifies the name of a predefined traffic class, which was configured with the class-map command, used to classify traffic to the traffic policy.
Step 8	priority { <i>kbps</i> percent <i>percent</i> } [<i>bytes</i>] Example: Router(config-pmap-c)# priority 250	(Optional) Specifies the guaranteed allowed bandwidth, in kbps or percentage, for priority (time-sensitive) traffic. The optional <i>bytes</i> argument controls the size of the burst allowed to pass through the system without being considered in excess of the configured kbps rate.
Step 9	exit Example: Router(config-pmap-c)# exit	Exits policy-map configuration mode.
Step 10	interface <i>type number</i> Example: Router(config-if)# interface s4/0	Configures an interface (or subinterface) type and enters interface configuration mode.
Step 11	service-policy { input output } <i>policy-map-name</i> Example: Router(config-if)# service-policy output output-policy	Specifies the name of the policy map to be attached to the input or output direction of the interface.
Step 12	frame-relay congestion-management Example: Router(config-if)# frame-relay congestion-management	Enables Frame Relay congestion management on all switched PVCs on an interface and enters Frame Relay congestion management configuration mode.
Step 13	threshold ecn <i>percentage</i> Example: Router(config-fr-congest)# threshold ecn 50	Configures the threshold at which ECN bits will be set on packets in switched PVCs on the output interface.

Verifying the Configuration

To verify Frame Relay congestion management on switched PVCs, use the following commands:

- To displays statistics about PVCs for Frame Relay interfaces, issue the **show frame-relay pvc** command:

```
Router# show frame-relay pvc [interface interface] [dlci]
```

- To display information about the configuration and queue at the interface, issue the **show interfaces** command:

```
Router# show interfaces type number
```

For the Cisco 7200 series routers, you can issue the **show hqf interface** command to show the queue size for interface and class. For the Cisco 7500 series routers, log on to VIP slot and issue **show vip hqf** command. For the marking to start, the queue size has to be greater than the aggregate limit multiplied by the threshold ecn percentage.

```
Router # show hqf interface s2/1
```

```
Interface Number 7 (type 53) Serial2/1
  blt (0x61DDB97C, index 0, fast_if_number 8) layer PHYSICAL
  scheduling policy: WFQ
  classification policy: CLASS_BASED
  drop policy: TAIL
  blt flags: 0x0    scheduler: 0x61E9377C

  txcount 1532432 drops 0 qdrops 0 nobuffers 0 flowdrops 0
  qsize 0 qsize_bytes 0 aggregate limit 918 availbuffers 918 weight 1 perc 0.00
  visible_bw 10000000 allocated_bw 10000000 vc_encap 0 ecn_threshold 91
  quantum 1500 credit 0 backpressure_policy 1 scheduler_flags 3F
  calQ[A]->last_sortq 75, calQ[B]->last_sortq 0, leaf_blt 0x61E9372C

  next layer HQFLAYER_CLASS_HIER0 (max entries 256)

  blt (0x61DDB918, index 0, fast_if_number 8) layer CLASS_HIER0
  scheduling policy: FIFO
  classification policy: NONE
  drop policy: TAIL
  blt flags: 0x0    scheduler: 0x61E9372C
  txcount 1532432 drops 0 qdrops 0 nobuffers 0 flowdrops 0
  qsize 0 qsize_bytes 0 aggregate limit 918 availbuffers 918 weight 1 perc 0.00
  visible_bw 10000000 allocated_bw 10000000 vc_encap 0 ecn_threshold 91
  quantum 1500 credit 0 backpressure_policy 1 scheduler_flags 3F
  calQ[A]->last_sortq 75, calQ[B]->last_sortq 0, leaf_blt 0x61E9372C
```

Configuration Examples for BECN and FECN Marking for Frame Relay over MPLS

Table 1 shows two examples of FECN and BECN marking; one at the class level, the other at the interface level.

Table 1 *FECN and BECN Marking at the Class Level and Interface Level Configuration Examples*

Class Level	Interface Level
<pre>class-map match-all dlci-100 match fr-dlci 100 ! policy-map output-policy class dlci-100 bandwidth 250 queue-limit 10 set fr-fecn-becn 30 ! interface Serial2/1 service-policy output output-policy</pre>	<pre>class-map match-all dlci-100 match fr-dlci 100 ! policy-map output-policy class dlci-100 bandwidth 250 ! interface Serial2/1 bandwidth 50000 service-policy output output-policy frame-relay congestion-management threshold ecn 50</pre>

Additional References

Related Documents

Related Topic	Document Title
Frame Relay over MPLS	<i>Any Transport over MPLS</i>

Standards

Standard	Title
None	—

MIBs

MIB	MIBs Link
None	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFC	Title
None	—

Technical Assistance

Description	Link
The Cisco Technical Support website contains thousands of pages of searchable technical content, including links to products, technologies, solutions, technical tips, and tools. Registered Cisco.com users can log in from this page to access even more content.	http://www.cisco.com/techsupport

Command Reference

This section documents modified commands. All other commands used with this feature are documented in the Cisco IOS Release 12.3 command reference publications.

- [frame-relay congestion-management](#)
- [set fr-fecn-becn](#)
- [threshold ecn](#)

frame-relay congestion-management

To enable Frame Relay congestion management functions on all switched permanent virtual circuits (PVCs) on an interface, and to enter Frame Relay congestion management configuration mode, use the **frame-relay congestion-management** command in interface configuration mode. To disable Frame Relay congestion management, use the **no** form of this command.

frame-relay congestion-management

no frame-relay congestion-management

Syntax Description This command has no arguments or keywords.

Defaults Frame Relay congestion management is not enabled on switched PVCs.

Command Modes Interface configuration

Command History	Release	Modification
	12.1(2)T	This command was introduced.
	12.0(26)S	This command was integrated into Cisco IOS Release 12.0(26)S.
	12.2(27)SBA	This command was integrated into Cisco IOS Release 12.2(27)SBA.

Usage Guidelines You must enable Frame Relay switching, using the **frame-relay switching** global command, before you can configure Frame Relay congestion management.

Frame Relay congestion management is supported only when the interface is configured with class-based weighted fair queuing (WFQ).

Examples In the following example, the **frame-relay congestion-management** command enables Frame Relay congestion management on serial interface 1. The command also enters Frame Relay congestion management configuration mode so that congestion threshold parameters can be configured.

```
interface serial1
 encapsulation frame-relay
 frame-relay intf-type dce
 frame-relay congestion-management
 threshold ecn be 0
 threshold ecn bc 20
```

Related Commands	Command	Description
	threshold ecn	Configures the threshold at which ECN bits are set on packets in switched PVCs on the output interface.

set fr-fecn-becn

To enable forward explicit congestion notification (FECN) and backward explicit congestion notification (BECN) with Frame Relay over MPLS, use the **set fr-fecn-becn** command in policy map class configuration mode. To disable the configuration notification, use the **no** form of this command.

set fr-fecn-becn *percent*

no set fr-fecn-becn *percent*

Syntax Description	<i>percent</i>	Specifies how much (percentage) of the total queue size should be used before marking the FECN and BECN bits. The valid range of percentages is 0 to 99. Setting the threshold to 0 indicates that all traffic is marked with FECN and BECN bits.
---------------------------	----------------	---

Defaults	Frame Relay does not perform FECN and BECN marking.
-----------------	---

Command Modes	Policy map class configuration
----------------------	--------------------------------

Command History	Release	Modification
	12.0(26)S	This command was introduced.
	12.2(27)SBA	This command was integrated into Cisco IOS Release 12.2(27)SBA.

Usage Guidelines	This command works only with Frame Relay over MPLS.
	If you configure FECN and BECN bit marking, you cannot configure bandwidth or priority.

Examples	The following example enables marking the FECN and BECN bits when 20 percent of the queue is used: Router(config)# policy-map policy1 Router(config-pmap)# class class1 Router(config-pmap-c)# shape 80000 Router(config-pmap-c)# set fr-fecn-becn 20
-----------------	---

Related Commands	Command	Description
	threshold ecn	Sets the FECN and BECN marking at the interface level.

threshold ecn

To configure the threshold at which explicit congestion notification (ECN) bits will be set on packets in switched permanent virtual circuits (PVCs) on the output interface, use the **threshold ecn** command in Frame Relay congestion management configuration mode. To remove the threshold configuration, use the **no** form of this command.

For Frame Relay Switching

threshold ecn { **bc** | **be** } *percentage*

no threshold ecn { **bc** | **be** } *percentage*

For Frame Relay over MPLS

threshold ecn *percentage*

no threshold ecn *percentage*

Syntax Description	bc	Specifies threshold for committed traffic. This keyword is not available for Frame Relay over MPLS.
	be	Specifies threshold for excess traffic. This keyword is not available for Frame Relay over MPLS.
	<i>percentage</i>	Threshold at which ECN bits will be set on packets, specified as a percentage of maximum queue size.

Defaults	100 percent
-----------------	-------------

Command Modes	Frame Relay congestion management configuration
----------------------	---

Command History	Release	Modification
	12.1(2)T	This command was introduced.
	12.0(26)S	This command was modified for Frame Relay over MPLS.
	12.2(27)SBA	This command was integrated into Cisco IOS Release 12.2(27)SBA.

Usage Guidelines	You must enable Frame Relay congestion management on the interface before congestion management parameters will be effective. To enable Frame Relay congestion management and to enter Frame Relay congestion management configuration mode, use the frame-relay congestion-management interface command.
-------------------------	--

Frame Relay Switching Guidelines

- You must enable Frame Relay switching, using the **frame-relay switching** global command, before the **threshold ecn** command will be effective on switched PVCs.

- You can configure separate queue thresholds for committed and excess traffic.
- Configure the Be ECN threshold so that it is greater than or equal to zero and less than or equal to the Bc ECN threshold. Configure the Bc ECN threshold so that it is less than or equal to 100.

Examples

Frame Relay Switching Example

The following example shows how to configure a Be threshold of 0 and a Bc threshold of 20 percent on serial interface 1.

```
interface serial1
  encapsulation frame-relay
  frame-relay congestion-management
    threshold ecn be 0
    threshold ecn bc 20
```

Frame Relay over MPLS Example

The following example shows a configuration of interface serial2/1 for a threshold of 50 percent.

```
interface Serial2/1
  bandwidth 50000
  service-policy output output-policy
  frame-relay congestion-management
    threshold ecn 50
```

Related Commands

Command	Description
frame-relay congestion-management	Enables Frame Relay congestion management functions on all switched PVCs on an interface, and enters congestion management configuration mode.
frame-relay switching	Enables PVC switching on a Frame Relay DCE or NNI.

Cisco logo, and Welcome to the Human Network are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, FrameShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuick Study, LightStream, MGX, Networkers, Networking Academy, Network Registrar, PIX, ProConnect, ScriptShare, SMARTnet, StackWise, The Fastest Way to Increase Your ROI, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

Trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership with Cisco and any other company. (0711R)

Copyright © 2005 Cisco Systems, Inc. All rights reserved.