



# 1-Port G.SHDSL WAN Interface Card for Cisco 2600 Series and Cisco 3600 Series Routers

---

This document describes the Multirate Symmetrical High-Speed Digital Subscriber Line (G.SHDSL) feature supported on the 1-port G.SHDSL WAN interface card (WIC) (WIC-1SHDSL) on Cisco 2600 series and Cisco 3600 series routers in Cisco IOS Release 12.2(8)T.

G.SHDSL is an ATM-based, multirate, high-speed (up to 2.3 MB), symmetrical digital subscriber line technology for data transfer between a single customer premises equipment (CPE) subscriber and a central office.

G.SHDSL is supported on the G.SHDSL WAN interface card (WIC-1SHDSL), a 1-port WAN interface card (WIC) for Cisco 2600 series and Cisco 3600 series routers.

The G.SHDSL WIC is compatible with the Cisco 6015, Cisco 6130, Cisco 6160, and Cisco 6260 Digital Subscriber Line Access Multiplexers (DSLAMs). The DSLAM must be equipped with G.SHDSL line cards that are compatible with the DSL service to be configured.

The G.SHDSL WIC supports ATM Adaptation Layer 2 (AAL2), ATM Adaptation Layer 5 (AAL5), and various classes of service for ATM.

## Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the “[Feature Information for 1-Port G.SHDSL WAN Interface Card](#)” section on page 14.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.

## Contents

- <<Text.>>



## Prerequisites for 1-Port G.SHDSL WAN Interface Card

A G.SHDSL WIC must be installed in the router to match the DSL service to be configured. A compatible G.SHDSL line card must be installed in the DSLAM.

## Restrictions for 1-Port G.SHDSL WAN Interface Card

- The G.SHDSL WIC does not support dual latency. When the DSL link is intended to support both voice and data traffic simultaneously, the total supported data rate must be reduced to adjust for the reduced coding gain, which is usually present with high-latency traffic.
- The G.SHDSL WIC does not support Dying Gasp in ANSI T1.413 Issue 2.
- The G.SHDSL WIC does not support available bit rate (ABR) class of service (CoS).
- The G.SHDSL WIC should be inserted only into onboard WIC slots or 1FE2W, 2W, 1FE1R, 2FE2W network modules. This WIC is not supported in old combination network modules.

## Information About 1-Port G.SHDSL WAN Interface Card

- [Benefits, page 2](#)

## Benefits

- Enables business-class broadband service with voice integration, scalable performance, flexibility, and security.
- Symmetrical WAN speeds (up to 2.3Mbps) over a single copper pair.
- Repeatable and has thirty percent longer reach than SDSL.
- Rate adaptive with G.HS “handshake” Protocol.
- Based on ITU Recommendation G.991.2 (Accepted Worldwide).
- Support for G.SHDSL Annex A (U.S. signaling) and Annex B (European signaling).
- Multiple G.SHDSL WAN Interface Cards configurable per Cisco 2600 series and Cisco 3600 series chassis.
- Toll-quality voice over IP delivery over AAL2 and AAL5.
- Provides ATM traffic management to enable service providers to manage their core ATM network infrastructures.
- Supports ATM class of service features constant bit rate (CBR), variable bit rate-nonreal time (VBR-nrt), variable bit rate-real time (VBR-rt), and unspecified bit rate (UBR and UBR+).
- Operates back-to-back or through a DSLAM.
- Sustains up to 23 virtual circuits per WAN on a WIC in Cisco 2600 series and Cisco 3600 series routers.

# How to Configure 1-Port G.SHDSL WAN Interface Card

- [Configuring G.SHDSL on a Cisco Router, page 3](#) (required)
- [Configuring ILMI on the DSLAM Connected to the G.SHDSL WIC, page 5](#) (optional)
- [Verifying ATM Configuration, page 5](#) (optional)

## Configuring G.SHDSL on a Cisco Router

To configure G.SHDSL service on a Cisco router containing a G.SHDSL WIC, complete the following steps, beginning in global configuration mode:

Command	Purpose
<b>Step 1</b> Router(config)# <b>interface atm 1/0</b>	<p>Enters ATM configuration mode for interface ATM 0 in slot 1.</p> <p><b>Note</b> If a slot has two subslots for WIC modules and no ATM interface is present in subslot 0, the WIC will take ATM x/0 as its interface number even if placed in subslot 1 (ATMx/1).</p> <p>If a two-port ATM module is present in subslot 0, the WIC will use ATM x/2 as its interface number. This subslot number is pertinent to all interface commands such as <b>show interface atm</b> and <b>show dsl interface atm</b>.</p>
<b>Step 2</b> Router(config-if)# <b>ip-address IP-address</b>	Assigns an IP address to the DSL ATM interface.
<b>Step 3</b> Router(config-if)# <b>atm ilmi-keepalive seconds</b>	<p>(Optional) Enables Integrated Local Management Interface (ILMI) keepalives.</p> <p>If you enable ILMI keepalives without specifying the seconds, the default time interval is 3 seconds.</p>
<b>Step 4</b> Router(config-if)# <b>pvc [name] vpi/vci</b>	<p>Enters atm-virtual-circuit (interface-atm-vc) configuration mode, and configures a new ATM permanent virtual circuit (PVC) by assigning a name (optional) and VPI/VCI numbers.</p> <p>The default traffic shaping is an unspecified bit rate (UBR); the default encapsulation is AAL5+LLC/SNAP.</p>
<b>Step 5</b> Router(config-if-vc)# <b>protocol ip IP-address</b>	(Optional) Enables IP connectivity and create a point-to-point IP address for the virtual circuit (VC).
<b>Step 6</b> Router(config-if-vc)# <b>vbr-rt peak-rate average-rate burst</b>	<p>(Optional) Configures the PVC for real-time variable bit rate (VBR) traffic shaping.</p> <ul style="list-style-type: none"> <li>• <i>Peak rate</i>—Peak information rate (PIR)</li> <li>• <i>Average rate</i>—Average information rate (AIR)</li> <li>• <i>Burst</i>—Burst size in cells</li> </ul>

## How to Configure 1-Port G.SHDSL WAN Interface Card

Command	Purpose
<b>Step 7</b> Router(config-if-vc)# <b>encapsulation</b> {aal1   aal2   aal5ciscopp   aal5mux   aal5nlpid   aal5snap}	<p>(Optional) Configures the ATM adaptation layer (AAL) and encapsulation type.</p> <ul style="list-style-type: none"> <li>• <b>aal1</b>—AAL1</li> <li>• <b>aal2</b>—AAL2</li> <li>• <b>aal5ciscopp</b>—Cisco PPP over AAL5</li> <li>• <b>aal5mux</b>—AAL5+MUX</li> <li>• <b>aal5nlpid</b>—AAL5+NLPID</li> <li>• <b>aal5snap</b>—AAL5+LLC/SNAP</li> </ul> <p>The default is <b>aal5snap</b>.</p>
<b>Step 8</b> Router(config-if-vc)# <b>exit</b>	Exits from interface-atm-vc configuration mode.
<b>Step 9</b> Router(config-if)# <b>ds1 operating-mode</b> {gshdsl symmetric annex {A   B}}	<p>Configures the DSL interface to operate in a specified DSL mode:</p> <ul style="list-style-type: none"> <li>• <b>gshdsl</b>—Configures multirate, high-speed DSL per ITU G.991.2</li> <li>• <b>symmetric</b>—Configures symmetrical mode per ITU G.992.1.</li> <li>• <b>annex</b>—Configures the regional operating parameters.</li> <li>• <b>A</b>—Sets the operating parameters for North America. This value is the default.</li> <li>• <b>B</b>—Sets the operating parameters for Europe.</li> </ul> <p>The default is <b>gshdsl symmetric annex A</b>.</p>
<b>Step 10</b> Router(config-if)# <b>equipment-type</b> {co   cpe}	<p>Configures the DSL interface to function as central office equipment or customer premises equipment:</p> <ul style="list-style-type: none"> <li>• <b>co</b>—The WIC functions as central office equipment and can interface with another G.SHDSL WIC configured as <b>cpe</b>.</li> <li>• <b>cpe</b>—The WIC functions as customer premises equipment and can interface with a DSLAM or with another G.SHDSL WIC configured as <b>co</b>.</li> </ul> <p>The default is <b>cpe</b>.</p>
<b>Step 11</b> Router(config-if)# <b>ds1 linerate</b> {kbps   auto }	<p>Configures the DSL line rate:</p> <ul style="list-style-type: none"> <li>• <b>kbps</b>—Line rate (data transfer rate) in kilobits per second. Allowable entries are <b>72, 136, 200, 264, 392, 520, 776, 1032, 1160, 1544, 2056</b>, and <b>2312</b>.</li> <li>• <b>auto</b>—The WIC automatically trains for an optimal line rate by negotiating with the far-end DSLAM or WIC.</li> </ul> <p>The default is <b>auto</b>.</p>
<b>Step 12</b> Router(config-if)# <b>exit</b>	Exits from ATM interface configuration mode.
<b>Step 13</b> Router(config)# <b>exit</b>	Exits from global configuration mode.
<b>Step 14</b> Router# <b>show interface atm 1/0</b>	Verifies the ATM interface configuration.
<b>Step 15</b> Router# <b>clear interface atm 1/0</b>	Permits the configuration changes to take effect.

## Configuring ILMI on the DSLAM Connected to the G.SHDSL WIC

The ILMI protocol allows DSLAMs to be used for ATM address registration across an ATM User-Network Interface (UNI). If ILMI is configured on the G.SHDSL WIC, the ATM PVC must be configured on the DSLAM. All switch terminating connections use interface 0/0 to connect to the switch CPU.

For information about configuring the DSLAM, see the *Configuration Guide for Cisco DSLAMs with NI-2*.

## Verifying ATM Configuration

Use the following commands to verify your configuration:

- To verify current configuration and to view the status for all controllers, use the **show running-config** command.
- To view ATM controller statistics, use the **show controllers atm slot/port** command.
- To verify the PVC status, use the **show atm vc** command. Make sure that active PVCs are up.
- To help identify ATM related events as they are generated, use the **debug atm events** command.
- To indicate which interfaces are having trouble, use the **debug atm errors** command.
- To identify an entry for the ATM interface you configured and to show an entry for the ATM slot/port you configured, use the **show ip route** command.
- To view the status of ATM interface, use the **show interface atm** command. Make sure that the ATM slot/port and the line protocol are up, as shown in the following example:

```
Router# show interface atm 1/0
ATM1/0 is up, line protocol is up
Hardware is DSLSAR (with Globespan G.SHDSL Module)
MTU 4470 bytes, sub MTU 4470, BW 800 Kbit, DLY 2560 usec,
    reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ATM, loopback not set
Keepalive not supported
Encapsulation(s):AAL5 AAL2, PVC mode
24 maximum active VCs, 256 VCs per VP, 2 current VCCs
VC idle disconnect time:300 seconds
Last input never, output 00:00:01, output hang never
Last clearing of "show interface" counters 03:16:00
Queueing strategy:fifo
Output queue 0/40, 0 drops; input queue 0/75, 0 drops
30 second input rate 0 bits/sec, 0 packets/sec
30 second output rate 0 bits/sec, 0 packets/sec
    2527 packets input, 57116 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    10798 packets output, 892801 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 output buffer failures, 0 output buffers swapped out
```

Interface	VCD / Name	VPI	VCI	Type	Encaps	SC	Peak Kbps	Avg/Min Kbps	Burst Cells	Sts
1/0.3	2	9	36	PVC	MUX	UBR	800			UP
1/0.2	1	9	37	PVC	SNAP	UBR	800			UP

```
Router# show controllers atm 1/0
Interface ATM1/0 is up
```

## How to Configure 1-Port G.SHDSL WAN Interface Card

```

Hardware is DSLSAR (with Globespan G.SHDSL Module)
IDB: 62586758 Instance:6258E054 reg_dslsar:3C810000 wic_regs:3C810080
PHY Inst:62588490 Ser0Inst:62573074 Ser1Inst: 6257CBD8 us_bwidth:800
Slot: 1 Unit: 1 Subunit: 0 pkt Size:4496
VCperVP:256 max_vp: 256 max_vc: 65536 total vc:2
rct_size:65536 vpivcibit:16 connTblVCI:8 vpi_bits:8
vpvc_sel:3 enabled: 0 throttled:0

WIC Register Value Notes
-----
FPGA Dev ID (LB) 0x44 'D'
FPGA Dev ID (UB) 0x53 'S'
FPGA Revision 0x99
WIC Config Reg 0x45 WIC / VIC select = WIC;
                      CTRLE addr bit 8 = 1;
                      OK LED on;
                      LOOPBACK LED off;
                      CD LED on;
WIC Config Reg2 0x07 Gen bus error on bad ADSL access
Int 0 Enable Reg 0x03 ADSL normal interrupt enabled
                      ADSL error interrupt enabled

```

- To view the status of the G.SHDSL modem, use the **show dsl interface atm** command. If the line is down, the following statement appears: Line is not active. Some of the values may not be accurate. You can also verify whether the equipment type and operating mode configuration are correct for your application.

### Sample output—The WIC is configured as central office equipment, and the line is up

```

Router# show dsl interface atm 0/0
Globespan G.SHDSL Chipset Information

Equipment Type: Central Office
Operating Mode: G.SHDSL
Clock Rate Mode: Auto rate selection Mode
Reset Count: 2
Actual rate: 2320 Kbps
Modem Status: Data
Noise Margin: 43 dB
Loop Attenuation: 0.0 dB
Transmit Power: 13.5 dB
Receiver Gain: 204.8000 dB
Last Activation Status:No Failure
CRC Errors: 0
Chipset Version: 1
Firmware Version: R1.0

Farend Statistics since CO boot-time:

CRC Errors: 0
Errored Seconds: 0
Severly ES: 0
Un Available S: 48
Loss Of Sync S: 0

```

### Sample output—The WIC is configured as customer premises equipment, and the line is up

```

Router# show dsl interface atm 0/0
Globespan G.SHDSL Chipset Information

Equipment Type: Customer Premise
Operating Mode: G.SHDSL

```

```

Clock Rate Mode:          Auto rate selection Mode
Reset Count:              1
Actual rate:              2320 Kbps
Modem Status:             Data
Noise Margin:              42 dB
Loop Attenuation:         0.0 dB
Transmit Power:           13.5 dB
Receiver Gain:            204.8000 dB
Last Activation Status:   No Failure
CRC Errors:                0
Chipset Version:           1
Firmware Version:          R1.0

```

## Configuration Examples for 1-Port G.SHDSL WAN Interface Card

This section provides the following configuration examples:

- [“Configuration in CPE Mode Example” section on page 7](#)
- [Configuration in CO Mode Example, page 10](#)

### Configuration in CPE Mode Example

The following example shows a G.SHDSL configuration of VoATM over AAL2, operating in customer premises equipment (CPE) mode, on a Cisco 2600 series router. This router in CPE mode can be linked to either a DSLAM or to another router that is configured to operate in central office (CO) mode.

```

Router#
Router# show running config

Building configuration...

version 12.2
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname host1
!
memory-size iomem 10
voice-card 1
!
ip subnet-zero
ip host host2 225.255.255.224
!
no mgcp timer receive-rtcp
call rsvp-sync
!
!
controller T1 1/0
framing esf
linecode b8zs
ds0-group 0 timeslots 1 type e&m-wink-start
ds0-group 1 timeslots 2 type e&m-wink-start
.
.
ds0-group 23 timeslots 24 type e&m-wink-start
!
```

**■ Configuration Examples for 1-Port G.SHDSL WAN Interface Card**

```

controller T1 1/1
  framing esf
  linecode b8zs
!
interface Ethernet0/0
  ip address 209.165.202.128 255.255.255.224
  half-duplex
  no cdp enable
!
interface Serial0/0
  no ip address
  shutdown
!
interface ATM0/1
  ip address 209.165.201.1 255.255.255.224
  dsl operating-mode gshdsl symmetric annex A
  dsl equipment-type cpe
  dsl linerate auto
  load-interval 30
  atm vc-per-vp 256
  no atm ilmi-keepalive
  pvc 10/100
    vbr-rt 672 672 512
    encapsulation aal2
  !
  pvc 10/200
    protocol ip 209.165.202.159 broadcast
    encapsulation aal5snap
  !
  no fair-queue
!
interface Ethernet0/1
  no ip address
  shutdown
!
ip classless
ip route 209.165.202.128 255.255.255.224 Ethernet0/0
no ip http server
!
!
snmp-server engineID local 000000090200003080477F20
snmp-server manager
!
voice-port 1/0:0
  local-alerting
  timeouts wait-release 3
  connection trunk 3001
!
voice-port 1/0:1
  local-alerting
  timeouts wait-release 3
  connection trunk 3002
.
.
.
voice-port 1/0:23
  local-alerting
  timeouts wait-release 3
  connection trunk 3024
  shutdown
!
dial-peer cor custom
!
dial-peer voice 3001 voatm

```

```
destination-pattern 3001
called-number 4001
session protocol aal2-trunk
session target ATM0/1 pvc 10/100 31
codec aal2-profile ITUT 1 g711ulaw
no vad
!
dial-peer voice 3002 voatm
destination-pattern 3002
called-number 4002
session protocol aal2-trunk
session target ATM0/1 pvc 10/100 32
codec aal2-profile custom 100 g726r32
no vad
!
dial-peer voice 3003 voatm
destination-pattern 3003
called-number 4003
session protocol aal2-trunk
session target ATM0/1 pvc 10/100 33
codec aal2-profile ITUT 7 g729abr8
no vad
.
.
.
dial-peer voice 3024 voatm
destination-pattern 3024
called-number 3024
session protocol aal2-trunk
session target ATM0/1 pvc 10/100 54
codec aal2-profile ITUT 7 g729abr8
no vad
!
dial-peer voice 1 pots
destination-pattern 4001
port 1/0:0
!
dial-peer voice 2 pots
destination-pattern 4002
port 1/0:1
.
.
.
dial-peer voice 24 pots
destination-pattern 4024
port 1/0:23
!
!
line con 0
exec-timeout 0 0
transport input none
line aux 0
line vty 0 4
login
!
no scheduler allocate
end
```

## Configuration in CO Mode Example

The following example shows a G.SHDSL configuration of VoATM over AAL2, operating in central office (CO) mode, on a Cisco 2600 series router. This router in CO mode can be linked to another router that is configured to operate in CPE mode.

```

Router#
version 12.2
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname host2
!
memory-size iomem 10
voice-card 1
!
ip subnet-zero
ip host host2 225.255.255.224
!
no mgcp timer receive-rtcp
call rsvp-sync
!
!
controller T1 1/0
framing esf
linecode b8zs
ds0-group 0 timeslots 1 type e&m-wink-start
ds0-group 1 timeslots 2 type e&m-wink-start
.
.
.
ds0-group 23 timeslots 24 type e&m-wink-start
!
controller T1 1/1
framing esf
linecode b8zs
!
interface Ethernet0/0
ip address 209.165.202.128 255.255.255.224
half-duplex
no cdp enable
!
interface Serial0/0
no ip address
shutdown
!
interface ATM0/1
ip address 209.165.201.1 255.255.255.224
dsl operating-mode gshdsl symmetric annex A
dsl equipment-type co
dsl linerate auto
load-interval 30
atm vc-per-vp 256
no atm ilmi-keepalive
pvc 10/100
  vbr-rt 672 672 512
  encapsulation aal2
!
pvc 10/200
  protocol ip 209.165.202.159 broadcast
  encapsulation aal5snap
!
```

```
no fair-queue
!
interface Ethernet0/1
  no ip address
  shutdown
!
ip classless
ip route 209.165.202.128 255.255.255.224 Ethernet0/0
no ip http server
!
!
snmp-server engineID local 00000090200003080477F20
snmp-server manager
!
voice-port 1/0:0
  local-alerting
  timeouts wait-release 3
  connection trunk 3001
!
voice-port 1/0:1
  local-alerting
  timeouts wait-release 3
  connection trunk 3002
.
.
.
voice-port 1/0:23
  local-alerting
  timeouts wait-release 3
  connection trunk 3024
  shutdown
!
dial-peer cor custom
!
dial-peer voice 3001 voatm
  destination-pattern 3001
  called-number 4001
  session protocol aal2-trunk
  session target ATM0/1 pvc 10/100 31
  codec aal2-profile ITUT 1 g711ulaw
  no vad
!
dial-peer voice 3002 voatm
  destination-pattern 3002
  called-number 4002
  session protocol aal2-trunk
  session target ATM0/1 pvc 10/100 32
  codec aal2-profile custom 100 g726r32
  no vad
!
dial-peer voice 3003 voatm
  destination-pattern 3003
  called-number 4003
  session protocol aal2-trunk
  session target ATM0/1 pvc 10/100 33
  codec aal2-profile ITUT 7 g729abr8
  no vad
.
.
.
dial-peer voice 3024 voatm
  destination-pattern 3024
  called-number 3024
  session protocol aal2-trunk
```

## ■ Additional References

```

session target ATM0/1 pvc 10/100 54
codec aal2-profile ITUT 7 g729abr8
no vad
!
dial-peer voice 1 pots
destination-pattern 4001
port 1/0:0
!
dial-peer voice 2 pots
destination-pattern 4002
port 1/0:1
.
.
.
dial-peer voice 24 pots
destination-pattern 4024
port 1/0:23
!
!
line con 0
exec-timeout 0 0
transport input none
line aux 0
line vty 0 4
login
!
no scheduler allocate
end

```

# Additional References

## Related Documents

Related Topic	Document Title
Cisco IOS commands	<i>Cisco IOS Master Commands List, All Releases</i>
Voice configuration	<ul style="list-style-type: none"> <li>• <i>Cisco IOS Voice, Video, and Fax Configuration Guide</i>, Release 12.2</li> <li>• <i>Cisco IOS Voice, Video, and Fax Command Reference</i>, Release 12.2</li> </ul>
Configuring IP	<i>Cisco IOS IP Configuration Guide</i> , Release 12.2
Configuring ATM	<i>Configuring ATM</i> in the <i>Wide-Area Networking Configuration Guide</i> , Release 12.2.
Configuring a DSLAM	<i>Configuration Guide for Cisco DSLAMs with NI-2</i>
Installing Cisco 2600 series hardware	<a href="http://www.cisco.com/univercd/cc/td/doc/product/access/acs_mod/cis2600/index.htm">http://www.cisco.com/univercd/cc/td/doc/product/access/acs_mod/cis2600/index.htm</a>
Installing Cisco 3600 series hardware	<a href="http://www.cisco.com/univercd/cc/td/doc/product/access/acs_mod/cis3600/index.htm">http://www.cisco.com/univercd/cc/td/doc/product/access/acs_mod/cis3600/index.htm</a>

## Standards

Standard	Title
Supports ITU-T G.991.2	<i>SHDSL</i>

## MIBs

MIB	MIBs Link
• None	To locate and download MIBs for selected platforms, Cisco software releases, and feature sets, use Cisco MIB Locator found at the following URL: <a href="http://www.cisco.com/go/mibs">http://www.cisco.com/go/mibs</a>

## RFCs

RFC	Title
None	—

## Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	<a href="http://www.cisco.com/cisco/web/support/index.html">http://www.cisco.com/cisco/web/support/index.html</a>

# Feature Information for 1-Port G.SHDSL WAN Interface Card

**Table 1** lists the release history for this feature.

Use Cisco Feature Navigator to find information about platform support and software image support. Cisco Feature Navigator enables you to determine which software images support a specific software release, feature set, or platform. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.



**Note**

**Table 1** lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

**Table 1** *Feature Information for 1-Port G.SHDSL WAN Interface Card*

Feature Name	Releases	Feature Information
1-Port G.SHDSL WAN Interface Card	12.2(4)XL 12.2(8)T	<p>G.SHDSL is an ATM-based, multirate, high-speed (up to 2.3 MB), symmetrical digital subscriber line technology for data transfer between a single customer premises equipment (CPE) subscriber and a central office.</p> <p>The following sections provide information about this feature: Cisco 2610, Cisco 2611, Cisco 2612, Cisco 2613, Cisco 2620, Cisco 2621, Cisco 2650, Cisco 2651, Cisco 3620, Cisco 3631, Cisco 3640, Cisco 3661, Cisco 3662.</p> <p>The following commands were introduced or modified: <b>dsl equipment-type</b>, <b>dsl linerate</b>, <b>dsl operating-mode (G.SHDSL)</b> .</p>

# Glossary

**ABR**—available bit rate.

**ADSL**—asymmetric digital subscriber line. Available through several telecommunications carriers to accommodate the need for increased bandwidth for Internet access and telecommuting applications.

**ATM**—Asynchronous Transfer Mode. International standard for cell relay in which multiple service types (such as voice, video, or data) are conveyed in fixed-length (53-byte) cells. Fixed-length cells allow cell processing to occur in hardware, thereby reducing transit delays. ATM is designed to take advantage of high-speed transmission media such as E3, SONET, and T3.

**CLI**—command-line interface.

**CO**—central office. Local exchange (local switch) that terminates individual local telephone subscriber lines for switching, and connects to the public network. A CO is known as a class 5 switch office. For example, 5ESS by Lucent and DMS 100 by Nortel.

**CPE**—customer premise equipment. Devices such as channel service units (CSUs)/data service units (DSUs), modems, and ISDN terminal adapters, required to provide an electromagnetic termination for wide-area network circuits before connecting to the router or access server. This equipment was historically provided by the telephone company, but is now typically provided by the customer in North American markets.

**DSL**—digital subscriber line available through several telecommunications carriers to accommodate the need for increased bandwidth for Internet access and telecommuting applications.

**FXO**—foreign exchange office. An FXO interface connects to a central office.

**FXS**—foreign exchange station. An FXS interface connects directly to a standard telephone, supplying ring voltage, dial tone, and so on.

**G.SHDSL**—Multirate Symmetrical High-Speed Digital Subscriber Line

**IAD**—integrated access device. A CPE device used to combine services from various sources onto a common platform for transmission on a common transport span. Typically, an IAD combines various voice and data services such as circuit-based services like traditional POTS and packet-switched services such as frame relay or ATM.

**PVC**—permanent virtual circuit.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2008 Cisco Systems, Inc. All rights reserved.

**Glossary**