



## Release Notes for Cisco 8000 Series Routers, IOS XR Release 7.3.2

<a href="#">Cisco 8100, 8200, and 8800 Series</a>	<a href="#">2</a>
<a href="#">What's New in Cisco IOS XR Release 7.3.2</a>	<a href="#">2</a>
<a href="#">Release 7.3.2 Packages</a>	<a href="#">10</a>
<a href="#">Cisco IOS XR Caveats</a>	<a href="#">13</a>
<a href="#">Determine Software Version</a>	<a href="#">13</a>
<a href="#">Determine Firmware Support</a>	<a href="#">14</a>
<a href="#">Supported Transceiver Modules</a>	<a href="#">19</a>
<a href="#">Other Important Information</a>	<a href="#">19</a>
<a href="#">Full Cisco Trademarks with Software License</a>	<a href="#">21</a>

Revised: January 12, 2023

# Cisco 8100, 8200, and 8800 Series

## What's New in Cisco IOS XR Release 7.3.2

Cisco is continuously enhancing the product with every release and this section covers a brief description of key features and enhancements. It also includes links to detailed documentation, where available.

### Software Features Introduced and Enhanced

To learn about features introduced in other Cisco IOS XR releases, select the release from the [What's new](#) page.

Feature	Description
<b>System Error Messages</b>	
<a href="#">System Error Messages</a>	An intuitive interface to view, search, compare, and download Cisco IOS XR Error Messages.
<b>System Setup</b>	
<a href="#">Secure Zero Touch Provisioning with Removable Storage Device</a>	This feature allows you to securely sign onboarding data in a removable storage device so that you can use the device for secure ZTP operations. This support gives you the plug-and-play flexibility for ZTP without any additional infrastructure requirements.
<b>Telemetry</b>	
<a href="#">Stream Telemetry Data about PBR Decapsulation Statistics</a>	This feature streams telemetry data about header decapsulation statistics for traffic that uses the Policy-Based Routing (PBR) functionality to bypass a routing table lookup for egress. You use the <code>Cisco-IOS-XR-infra-policymgr-oper.yang</code> data model to capture the decapsulation data for Generic Routing Encapsulation (GRE) and Generic UDP Encapsulation (GUE) tunneling protocols. Decapsulation data helps you understand if all encapsulated packets are decapsulated and alerts you to issues if there is a mismatch in the number of packets.
<b>Programmability</b>	
<a href="#">Contextual Script Infrastructure</a>	When you create and run Python scripts on the router, this feature enables a contextual interaction between the scripts, the IOS XR software, and the external servers. This context, programmed in the script, uses Cisco IOS XR Python packages, modules, and libraries to: <ul style="list-style-type: none"><li>• obtain operational data from the router</li><li>• set configurations and conditions</li><li>• detect events in the network and trigger an appropriate action</li></ul>

Feature	Description
<a href="#">Enhancements to openconfig-platform YANG data model</a>	<p>The openconfig-platform YANG data model provides a structure for querying hardware and software router components via the NETCONF protocol. This release delivers an enhanced openconfig-platform YANG data model to provide information about:</p> <ul style="list-style-type: none"> <li>• software version</li> <li>• golden ISO (GISO) label</li> <li>• committed IOS XR packages</li> </ul> <p>You can access this data model from the <a href="#">Github</a> repository.</p>
<a href="#">Manage Automation Scripts Using YANG RPCs</a>	<p>This feature enables you to use remote procedure calls (RPCs) on YANG data models to perform the same automated operations as CLIs, such as edit configurations or retrieve router information.</p>
<a href="#">Model-driven CLI to Display Running Configuration in XML and JSON Formats</a>	<p>This feature enables you to display the configuration data for Cisco IOS XR platforms in both JSON and XML formats.</p> <p>This feature introduces the <b>show run   [xml   json]</b> command.</p>
<a href="#">Model-driven CLI to Show YANG Operational Data</a>	<p>This feature enables you to use a traditional CLI command to display YANG data model structures on the router console and also obtain operational data from the router in JSON or XML formats. The functionality helps you transition smoothly between CLI and YANG models, easing data retrieval from your router and network.</p> <p>This feature introduces the <b>show yang operational</b> command.</p>
<a href="#">Operational Simplicity Using Automation Scripts</a>	<p>This feature lets you host and execute your automation scripts directly on a router running IOS XR software, instead of managing them on external controllers. The scripts available on-box can now leverage Python libraries, access the underlying router information to execute CLI commands, and monitor router configurations continuously. This results in setting up a seamless automation workflow by improving connectivity, access to resources, and speed of script execution.</p> <p>The following categories of on-box scripts are used to achieve operational simplicity:</p> <ul style="list-style-type: none"> <li>• <a href="#">Config scripts</a></li> <li>• <a href="#">Exec scripts</a></li> <li>• <a href="#">Process scripts</a></li> <li>• <a href="#">EEM scripts</a></li> </ul>
<b>IP Addresses and Services</b>	
<a href="#">Monitor LPTS host path drops via YANG data model</a>	<p>This feature allows you to use the <code>Cisco-IOS-XR-lpts-pre-ifib-oper.yang</code> data model to monitor the policer action for Local Packet Transport Services (LPTS) flow type for all IOS XR platforms.</p> <p>To access this data model, see the <a href="#">Github</a> repository.</p>

Feature	Description
<a href="#">Permit statistics for ACL-based Forwarding (ABF)</a>	<p>This feature enables the inclusion of permitted packet count for ABF in the hardware profile statistics, thus providing the cumulative packet count of permit and deny ACL and ABF. This information helps you plan your traffic management and distribution more effectively.</p> <p>Modified command:</p> <ul style="list-style-type: none"> <li>• <a href="#">hw-module profile stats acl-permit</a></li> </ul>
<b>L2VPN</b>	
<a href="#">CFM on VPLS</a>	<p>This feature helps you monitor and manage a Layer 2 VPN running VPLS. It does so by providing proactive network management, enabling fault detection and isolation, and reporting end-to-end ethernet connectivity issues.</p>
<a href="#">Double-Tagged 802.1ad Encapsulation Options for Layer 3 Physical and Bundle Subinterfaces</a>	<p>This feature enables you to increase the number of VLAN tags in an interface and increment the number of subinterfaces up to 4094. Hence, with the dual tag, the number of VLANs can reach up to 4094*4094. You can enable this feature either on a physical interface or a bundle interface. When you configure this feature with the dual tag, interfaces check for IP addresses along with MAC addresses.</p>
<a href="#">GTP Load Balancing</a>	<p>In addition to the source IP address, destination IP address, and port number, this functionality enables using the unique tunnel endpoint identifier (TEID) to compute load balancing (or hashing) of traffic in tunnels between endpoints. The load balancing occurring at the TEID is unique for each traffic flow and achieves better distribution of traffic over equal-cost links. It also helps in load balancing GTP traffic over bundles at transit routers. By default, this functionality is enabled on the Cisco 8000 Series routers, and you cannot disable it.</p>
<a href="#">Split-Horizon Groups</a>	<p>This feature prevents packets from going into endless loops by aggregating attachment circuits and pseudowires into one of three groups called split-horizon groups. Split-horizon groups operate on the principle that members within a group will not send traffic to each other thereby preventing traffic loops.</p>
<a href="#">Traffic Storm Control</a>	<p>This feature monitors incoming traffic levels on a port in the VPLS bridge. It drops traffic when the number of packets reaches the configured threshold level, thus preventing packets from flooding the VPLS bridge and creating excessive traffic and degrading network performance.</p>
<a href="#">Transparent Layer 2 Protocol Tunneling</a>	<p>This feature allows Layer 2 protocol data units (PDUs) to be kept intact and delivered across the service-provider network to the other side of the customer network. Such delivery is transparent because the VLAN and Layer 2 protocol configurations are maintained throughout.</p> <p>With this feature, service providers can send traffic from multiple customers across a core network without impacting the traffic of other customers.</p> <p>This feature is enabled by default.</p>
<a href="#">Virtual Private LAN Bridging Services</a>	<p>This feature employs PE routers connected by a mesh of tunnels, enabling you to connect multiple customer devices in a single bridged domain. Such a setup allows service providers to seamlessly offer a variety of services that they can provision rapidly.</p>
<b>L3VPN</b>	
<a href="#">L3VPN over RSVP-TE</a>	<p>Using labeled switch paths (LSPs), this feature enables resource reservations in each node across data paths on MPLS-configured Layer 3 VPNs. Such reservations allow service providers to offer high throughput to their subscribers with optimal network operations.</p>

Feature	Description
<b>Modular QoS</b>	
<a href="#">Improve ACL Scaling Using Peering QoS</a>	<p>This feature merges the functions of QoS and security access control lists (ACLs). This combination enables using the ACL filter with the Object Group ACL, which provides a vastly improved ACL scale due to much lower TCAM usage.</p> <p>Before this functionality was introduced, ACLs applied for QoS group actions consumed a sizeable number of TCAM entries, reducing the available scale of the feature.</p>
<b>System Security</b>	
<a href="#">CiscoSSH</a>	<p>This release introduces CiscoSSH, a newer implementation of SSH, on this platform.</p> <p>CiscoSSH leverages OpenSSH implementation, by using the Linux TCP/IP stack to transmit and receive SSH packets over the management Ethernet interface and line card interfaces on the router. CiscoSSH provides additional security features like FIPS compliance and X.509 digital certification. It supports packet path features like MPP, ACL and VRF support, and ensures interoperability with various existing SSH implementations.</p> <p><b>Note</b> Cisco IOS XR SSH, the SSH implementation that existed prior to this release, is now deprecated.</p>
<a href="#">Public Key-Pair Generation in XR Config Mode</a>	<p>This feature allows you to generate public-key pairs in the XR Config mode, which in turn lets you save configurations. You can then load these saved configurations across different routers to quickly deploy the key-pair configurations.</p> <p>You could generate public-key pairs in earlier releases only in the XR EXEC mode, which does not save configurations. So manually executing the key-pair generation commands on every router was time-consuming.</p> <p>The following commands are available in XR Config mode, in addition to XR EXEC mode:</p> <ul style="list-style-type: none"> <li>• <a href="#">crypto key generate rsa</a></li> <li>• <a href="#">crypto key generate dsa</a></li> <li>• <a href="#">crypto key generate ecdsa</a></li> <li>• <a href="#">crypto key generate ed25519</a></li> </ul>
<a href="#">SSH Port Forwarding with CiscoSSH</a>	<p>This release introduces SSH port forwarding with CiscoSSH, an OpenSSH-based implementation of SSH. CiscoSSH replaces Cisco IOS XR SSH, which is the older SSH implementation that existed prior to this release.</p>
<a href="#">Graceful Termination of SSH Sessions</a>	<p>This functionality gracefully terminates the active SSH sessions on the router by returning a successful exit code (0) to the SSH client. This functionality is mainly helpful for automation scenarios such as image installation on a router initiated by a client through an SSH session, where the router reloads automatically post-upgrade. This functionality existed earlier with Cisco IOS XR SSH and is now getting introduced with CiscoSSH.</p> <p>Without this functionality, the SSH sessions terminated abruptly by returning a failure error code (255) to the SSH client, causing the automation scripts to fail.</p> <p>The new functionality is applicable only for upgrade and router reload scenarios; not for RP failovers and active RP reload scenarios.</p>

Feature	Description
<b>Segment Routing</b>	
<a href="#">BFDv6-triggered TI-LFA</a>	<p>Topology-Independent Loop-Free Alternate (TI-LFA) uses segment routing to provide link, node, and Shared Risk Link Groups (SRLG) protection in topologies where other fast reroute techniques cannot provide protection.</p> <p>BFDv6-triggered TI-LFA allows you to obtain link, node, and SRLG protection using the Bidirectional Forwarding Detection (BFD) over IPv6 protocol.</p>
<a href="#">BGP Proxy Prefix SID</a>	<p>This feature is a BGP extension to signal BGP prefix-SIDs. This feature allows you to attach BGP prefix SID attributes for remote prefixes learned over BGP labeled unicast (LU) sessions and propagate them as SR prefixes using BGP LU. This allows an LSP towards non-SR endpoints to use segment routing global block in the SR domain.</p>
<b>Interface and Hardware Component</b>	
<a href="#">Disabling time-to-live (TTL) decrement at GRE encapsulation</a>	<p>This feature allows you to disable the time-to-live (TTL) decrement of the incoming packets. The result is that encapsulation of the original incoming packet takes place without any change in the TTL value.</p> <p>This feature avoids dropping incoming packets with a TTL value equal to one after GRE encapsulation. Before this release, the TTL value of incoming packets was decremented by one before GRE decapsulation. This feature introduces the <b>tunnel ttl disable</b> command.</p>
<a href="#">ERSPAN over GRE IPv6</a>	<p>With this release, the router allows you to mirror IPv4 or IPv6 traffic with ERSPAN over GRE IPv6 sessions to monitor traffic on remote traffic analyzers. In earlier releases, ERSPAN traffic monitoring was possible only on IPv4 networks</p>
<a href="#">Higher Payload Analysis with Eight ERSPAN Sessions</a>	<p>With this release, Cisco 8000 Series routers support eight ERSPAN sessions. This functionality helps you analyze higher payloads in real time across Layer 3 domains on your network.</p>
Dynamic TCAM carving	<p>This feature enables the dynamic modification of the hardware resource TCAM, depending on the user configuration. Hence, allowing the system to accommodate changing service requirements. This feature doesn't require a system reboot for the revised TCAM configuration to take effect.</p> <p>The following options are added to the <b>show controller npu resources</b> command:</p> <ul style="list-style-type: none"> <li>• ingressactcam</li> <li>• egressactcam</li> </ul>
Layer 3 VLAN Interfaces and Subinterfaces Scale	<p>The total number of Layer 3 VLAN interfaces supported on a router that is running IOS-XR has been increased from 2000 to 3580. This number includes main, bundle, and Layer 3 subinterfaces. For example, if the router is already configured with 96 main interfaces, you can configure up to a maximum of 3484 (3580 — 96) subinterfaces. Also, the maximum number of Layer 3 subinterfaces under each main interface can be only up to 2000.</p>
<b>Routing</b>	

Feature	Description
<a href="#">Conditional Default Route Originating in IS-IS</a>	<p>The Conditional Default Route Originating in IS-IS feature allows you to enhance the granularity of the default route the IS-IS originates based on a condition. It enables IS-IS to originate the default route based on the presence of a specific route in the RIB originated by a particular BGP speaker.</p> <p>This feature improves the reaction time of the watched route in the RIB by avoiding periodical queries of the routing policy. This feature enables you to respond to the client in a timely fashion when the watched route changes in the RIB.</p>
<b>System Monitoring</b>	
<a href="#">Extending Graceful Handling of Out of Resource (OOR) Situations for GRE and MPLS traffic</a>	<p>This release extends the graceful handling of dropped traffic in an out-of-resource situation to GRE and MPLS-enabled traffic.</p> <p>Modified command:</p> <ul style="list-style-type: none"> <li>• <a href="#">show controllers npu resources</a></li> </ul>
<a href="#">IP Service level Agreement</a>	<p>This feature allows you to actively monitor, measure, and report traffic information continuously across the network. You can configure the router to measure and report jitter, response time, packet loss, QoS thresholds, connectivity, response or downtime, and delays.</p>
<b>System Management</b>	
<a href="#">Dynamic Power Management</a>	<p>Previously available for fabric and line cards, this feature that helps avoid excess power allocation by considering dynamic factors before allocating power to them is now available for optical modules.</p> <p>To view the power allocation on a per port basis, a new command “<b>show environment power allocated [details]</b>” is introduced.</p>
<a href="#">Flexible Consumption model of Smart Licensing for 8100 Fixed chassis and 8800 Modular chassis</a>	<p>The 8100 fixed chassis and 8800 modular chassis and licenses that are available are as follows:</p> <ul style="list-style-type: none"> <li>• 8101-32FH — 8101-32FH-TRK</li> <li>• 8102-64H — 8102-64H-TRK</li> <li>• 8101-32H — 8101-32H-TRK</li> <li>• 8808 — 8804-TRK</li> </ul>
<a href="#">PTP Delay Asymmetry</a>	<p>Any delays on Precision Time Protocol (PTP) paths can impact PTP accuracy and in turn impact clock settings for all devices in a network. This feature allows you to configure the static asymmetry such that the delay is accounted for and the PTP synchronization remains accurate.</p> <p>The <b>delay-symmetry</b> command is introduced for this feature.</p>

## Hardware Introduced

Cisco IOS XR Release 7.3.2 introduces the following hardware support:



Hardware Feature	Description
<a href="#">Introducing Cisco 8101-32H, Cisco 8102-64H, and Cisco 8101-32FH Variants</a>	<p>This release introduces new variants in the Cisco 8100 Series routers. Based on the new Router-on-Chip (RoC) model, these routers deliver full routing functionality with a single ASIC per router. The newly introduced variants are:</p> <ul style="list-style-type: none"> <li>• <b>Cisco 8101-32H</b> – this router provides 3.2 Tbps of network bandwidth with dramatically lower power consumption than the current 10 Tbps systems. Supported ports include 32 QSFP28 100 GbE.</li> <li>• <b>Cisco 8102-64H</b> – this router provides 6.4 Tbps of network bandwidth with dramatically lower power consumption than the current 10 Tbps systems. Supported ports include 64 QSFP28 100 GbE.</li> <li>• <b>Cisco 8101-32FH</b> – This router provides 12.8 Tbps of network bandwidth. Supported ports include 32 QSFP56-DD 400 GbE.</li> </ul>
<a href="#">Cisco QDD-4X100G-FR-S</a>	<p>This is a new optical module that supports 100G breakout link lengths of up to 2 km. The module has four pairs of single-mode fiber (SMF) with an MPO-12 connector and is compliant to the IEEE 802.3cu for 100GBASE-FR1, and 400GAUI-8/CEI-56G-VSR-PAM4 standards. The 400 Gigabit Ethernet signal is carried over four parallel lanes by one wavelength per lane. It can be used as 4x100G breakout to QSFP28 100G-DR (up to 500m), 100G-FR, and 100G-LR. See <a href="#">QDD-4X100G-FR-S Data Sheet</a>.</p>
<p>8800-LC-48H, 8800-LC-36FH, 88-LC0-36FH, and 88-LC0-36FH-M compatibility, with no slot restrictions</p>	<p>This release supports the following line cards:</p> <ul style="list-style-type: none"> <li>• <a href="#">8800-LC-48H</a></li> <li>• <a href="#">8800-LC-36FH</a></li> <li>• <a href="#">88-LC0-36FH</a></li> <li>• <a href="#">88-LC0-36FH-M</a></li> </ul> <p>It enables the Cisco 8800 chassis on the Q200 Silicon One ASIC NPU, to perform at its full capacity and without any slot restrictions. Find more details about the Cisco 8000 series routers <a href="#">here</a>.</p>



Hardware Feature	Description
Support for parity features on Q200 Silicon One ASIC NPU for pre-7.3.2 Release Features	<p>With this release, additional feature support is introduced on Cisco 8000 Series Routers with <a href="#">Q200 Silicon One ASIC NPU</a>. This enhancement significantly improves the router's forwarding and routing capabilities. Some of the key features now supported are:</p> <ul style="list-style-type: none"> <li>• <a href="#">Multicast 120K Route</a></li> <li>• <a href="#">L2 Local/Cross Connect</a></li> <li>• <a href="#">L2VPN</a></li> <li>• <a href="#">IRB</a></li> <li>• <a href="#">L2 QoS</a></li> <li>• <a href="#">Carrier Supporting Carrier</a></li> <li>• <a href="#">L3VPN per VRF</a></li> <li>• <a href="#">BFD with Ti-IFA</a></li> <li>• <a href="#">GRE and GUE</a></li> </ul>
Support of QDD-400G-ZR-S and QDD-400G-ZRP-S Optical Module	<p>The QDD-400G-ZR-S and QDD-400G-ZRP-S optical modules, combined with routers optimized for 400G port bandwidth, offer customers a massive increase in router scale and capacity at significantly improved cost points.</p> <p>This release supports QDD-400G-ZR-S and QDD-400G-ZRP-S optical modules on the following fixed-port routers and line card:</p> <ul style="list-style-type: none"> <li>• 8101-32FH fixed-port router</li> <li>• 8201-32FH fixed-port router</li> <li>• 88-LC0-36FH line card</li> </ul> <p>In this release, the QDD-400G-ZRP-S optical module additionally supports 3x100 and 2x100 muxponder and 1x100 transponder modes. With these modes, the QDD-400G-ZRP-S optical module can support link lengths of up to 2000 km.</p> <p>This optical module supports QPSK modulation for 1x100 and 2x100 modes and 8QAM modulation for 3x100 mode.</p> <p>The CD (chromatic dispersion) range selection is increased between -160000 to + 160000.</p> <p>For configuration details, see the <a href="#">Configuring 400G Digital Coherent Optics</a>.</p> <p>For command details, see the <a href="#">Coherent Optics Commands</a>.</p> <p>See the <a href="#">Cisco 400G Digital Coherent Optics QSFP-DD Optical Modules Data Sheet</a> for more information about the optic module portfolio.</p>

Hardware Feature	Description
60A support on the PSU4.8KW-DC100 (DC100) power supply	This feature allows you to operate the 4.8 KW power supply for 48V 100A DC with 48V 60A.  By default, the power module accepts 100A. To change the power mode to 60A, a toggle switch is provided in the power tray.
PSU4.8KW-DC100 power supply for Cisco 8804 and 8808 routers.	This feature introduces support for the 4.8 KW power supply for 48V 100A DC (DC100) on the Cisco 8804 and 8808 routers.  The power supply accepts a nominal input voltage of 48V 100A DC, with an operational tolerance range of -40 to -75 VDC.

For a complete list of supported hardware and ordering information, see the [Cisco 8000 Series Data Sheet](#).

## Release 7.3.2 Packages

The Cisco IOS XR software is composed of a base image (ISO) that provides the XR infrastructure. The ISO image is made up of a set of packages (also called RPMs). These packages are of three types:

- A mandatory package that is included in the ISO
- An optional package that is included in the ISO
- An optional package that is not included in the ISO

Visit the [Cisco Software Download](#) page to download the Cisco IOS XR software images.

To determine the Cisco IOS XR Software packages installed on your router, log in to the router and enter the **show install active** command:

```
RP/0/RP0/CPU0#show install active
Package                                     Version
-----
xr-8000-af-ea                               7.3.2v1.0.0-1
xr-8000-aib                                  7.3.2v1.0.0-1
xr-8000-bfd                                  7.3.2v1.0.0-1
xr-8000-bmc                                  7.3.2v1.0.0-1
xr-8000-buffhdr-ea                           7.3.2v1.0.0-1
xr-8000-bundles                              7.3.2v1.0.0-1
xr-8000-card-support                         7.3.2v1.0.0-1
xr-8000-cdp-ea                               7.3.2v1.0.0-1
xr-8000-cfm                                  7.3.2v1.0.0-1
xr-8000-core                                 7.3.2v1.0.0-1
xr-8000-cpa                                  7.3.2v1.0.0-1
xr-8000-cpa-npu                              7.3.2v1.0.0-1
xr-8000-cpa-sb-data                          7.3.2v1.0.0-1
xr-8000-dsm                                  7.3.2v1.0.0-1
xr-8000-encap-id                             7.3.2v1.0.0-1
xr-8000-ether-ea                             7.3.2v1.0.0-1
xr-8000-fabric                               7.3.2v1.0.0-1
xr-8000-feat-mgr                             7.3.2v1.0.0-1
xr-8000-fib-ea                               7.3.2v1.0.0-1
xr-8000-forwarder                           7.3.2v1.0.0-1
xr-8000-fpd                                  7.3.2v1.0.0-1
xr-8000-fwplib                              7.3.2v1.0.0-1
xr-8000-host-core                           7.3.2v1.0.0-1
xr-8000-l2fib                                7.3.2v1.0.0-1
```

xr-8000-leabaofa	7.3.2v1.0.0-1
xr-8000-libofaasync	7.3.2v1.0.0-1
xr-8000-lpts-ea	7.3.2v1.0.0-1
xr-8000-mcast	7.3.2v1.0.0-1
xr-8000-netflow	7.3.2v1.0.0-1
xr-8000-npu	7.3.2v1.0.0-1
xr-8000-oam	7.3.2v1.0.0-1
xr-8000-optics	7.3.2v1.0.0-1
xr-8000-os	7.3.2v1.0.0-1
xr-8000-pbr	7.3.2v1.0.0-1
xr-8000-pfilter	7.3.2v1.0.0-1
xr-8000-pidb	7.3.2v1.0.0-1
xr-8000-pktio	7.3.2v1.0.0-1
xr-8000-port-mapper	7.3.2v1.0.0-1
xr-8000-port-mode	7.3.2v1.0.0-1
xr-8000-ppinfo	7.3.2v1.0.0-1
xr-8000-qos-ea	7.3.2v1.0.0-1
xr-8000-secy-driver	7.3.2v1.0.0-1
xr-8000-span	7.3.2v1.0.0-1
xr-8000-spio	7.3.2v1.0.0-1
xr-8000-spp-ea	7.3.2v1.0.0-1
xr-8000-tams	7.3.2v1.0.0-1
xr-8000-timing	7.3.2v1.0.0-1
xr-8000-tunnel-ip	7.3.2v1.0.0-1
xr-8000-utapp-blaze	7.3.2v1.0.0-1
xr-8000-vether	7.3.2v1.0.0-1
xr-8000-ztp-ea	7.3.2v1.0.0-1
xr-aaa	7.3.2v1.0.0-1
xr-acl	7.3.2v1.0.0-1
xr-apphosting	7.3.2v1.0.0-1
xr-appmgr	7.3.2v1.0.0-1
xr-bcdl	7.3.2v1.0.0-1
xr-bfd	7.3.2v1.0.0-1
xr-bgp	7.3.2v1.0.0-1
xr-bgputil	7.3.2v1.0.0-1
xr-bng-stubs	7.3.2v1.0.0-1
xr-bundles	7.3.2v1.0.0-1
xr-cal-pi	7.3.2v1.0.0-1
xr-cdp	7.3.2v1.0.0-1
xr-cds	7.3.2v1.0.0-1
xr-cfgmgr	7.3.2v1.0.0-1
xr-cfm	7.3.2v1.0.0-1
xr-cofo	7.3.2v1.0.0-1
xr-core	7.3.2v1.0.0-1
xr-core-calv	7.3.2v1.0.0-1
xr-cpa-common	7.3.2v1.0.0-1
xr-cpa-common-optics	7.3.2v1.0.0-1
xr-cpa-common-psu	7.3.2v1.0.0-1
xr-cpa-driver-devobj-misc	7.3.2v1.0.0-1
xr-cpa-driver-devobj-npu	7.3.2v1.0.0-1
xr-cpa-driver-devobj-phy	7.3.2v1.0.0-1
xr-cpa-driver-devobj-sensors	7.3.2v1.0.0-1
xr-cpa-driver-devobj-storage	7.3.2v1.0.0-1
xr-cpa-driver-devobj-test	7.3.2v1.0.0-1
xr-cpa-driver-devobj-timing	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-access	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-common	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-infra	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-kmod	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-misc	7.3.2v1.0.0-1
xr-cpa-driver-fpgalib-optics	7.3.2v1.0.0-1
xr-cpa-driver-optics	7.3.2v1.0.0-1
xr-cpa-ethsw	7.3.2v1.0.0-1
xr-cpa-idprom	7.3.2v1.0.0-1

xr-cpa-tamlib	7.3.2v1.0.0-1
xr-ctc	7.3.2v1.0.0-1
xr-debug	7.3.2v1.0.0-1
xr-dhcp	7.3.2v1.0.0-1
xr-diskboot	7.3.2v1.0.0-1
xr-drivers	7.3.2v1.0.0-1
xr-eem	7.3.2v1.0.0-1
xr-elmi-stubs	7.3.2v1.0.0-1
xr-ema	7.3.2v1.0.0-1
xr-enhancedmanageability	7.3.2v1.0.0-1
xr-fib	7.3.2v1.0.0-1
xr-filesysinv	7.3.2v1.0.0-1
xr-foundation-8000	7.3.2v1.0.0-1
xr-fpd	7.3.2v1.0.0-1
xr-ha-infra	7.3.2v1.0.0-1
xr-healthcheck	7.3.2v1.0.0-1
xr-host-core	7.3.2v1.0.0-1
xr-httpclient	7.3.2v1.0.0-1
xr-icpe-eth	7.3.2v1.0.0-1
xr-icpe-opt	7.3.2v1.0.0-1
xr-identifier	7.3.2v1.0.0-1
xr-infra-sla	7.3.2v1.0.0-1
xr-install	7.3.2v1.0.0-1
xr-ip-apps	7.3.2v1.0.0-1
xr-ip-core	7.3.2v1.0.0-1
xr-ip-infra-vrf	7.3.2v1.0.0-1
xr-ip-mibs	7.3.2v1.0.0-1
xr-ip-static	7.3.2v1.0.0-1
xr-ipc	7.3.2v1.0.0-1
xr-ipsla	7.3.2v1.0.0-1
xr-is-is	7.3.2v1.0.0-1
xr-k9sec	7.3.2v1.0.0-1
xr-l2snooptransport	7.3.2v1.0.0-1
xr-l2vpn	7.3.2v1.0.0-1
xr-ldp	7.3.2v1.0.0-1
xr-licensing	7.3.2v1.0.0-1
xr-link-oam	7.3.2v1.0.0-1
xr-linuxnetworking	7.3.2v1.0.0-1
xr-lldp	7.3.2v1.0.0-1
xr-lpts	7.3.2v1.0.0-1
xr-manageabilityxml	7.3.2v1.0.0-1
xr-mandatory	7.3.2v1.0.0-1
xr-mcast	7.3.2v1.0.0-1
xr-mds	7.3.2v1.0.0-1
xr-mpls	7.3.2v1.0.0-1
xr-mpls-oam	7.3.2v1.0.0-1
xr-mpls-oam-client	7.3.2v1.0.0-1
xr-mpls-static	7.3.2v1.0.0-1
xr-netflow	7.3.2v1.0.0-1
xr-networkboot	7.3.2v1.0.0-1
xr-nosi	7.3.2v1.0.0-1
xr-ntp	7.3.2v1.0.0-1
xr-ofa	7.3.2v1.0.0-1
xr-optics	7.3.2v1.0.0-1
xr-orrsfpf	7.3.2v1.0.0-1
xr-os	7.3.2v1.0.0-1
xr-ospf	7.3.2v1.0.0-1
xr-perf-meas	7.3.2v1.0.0-1
xr-perfmgmt	7.3.2v1.0.0-1
xr-pfi	7.3.2v1.0.0-1
xr-platforms-ras	7.3.2v1.0.0-1
xr-pm-alarm	7.3.2v1.0.0-1
xr-procmgr	7.3.2v1.0.0-1
xr-python	7.3.2v1.0.0-1

```

xr-qos 7.3.2v1.0.0-1
xr-rid-mgr 7.3.2v1.0.0-1
xr-routing 7.3.2v1.0.0-1
xr-rpl 7.3.2v1.0.0-1
xr-rsvp-te 7.3.2v1.0.0-1
xr-security 7.3.2v1.0.0-1
xr-servicelayer 7.3.2v1.0.0-1
xr-snmp 7.3.2v1.0.0-1
xr-span 7.3.2v1.0.0-1
xr-spi-core 7.3.2v1.0.0-1
xr-spi-hw 7.3.2v1.0.0-1
xr-spp 7.3.2v1.0.0-1
xr-sr 7.3.2v1.0.0-1
xr-stats 7.3.2v1.0.0-1
xr-stp 7.3.2v1.0.0-1
xr-stubs 7.3.2v1.0.0-1
xr-sysdb 7.3.2v1.0.0-1
xr-syslog 7.3.2v1.0.0-1
xr-telemetry 7.3.2v1.0.0-1
xr-telnet 7.3.2v1.0.0-1
xr-timing 7.3.2v1.0.0-1
xr-tmpdir-cleanup 7.3.2v1.0.0-1
xr-track 7.3.2v1.0.0-1
xr-transport 7.3.2v1.0.0-1
xr-tty 7.3.2v1.0.0-1
xr-tunnel-ip 7.3.2v1.0.0-1
xr-utils 7.3.2v1.0.0-1
xr-vether 7.3.2v1.0.0-1
xr-vpnmib 7.3.2v1.0.0-1
xr-xmlinfra 7.3.2v1.0.0-1
xr-xrlicurl 7.3.2v1.0.0-1
xr-ztp 7.3.2v1.0.0-1

```

To know about all the RPMs installed including XR, OS and other components use the **show install active all** command.

The software modularity approach provides a flexible model that allows you to install a subset of IOS XR packages on devices based on your individual requirements. All critical components are modularized as packages so that you can select the features that you want to run on your router.




---

**Note** The above show command output displays mandatory packages that are installed on the router. To view the optional and bug fix RPM packages, first install the package and use the **show install active summary** command.

---

## Cisco IOS XR Caveats

These caveats are applicable for Cisco IOS XR Software:

Bug ID	Headline
<a href="#">CSCvy13197</a>	Telemetry Syslog events are not received by telemetry client

## Determine Software Version

Log in to the router and enter the **show version** command:

```
RP/0/RP0/CPU0# show version
Thu Oct 14 13:19:38.556 PDT
Cisco IOS XR Software, Version 7.3.2 LNT
Copyright (c) 2013-2021 by Cisco Systems, Inc.
```

```
Build Information:
  Built By      : ingunawa
  Built On     : Thu Oct 14 08:42:55 UTC 2021
  Build Host   : iox-ucs-020
  Workspace    : /auto/srcarchive17/prod/7.3.2/8000/ws
  Version     : 7.3.2
  Label       : 7.3.2-Renumber
```

```
cisco 8000 (Intel(R) Xeon(R) CPU D-1530 @ 2.40GHz)
cisco 8201 (Intel(R) Xeon(R) CPU D-1530 @ 2.40GHz) processor with 32GB of memory
r4 uptime is 2 hours, 3 minutes
Cisco 8201 Chassis w/ 24x400GE QSFP56-DD&12x100GE QSFP28
```

## Determine Firmware Support

Log in to the router and enter **show fpd package** command:

### Cisco 8200 Series Router

```
RP/0/RP0/CPU0# show fpd package
```

```
=====
```

Field Programmable Device Package					
Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
8201	Bios	YES	1.22	1.22	0.0
	BiosGolden	YES	1.22	1.15	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.01	1.01	0.0
	BmcFpgaGolden	YES	1.01	0.86	0.0
	BmcTamFw	YES	5.06	5.06	0.0
	BmcTamFwGolden	YES	5.06	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	IoFpga	YES	1.06	1.06	0.1
	IoFpgaGolden	YES	1.06	0.48	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.02	1.02	0.0
	x86FpgaGolden	YES	1.02	0.48	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
8201-ON	Bios	YES	1.208	1.208	0.0
	BiosGolden	YES	1.208	1.207	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.01	1.01	0.0
	BmcFpgaGolden	YES	1.01	0.86	0.0
	BmcTamFw	YES	5.06	5.06	0.0

```
=====
```

	BmcTamFwGolden	YES	5.06	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	IoFpga	YES	1.06	1.06	0.1
	IoFpgaGolden	YES	1.06	0.48	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.02	1.02	0.0
	x86FpgaGolden	YES	1.02	0.48	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8201-SYS	Bios	YES	1.22	1.22	0.0
	BiosGolden	YES	1.22	1.15	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.01	1.01	0.0
	BmcFpgaGolden	YES	1.01	0.86	0.0
	BmcTamFw	YES	5.06	5.06	0.0
	BmcTamFwGolden	YES	5.06	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	IoFpga	YES	1.06	1.06	0.1
	IoFpgaGolden	YES	1.06	0.48	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.02	1.02	0.0
	x86FpgaGolden	YES	1.02	0.48	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8201-SYS-ON	Bios	YES	1.208	1.208	0.0
	BiosGolden	YES	1.208	1.207	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.01	1.01	0.0
	BmcFpgaGolden	YES	1.01	0.86	0.0
	BmcTamFw	YES	5.06	5.06	0.0
	BmcTamFwGolden	YES	5.06	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	IoFpga	YES	1.06	1.06	0.1
	IoFpgaGolden	YES	1.06	0.48	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.02	1.02	0.0
	x86FpgaGolden	YES	1.02	0.48	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
PSU-2KW-HVPI	PO-PrimMCU	NO	17.136	17.136	0.0
-----					
PSU1.4KW-ACPE	DC-PrimMCU	NO	3.01	3.01	0.0
	DC-SecMCU	NO	2.02	2.02	0.0
-----					
PSU1.4KW-ACPI	DC-PrimMCU	NO	3.01	3.01	0.0
	DC-SecMCU	NO	2.02	2.02	0.0
-----					



PSU2KW-ACPE	PO-PrimMCU	NO	17.54	17.54	0.0
PSU2KW-ACPI	PO-PrimMCU	NO	17.56	17.56	0.0
PSU2KW-DCPE	PO-PrimMCU	NO	1.07	1.07	0.0
PSU2KW-DCPI	PO-PrimMCU	NO	1.07	1.07	0.0

## Cisco 8800 Series Router

RP/0/RP0/CPU0# show fpd package

```

=====
                          Field Programmable Device Package
=====

```

Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
88-LC0-36FH	Bios	YES	0.17	0.17	0.0
	BiosGolden	YES	0.17	0.13	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.00	1.00	0.1
	IoFpgaGolden	YES	1.00	1.00	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.06	1.06	0.1
	x86FpgaGolden	YES	1.06	1.04	0.1
	x86TamFw	YES	6.05	6.05	0.1
x86TamFwGolden	YES	6.05	6.05	0.1	
88-LC0-36FH-M	Bios	YES	0.17	0.17	0.0
	BiosGolden	YES	0.17	0.13	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.00	1.00	0.1
	IoFpgaGolden	YES	1.00	1.00	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.06	1.06	0.1
	x86FpgaGolden	YES	1.06	1.04	0.1
	x86TamFw	YES	6.05	6.05	0.1
x86TamFwGolden	YES	6.05	6.05	0.1	
88-LC0-36FH-MO	Bios	YES	0.217	0.217	0.0
	BiosGolden	YES	0.217	0.217	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.00	1.00	0.1
	IoFpgaGolden	YES	1.00	1.00	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.06	1.06	0.1
	x86FpgaGolden	YES	1.06	1.04	0.1
	x86TamFw	YES	6.05	6.05	0.1
x86TamFwGolden	YES	6.05	6.05	0.1	
88-LC0-36FH-O	Bios	YES	0.217	0.217	0.0

	BiosGolden	YES	0.217	0.217	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.00	1.00	0.1
	IoFpgaGolden	YES	1.00	1.00	0.1
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.06	1.06	0.1
	x86FpgaGolden	YES	1.06	1.04	0.1
	x86TamFw	YES	6.05	6.05	0.1
	x86TamFwGolden	YES	6.05	6.05	0.1
-----					
8800-LC-36FH	Bios	YES	1.22	1.22	0.0
	BiosGolden	YES	1.22	1.15	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.12	1.12	0.0
	IoFpgaGolden	YES	1.12	0.08	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.13	1.13	0.0
	x86FpgaGolden	YES	1.13	0.33	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8800-LC-36FH-O	Bios	YES	1.208	1.208	0.0
	BiosGolden	YES	1.208	1.207	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.12	1.12	0.0
	IoFpgaGolden	YES	1.12	0.08	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.13	1.13	0.0
	x86FpgaGolden	YES	1.13	0.33	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8800-LC-48H	Bios	YES	1.22	1.22	0.0
	BiosGolden	YES	1.22	1.15	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.12	1.12	0.0
	IoFpgaGolden	YES	1.12	0.08	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.13	1.13	0.0
	x86FpgaGolden	YES	1.13	0.33	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8800-LC-48H-O	Bios	YES	1.208	1.208	0.0
	BiosGolden	YES	1.208	1.207	0.0
	EthSwitch	YES	1.03	1.03	0.0
	EthSwitchGolden	YES	1.03	0.07	0.0
	IoFpga	YES	1.12	1.12	0.0

	IoFpgaGolden	YES	1.12	0.08	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	x86Fpga	YES	1.13	1.13	0.0
	x86FpgaGolden	YES	1.13	0.33	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8800-RP	Bios	YES	1.22	1.22	0.0
	BiosGolden	YES	1.22	1.15	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.03	1.03	0.0
	BmcFpgaGolden	YES	1.03	0.19	0.0
	BmcTamFw	YES	5.08	5.08	0.0
	BmcTamFwGolden	YES	5.08	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	EthSwitch	YES	1.02	1.02	0.0
	EthSwitchGolden	YES	1.02	0.07	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	TimingFpga	YES	1.02	1.02	0.0
	TimingFpgaGolden	YES	1.02	0.11	0.0
	x86Fpga	YES	1.23	1.23	0.0
	x86FpgaGolden	YES	1.23	0.24	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8800-RP-O	Bios	YES	1.208	1.208	0.0
	BiosGolden	YES	1.208	1.207	0.0
	BmcFitGolden	YES	3.300	0.240	0.0
	BmcFitPrimary	YES	3.300	3.300	0.0
	BmcFpga	YES	1.03	1.03	0.0
	BmcFpgaGolden	YES	1.03	0.19	0.0
	BmcTamFw	YES	5.08	5.08	0.0
	BmcTamFwGolden	YES	5.08	5.05	0.0
	BmcUbootGolden	YES	1.02	0.15	0.0
	BmcUbootPrimary	YES	1.02	1.02	0.0
	EthSwitch	YES	1.02	1.02	0.0
	EthSwitchGolden	YES	1.02	0.07	0.0
	SsdIntelS3520	YES	1.21	1.21	0.0
	SsdIntelS4510	YES	11.32	11.32	0.0
	SsdMicron5100	YES	7.01	7.01	0.0
	SsdMicron5300	YES	0.01	0.01	0.0
	TimingFpga	YES	1.02	1.02	0.0
	TimingFpgaGolden	YES	1.02	0.11	0.0
	x86Fpga	YES	1.23	1.23	0.0
	x86FpgaGolden	YES	1.23	0.24	0.0
	x86TamFw	YES	5.06	5.06	0.0
	x86TamFwGolden	YES	5.06	5.05	0.0
-----					
8804-FAN	FtFpga	NO	1.00	1.00	0.0
	FtFpgaGolden	NO	1.00	0.16	0.0
-----					
8804-FC0	IoFpga	YES	1.00	1.00	0.0
	IoFpgaGolden	YES	1.00	0.16	0.0
-----					
8808-FAN	FtFpga	NO	1.00	1.00	0.0
	FtFpgaGolden	NO	1.00	0.16	0.0

8808-FC	IoFpga	YES	1.02	1.02	0.0
	IoFpgaGolden	YES	1.02	0.05	0.0
8808-FC0	IoFpga	YES	1.00	1.00	0.0
	IoFpgaGolden	YES	1.00	0.16	0.0
8812-FAN	FtFpga	NO	1.00	1.00	0.0
	FtFpgaGolden	NO	1.00	0.16	0.0
8812-FC	IoFpga	YES	1.02	1.02	0.0
	IoFpgaGolden	YES	1.02	0.05	0.0
	Retimer	YES	3.00	3.00	0.0
8818-FAN	FtFpga	NO	1.00	1.00	0.0
	FtFpgaGolden	NO	1.00	0.16	0.0
8818-FC	IoFpga	YES	1.02	1.02	0.0
	IoFpgaGolden	YES	1.02	0.05	0.0
	Retimer	YES	3.00	3.00	0.0
8818-FC0	IoFpga	YES	1.00	1.00	0.0
	IoFpgaGolden	YES	1.00	0.16	0.0
	Retimer	YES	3.00	3.00	0.0
PSU-4.8KW-DC100	PO-PrimMCU	NO	51.85	51.85	0.0
PSU6.3KW-20A-HV	DT-LogicMCU	NO	1.00	1.00	0.0
	DT-PrimMCU	NO	1.00	1.00	0.0
	DT-SecMCU	NO	1.00	1.00	0.0
PSU6.3KW-HV	AB-LogicMCU	NO	3.08	3.08	0.0
	AB-PrimMCU	NO	3.08	3.08	0.0
	AB-SecMCU	NO	3.06	3.06	0.0
	DT-LogicMCU	NO	4.11	4.11	0.0
	DT-PrimMCU	NO	4.01	4.01	0.0
	DT-SecMCU	NO	4.00	4.00	0.0
PWR-4.4KW-DC-V3	DT-LogicMCU	NO	3.02	3.02	0.0
	DT-Prim1MCU	NO	3.01	3.01	0.0
	DT-Prim2MCU	NO	3.01	3.01	0.0
	DT-Sec1MCU	NO	3.01	3.01	0.0
	DT-Sec2MCU	NO	3.01	3.01	0.0

## Supported Transceiver Modules

To determine the transceivers that Cisco hardware device supports, refer to the [Transceiver Module Group \(TMG\) Compatibility Matrix](#) tool.

## Other Important Information

- The warning message that the smart licensing evaluation period has expired is displayed in the console every hour. There is, however, no functionality impact on the device. The issue is seen on routers that don't have the Flexible Consumption licensing model enabled. To stop the repetitive messaging, register the device with the smart licensing server and enable the Flexible Consumption model. Later load a new registration token.

To register the device with the smart licensing server, see the [Registering and Activating Your Router](#).

- When you execute the **show tech-support** command, a temporary directory is created and the related data is stored in this directory. This directory is deleted after the command is completed. For example,

```
Router#run ls -ltr  
drwxrwxrwx. 3 root root show-tech-fabric-link-incl-loca-010cpu0_2.tgz
```

In case, you terminate the **show tech-support** command manually, we recommend you to delete the corresponding show tech directory if not needed.

## Related Documentation

The most current Cisco 8000 router documentation is located at the following URL:

<https://www.cisco.com/c/en/us/td/docs/iosxr/8000-series-routers.html>

# Full Cisco Trademarks with Software License

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

The documentation set for this product strives to use bias-free language. For purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on standards documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)







**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA 95134-1706  
USA

**Asia Pacific Headquarters**  
CiscoSystems(USA)Pte.Ltd.  
Singapore

**Europe Headquarters**  
CiscoSystemsInternationalBV  
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).