



## Enhancements to Streaming Telemetry

This section provides an overview of the enhancements made to streaming telemetry data.

- [Hardware Timestamp, on page 1](#)
- [Target-Defined Mode for Cached Generic Counters Data, on page 3](#)
- [Stream Telemetry Data about PBR Decapsulation Statistics, on page 5](#)
- [Stream Telemetry Data for BGP FlowSpec, on page 7](#)
- [Stream Telemetry Data for ACL, on page 12](#)

### Hardware Timestamp

*Table 1: Feature History Table*

Feature Name	Release Information	Description
Hardware Timestamp	Release 7.3.1	<p>Whenever periodic statistics are streamed, the collector reads the data from its internal cache, instead of fetching the data from the hardware.</p> <p>When the data is read from the cache, the rate at which data is processed shows spikes because the timestamp from the collector is off by several seconds. With hardware timestamping, the inconsistencies that are observed when reading data from the cache file is removed.</p>

Whenever periodic stats are streamed, the collector reads the stats from its internal cache, instead of fetching the stats from the hardware. When the data is read from the sensor paths of Stats manager cache, the rate calculation shows spikes. This behavior is due to the timestamp from the collector that is off by several seconds. Therefore, timestamp of some other collector takes precedence because timestamps of collectors are not in synchronization with the current timestamp. This is observed when there are multiple collectors providing stats updates for the same interface.

The YANG data model for Stats manager `Cisco-IOS-XR-infra-statsd-oper.yang` is enhanced to enable the collector to read periodic stats data from the router using hardware timestamp.

The hardware timestamp is taken into account when a primary collector (for generic or proto stats) provides stats updates from the hardware to the Stats manager. With hardware timestamping in rate computation while streaming periodic stats, the spikes due to the timestamp issue is resolved.

The hardware timestamp is updated only when the collector attempts to read the counters from hardware. Else, the value remains 0. The latest stats can be streamed at a minimum cadence of 10 seconds and periodic stats at a cadence of 30 seconds. The support is available only for physical interfaces and subinterfaces, and bundle interface and subinterfaces.

When there is no traffic flow on protocols for an interface, the hardware timestamp for the protocols is published as 0. This is due to non-synchronized timestamps sent by the collector for protocols in traffic as compared to non-traffic scenarios.

A non-zero value is published for protocols that have stats published by a primary collector for both traffic and non-traffic scenarios.




---

**Note** The hardware timestamp is supported only for primary collectors. When the hardware has no update, the timestamp will be same. However generic counters are computed for primary and non-primary collectors. The non-primary collectors show the latest stats, but not the timestamp.

---

When the counters are cleared for an interface using **clear counters interface** command, all counter-related data including the timestamps for the interface is cleared. After all counter values are cleared and set to 0, the last data time is updated only when there is a request for it from a collector. For example, last data time gets updated from a collector:

```
Router#:Aug 7 09:01:08.471 UTC: statsd_manager_1[168]: Updated last data time for ifhandle
0x02000408,
stats type 2 from collector with node 0x100, JID 250, last data time 1596790868.
INPUT: last 4294967295 updated 1596469986. OUTPUT: last 4294967295 updated 1596469986
```

All other counter values and hardware timestamp are updated when the counters are fetched from the hardware. In this case, all counters including the hardware timestamp is 0:

```
{"node_id_str":"MGBL_MTB_5504","subscription_id_str":"app_TEST_200000001",
"encoding_path":"Cisco-IOS-XR-infra-statsd-oper:infra-statistics/interfaces/interface/cache/generic-counters",
"collection_id":"7848",
"collection_start_time":"1596790879567",
"msg_timestamp":"1596790879571","data_json":
[{"timestamp":"1596790879570","keys":[{"interface-name":"FortyGigE0/1/0/11"}],
"content":{"packets-received":"0","bytes-received":"0","packets-sent":"0",
"bytes-sent":"0","multicast-packets-received":"0","broadcast-packets-received":"0",
"multicast-packets-sent":"0","broadcast-packets-sent":"0","output-drops":0,"output-queue-drops":0,
"input-drops":0,"input-queue-drops":0,"runt-packets-received":0,"giant-packets-received":0,
"throttled-packets-received":0,"parity-packets-received":0,"unknown-protocol-packets-received":0,
"input-errors":0,"crc-errors":0,"input-overruns":0,"framing-errors-received":0,"input-ignored-packets":0,
"input-aborts":0,"output-errors":0,"output-underruns":0,"output-buffer-failures":0,"output-buffers-swapped-out":0,
"applique":0,"resets":0,"carrier-transitions":0,"availability-flag":0,
"last-data-time":"1596790868","hardware-timestamp":"0",
"seconds-since-last-clear-counters":15,"last-discontinuity-time":1596469946,"seconds-since-packet-received":0,
"seconds-since-packet-sent":0}}],"collection_end_time":"1596790879571"}
```

# Target-Defined Mode for Cached Generic Counters Data

Table 2: Feature History Table

Feature Name	Release Information	Description
Target-Defined Mode for Cached Generic Counters Data	Release 7.5.1	<p>This feature streams telemetry data for cached generic counters using a TARGET_DEFINED subscription. This subscription ensures that any change to the cache streams the latest data to the collector as an event-driven telemetry notification.</p> <p>This feature introduces support for the following sensor path:</p> <pre>Cisco-IOS-XR-infra-statsd-oper:infra-statistics/interfaces/interface/cache/generic-counters</pre>

Streaming telemetry pushes the subscribed data from the router to one or more collectors. The telemetry infrastructure retrieves the data from the system database when you send a subscription request. Based on the subscription request or the telemetry configuration the cached generic counters data can be retrieved periodically based on the sample-interval. Data, such as interface statistics, is cached and refreshed at certain intervals. The TARGET\_DEFINED subscription mode can be used to retrieve data when the cache gets updated, and is not based on a timer.

The application can register as a data producer with the telemetry library and the SysdB paths it supports. One of the data producers, Statsd, uses the library with a TARGET\_DEFINED subscription mode. As part of this mode, the producer registers the sensor paths. The statistics infrastructure streams the incremental updates for statsd cache sensor path

`Cisco-IOS-XR-infra-statsd-oper:infra-statistics/interfaces/interface/cache/generic-counters`. With this path in the subscription, whenever cache is updated, the statsd application pushes the updates to the telemetry daemon. The daemon sends these incremental updates to the collector. The cache updates are pushed for physical interfaces, physical subinterfaces, bundle interfaces, and bundle subinterfaces. You can subscribe to the sensor path for the cached generic counters with TARGET\_DEFINED mode instead of the sensor path for the latest generic counters (`Cisco-IOS-XR-infra-statsd-oper:infra-statistics/interfaces/interface/latest/generic-counters`) to reduce the system load.

Configure the router to stream telemetry data from cache for generic counters using the following instructions:

Create a TARGET\_DEFINED subscription mode for cached generic counters using one of the two options:

- **Option 1:** gRPC Network Management Interface (gNMI) subscribe request

```
{
  "name": "SubscribeRequest",
  "subscribe": {
    "prefix": {"origin":
      "Cisco-IOS-XR-infra-statsd-oper"
    },
  },
  "mode": "STREAM", "encoding": "PROTO", "updates_only": "false",
  "subscription": [
    { "path": {"elem": [ {"name": "infra-statistics"},
      {"name": "interfaces"},
```



```
Heartbeat Interval: NA
Sensor Path: Cisco-IOS-XR-infra-statsd-oper:infra-statistics/interfaces/interface/cache/
             generic-counters
Sensor Path State: Resolved

Destination Groups:
Group Id: statsd-target
Destination IP: 192.0.2.1
Destination Port: 56000
Encoding: json
Transport: grpc
State: Active
TLS : False
Total bytes sent: 623656
Total packets sent: 13
Last Sent time: 2021-08-16 08:51:15.1304821089 +0000

Collection Groups:
-----
Id: 2
Sample Interval: 0 ms (Incremental Updates)
Heartbeat Interval: NA
Heartbeat always: False
Encoding: json
Num of collection: 1
Incremental updates: 3
Collection time: Min: 94 ms Max: 94 ms
Total time: Min: 100 ms Avg: 100 ms Max: 100 ms
Total Deferred: 0
Total Send Errors: 0
Total Send Drops: 0
Total Other Errors: 0
No data Instances: 0
Last Collection Start: 2021-08-16 08:51:04.1293895665 +0000
Last Collection End: 2021-08-16 08:51:04.1293996284 +0000
```

The sample interval of 0 indicates that the data is streamed whenever an event occurs. Here, the event represents the updates to the cache state.

#### Related Commands:

- **show tech telemetry model-driven**
- **show running-config telemetry model-driven**
- **show telemetry producers trace *producer name* info**
- **show telemetry producers trace *producer name* err**

## Stream Telemetry Data about PBR Decapsulation Statistics

You can stream telemetry data about PBR decapsulation statistics for GRE and GUE encapsulation protocols that deliver packets using IPv4 or IPv6. The encapsulated data has source and destination address that must match with the source and destination address in the classmap. Both encapsulation and decapsulation interfaces collect statistics periodically. The statistics can be displayed on demand using **show policy-map type pbr [vrf vrf-name] address-family ipv4/ipv6 statistics** command. For more information on PBR-based decapsulation, see *Interface and Hardware Component Configuration Guide for Cisco NCS 5000 Series Routers*.

With this release, the decapsulation statistics can be displayed using

Cisco-IOS-XR-infra-policymgr-oper.yang data model and telemetry data. You can stream telemetry data from the sensor path:

Cisco-IOS-XR-infra-policymgr-oper:policy-manager/global/policy-map/policy-map-types/policy-map-type/vrf-table/vrf/afi-table/afi/stats

The following steps show the PBR configuration and the decapsulation statistics that is streamed as telemetry data to the collector.

**Step 1** Check the running configuration to view the configured PBR per VRF.

**Example:**

```
Router#show running-config
Building configuration...
!! IOS XR Configuration 0.0.0
!!
vrf vrf1
  address-family ipv4 unicast
  !
  address-family ipv6 multicast
  !
!
netconf-yang agent
  ssh
!
!
class-map type traffic match-all cmap1
  match protocol gre
  match source-address ipv4 161.0.1.1 255.255.255.255
  match destination-address ipv4 161.2.1.1 255.255.255.255
  end-class-map
!
policy-map type pbr gre-policy
  class type traffic cmap1
    decapsulate gre
  !
  class type traffic class-default
  !
end-policy-map
!
interface GigabitEthernet0/0/0/1
  vrf vrf1
  ipv4 address 2.2.2.2 255.255.255.0
  shutdown
!
vrf-policy
  vrf vrf1 address-family ipv4 policy type pbr input gre-policy
!
end
```

**Step 2** View the output of the VRF statistics.

**Example:**

```
Router#show policy-map type pbr vrf vrf1 addr-family ipv4 statistics
```

```
VRF Name:      vrf1
Policy-Name:   gre-policy
Policy Type:   pbr
Addr Family:   IPv4
```

```

Class:      cmapl
Classification statistics      (packets/bytes)
  Matched      :      13387587/1713611136
Transmitted statistics      (packets/bytes)
  Total Transmitted :      13387587/1713611136

Class:      class-default
Classification statistics      (packets/bytes)
  Matched      :      0/0
Transmitted statistics      (packets/bytes)
  Total Transmitted :      0/0

```

After you have verified that the statistics are displayed correctly, stream telemetry data and check the streamed data at the collector. For more information about collectors, see *Operate on Telemetry Data for In-depth Analysis of the Network* section in the [Monitor CPU Utilization Using Telemetry Data to Plan Network Infrastructure](#) chapter.

```

ios.0/0/CPU0/ $ mdt_exec -s Cisco-IOS-XR-infra-policymgr-oper:policy-manager
/global/policy-map/policy-map-types/policy-map-type/vrf-table/vrf/afi-table/afi/stats -c 100
{"node_id_str":"ios","subscription_id_str":"app_TEST_200000001","encoding_path":
"Cisco-IOS-XR-infra-policymgr-oper:policy-manager/global/policy-map/policy-map-types/policy-map-type
/vrf-table/vrf/afi-table/afi/stats","collection_id":"1","collection_start_time":"1601361558157",
"msg_timestamp":"1601361559179","data_json":[{"timestamp":"1601361559178","keys":[{"type":"ipv6"},
{"vrf-name":"vrf_gue_ipv4"},{"type":"ipv4"}],"content":{"pmap-name":"gre-policy","vrf-name":
"vrf1","appln-type":2,"addr-family":1,"rc":0,"plmgr-vrf-stats":[{"pmap-name":"gre-policy",
"cmmap-stats-arr":[{"cmmap-name":"cmap1","matched-bytes":"1713611136","matched-packets":"13387587",
"transmit-bytes":"1713611136","transmit-packets":"13387587"}]}]}]}],
"collection_end_time":"1601361559183"}
----- snipped for brevity -----

```

## Stream Telemetry Data for BGP FlowSpec

**Table 3: Feature History Table**

Feature Name	Release Information	Description
Stream Telemetry Data for BGP FlowSpec Statistics	Release 7.8.1	<p>Use Border Gateway Protocol (BGP) FlowSpec to mitigate the effects of distributed denial-of-service (DDoS) attack over the network.</p> <p>We have introduced streaming of BGP FlowSpec statistics using YANG data and telemetry. It allows you to monitor traffic flow match, drop in the traffic, or policing at definite rate for IPv4 and IPv6 parameters such as IP address, port, DSCP, and so on. In earlier releases, you could monitor BGP FlowSpec statistics through CLI.</p> <p>This feature introduces the <code>Cisco-IOS-XR-flowspec-oper.yang</code> data models to capture BGP FlowSpec statistics such as matched, dropped, and transmitted packet count on Cisco Network Convergence System 5700 Series Routers.</p>

Prior to Cisco IOS XR Software Release 7.8.1, BGP FlowSpec statistics were viewed using **show flowspec vrf all afi-all detail statistics** command. From Cisco IOS XR Software Release 7.8.1 you can stream telemetry data for BGP FlowSpec statistics using a `Cisco-IOS-XR-flowspec-oper.yang` data model.

For more information on BGP FlowSpec, see *BGP Configuration Guide for Cisco NCS 5500 Series Routers*.

You can stream BGP FlowSpec telemetry data from the XPath:

```
Cisco-IOS-XR-flowspec-oper:flow-spec/vrfs/vrf/afs/af/flows/flow
```

The following steps show the BGP FlowSpec configuration and the statistics that is streamed as telemetry data to the collector.

## SUMMARY STEPS

1. Check the configuration of the BGP FlowSpec.
2. View BGP FlowSpec statistics for IPv4 and IPv6.
3. View Model Driven Telemetry (MDT) of BGP FlowSpec statistics.

## DETAILED STEPS

**Step 1** Check the configuration of the BGP FlowSpec.

### Example:

```
Router# show running-config
Client config:
router bgp 100
nsr
bgp router-id 2.2.2.1
address-family ipv4 unicast
!
address-family vpnv4 unicast
!
address-family ipv6 unicast
!
address-family vpnv6 unicast
!
address-family ipv4 flowspec
!
address-family ipv6 flowspec
!
address-family vpnv4 flowspec
!
address-family vpnv6 flowspec
!
neighbor 1.1.1.1
  remote-as 100
  update-source Loopback1
  address-family ipv4 unicast
  !
  address-family vpnv4 unicast
  !
  address-family ipv4 flowspec
  !
  address-family vpnv4 flowspec
  !
!
neighbor 1.1.1.2
  remote-as 100
  update-source Loopback2
```



```
    address-family ipv6 unicast
    !
    address-family vpnv6 unicast
    !
    address-family ipv6 flowspec
    !
    address-family vpnv6 flowspec
    !
!
!
flowspec
local-install interface-all
address-family ipv4
    local-install interface-all
    service-policy type pbr redirect
!
!
end

class-map type traffic match-all c1
match protocol sctp
end-class-map
!
!
class-map type traffic match-all c2
match protocol udp
end-class-map
!
class-map type traffic match-all c3
match dscp 3
end-class-map
!
class-map type traffic match-all c1_6
match dscp af11
end-class-map
!
class-map type traffic match-all c2_6
match dscp 20
end-class-map
!
policy-map type pbr p1
class type traffic c1
    drop
!
class type traffic c2
    drop
!
class type traffic c3
    drop
!
class type traffic class-default
!
end-policy-map
!
policy-map type pbr p1_6
class type traffic c1_6
    set dscp af21
!
class type traffic c2_6
    set dscp af22
!
class type traffic class-default
!
end-policy-map
```

```

!
router bgp 100
nsr
bgp router-id 1.1.1.1
address-family ipv4 unicast
!
address-family vpnv4 unicast
!
address-family ipv6 unicast
!
address-family vpnv6 unicast
!
address-family ipv4 flowspec
!
address-family ipv6 flowspec
!
address-family vpnv4 flowspec
!
address-family vpnv6 flowspec
!
neighbor 2.2.2.1
  remote-as 100
  update-source Loopback1
  address-family ipv4 unicast
  !
  address-family vpnv4 unicast
  !
  address-family ipv4 flowspec
  !
  address-family vpnv4 flowspec
  !
!
neighbor 2.2.2.2
  remote-as 100
  update-source Loopback2
  address-family ipv6 unicast
  !
  address-family vpnv6 unicast
  !
  address-family ipv6 flowspec
  !
  address-family vpnv6 flowspec
  !
!
!
flowspec
address-family ipv4
  service-policy type pbr p1
!
address-family ipv6
  service-policy type pbr p1_6
!
!

```

## Step 2 View BGP FlowSpec statistics for IPv4 and IPv6.

### Example:

```

Router# show flowspec vrf all afi-all detail statistics
AFI: IPv4
  Flow          :Proto:=17
Flowspec Rule:
  Matches:
    Protocol      :                17
  Actions       :Traffic-rate: 0 bps (bgp.1)

```

```

    Statistics                (packets/bytes)
    Matched                   :                0/0
    Transmitted                :                0/0
    Dropped                    :                0/0
  Flow                        :Proto:=132
Flowspec Rule:
  Matches:
    Protocol                   :                132
    Actions                    :Traffic-rate: 0 bps (bgp.1)
    Statistics                  (packets/bytes)
    Matched                    :                0/0
    Transmitted                 :                0/0
    Dropped                     :                0/0
  Flow                        :DSCP:=3
Flowspec Rule:
  Matches:
    DSCP                       :                3
    Actions                    :Traffic-rate: 0 bps (bgp.1)
    Statistics                  (packets/bytes)
    Matched                     :                0/0
    Transmitted                  :                0/0
    Dropped                      :                0/0

AFI: IPv6
  Flow                        :DSCP:=10
Flowspec Rule:
  Matches:
    DSCP                       :                10
    Actions                    :DSCP: af21 (bgp.1)
    Statistics                  (packets/bytes)
    Matched                     :                0/0
    Transmitted                  :                0/0
    Dropped                      :                0/0
  Flow                        :DSCP:=20
Flowspec Rule:
  Matches:
    DSCP                       :                20
    Actions                    :DSCP: af22 (bgp.1)
    Statistics                  (packets/bytes)
    Matched                     :                0/0
    Transmitted                  :                0/0
    Dropped                      :

```

### Step 3 View Model Driven Telemetry (MDT) of BGP FlowSpec statistics.

After you have verified that the statistics are displayed correctly, stream telemetry data and check the streamed data at the collector. For more information about Model-Driven Telemetry collectors, see [Establish a Model-Driven Telemetry Session from a Router to a Collector](#).

#### Example:

##### MDT of BGP FlowSpec statistics

```

Router# run mdt_exec -s Cisco-IOS-XR-flowspec-oper:flow-spec/vrfs/vrf/afs/af/flows/flow
Enter any key to exit...
Request datatree:
  filter
    flow-spec (ka)
      vrfs
        vrf
          afs
            af
              flows
                flow

```

```

Sub_id 200000001, flag 0, len 0
Sub_id 200000001, flag 4, len 3952
-----
{"node_id_str":"PE","subscription_id_str":"app_TEST_200000001",
"encoding_path":"Cisco-IOS-XR-flowspec-oper:flow-spec/
vrf/vrf/afs/af/flows/flow","collection_id":"2",
"collection_start_time":"1661410086614","msg_timestamp":"1661410086633",
...
"dscp":[{"min":20,"max":20}], "fragment-type":0, "tcp-flag":{"value":0,
"match-any":false}}}], "collection_end_time":"1661410086635"}
-----
Sub_id 200000001, flag 8, len 0

```

## Stream Telemetry Data for ACL

**Table 4: Feature History Table**

Feature Name	Release Information	Description
Stream Telemetry Data for ACL	Release 7.8.1	<p>The Access control List (ACL) is an ordered list of rules used to filter the traffic to increase network performance, and to specify the system resource access permissions either grant or deny to users or systems for security.</p> <p>We have introduced the streaming of ACL statistics to monitor the traffic flow using YANG data and telemetry. It allows you to monitor dropped, matched, and denied packets of IPv4 and IPv6. In earlier releases, you could monitor ACL statistics through CLI.</p> <p>This feature introduces the <code>Cisco-IOS-XR-ipv4-acl-oper.yang</code> and <code>Cisco-IOS-XR-ipv6-acl-oper.yang</code> models to capture IPv4 and IPv6 ACL statistics on Cisco Network Convergence System 5700 Series Routers.</p>

Prior to Cisco IOS XR Software Release 7.8.1, ACL statistics were viewed using **show run ipv4 access-list** and **show run ipv6 access-list** commands. From Cisco IOS XR Software Release 7.8.1 you can stream telemetry data for ACL statistics using `Cisco-IOS-XR-ipv4-acl-oper.yang` and `Cisco-IOS-XR-ipv6-acl-oper.yang` data models.

For more information on ACL, see .

You can stream ACL telemetry data from the following XPath:

```
Cisco-IOS-XR-ipv4-acl-oper:ipv4-acl-and-prefix-list/
access-list-manager/accesses/access/access-list-sequences/access-list-sequence
```

```
Cisco-IOS-XR-ipv6-acl-oper:ipv6-acl-and-prefix-list/
access-list-manager/accesses/access/access-list-sequences/access-list-sequence
```

The following steps show the ACL configuration and the statistics that is streamed as telemetry data to the collector.

## SUMMARY STEPS

1. Check the configuration of ACL packets for IPv4 and IPv6.
2. View ACL statistics for IPv4 and IPv6 (Ingress or Egress direction-wise).
3. View Model Driven Telemetry (MDT) of ACL statistics.

## DETAILED STEPS

---

**Step 1** Check the configuration of ACL packets for IPv4 and IPv6.

**Example:**

```
Router# show run ipv4 access-list
ipv4 access-list test
 10 permit tcp any any
 20 deny udp any any
!
ipv4 access-list tempv4
 10 deny udp any port-group p1 any
 20 deny tcp any any
!
```

**Example:**

```
Router# show run ipv6 access-list
Thu Jun 16 18:03:29.864 UTC
ipv6 access-list v6
 10 permit tcp any any
 20 deny udp any any
!
ipv6 access-list tempv6
 10 deny udp any port-group p1 any
 20 deny tcp any any
!
```

**Step 2** View ACL statistics for IPv4 and IPv6 (Ingress or Egress direction-wise).

**Example:**

```
Router# show access-lists ipv4 tempv4 hardware ingress location 0/1/CPU0
ipv4 access-list tempv4
 10 deny udp any port-group p1 any (83319 matches)
 20 deny tcp any any (83319 matches)
```

**Example:**

```
Router# show access-lists ipv6 tempv6 hardware ingress location 0/1/CPU0
ipv6 access-list tempv6
 10 deny udp any port-group p1 any (55792 matches)
 20 deny tcp any any (55792 matches)
!
```

**Step 3** View Model Driven Telemetry (MDT) of ACL statistics.

After you have verified that the statistics are displayed correctly, stream telemetry data and check the streamed data at the collector. For more information about Model-Driven Telemetry collectors, see [Establish a Model-Driven Telemetry Session from a Router to a Collector](#).

**Example:**

MDT of ACL IPv4 statistics

```

Router# run mdt_exec -s Cisco-IOS-XR-ipv4-acl-oper:ipv4-acl-and-prefix-list/
access-list-manager/accesses/access-list-sequences/access-list-sequence -c 30000
Enter any key to exit...
Request datatree:
  filter
    ipv4-acl-and-prefix-list (ka)
      access-list-manager
        accesses
          access
            access-list-sequences
              access-list-sequence
Sub_id 200000001, flag 0, len 0
Sub_id 200000001, flag 4, len 6739
-----
{"node_id_str":"ios","subscription_id_str":"app_TEST_200000001",
"encoding_path":"Cisco-IOS-XR-ipv4-acl-oper:ipv4-acl-and-prefix-list/access-list-manager/
accesses/access-list-sequences/access-list-sequence","collection_id":"1",
"collection_start_time":"1655427578624","msg_timestamp":"1655427578632",
"data_json":[{"timestamp":"1655427578629","keys":[{"access-list-name":"tel_test"},
{"sequence-number":10}], "content":{"item-type":"normal","sequence":10,"grant":"permit",
"protocol-operator":0,"protocol":512,"protocol2":0,"source-address":"0.0.0.0","source-address-mask":"255.255.255.255"
-----
"fragment-offset1":0,"fragment-offset2":0,"set-ttl":65535,"fragment-flags":0,"police":{"police-value":0,
"police-unit":"pps"},"police-peak-value":0,"police-peak-unit":"pps"},"priority":"acl-priority-unspec",
"is-icmp-on":false}}],"collection_end_time":"1655427578633"}
-----

```

**Example:****MDT of ACL IPv6 statistics:**

```

Router# run mdt_exec -s
Cisco-IOS-XR-ipv6-acl-oper:ipv6-acl-and-prefix-list/access-list-manager/accesses/
access-list-sequences/access-list-sequence -c 30000
Enter any key to exit...
Request datatree:
  filter
    ipv6-acl-and-prefix-list (ka)
      access-list-manager
        accesses
          access
            access-list-sequences
              access-list-sequence
Sub_id 200000001, flag 0, len 0
Sub_id 200000001, flag 4, len 4005
-----
{"node_id_str":"ios","subscription_id_str":"app_TEST_200000001","encoding_path":
"Cisco-IOS-XR-ipv6-acl-oper:ipv6-acl-and-prefix-list/access-list-manager/accesses/
access-list-sequences/access-list-sequence","collection_id":"1",
"collection_start_time":"1655432482881","msg_timestamp":"1655432482886",
"data_json":[{"timestamp":"1655432482884","keys":[{"access-list-name":"test"},
{"sequence-number":10}], "content":{"is-ace-type":"normal","is-ace-sequence-number":10,
"is-packet-allow-or-deny":"permit","is-protocol-operator":"none",
"is-ipv6-protocol-type":6,"is-ipv6-protocol2-type":0,"is-source-address-in-numbers":
....
"police-peak-unit":"pps"},"priority":"acl-priority-unspec","fragment-flags":0,
"is-icmp-message-on":0}}],"collection_end_time":"1655432482886"}
-----
Sub_id 200000001, flag 8, len 0
Sub_id 200000001, flag 4, len 4005

```

You can apply filter on ACL name as followed:

```
Router# run mdt_exec -s  
Cisco-IOS-XR-ipv4-acl-oper:ipv4-acl-and-prefix-list/access-list-manager/accesses/  
access[access-list-name="test"]/access-list-sequences/access-list-sequence -c 30000
```

---

