



## **Netflow Command Reference for Cisco NCS 5500 Series, Cisco NCS 540 Series and Cisco NCS 560 Series Routers**

**First Published:** 2015-12-23

**Last Modified:** 2021-07-15

### **Americas Headquarters**

Cisco Systems, Inc.  
170 West Tasman Drive  
San Jose, CA 95134-1706  
USA  
<http://www.cisco.com>  
Tel: 408 526-4000  
800 553-NETS (6387)  
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2015–2021 Cisco Systems, Inc. All rights reserved.



## CONTENTS

---

### PREFACE

#### **Preface** v

Changes to This Document v

Communications, Services, and Additional Information vi

---

### CHAPTER 1

#### **NetFlow Commands** 1

cache entries 3

cache permanent 4

cache timeout 5

cache immediate 6

clear flow exporter 7

clear flow monitor 8

destination 9

dscp 10

exporter 11

flow 12

flow exporter-map 14

flow monitor-map 16

flow datalinkframe section monitor 18

hw-module profile netflow fpc-enable 19

options 20

option filtered 23

random 1 out-of 24

record ipv4 25

record ipv6 27

record mpls 29

record datalinksection 31

sampler-map	32
show flow exporter	34
show flow exporter-map	36
show flow monitor	39
show flow monitor-map	44
show flow platform producer statistics location	47
show sampler-map	49
source (NetFlow)	50
template (NetFlow)	52
transport udp	53
version v9	54
version ipfix	55

---

**CHAPTER 2****sFlow Commands 57**

hw-module profile netflow sflow-enable	58
record sflow	59
sflow options	60
version sflow v5	62
router-id	63



## Preface

This guide consists of information regarding the commands for NetFlow in Cisco IOS XR Software.

For more information about the NetFlow , see the *Configuring NetFlow* module in the *Netflow Configuration Guide for Cisco NCS 5500 Series Routers*, *Netflow Configuration Guide for Cisco NCS 540 Series Routers*, or *Netflow Configuration Guide for Cisco NCS 560 Series Routers*.

The preface consists of these sections:

- [Changes to This Document, on page v](#)
- [Communications, Services, and Additional Information, on page vi](#)

## Changes to This Document

This table lists the technical changes made to this document since it was first released.

**Table 1: Changes to This Document**

Date	Summary
December 2015	Initial release of this document.
July 2016	Republished with documentation updates for Cisco IOS XR Release 6.0.2 features.
August 2016	Republished with documentation updates for Cisco IOS XR Release 6.1.2 features.
July 2017	Republished with documentation updates for Cisco IOS XR Release 6.2.2 features.
September 2017	Republished with documentation updates for Cisco IOS XR Release 6.3.1 features.
March 2018	Republished with documentation updates for Cisco IOS XR Release 6.3.2 features.
August 2018	Republished with documentation updates for Cisco IOS XR Release 6.5.1 features.
May 2019	Republished for the Cisco IOS XR Release 6.6.25.

Date	Summary
August 2019	Republished for the Cisco IOS XR Release 7.0.1.
February 2021	Republished for the Cisco IOS XR Release 7.3.1.
July 2021	Republished for Cisco IOS XR Release 7.4.1.
November 2021	Republished for Cisco IOS XR Release 7.4.16.
November 2021	Republished for Cisco IOS XR Release 7.5.1.

## Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions and services, visit [Cisco Marketplace](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

### Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.



# NetFlow Commands

---



---

**Note** All commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 540 Series Router that is introduced from Cisco IOS XR Release 6.3.2. References to earlier releases in Command History tables apply to only the Cisco NCS 5500 Series Router.

---



- Note**
- Starting with Cisco IOS XR Release 6.6.25, all commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 560 Series Routers.
  - Starting with Cisco IOS XR Release 6.3.2, all commands applicable for the Cisco NCS 5500 Series Router are also supported on the Cisco NCS 540 Series Router.
  - References to releases before Cisco IOS XR Release 6.3.2 apply to only the Cisco NCS 5500 Series Router.
  - Cisco IOS XR Software Release 7.0.1 specific updates are not applicable for the following variants of Cisco NCS 540 Series Routers:
    - N540-28Z4C-SYS-A
    - N540-28Z4C-SYS-D
    - N540X-16Z4G8Q2C-A
    - N540X-16Z4G8Q2C-D
    - N540X-16Z8Q2C-D
    - N540-12Z20G-SYS-A
    - N540-12Z20G-SYS-D
    - N540X-12Z16G-SYS-A
    - N540X-12Z16G-SYS-D
- 

This module provides command line interface (CLI) commands for configuring NetFlow on the Cisco NCS 5500 Series RouterCisco NCS 540 Series Router.

To use commands of this module, you must be in a user group associated with a task group that includes appropriate task IDs. If the user group assignment is preventing you from using any command, contact your AAA administrator for assistance.

- [cache entries](#), on page 3
- [cache permanent](#), on page 4
- [cache timeout](#), on page 5
- [cache immediate](#), on page 6
- [clear flow exporter](#), on page 7
- [clear flow monitor](#), on page 8
- [destination](#), on page 9
- [dscp](#), on page 10
- [exporter](#), on page 11
- [flow](#), on page 12
- [flow exporter-map](#), on page 14
- [flow monitor-map](#), on page 16
- [flow datalinkframesection monitor](#), on page 18
- [hw-module profile netflow fpc-enable](#), on page 19
- [options](#), on page 20
- [option filtered](#), on page 23
- [random 1 out-of](#), on page 24
- [record ipv4](#), on page 25
- [record ipv6](#), on page 27
- [record mpls](#), on page 29
- [record datalinksection](#), on page 31
- [sampler-map](#), on page 32
- [show flow exporter](#), on page 34
- [show flow exporter-map](#), on page 36
- [show flow monitor](#), on page 39
- [show flow monitor-map](#), on page 44
- [show flow platform producer statistics location](#), on page 47
- [show sampler-map](#), on page 49
- [source \(NetFlow\)](#), on page 50
- [template \(NetFlow\)](#), on page 52
- [transport udp](#), on page 53
- [version v9](#), on page 54
- [version ipfix](#), on page 55

## cache entries

To configure the number of entries in the monitor map flow cache, enter the **cache entries** command in flow monitor map configuration mode. To remove a configured number of entries and return the cache to the default configuration, use the **no** form of this command.

**cache entries** *number*

<b>Syntax Description</b>	<i>number</i> Number of entries in the flow cache. Replace the <i>number</i> argument with the number of flow entries allowed in the flow cache. Range is from 4096 through 1000000.
---------------------------	--

<b>Command Default</b>	<i>number</i> : 65535
------------------------	-----------------------

<b>Command Modes</b>	Flow monitor map configuration
----------------------	--------------------------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.
-------------------------	--

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

<b>Examples</b>	This example shows how to configure the number of entries in the monitor map flow cache to be 10000:
-----------------	--

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# cache entries 10000
```

# cache permanent

To disable the removal of entries from the monitor map flow cache, enter the **cache permanent** command in flow monitor map configuration mode. To re-enable the removal of entries from the flow cache, use the **no** form of this command.

## cache permanent

<b>Syntax Description</b>	This command has no keywords or arguments.	
<b>Command Default</b>	The removal of entries from the monitor map flow cache is enabled.	
<b>Command Modes</b>	Flow monitor map configuration	
<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.	
<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

## Examples

This example shows how to disable the removal of entries from the monitor map flow cache:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# cache permanent
```

This example shows how to re-enable the removal of entries from the monitor map flow cache:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# no cache permanent
```

# cache timeout

To configure the active, inactive, and update flow cache timeout, enter the **cache timeout** command in flow monitor map configuration mode. To remove the configured timeout value and return the cache to its default timeout value, use the **no** form of this command.

**cache timeout** {**active** | **inactive** | **update**} *timeout\_value*

Syntax Description	active	Specifies the active flow timeout.
	<b>inactive</b>	Specifies the inactive flow timeout.
	<b>update</b>	Specifies the update timeout.
	<i>timeout_value</i>	Timeout value for the specified keyword ( <b>active</b> , <b>inactive</b> or <b>update</b> ) in seconds. Range is from 1 through 604800.

Command Default	For active timeout, the default value is 1800 seconds. For inactive timeout, the default value is 15 seconds. For update timeout, the default value is 1800 seconds.
-----------------	--

Command Modes	Flow monitor map configuration
---------------	--------------------------------

Command History	Release	Modification
	Release 6.0	This command was introduced.

Usage Guidelines	The <b>inactive</b> timeout value should be smaller than the <b>active</b> timeout value. The <b>update</b> keyword is used for permanent caches only. It specifies the timeout value that is used to export entries from permanent caches. In this case, the entries are exported but remain the cache.
------------------	--

Task ID	Task ID	Operations
	netflow	read, write

Examples	This example shows how to set the active timeout for the monitor map cache to 200,000 seconds:
----------	--

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# cache timeout active 200000
```

# cache immediate

To enable immediate aging cache type, use the **cache immediate** command in flow monitor map configuration mode. To disable, use **no** form of the command.

**cache immediate**

**Syntax Description** This command has no keywords or arguments.

**Command Default** None

**Command Modes** Flow monitor map configuration

Command History	Release	Modification
	Release 6.3.2	This command was introduced.
	Release 7.0.1	This command was introduced.

**Usage Guidelines** Immediate Aging is a special cache type that ensures that the flows are exported as soon as they are added to the cache.

Task ID	Task ID	Operations
	netflow	read, write

This example shows how to enable immediate aging cache type:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)#flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# cache immediate
```

# clear flow exporter

To export flow exporter templates to the collector or restart the flow exporter statistics collector, enter the **clear flow exporter** command in XR EXEC mode.

```
clear flow exporter [fem-name] {restart | statistics} location node-id
```

Syntax Description	
<i>fem-name</i>	(Optional) Flow exporter name.
<b>restart</b>	Exports all of the current templates to the collector.
<b>statistics</b>	Clears the exporter statistics.
<b>location</b> <i>node-id</i>	Identifies the node whose flow exporter statistics you want to clear, or whose flow exporter statistics collector you want to restart. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.

**Command Default** No default behavior or values

**Command Modes** XR EXEC mode

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	basic-services	read, write
	netflow	read, write

## Examples

This example exports all templates to the collector:

```
RP/0/RP0/CPU0:router# clear flow exporter restart location 0/0/SP  
Restart exporter all locations. Continue? [confirm]
```

This example shows how to clear flow exporter statistics on a specific node:

```
RP/0/RP0/CPU0:router# clear flow exporter statistics location 0/0/CPU0  
Clear statistics for all exporters on the location. Continue? [confirm]
```

# clear flow monitor

To clear the flow monitor data, enter the **clear flow monitor** command in XR EXEC mode.

```
clear flow monitor [name] cache [{force-export | statistics}] location node-id
```

Syntax Description	
<i>name</i>	(Optional) Identifies a specific cache you want to clear.
<b>cache</b>	Clears all cache related information.
<b>force-export</b>	(Optional) Forces the export of flow records on flushing the cache on the specified node.
<b>statistics</b>	(Optional) Clears cache statistics on a specific node.
<b>location</b> <i>node-id</i>	Node whose flow monitor you want to clear. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.

**Command Default** None

**Command Modes** XR EXEC mode

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

## Examples

This example shows how to clear the cache-related flow records on a specific node:

```
RP/0/RP0/CPU0:router# clear flow monitor cache force-export location 0/0/CPU0
Clear cache entries for this monitor on this location. Continue? [confirm]
```

# destination

To configure the collector export destination, enter the **destination** command in flow exporter map configuration mode. To remove a configured export destination, use the **no** form of this command.

**destination** *hostname\_or\_IP\_address* [**vrf** *vrf\_name*]

<b>Syntax Description</b>	<p><i>hostname_or_IP_address</i> Specify the export destination for the current flow exporter map. Enter the hostname or destination IP address in the <i>A.B.C.D</i> format.</p> <hr/> <p><b>vrf</b> <i>vrf_name</i> (Optional) Specify the name of the VRF that is used to reach export destination. This is an optional keyword. If the <b>vrf</b> keyword is specified, then the destination is searched in the VRF that is specified (<i>vrf_name</i>). If the <b>vrf</b> keyword is not specified then, the destination is searched in the default routing table.</p>				
<b>Command Default</b>	None				
<b>Command Modes</b>	Flow exporter map configuration				
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.
Release	Modification				
Release 6.0	This command was introduced.				
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.				
<b>Task ID</b>	<table border="1"> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read, write</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				

## Examples

This example shows how to configure the flow exporter map export destination to be a specific IP address:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# destination 172.18.189.38
```

# dscp

To configure the differentiated services codepoint (DSCP) value for export packets, enter the **dscp** command in flow exporter map configuration mode. To remove a configured DSCP value, use the **no** form of this command.

**dscp** *dscp\_value*

<b>Syntax Description</b>	<i>dscp_value</i> Specifies the DSCP value for export packets. Replace <i>dscp_value</i> with a number. Range is from 0 through 63.				
<b>Command Default</b>	None				
<b>Command Modes</b>	Flow exporter map configuration				
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.
Release	Modification				
Release 6.0	This command was introduced.				
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.				
<b>Task ID</b>	<table border="1"> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read, write</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				
<b>Examples</b>	<p>This example shows how to configure the DSCP value for export packets to be 30:</p> <pre>RP/0/RP0/CPU0:router# configure RP/0/RP0/CPU0:router(config)# flow exporter-map map1 RP/0/RP0/CPU0:router(config-fem)# dscp 30</pre>				

# exporter

To associate a flow exporter map with the current flow monitor map, enter the **exporter** command in flow monitor map configuration mode. To remove an associated flow exporter map from a flow monitor map, use the **no** form of this command.

**exporter** *map\_name*

## Syntax Description

*map\_name* Name of the flow exporter map you want to associate with the current flow monitor map. The exporter map name can be a maximum of 32 characters.

**Note** A single flow monitor map supports up to 8 exporters.

## Command Default

None

## Command Modes

Flow monitor map configuration

## Command History

Release	Modification
Release 6.0	This command was introduced.

## Usage Guidelines

No specific guidelines impact the use of this command.

## Task ID

Task ID	Operations
netflow	read, write

## Examples

This example shows how to associate a flow exporter map called “fem\_1” with the current flow monitor map:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# exporter fem_1
```

# flow

To specify a flow monitor map and a sampler map for the packets on an interface, use the **flow** command in interface configuration mode. To remove a configured flow monitor map, use the **no** form of this command.

**flow** [{**ipv4** | **ipv6** | **mpls**}] **monitor** *name* **sampler** *name* {**ingress**}

Syntax Description		
<b>ipv4</b>		Enables IPV4 NetFlow on the specified interface.
<b>ipv6</b>		Enables IPV6 NetFlow on the specified interface.
<b>mpls</b>		Enables Multiprotocol Label Switching (MPLS)-aware NetFlow on the specified interface.
<b>monitor</b> <i>name</i>		Specifies the name of the flow monitor map you want to specify for IPv4, IPv6, or MPLS packets.
<b>sampler</b> <i>name</i>		Name of the sampler map you want to apply to the flow monitor map.
<b>ingress</b>		Applies the flow monitor map on incoming packets.

**Command Default** None

**Command Modes** Interface configuration

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

## Examples

This example shows how to enable IPV4 NetFlow on a HundredGigE interface, and then apply the flow monitor map, named "map1," on incoming IPV4 packets:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/3/0/0
RP/0/RP0/CPU0:router(config-if)# flow ipv4 monitor map1 sampler smap1 ingress
```

This example shows how to enable MPLS NetFlow on a HundredGigE interface, and apply the flow monitor map, named "map\_mpls1," on incoming MPLS packets:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow mpls monitor map_mpls1 sampler smap1 ingress
```

This example shows how to enable IPv4 NetFlow on a Bridge-group virtual interface, and then apply the flow monitor map on incoming IPv4 packets:

```
RP/0/RP0/CPU0:router# configure  
RP/0/RP0/CPU0:router(config)# interface BVI 1  
RP/0/RP0/CPU0:router(config-if)# flow ipv4 monitor NMS sampler NMS ingress
```

This example shows how to enable IPv6 NetFlow on a Bridge-group virtual interface, and then apply the flow monitor map on incoming and incoming IPv6 packets:

```
RP/0/RP0/CPU0:router# configure  
RP/0/RP0/CPU0:router(config)# interface BVI 1  
RP/0/RP0/CPU0:router(config-if)# flow ipv6 monitor NMS sampler NMS ingress
```

## flow exporter-map

To create a flow exporter map and enter flow exporter map configuration mode, use the **flow exporter-map** command in XR Config mode. To remove a configured flow exporter map, use the **no** form of this command.

**flow exporter-map** *fem-name*

<b>Syntax Description</b>	<i>fem-name</i> Creates a new exporter map name, or specifies the name of an existing exporter map.				
<b>Command Default</b>	None				
<b>Command Modes</b>	XR Config mode				
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.
Release	Modification				
Release 6.0	This command was introduced.				

**Usage Guidelines** When you issue the **flow exporter-map** *fem-name* command in XR Config mode, the CLI prompt changes to “config-fem,” indicating that you have entered the flow exporter map configuration submodule.

In this sample output, the question mark ( ? ) online help function displays all the commands available under flow exporter map configuration submodule:

```
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# ?

RP/0/RP0/CPU0:router(config-fem)#?
clear          Clear the uncommitted configuration
commit        Commit the configuration changes to running
describe      Describe a command without taking real actions
do            Run an exec command
dscp          Specify DSCP value for export packets
exit          Exit from this submodule
no            Negate a command or set its defaults
pwd           Commands used to reach current submodule
root          Exit to the XR Config mode
show          Show contents of configuration
source        Source interface
transport     Specify the transport protocol for export packets
version       Specify export version parameters
```

Task ID	Task ID	Operations
	netflow	read, write

### Examples

This example shows how to create a flow exporter map called “map1,” and then enter the flow exporter map configuration submodule for that map:

```
RP/0/RP0/CPU0:router# configure  
RP/0/RP0/CPU0:router(config)# flow exporter-map map1  
RP/0/RP0/CPU0:router(config-fem)#
```

# flow monitor-map

To create and configure a flow monitor map and enter flow monitor map configuration submenu, use the **flow monitor-map** command in XR Config mode. To remove a configured flow monitor map, use the **no** form of this command:

```
flow monitor-map map_name
```

<b>Syntax Description</b>	<i>map_name</i> New monitor map name, or specifies the name of an existing monitor map. The monitor map name can be a maximum 32 characters.
---------------------------	--

<b>Command Default</b>	None
------------------------	------

<b>Command Modes</b>	XR Config mode
----------------------	----------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

**Usage Guidelines** When you issue the **flow monitor-map** *map\_name* command in XR Config mode, the CLI prompt changes to “config-fmm,” indicating that you have entered the flow monitor map configuration submenu. In the following sample output, the question mark ( ? ) online help function displays all the commands available under flow monitor map configuration submenu:

```
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)#?

  cache      Specify flow cache attributes
  clear      Clear the uncommitted configuration
  commit     Commit the configuration changes to running
  describe   Describe a command without taking real actions
  do         Run an exec command
  exit       Exit from this submenu
  exporter   Specify flow exporter map name
  no         Negate a command or set its defaults
  pwd        Commands used to reach current submenu
  record     Specify a flow record map name
  root       Exit to the XR Config mode
  show       Show contents of configuration
```

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

**Examples** This example shows how to enter flow monitor map configuration mode for a monitor map called “map1.”

```
RP/0/RP0/CPU0:router# configure  
RP/0/RP0/CPU0:router(config)# flow monitor-map map1  
RP/0/RP0/CPU0:router(config-fmm)#
```

## flow datalinkframesection monitor

To monitor and capture information element that carries  $n$  octets from the data link frame (IPFIX 315) of a selected frame in the ingress direction of an interface, use **flow datalinkframesection monitor** command in interface configuration mode.

**flow datalinkframesection monitor** *monitor-map* **sampler** *sampler-map* **ingress**

Syntax Description	
<b>monitor</b> <i>monitor-map</i>	Specify flow monitor map name.
<b>sampler</b> <i>sampler-map</i>	Specify flow sampler map name.
<b>ingress</b>	Specify ingress direction. The IPFIX 315 info is captured from incoming traffic on specified interface.

**Command Default** None.

**Command Modes** Interface configuration mode

Command History	Release	Modification
	Release 6.3.2	This command was introduced.
	Release 7.0.1	This command was introduced.

**Usage Guidelines** When datalinkframesection flow type is enabled on an interface, other flows like IPv4, IPv6 and MPLS are not allowed. The option field in the frame indicates the IPFIX 315 info.

Task ID	Task	Operation
	netflow	read, write

This sample shows how to enable flow datalinkframesection monitor on hundredGigE interface:

```
RP/0/RP0/CPU0:router (config) #interface hundredGigE 0/0/0/18
RP/0/RP0/CPU0:router (config-if) #flow datalinkframesection monitor ipfix-mon sampler ipfix-sam
ingress
```

# hw-module profile netflow fpc-enable

To enable full packet capture feature on a specified node location, use the **hw-module profile netflow fpc-enable location** command in the configuration mode.

**hw-module profile profile netflow fpc-enable location** *node-id*

<b>Syntax Description</b>	<i>node-id</i> The node-id argument is entered in the rack/slot/module notation.
---------------------------	--

<b>Command Default</b>	Netflow Full Packet Capture(FPC) is disabled.
------------------------	---

<b>Command Modes</b>	Configuration
----------------------	---------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 7.0.1	This command was introduced.

<b>Usage Guidelines</b>	When no location is specified the full packet capture gets enabled on all line cards.
-------------------------	---



- |             |  |
|-------------|--|
| <b>Note</b> | <ul style="list-style-type: none"> <li>• You should reload the line card for the changes to take effect.</li> <li>• If full packet capture is disabled, then Netflow captures only IPv4 and IPv6 packets.</li> <li>• If full packet capture is enabled, then Netflow captures IPv4, IPv6, and L2VPN pseudo wire (PW) packets.</li> </ul> |
|-------------|--|

<b>Task ID</b>	<b>Task ID</b>	<b>Operation</b>
	netflow	read, write

This example shows how to enable full packet capture on node location 0/0/cpu0:

```
(config)# hw-module profile netflow fpc-enable location 0/0/CPU0
```

# options

To export the tables in the options template and specify export timeout values, enter the **options** command in flow exporter map version configuration mode. To return the options template to its default configuration values, use the **no** form of this command.

**options** {**interface-table** | **sampler-table** | **vrf-table**} [**timeout** *seconds*]

## Syntax Description

<b>interface-table</b>	Export the interface table.
<b>sampler-table</b>	Exports the sampler table.  Use <b>options sampler-table timeout</b> command to send IE 305. This command configures the timeout value for the sampler table. This timeout value can be in the range 1–604800 seconds and the default value is 1800 seconds.  You can also use <b>options sampler-table</b> command to export the following IEs: <ul style="list-style-type: none"> <li>• IE 302—to export selector ID.</li> <li>• IE 304—to export sampling algorithm.</li> <li>• IE 309—to export sampling size.</li> <li>• IE 310—to export sampling population.</li> <li>• IE 84—to export sampler name.</li> <li>• IE 335—to export selector name.</li> </ul> <p style="text-align: center;">IE 309, IE 310, and IE 335 are supported starting from Release 7.8.2</p>
<b>vrf-table</b>	Exports the VRF to VRF-Name table.
<b>timeout</b> <i>seconds</i>	Specifies the export timeout value. Replace <i>seconds</i> with the export timeout value. Range is from 1 through 604800 seconds.

## Command Default

Without options command, the default value for timeout is 0 seconds, which means that the template options are not exported by default. Where as when options command is used without mentioning any timeout, default timeout is 1800 seconds.

## Command Modes

Flow exporter map version configuration

## Command History

Release	Modification
Release 6.0	This command was introduced.

## Usage Guidelines

No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow read, write	

### Examples

This example shows how to export the timeout in the interface table to the options template.

```
RP/0/RP0/CPU0:router(config)# flow exporter-map f1
RP/0/RP0/CPU0:router(config-fem)# version v9
RP/0/RP0/CPU0:router(config-fem)# options interface-table timeout 45
```

### Examples

This is the sample output after setting to export the interface table and configure the export timeout value:

```
RP/0/RP0/CPU0:router(config-fem-ver)# show running-config flow exporter-map f1
flow exporter-map f1
  version v9
  options vrf-table 50
  !
  transport udp 9321
  source HundredGigE 0/4/3/0
  destination 10.64.81.237
  !

RP/0/RP0/CPU0:router(config-fem-ver)# do show flow exporter-map f1

Flow Exporter Map : f1
-----
Id                : 21
DestinationIpAddr : 10.64.81.237
SourceIfName      : HundredGigE 0/4/3/0
SourceIpAddr      : 0.0.0.0
DSCP              : 0
TransportProtocol : UDP
TransportDestPort : 9321

Export Version: 9
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout : 1800 seconds
  Interface-Table Export Timeout : 0 seconds
  Sampler-Table Export Timeout : 0 seconds
  VRF-Table Export Timeout : 50 seconds

RP/0/RP0/CPU0:router(config-fem-ver)# do show running-config flow exporter-map f1
flow exporter-map f1
  version v9
  options interface-table
  options sampler-table
  options vrf-table
  !
  transport udp 9321
  source HundredGigE 0/4/3/0
  destination 10.64.81.237
  !
RP/0/RP0/CPU0:router(config-fem-ver)# show flow exporter-map f1
```

Flow Exporter Map : f1

```
-----  
Id : 21  
DestinationIpAddr : 10.64.81.237  
SourceIfName : HundredGigE 0/4/3/0  
SourceIpAddr : 0.0.0.0  
DSCP : 0  
TransportProtocol : UDP  
TransportDestPort : 9321
```

Export Version: 9

```
Common Template Timeout : 1800 seconds  
Options Template Timeout : 1800 seconds  
Data Template Timeout : 1800 seconds  
Interface-Table Export Timeout : 1800 seconds  
Sampler-Table Export Timeout : 1800 seconds  
VRF-Table Export Timeout : 1800 seconds
```

# option filtered

To enable filtering of the Netflow records, use **option filtered** command in flow monitor map configuration mode.

## option filtered

<b>Syntax Description</b>	<b>filtered</b> Enables filtering of records
---------------------------	--

<b>Command Default</b>	Flow filtering is disabled.
------------------------	-----------------------------

<b>Command Modes</b>	Flow monitor map configuration
----------------------	--------------------------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 7.2.2	This command was introduced.

<b>Usage Guidelines</b>	MPLS netflow filtering is not supported.
-------------------------	--

Since the filtering of packets is based on the ACL, you must define ACL configuration before using **option filtered** command. Use the **capture** keyword while defining ACL. For example:

```
ipv4 access-list nf_ex
 10 permit ipv4 10.1.1.1/24 any capture
```

<b>Task ID</b>	<b>Task ID</b>	<b>Operation</b>
	netflow	read, write

This example shows how to create flow monitor map that filters Netflow records with cache entries upto 10000:

```
RP/0/RP0/CPU0:router# config
RP/0/RP0/CPU0:router(config)# flow monitor-map fmm1
RP/0/RP0/CPU0:router(config-fmm)# record ipv4
RP/0/RP0/CPU0:router(config-fmm)# option filtered
RP/0/RP0/CPU0:router(config-fmm)# exporter fem1
RP/0/RP0/CPU0:router(config-fmm)# cache entries 10000
RP/0/RP0/CPU0:router(config-fmm)# cache timeout active 1800
RP/0/RP0/CPU0:router(config-fmm)# cache timeout inactive 15
RP/0/RP0/CPU0:router(config-fmm)# exit
```

## random 1 out-of

To configure the packet sampling interval for a monitor map, use the **random 1 out-of** command in sampler map configuration submode. To remove a configured sampling interval and return to the default sampling interval, use the **no** form of this command. The limit of sampling rate values per line card per direction is 4, and limit of total samplers per line card per direction is 16.

**random 1 out-of** *number\_of\_packets*

<b>Syntax Description</b>	<i>number_of_packets</i> Sampling interval in units of packets. Replace the <i>number_of_packets</i> argument with a number. Range is from 1 through 65535 units.
---------------------------	---

<b>Command Default</b>	There is no default value to <i>number_of_packets</i> . However, for optimal performance, the recommended value for <i>number_of_packets</i> is 10000.
------------------------	--

<b>Command Modes</b>	Sampler map configuration
----------------------	---------------------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.
	Release 6.3.1	Support for sampling interval of 1:1000 was introduced.

<b>Usage Guidelines</b>	On high bandwidth interfaces, applying NetFlow processing to every single packet can result in significant CPU utilization.
-------------------------	---

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

<b>Examples</b>	This example shows how to configure the sampler map to randomly sample 1 out of every 2000 packets:
-----------------	---

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# sampler map1
RP/0/RP0/CPU0:router(config-sm)# random 1 out-of 2000
```

# record ipv4

To activate an IPv4 flow record, use the **record ipv4** command in flow monitor map configuration mode. To deactivate the flow record, use the **no** form of this command.

```
record ipv4 [ { peer-as | | [srv6][12-13] } ]
```

## Syntax Description

**peer-as** (Optional) Records peer AS.

**Note** The Border Gateway Protocol (BGP) AS is not collected unless the **bgp attribute download** command is configured.

**srv6** Records SRv6 based NetFlow data.

**12-13** Records L2 and L3 specific NetFlow data.

## Command Default

The default is that no IPv4 flow record is enabled.

## Command Modes

Flow monitor map configuration

## Command History

Release	Modification
Release 6.0	This command was introduced.
Release 7.8.1	This command was modified and a new optional keyword, <code>srv6</code> is introduced for the <code>record ipv4</code> option.
Release 7.10.1	This command was modified and a new optional keyword, <code>12-13</code> is introduced for the <code>record ipv4</code> option.

## Usage Guidelines

- The BGP AS is not collected unless the **bgp attribute download** command is configured.
- The **record ipv4** command exports the BGP AS information in the following format:
 

```
bgpSourceAsNumber
bgpDestinationAsNumber
```
- The **record ipv4 peer-as** command exports the adjacent BGP AS information in the following format:
 

```
bgpPrevAdjacentAsNumber
bgpNextAdjacentAsNumber
```

## Task ID

Task ID	Operations
netflow	read, write

## Examples

This example shows how to configure an IPv4 flow record:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# record ipv4
```

This example shows how to configure an IPv4 flow record:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# record ipv4
RP/0/RP0/CPU0:router(config-fmm)# exit
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow ipv4 monitor monitor1 ingress
RP/0/RP0/CPU0:router(config-if)# end
```

This example shows how to configure the srv6 flow record map name for the record ipv4 option:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config-fem)# flow monitor-map MON-MAP-v6
RP/0/RP0/CPU0:router(config-fmm)# record ipv6 srv6
RP/0/RP0/CPU0:router(config-fmm)# exporter EXP
RP/0/RP0/CPU0:router(config-fmm)# cache timeout inactive 5
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router(config-fmm)# sampler-map SAMP
RP/0/RP0/CPU0:router(config-fmm)# random 1 out-of 1000
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router(config-fmm)# interface GigabitEthernet0/1/0/0
RP/0/RP0/CPU0:router(config-fmm)# ipv4 address 1.1.1.1 255.255.255.0
RP/0/RP0/CPU0:router(config-fmm)# flow ipv6 monitor M1 sampler SAMP ingres
```

This example shows how to configure the 12-13 flow record map name for the record ipv4 option:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config-fem)# flow monitor-map M-IPv4
RP/0/RP0/CPU0:router(config-fmm)# record ipv4 12-13
RP/0/RP0/CPU0:router(config-fmm)# exporter EXP-ipfix
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router(config-fmm)# flow monitor-map M-IPv6
RP/0/RP0/CPU0:router(config-fmm)# record ipv6 12-13
RP/0/RP0/CPU0:router(config-fmm)# exporter EXP-ipfix
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router(config-fmm)# sampler-map SAMP
RP/0/RP0/CPU0:router(config-fmm)# random 1 out-of 1000
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router(config-fmm)# interface GigabitEthernet0/1/0/0
RP/0/RP0/CPU0:router(config-fmm)# description CE-PE Interface
RP/0/RP0/CPU0:router(config-fmm)# ipv4 address<>
RP/0/RP0/CPU0:router(config-fmm)# ipv6 address<>
RP/0/RP0/CPU0:router(config-fmm)# flow ipv4 monitor M-IPv4 sampler SAMP ingres
RP/0/RP0/CPU0:router(config-fmm)# flow ipv6 monitor M-IPv6 sampler SAMP ingress
RP/0/RP0/CPU0:router(config-fmm)# !
RP/0/RP0/CPU0:router
```

# record ipv6

To configure the flow record map name for IPv6, use the **record ipv6** command in flow monitor map configuration mode. To remove the configured name from a flow record, use the **no** form of this command.

```
record ipv6 { [peer-as] | [srv6][l2-l3] }
```

Syntax Description	peer-as	Records peer AS.
	srv6	Records SRv6 based NetFlow data.
	l2-l3	Records L2 and L3 specific NetFlow data.

**Command Default** The default is that originating AS numbers are recorded.

**Command Modes** Flow monitor map configuration

Command History	Release	Modification
	Release 6.0	This command was introduced.
	Release 7.8.1	This command was modified and a new optional keyword, <code>srv6</code> is introduced for the <code>record ipv6</code> option.
	Release 7.10.1	This command was modified and a new optional keyword, <code>l2-l3</code> is introduced for the <code>record ipv6</code> option.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

## Examples

This example shows how to configure the flow record map name for IPv6:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# record ipv6
```

This example shows how to configure the peer-as to collect and export the IPv6 peer AS numbers:

```
RP/0/RP0/CPU0:router#configure
RP/0/RP0/CPU0:router(config)#flow monitor-map IPv6-peer
RP/0/RP0/CPU0:router(config-fmm)#record ipv6 peer-as
```

This example shows how to configure the `srv6` flow record map name for the `record ipv6` option:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router (config-fem) # flow monitor-map MON-MAP-v6
RP/0/RP0/CPU0:router (config-fmm) # record ipv6 srv6
RP/0/RP0/CPU0:router (config-fmm) # exporter EXP
RP/0/RP0/CPU0:router (config-fmm) # cache timeout inactive 5
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router (config-fmm) # sampler-map SAMP
RP/0/RP0/CPU0:router (config-fmm) # random 1 out-of 1000
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router (config-fmm) # interface GigabitEthernet0/1/0/0
RP/0/RP0/CPU0:router (config-fmm) # ipv4 address 1.1.1.1 255.255.255.0
RP/0/RP0/CPU0:router (config-fmm) # flow ipv6 monitor M1 sampler SAMP ingres
```

This example shows how to configure the `l2-13` flow record map name for the `record ipv6` option:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router (config-fem) # flow monitor-map M-IPv4
RP/0/RP0/CPU0:router (config-fmm) # record ipv4 l2-13
RP/0/RP0/CPU0:router (config-fmm) # exporter EXP-ipfix
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router (config-fmm) # flow monitor-map M-IPv6
RP/0/RP0/CPU0:router (config-fmm) # record ipv6 l2-13
RP/0/RP0/CPU0:router (config-fmm) # exporter EXP-ipfix
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router (config-fmm) # sampler-map SAMP
RP/0/RP0/CPU0:router (config-fmm) # random 1 out-of 1000
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router (config-fmm) # interface GigabitEthernet0/1/0/0
RP/0/RP0/CPU0:router (config-fmm) # description CE-PE Interface
RP/0/RP0/CPU0:router (config-fmm) # ipv4 address<>
RP/0/RP0/CPU0:router (config-fmm) # ipv6 address<>
RP/0/RP0/CPU0:router (config-fmm) # flow ipv4 monitor M-IPv4 sampler SAMP ingres
RP/0/RP0/CPU0:router (config-fmm) # flow ipv6 monitor M-IPv6 sampler SAMP ingress
RP/0/RP0/CPU0:router (config-fmm) # !
RP/0/RP0/CPU0:router
```

# record mpls

To configure the flow record map name for MPLS, use the **record mpls** command in flow monitor map configuration mode. To remove the configured name from a flow record, use the **no** form of this command.

**record mpls** [**ipv4-fields**] [**ipv6-fields**] [**ipv4-ipv6-fields**] [**labels** *number*]

Syntax Description	
<b>ipv4-fields</b>	(Optional) Collects IPv4 fields in the MPLS-aware Netflow when the payload of the MPLS packet has IPv4 fields. It also collects MPLS traffic with no IPv4 payload, but the IPv4 fields are set to zero.
<b>ipv6-fields</b>	(Optional) Collects IPv6 fields in the MPLS-aware Netflow when the payload of the MPLS packet has IPv6 fields. It also collects MPLS traffic with no IPv6 payload, but the IPv6 fields are set to zero.
<b>ipv4-ipv6-fields</b>	(Optional) Collects IPv4 and IPv6 fields in the MPLS-aware Netflow when the payload of the MPLS packet has either IPv4 fields or IPv6 fields. It also collects MPLS traffic with no IPv4 or IPv6 payload, but those fields are set to zero.
<b>labels</b> <i>number</i>	(Optional) Changes the number of labels stored in the NetFlow cache. The <i>number</i> argument is the number of labels that are used in hashing. The range is from 1 to 6.

**Command Default** The default is no IPV4 fields and six labels.

**Command Modes** Flow monitor map configuration

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** In Cisco IOS XR software, you can have only one MPLS flow monitor running on an interface at a time. If you apply an additional MPLS flow monitor to the interface, the new flow monitor overwrites the existing one.

You can configure the MPLS flow monitor to collect IPv4 fields, IPv6 fields, or both types of fields.

Task ID	Task ID	Operations
	netflow	read, write

## Examples

This configuration allows you to collect only MPLS fields. No payload information is collected.

```
RP/0/RP0/CPU0:router(config)# flow monitor-map MPLS-fmm
RP/0/RP0/CPU0:router(config-fmm)# record mpls labels 3
RP/0/RP0/CPU0:router(config-fmm)# cache permanent
RP/0/RP0/CPU0:router(config)# exit
```

```
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow mpls monitor MPLS-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with IPv4 fields. It also collects MPLS traffic with no IPv4 payload, but the IPv4 fields are set to zero.

```
RP/0/RP0/CPU0:router(config)# flow monitor-map MPLS-IPv4-fmm
RP/0/RP0/CPU0:router(config-fmm)# record mpls IPv4-fields labels 3
RP/0/RP0/CPU0:router(config-fmm)# cache permanent
RP/0/RP0/CPU0:router(config-fmm)# exit
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv4-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with IPv6 fields. It also collects MPLS traffic with no IPv6 payload, but the IPv6 fields are set to zero.

```
RP/0/RP0/CPU0:router(config)# flow monitor-map MPLS-IPv6-fmm
RP/0/RP0/CPU0:router(config-fmm)# record mpls IPv6-fields labels 3
RP/0/RP0/CPU0:router(config-fmm)# cache permanent
RP/0/RP0/CPU0:router(config-fmm)# exit
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv6-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with both IPv6 and IPv4 fields. It also collects MPLS traffic with no IPv4 or IPv6 payload, but those fields are set to zero.

```
RP/0/RP0/CPU0:router(config)# flow monitor-map MPLS-IPv4-IPv6-fmm
RP/0/RP0/CPU0:router(config-fmm)# record mpls IPv4-IPv6-fields labels 3
RP/0/RP0/CPU0:router(config-fmm)# cache permanent
RP/0/RP0/CPU0:router(config-fmm)# exit
RP/0/RP0/CPU0:router(config)# interface HundredGigE 0/0/0/0
RP/0/RP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv4-IPv6-fmm sampler fsm ingress
```

This example shows how to configure three labels for hashing:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow monitor-map map1
RP/0/RP0/CPU0:router(config-fmm)# record mpls labels 3
```

# record datalinksection

To record the information element that carries  $n$  octets from the data link frame (IPFIX 315), use the **record datalinksection** command in flow monitor map configuration mode. To disable recording, use the **no** form of this command.

## record datalinksection

**Syntax Description** This command has no keywords or arguments.

**Command Default** None

**Command Modes** Flow monitor map configuration

Command History	Release	Modification
	Release 6.3.2	This command was introduced.
	Release 7.0.1	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

Task ID	Task ID	Operations
	netflow	read, write

## Examples

This configuration allows you to collect IPFIX 315 element information:

```
RP/0/RP0/CPU0:router(config)# flow monitor-map ipfix-mon
RP/0/RP0/CPU0:router(config-fmm)# record datalinkframesection
RP/0/RP0/CPU0:router(config-fmm)# cache immediate
RP/0/RP0/CPU0:router(config)# exit
RP/0/RP0/CPU0:router(config)# interface Gigabit Ethernet 0/0/0/1
RP/0/RP0/CPU0:router(config-if)# flow datalinkframesection monitor ipfix-mon sampler ipfix-sm
ingress
```

# sampler-map

To enter sampler map configuration submode for a specific monitor map, use the **sampler-map** command in XR Config mode. To remove a configured sampler map, use the **no** form of this command.

**sampler-map** *map\_name*

<b>Syntax Description</b>	<i>map_name</i> Name of the sampler map you want to configure. The sampler map name can be a maximum 32 characters.
---------------------------	---

<b>Command Default</b>	None
------------------------	------

<b>Command Modes</b>	XR Config mode
----------------------	----------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

**Usage Guidelines** When you issue the **sampler-map** *map\_name* command in XR Config mode, the CLI prompt changes to “config-sm,” indicating that you have entered the sampler map configuration submode. In this sample output, the question mark ( ? ) online help function displays all the commands available under sampler map configuration submode:

```
RP/0/RP0/CPU0:router(config)# sampler-map test
RP/0/RP0/CPU0:router(config-sm)# ?

clear      Clear the uncommitted configuration
commit     Commit the configuration changes to running
describe   Describe a command without taking real actions
do         Run an exec command
exit       Exit from this submode
no         Negate a command or set its defaults
pwd        Commands used to reach current submode
random     Use random mode for sampling packets
root       Exit to the XR Config mode
show       Show contents of configuration
```

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

## Examples

This example shows how to use the **sampler-map** command to enter sampler map configuration submode for the monitor map called “map1:”

```
RP/0/RP0/CPU0:router# configure
```

```
RP/0/RP0/CPU0:router(config)# sampler-map map1  
RP/0/RP0/CPU0:router(config-sm)#
```

# show flow exporter

To display flow exporter data, enter the **show flow exporter** command in XR EXEC mode.

**show flow exporter** [*exporter\_name*] **location** *node-id*

Syntax Description	
<i>exporter_name</i>	Identifies the flow exporter whose data you want to display.
<b>location</b> <i>node-id</i>	Location where the cache resides. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.
<b>Note</b>	Enter the <b>show platform</b> command to see the location of all nodes installed in the router.

Command Default	None
-----------------	------

Command Modes	XR EXEC mode
---------------	--------------

Command History	Release	Modification
	Release 6.0	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
------------------	--

Task ID	Task ID	Operations
	netflow	read

## Examples

This example shows how to display flow exporter map data:

```
RP/0/RP0/CPU0:router# show flow exporter fem1 location 0/0/CPU0

Flow Exporter: NFC
Used by flow monitors: fmm4

Status: Normal
Transport    UDP
Destination 12.24.39.0      (50001)
Source      12.25.54.3      (5956)
Flows exported:                                0 (0 bytes)
Flows dropped:                                 0 (0 bytes)

Templates exported:                             1 (88 bytes)
Templates dropped:                              0 (0 bytes)

Option data exported:                           0 (0 bytes)
Option data dropped:                            0 (0 bytes)

Option templates exported:                      2 (56 bytes)
```

```

Option templates dropped:                0 (0 bytes)

Packets exported:                        3 (144 bytes)
Packets dropped:                         0 (0 bytes)

Total export over last interval of:
  1 hour:                                0 pkts
                                           0 bytes
                                           0 flows
  1 minute:                              3 pkts
                                           144 bytes
                                           0 flows
  1 second:                              0 pkts
                                           0 bytes
                                           0 flows

```

**Table 2: show flow exporter Field Descriptions**

Field	Description
Id	Identifies the flow exporter map.
Used by flow monitors	Name of the flow monitors associated with the specified flow exporter map.
Status	Status of the exporter. <ul style="list-style-type: none"> <li>• Normal—Exporter is active and can export packets.</li> <li>• Disabled—Exporter cannot send out packets because the collector is unreachable or the configuration is incomplete.</li> </ul>
Destination	Export destination address the current flow exporter map.
Flows exported	Flows exported, in bytes.
Flows dropped	Flows dropped, in bytes.
Templates exported	Templates exported, in bytes.
Templates dropped	Templates dropped, in bytes.
Option data exported	Option data exported, in bytes.
Option data dropped	Option data dropped, in bytes.
Option templates exported	Option templates exported, in bytes.
Option templates dropped	Option templates dropped, in bytes.
Packets exported:	Packets exported, in bytes.
Packets dropped	Packets dropped, in bytes.
Average export rate over interval of last:	Average export rate, in bytes/pkts. Information is displayed for intervals of the last hour, minute, and second.

# show flow exporter-map

To display flow exporter map information for a specific node, enter the **show flow exporter-map** command in XR EXEC mode.

```
show flow exporter-map [name]
```

<b>Syntax Description</b>	<i>name</i> Name of the exporter map whose information you want to display.						
<b>Command Default</b>	None						
<b>Command Modes</b>	XR EXEC mode						
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> <tr> <td>Release 7.10.1</td> <td>The show command output was updated to display <b>router-id</b> information.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.	Release 7.10.1	The show command output was updated to display <b>router-id</b> information.
Release	Modification						
Release 6.0	This command was introduced.						
Release 7.10.1	The show command output was updated to display <b>router-id</b> information.						
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.						
<b>Task ID</b>	<table border="1"> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read		
Task ID	Operations						
netflow	read						

## Examples

This example shows how to display flow exporter map information:

```
RP/0/RP0/CPU0:router# show flow exporter-map map1
```

```
Flow Exporter Map : map1
-----
Id                : 2
DestinationIpAddr : 10.1.1.1
SourceIfName      : Loopback0
SourceIpAddr      : 10.1.1.1
DSCP              : 10
TransportProtocol : UDP
TransportDestPort : 1024
```

```
Export Version: 9
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout   : 600 seconds
  Interface-Table Export Timeout : 1800 seconds
  Sampler-Table Export Timeout : 0 seconds
```

This example shows how to display flow exporter map with **router-id** information:

```

Router# show flow exporter-map E
Fri Mar 24 13:28:13.617 IST

Flow Exporter Map    : E
-----
Id                   : 6
Packet-Length       : 1468
DestinationIpAddr   :
VRFName             :
SourceIfName        :
SourceIpAddr        : Unsupported family type (0)
DSCP                 : 0
TransportProtocol   :
TransportDestPort   :
TransportSourcePortSelectionMethod :
Do Not Fragment     : Not Enabled
Router-Id           : 209.165.201.1

Export Version: 9
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout : 1800 seconds
  Interface-Table Export Timeout : 0 seconds
  Sampler-Table Export Timeout : 0 seconds
  VRF-Table Export Timeout : 0 seconds

```

This table describes the significant fields shown in the display.

**Table 3: show flow exporter-map Field Descriptions**

Field	Description
Id	Identifies the flow exporter map.
DestinationIpAddr	Exports destination configuration.
SourceIfName	Source interface for this exporter map. You can specify the source interface with the <b>flow exporter-map</b> command.
SourceIpAddr	IP address of the source interface (SourceIfName).
DSCP	Differentiated services codepoint (DSCP) value for export packets. <b>Note</b> You can specify the DSCP with the <b>flow exporter-map</b> command.
TransportProtocol	Displays the configured transport protocol. <b>Note</b> Cisco IOS XR software supports the UDP transport protocol only. <b>Note</b> You can specify the transport protocol with the <b>flow exporter-map</b> command.
TransportDestPort	Displays the configured destination port for UDP packets.
Router-Id	Displays the configured router-id or agent-id.

Field	Description
Export Version	Displays the configured export format. <b>Note</b> Cisco IOS XR software supports export format version 9 only.
Common Template Timeout	Displays the configured common template timeout.
Options Template Timeout	Displays the configured options template timeout. <b>Note</b> You can specify the options template timeout with the <b>flow exporter-map</b> command.
Data Template Timeout	Displays the configured data template timeout. <b>Note</b> You can specify the data template timeout with the <b>flow exporter-map</b> command.
Interface-Table Export Timeout	Displays the export timeout value for the interface table. <b>Note</b> You can specify the export timeout for the interface table with the <b>flow exporter-map</b> command.
Sampler-Table Export Timeout	Displays the export timeout value for the sampler table. <b>Note</b> You can specify the export timeout for the sampler table with the <b>flow exporter-map</b> command.

# show flow monitor

To display flow monitor cache data in various formats, enter the **show flow monitor** command in XR EXEC mode.

To match on Access Control Lists (ACLs) and one or more fields:

```
show flow monitor monitor-name cache match {ipv4 {acl name | source-address match-options | destination-address match-options | protocol match-options | tos match-options} | ipv6 {acl name | source-address match-options | destination-address match-options | protocol match-options | tc match-options} | layer4 {source-port-overloaded match-options | destination-port-overloaded match-options | tcp-flags match-flags-options} | bgp {source-as match-options | destination-as match-options} | interface {ingress match-if-options} | timestamp {first match-options | last match-options} | counters {byte match-options | packets match-options} | misc {forwarding-status match-options | direction match-dir-options}}
```

To sort flow record information according to a particular field:

```
show flow monitor monitor-name cache sort {ipv4 {source-address | destination-address | tos | protocol} | ipv6 {source-address | destination-address | tc | protocol} | mpls {label-2 | label-3 | label-4 | label-5 | label-6 | label-type | prefix | top-label} | layer4 {source-port-overloaded | destination-port-overloaded} | bgp {source-as | destination-as} | timestamp {first | last} | counters {bytes | packets} | misc {forwarding-status | direction} {top | bottom} [entries]
```

To include or exclude one or more fields in the **show flow monitor** command output:

```
show flow monitor monitor-name cache {include | exclude} {ipv4 {source-address | destination-address | tos | protocol} | ipv6 {source-address | destination-address | tc | flow-label | option-headers | protocol} | mpls {label-2 | label-3 | label-4 | label-5 | label-6 | top-label} | layer4 {source-port-overloaded | destination-port-overloaded} | bgp {source-as | destination-as} | timestamp {first | last} | counters {bytes | packets} | misc {forwarding-status match-options | direction match-dir-options}}
```

To display summarized flow record statistics:

```
show flow monitor monitor-name cache summary location node-id
```

To display only key field, packet, and byte information for the flow records:

```
show flow monitor monitor-name cache brief location node-id
```

To display flow record information for a particular node only:

```
show flow monitor monitor-name cache location node-id
```

---

## Syntax Description

If you specified the **show flow monitor monitor-name cache match** command to match on ACL and one or more fields:

---

## Syntax Description

*map\_name* Name of the sampler map you want to configure. The sampler map name can be a maximum 32 characters.

---

This table describes the significant fields shown in the display.

**Table 4: show flow monitor Field Descriptions**

Field	Description
Cache summary for Flow Monitor fmm2	Displays general cache information for the specified flow monitor. The following information is displayed <ul style="list-style-type: none"> <li>• Cache size for the specified flow monitor map</li> <li>• Current number of entries in the cache</li> <li>• High watermark for this cache</li> <li>• Number of flows added to the cache</li> <li>• Number of flows not added to the cache</li> </ul>
Ager Polls	Displays the following ager statistics: <ul style="list-style-type: none"> <li>• Active timeout</li> <li>• Inactive timeout</li> <li>• TCP FIN flag</li> <li>• Watermark aged</li> <li>• Emergency aged</li> <li>• Counter wrap aged</li> <li>• Total</li> </ul>
Periodic export	<ul style="list-style-type: none"> <li>• Counter wrap</li> <li>• TCP FIN flag</li> </ul>
Cache summary for Flow Monitor fmm2	Displays general cache information for the specified flow monitor. The following information is displayed <ul style="list-style-type: none"> <li>• Cache size for the specified flow monitor map</li> <li>• Current number of entries in the cache</li> <li>• High watermark for this cache</li> <li>• Number of flows added to the cache</li> <li>• Number of flows not added to the cache</li> </ul>

**Command Default** None

**Command Modes** XR EXEC mode

Command History	Release	Modification
	Release 6.0	This command was introduced.
	Release 24.1.1	This command was modified to include additional BGP information elements.

**Usage Guidelines** To collect source and destination AS information, you must enable BGP on the relevant BGP AFI/SAFI. Unless this is done, all AS numbers in the flow records are displayed as 0.

Keep these information in mind when using the **show flow monitor** command:

- The **show flow monitor** command can include combinations of these options:
  - **format**
  - **match**
  - **include**
  - **exclude**
  - **sort**
  - **summary**
  - **location**
- We do not recommend including the **summary** option with the **sort** and **format** options.
- The mutually exclusive options are **summary**, **brief**, **include**, and **exclude**.
- To see a list of fields that can be included after a keyword, enter the **?** command, as shown in this example:

```
RP/0/RP0/CPU0:router# show flow monitor map1 cache summary ?

brief      Show just the key fields
exclude    Exclude field
format     Display format
include    Include field
location   Specify a location
match      Match criteria
sort       Sorting criteria
```

Task ID	Task ID	Operations
	netflow	read

## Examples

This example shows how to display flow monitor data for a specific monitor map cache in the location 0/0/CPU0 :

This example shows how to display flow monitor data for a specific monitor map cache in the location 0/0/CPU0 :

```
Router#show flow monitor mpls-1 cache summary location 0/0/CPU0
```

```
===== Record number: 1 =====
LabelType       : Unknown
Prefix/Length   : 20.1.1.0/24
Label1-EXP-S    : 16001-0-1
Label2-EXP-S    : -
Label3-EXP-S    : -
Label4-EXP-S    : -
Label5-EXP-S    : -
Label6-EXP-S    : -
InputInterface  : FH0/0/0/1
OutputInterface : FH0/0/0/0
ForwardStatus   : Fwd
```

## show flow monitor

```

FirstSwitched      : 00 08:28:52:189
LastSwitched       : 00 08:28:57:649
ByteCount          : 2352
PacketCount        : 56
Dir                 : Ing
SamplerID          : 1
IPv4SrcAddr        : 30.1.1.1
IPv4DstAddr        : 20.1.1.1
IPv4TOS            : 0
IPv4Prot           : udp
L4SrcPort          : 2025
L4DestPort         : 2500
L4TCPFlags         : 0
IPv4SrcPrfxLen    : 24
IPv4DstPrfxLen    : 24
BGPNextHopV4      : 192.168.10.10
BGPNextHopV6      : ::
BGPSrcOrigAS      : 2000
BGPDstOrigAS      : 1000
IPv4NextHop        : 192.168.10.10
IPv6NextHop        : ::
MinimumTTL         : 90
MaximumTTL         : 110
InputVRFID         : default
OutputVRFID        : default

```

===== Record number: 1 =====

```

LabelType          : Unknown
Prefix/Length      : ::/0
Label1-EXP-S       : 16001-0-1
Label2-EXP-S       : -
Label3-EXP-S       : -
Label4-EXP-S       : -
Label5-EXP-S       : -
Label6-EXP-S       : -
InputInterface     : FH0/0/0/1
OutputInterface    : FH0/0/0/0
ForwardStatus      : Fwd
FirstSwitched      : 00 08:27:38:692
LastSwitched       : 00 08:27:47:572
ByteCount          : 5580
PacketCount        : 90
Dir                 : Ing
SamplerID          : 1
IPv6SrcAddr        : 50::1
IPv6DstAddr        : 40::1
IPv6TC             : 0
IPv6FlowLabel      : 0
IPv6OptHdrs        : 0x0
IPv6Prot           : udp
L4SrcPort          : 2025
L4DestPort         : 2500
L4TCPFlags         : 0
IPv6SrcPrfxLen    : 64
IPv6DstPrfxLen    : 64
BGPNextHopV4      : 0.0.0.0
BGPNextHopV6      : ::ffff:192.168.10.10
BGPSrcOrigAS      : 2000
BGPDstOrigAS      : 1000
IPv4NextHop        : 192.168.10.10
IPv6NextHop        : ::
MinimumTTL         : 195
MaximumTTL         : 205

```

```
InputVRFID      : default
OutputVRFID     : default
```

# show flow monitor-map

To display flow monitor map data, enter the **show flow monitor-map** command in XR EXEC mode.

**show flow monitor-map** *map-name* **Optional:** [srv6]

<b>Syntax Description</b>	<i>map-name</i> Name of the monitor map whose data you want to display.						
<b>Command Default</b>	None						
<b>Command Modes</b>	XR EXEC mode						
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> <tr> <td>Release 7.8.1</td> <td>The show flow monitor-map command output was modified to display the monitor-map data for ipv6 srv6 subtypes.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.	Release 7.8.1	The show flow monitor-map command output was modified to display the monitor-map data for ipv6 srv6 subtypes.
Release	Modification						
Release 6.0	This command was introduced.						
Release 7.8.1	The show flow monitor-map command output was modified to display the monitor-map data for ipv6 srv6 subtypes.						
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.						
<b>Task ID</b>	<table border="1"> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read		
Task ID	Operations						
netflow	read						

## Examples

This example shows how to display monitor-map data for a specific flow:

```
RP/0/RP0/CPU0:router# show flow monitor-map map1
```

```
Flow Monitor Map : map1
-----
Id:                1
RecordMapName:    ipv4
ExportMapName:    NFC
CacheAgingMode:   Permanent
CacheMaxEntries:  10000
CacheActiveTout:  N/A
CacheInactiveTout: N/A
CacheUpdateTout:  60 seconds
```

This example shows how to display SRv6 monitor-map data for a specific flow:

```
RP/0/RP0/CPU0:router# show flow monitor-map MON-MAP-1
```

```
Flow Monitor Map : MON
-----
Id:                1
RecordMapName:    srv6
ExportMapName:    EXP
```

```

CacheAgingMode:    Normal
CacheMaxEntries:   65535
CacheActiveTout:   101 seconds
CacheInactiveTout: 15 seconds
CacheUpdateTout:   N/A
CacheRateLimit:    2000
HwCacheExists:     False
HwCacheInactTout: 50

```

This table describes the significant fields shown in the display.

**Table 5: show flow monitor-map Field Descriptions**

Field	Description
Flow Monitor Map	Name of the flow monitor map whose information is display in the <b>show flow monitor-map</b> command output.
Id	Number that identifies the flow monitor map.
RecordMapName	Name of the flow record map that is associated with this monitor map. The RecordMapName indicates the type of packets NetFlow captures as they leave the router.
ExportMapName	Name of the export map that is associated with this monitor map.
CacheAgingMode	<p>Current aging mode configured on this cache. “Permanent” indicates that the removal of entries from the monitor map flow cache is disabled.</p> <p><b>Note</b> To configure the number of entries allowed in the monitor map flow cache, enter the <b>cache entries</b> command in flow monitor map configuration mode. To disable the removal of entries from the monitor map flow cache, enter the <b>cache permanent</b> command in flow monitor map configuration mode.</p>
CacheMaxEntries	<p>Number of flow entries currently allowed in the flow cache before the oldest entry is removed.</p> <p><b>Note</b> To modify the number of entries in the monitor map flow cache, enter the <b>cache entries</b> command in flow monitor map configuration mode</p>
CacheActiveTout	<p>Active flow timeout configured for this cache, in seconds.</p> <p><b>Note</b> To modify the configured active flow timeout, use the <b>cache timeout</b> command in flow monitor map configuration mode.</p>
CacheInactiveTout	<p>Inactive flow timeout configured for this cache, in seconds.</p> <p><b>Note</b> To modify the configured inactive flow timeout, use the <b>cache timeout</b> command in flow monitor map configuration mode.</p>
CacheUpdateTout	<p>Update timeout configured for this cache, in seconds.</p> <p><b>Note</b> To modify the configured update timeout, use the <b>cache timeout</b> command in flow monitor map configuration mode.</p>

This example shows how to display monitor-map data for a specific IPv6 flow:

```
RP/0/RP0/CPU0:router# show flow monitor-map map2
```

```
Tue Jan 22 00:15:53.424 PST  
Flow Monitor Map : map2
```

```
-----  
Id: 1  
RecordMapName: ipv6  
CacheAgingMode: Normal  
CacheMaxEntries: 65535  
CacheActiveTout: 1800 seconds  
CacheInactiveTout: 15 seconds  
CacheUpdateTout: N/A
```

# show flow platform producer statistics location

To display statistics collected by the NetFlow producer, use the **show flow platform producer statistics location** command in XR EXEC mode.

**show flow platform producer statistics location** *node-id*

<b>Syntax Description</b>	<p><i>node-id</i> Location of the node whose NetFlow producer statistics you want to display. The <i>node-id</i> is expressed in the <i>rack/slot/module</i> notation.</p> <p><b>Note</b> Enter the <b>show platform</b> command to see the location of all nodes installed in the router.</p>				
<b>Command Default</b>	None				
<b>Command Modes</b>	XR EXEC mode				
<b>Command History</b>	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0	This command was introduced.
Release	Modification				
Release 6.0	This command was introduced.				
<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.				
<b>Task ID</b>	<table border="1"> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read
Task ID	Operations				
netflow	read				

## Examples

This example shows how to display statistics collected by the NetFlow producer for the CPU card in slot 0:

```
RP/0/RP0/CPU0:router# show flow platform producer statistics location 0/0/CPU0

Netflow Platform Producer Counters:
IPv4 Ingress Packets:           0
IPv4 Egress Packets:           0
IPv6 Ingress Packets:          0
IPv6 Egress Packets:           0
MPLS Ingress Packets:          0
MPLS Egress Packets:           0
Drops (no space):              0
Drops (other):                 0
Unknown Ingress Packets:       0
Unknown Egress Packets:       0
Worker waiting:                 0
```

This table describes the significant fields shown in the display.

**Table 6: show flow platform producer statistics Field Descriptions**

Field	Description
IPv4 Ingress Packets	Number of IPV4 packets that were received from the remote end.
IPv4 Egress Packets	Number of transmitted IPV4 packets.
MPLS Ingress Packets	Number of MPLS packets that were received from the remote end.
MPLS Egress Packets	Number of transmitted MPLS packets.
Drops (no space)	Number of packets that the producer could not enqueue to the NetFlow server because the server input ring was full.
Drops (other)	Number of packets that the producer could not enqueue to the NetFlow server due to errors other than the server input ring being full.
Unknown Ingress Packets	Number of unrecognized packets received from the remote end that were dropped.
Unknown Egress Packets	Number of packets transmitted to the remote end that were dropped because they were not recognized by the remote end.
Worker waiting	Number of times that the producer needed to use the server.  <b>Note</b> This field is strictly informational and does not indicate any error.

# show sampler-map

To display sampler map information, enter the **show sampler-map** command in XR EXEC mode.

```
show sampler-map [sampler-name]
```

<b>Syntax Description</b>	<i>sampler-name</i> Identifies the sampler map whose information you want to display.
---------------------------	---

<b>Command Default</b>	None
------------------------	------

<b>Command Modes</b>	XR EXEC mode
----------------------	--------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.
-------------------------	--

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow read	

## Examples

This example shows how to display sampler map information for a router:

```
RP/0/RP0/CPU0:router# show sampler-map map1
```

```
Sampler Map : map1
```

```
-----
Id:      1
Mode:    Random (1 out of 100 Pkts)
```

This table describes the significant fields shown in the display.

**Table 7: show sampler-map Field Descriptions**

Field	Description
Id	Flow sampler map identifier.
Mode	Sampling interval in units of packet. “Random” mode is any mode that was configured with the <b>flow monitor-map</b> command.
<b>Note</b>	Currently, Cisco IOS XR software supports “Random” mode only.

## source (NetFlow)

To configure a source interface for the current collector, use the **source** command in flow exporter map configuration mode. To remove a configured source interface, use the **no** form of this command.

**source** *type interface-path-id*

<b>Syntax Description</b>	<i>type</i>	Interface type. For more information, use the question mark ( ? ) online help function.
	<i>interface-path-id</i>	Physical interface or virtual interface.
	<b>Note</b>	Use the <b>show interfaces</b> command to see a list of all interfaces currently configured on the router.
		For more information about the syntax for the router, use the question mark ( ? ) online help function.

**Command Default** None

**Command Modes** Flow exporter map configuration

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

**Usage Guidelines** For the *interface-path-id* argument, use the following guidelines:

- If specifying T1/E1/DS0 physical interfaces, the naming notation is *rack/slot/module/port/t1-num:channel-group-number*. If specifying other physical interface types, the naming notation is *rack/slot/module/port*. The slash between values is required as part of the notation. An explanation of each component of the naming notation is as follows:
  - *rack*: Chassis number of the rack.
  - *slot*: Physical slot number of the modular services card or line card.
  - *module*: Module number. A physical layer interface module (PLIM) is always 0. Shared port adapters (SPAs) are referenced by their subslot number.
  - *port*: Physical port number of the T3 controller.
  - *t1-num* : T1 or E1 channel number. T1 channels range from 1 to 24; E1 channels range from 1 to 31.
  - *channel-group-number* : Time slot number. T1 time slots range from 1 to 24; E1 time slots range from 1 to 31. The *channel-group-number* is preceded by a colon and not a slash.
  - **source-address** : Source address supports IPv4 or IPv6 address.
- If specifying a virtual interface, the number range varies, depending on interface type.

Task ID	Task ID	Operations
	netflow	read, write

### Examples

This example shows how to configure a physical interface as a source for the current collector:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# source HundredGigE 0/3/0/0
RP/0/RP0/CPU0:router(config-fem)# source-address 192.127.10.1
```

This example shows how to configure a virtual interface as a source for the current collector. In this example, the source is an Ethernet bundle:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# source Bundle-Ether 1
```

## template (NetFlow)

To configure the export timeout value for the data and options templates, enter the **template** command in flow exporter map version configuration mode. To remove a configured template export timeout value, use the **no** form of this command.

**template** [{**data** | **options**}] **timeout** *seconds*

Syntax Description	Parameter	Description
	<b>data</b>	(Optional) Specifies the data template.
	<b>options</b>	(Optional) Specifies the options template.
	<b>timeout</b> <i>seconds</i>	Configures the timeout value for the specified template, or for both the data and options templates. Replace <i>seconds</i> with the export timeout value. Range is from 1 through 604800 seconds.

**Command Default** Default timeout value for data and options template is 1800 seconds.

**Command Modes** Flow exporter map version configuration

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

### Examples

This example shows how to configure the export timeout value for the data template to be 300 seconds:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map fem1
RP/0/RP0/CPU0:router(config-fem)# version v9
RP/0/RP0/CPU0:router(config-fem-ver)# template data timeout 300
```

# transport udp

To configure the destination port for User Datagram Protocol (UDP) packets, enter the **transport udp** command in flow exporter map configuration mode. To remove a configured destination port, use the **no** form of this command.

**transport udp** *port\_value*

<b>Syntax Description</b>	<i>port_value</i> Destination port for UDP packets. Replace <i>port</i> with the destination port value. Range is from 1024 through 65535.
---------------------------	--

<b>Command Default</b>	None
------------------------	------

<b>Command Modes</b>	Flow exporter map configuration
----------------------	---------------------------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 6.0	This command was introduced.

<b>Usage Guidelines</b>	No specific guidelines impact the use of this command.
-------------------------	--

<b>Task ID</b>	<b>Task ID</b>	<b>Operations</b>
	netflow	read, write

**Examples** This example shows how to configure the destination port for UDP packets:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# transport udp 1030
```

## version v9

To enter flow exporter map version configuration submode so that you can configure export version parameters, enter the **version v9** command in flow exporter map configuration mode. To remove the current export version configuration and return to the default configuration, use the **no** form of this command.

### version v9

**Syntax Description** This command has no keywords or arguments.

**Command Default** None

**Command Modes** Flow exporter map configuration

Command History	Release	Modification
	Release 6.0	This command was introduced.

**Usage Guidelines** When you issue the **version v9** command, the CLI prompt changes to “config-fem-ver,” indicating that you have entered flow exporter map version configuration submode. In this sample output, the question mark ( ? ) online help function displays all the commands available under flow exporter map version configuration submode:

```
RP/0/RP0/CPU0:router(config-fem)# version v9
RP/0/RP0/CPU0:router(config-fem-ver)#?

  clear      Clear the uncommitted configuration
  commit     Commit the configuration changes to running
  describe   Describe a command without taking real actions
  do         Run an exec command
  exit       Exit from this submode
  no         Negate a command or set its defaults
  options    Specify export of options template
  pwd        Commands used to reach current submode
  root       Exit to the XR Config mode
  show       Show contents of configuration
  template   Specify template export parameters
```

Task ID	Task ID	Operations
	netflow	read, write

### Examples

This example shows how to enter flow exporter map version configuration submode:

```
RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# version v9
RP/0/RP0/CPU0:router(config-fem-ver)#
```

## version ipfix

To configure Internet Protocol Flow Information Export (IPFIX) as an export version and configure export version parameters, enter the **version ipfix** command in flow exporter map configuration mode. To remove the current export version configuration and return to the default configuration, use the **no** form of this command.

**version ipfix** [{**options** {**interface-table** | **sampler-table** | **vrf-table**} **timeout** *timeout-value* | **template** {**data** | **options**} **timeout** *timeout-value*}]

Syntax Description	options	(Optional) Specifies export of options template. Options template provide extra information about the flow records. The options template include these options:
		<ul style="list-style-type: none"> <li>• interface-table</li> <li>• sampler-table</li> <li>• vrf-table</li> </ul>
		For each options template specify timeout value (in seconds) during which the exporter has to retransmit each active options template.
	template	(Optional) Specifies template export parameters such as data template and options template timeout configurations.
	timeout	Specifies custom timeout value (in seconds) during which the exporter has to retransmit each active template. The range of <i>timeout-value</i> is 1 to 604800 seconds.
	<i>timeout-value</i>	

**Command Default** None

**Command Modes** Flow exporter map configuration

Command History	Release	Modification
	Release 6.2.2	This command was introduced.
	Release 6.3.1	This command was introduced.

**Usage Guidelines** When you issue the **version ipfix** command, the CLI prompt changes to “config-fem-ver,” indicating that you have entered flow exporter map version configuration submenu. In this sample output, the question mark ( ? ) online help function displays all the commands available under flow exporter map version configuration submenu:

```
RP/0/RP0/CPU0:router(config-fem)# version ipfix
RP/0/RP0/CPU0:router(config-fem-ver)#?

clear      Clear the uncommitted configuration
commit     Commit the configuration changes to running
describe   Describe a command without taking real actions
do         Run an exec command
```

```

exit      Exit from this submode
no        Negate a command or set its defaults
options   Specify export of options template
pwd       Commands used to reach current submode
root      Exit to the mode
show      Show contents of configuration
template  Specify template export parameters

```

---

**Task ID**


---

Task ID	Operations
---------	------------

---

netflow	read, write
---------	----------------

---



---


**Examples**

This example shows how to configure IPFIX as an exporter in a flow exporter map configuration submode:

```

RP/0/RP0/CPU0:router# configure
RP/0/RP0/CPU0:router(config)# flow exporter-map map1
RP/0/RP0/CPU0:router(config-fem)# version ipfix
RP/0/RP0/CPU0:router(config-fem-ver)#

```



## sFlow Commands

---

This module provides command line interface (CLI) commands for configuring sFlow on the Cisco 8000 Series Routers.

To use commands of this module, you must be in a user group associated with a task group that includes appropriate task IDs. If the user group assignment is preventing you from using any command, contact your AAA administrator for assistance.

- [hw-module profile netflow sflow-enable](#) , on page 58
- [record sflow](#), on page 59
- [sflow options](#) , on page 60
- [version sflow v5](#), on page 62
- [router-id](#), on page 63

# hw-module profile netflow sflow-enable

To enable sFlow on a specified node location, use the **hw-module profile netflow sflow enable** command in the configuration mode.

**hw-module profile netflow sflow enable location *node-id***

<b>Syntax Description</b>	<i>node-id</i> The node-id argument is entered in the rack/slot/module notation.
---------------------------	--

<b>Command Default</b>	sFlow is disabled
------------------------	-------------------

<b>Command Modes</b>	Configuration
----------------------	---------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 7.2.12	This command was introduced.

<b>Usage Guidelines</b>	The Netflow, IPFIX315 and sFlow features are mutually exclusive. Therefore, Netflow, IPFIX315 and sFlow should not be configured on the same node. However, some nodes can have Netflow, IPFIX315 and other nodes can have sFlow configurations.
-------------------------	--

You must reload the router for the configurations to take effect.

## Example

This example shows how to enable sFlow on the node location 0/0/CPU0:

```
Router(config)# hw-module profile netflow sflow-enable location 0/0/CPU0
```

## record sflow

To activate an sFlow flow record, use the **record sflow** command in flow monitor map configuration mode. To deactivate the flow record, use the **no** form of this command.

**record sflow**

**Syntax Description** This command has no keywords or arguments.

**Command Default** None

**Command Modes** Flow monitor map configuration

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 7.2.12	This command was introduced.

**Usage Guidelines** No specific guidelines impact the use of this command.

This example shows how to configure an sFlow flow record:

```
Router# configure
Router(config)# flow monitor-map SAMPLE-MON-1
Router(config-fmm)# record sflow
```

## sflow options

To configure sFlow related options, use the **sflow options** command in flow monitor map configuration mode.

### sflow options

[ **extended-gateway** | **extended-router** | **extended-ipv4-tunnel-egress** | **extended-ipv6-tunnel-egress** | **if-counters polling-interval** <time-in-seconds> | **input ifindex physical** | **Output ifindex physical** | **sample-header size** <bytes> ]

Syntax Description	
<b>extended-gateway</b>	(Optional) Enables extended-gateway flow data type. When enabled, the following information is exported to the sFlow agent: <ul style="list-style-type: none"> <li>• Next-hop IP</li> <li>• Autonomous system number of router, source and source peer</li> <li>• Autonomous system path to the destination</li> <li>• Communities</li> </ul>
<b>extended-router</b>	(Optional) Enables extended-router flow data type. When enabled the following information is exported to the sFlow agent: <ul style="list-style-type: none"> <li>• Next-hop IP</li> <li>• Source and destination mask lengths</li> </ul>
<b>if-counters polling-interval</b> <time-in-seconds>	(Optional) Specifies polling interval for polling interface counters. The range is from 15-120 seconds.  When enabled, the sFlow agent collects the interface statistics from interface counters.
<b>input ifindex physical</b>	(Optional) Specifies ifindex-related options. When enabled the input (physical) interface SNMP ifindex on which the packet arrived is exported to the external collector.
<b>output ifindex physical</b>	(Optional) Specifies ifindex-related options. When enabled the output (physical) interface SNMP ifindex on which the packet departed is exported to the external collector.
<b>sample-header size</b> <bytes>	(Optional) Specifies maximum sample-header size to be exported.  The size is expressed in bytes. The default size is 128 bytes. The sampler header size can be up to 200 bytes.
<b>extended-ipv4-tunnel-egress</b>	(Optional) Enables extended-ipv4-tunnel-egress flow data type.
<b>extended-ipv6-tunnel-egress</b>	(Optional) Enables extended-ipv6-tunnel-egress flow data type.
<b>Command Default</b>	None

---

**Command Modes** Flow monitor map configuration

---

Command History	Release	Modification
	Release 7.2.12	This command was introduced.
	Release 7.3.3	Keyword <code>extended-ipv4-tunnel-egress</code> was introduced.
	Release 7.3.3	Keyword <code>extended-ipv6-tunnel-egress</code> was introduced.

---

**Usage Guidelines** No specific guidelines impact the use of this command.

### Example

This example shows how to configure various sFlow options:

```
Router(config)#flow monitor-map slow_mon
Router(config-fmm)#record sflow
Router(config-fmm-sflow)#sflow options
Router(config-fmm-sflow)#input ifindex physical
Router(config-fmm-sflow)#output ifindex physical
Router(config-fmm-sflow)#sample-header size 200
Router(config-fmm-sflow)#if-counters polling-interval 30
Router(config-fmm-sflow)#extended-router
Router(config-fmm-sflow)#extended-gateway
Router(config-fmm-sflow)#extended-ipv4-tunnel-egress
Router(config-fmm-sflow)#extended-ipv6-tunnel-egress
Router(config-fmm-sflow)#commit
!
```

## version sflow v5

To configure version 5 as an export version for sFlow, use the **version sflow v5** command in flow exporter map configuration mode. To remove the current export version configuration and return to the default configuration, use the **no** form of this command.

```
version sflow v5 [{ options {interface-table | sampler-table | vrf-table} timeout
timeout-value | template {data | options } timeout timeout-value }]
```

Syntax Description	options
	(Optional) Specifies export of options template. Options template provides extra information about the flow records. The options template include these options: <ul style="list-style-type: none"> <li>• interface-table</li> <li>• sampler-table</li> <li>• vrf-table</li> </ul> <p>For each options template, specify timeout value (in seconds) during which the exporter has to retransmit each active options template.</p>
	template
	(Optional) Specifies export parameters of the template such as data template and options template timeout configurations.
	timeout
	<i>timeout-value</i> Specifies custom timeout value (in seconds) during which the exporter has to retransmit each active template. The range of <i>timeout-value</i> is 1 to 604800 seconds.

**Command Default** None

**Command Modes** Flow exporter map configuration

Command History	Release	Modification
	Release 7.2.12	This command was introduced.

**Usage Guidelines** When you issue the **version sflow v5** command, the CLI prompt changes to `config-fem-ver`, indicating that you have entered the version submode of the flow exporter map configuration mode.

**Examples** This example shows how to configure sFlow v5 as an exporter in a flow exporter map configuration submode:

```
Router# configure
Router(config)# flow exporter-map SAMPLE-1
Router(config-fem)# version sflow v5
Router(config-fem-ver)#
```

# router-id

To configure the sFlow agent ID with a specific IPv4 or IPv6 address, use the **router-id** command in flow exporter map configuration mode.

```
router-id address { ipv4 | ipv6 }
```

<b>Syntax Description</b>	<b>address</b> <i>ipv4</i>   <i>ipv6</i>	Specifies the router id in IPv4 or IPv6 address format.
<b>Command Default</b>	None	
<b>Command Modes</b>	Flow exporter map configuration	
<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	Release 7.10.1	This command was introduced.

## Examples

This example shows how to configure sFlow agent ID for an IPv4 address in flow exporter map configuration submode:

```
Router#configure
Router(config)#flow exporter-map E
Router(config-fem)#router-id address 209.165.201.1
Router(config-fem)#commit
```

router-id