



Power Down the Node

This chapter explains how to power down a node and stop all node activity on the Cisco ONS 15454 SDH.

NTP-D114 Power Down the Node

Purpose	This procedure stops all node activity.
Tools/Equipment	None
Prerequisite Procedures	None
Required/As Needed	As needed
Onsite/Remote	Onsite
Security Level	For software steps, Provisioning level or higher is required. For hardware steps, any level is allowed.



Warning

Do not reach into a vacant slot or chassis while you install or remove a module or a fan. Exposed circuitry could constitute an energy hazard. Statement 206



Caution

The following procedure is designed to minimize traffic outages when powering down nodes, but traffic will be lost if you delete and recreate circuits that passed through a working node.



Note

Always use the supplied ESD wristband when working with the Cisco ONS 15454 SDH. Plug the wristband into the ESD jack located on the fan-tray assembly or on the lower right outside edge of the shelf assembly. To access the ESD plug on the shelf assembly, open the front door of the Cisco ONS 15454 SDH. The front door is grounded to prevent electrical shock.

-
- Step 1** Identify the node that you want to power down. If no cards are installed, go to Step 13. If cards are installed, log into the node. See the “[DLP-D60 Log into CTC](#)” task on page 17-47 for instructions.
- Step 2** In node (login) view, choose **Go to Network View** from the View menu.

- Step 3** In network view, verify that the node is not connected to a network.
- If the node is part of a working network, log out of the node and complete the “[NTP-D322 Remove an In-Service Node from a Linear ADM](#)” procedure on page 14-17, the “[NTP-D213 Remove an MS-SPRing Node](#)” procedure on page 14-6, or the “[NTP-D106 Remove an SNCP Node](#)” procedure on page 14-11. If the node is part of a dense wavelength division multiplexing (DWDM) network, consult your network administrator. (Linear configurations will be deleted in [Step 5](#).) Continue with the next step.
 - If the node is not connected to a working network and the current configurations are no longer required, continue with the next step.



Note Current configurations will be saved if Steps 4 through 13 are skipped.

- Step 4** In node view, click the **Circuits** tab and verify that no circuits are displayed, then proceed to [Step 5](#). If circuits appear, delete all the circuits that originate or terminate in the node, as follows:

- Click the circuits that need to be deleted and click **Delete**.
- Click **Yes**.

Repeat until no circuits appear.

- Step 5** In node view, click the **Provisioning > Protection** tabs and delete all protection groups:

- Click the protection group that needs to be deleted and click **Delete**.
- Click **Yes**.

Repeat until no protection groups appear.

- Step 6** In node view, click the **Provisioning > Comm Channels** tabs and delete all RS-DCC, MS-DCC, GCC, or OSC terminations:

- Click the regenerator section data communications channel (RS-DCC), multiplex section data communications channel (MS-DCC), generic communications channel (GCC), or optical service channel (OSC) termination that needs to be deleted and click **Delete**.
- Click **Yes**.

Repeat until no RS-DCC, MS-DCC, GCC, or OSC terminations are present.



Note Before deleting the OSC termination, make sure the Ring ID is deleted. Click the **Provisioning > Comm Channels > OSC** tabs. Select the Ring ID and click **Delete**.

- Step 7** For each installed STM-N or DS-N card, make sure all ports are in Locked-enabled,disabled service state:

- In card view, click the **Provisioning > Line** tabs.
- Click under the Status column for each port and choose **Locked,disabled**.

- Step 8** Remove all fiber connections to the cards.

- Step 9** In node view, right-click an installed card and click **Delete**.

- Step 10** Click **Yes**.

- Step 11** After you have deleted the card, open the card ejectors and remove it from the node.

- Step 12** Repeat Steps 7 through 11 for each installed card.



Note You cannot delete a TCC2/TCC2P card in CTC. Physically remove it after all the other cards have been deleted and removed.

- Step 13** Shut off the power from the power supply that feeds the node.
- Step 14** Disconnect the node from its external fuse source.
- Step 15** Store all the cards you removed and update inventory records according to local site practice.
- Stop. You have completed this procedure.**
-

