APPENDIX A

Network Element Defaults

Note The terms "Unidirectional Path Switched Ring" and "UPSR" may appear in Cisco literature. These terms do not refer to using Cisco ONS 15xxx products in a unidirectional path switched ring configuration. Rather, these terms, as well as "Path Protected Mesh Network" and "PPMN," refer generally to Cisco's path protection feature, which may be used in any topological network configuration. Cisco does not recommend using its path protection feature in any particular topological network configuration.

This appendix describes the factory-configured (default) network element (NE) settings for the Cisco ONS 15454, Cisco ONS 15454 M2, and Cisco ONS 15454 M6 platforms. It includes descriptions of card, node, and Cisco Transport Controller (CTC) default settings. To import, export, or edit the settings, see the "Maintain the Node" chapter in the *Cisco ONS 15454 DWDM Procedure Guide*. Cards supported by this platform that are not listed in this appendix are not supported by user-configurable NE defaults settings.

Note Unless otherwise specified, in this appendix "ONS 15454" refers to both ANSI (ONS 15454 SONET) and ETSI (ONS 15454 SDH) shelf assemblies.

A.1 Network Element Defaults Description

The NE defaults are preinstalled on each Cisco ONS 15454 TCC2 and TCC2P, TCC3, TNC and TSC cards. Cisco also ships a file named 15454-defaults.txt (ANSI shelves) or 15454SDH-defaults.txt (ETSI shelves) on the CTC software CD in case you want to import the defaults onto existing TCC2/TCC2P/TCC3/TNC/TSC cards. The NE defaults include card-level, CTC, and node-level defaults.

Note The TCC2/TCC2P/TCC3 cards are supported only on the Cisco ONS 15454 platform. The TNC/TSC cards are supported on the Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Manual card provisioning overrides default settings. Manual changes are those made using the "Provision Transponder and Muxponder Cards" chapter or the "Change DWDM Card Settings" chapter in the *Cisco ONS 15454 DWDM Procedure Guide*. If you use the CTC Defaults editor (on the node view Provisioning > Defaults tabs) or import a new defaults file, any changes to card or port settings that result only affect cards that are installed or preprovisioned after the defaults have changed.

Changes made manually to most node-level default settings override the current settings, whether default or provisioned. If you change node-level default settings, either by using the Defaults editor or by importing a new defaults file, the new defaults reprovision the node immediately for all settings except those relating to protection (1+1 bidirectional switching, 1+1 reversion time, 1+1 revertive, Bidirectional Line Switched Ring [BLSR] or multiplex section-shared protection ring [MS-SPRing] reversion time, BLSR/MS-SPRing ring revertive, BLSR/MS-SPRing span reversion time, BLSR/MS-SPRing span revertive, y cable revertive or reversion time, splitter revertive or reversion time). Settings relating to protection apply to subsequent provisioning.

Note Changing some node-level provisioning through NE defaults can cause CTC disconnection or a reboot of the node in order for the provisioning to take effect. Before you change a default, check in the Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) and be prepared for the occurrence of any side effects listed for that default.

A.2 ANSI Platform Defaults

The following sections give the NE defaults for the ONS 15454 ANSI platform. To see defaults for the ONS 15454 ETSI platform, see the "A.4 ETSI Platform Defaults" section on page A-563.

A.2.1 ANSI Card Defaults

The tables in this section list the default settings for each DWDM, Transponder (TXP), Muxponder (MXP), or Ethernet card. Cisco provides several types of user-configurable defaults for Cisco ONS 15454 DWDM, TXP, MXP, and Ethernet cards. Types of card defaults can be broadly grouped by function, as outlined in the following subsections. For information about individual card settings, refer to the "Provision Transponder and Muxponder Cards" chapter or the "Change DWDM Card Settings" chapter in the *Cisco ONS 15454 DWDM Procedure Guide*.

Note When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.

Note The tables in this section list the default settings for each DWDM, TXP, and MXP card. For all other cards, including electrical, optical, Ethernet, and Fibre Channel, refer to the *Cisco ONS 15454 Reference Manual* or the *Cisco ONS 15454 SDH Reference Manual.*

The following types of defaults are defined for DWDM, TXP, MXP, and Ethernet cards.

A.2.1.1 ANSI Configuration Defaults

Most card-level and port-level configuration defaults correspond to settings found in the CTC card-level Provisioning tabs.

Note The full set of Automatic Laser Shutdown (ALS) configuration defaults can be found in the CTC card-level Maintenance > ALS tab for supported cards. ALS defaults are supported for OSCM, OSC-CSM, OPT-BST, OPT-BST-L, ADM-10G, GE_XP, 10GE_XP, TXP, MXP, OTU2-XP, and PSM cards. For information on how ALS card settings achieve network level optical safety, see Chapter 3, "Optical Service Channel Cards," Chapter 4, "Optical Amplifier Cards," or Chapter 10, "Transponder and Muxponder Cards."

Configuration defaults that are reachable from the CTC card-level Provisioning tabs (except as noted) include the following types of options (arranged by CTC subtab):

- Line—(ADM-10G, GE_XP, 10GE_XP, TXP and MXP cards) Line-level configuration settings, including SONET, Wavelength Trunk, Trunk, Client, Distance Extension, and Enhanced FC/FICON ISL settings.

Note Some line configuration tabs, including Client, Distance Extension, and Enhanced FC/FICON ISL settings tabs, only appear in the card-level Provisioning > Line tab after a pluggable port module (PPM) is provisioned to a fibre channel payload type (port rate) for the particular card.

- OTN—(ADM-10G, GE_XP, 10GE_XP, MXP-2.5G-10E, MXP-2_5G-10G, MXP-MR-10DME, TXP-MR-10E, TXP-MR-10G, TXP-MR-2.5G, and TXPP-MR-2.5G cards) Optical transport network (OTN) line configuration settings.
- Card—(See listed settings for applicable cards)
  - Card mode—MXPP-MR-2.5G and MXP-MR-2.5G (ESCON, FC_GE, or MIXED), GE_XP (20GE MXP, 10GE MXP, or L2 over DWDM) , and 10GE_XP (10GE TXP or L2 over DWDM)
  - Port range-level mode settings—MXP-MR-10DME cards only
  - Termination mode—TXP-MR-10E, MXP-2.5G-10E, MXP-2.5G-10G, TXPP_MR_2.5G, TXP_MR_10G, and TXP_MR_2.5G cards
  - AIS squelch settings—TXP-MR-10E and MXP-2.5G-10E cards
- ALS (card-level Maintenance > ALS tab)—(OSC-CSM, OSCM, OPT-BST, OPT-BST-L, ADM-10G, GE_XP, 10GE_XP, TXP, MXP, and PSM cards) ALS configuration defaults.

Note For further information about supported features on each card, see Chapter 3, "Optical Service Channel Cards," Chapter 4, "Optical Amplifier Cards," or Chapter 10, "Transponder and Muxponder Cards."

A.2.1.2 ANSI Threshold Defaults

Threshold default settings define the default cumulative values (thresholds) beyond which a threshold crossing alert (TCA) will be raised, making it possible to monitor the network and detect errors early.

Card threshold default settings are provided as follows:

- PM thresholds—(OSCM, OSC-CSM, OTU2-XP, TXP, and MXP cards) Expressed in counts or seconds; includes line and SONET thresholds.
- Optical thresholds—(ADM-10G, GE_XP, 10GE_XP, OTU2-XP, TXP, and MXP cards) Expressed in percentages or dBm; includes client and trunk optical thresholds.

- OTN FEC thresholds (ADM-10G, GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts; includes enhanced, standard, 1G Ethernet, 1G Fibre channel, 1G FICON, OC-3, OC-12, OC-48, 2G FICON, and 2G Fibre channel thresholds.
- OTN G.709 thresholds (ADM-10G, GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts or seconds; includes ITU-T G.709 PM and SM thresholds.

Threshold defaults are defined for near end and/or far end, at 15-minute and one-day intervals. Thresholds are further broken down by type, such as Multiplex Section, Regeneration Section, VC LO, MS, RS, or Path, for performance monitoring (PM) thresholds, and TCA (warning) or Alarm for physical thresholds. PM threshold types define the layer to which the threshold applies. Physical threshold types define the level of response expected when the threshold is crossed.

Note For full descriptions of the thresholds you can set for each card, see Chapter 19, "Performance Monitoring."

Note When LOS, LOS-P, or LOF alarms occur on transponder and muxponder trunks, ITU-T G.709 SONET/SDH TCAs are suppressed. For details, see Chapter 18, "Alarm and TCA Monitoring and Management."

Note For additional information regarding PM parameter threshold defaults as defined by Telcordia specifications, refer to Telcordia GR-820-CORE and GR-253-CORE.

A.2.1.3 ANSI Defaults by Card

In the tables that follow, card defaults are defined by the default name, its factory-configured value, and the domain of allowable values that you can assign to it.

Note When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.

Note Some default values, such as certain thresholds, are interdependent. Before changing a value, review the domain for that default and any other related defaults for potential dependencies.

A.2.1.3.1 ANSI ADM-10G Card Default Settings

Table A-1 lists the ADM-10G card default settings.

Note ADM-10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-1 ANSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.config.interlink.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.interlink.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.interlink.ppmPortAssignment	UNASSIGNED	UNASSIGNED; Internal Link
ADM-10G.config.oc12.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc12.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.oc12.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc12.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc12.line.PJStsMon#	0 (STS #)	0 - 12
ADM-10G.config.oc12.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc12.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc12.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc12.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc12.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.oc3.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc3.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.oc3.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc3.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc3.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc3.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc3.line.PJStsMon#	0 (STS #)	0 - 3
ADM-10G.config.oc3.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc3.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc3.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.oc48.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.oc48.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.oc48.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.oc48.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.oc48.line.PJStsMon#	0 (STS #)	0 - 48
ADM-10G.config.oc48.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.oc48.sts.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.oc48.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.oc48.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.oc48.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
ADM-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
ADM-10G.config.trunk.IPPMEnabled	FALSE	TRUE; FALSE
ADM-10G.config.trunk.PJStsMon#	0 (STS #)	0 - 192
ADM-10G.config.trunk.ppmPortAssignment	OC192	UNASSIGNED; OC192
ADM-10G.etherPortConfig.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.etherPortConfig.AutoNegotiation	1000 Mbps	Auto; 1000 Mbps
ADM-10G.etherPortConfig.MTU	Jumbo	1548; Jumbo
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.mm.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.mm.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
ADM-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
ADM-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.CV	75 (B3 count)	0 - 2160000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.SES	3 (seconds)	0 - 900

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700
ADM-10G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
ADM-10G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
ADM-10G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc3.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
ADM-10G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc3.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
ADM-10G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
ADM-10G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.ES	200 (seconds)	0 - 86400

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts3c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts3c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts3c.farend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc3.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc3.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc3.sts1.farend.1day.ES	100 (seconds)	0 - 86400

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc3.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc3.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc3.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc3.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
ADM-10G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
ADM-10G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
ADM-10G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc48.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc48.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
ADM-10G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc48.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc48.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
ADM-10G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
ADM-10G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc48.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.nearend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.nearend.15min.CV	75 (B3 count)	0 - 2160000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts12c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts12c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.SES	3 (seconds)	0 - 900

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.oc12.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.oc12.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
ADM-10G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
ADM-10G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
ADM-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
ADM-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
ADM-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
ADM-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.line.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.trunk.line.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
ADM-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.line.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.trunk.line.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
ADM-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
ADM-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.section.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.nearend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.ES	200 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.1day.CV	250 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.ES	20 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts3c-9c.farend.15min.CV	25 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.1day.CV	750 (B3 count)	0 - 207360000

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.ES	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.1day.CV	750 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.ES	60 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts12c-192c.farend.15min.CV	75 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.FC	40 (count)	0 - 6912

Table A-1 ANSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.nearend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.nearend.15min.CV	15 (B3 count)	0 - 2160000
ADM-10G.pmthresholds.trunk.sts1.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.pmthresholds.trunk.sts1.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.sts1.farend.1day.CV	125 (B3 count)	0 - 207360000
ADM-10G.pmthresholds.trunk.sts1.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.FC	10 (count)	0 - 72
ADM-10G.pmthresholds.trunk.sts1.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.sts1.farend.15min.CV	15 (B3 count)	0 - 2160000

A.2.1.3.2 ANSI 40G-MXP-C Card Default Settings

Table A-2 lists the 40G-MXP-C card default settings.

Note 40G-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-MXP-C.pmthresholds.wis.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-MXP-C.pmthresholds.wis.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.wis.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.line.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.wis.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.wis.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.wis.line.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.wis.line.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.wis.line.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.sts192c.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.SES	7 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.FC	40 (count)	0 - 6912

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.ES	600 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.sts192c.nearend.1day.CV	750 (B3 count)	0 - 207360000
40G-MXP-C.pmthresholds.sts192c.nearend.15min.UAS	10 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.15min.SES	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.sts192c.nearend.15min.ES	60 (seconds)	0 - 900
40G-MXP-C.pmthresholds.sts192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
40G-MXP-C.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
40G-MXP-C.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
40G-MXP-C.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
40G-MXP-C.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
40G-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.config.wis.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.wis.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
40G-MXP-C.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
40G-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40G-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel

Table A-2 ANSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.section.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC192; Transparent when ppmPortAssignment UNASSIGNED; OC192; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40G-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

A.2.1.3.3 ANSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Table A-3 lists the 40-WXC-C, 40-WSS-C, and 80-WXC-Ccard default settings.

Note 40-WXC-C, 40-WSS-C, and 80-WXC-C cards are supported on the Cisco ONS 15454 and Cisco ONS 15454 M6 platforms.

Table A-3 ANSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Default Name	Default Value	Default Domain
WXC-80.config.card.WavelengthDrift	Enable	Disable; Enable
WXC-40.config.card.WavelengthDrift	Enable	Disable; Enable
WSS-40.config.card.WavelengthDrift	Enable	Disable; Enable

A.2.1.3.4 ANSI MXP_2.5G_10E Card Default Settings

Table A-4 lists the MXP_2.5G_10E card default settings.

Note MXP_2.5G_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-4 ANSI MXP_2.5G_10E Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
MXP-2_5G-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-2_5G-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-2_5G-10E.config.client.TerminationMode	Transparent	Transparent; Section
MXP-2_5G-10E.config.client.ppmPortAssignment	OC48	UNASSIGNED; OC48
MXP-2_5G-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-2_5G-10E.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10E.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10E.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10E.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.15min.HighRxPower	-9 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.15min.HighTxPower	9 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.1day.HighRxPower	-9 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.1day.HighTxPower	9 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	-6.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr1.alarm.LowTxPower	-4.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.otnLines.AsynchSynchMapping	ODU Multiplex	ODU Multiplex
MXP-2_5G-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced
MXP-2_5G-10E.otn.otnLines.G709OTN	Enable	Enable
MXP-2_5G-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900

Table A-4 ANSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.5 ANSI MXP_2.5G_10G Card Default Settings

Table A-5 lists the MXP_2.5G_10G card default settings.

Note MXP_2.5G_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-5 ANSI MXP_2.5G_10G Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-2_5G-10G.config.client.TerminationMode	Transparent	Transparent; Line
MXP-2_5G-10G.config.client.ppmPortAssignment	OC48	UNASSIGNED; OC48
MXP-2_5G-10G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-2_5G-10G.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10G.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10G.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-2_5G-10G.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
MXP-2_5G-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-2_5G-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-2_5G-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
MXP-2_5G-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
MXP-2_5G-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900

Table A-5 ANSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.6 ANSI MXP_MR_2.5G Card Default Settings

Table A-6 lists the MXP_MR_2.5G card default settings.

Note MXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-6 ANSI MXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.card.Mode	FC_GE	FC_GE; MIXED; ESCON
MXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE_GE; FC1G ISL; FC2G ISL; FICON1G ISL; FICON2G ISL when //.card.Mode FC_GE; UNASSIGNED; ONE_GE; ESCON; FC1G ISL; FICON1G ISL when //.card.Mode MIXED; UNASSIGNED; ESCON when //.card.Mode ESCON
MXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16; 32; 48 .. 1200
MXP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148; 2152; 2156; 2160; 2164; 2168; 2172
MXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-MR-2_5G.config.trunk.sdh.SendDoNotUse	FALSE	TRUE; FALSE
MXP-MR-2_5G.config.trunk.sdh.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-2_5G.config.trunk.sonet.SendDoNotUse	FALSE	TRUE; FALSE
MXP-MR-2_5G.config.trunk.sonet.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table A-6 ANSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.7 ANSI MXPP_MR_2.5G Card Default Settings

Table A-7 lists the MXPP_MR_2.5G card default settings.

Note MXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.card.Mode	FC_GE	FC_GE; MIXED; ESCON
MXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE_GE; FC1G ISL; FC2G ISL; FICON1G ISL; FICON2G ISL when //.card.Mode FC_GE; UNASSIGNED; ONE_GE; ESCON; FC1G ISL; FICON1G ISL when //.card.Mode MIXED; UNASSIGNED; ESCON when //.card.Mode ESCON
MXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXPP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXPP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16; 32; 48 .. 1200
MXPP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148; 2152; 2156; 2160; 2164; 2168; 2172
MXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
MXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXPP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200

Table A-7 ANSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Table A-8 lists the MXP_MR_10DME_C and MXP_MR_10DME_L card default settings.

Note MXP_MR_10DME_C and MXP_MR_10DME_L cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.card.Mode	Port 1-8: FC_GE_ISC	Port 1-8: FC_GE_ISC; Port 1-4: FC_GE_ISC; Port 5-8: FC4G; Port 1-4: FC4G; Port 5-8: FC_GE_ISC; Port 1-8: FC4G
MXP-MR-10DME.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-MR-10DME.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE-GE; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC3 PEER 1G; ISC3 PEER 2G when //.card.Mode Port 1-8: FC_GE_ISC; UNASSIGNED; FC4G_PORT when //.card.Mode Port 1-8: FC4G; UNASSIGNED; ONE-GE; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; FC4G; ISC3 PEER 1G; ISC3 PEER 2G when //.card.Mode Port 1-4: FC_GE_ISC; Port 5-8: FC4G; Port 1-4: FC4G; Port 5-8: FC_GE_ISC
MXP-MR-10DME.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
MXP-MR-10DME.config.fc.distanceExtension.Enabled	TRUE	TRUE; FALSE
MXP-MR-10DME.config.fc.distanceExtension.Fastswitch	FALSE	TRUE; FALSE
MXP-MR-10DME.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-MR-10DME.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-10DME.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
MXP-MR-10DME.config.trunk.SendDoNotUse	FALSE	FALSE; TRUE
MXP-MR-10DME.config.trunk.SyncMsgIn	TRUE	FALSE; TRUE
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowRxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.otnLines.AsynchSynchMapping	Synch Mapping	Synch Mapping
MXP-MR-10DME.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-MR-10DME.otn.otnLines.G709OTN	Enable	Disable; Enable
MXP-MR-10DME.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400

Table A-8 ANSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.9 ANSI SMR Card Default Settings

Table A-9 lists the SMR card default settings.

Note 40-SMR1-C and 40-SMR2-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-9 ANSI SMR Card Default Settings

Default Name	Default Value	Default Domain
SMR1-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR1-40.config.card.WavelengthDrift	Enable	Disable; Enable
SMR2-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR2-40.config.card.WavelengthDrift	Enable	Disable; Enable

A.2.1.3.10 ANSI TNC Card Default Settings

Table A-10 lists the TNC card default settings.

Note TNC cards are supported only on the Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-10 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TNC.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TNC.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
TNC.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
TNC.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
TNC.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
TNC.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TNC.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
TNC.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
TNC.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TNC.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912
TNC.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
TNC.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
TNC.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
TNC.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
TNC.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
TNC.opticalthresholds.oc3.ulh.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.alarm.LowRxPower	-45.5 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-10 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.opticalthresholds.oc3.ulh.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.ulh.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.1day.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.ulh.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.ulh.15min.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.oc3.ulh.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.ulh.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.alarm.LowRxPower	-36.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.oc3.lr2.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-10 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.opticalthresholds.oc3.lr2.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.oc3.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.oc3.lr2.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.oc3.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.LowRxPower	-45.5 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.ulh.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.1day.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-10 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.opticalthresholds.fastethernet.ulh.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.ulh.15min.LowRxPower	-43.0 (dBm)	-50.0; -49.9; -49.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.ulh.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.ulh.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.alarm.LowRxPower	-36.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.fastethernet.lx.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.fastethernet.lx.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.fastethernet.lx.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-10 ANSI TNC Card Default Settings

Default Name	Default Value	Default Name
TNC.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TNC.opticalthresholds.fastethernet.lx.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.1day.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.opticalthresholds.1gethernet.cwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TNC.opticalthresholds.1gethernet.cwdm.15min.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TNC.opticalthresholds.1gethernet.cwdm.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TNC.opticalthresholds.1gethernet.cwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TNC.config.oc3.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.ge.AlsMode	Auto Restart	Disabled; Auto Restart
TNC.config.fe.AlsMode	Auto Restart	Disabled; Auto Restart

A.2.1.3.11 ANSI TXP_MR_10E Card Default Settings

Table A-11 lists the TXP_MR_10E card default settings.

Note TXP_MR_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-11 ANSI TXP_MR_10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
TXP-MR-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
TXP-MR-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; SONET (including 10G Ethernet WAN Phy); Transparent when ppmPortAssignment 10G Ethernet LAN Phy; 10G Fiber Channel
TXP-MR-10E.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SONET (including 10G Ethernet WAN Phy); 10G Ethernet LAN Phy; 10G Fiber Channel

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-10E.config.client.sdh.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.sdh.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.client.sonet.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.sonet.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	6.0; 6.1; 6.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
TXP-MR-10E.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.15min.LowTxPower	0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir2.alarm.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.ir5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr1.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr2.alarm.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.lr5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.p1l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr1.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighRxPower	-1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.HighTxPower	5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.LowRxPower	-11 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.1day.LowTxPower	-12 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighRxPower	1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.HighTxPower	1 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.LowRxPower	-13 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr2.alarm.LowTxPower	-8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.sr5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.oc192.v3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.otnLines.AsynchSynchMapping	Synch Mapping	Asynch mapping; Synch Mapping
TXP-MR-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10E.otn.otnLines.G709OTN	Enable	Disable; Enable
TXP-MR-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.pmthresholds.client.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.client.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.client.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.client.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.line.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.client.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.client.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10E.pmthresholds.client.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600

Table A-11 ANSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.12 ANSI TXP_MR_10G Card Default Settings

Table A-12 lists the TXP_MR_10G card default settings.

Note TXP_MR_10G cards are supported only on the Cisco ONS 15454 platform.

Table A-12 ANSI TXP_MR_10G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED, SONET (including 10G Ethernet WAN Phy), 10G Ethernet LAN Phy
TXP-MR-10G.config.client.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.client.SFBER	1.00E-04	1E-3, 1E-4, 1E-5
TXP-MR-10G.config.client.TerminationMode	Transparent	Transparent, Line when mrPortAssignment UNASSIGNED, SONET (including 10G Ethernet WAN Phy); Transparent when mrPortAssignment 10G Ethernet LAN Phy
TXP-MR-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.trunk.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.trunk.SFBER	1.00E-04	1E-3, 1E-4, 1E-5
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.oc192.lw.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.oc192.lw.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-10G.otn.otnLines.SDBER	1.00E-07	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600

Table A-12 ANSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.13 ANSI TXP_MR_2.5G Card Default Settings

Table A-13 lists the TXP_MR_2.5G card default settings.

Note TXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-13 ANSI TXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC3; OC12; OC48; Transparent when ppmPortAssignment OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc12.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc12.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.oc12.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc12.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc3.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc3.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.oc3.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc3.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.oc48.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.oc48.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.oc48.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.oc48.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable; Enable
TXP-MR-2_5G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table A-13 ANSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.14 ANSI TXPP_MR_2.5G Card Default Settings

Table A-14 lists the TXPP_MR_2.5G card default settings.

Note TXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXPP-MR-2_5G.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; OC3; OC12; OC48; Transparent when ppmPortAssignment OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; OC3; OC12; OC48; ONE-GE; ESCON; DV6000; SDI-D1-VIDEO; HDTV; PASS-THRU; ETR-CLO; ISC COMPAT; FC1G; FC2G; FICON1G; FICON2G; ISC PEER
TXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc12.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighRxPower	-10.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowRxPower	-34.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowRxPower	-38.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc3.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.oc48.sr1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc12.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc12.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc12.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc12.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc3.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc3.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc3.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc3.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.oc48.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.oc48.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.oc48.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.oc48.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.otnLines.FEC	Enable	Disable; Enable when G709OTN Enable; Disable when G709OTN Disable
TXPP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable; Enable
TXPP-MR-2_5G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.CV	5315 (B2 count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.CV	53150 (B2 count)	0 - 53049600
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.FC	40 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.CV	5315 (B2 count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.SES	1 (seconds)	0 - 900

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.CV	53150 (B2 count)	0 - 53049600
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.CV	10000 (B1 count)	0 - 553500
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.CV	100000 (B1 count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc12.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.CV	1312 (B2 count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.farend.1day.UAS	10 (seconds)	0 - 86400

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc3.section.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.CV	21260 (B2 count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.CV	212600 (B2 count)	0 - 212371200

Table A-14 ANSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.CV	21260 (B2 count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.CV	212600 (B2 count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.line.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.CV	10000 (B1 count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SEFS	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.CV	100000 (B1 count)	0 - 206582400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.oc48.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.15 ANSI GE_XP Card Default Settings

Table A-15 lists the GE_XP card default settings.

Note GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-15 ANSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.config.card.Mode	10GE MXP	20GE MXP; 10GE MXP; L2 over DWDM
XP-GE.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-GE.config.client.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.client.DS1.LineCoding	B8ZS	B8ZS; AMI
XP-GE.config.client.DS1.LineLength	266-399 ft	0-133 ft; 133-266 ft; 266-399 ft; 399-533 ft; 533-655 ft
XP-GE.config.client.DS1.LineType	ESF	ESF; Unframed
XP-GE.config.client.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.client.FlowControl	OFF	OFF; ON
XP-GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.client.Speed	Auto	10 Mbps; 100 Mbps; 1000 Mbps; Auto
XP-GE.config.client.cEtherType	8100 (Hex)	Free form field

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.config.client.macLearningState	OFF	OFF; ON
XP-GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-GE.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; ONE-GE; FE
XP-GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-GE.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-GE.config.trunk.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-GE.config.trunk.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-GE.config.trunk.FlowControl	OFF	OFF; ON
XP-GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.macLearningState	OFF	OFF; ON
XP-GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.dwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighRxPower	-5.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighTxPower	-5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowRxPower	-30.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowTxPower	-17.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowRxPower	-33.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowTxPower	-21.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900

Table A-15 ANSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

A.2.1.3.16 ANSI 10GE_XP Card Default Settings

Table A-16 lists the 10GE_XP card default settings.

Note 10GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-16 ANSI 10GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-10GE.config.card.Mode	10GE TXP	10GE TXP; L2 over DWDM
XP-10GE.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-10GE.config.client.AlsMode	Disabled	Disabled; Manual Restart; Manual Restart for Test

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-10GE.config.client.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.client.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-10GE.config.client.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.client.FlowControl	OFF	OFF; ON
XP-10GE.config.client.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.client.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.client.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.macLearningState	OFF	OFF; ON
XP-10GE.config.client.niMode	UNI MODE	UNI MODE; NNI MODE
XP-10GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-10GE.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
XP-10GE.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
XP-10GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-10GE.config.trunk.CommittedBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.trunk.CommittedInfoRate	100 (%)	0; 1; 2 .. 100
XP-10GE.config.trunk.ExcessBurstSize	4K	4K; 8K; 16K .. 16M
XP-10GE.config.trunk.FlowControl	OFF	OFF; ON
XP-10GE.config.trunk.MTU	9700 (max 9700)	64; 65; 66 .. 9700
XP-10GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.macLearningState	OFF	OFF; ON
XP-10GE.config.trunk.niMode	NNI MODE	UNI MODE; NNI MODE
XP-10GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.sIngressCOS	0	0; 1; 2; 3; 4; 5; 6; 7; Trust; CVLAN
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table A-16 ANSI 10GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-10GE.otn.otnLines.G709OTN	Enable	Disable; Enable
XP-10GE.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

A.2.1.3.17 ANSI OSCM Card Default Settings

Table A-17 lists the OSCM card default settings.

Note OSCM cards are supported only on the Cisco ONS 15454 platform.

Table A-17 ANSI OSCM Card Default Settings

Default Name	Default Value	Default Domain
OSCM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSCM.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
OSCM.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
OSCM.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
OSCM.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912

Table A-17 ANSI OSCM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSCM.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
OSCM.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
OSCM.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
OSCM.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
OSCM.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
OSCM.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
OSCM.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
OSCM.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OSCM.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.18 ANSI OSC-CSM Card Default Settings

Table A-18 lists the OSC-CSM card default settings.

Note OSC-CSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-18 ANSI OSC-CSM Card Default Settings

Default Name	Default Value	Default Domain
OSC_CSM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSC_CSM.pmthresholds.line.farend.15min.CV	1312 (B2 count)	0 - 137700
OSC_CSM.pmthresholds.line.farend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.farend.15min.FC	10 (count)	0 - 72
OSC_CSM.pmthresholds.line.farend.15min.SES	1 (seconds)	0 - 900

Table A-18 ANSI OSC-CSM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSC_CSM.pmthresholds.line.farend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.farend.1day.CV	13120 (B2 count)	0 - 13219200
OSC_CSM.pmthresholds.line.farend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.farend.1day.FC	40 (count)	0 - 6912
OSC_CSM.pmthresholds.line.farend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.farend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.15min.CV	1312 (B2 count)	0 - 137700
OSC_CSM.pmthresholds.line.nearend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.15min.FC	10 (count)	0 - 72
OSC_CSM.pmthresholds.line.nearend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.line.nearend.1day.CV	13120 (B2 count)	0 - 13219200
OSC_CSM.pmthresholds.line.nearend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.1day.FC	40 (count)	0 - 6912
OSC_CSM.pmthresholds.line.nearend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.15min.CV	10000 (B1 count)	0 - 138600
OSC_CSM.pmthresholds.section.nearend.15min.ES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.15min.SES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.section.nearend.1day.CV	100000 (B1 count)	0 - 13305600
OSC_CSM.pmthresholds.section.nearend.1day.ES	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.19 ANSI OTU2-XP Card Default Settings

Table A-21 lists the OTU2-XP card default settings.

Note OTU2-XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Note NE default values for flow control and client distance parameters do not exist.

Table A-19 ANSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.config.port.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
OTU2-XP.config.port.AisSquelchMode	Squelch	Ais; Squelch
OTU2-XP.config.port.OduTransparency	Cisco Extended Use	Transparent Standard Use; Cisco Extended Use
OTU2-XP.config.port.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.config.port.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
OTU2-XP.config.port.TerminationMode	Transparent	Transparent; Section; Line when ppmPortAssignment UNASSIGNED; SONET (including 10G Ethernet WAN Phy); Transparent when ppmPortAssignment 10G Ethernet LAN Phy; 10G Fiber Channel
OTU2-XP.config.port.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SONET (including 10G Ethernet WAN Phy); 10G Ethernet LAN Phy; 10G Fiber Channel; IB_5G
OTU2-XP.config.port.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir2 .disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr. disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr.disabledfec.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2 .standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.sr1 .disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr. disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr.disabledfec.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.mm.disabled fec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.sr1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.oc192.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
OTU2-XP.otn.otnLines.G709OTN	Enable	Disable; Enable
OTU2-XP.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.pmthresholds.sts192c.nearend.15min.CV	75 (B3 count)	0 - 2160000
OTU2-XP.pmthresholds.sts192c.nearend.15min.ES	60 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.sts192c.nearend.15min.SES	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.15min.UAS	10 (seconds)	0 - 900
OTU2-XP.pmthresholds.sts192c.nearend.1day.CV	750 (B3 count)	0 - 207360000
OTU2-XP.pmthresholds.sts192c.nearend.1day.ES	600 (seconds)	0 - 86400
OTU2-XP.pmthresholds.sts192c.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.sts192c.nearend.1day.SES	7 (seconds)	0 - 86400
OTU2-XP.pmthresholds.sts192c.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.15min.CV	85040 (B2 count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.line.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.trunk.line.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.farend.1day.CV	850400 (B2 count)	0 - 849657600

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.trunk.line.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.trunk.line.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.15min.CV	85040 (B2 count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.line.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.pmthresholds.trunk.line.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.line.nearend.1day.CV	850400 (B2 count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.line.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.pmthresholds.trunk.line.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.line.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.section.nearend.15min.CV	10000 (B1 count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.section.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.15min.SEFS	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.section.nearend.1day.CV	100000 (B1 count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.section.nearend.1day.ES	5000 (seconds)	0 - 86400

Table A-19 ANSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.trunk.section.nearend.1day.SEFS	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.section.nearend.1day.SES	5000 (seconds)	0 - 86400

A.2.1.3.20 ANSI PSM Card Default Settings

Table A-21 lists the PSM card default settings.

Note PSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-20 ANSI Amplifier Card Default Settings

Default Name	Default Value	Default Domain
PSM.config.card.AlsMode	Disabled	Disabled, Auto Restart

A.2.1.3.21 ANSI Amplifier Card Default Settings

Table A-21 lists the OPT-BST, OPT-BST-L, OPT-AMP-C, and OPT-AMP-17-C card default settings.

Note The OPT-BST-L card is supported only on the Cisco ONS 15454 platform. The OPT-BST and OPT-AMP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-21 ANSI Amplifier Card Default Settings

Default Name	Default Value	Default Domain
OPT-AMP-17-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-AMP-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST-L.config.card.AlsMode	Auto Restart	Disabled, Auto Restart

A.2.2 ANSI Node Default Settings

Table A-22 on page A-544 lists the node-level default settings for the Cisco ONS 15454. Cisco provides the following types of user-configurable defaults for each Cisco ONS 15454 node:

Note The node default settings described in this section are supported on the Cisco ONS 15454, Cisco ONS 15454 M6, Cisco ONS 15454 M2 platforms, unless noted otherwise.

- Circuit settings—Set the administrative state and path protection circuit defaults, and whether to have circuits send a payload defect indication condition (PDIP).
- General settings—Set general node management defaults, including whether to use Daylight Savings Time (DST), whether to insert Alarm Indication Signal VT (AIS-V) in each VT when the carrying STS crosses the signal degrade (SD) path bit error rate (BER) threshold, the IP address of the Network Time Protocol/Simple Network Time Protocol (NTP/SNTP) server to be used, the time zone where the node is located, the SD path BER value, the defaults description, whether to raise a condition on an empty card slot, whether automatic autonomous Transcation Language One (TL1) reporting of PM data is enabled for cross-connect paths on the node, whether or not to allow ports to be disabled when they are providing services (when the default is set to FALSE users must remove or disable the services first, then put the ports out of service), and whether to report loopback conditions on Out-of-Service, Maintenance (OOS-MT) state ports.
- Link Management Protocol settings—Set link management protocol data link type, traffic engineering link, and general settings.
- Power Monitor settings—Set default voltage thresholds for the node.
- Network settings—Set whether to prevent display of node IP addresses in CTC (applicable for all users except Superusers); default gateway node type; whether to raise an alarm when the backplane LAN cable is disconnected; and whether to display the IP address in the LCD in an editable mode (in which you can change the IP address directly from LCD screen), to display the IP address on the LCD as read-only, or to suppress display of the IP on the LCD entirely.
- OSI settings—Set the Open System Interconnection (OSI) main setup, generic routing encapsulation (GRE) tunnel, link access protocol on the D channel (LAP-D), the router subnet, and the TID address resolution protocol (TARP) settings.
- 1+1 and Optimized 1+1 protection settings—Set whether or not protected circuits have bidirectional switching, are revertive, and what the reversion time is; set optimized 1+1 detection, recovery, and verify guard timer values.

  Note Optimized 1+1 supports three timers that ensure the correct state of the cards at key points in card communication. A verification guard timer is used when a Force is issued, to ensure that the far end has a chance to respond. A detection guard timer is used to ensure the presence of an SF/SD condition before switching away from a card. A recover guard timer ensures the absence of SF/SD prior to switching to a card. You can change the default number of seconds before these timers expire by changing the NE default for the corresponding timer to a value within its domain of allowable values.

- BLSR protection settings—Set whether BLSR-protected circuits are revertive, and what the reversion time is, at both the ring and span levels.
- Y Cable protection settings—Set whether Y-cable protected circuits are revertive, and what the reversion time is.
- Splitter protection settings—Set whether splitter protected circuits are revertive, and what the reversion time is.

- Legal Disclaimer—Set the legal disclaimer that warns users at the login screen about the possible legal or contractual ramifications of accessing equipment, systems, or networks without authorization.
- Security Grant Permissions—Set default user security levels for activating/reverting software, PM data clearing, database restoring, and retrieving audit logs.
- Security DataComm settings—Set default security settings for TCC Ethernet IP address and IP netmask, and CTC backplane IP suppression; set secure mode on and secure mode locked (for TCC2P cards only).
- Security Access settings—Set default security settings for LAN access, shell access, serial craft access, element management system (EMS) access (including Internet Inter-Object Request Broker Protocol [IIOP] listener port number), TL1 access, and Simple Network Management Protocol (SNMP) access.
- Security RADIUS settings—Set default RADIUS server settings for the accounting port number and the authentication port number, and whether to enable the node as a final authenticator.
- Security Policy settings—Set the allowable failed logins before lockout, idle user timeout for each user level, optional lockout duration or manual unlock enabled, password reuse and change frequency policies, number of characters difference that is required between the old and new password, password aging by security level, enforced single concurrent session per user, and option to disable inactive user after a set inactivity period.
- Security Password settings—Set when passwords can be changed, how many characters they must differ by, whether or not password reuse is allowed, and whether a password change is required on first login to a new account; set password aging enforcement and user-level specific aging and warning periods; set how many consecutive identical characters are allowed in a password, maximum password length, minimum password length, minimum number and combination of nonalphabetical characters required, and whether or not to allow a password that is a reversal of the login ID associated with the password.
- BITS Timing settings—Set the AIS threshold, Admin synchronization status messaging (SSM), coding, facility type, framing, state, and line build-out (LBO) settings for building integrated timing supply 1 (BITS-1) and BITS2 timing.
- General Timing settings—Set the mode (External, Line, or Mixed), quality of reserved (RES) timing (the rule that defines the order of clock quality from lowest to highest), revertive, reversion time, and SSM message set for node timing.

Note Any node level defaults changed using the **Provisioning > Defaults** tab, changes existing node level provisioning. Although this is service affecting, it depends on the type of defaults changed, for example, general, and all timing and security attributes. The “Changing default values for some node level attributes overrides the current provisioning.” message is displayed. The Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) explains the effect of changing the default values. However, when the card level defaults are changed using the **Provisioning > Defaults** tab, existing card provisioning remains unaffected.

Note For more information about each individual node setting, refer to the “Manage the Node” chapter in the *Cisco ONS 15454 DWDM Procedure Guide*.

Table A-22 ANSI Node Default Settings

Default Name	Default Value	Default Domain
NODE.circuits.SendPDIP	TRUE	TRUE, FALSE
NODE.circuits.State	IS,AINS	IS, OOS,DSBLD, OOS,MT, IS,AINS
NODE.circuits.upsr.AllowUpsrOverOnePlusOne	FALSE	TRUE, FALSE
NODE.circuits.upsr.ProvisionWorkingGoAndReturnOnPrimaryPath	TRUE	TRUE, FALSE
NODE.circuits.upsr.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.circuits.upsr.Revertive	FALSE	TRUE, FALSE
NODE.circuits.upsr.STS_SDBER	1.00E-06	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.circuits.upsr.STS_SFBER	1.00E-04	1E-3, 1E-4, 1E-5
NODE.circuits.upsr.SwitchOnPDIP	FALSE	TRUE, FALSE
NODE.circuits.upsr.VT_SDBER	1.00E-05	1E-5, 1E-6, 1E-7, 1E-8
NODE.circuits.upsr.VT_SFBER	1.00E-03	1E-3, 1E-4, 1E-5
NODE.general.AllowServiceAffectingPortChangeToDisabled	TRUE	FALSE, TRUE
NODE.general.AutoPM (only Cisco ONS 15454)	FALSE	FALSE, TRUE
NODE.general.BackupNtpSntpServer	0.0.0.0	IP Address
NODE.general.DefaultsDescription	Factory Defaults	Free form field
NODE.general.InsertAISVOnSDP	FALSE	TRUE, FALSE
NODE.general.NtpSntpServer	0.0.0.0	IP Address
NODE.general.RaiseConditionOnEmptySlot	FALSE	TRUE, FALSE
NODE.general.ReportLoopbackConditionsOnOOS-MTPorts	FALSE	FALSE, TRUE
NODE.general.SDPBER	1.00E-06	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.general.TimeZone	(GMT-08:00) Pacific Time (US & Canada), Tijuana	(For applicable time zones, see Table A-23 on page A-560.)
NODE.general.UseDST	TRUE	TRUE, FALSE
NODE.lmp.controlChannel.AdminState	OOS,DSBLD	IS, OOS,DSBLD

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.HelloDeadInterval	12000 (ms)	maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)), maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 1, maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 2 .. minimum_of(20000,MaxHelloDeadInterval)
NODE.lmp.controlChannel.HelloInterval	500 (ms)	maximum_of(300,MinHelloInterval), maximum_of(300,MinHelloInterval) + 1, maximum_of(300,MinHelloInterval) + 2 .. minimum_of(5000,MaxHelloInterval,quotient_of(HelloDeadInterval,3))
NODE.general.mvAirFilterBasedFanEnable	FALSE	TRUE, FALSE
NODE.lmp.controlChannel.MaxHelloDeadInterval	20000 (ms)	maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)), maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 1, maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 2 .. 20000

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.MaxHelloInterval	2000 (ms)	maximum_of(300,HelloInterval), maximum_of(300,HelloInterval) + 1, maximum_of(300,HelloInterval) + 2 .. minimum_of(5000,difference_of(MaxHelloDeadInterval,1))
NODE.lmp.controlChannel.MinHelloDeadInterval	2000 (ms)	maximum_of(2000,sum_of(MinHelloInterval,1)), maximum_of(2000,sum_of(MinHelloInterval,1)) + 1, maximum_of(2000,sum_of(MinHelloInterval,1)) + 2 .. minimum_of(20000,HelloDeadInterval)
NODE.lmp.controlChannel.MinHelloInterval	300 (ms)	300, 301, 302 .. minimum_of(5000,HelloInterval,difference_of(MinHelloDeadInterval,1))
NODE.lmp.dataLink.Type	Port	Port, Component
NODE.lmp.general.Allowed	TRUE	FALSE, TRUE
NODE.lmp.general.Enabled	FALSE	FALSE, TRUE when Allowed TRUE; FALSE when Allowed FALSE
NODE.lmp.general.LMP-WDM	TRUE	FALSE, TRUE
NODE.lmp.general.Role	OLS	PEER, OLS
NODE.lmp.teLink.AdminState	OOS,DSBLD	IS, OOS,DSBLD
NODE.lmp.teLink.DWDM	TRUE	FALSE, TRUE

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.teLink.MuxCapability	Lambda Switch	Packet Switch - Level 1, Packet Switch - Level 2, Packet Switch - Level 3, Packet Switch - Level 4, Layer 2 Switch, TDM Cross-connect, Lambda Switch, Fiber Switch
NODE.network.general.AlarmMissingBackplaneLAN	FALSE	TRUE, FALSE
NODE.network.general.CtcIpDisplaySuppression	FALSE	TRUE, FALSE
NODE.network.general.GatewaySettings	None	LeaveAsIs, None, ENE, GNE, ProxyOnlyNode
NODE.network.general.LcdSetting	Allow Configuration	Allow Configuration, Display Only, Suppress Display
NODE.osi.greTunnel.OspfCost	110	110 - 65535
NODE.osi.greTunnel.SubnetMask	24 (bits)	8, 9, 10 .. 32
NODE.osi.lapd.Mode	AITS	AITS, UITS
NODE.osi.lapd.MTU	512	512, 513, 514 .. 1500
NODE.osi.lapd.Role	Network	Network, User
NODE.osi.lapd.T200	200 (ms)	200, 300, 400 .. 20000
NODE.osi.lapd.T203	10000 (ms)	4000, 4100, 4200 .. 120000
NODE.osi.mainSetup.L1L2LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.L1LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.NodeRoutingMode	Intermediate System Level 1	End System, Intermediate System Level 1, Intermediate System Level 1/Level 2
NODE.osi.subnet.DISPriority	63	1, 2, 3 .. 127
NODE.osi.subnet.ESH	10 (sec)	10, 20, 30 .. 1000

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.osi.subnet.GCCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.IIH	3 (sec)	1, 2, 3 .. 600
NODE.osi.subnet.ISH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.LANISISCost	20	1, 2, 3 .. 63
NODE.osi.subnet.LDCCISISCost	40	1, 2, 3 .. 63
NODE.osi.subnet.OSCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.SDCCISISCost	60	1, 2, 3 .. 63
NODE.osi.tarp.L1DataCache	TRUE	FALSE, TRUE
NODE.osi.tarp.L2DataCache	FALSE	FALSE, TRUE
NODE.osi.tarp.LANStormSuppression	TRUE	FALSE, TRUE
NODE.osi.tarp.LDB	TRUE	FALSE, TRUE
NODE.osi.tarp.LDBEntry	5 (min)	1 - 10
NODE.osi.tarp.LDBFlush	5 (min)	0 - 1440
NODE.osi.tarp.PDUsL1Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsL2Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsOrigination	TRUE	FALSE, TRUE
NODE.osi.tarp.T1Timer	15 (sec)	0 - 3600
NODE.osi.tarp.T2Timer	25 (sec)	0 - 3600
NODE.osi.tarp.T3Timer	40 (sec)	0 - 3600
NODE.osi.tarp.T4Timer	20 (sec)	0 - 3600
NODE.osi.tarp.Type4PDUDelay	0 (sec)	0 - 255
NODE.powerMonitor.EHIBATVG	-56.5 (Vdc)	-54.0, -54.5, -55.0, -55.5, -56.0, -56.5
NODE.powerMonitor.ELWBATVG	-40.5 (Vdc)	-40.5, -41.0, -41.5, -42.0, -42.5, -43.0, -43.5, -44.0
NODE.powerMonitor.HIBATVG	-54.0 (Vdc)	-44.0, -44.5, -45.0 .. -56.5
NODE.powerMonitor.LWBATVG	-44.0 (Vdc)	-40.5, -41.0, -41.5 .. -54.0
NODE.protection.1+1.BidirectionalSwitching	FALSE	TRUE, FALSE
NODE.protection.1+1.DetectionGuardTimer	1 (seconds)	0, 0.05, 0.1, 0.5, 1, 2, 3, 4, 5
NODE.protection.1+1.RecoveryGuardTimer	1 (seconds)	0, 0.05, 0.1 .. 10
NODE.protection.1+1.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.protection.1+1.Revertive	FALSE	TRUE, FALSE
NODE.protection.1+1.VerifyGuardTimer	0.5 (seconds)	0.5, 1
NODE.protection.blsr.RingReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.blsr.RingRevertive	TRUE	TRUE, FALSE
NODE.protection.blsr.SpanReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.blsr.SpanRevertive	TRUE	TRUE, FALSE
NODE.protection.splitter.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.splitter.Revertive	FALSE	TRUE, FALSE
NODE.protection.ycable.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.ycable.Revertive	FALSE	TRUE, FALSE
NODE.security.dataComm.CtcBackplaneIpDisplaySuppression	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.DefaultTCCEthernetIP	10.0.0.1	IP Address
NODE.security.dataComm.DefaultTCCEthernetIPNetmask	24 (bits)	8, 9, 10 .. 32
NODE.security.dataComm.isSecureModeSupportedOnControlCard	TRUE	FALSE, TRUE
NODE.security.dataComm.LcdBackplaneIpSetting	NOT SUPPORTED	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.SecureModeLocked	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.dataComm.SecureModeOn (May reboot node)	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.emsAccess.AccessState	NonSecure	NonSecure, Secure
NODE.security.emsAccess.IIOPListenerPort (May reboot node)	57790 (port #)	0 - 65535
NODE.security.grantPermission.ActivateRevertSoftware	Superuser	Provisioning, Superuser
NODE.security.grantPermission.PMClearingPrivilege	Provisioning	Provisioning, Superuser
NODE.security.grantPermission.RestoreDB	Superuser	Provisioning, Superuser
NODE.security.grantPermission.RetrieveAuditLog	Superuser	Provisioning, Superuser
NODE.security.idleUserTimeout.Maintenance	01:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Provisioning	00:30 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Retrieve	00:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Superuser	00:15 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.lanAccess.LANAccess (May disconnect CTC from node)	Front & Backplane	No LAN Access, Front Only, Backplane Only, Front & Backplane
NODE.security.lanAccess.LANAccess (only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	Front Craft & EMS	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.RestoreTimeout	5 (minutes)	0 - 60

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.legalDisclaimer.LoginWarningMessage	<html> WARNING This system is restricted to authorized users for business purposes. Unauthorized <p>access is a violation of the law. This service may be monitored for administrative <p>and security reasons. By proceeding, you consent to this monitoring.	Free form field
NODE.security.other.DisableInactiveUser	FALSE	FALSE, TRUE
NODE.security.other.InactiveDuration	45 (days)	1, 2, 3 .. 99 when nothing TRUE; 45 when nothing FALSE
NODE.security.other.SingleSessionPerUser	FALSE	TRUE, FALSE
NODE.security.passwordAging.EnforcePasswordAging	FALSE	TRUE, FALSE
NODE.security.passwordAging.maintenance.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.maintenance.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.provisioning.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.provisioning.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.retrieve.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.retrieve.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.superuser.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.superuser.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordChange.CannotChangeNewPassword	FALSE	TRUE, FALSE
NODE.security.passwordChange.CannotChangeNewPasswordForNDays	20 (days)	20 - 95
NODE.security.passwordChange.NewPasswordMustDifferFromOldByNCharacters	1 (characters)	1 - 5

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.passwordChange.PreventReusingLastNPasswords	1 (times)	1 - 10
NODE.security.passwordChange.RequirePasswordChangeOnFirstLoginToNewAccount	FALSE	TRUE, FALSE
NODE.security.passwordComplexity.IdenticalConsecutiveCharactersAllowed	3 or more	0-2, 3 or more
NODE.security.passwordComplexity.MaximumLength	20	20, 80
NODE.security.passwordComplexity.MinimumLength	6	6, 8, 10, 12
NODE.security.passwordComplexity.MinimumRequiredCharacters	1 num, 1 letter & 1 TL1 special	1 num, 1 letter & 1 TL1 special, 1 num, 1 letter & 1 special, 2 each of any 2 of num, upper, lower & TL1 special, 2 each of any 2 of num, upper, lower & special
NODE.security.passwordComplexity.ReverseUserIdAllowed	TRUE	TRUE, FALSE
NODE.security.pseudoIOSAccess.AccessState	NonSecure	Disabled; NonSecure; Secure
NODE.security.pseudoIOSAccess.Port	65000	1024 - 65535
NODE.security.pseudoIOSAccess.SecurePort	64000	1024 - 65535
NODE.security.radiusServer.AccountingPort	1813 (port)	0 - 32767
NODE.security.radiusServer.AuthenticationPort	1812 (port)	0 - 32767
NODE.security.radiusServer.EnableNodeAsFinalAuthenticator	TRUE	FALSE, TRUE
NODE.security.serialCraftAccess.EnableCraftPort	TRUE	TRUE, FALSE
NODE.security.shellAccess.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.shellAccess.EnableShellPassword	FALSE	TRUE, FALSE
NODE.security.shellAccess.TelnetPort	23	23 - 9999
NODE.security.snmpAccess.AccessState	NonSecure	Disabled, NonSecure
NODE.security.tl1Access.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.userLockout.FailedLoginsAllowedBeforeLockout	5 (times)	0 - 10
NODE.security.userLockout.LockoutDuration	00:30 (mins:secs)	00:00, 00:05, 00:10 .. 10:00
NODE.security.userLockout.ManualUnlockBySuperuser	FALSE	TRUE, FALSE
NODE.software.AllowDelayedUpgrades	FALSE	FALSE, TRUE

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.software.DefaultDelayedUpgrades	FALSE	FALSE, TRUE when AllowDelayedUpgrades TRUE; FALSE when AllowDelayedUpgrades FALSE
NODE.timing.bits-1.AdminSSMIn	STU	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A
NODE.timing.bits-1.AISThreshold	SMC	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.Coding	B8ZS	B8ZS, AMI when FacilityType DS1; HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-1.CodingOut	B8ZS	B8ZS, AMI when FacilityTypeOut DS1; HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-1.FacilityType	DS1	DS1, 64kHz+8kHz when //.general.TimingStandard SONET; E1, 64kHz+8kHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-1.FacilityTypeOut	DS1	DS1, 6MHz when //.general.TimingStandard SONET; E1, 6MHz, 2MHz when //.general.TimingStandard SDH

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.Framing	ESF	ESF, D4 when FacilityType DS1; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-1.FramingOut	ESF	ESF, D4 when FacilityTypeOut DS1; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; N/A when FacilityTypeOut 6MHz
NODE.timing.bits-1.LBO	0-133	0-133, 134-266, 267-399, 400-533, 534-655
NODE.timing.bits-1.SaBit	N/A	N/A when FacilityType DS1; 4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-1.State	OOS,DSBLD	IS, OOS,DSBLD

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.StateOut	OOS,DSBLD	IS, OOS,DSBLD
NODE.timing.bits-2.AdminSSMIn	STU	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A
NODE.timing.bits-2.AISThreshold	SMC	PRS, STU, ST2, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 1; PRS, STU, ST2, TNC, ST3E, ST3, SMC, ST4, DUS, RES when //.general.SSM MessageSet Generation 2; G811, STU, G812T, G812L, SETS, DUS when //.general.SSM MessageSet N/A

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.Coding	B8ZS	B8ZS, AMI when FacilityType DS1; HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-2.CodingOut	B8ZS	B8ZS, AMI when FacilityTypeOut DS1; HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-2.FacilityType	DS1	DS1, 64kHz+8kHz when //.general.TimingStandard SONET; E1, 64kHz+8kHz, 2MHz when //.general.TimingStandard SDH
NODE.timing.bits-2.FacilityTypeOut	DS1	DS1, 6MHz when //.general.TimingStandard SONET; E1, 6MHz, 2MHz when //.general.TimingStandard SDH

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.Framing	ESF	ESF, D4 when FacilityType DS1; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-2.FramingOut	ESF	ESF, D4 when FacilityTypeOut DS1; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; N/A when FacilityTypeOut 6MHz
NODE.timing.bits-2.LBO	0-133	0-133, 134-266, 267-399, 400-533, 534-655
NODE.timing.bits-2.SaBit	N/A	N/A when FacilityType DS1; 4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-2.State	OOS,DSBLD	IS, OOS,DSBLD

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.StateOut	OOS,DSBLD	IS, OOS,DSBLD
NODE.timing.general.Mode	Line	External, Line, Mixed
NODE.timing.general.QualityOfRES	RES=DUS	PRS<RES, STU<RES<PRS, ST2<RES<STU, ST3<RES<ST2, SMC<RES<ST3, ST4<RES<SMC, RES<ST4, RES=DUS when SSMMessageSet Generation 1; PRS<RES, STU<RES<PRS, ST2<RES<STU, TNC<RES<ST2, ST3E<RES<TNC, ST3<RES<ST3E, SMC<RES<ST3, ST4<RES<SMC, RES<ST4, RES=DUS when SSMMessageSet Generation 2; N/A when SSMMessageSet N/A
NODE.timing.general.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.timing.general.Revertive	TRUE	TRUE, FALSE

Table A-22 ANSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.general.SSMMessageSet	Generation 1	Generation 1, Generation 2 when TimingStandard SONET; N/A when TimingStandard SDH
NODE.timing.general.TimingStandard	SONET	SONET, SDH

A.2.2.1 Time Zones

Table A-23 lists the time zones that apply for node time zone defaults. Time zones in the table are ordered by their relative relationships to Greenwich Mean Time (GMT), and the default values are displayed in the correct format for valid default input.

Table A-23 Time Zones

Time Zone (GMT +/– Hours)	Default Value
GMT-11:00	(GMT-11:00) Midway Islands, Samoa
GMT-10:00	(GMT-10:00) Hawaiian Islands, Tahiti
GMT-09:00	(GMT-09:00) Anchorage - Alaska
GMT-08:00	(GMT-08:00) Pacific Time (US & Canada), Tijuana
GMT-07:00	(GMT-07:00) Mountain Time (US & Canada)
GMT-07:00	(GMT-07:00) Phoenix - Arizona
GMT-06:00	(GMT-06:00) Central Time (US & Canada)
GMT-06:00	(GMT-06:00) Mexico City
GMT-06:00	(GMT-06:00) Costa Rica, Managua, San Salvador
GMT-06:00	(GMT-06:00) Saskatchewan
GMT-05:00	(GMT-05:00) Bogota, Lima, Quito
GMT-05:00	(GMT-05:00) Eastern Time (US & Canada)
GMT-05:00	(GMT-05:00) Havana
GMT-05:00	(GMT-05:00) Indiana (US)
GMT-04:00	(GMT-04:00) Asuncion
GMT-04:00	(GMT-04:00) Caracas, La Paz, San Juan
GMT-04:00	(GMT-04:00) Atlantic Time (Canada), Halifax, Saint John, Charlottetown
GMT-04:00	(GMT-04:00) Santiago
GMT-04:00	(GMT-04:00) Thule (Qaanaaq)
GMT-03:30	(GMT-03:30) St. John's - Newfoundland
GMT-03:00	(GMT-03:00) Brasilia, Rio de Janeiro, Sao Paulo

Table A-23 Time Zones (continued)

Time Zone (GMT +/– Hours)	Default Value
GMT-03:00	(GMT-03:00) Buenos Aires, Georgetown
GMT-03:00	(GMT-03:00) Godthab (Nuuk) - Greenland
GMT-02:00	(GMT-02:00) Mid-Atlantic
GMT-01:00	(GMT-01:00) Azores, Scoresbysund
GMT-01:00	(GMT-01:00) Praia - Cape Verde
GMT 00:00	(GMT 00:00) Casablanca, Reykjavik, Monrovia
GMT	(GMT) Greenwich Mean Time
GMT 00:00	(GMT 00:00) Dublin, Edinburgh, London, Lisbon
GMT+01:00	(GMT+01:00) Amsterdam, Berlin, Rome, Stockholm, Paris
GMT+01:00	(GMT+01:00) Belgrade, Bratislava, Budapest, Ljubljana, Prague
GMT+01:00	(GMT+01:00) Brussels, Copenhagen, Madrid, Vienna
GMT+01:00	(GMT+01:00) Sarajevo, Skopje, Sofija, Vilnius, Warsaw, Zagreb
GMT+01:00	(GMT+01:00) West Central Africa, Algiers, Lagos, Luanda
GMT+01:00	(GMT+01:00) Windhoek (Namibia)
GMT+02:00	(GMT+02:00) Al Jizah, Alexandria, Cairo
GMT+02:00	(GMT+02:00) Amman
GMT+02:00	(GMT+02:00) Athens, Bucharest, Istanbul
GMT+02:00	(GMT+02:00) Beirut
GMT+02:00	(GMT+02:00) Cape Town, Harare, Johannesburg, Pretoria
GMT+02:00	(GMT+02:00) Jerusalem
GMT+02:00	(GMT+02:00) Kaliningrad, Minsk
GMT+03:00	(GMT+03:00) Aden, Antananarivo, Khartoum, Nairobi
GMT+03:00	(GMT+03:00) Baghdad
GMT+03:00	(GMT+03:00) Kuwait, Riyadh
GMT+03:00	(GMT+03:00) Moscow, St. Petersburg, Novgorod
GMT+03:30	(GMT+03:30) Tehran
GMT+04:00	(GMT+04:00) Abu Dhabi, Mauritius, Muscat
GMT+04:00	(GMT+04:00) Aqtau, T'bilisi
GMT+04:00	(GMT+04:00) Baku
GMT+04:00	(GMT+04:00) Yerevan, Samara
GMT+04:30	(GMT+04:30) Kabul
GMT+05:00	(GMT+05:00) Chelyabinsk, Prem, Yekaterinburg, Ufa
GMT+05:00	(GMT+05:00) Islamabad, Karachi, Tashkent
GMT+05:30	(GMT+05:30) Calcutta, Mumbai, New Delhi, Chennai
GMT+05:45	(GMT+05:45) Kathmandu
GMT+06:00	(GMT+06:00) Almaty

Table A-23 Time Zones (continued)

Time Zone (GMT +/– Hours)	Default Value
GMT+06:00	(GMT+06:00) Colombo, Dhaka, Astana
GMT+06:00	(GMT+06:00) Novosibirsk, Omsk
GMT+06:30	(GMT+06:30) Cocos, Rangoon
GMT+07:00	(GMT+07:00) Bangkok, Hanoi, Jakarta
GMT+07:00	(GMT+07:00) Krasnoyarsk, Norilsk, Novokuznetsk
GMT+08:00	(GMT+08:00) Irkutsk, Ulaan Bataar
GMT+08:00	(GMT+08:00) Beijing, Shanghai, Hong Kong, Urumqi
GMT+08:00	(GMT+08:00) Perth
GMT+08:00	(GMT+08:00) Singapore, Manila, Taipei, Kuala Lumpur
GMT+09:00	(GMT+09:00) Chita, Yakutsk
GMT+09:00	(GMT+09:00) Osaka, Sapporo, Tokyo
GMT+09:00	(GMT+09:00) Palau, Pyongyang, Seoul
GMT+09:30	(GMT+09:30) Adelaide, Broken Hill
GMT+09:30	(GMT+09:30) Darwin
GMT+10:00	(GMT+10:00) Brisbane, Port Moresby, Guam
GMT+10:00	(GMT+10:00) Canberra, Melbourne, Sydney
GMT+10:00	(GMT+10:00) Hobart
GMT+10:00	(GMT+10:00) Khabarovsk, Vladivostok
GMT+10:30	(GMT+10:30) Lord Howe Island
GMT+11:00	(GMT+11:00) Honiara, Magadan, Soloman Islands
GMT+11:00	(GMT+11:00) Noumea - New Caledonia
GMT+11:30	(GMT+11:30) Kingston - Norfolk Island
GMT+12:00	(GMT+12:00) Andyra, Kamchatka
GMT+12:00	(GMT+12:00) Auckland, Wellington
GMT+12:00	(GMT+12:00) Marshall Islands, Eniwetok
GMT+12:00	(GMT+12:00) Suva - Fiji
GMT+12:45	(GMT+12:45) Chatham Island
GMT+13:00	(GMT+13:00) Nuku'alofa - Tonga
GMT+13:00	(GMT+13:00) Rawaki, Phoenix Islands
GMT+14:00	(GMT+14:00) Line Islands, Kiritimati - Kiribati

A.3 CTC Default Settings

Table A-24 on page A-563 lists the CTC-level default settings for the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6. Cisco provides the following user-configurable defaults for CTC:

- Automatic Routing—Set circuit creation with the Route Automatically check box selected by default.
- Network Circuit Automatic Routing Overridable—Set by default whether or not a user creating circuits can change (override) the Automatic Circuit Routing setting (also provisionable as a default) in the CTC Circuit Routing Preferences area. When this default is set to TRUE it enables users to change whether or not Route Automatically is selected in the check box. When this default is set to FALSE it ensures that users cannot change the Route Automatically setting while creating circuits in CTC.

Note When the Route Automatically check box is not selectable (and is not checked) during circuit creation, the following automatic routing suboptions are also unavailable: Using Required Nodes/Spans, Review Route Before Creation, and VT-DS3 Mapped Conversion.

- Create TL1-like—Set whether to create only TL1-like circuits; that is, instruct the node to create only cross-connects, allowing the resulting circuits to be in an upgradable state.
- Local domain creation and viewing—Set whether domains that users create and view persist globally (all CTC sessions), or only locally (within the current CTC session).
- Network Map—Set the default network map (which country's map is displayed in CTC network view).

Table A-24 CTC Default Settings

Default Name	Default Value	Default Domain
CTC.circuits.CreateLikeTL1	FALSE	TRUE, FALSE
CTC.circuits.RouteAutomatically	TRUE	TRUE, FALSE
CTC.circuits.RouteAutomaticallyDefaultOverridable	TRUE	TRUE, FALSE
CTC.network.Map	United States	-none-, Germany, Japan, Netherlands, South Korea, United Kingdom, United States

A.4 ETSI Platform Defaults

The following sections give the NE defaults for the ONS 15454 ETSI platform. To see defaults for the ONS 15454 ANSI platform, see the "A.2 ANSI Platform Defaults" section on page A-2.

A.4.1 ETSI Card Defaults

The tables in this section list the default settings for each DWDM, Transponder (TXP), Muxponder (MXP), or Ethernet card. Cisco provides several types of user-configurable defaults for Cisco ONS 15454 DWDM, TXP, MXP, and Ethernet cards. Types of card defaults can be broadly grouped by function, as outlined in the following subsections. For information about individual card settings, refer to the "Provision Transponder and Muxponder Cards" chapter, or the "Change DWDM Card Settings" chapter in the *Cisco ONS 15454 DWDM Procedure Guide*.

Note When the card level defaults are changed, the new provisioning done after the defaults have changed is affected. Existing provisioning remains unaffected.

Note The tables in this section list the default settings for each DWDM, TXP, and MXP card. For all other cards, including electrical, optical, Ethernet, and Fibre Channel, refer to the *Cisco ONS 15454 Reference Manual* or the *Cisco ONS 15454 SDH Reference Manual.*

The following types of defaults are defined for DWDM, TXP, MXP, and Ethernet cards.

A.4.1.1 ETSI Configuration Defaults

Most card and port-level configuration defaults correspond to settings found in the CTC card-level Provisioning tabs.

Note The full set of Automatic Laser Shutdown (ALS) configuration defaults can be found in the CTC card-level Maintenance > ALS tab for supported cards. ALS defaults are supported for OSCM, OSC-CSM, OPT-BST, OPT-BST-L, GE_XP, 10GE_XP, TXP, and MXP cards. For information on how ALS card settings achieve network level optical safety, see Chapter 3, "Optical Service Channel Cards," Chapter 4, "Optical Amplifier Cards," or Chapter 10, "Transponder and Muxponder Cards."

Configuration defaults that are reachable from the CTC card-level Provisioning tabs (except as noted) include the following types of options (arranged by CTC subtab):

- Line—(GE_XP, 10GE_XP, TXP and MXP cards) Line-level configuration settings, including SONET, Wavelength Trunk, Trunk, Client, Distance Extension, and Enhanced FC/FICON ISL settings.

Note Some line configuration tabs, including Client, Distance Extension, and Enhanced FC/FICON ISL settings tabs, only appear in the card-level Provisioning > Line tab after a pluggable port module (PPM) is provisioned to a fibre channel payload type (port rate) for the particular card.

- OTN—(GE_XP, 10GE_XP, MXP-2.5G-10E, MXP-2_5G-10G, MXP-MR-10DME, TXP-MR-10E, TXP-MR-10G, TXP-MR-2.5G, and TXPP-MR-2.5G cards) Optical transport network (OTN) line configuration settings.
- Card—(See listed settings for applicable cards)
  - Card mode—MXPP-MR-2.5G and MXP-MR-2.5G (ESCON, FC_GE, or MIXED), GE_XP (20GE MXP, 10GE MXP, or L2 over DWDM) , and 10GE_XP (10GE TXP or L2 over DWDM)
  - Port range-level mode settings—MXP-MR-10DME cards only
  - Termination mode—TXP-MR-10E, MXP-2.5G-10E, MXP-2.5G-10G, TXPP_MR_2.5G, TXP_MR_10G, and TXP_MR_2.5G cards
  - AIS squelch settings—TXP-MR-10E and MXP-2.5G-10E cards
- ALS (card-level Maintenance > ALS tab)—(OSC-CSM, OSCM, OPT-BST, OPT-BST-L, GE_XP, 10GE_XP, TXP, and MXP cards) ALS configuration defaults.

Note For further information about supported features on each card, see Chapter 3, "Optical Service Channel Cards," Chapter 4, "Optical Amplifier Cards," or Chapter 10, "Transponder and Muxponder Cards."

A.4.1.2 ETSI Threshold Defaults

Threshold default settings define the default cumulative values (thresholds) beyond which a threshold crossing alert (TCA) will be raised, making it possible to monitor the network and detect errors early.

Card threshold default settings are provided as follows:

- PM thresholds—(OSCM, OSC-CSM, TXP and MXP cards) Expressed in counts or seconds; includes line and SDH thresholds.
- Optical thresholds—(GE_XP, 10GE_XP, TXP, and MXP cards) Expressed in percentages or dBm; includes client and trunk optical thresholds.
- OTN FEC thresholds (GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts; includes enhanced, standard, 1G Ethernet, 1G Fibre channel, 1G FICON, STM-1, STM-4, STM-16, 2G FICON, and 2G Fibre channel thresholds.
- OTN G.709 thresholds (GE_XP, 10GE_XP, TXP, and MXP cards)—Expressed in counts or seconds; includes ITU-T G.709 PM and SM thresholds.

Threshold defaults are defined for near end and/or far end, at 15-minute and one-day intervals. Thresholds are further broken down by type, such as Multiplex Section, Regeneration Section, VC LO, MS, RS, or Path, for performance monitoring (PM) thresholds, and TCA (warning) or Alarm for physical thresholds. PM threshold types define the layer to which the threshold applies. Physical threshold types define the level of response expected when the threshold is crossed.

Note For full descriptions of the thresholds you can set for each card, see Chapter 19, "Performance Monitoring."

Note In R7.0.1, when LOS, LOS-P, or LOF alarms occur on TXP and MXP trunks, certain TCAs are suppressed. For details, see Chapter 18, "Alarm and TCA Monitoring and Management."

Note For additional information regarding PM parameter threshold defaults as defined by Telcordia specifications, refer to Telcordia GR-820-CORE and GR-253-CORE.

A.4.1.3 ETSI Defaults by Card

In the tables that follow, card defaults are defined by the default name, its factory-configured value, and the domain of allowable values that you can assign to it.

Note Some default values, such as certain thresholds, are interdependent. Before changing a value, review the domain for that default and any other related defaults for potential dependencies.

A.4.1.3.1 ETSI ADM-10G Card Default Settings

Table A-25 lists the ADM-10G card default settings.

Note ADM-10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-25 ETSI ADM-10G Card Default Settings

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
ADM-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
ADM-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
ADM-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
ADM-10G.pmthresholds.trunk.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.trunk.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.nearend.1day.BBE	250 (count)	0 - 207273600

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.trunk.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.trunk.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.trunk.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.trunk.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.trunk.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.trunk.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
ADM-10G.pmthresholds.stm4.rs.nearend.1day.BBE	100000 (count)	0 - 53136000
ADM-10G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 553500
ADM-10G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 553500
ADM-10G.pmthresholds.stm4.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm4.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm4.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm4.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm4.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm4.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm4.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm4.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm4.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm4.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53049600
ADM-10G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
ADM-10G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400
ADM-10G.pmthresholds.stm16.rs.nearend.1day.BBE	100000 (count)	0 - 206582400
ADM-10G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
ADM-10G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2151900
ADM-10G.pmthresholds.stm16.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm16.path.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm16.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm16.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm16.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm16.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm16.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm16.path.farend.1day.BBE	250 (count)	0 - 207273600

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm16.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm16.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
ADM-10G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200
ADM-10G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
ADM-10G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 138600
ADM-10G.pmthresholds.stm1.path.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.PPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.PPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCS-PGEN	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCS-PDET	9600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.nearend.1day.PJCDIFF	5760 (count)	0 - 1382400000
ADM-10G.pmthresholds.stm1.path.nearend.1day.NPJC-PGEN	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.NPJC-PDET	5760 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.ES	100 (seconds)	0 - 86400

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm1.path.nearend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.nearend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm1.path.nearend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.PPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.PPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCS-PGEN	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCS-PDET	100 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.PJCDIFF	60 (count)	0 - 14400000
ADM-10G.pmthresholds.stm1.path.nearend.15min.NPJC-PGEN	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.NPJC-PDET	60 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.nearend.15min.EB	15 (count)	0 - 7200000
ADM-10G.pmthresholds.stm1.path.nearend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm1.path.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.1day.SES	7 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.1day.ES	100 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.path.farend.1day.EB	125 (count)	0 - 691200000
ADM-10G.pmthresholds.stm1.path.farend.1day.BBE	250 (count)	0 - 207273600
ADM-10G.pmthresholds.stm1.path.farend.15min.UAS	10 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.15min.SES	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.15min.ES	12 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.path.farend.15min.EB	15 (count)	0 - 13305600
ADM-10G.pmthresholds.stm1.path.farend.15min.BBE	25 (count)	0 - 2159100
ADM-10G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.nearend.1day.PSD	600 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.nearend.1day.PSC	5 (count)	0 - 57600
ADM-10G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 53049600
ADM-10G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.15min.PSD	300 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.15min.PSC	1 (count)	0 - 600
ADM-10G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200
ADM-10G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
ADM-10G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
ADM-10G.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.otn.otnLines.G709OTN	Enable	Disable; Enable
ADM-10G.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
ADM-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
ADM-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
ADM-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
ADM-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
ADM-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
ADM-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
ADM-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
ADM-10G.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
ADM-10G.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
ADM-10G.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.ir2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.interlink.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.sr.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.LowTxPower	-22.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.mm.alarm.LowRxPower	-28.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.1day.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.mm.1day.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm4.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.LowTxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.mm.15min.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.stm1.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.stm1.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
ADM-10G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
ADM-10G.etherPortConfig.MTU	Jumbo	1548; Jumbo
ADM-10G.etherPortConfig.AutoNegotiation	1000 Mbps	Auto; 1000 Mbps
ADM-10G.etherPortConfig.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.trunk.ppmPortAssignment	STM64	UNASSIGNED; STM64
ADM-10G.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0; 60.1; 60.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm4.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm4.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm4.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.stm4.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm4.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.stm4.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm4.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm4.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm16.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm16.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm16.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.stm16.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm16.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.stm16.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm16.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm16.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.stm1.line.SyncMsgIn	TRUE	FALSE; TRUE
ADM-10G.config.stm1.line.SendDoNotUse	FALSE	TRUE; FALSE
ADM-10G.config.stm1.line.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
ADM-10G.config.stm1.line.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
ADM-10G.config.stm1.line.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
ADM-10G.config.stm1.line.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.stm1.line.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
ADM-10G.config.stm1.line.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
ADM-10G.config.ppmSlotAssignment	PPM (1 Port)	UNASSIGNED; PPM (1 Port)
ADM-10G.config.interlink.ppmPortAssignment	Internal Link	UNASSIGNED; Internal Link
ADM-10G.config.interlink.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table A-25 ETSI ADM-10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
ADM-10G.config.interlink.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
ADM-10G.config.interlink.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test

A.4.1.3.2 ETSI 40G-MXP-C Card Default Settings

Table A-26 lists the 40G-MXP-C card default settings.

Note 40G-MXP-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.EB	100000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.EB	10000 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.EB	850400 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.nearend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.EB	85040 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.nearend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.wis.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.EB	850400 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.wis.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.wis.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.EB	85040 (seconds)	0 - 900
40G-MXP-C.pmthresholds.wis.ms.farend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.path.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.1day.SES	7 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.1day.ES	100 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.path.nearend.1day.EB	125 (count)	0 - 691200000

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.path.nearend.1day.BBE	250 (count)	0 - 207273600
40G-MXP-C.pmthresholds.path.nearend.15min.UAS	10 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.15min.SES	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.15min.ES	12 (seconds)	0 - 900
40G-MXP-C.pmthresholds.path.nearend.15min.EB	15 (count)	0 - 7200000
40G-MXP-C.pmthresholds.path.nearend.15min.BBE	25 (count)	0 - 2159100
40G-MXP-C.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.EB	100000 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.rs.nearend.1day.BBE	100000 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.EB	10000 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.rs.nearend.15min.BBE	10000 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.EB	850400 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.nearend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.pmthresholds.client.ms.nearend.15min.EB	85040 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.nearend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.EB	850400 (seconds)	0 - 86400
40G-MXP-C.pmthresholds.client.ms.farend.1day.BBE	850400 (seconds)	0 - 849657600
40G-MXP-C.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.EB	85040 (seconds)	0 - 900
40G-MXP-C.pmthresholds.client.ms.farend.15min.BBE	85040 (seconds)	0 - 8850600
40G-MXP-C.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.otn.otnLines.G709OTN	Enable	Enable
40G-MXP-C.otn.otnLines.FEC	Standard	Standard; Enhanced when G709OTN Enable
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
40G-MXP-C.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
40G-MXP-C.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
40G-MXP-C.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
40G-MXP-C.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
40G-MXP-C.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
40G-MXP-C.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
40G-MXP-C.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
40G-MXP-C.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
40G-MXP-C.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-6.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.l2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l1.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l1.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l1.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.l1.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.l1.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.l1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.l1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.stm64.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.s2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowTxPower	-11.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.LowRxPower	-20.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighTxPower	-0.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.mm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowTxPower	-15.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighRxPower	-1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.mm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.lr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l1.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l1.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l1.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.l1.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.l1.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.l1.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.l1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowTxPower	-1.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.ir1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowTxPower	-8.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.LowRxPower	-16.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighTxPower	3.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.LowRxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.i1.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.er.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.LowRxPower	-29.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.dwdm.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighRx Power	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.otu2.cwdm40km.enhancedfec.15min.HighLa serBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowTxPower	-10.9 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.LowRxPower	-16.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighTxPower	12.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowTxPower	-14.4 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.LowRxPower	-13.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighTxPower	16.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighRxPower	0.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.8gfibrechannel.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.zr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.lr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.er.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gfibrechannel.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.ir1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.i2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.i1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.dwdm.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
40G-MXP-C.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
40G-MXP-C.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.trunk.Overclock	OFF	OFF; ON
40G-MXP-C.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
40G-MXP-C.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
40G-MXP-C.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel

Table A-26 ETSI 40G-MXP-C Card Default Settings

Default Name	Default Value	Default Domain
40G-MXP-C.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; STM64; Transparent when ppmPortAssignment UNASSIGNED; STM64; 10G Ethernet LAN Phy; 10G Fiber Channel; OTU2; 8G Fiber Channel
40G-MXP-C.config.client.SyncMsgIn	TRUE	FALSE; TRUE
40G-MXP-C.config.client.SendDoNotUse	FALSE	TRUE; FALSE
40G-MXP-C.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
40G-MXP-C.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
40G-MXP-C.config.client.AlsRecoveryPulseInterval	300 (seconds)	100 - 2000
40G-MXP-C.config.client.AlsRecoveryPulseDuration	100.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
40G-MXP-C.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
40G-MXP-C.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

A.4.1.3.3 ETSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Table A-27 lists the 40-WXC-C, 40-WSS-C, and 80-WXC-Ccard default settings.

Note 40-WXC-C, 40-WSS-C, and 80-WXC-C cards are supported on the Cisco ONS 15454 and Cisco ONS 15454 M6 platforms.

Table A-27 ETSI 40-WXC-C, 40-WSS-C, and 80-WXC-C Card Default Settings

Default Name	Default Value	Default Domain
WXC-80.config.card.WavelengthDrift	Enable	Disable; Enable
WXC-40.config.card.WavelengthDrift	Enable	Disable; Enable
WSS-40.config.card.WavelengthDrift	Enable	Disable; Enable

A.4.1.3.4 ETSI MS-ISC-100T Card Default Settings

Table A-28 lists the MS-ISC-100T card default settings.

Note MS-ISC-100T cards are supported only on the Cisco ONS 15454 platform.

Table A-28 MS-ISC-100T Card Default Settings

Default Name	Default Value	Default Domain
MS-ISC-100T.config.PreServiceAlarmSuppression	TRUE	TRUE, FALSE
MS-ISC-100T.config.SoakTime	00:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MS-ISC-100T.config.card.Mode	HDLC	HDLC, GFP-F, RPR 802.17
MS-ISC-100T.ios.consolePortAccess	TRUE	TRUE, FALSE
MS-ISC-100T.ios.radiusServerAccess	FALSE	TRUE, FALSE

A.4.1.3.5 ETSI MXP_2.5G_10E Card Default Settings

Table A-29 lists the MXP_2.5G_10E card default settings.

Note MXP_2.5G_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-29 ETSI MXP_2.5G_10E Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10E.config.client.AisSquelchMode	Squelch	Ais, Squelch
MXP-2_5G-10E.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
MXP-2_5G-10E.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10E.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-2_5G-10E.config.client.SendDoNotUse	FALSE	TRUE, FALSE
MXP-2_5G-10E.config.client.SyncMsgIn	TRUE	FALSE, TRUE
MXP-2_5G-10E.config.client.TerminationMode	Transparent	Transparent, Regeneration Section
MXP-2_5G-10E.config.client.ppmPortAssignment	STM16	UNASSIGNED, STM16
MXP-2_5G-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-2_5G-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10E.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-2_5G-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10E.otn.otnLines.AsynchSynchMapping	ODU Multiplex	ODU Multiplex
MXP-2_5G-10E.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced
MXP-2_5G-10E.otn.otnLines.G709OTN	Enable	Enable
MXP-2_5G-10E.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.BBE	21260 (count)	0 - 2212200

Table A-29 ETSI MXP_2.5G_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10E.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.6 ETSI MXP_2.5G_10G Card Default Settings

Table A-30 lists the MXP_2.5G_10G card default settings.

Note MXP_2.5G_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-30 ETSI MXP_2.5G_10G Card Default Settings

Default Name	Default Value	Default Domain
MXP-2_5G-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-2_5G-10G.config.client.SendDoNotUse	FALSE	TRUE, FALSE
MXP-2_5G-10G.config.client.SyncMsgIn	TRUE	FALSE, TRUE
MXP-2_5G-10G.config.client.TerminationMode	Transparent	Transparent, Multiplex Section
MXP-2_5G-10G.config.client.ppmPortAssignment	STM16	UNASSIGNED, STM16
MXP-2_5G-10G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-2_5G-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-2_5G-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-2_5G-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-2_5G-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-2_5G-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-2_5G-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-2_5G-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-2_5G-10G.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-2_5G-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
MXP-2_5G-10G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-30 ETSI MXP_2.5G_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-2_5G-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.7 ETSI MXP_MR_2.5G Card Default Settings

Table A-31 lists the MXP_MR_2.5G card default settings.

Note MXP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-31 ETSI MXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.card.Mode	FC_GE	FC_GE, MIXED, ESCON
MXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, ONE_GE, FC1G ISL, FC2G ISL, FICON1G ISL, FICON2G ISL when //.card.Mode FC_GE; UNASSIGNED, ONE_GE, ESCON, FC1G ISL, FICON1G ISL when //.card.Mode MIXED; UNASSIGNED, ESCON when //.card.Mode ESCON
MXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16, 32, 48 .. 1200
MXP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148, 2152, 2156, 2160, 2164, 2168, 2172
MXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.config.trunk.SendDoNotUse	FALSE	TRUE, FALSE
MXP-MR-2_5G.config.trunk.SyncMsgIn	TRUE	FALSE, TRUE
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.BBE	212600 (count)	0 - 212371200

Table A-31 ETSI MXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.8 ETSI MXPP_MR_2.5G Card Default Settings

Table A-32 lists the MXPP_MR_2.5G card default settings.

Note MXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.card.Mode	FC_GE	FC_GE, MIXED, ESCON
MXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, ONE_GE, FC1G ISL, FC2G ISL, FICON1G ISL, FICON2G ISL when //.card.Mode FC_GE; UNASSIGNED, ONE_GE, ESCON, FC1G ISL, FICON1G ISL when //.card.Mode MIXED; UNASSIGNED, ESCON when //.card.Mode ESCON
MXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXPP-MR-2_5G.config.fc.distanceExtension.AutoDetect	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.AutoadjustGFPBufferThreshold	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXPP-MR-2_5G.config.fc.distanceExtension.NumCredits	32	2 - 256
MXPP-MR-2_5G.config.fc.distanceExtension.NumGFPBuffers	16	16, 32, 48 .. 1200
MXPP-MR-2_5G.config.fc.enhancedFibreChannelFicon.MaxFrameSize	2148	2148, 2152, 2156, 2160, 2164, 2168, 2172
MXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
MXPP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXPP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.mm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.15min.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighRxPower	-14.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.HighTxPower	-8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.1day.LowTxPower	-35.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighRxPower	-11.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.HighTxPower	-12.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.client.escon.sm.alarm.LowTxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.BBE	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.EB	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.BBE	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.EB	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.EB	21260 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900

Table A-32 ETSI MXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.EB	212600 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 2151900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 212371200
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 206582400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXPP-MR-2_5G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.9 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Table A-33 lists the MXP_MR_10DME_C and MXP_MR_10DME_L card default settings.

Note MXP_MR_10DME_C and MXP_MR_10DME_L cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.card.Mode	Port 1-8: FC_GE_ISC	Port 1-8: FC_GE_ISC, Port 1-4: FC_GE_ISC, Port 5-8: FC4G, Port 1-4: FC4G, Port 5-8: FC_GE_ISC, Port 1-8: FC4G
MXP-MR-10DME.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, ONE-GE, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC3 PEER 1G, ISC3 PEER 2G when //.card.Mode Port 1-8: FC_GE_ISC; UNASSIGNED, FC4G_PORT when //.card.Mode Port 1-8: FC4G; UNASSIGNED, ONE-GE, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, FC4G, ISC3 PEER 1G, ISC3 PEER 2G when //.card.Mode Port 1-4: FC_GE_ISC, Port 5-8: FC4G, Port 1-4: FC4G, Port 5-8: FC_GE_ISC
MXP-MR-10DME.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
MXP-MR-10DME.config.fc.distanceExtension.Enabled	TRUE	TRUE, FALSE
MXP-MR-10DME.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
MXP-MR-10DME.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
MXP-MR-10DME.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
MXP-MR-10DME.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
MXP-MR-10DME.config.trunk.SendDoNotUse	FALSE	FALSE, TRUE
MXP-MR-10DME.config.trunk.SyncMsgIn	TRUE	FALSE, TRUE
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.1gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.2gisc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gfibrechannel.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowRxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.mm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.15min.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighRxPower	-1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.1day.LowTxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighRxPower	2.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.HighTxPower	0.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.4gficon.sm.alarm.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
MXP-MR-10DME.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
MXP-MR-10DME.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
MXP-MR-10DME.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
MXP-MR-10DME.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
MXP-MR-10DME.otn.otnLines.AsynchSynchMapping	Synch Mapping	Synch Mapping
MXP-MR-10DME.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
MXP-MR-10DME.otn.otnLines.G709OTN	Enable	Disable, Enable
MXP-MR-10DME.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-33 ETSI MXP_MR_10DME_C and MXP_MR_10DME_L Card Default Settings (continued)

Default Name	Default Value	Default Domain
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
MXP-MR-10DME.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.10 ETSI OTU2-XP Card Default Settings

Table A-34 lists the OTU2-XP card default settings.

Note OTU2-XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Note NE default values for flow control and client distance parameters do not exist.

Table A-34 ETSI OTU2-XP Card Default Settings

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.pmthresholds.path.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.pmthresholds.path.nearend.1day.SES	7 (seconds)	0 - 86400
OTU2-XP.pmthresholds.path.nearend.1day.ES	100 (seconds)	0 - 86400
OTU2-XP.pmthresholds.path.nearend.1day.EB	125 (count)	0 - 691200000
OTU2-XP.pmthresholds.path.nearend.1day.BBE	250 (count)	0 - 207273600
OTU2-XP.pmthresholds.path.nearend.15min.UAS	10 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.15min.SES	3 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.15min.ES	12 (seconds)	0 - 900
OTU2-XP.pmthresholds.path.nearend.15min.EB	15 (count)	0 - 7200000
OTU2-XP.pmthresholds.path.nearend.15min.BBE	25 (count)	0 - 2159100
OTU2-XP.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.otn.otnLines.G709OTN	Enable	Disable; Enable
OTU2-XP.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerWindow	30 (milliseconds)	10 - 10000

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.otn.proactiveProtectionRegen.standardfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.standardfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerWindow	30 (milliseconds)	10 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.TriggerThreshold	1.00E-03	1E-3; 9E-4; 8E-4 .. 1E-7
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertWindow	2000 (milliseconds)	2000 - 10000
OTU2-XP.otn.proactiveProtectionRegen.enhancedfec.RevertThreshold	1.00E-04	1E-4; 9E-5; 8E-5 .. 5E-8
OTU2-XP.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
OTU2-XP.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
OTU2-XP.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
OTU2-XP.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
OTU2-XP.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
OTU2-XP.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
OTU2-XP.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
OTU2-XP.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
OTU2-XP.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
OTU2-XP.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.mm.disabled fec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfe c.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.l1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.stm64.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.lx.disabledfec.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.ib5g.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mx.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.l1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.ir1 .disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2. disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gfibrechannel.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.sr.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.s2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.mm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.l1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowTxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighTxPower	7.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowTxPower	-5.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighTxPower	11.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.ir1.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i2.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.i1.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.er.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
OTU2-XP.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
OTU2-XP.config.port.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)

Table A-34 ETSI OTU2-XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
OTU2-XP.config.port.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SDH; 10G Ethernet; 10G Fiber Channel; IB_5G
OTU2-XP.config.port.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; SDH; Transparent when ppmPortAssignment 10G Ethernet; 10G Fiber Channel
OTU2-XP.config.port.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
OTU2-XP.config.port.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
OTU2-XP.config.port.OduTransparency	Cisco Extended Use	Transparent Standard Use; Cisco Extended Use
OTU2-XP.config.port.AisSquelchMode	Squelch	Ais; Squelch
OTU2-XP.config.port.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

A.4.1.3.11 ETSI SMR Card Default Settings

Table A-35 lists the SMR card default settings.

Note 40-SMR1-C and 40-SMR2-C cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-35 ETSI SMR Card Default Settings

Default Name	Default Value	Default Name
SMR1-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR1-40.config.card.WavelengthDrift	Enable	Disable; Enable
SMR2-40.config.card.AlsMode	Auto Restart	Disabled; Auto Restart
SMR2-40.config.card.WavelengthDrift	Enable	Disable; Enable

A.4.1.3.12 ETSI TXP_MR_10E Card Default Settings

Table A-36 lists the TXP_MR_10E card default settings.

Note TXP_MR_10E cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-36 ETSI TXP_MR_10E Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 764899200
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 7967700
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10E.pmthresholds.client.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.otnLines.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.otn.otnLines.G709OTN	Enable	Disable; Enable
TXP-MR-10E.otn.otnLines.FEC	Standard	Disable; Standard; Enhanced when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10E.otn.otnLines.AsynchSynchMapping	Synch Mapping	Asynch mapping; Synch Mapping
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10E.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10E.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10E.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10E.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10E.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10E.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.LowRxPower	-18.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-20.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	7.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowTxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-22.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.v2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.LowRxPower	-12.4 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.LowRxPower	-9.9 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.sr.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.sr.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s2.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.s1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.p1l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.l5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.LowTxPower	-4.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.LowTxPower	-40 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.LowRxPower	-40 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.HighTxPower	30 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.HighRxPower	30 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.1day.HighLaserBias	100 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.15min.LowTxPower	-40 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.15min.LowRxPower	-40 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l2.15min.HighTxPower	30 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.15min.HighRxPower	30 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l2.15min.HighLaserBias	100 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.l1.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.l1.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i5.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i3.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.LowTxPower	-8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.LowRxPower	-13 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighTxPower	1 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighRxPower	1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.LowTxPower	-12 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.LowRxPower	-11 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighTxPower	5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighRxPower	-1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.LowTxPower	-12 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.LowRxPower	-11 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighTxPower	5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighRxPower	-1 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i2.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.LowRxPower	-13.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.stm64.i1.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.stm64.i1.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.ib5g.lx.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowTxPower	-9.8 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.LowRxPower	-13.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighTxPower	1.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighRxPower	1.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowTxPower	-13.3 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.LowRxPower	-11.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighRxPower	-1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gfibrechannel.mm.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-2.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	0.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	6.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	0.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lw.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lrm.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.ew.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.LowRxPower	-18.3 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighTxPower	4.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighRxPower	4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.LowRxPower	-15.8 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighTxPower	8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighRxPower	2.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
TXP-MR-10E.opticalthresholds.client.10gethernet.er.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
TXP-MR-10E.config.trunk.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.config.trunk.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
TXP-MR-10E.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	6.0; 6.1; 6.2 .. 200.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.trunk.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00
TXP-MR-10E.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED; PPM (1 Port)
TXP-MR-10E.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED; SDH; 10G Ethernet; 10G Fiber Channel; IB_5G

Table A-36 ETSI TXP_MR_10E Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10E.config.client.TerminationMode	Transparent	Transparent; Regeneration Section; Multiplex Section when ppmPortAssignment UNASSIGNED; SDH; Transparent when ppmPortAssignment 10G Ethernet; 10G Fiber Channel
TXP-MR-10E.config.client.SyncMsgIn	TRUE	FALSE; TRUE
TXP-MR-10E.config.client.SendDoNotUse	FALSE	TRUE; FALSE
TXP-MR-10E.config.client.SFBER	1.00E-04	1E-3; 1E-4; 1E-5
TXP-MR-10E.config.client.SDBER	1.00E-07	1E-5; 1E-6; 1E-7; 1E-8; 1E-9
TXP-MR-10E.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
TXP-MR-10E.config.client.AlsRecoveryPulseDuration	2.0 (seconds)	2.0; 2.1; 2.2 .. 100.0 when AlsMode Disabled; Auto Restart; Manual Restart; 80.0; 80.1; 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10E.config.client.AlsMode	Disabled	Disabled; Auto Restart; Manual Restart; Manual Restart for Test
TXP-MR-10E.config.client.AisSquelchMode	Squelch	Ais; Squelch
TXP-MR-10E.config.client.AINSSoakTime	08:00 (hours:mins)	00:00; 00:15; 00:30 .. 48:00

A.4.1.3.13 ETSI TXP_MR_10G Card Default Settings

Table A-37 lists the TXP_MR_10G card default settings.

Note TXP_MR_10G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-37 ETSI TXP_MR_10G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-10G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 300
TXP-MR-10G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-10G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when mrPortAssignment UNASSIGNED, SDH; Transparent when mrPortAssignment 10G Ethernet
TXP-MR-10G.config.client.mrPortAssignment	UNASSIGNED	UNASSIGNED, SDH, 10G Ethernet
TXP-MR-10G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-10G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-10G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-10G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.client.stm64.lw.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.client.stm64.lw.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-22.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.HighTxPower	7.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-1.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-10G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-10G.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
TXP-MR-10G.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
TXP-MR-10G.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
TXP-MR-10G.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-10G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-10G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-10G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-10G.pmthresholds.client.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.ms.nearend.15min.UAS	3 (seconds)	0 - 900

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.client.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.SES	4 (seconds)	0 - 86400

Table A-37 ETSI TXP_MR_10G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-10G.pmthresholds.trunk.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.BBE	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.EB	85040 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.BBE	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.EB	850400 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.EB	10000 (count)	0 - 7967700
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.EB	100000 (count)	0 - 764899200
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-10G.pmthresholds.trunk.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.14 ETSI TXP_MR_2.5G Card Default Settings

Table A-38 lists the TXP_MR_2.5G card default settings.

Note TXP_MR_2.5Gcards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-38 ETSI TXP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when ppmPortAssignment UNASSIGNED, STM1, STM4, STM16; Transparent when ppmPortAssignment STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
TXP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm1.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm1.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm1.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm1.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm16.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm16.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm16.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm16.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.fecthresholds.stm4.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXP-MR-2_5G.otn.fecthresholds.stm4.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXP-MR-2_5G.otn.fecthresholds.stm4.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXP-MR-2_5G.otn.fecthresholds.stm4.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXP-MR-2_5G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXP-MR-2_5G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 137700

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.BBE	10000 (count)	0 - 13219200
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.BBE	10000 (count)	0 - 212371200
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900

Table A-38 ETSI TXP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 552600
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.BBE	10000 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.15 ETSI TXPP_MR_2.5G Card Default Settings

Table A-39 lists the TXPP_MR_2.5G card default settings.

Note TXPP_MR_2.5G cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXPP-MR-2_5G.config.client.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.client.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.client.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.config.client.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXPP-MR-2_5G.config.client.TerminationMode	Transparent	Transparent, Regeneration Section, Multiplex Section when ppmPortAssignment UNASSIGNED, STM1, STM4, STM16; Transparent when ppmPortAssignment STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.config.client.ppmPortAssignment	UNASSIGNED	UNASSIGNED, STM1, STM4, STM16, ONE-GE, ESCON, DV6000, SDI-D1-VIDEO, HDTV, PASS-THRU, ETR-CLO, ISC COMPAT, FC1G, FC2G, FICON1G, FICON2G, ISC PEER
TXPP-MR-2_5G.config.client.ppmSlotAssignment	UNASSIGNED	UNASSIGNED, PPM (1 Port)
TXPP-MR-2_5G.config.trunk.AINSSoakTime	08:00 (hours:mins)	00:00, 00:15, 00:30 .. 48:00
TXPP-MR-2_5G.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseDuration	40.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
TXPP-MR-2_5G.config.trunk.AlsRecoveryPulseInterval	100 (seconds)	60 - 300
TXPP-MR-2_5G.config.trunk.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.config.trunk.SFBER	1E-4	1E-3, 1E-4, 1E-5
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.cx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.dx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.hx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.t.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.vx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.1gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gfibrechannel.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowRxPower	-15.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.2gficon.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.dv6000.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.hdtv.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.mm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.isc3.sm.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighRxPower	-4.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.ir2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.lr3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.sdid1video.sr1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighRxPower	-10.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm1.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.i1.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.15min.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.HighTxPower	9.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.1day.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.HighTxPower	4.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowRxPower	-29.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l2.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.15min.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowRxPower	-18.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.1day.LowTxPower	-11.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowRxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s1.alarm.LowTxPower	-7.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm16.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.cwdm.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.i1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.15min.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighRxPower	-8.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.1day.LowTxPower	-21.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.HighTxPower	-6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.LowRxPower	-31.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l1.alarm.LowTxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.l3.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s1.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.client.stm4.s2.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowRxPower	-24.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.2r.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowRxPower	-25.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowRxPower	-28.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.disabledfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighRxPower	-9.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
TXPP-MR-2_5G.opticalthresholds.trunk.standardfec.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.BitErrorsCorrected	112500 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.BitErrorsCorrected	10800000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gethernet.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.BitErrorsCorrected	90000 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.BitErrorsCorrected	8640000 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.1gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.15min.UncorrectableWords	1 (count)	0 - 4724697600

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gfiberchannel.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.BitErrorsCorrected	180900 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.BitErrorsCorrected	17366400 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.2gficon.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm1.15min.BitErrorsCorrected	15012 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm1.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.stm1.1day.BitErrorsCorrected	1441152 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm1.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm16.15min.BitErrorsCorrected	225837 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm16.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.stm16.1day.BitErrorsCorrected	21680352 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm16.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.fecthresholds.stm4.15min.BitErrorsCorrected	56457 (count)	0 - 9033621811200
TXPP-MR-2_5G.otn.fecthresholds.stm4.15min.UncorrectableWords	1 (count)	0 - 4724697600
TXPP-MR-2_5G.otn.fecthresholds.stm4.1day.BitErrorsCorrected	5419872 (count)	0 - 867227693875200
TXPP-MR-2_5G.otn.fecthresholds.stm4.1day.UncorrectableWords	96 (count)	0 - 453570969600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.BBE	21260 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.BBE	212600 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.otn.otnLines.FEC	Enable	Disable, Enable when G709OTN Enable; Disable when G709OTN Disable
TXPP-MR-2_5G.otn.otnLines.G709OTN	Enable	Disable, Enable
TXPP-MR-2_5G.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.BBE	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.EB	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.BBE	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.EB	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.BBE	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.EB	1312 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.EB	13120 (count)	0 - 13219200

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.BBE	10000 (count)	0 - 137700
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.EB	10000 (count)	0 - 138600
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.BBE	10000 (count)	0 - 13219200
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.EB	100000 (count)	0 - 13305600
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm1.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.BBE	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.EB	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.BBE	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.EB	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.BBE	21260 (count)	0 - 2212200

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.EB	21260 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.BBE	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.EB	212600 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.BBE	10000 (count)	0 - 2212200
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.BBE	10000 (count)	0 - 212371200
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.EB	100000 (count)	0 - 206582400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm16.rs.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.BBE	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.EB	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.BBE	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.EB	53150 (count)	0 - 53136000

Table A-39 ETSI TXPP_MR_2.5G Card Default Settings (continued)

Default Name	Default Value	Default Domain
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.farend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.BBE	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.EB	5315 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.ES	87 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.SES	1 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.BBE	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.EB	53150 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.ES	864 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.SES	4 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.BBE	10000 (count)	0 - 552600
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.EB	10000 (count)	0 - 2151900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.ES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.SES	500 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.15min.UAS	3 (seconds)	0 - 900
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.BBE	10000 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.EB	100000 (count)	0 - 53136000
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
TXPP-MR-2_5G.pmthresholds.stm4.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.16 ETSI GE_XP Card Default Settings

Table A-40 lists the GE_XP card default settings.

Note GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-40 ETSI GE_XP Card Default Settings

Default Name	Default Value	Default Domain
XP-GE.config.card.Mode	10GE MXP	20GE MXP, 10GE MXP, L2 over DWDM
XP-GE.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-GE.config.client.CommittedInfoRate	100 (%)	0, 1, 2 .. 100
XP-GE.config.client.FlowControl	OFF	OFF, ON
XP-GE.config.client.MTU	9700	64, 65, 66 .. 9700
XP-GE.config.client.Speed	Auto	1000 Mbps, Auto
XP-GE.config.client.cEtherType	8100 (Hex)	Free form field
XP-GE.config.client.macLearningState	OFF	OFF, ON
XP-GE.config.client.niMode	UNI MODE	UNI MODE, NNI MODE
XP-GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-GE.config.client.sIngressCOS	0	0, 1, 2, 3, 4, 5, 6, 7, Trust
XP-GE.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-GE.config.trunk.CommittedInfoRate	100 (%)	0, 1, 2 .. 100
XP-GE.config.trunk.FlowControl	OFF	OFF, ON
XP-GE.config.trunk.MTU	9700	64, 65, 66 .. 9700
XP-GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.macLearningState	OFF	OFF, ON
XP-GE.config.trunk.niMode	NNI MODE	UNI MODE, NNI MODE
XP-GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-GE.config.trunk.sIngressCOS	0	0, 1, 2, 3, 4, 5, 6, 7, Trust
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighRxPower	-6.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.HighTxPower	8.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowRxPower	-32.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.cwdm.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighRxPower	-3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.HighTxPower	-1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.lx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.15min.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.HighTxPower	3.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowRxPower	-17.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.1day.LowTxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.HighTxPower	-2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowRxPower	-20.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.sx.alarm.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.15min.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.1day.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighLaserBias	100.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighRxPower	30.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.HighTxPower	30.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowRxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.1gethernet.zx.alarm.LowTxPower	-40.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTx Power	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRx Power	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTx Power	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRx Power	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTx Power	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRx Power	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTx Power	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRx Power	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowTxPower	-21.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.LowRxPower	-33.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighTxPower	-11.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighRxPower	-11.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowTxPower	-25.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.LowRxPower	-31.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighTxPower	-8.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighRxPower	-14.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.sx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowTxPower	-17.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.LowRxPower	-30.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighTxPower	-5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighRxPower	-5.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.1day.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowTxPower	-21.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.LowRxPower	-28.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighTxPower	-2.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighRxPower	-8.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.client.fastethernet.lx.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72

Table A-40 ETSI GE_XP Card Default Settings (continued)

Default Name	Default Value	Default Domain
XP-GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-GE.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-GE.otn.otnLines.G709OTN	Enable	Disable, Enable
XP-GE.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9

A.4.1.3.17 ETSI 10GE_XP Card Default Settings

Table A-41 lists the 10GE_XP card default settings.

Note 10GE_XP cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-41 **ETSI 10GE_XP Card Default Settings**

Default Name	Default Value	Default Domain
XP-10GE.config.card.Mode	10GE TXP	10GE TXP, L2 over DWDM
XP-10GE.config.client.AlsMode	Disabled	Disabled, Manual Restart, Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseDuration	4.0 (seconds)	2.0, 2.1, 2.2 .. 100.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.client.AlsRecoveryPulseInterval	100 (seconds)	100 - 2000
XP-10GE.config.client.CommittedInfoRate	100 (%)	0, 1, 2 .. 100
XP-10GE.config.client.FlowControl	OFF	OFF, ON
XP-10GE.config.client.MTU	9700	64, 65, 66 .. 9700
XP-10GE.config.client.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.client.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.macLearningState	OFF	OFF, ON
XP-10GE.config.client.niMode	UNI MODE	UNI MODE, NNI MODE
XP-10GE.config.client.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.client.sIngressCOS	0	0, 1, 2, 3, 4, 5, 6, 7, Trust
XP-10GE.config.trunk.AlsMode	Disabled	Disabled, Auto Restart, Manual Restart, Manual Restart for Test

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.config.trunk.AlsRecoveryPulseDuration	100.0 (seconds)	60.0, 60.1, 60.2 .. 200.0 when AlsMode Disabled, Auto Restart, Manual Restart; 80.0, 80.1, 80.2 .. 100.0 when AlsMode Manual Restart for Test
XP-10GE.config.trunk.AlsRecoveryPulseInterval	300 (seconds)	200 - 2000
XP-10GE.config.trunk.CommittedInfoRate	100 (%)	0, 1, 2 .. 100
XP-10GE.config.trunk.FlowControl	OFF	OFF, ON
XP-10GE.config.trunk.MTU	9700	64, 65, 66 .. 9700
XP-10GE.config.trunk.Speed	10000 Mbps	10000 Mbps
XP-10GE.config.trunk.cEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.macLearningState	OFF	OFF, ON
XP-10GE.config.trunk.niMode	NNI MODE	UNI MODE, NNI MODE
XP-10GE.config.trunk.sEtherType	8100 (Hex)	Free form field
XP-10GE.config.trunk.sIngressCOS	0	0, 1, 2, 3, 4, 5, 6, 7, Trust
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.cwdm40km.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.lr2.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.alarm.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.1day.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowTxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.LowRxPower	-40.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighTxPower	30.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighRxPower	30.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.sr.15min.HighLaserBias	100.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighLaserBias	81.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowRxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.15min.LowTxPower	-6.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighLaserBias	85.5 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighRxPower	0.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowRxPower	0.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.1day.LowTxPower	-6.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighLaserBias	90.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighRxPower	2.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.HighTxPower	2.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowRxPower	-2.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.client.10gethernet.zr.alarm.LowTxPower	-2.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowTxPower	0.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.LowRxPower	-16.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighTxPower	9.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowTxPower	-3.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighTxPower	13.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.cwdm40km.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowRxPower	-23.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowRxPower	-26.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.disabledfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowRxPower	-30.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.enhancedfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.15min.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.HighTxPower	6.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.1day.LowTxPower	-4.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighRxPower	-5.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowRxPower	-30.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.dwdm.standardfec.alarm.LowTxPower	-3.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.standardfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowTxPower	-3.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.LowRxPower	-29.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighTxPower	5.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowTxPower	-7.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.LowRxPower	-27.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighTxPower	9.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.enhancedfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowTxPower	-2.5 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.LowRxPower	-26.5 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighTxPower	6.5 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighRxPower	-4.5 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.1day.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowTxPower	-6.0 (dBm)	-40.0; -39.9; -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.LowRxPower	-24.0 (dBm)	-40.0; -39.9; -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighTxPower	10.0 (dBm)	LowTxPower; LowTxPower + 0.1; LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighRxPower	-7.0 (dBm)	LowRxPower; LowRxPower + 0.1; LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.lr2.disabledfec.15min.HighLaserBias	98.0 (%)	0.0; 0.1; 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighLaserBias	95.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.15min.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighLaserBias	96.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighRxPower	1.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.HighTxPower	5.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowRxPower	-14.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.1day.LowTxPower	-12.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighLaserBias	98.0 (%)	0.0, 0.1, 0.2 .. 100.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighRxPower	3.0 (dBm)	LowRxPower, LowRxPower + 0.1, LowRxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.HighTxPower	1.0 (dBm)	LowTxPower, LowTxPower + 0.1, LowTxPower + 0.2 .. 30.0
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowRxPower	-16.0 (dBm)	-40.0, -39.9, -39.8 .. HighRxPower
XP-10GE.opticalthresholds.trunk.10gethernet.zr.disabledfec.alarm.LowTxPower	-8.0 (dBm)	-40.0, -39.9, -39.8 .. HighTxPower
XP-10GE.otn.fecthresholds.enhanced.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.enhanced.15min.UncorrectableWords	5 (count)	0 - 4724697600
XP-10GE.otn.fecthresholds.enhanced.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.enhanced.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.fecthresholds.standard.15min.BitErrorsCorrected	903330 (count)	0 - 9033621811200
XP-10GE.otn.fecthresholds.standard.15min.UncorrectableWords	5 (count)	0 - 4724697600

Table A-41 **ETSI 10GE_XP Card Default Settings** ***(continued)***

Default Name	Default Value	Default Domain
XP-10GE.otn.fecthresholds.standard.1day.BitErrorsCorrected	86719680 (count)	0 - 867227693875200
XP-10GE.otn.fecthresholds.standard.1day.UncorrectableWords	480 (count)	0 - 453570969600
XP-10GE.otn.g709thresholds.pm.farend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.farend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.farend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.farend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.farend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.farend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.farend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.15min.BBE	85040 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.pm.nearend.15min.ES	87 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.pm.nearend.15min.SES	1 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.15min.UAS	3 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.pm.nearend.1day.BBE	850400 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.pm.nearend.1day.ES	864 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.pm.nearend.1day.SES	4 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.pm.nearend.1day.UAS	10 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.farend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.farend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.farend.15min.UAS	500 (seconds)	0 - 900

Table A-41 **ETSI 10GE_XP Card Default Settings** *(continued)*

Default Name	Default Value	Default Domain
XP-10GE.otn.g709thresholds.sm.farend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.farend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.farend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.farend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.15min.BBE	10000 (count)	0 - 8850600
XP-10GE.otn.g709thresholds.sm.nearend.15min.ES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.FC	10 (count)	0 - 72
XP-10GE.otn.g709thresholds.sm.nearend.15min.SES	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.15min.UAS	500 (seconds)	0 - 900
XP-10GE.otn.g709thresholds.sm.nearend.1day.BBE	100000 (count)	0 - 849657600
XP-10GE.otn.g709thresholds.sm.nearend.1day.ES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.FC	40 (count)	0 - 6912
XP-10GE.otn.g709thresholds.sm.nearend.1day.SES	5000 (seconds)	0 - 86400
XP-10GE.otn.g709thresholds.sm.nearend.1day.UAS	5000 (seconds)	0 - 86400
XP-10GE.otn.otnLines.FEC	Standard	Disable, Standard, Enhanced when G709OTN Enable; Disable when G709OTN Disable
XP-10GE.otn.otnLines.G709OTN	Enable	Disable, Enable
XP-10GE.otn.otnLines.SDBER	1E-7	1E-5, 1E-6, 1E-7, 1E-8, 1E-9

A.4.1.3.18 ETSI OSCM Card Default Settings

Table A-42 lists the OSCM card default settings.

Note OSCM cards are supported only on the Cisco ONS 15454 platform.

Table A-42 ETSI OSCM Card Default Settings

Default Name	Default Value	Default Domain
OSCM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSCM.pmthresholds.ms.farend.15min.BBE	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.farend.15min.EB	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.farend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.ms.farend.1day.BBE	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.farend.1day.EB	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.farend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.ms.farend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.15min.BBE	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.nearend.15min.EB	1312 (count)	0 - 137700
OSCM.pmthresholds.ms.nearend.15min.ES	87 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.15min.SES	1 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.nearend.1day.EB	13120 (count)	0 - 13219200
OSCM.pmthresholds.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OSCM.pmthresholds.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.15min.BBE	10000 (count)	0 - 138600
OSCM.pmthresholds.rs.nearend.15min.EB	10000 (count)	0 - 138600
OSCM.pmthresholds.rs.nearend.15min.ES	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.OFS	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.SES	500 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OSCM.pmthresholds.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
OSCM.pmthresholds.rs.nearend.1day.EB	100000 (count)	0 - 13305600
OSCM.pmthresholds.rs.nearend.1day.ES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.1day.OFS	5000 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OSCM.pmthresholds.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.19 ETSI OSC-CSM Card Default Settings

Table A-43 lists the OSC-CSM card default settings.

Note OSC-CSM cards are supported on the Cisco ONS 15454, Cisco ONS 15454 M2 and Cisco ONS 15454 M6 platforms.

Table A-43 ETSI OSC-CSM Card Default Settings

Default Name	Default Value	Default Domain
OSC_CSM.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OSC_CSM.pmthresholds.ms.farend.15min.BBE	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.farend.15min.EB	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.farend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.farend.1day.BBE	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.farend.1day.EB	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.farend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.farend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.farend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.15min.BBE	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.nearend.15min.EB	1312 (count)	0 - 137700
OSC_CSM.pmthresholds.ms.nearend.15min.ES	87 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.15min.SES	1 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.ms.nearend.1day.BBE	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.nearend.1day.EB	13120 (count)	0 - 13219200
OSC_CSM.pmthresholds.ms.nearend.1day.ES	864 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.1day.SES	4 (seconds)	0 - 86400
OSC_CSM.pmthresholds.ms.nearend.1day.UAS	10 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.15min.BBE	10000 (count)	0 - 138600
OSC_CSM.pmthresholds.rs.nearend.15min.EB	10000 (count)	0 - 138600
OSC_CSM.pmthresholds.rs.nearend.15min.ES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.15min.OFS	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.15min.SES	500 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.15min.UAS	3 (seconds)	0 - 900
OSC_CSM.pmthresholds.rs.nearend.1day.BBE	100000 (count)	0 - 13305600
OSC_CSM.pmthresholds.rs.nearend.1day.EB	100000 (count)	0 - 13305600
OSC_CSM.pmthresholds.rs.nearend.1day.ES	5000 (seconds)	0 - 86400

Table A-43 ETSI OSC-CSM Card Default Settings (continued)

Default Name	Default Value	Default Domain
OSC_CSM.pmthresholds.rs.nearend.1day.OFS	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.1day.SES	5000 (seconds)	0 - 86400
OSC_CSM.pmthresholds.rs.nearend.1day.UAS	10 (seconds)	0 - 86400

A.4.1.3.20 ETSI Amplifier Card Default Settings

Table A-44 lists the OPT-BST, OPT-AMP-17-C, and OPT-BST-L card default settings.

Note The OPT-BST-L card is supported only on the Cisco ONS 15454 platform. The OPT-BST and OPT-AMP cards are supported on the Cisco ONS 15454 , Cisco ONS 15454 M2, and Cisco ONS 15454 M6 platforms.

Table A-44 ETSI Amplifier Card Default Settings

Default Name	Default Value	Default Domain
OPT-AMP-17-C.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST-L.config.card.AlsMode	Auto Restart	Disabled, Auto Restart
OPT-BST.config.card.AlsMode	Auto Restart	Disabled, Auto Restart

A.4.2 ETSI Node Default Settings

Table A-45 on page A-1058 lists the Cisco ONS 15454 node-level default settings for the ETSI shelf assembly. Cisco provides the following types of user-configurable defaults for each Cisco ONS 15454 node:

Note The node default settings described in this section are supported on the Cisco ONS 15454, Cisco ONS 15454 M6, Cisco ONS 15454 M2 platforms, unless noted otherwise.

- Circuit settings—Set the administrative state, subnetwork connection protection (SNCP) circuit threshold levels for signal degradation and failure, SNCP reversion time, and whether SNCP circuits are revertive by default.
- General settings—Set general node management defaults, including whether to use Daylight Savings Time (DST), the IP address of the NTP/SNTP server to be used, the time zone where the node is located, the SD path BER value, whether automatic autonomous TL1 reporting of PM data is enabled for cross-connect paths on the node, whether or not to allow ports to be disabled when they are providing services (when the default is set to FALSE users must remove or disable the services first, then put the ports out of service), and the defaults description.
- Link Management Protocol settings—Set link management protocol data link type, traffic engineering link, and general settings.
- Power Monitor settings—Set default voltage thresholds for the node.

- Network settings—Set whether to prevent display of node IP addresses in CTC (applicable for all users except Superusers); default gateway node type; whether to raise an alarm when the backplane LAN cable is disconnected; and whether to display the IP address in the LCD in an editable mode (in which you can change the IP address directly from LCD screen), to display the IP address on the LCD as read-only, or to suppress display of the IP on the LCD entirely.
- OSI settings—Set the Open System Interconnection (OSI) main setup, generic routing encapsulation (GRE) tunnel default, the link access protocol on the D channel (LAP-D), the router subnet, and the TID address resolution protocol (TARP) settings.
- Linear Multiplex Section Protection (LMSP) settings—Set whether or not protected circuits have bidirectional switching, are revertive, and what the reversion time is.
- MS-SPRing protection settings—Set whether MS-SPRing-protected circuits are revertive, and what the reversion time is, at both the ring and span levels.
- Y Cable protection settings—Set whether Y-cable protected circuits are revertive, and what the reversion time is.
- Splitter protection settings—Set whether splitter protected circuits are revertive, and what the reversion time is.
- Legal Disclaimer—Set the legal disclaimer that warns users at the login screen about the possible legal or contractual ramifications of accessing equipment, systems, or networks without authorization.
- Security Grant Permissions—Set default user security levels for activating/reverting software, PM data clearing, database restoring, and retrieving audit logs.
- Security DataComm settings—Set default security settings for TCC Ethernet IP address and IP netmask, and CTC backplane IP suppression; set secure mode on and secure mode locked (for TCC2P cards only).
- Security Access settings—Set default security settings for LAN access, shell access, serial craft access, element management system (EMS) access (including Internet Inter-Object Request Broker Protocol [IIOP] listener port number), TL1 access, and SNMP access.
- Security RADIUS settings—Set default RADIUS server settings for the accounting port number and the authentication port number, and whether to enable the node as a final authenticator.
- Security Policy settings—Set the allowable failed logins before lockout, idle user timeout for each user level, optional lockout duration or manual unlock enabled, password reuse and change frequency policies, number of characters difference that is required between the old and new password, password aging by security level, enforced single concurrent session per user, and option to disable inactive user after a set inactivity period.
- Security Password settings—Set when passwords can be changed, how many characters they must differ by, whether or not password reuse is allowed, and whether a password change is required on first login to a new account; set password aging enforcement and user-level specific aging and warning periods; set how many consecutive identical characters are allowed in a password, maximum password length, minimum password length, minimum number and combination of nonalphabetical characters required, and whether or not to allow a password that is a reversal of the login ID associated with the password.
- BITS Timing settings—Set the AIS threshold, Admin synchronization status messaging (SSM), coding, facility type, framing, state, and Sa bit (the overhead bit that will carry the SSM) for building integrated timing supply 1 (BITS-1) and BITS2 timing.
- General Timing settings—Set the mode (External, Line, or Mixed), revertive, and reversion time.

Note Any node level defaults changed using the **Provisioning > Defaults** tab, changes existing node level provisioning. Although this is service affecting, it depends on the type of defaults changed, for example, general, and all timing and security attributes. The "Changing default values for some node level attributes overrides the current provisioning." message is displayed. The Side Effects column of the Defaults editor (right-click a column header and select **Show Column > Side Effects**) explains the effect of changing the default values. However, when the card level defaults are changed using the **Provisioning > Defaults** tab, existing card provisioning remains unaffected.

Note For more information about each individual node setting, refer to the "Manage the Node" chapter in the *Cisco ONS 15454 DWDM Procedure Guide*.

Note Refer to the A.3 CTC Default Settings, page A-562 for CTC-level default settings for the Cisco ONS 15454.

Table A-45 ETSI Node Default Settings

Default Name	Default Value	Default Domain
NODE.circuits.State	unlocked, automaticInService	unlocked, locked, disabled, locked, maintenance, unlocked, automaticInService
NODE.circuits.sncp.HO_SDBER	1E-6	1E-5, 1E-6, 1E-7, 1E-8, 1E-9
NODE.circuits.sncp.HO_SFBER	1E-4	1E-3, 1E-4, 1E-5
NODE.circuits.sncp.LO_SDBER	1E-6	1E-5, 1E-6, 1E-7, 1E-8
NODE.circuits.sncp.LO_SFBER	1E-4	1E-3, 1E-4, 1E-5
NODE.circuits.sncp.ProvisionWorkingGoAndReturnOnPrimaryPath	FALSE	TRUE, FALSE
NODE.circuits.sncp.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.circuits.sncp.Revertive	FALSE	TRUE, FALSE
NODE.general.AllowServiceAffectingPortChangeToDisabled	TRUE	FALSE, TRUE
NODE.general.AutoPM (only Cisco ONS 15454)	FALSE	FALSE, TRUE
NODE.general.BackupNtpSntpServer	0.0.0.0	IP Address
NODE.general.DefaultsDescription	Factory Defaults	Free form field
NODE.general.NtpSntpServer	0.0.0.0	IP Address
NODE.general.ReportLoopbackConditionsOnLocked,MaintenancePorts	FALSE	FALSE, TRUE

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.general.TimeZone	(GMT-08:00) Pacific Time (US & Canada), Tijuana	(For applicable time zones, see Table A-23 on page A-560.)
NODE.general.UseDST	TRUE	TRUE, FALSE
NODE.general.mvAirFilterBasedFanEnable	FALSE	TRUE, FALSE
NODE.lmp.controlChannel.AdminState	locked, disabled	unlocked, locked, disabled
NODE.lmp.controlChannel.HelloDeadInterval	12000 (ms)	maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)), maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 1, maximum_of(2000,MinHelloDeadInterval,product_of(HelloInterval,3)) + 2 .. minimum_of(20000,MaxHelloDeadInterval)
NODE.lmp.controlChannel.HelloInterval	500 (ms)	maximum_of(300,MinHelloInterval), maximum_of(300,MinHelloInterval) + 1, maximum_of(300,MinHelloInterval) + 2 .. minimum_of(5000,MaxHelloInterval,quotient_of(HelloDeadInterval,3))

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.controlChannel.MaxHelloDeadInterval	20000 (ms)	maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)), maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 1, maximum_of(2000,HelloDeadInterval,sum_of(MaxHelloInterval,1)) + 2 .. 20000
NODE.lmp.controlChannel.MaxHelloInterval	2000 (ms)	maximum_of(300,HelloInterval), maximum_of(300,HelloInterval) + 1, maximum_of(300,HelloInterval) + 2 .. minimum_of(5000,difference_of(MaxHelloDeadInterval,1))
NODE.lmp.controlChannel.MinHelloDeadInterval	2000 (ms)	maximum_of(2000,sum_of(MinHelloInterval,1)), maximum_of(2000,sum_of(MinHelloInterval,1)) + 1, maximum_of(2000,sum_of(MinHelloInterval,1)) + 2 .. minimum_of(20000,HelloDeadInterval)
NODE.lmp.controlChannel.MinHelloInterval	300 (ms)	300, 301, 302 .. minimum_of(5000,HelloInterval, difference_of(MinHelloDeadInterval,1))

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.lmp.dataLink.Type	Port	Port, Component
NODE.lmp.general.Allowed	TRUE	FALSE, TRUE
NODE.lmp.general.Enabled	FALSE	FALSE, TRUE when Allowed TRUE; FALSE when Allowed FALSE
NODE.lmp.general.LMP-WDM	TRUE	FALSE, TRUE
NODE.lmp.general.Role	OLS	PEER, OLS
NODE.lmp.teLink.AdminState	locked, disabled	unlocked, locked, disabled
NODE.lmp.teLink.DWDM	TRUE	FALSE, TRUE
NODE.lmp.teLink.MuxCapability	Lambda Switch	Packet Switch - Level 1, Packet Switch - Level 2, Packet Switch - Level 3, Packet Switch - Level 4, Layer 2 Switch, TDM Cross-connect, Lambda Switch, Fiber Switch
NODE.network.general.AlarmMissingBackplaneLAN	FALSE	TRUE, FALSE
NODE.network.general.CtcIpDisplaySuppression	FALSE	TRUE, FALSE
NODE.network.general.GatewaySettings	None	LeaveAsIs, None, ENE, GNE, ProxyOnlyNode
NODE.network.general.LcdSetting	Allow Configuration	Allow Configuration, Display Only, Suppress Display
NODE.osi.greTunnel.OspfCost	110	110 - 65535
NODE.osi.greTunnel.SubnetMask	24 (bits)	8, 9, 10 .. 32
NODE.osi.lapd.MTU	512	512, 513, 514 .. 1500
NODE.osi.lapd.Mode	AITS	AITS, UITS
NODE.osi.lapd.Role	Network	Network, User
NODE.osi.lapd.T200	200 (ms)	200, 300, 400 .. 20000

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.osi.lapd.T203	10000 (ms)	4000, 4100, 4200 .. 120000
NODE.osi.mainSetup.L1L2LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.L1LSPBufferSize	512 (bytes)	512 - 1500
NODE.osi.mainSetup.NodeRoutingMode	Intermediate System Level 1	End System, Intermediate System Level 1, Intermediate System Level 1/Level 2
NODE.osi.subnet.DISPriority	63	1, 2, 3 .. 127
NODE.osi.subnet.ESH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.GCCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.IIH	3 (sec)	1, 2, 3 .. 600
NODE.osi.subnet.ISH	10 (sec)	10, 20, 30 .. 1000
NODE.osi.subnet.LANISISCost	20	1, 2, 3 .. 63
NODE.osi.subnet.LDCCISISCost	40	1, 2, 3 .. 63
NODE.osi.subnet.OSCISISCost	60	1, 2, 3 .. 63
NODE.osi.subnet.SDCCISISCost	60	1, 2, 3 .. 63
NODE.osi.tarp.L1DataCache	TRUE	FALSE, TRUE
NODE.osi.tarp.L2DataCache	FALSE	FALSE, TRUE
NODE.osi.tarp.LANStormSuppression	TRUE	FALSE, TRUE
NODE.osi.tarp.LDB	TRUE	FALSE, TRUE
NODE.osi.tarp.LDBEntry	5 (min)	1 - 10
NODE.osi.tarp.LDBFlush	5 (min)	0 - 1440
NODE.osi.tarp.PDUsL1Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsL2Propagation	TRUE	FALSE, TRUE
NODE.osi.tarp.PDUsOrigination	TRUE	FALSE, TRUE
NODE.osi.tarp.T1Timer	15 (sec)	0 - 3600
NODE.osi.tarp.T2Timer	25 (sec)	0 - 3600
NODE.osi.tarp.T3Timer	40 (sec)	0 - 3600
NODE.osi.tarp.T4Timer	20 (sec)	0 - 3600
NODE.osi.tarp.Type4PDUDelay	0 (sec)	0 - 255
NODE.powerMonitor.EHIBATVG_48V	-56.5 (Vdc)	-40.5, -41.0, -41.5 .. -57.0
NODE.powerMonitor.EHIBATVG_60V	-72.0 (Vdc)	-50.0, -50.5, -51.0 .. -72.0
NODE.powerMonitor.ELWBATVG_48V	-40.5 (Vdc)	-40.5, -41.0, -41.5 .. -56.5

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.powerMonitor.ELWBATVG_60V	-50.0 (Vdc)	-50.0, -50.5, -51.0 .. -72.0
NODE.protection.lmsp.BidirectionalSwitching	FALSE	TRUE, FALSE
NODE.protection.lmsp.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.lmsp.Revertive	FALSE	TRUE, FALSE
NODE.protection.msspr.RingReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.msspr.RingRevertive	TRUE	TRUE, FALSE
NODE.protection.msspr.SpanReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.msspr.SpanRevertive	TRUE	TRUE, FALSE
NODE.protection.splitter.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.splitter.Revertive	FALSE	TRUE, FALSE
NODE.protection.ycable.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.protection.ycable.Revertive	FALSE	TRUE, FALSE
NODE.security.dataComm.CtcBackplaneIpDisplaySuppression	NOT SUPPORTED	FALSE; TRUE when nothing TRUE; (NOT SUPPORTED) when nothing FALSE
NODE.security.dataComm.DefaultTCCEthernetIP	10.0.0.1	IP Address
NODE.security.dataComm.DefaultTCCEthernetIPNetmask	24 (bits)	8, 9, 10 .. 32
NODE.security.dataComm.LcdBackplaneIpSetting	NOT SUPPORTED	Allow Configuration; Display Only; Suppress Display when nothing TRUE; (NOT SUPPORTED) when nothing FALSE

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.dataComm.SecureModeLocked	NOT SUPPORTED	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE
NODE.security.dataComm.SecureModeOn (May reboot node)	NOT SUPPORTED	FALSE, TRUE when isSecureModeSupportedOnControlCard TRUE; (NOT SUPPORTED) when isSecureModeSupportedOnControlCard FALSE
NODE.security.dataComm.isSecureModeSupportedOnControlCard	TRUE	FALSE, TRUE
NODE.security.emsAccess.AccessState	NonSecure	NonSecure, Secure
NODE.security.emsAccess.IIOPListenerPort (May reboot node)	57790 (port #)	0 - 65535
NODE.security.grantPermission.ActivateRevertSoftware	Superuser	Provisioning, Superuser
NODE.security.grantPermission.PMClearingPrivilege	Provisioning	Provisioning, Superuser
NODE.security.grantPermission.RestoreDB	Superuser	Provisioning, Superuser
NODE.security.grantPermission.RetrieveAuditLog	Superuser	Provisioning, Superuser
NODE.security.idleUserTimeout.Maintenance	01:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Provisioning	00:30 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Retrieve	00:00 (hours:mins)	00:00, 00:01, 00:02 .. 16:39
NODE.security.idleUserTimeout.Superuser	00:15 (hours:mins)	00:00, 00:01, 00:02 .. 16:39

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.lanAccess.LANAccess (May disconnect CTC from node)	Front & Backplane	No LAN Access, Front Only, Backplane Only, Front & Backplane
NODE.security.lanAccess.LANAccess (only Cisco ONS 15454 M2 and Cisco ONS 15454 M6)	Front Craft & EMS	No LAN Access; Front & Craft; EMS Only; Front Craft & EMS
NODE.security.lanAccess.RestoreTimeout	5 (minutes)	0 - 60
NODE.security.legalDisclaimer.LoginWarningMessage	<html> WARNING This system is restricted to authorized users for business purposes. Unauthorized <p>access is a violation of the law. This service may be monitored for administrative <p>and security reasons. By proceeding, you consent to this monitoring.	Free form field
NODE.security.other.DisableInactiveUser	FALSE	FALSE, TRUE
NODE.security.other.InactiveDuration	45 (days)	1, 2, 3 .. 99 when nothing TRUE; 45 when nothing FALSE
NODE.security.other.PreventInactiveSuperuserDisable	FALSE	TRUE, FALSE
NODE.security.other.SingleSessionPerUser	FALSE	TRUE, FALSE
NODE.security.passwordAging.EnforcePasswordAging	FALSE	TRUE, FALSE
NODE.security.passwordAging.maintenance.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.maintenance.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.provisioning.AgingPeriod	45 (days)	20 - 90

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.passwordAging.provisioning.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.retrieve.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.retrieve.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordAging.superuser.AgingPeriod	45 (days)	20 - 90
NODE.security.passwordAging.superuser.WarningPeriod	5 (days)	2 - 20
NODE.security.passwordChange.CannotChangeNewPassword	FALSE	TRUE, FALSE
NODE.security.passwordChange.CannotChangeNewPasswordForNDays	20 (days)	20 - 95
NODE.security.passwordChange.NewPasswordMustDifferFromOldByNCharacters	1 (characters)	1 - 5
NODE.security.passwordChange.PreventReusingLastNPasswords	1 (times)	1 - 10
NODE.security.passwordChange.RequirePasswordChangeOnFirstLoginToNewAccount	FALSE	TRUE, FALSE
NODE.security.passwordComplexity.IdenticalConsecutiveCharactersAllowed	3 or more	0-2, 3 or more
NODE.security.passwordComplexity.MaximumLength	20	20, 80
NODE.security.passwordComplexity.MinimumLength	6	6, 8, 10, 12
NODE.security.passwordComplexity.MinimumRequiredCharacters	1 num, 1 letter & 1 TL1 special	1 num, 1 letter & 1 TL1 special, 1 num, 1 letter & 1 special, 2 each of any 2 of num, upper, lower & TL1 special, 2 each of any 2 of num, upper, lower & special
NODE.security.passwordComplexity.ReverseUserIdAllowed	TRUE	TRUE, FALSE
NODE.security.radiusServer.AccountingPort	1813 (port)	0 - 32767
NODE.security.radiusServer.AuthenticationPort	1812 (port)	0 - 32767
NODE.security.radiusServer.EnableNodeAsFinalAuthenticator	TRUE	FALSE, TRUE
NODE.security.serialCraftAccess.EnableCraftPort	TRUE	TRUE, FALSE
NODE.security.shellAccess.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.shellAccess.EnableShellPassword	FALSE	TRUE, FALSE
NODE.security.shellAccess.TelnetPort	23	23 - 9999
NODE.security.snmpAccess.AccessState	NonSecure	Disabled, NonSecure
NODE.security.tl1Access.AccessState	NonSecure	Disabled, NonSecure, Secure
NODE.security.userLockout.FailedLoginsAllowedBeforeLockout	5 (times)	0 - 10

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.security.userLockout.LockoutDuration	00:30 (mins:secs)	00:00, 00:05, 00:10 .. 10:00
NODE.security.userLockout.ManualUnlockBySuperuser	FALSE	TRUE, FALSE
NODE.software.AllowDelayedUpgrades	FALSE	FALSE, TRUE
NODE.software.DefaultDelayedUpgrades	FALSE	FALSE, TRUE when AllowDelayedUpgrades TRUE; FALSE when AllowDelayedUpgrades FALSE
NODE.timing.bits-1.AISThreshold	DUS	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-1.AdminSSMIn	STU	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-1.Coding	HDB3	HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-1.CodingOut	HDB3	HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-1.FacilityType	E1	E1, 64kHz+8kHz, 2MHz
NODE.timing.bits-1.FacilityTypeOut	E1	E1, 6MHz, 2MHz

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-1.Framing	FAS+CAS+CRC	FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed, Unframed - 2Mhz when FacilityType 64kHz+8kHz
NODE.timing.bits-1.FramingOut	FAS+CAS+CRC	FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed, Unframed - 2Mhz when FacilityTypeOut 6MHz
NODE.timing.bits-1.SaBit	4	4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-1.State	unlocked	unlocked, locked, disabled
NODE.timing.bits-1.StateOut	unlocked	unlocked, locked, disabled

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.AISThreshold	DUS	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-2.AdminSSMIn	STU	G811, STU, G812T, G812L, SETS, DUS
NODE.timing.bits-2.Coding	HDB3	HDB3, AMI when FacilityType E1; N/A when FacilityType 2MHz; AMI when FacilityType 64kHz+8kHz
NODE.timing.bits-2.CodingOut	HDB3	HDB3, AMI when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; AMI when FacilityTypeOut 6MHz
NODE.timing.bits-2.FacilityType	E1	E1, 64kHz+8kHz, 2MHz
NODE.timing.bits-2.FacilityTypeOut	E1	E1, 6MHz, 2MHz
NODE.timing.bits-2.Framing	FAS+CAS+CRC	FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityType E1; N/A when FacilityType 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed, Unframed - 2Mhz when FacilityType 64kHz+8kHz

Table A-45 ETSI Node Default Settings (continued)

Default Name	Default Value	Default Domain
NODE.timing.bits-2.FramingOut	FAS+CAS+CRC	FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed when FacilityTypeOut E1; N/A when FacilityTypeOut 2MHz; FAS+CRC, FAS+CAS, FAS+CAS+CRC, FAS, Unframed, Unframed - 2Mhz when FacilityTypeOut 6MHz
NODE.timing.bits-2.SaBit	4	4, 5, 6, 7, 8 when FacilityType E1; N/A when FacilityType 2MHz; N/A when FacilityType 64kHz+8kHz
NODE.timing.bits-2.State	unlocked	unlocked, locked, disabled
NODE.timing.bits-2.StateOut	unlocked	unlocked, locked, disabled
NODE.timing.general.Mode	External	External, Line, Mixed
NODE.timing.general.ReversionTime	5.0 (minutes)	0.5, 1.0, 1.5 .. 12.0
NODE.timing.general.Revertive	FALSE	TRUE, FALSE