

Cisco IOS Release 15.9(3)M7a - Release Notes for Cisco IR800 Industrial Integrated Services Routers and Cisco CGR1000 Series Connected Grid Routers

First Published: 2023-03-26

Introduction

The following release notes support the Cisco IOS 15.9(3)M7a release. These release notes are updated to describe new features, limitations, troubleshooting, recommended configurations, caveats, and provide information on how to obtain support and documentation.

PSIRT ADVISORY

IMPORTANT INFORMATION - PLEASE READ!

FPGA and BIOS have been signed and updated to new versions.

For the 15.9 Release Train, this image (15.9-3.M) is considered as the baseline. Downgrade is **STRICTLY UNSUPPORTED** and bundle install to previous releases (158-3.M2a/157-3.M4b/156-3.M6b) will cause an error and fail if attempted. Any manual downgrade [non bundle operations] will impair router functionality thereafter.



Note After upgrading to this release, make sure to delete any old image files that may still be in the flash: filesystem. This will prevent an unintended IOS downgrade.

For additional information on the PSIRT see the following:

<https://tools.cisco.com/security/center/content/CiscoSecurityAdvisory/cisco-sa-20190513-secureboot>

Image Information and Supported Platforms



Note You must have a Cisco.com account to download the software.

Cisco IOS Release 15.9(3)M7a includes the following Cisco IOS images:

IR8x9

System Bundled Image: ir800-universalk9-bundle.SPA.159-3.M7a

This bundle contains the following components:

- IOS: ir800-universalk9-mz.SPA.159-3.M7a
- Guest Operating System: ir800-ref-gos.img.1.15.0.8.gz
- Hypervisor: ir800-hv.srp.SPA.3.1.35
- FPGA: 2.B.0
- BIOS: 29
- MCU Application: 53

IR807

IOS Image: ir800l-universalk9-mz.SPA.159-3-M7a

CGR1K

System Bundled image: cgr1000-universalk9-bundle.SPA.159-3-M7a

This bundle contains the following components:

- IOS Version: cgr1000-universalk9-mz.SPA.159-3-M7a
- Guest Operating System: cgr1000-ref-gos.img.1.8.2.22.gz
- Hypervisor: cgr1000-hv.srp.SPA.3.0.69
- FPGA: 2.E.0
- BIOS: 18

Important Note Regarding 159-3.M7a

CG-OS to IOS Migration:



Note When migrating from CG-OS to IOS on the CGR1K, Cisco recommends to upgrading from the Golden image to the required IOS image. Refer to the following example:

CG-OS -> 15.8(3)M3b -> <latest version>

Software Downloads

This section contains the following:

IR800 Series

The latest image files for the IR800 product family can be found here:

<https://software.cisco.com/download/navigator.html?mdfid=286287045&flowid=75322>

Click on the 807, 809 or 829 link to take you to the specific software you are looking for.



Important MANUAL [non-bundle] DOWNGRADE IS STRICTLY PROHIBITED. For newer releases with the PSIRT fix - while bundle downgrade to 158-3.M2a/157-3.M4b/156-3.M6b is supported, manual downgrade is unsupported.



Note On the IR8x9 devices, the IR800 bundle image can be copied via Trivial File Transfer Protocol (TFTP) or SCP to the IR800, and then installed using the bundle install flash:<image name> command. The IR800 <image>.bin file can NOT be directly booted using the boot system flash:/image_name. Detailed instructions are found in the [Cisco IR800 Integrated Services Router Software Configuration Guide](#).



Note On the IR8x9 devices, the cipher **dhe-aes-256-cbc-sha** (which is used with the commands **ip http client secure-ciphersuite** and **ip http secure-ciphersuite**) is no longer available in IOS 15.6(3)M and later as part of the weak cipher removal process. This cipher was flagged as a security vulnerability.

IR807

The IR807 link shows the following entries:

- ir800l-universalk9-mz.SPA.<version> .bin
- ir800l-universalk9_npe-mz.SPA.<version> .bin

IR809

The IR809 link shows the following entries:

- IOS Software
 - ir800-universalk9-bundle.<version> .bin
 - ir800-universalk9_npe-bundle.<version> .bin
- IOx Cartridges
 - Yocto 1.7.2 Base Rootfs (ir800_yocto-1.7.2.tar)
 - Python 2.7.3 Language Runtime (ir800_yocto-1.7.2_python-2.7.3.tar)
 - Azul Java 1.7 EJRE (ir800_yocto-1.7.2_zre1.7.0_65.7.6.0.7.tar)
 - Azul Java 1.8 Compact Profile 3 (ir800_yocto-1.7.2_zre1.8.0_65.8.10.0.1.tar)

IR829

The IR829 link shows the following entries:

Software on Chassis

- IOS Software
 - ir800-universalk9-bundle.<version> .bin
 - ir800-universalk9_npe-bundle.<version> .bin
- IOx Cartridges
 - Yocto 1.7.2 Base Rootfs (ir800_yocto-1.7.2.tar)
 - Python 2.7.3 Language Runtime (ir800_yocto-1.7.2_python-2.7.3.tar)
 - Azul Java 1.7 EJRE (ir800_yocto-1.7.2_zre1.7.0_65.7.6.0.7.tar)
 - Azul Java 1.8 Compact Profile 3 (ir800_yocto-1.7.2_zre1.8.0_65.8.10.0.1.tar)

AP803 Access Point Module

- Autonomous AP IOS Software
 - WIRELESS LAN (ap1g3-k9w7-tar.153-3.JH1.tar)
- Lightweight AP IOS Software
 - WIRELESS LAN (ap1g3-k9w8-tar.153-3.JH1.tar)
 - WIRELESS LAN LWAPP RECOVERY (ap1g3-rcvk9w8-tar.153-3.JH1.tar)

CGR1K Series

The latest image file for the CGR 1000 Series Cisco IOS image is available here:

<https://software.cisco.com/download/navigator.html?mdfid=284165761&flowid=75122>

For details on the CGR1000 installation, please see the following:

<http://www.cisco.com/c/en/us/td/docs/routers/connectedgrid/cgr1000/ios/release/notes/OL-31148-05.html#pgfid-9>

Warning about Installing the Image



Note

The bundle can be copied via Trivial File Transfer Protocol (TFTP), or Secure Copy Protocol (SCP) to the device, and then installed using the bundle install flash:<image name> command. The bin file can NOT be directly booted using the boot system flash:/image_name.



Caution

MANUAL [non-bundle] DOWNGRADE IS STRICTLY PROHIBITED.

Known Limitations

This release has the following limitations or deviations from expected behavior:

Space Limitation

The device requires a minimum 30MB additional space in the flash: file system before attempting an upgrade, or a downgrade between releases. Otherwise, the FPGA/BIOS will not have enough space to store files and perform the upgrade. In these current releases, the bundle installation will not display a warning, but future releases from September 2019 going forward will have a warning.

CSCvq88011 - IR809, IR829

Bundle install should internally handle “firmware downgrade enable” check

Symptoms: If you manually downgrade hypervisor and IOS only from releases (159-3.M+, 158-3.M3+, 156-3.M7+, 157-3.M5+) to the releases (158-3.M2a, 157-3.M4b, 156-3.M6b), the router will be stuck in a boot loop.

Workaround: If you use the recommended 'bundle install' to downgrade, the process will run correctly.

Major Enhancements

There are no Major Enhancement for the 15.9(3)M7a release.

Related Documentation

The following documentation is available:

- [Cisco IOS 15.9M cross-platform release notes](#)
- [All of the Cisco IR800 Industrial Integrated Services Router documentation](#)
- [All of the Cisco CGR 1000 Series Connected Grid Routers documentation](#)
- [IoT Field Network Director](#)
- [Cisco IOx Documentation](#)
- [Cisco IOx Developer information](#)

Caveats

Caveats describe unexpected behavior in Cisco IOS releases. Caveats listed as open in a prior release are carried forward to the next release as either open or resolved.

For more information about the Cisco Bug Search Tool, see the [Bug Search Tool Help & FAQ](#).

Open Caveats

There are no open caveats for Cisco IOS Release 15.9(3)M7a:

Resolved Caveats

The following table lists resolved caveats for Cisco IOS Release 15.9(3)M7a:

Item	Platform	Description
CSCwe62090	IR800	Devices going into rommon-2 mode and the boot variable is unset in 159(3)M7. Symptoms: BOOT variable is unavailable causing the router to stop at rommon-2. Limitations: The restoring of 'BOOT' variable using 'BOOT_BACKUP' will work in the following cases where: 1) BOOT variable missing 2) BOOT variable empty In order for this to work correctly, the image can be in any path in flash except that there should not be any image in direct flash:/<>.
CSCwe41339	IR800, CGR1000	PNP CONNECT fails to redirect contacting devices. Symptoms: On PnPC rollout, on-boarding fails due to trust pool issue and not redirect. Fix: Associate a unique trust pool to handle the same.

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit [Cisco DevNet](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a gateway to the Cisco bug-tracking system, which maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. The BST provides you with detailed defect information about your products and software.

Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

