



NetFlow Commands

To use commands of this module, you must be in a user group associated with a task group that includes appropriate task IDs. If the user group assignment is preventing you from using any command, contact your AAA administrator for assistance.

This module provides command line interface (CLI) commands for configuring NetFlow on the Cisco ASR 9000 Series Router.

- [cache entries, on page 3](#)
- [cache permanent, on page 4](#)
- [cache immediate, on page 5](#)
- [cache timeout, on page 6](#)
- [clear flow exporter, on page 7](#)
- [clear flow monitor, on page 8](#)
- [clear flow platform producer statistics location, on page 9](#)
- [destination, on page 10](#)
- [dscp, on page 11](#)
- [exporter, on page 12](#)
- [flow, on page 13](#)
- [flow datalinkframesection monitor, on page 15](#)
- [flow exporter-map, on page 16](#)
- [flow monitor-map, on page 18](#)
- [options, on page 20](#)
- [option filtered, on page 23](#)
- [random 1 out-of, on page 24](#)
- [record ipv4, on page 25](#)
- [record ipv6, on page 28](#)
- [record mpls, on page 30](#)
- [record datalinksection, on page 32](#)
- [sampler-map, on page 33](#)
- [show flow exporter, on page 35](#)
- [show flow exporter-map, on page 37](#)
- [show flow monitor, on page 41](#)
- [show flow monitor-map, on page 63](#)
- [show flow platform producer statistics location, on page 66](#)
- [show flow platform nfea sampler, on page 68](#)

- [show flow platform nfea interface](#), on page 69
- [show flow platform nfea sp location](#), on page 70
- [show flow platform nfea policer np](#), on page 71
- [show flow platform nfea bundle](#), on page 72
- [show flow platform nfea chkp](#), on page 73
- [show flow platform pal-cpp chkpt object](#), on page 74
- [show flow platform pal-cpp object](#), on page 75
- [show controllers pse qfp feature fnf datapath](#), on page 76
- [show flow trace platform producer location](#), on page 78
- [show flow trace ea location](#), on page 79
- [source \(NetFlow\)](#), on page 80
- [template \(NetFlow\)](#), on page 82
- [transport udp](#), on page 84
- [version v9](#), on page 85
- [version ipfix](#), on page 87

cache entries

To configure the number of entries in the monitor map flow cache, enter the **cache entries** command in flow monitor map configuration mode. To remove a configured number of entries and return the cache to the default configuration, use the **no** form of this command.

cache entries *number*

Syntax Description	<i>number</i> Number of entries in the flow cache. Replace the <i>number</i> argument with the number of flow entries allowed in the flow cache. Range is from 4096 through 1000000.				
Command Default	<i>number</i> : 65535				
Command Modes	Flow monitor map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				
Examples	This example shows how to configure the number of entries in the monitor map flow cache to be 10000:				

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm) # cache entries 10000
```

cache permanent

cache permanent

To disable the removal of entries from the monitor map flow cache, enter the **cache permanent** command in flow monitor map configuration mode. To re-enable the removal of entries from the flow cache, use the **no** form of this command.

cache permanent

Syntax Description This command has no keywords or arguments.

Command Default The removal of entries from the monitor map flow cache is enabled.

Command Modes Flow monitor map configuration

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Task ID	Task ID	Operations
	netflow	read, write

Examples This example shows how to disable the removal of entries from the monitor map flow cache:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# cache permanent
```

This example shows how to re-enable the removal of entries from the monitor map flow cache:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# no cache permanent
```

cache immediate

To enable immediate aging cache type, use the **cache immediate** command in flow monitor map configuration mode. To disable, use **no** form of the command.

cache immediate

Syntax Description	This command has no keywords or arguments.
---------------------------	--

Command Default	None
------------------------	------

Command Modes	Flow monitor map configuration
----------------------	--------------------------------

Command History	Release	Modification
	Release 6.5.1	This command was introduced.

Usage Guidelines	Immediate Aging is a special cache type that ensures that the flows are exported as soon as they are added to the cache.
-------------------------	--

Task ID	Task ID	Operations
	netflow	read, write

This example shows how to enable immediate aging cache type:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)#flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm) # cache immediate
```

cache timeout

cache timeout

To configure the active, inactive, and update flow cache timeout, enter the **cache timeout** command in flow monitor map configuration mode. To remove the configured timeout value and return the cache to its default timeout value, use the **no** form of this command.

cache timeout {active | inactive | update} timeout_value

Syntax Description

active	Specifies the active flow timeout.
inactive	Specifies the inactive flow timeout.
update	Specifies the update timeout.
<i>timeout_value</i>	Timeout value for the specified keyword (active , inactive , or update), in seconds. Range is from 1 through 604800.

Command Default

- For active timeout, the default value is 1800 seconds.
- For inactive timeout, the default value is 15 seconds.
- For update timeout, the default value is 1800 seconds.

Command Modes

Flow monitor map configuration

Command History

Release	Modification
Release 3.9.1	This command was introduced.

Usage Guidelines



Note The **inactive** timeout value should be smaller than the **active** timeout value. The **update** keyword is used for permanent caches only. It specifies the timeout value that is used to export entries from permanent caches. In this case, the entries are exported but remain in the cache.

Task ID

Task ID	Operations
---------	------------

netflow read,
write

Examples

This example shows how to set the active timeout for the monitor map cache to 200,000 seconds:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# cache timeout active 200000
```

clear flow exporter

To export flow exporter templates to the collector or restart the flow exporter statistics collector, enter the **clear flow exporter** command in EXEC mode.

clear flow exporter [*fem-name*] {restart | statistics} location *node-id*

Syntax Description	<p><i>fem-name</i> (Optional) Flow exporter name.</p> <p>restart Exports all of the current templates to the collector.</p> <p>statistics Clears the exporter statistics.</p> <p>location <i>node-id</i> Identifies the node whose flow exporter statistics you want to clear, or whose flow exporter statistics collector you want to restart. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.</p>						
Command Default	No default behavior or values						
Command Modes	EXEC mode						
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.		
Release	Modification						
Release 3.9.1	This command was introduced.						
Usage Guidelines	No specific guidelines impact the use of this command.						
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>basic-services</td><td>read, write</td></tr> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	basic-services	read, write	netflow	read, write
Task ID	Operations						
basic-services	read, write						
netflow	read, write						

Examples This example exports all templates to the collector:

```
RP/0/RSP0/CPU0:router# clear flow exporter restart location 0/0/SP
Restart exporter all locations. Continue? [confirm]
```

This example shows how to clear flow exporter statistics on a specific node:

```
RP/0/RSP0/CPU0:router# clear flow exporter statistics location 0/0/CPU0
Clear statistics for all exporters on the location. Continue? [confirm]
```

clear flow monitor

clear flow monitor

To clear the flow monitor data, enter the **clear flow monitor** command in EXEC mode.

```
clear flow monitor [name] cache [force-export | statistics] location node-id
```

Syntax Description	<table border="0"> <tr> <td>name</td><td>(Optional) Identifies a specific cache you want to clear.</td></tr> <tr> <td>cache</td><td>Clears all cache related information.</td></tr> <tr> <td>force-export</td><td>(Optional) Forces the export of flow records on flushing the cache on the specified node.</td></tr> <tr> <td>statistics</td><td>(Optional) Clears cache statistics on a specific node.</td></tr> <tr> <td>location node-id</td><td>Node whose flow monitor you want to clear. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.</td></tr> </table>	name	(Optional) Identifies a specific cache you want to clear.	cache	Clears all cache related information.	force-export	(Optional) Forces the export of flow records on flushing the cache on the specified node.	statistics	(Optional) Clears cache statistics on a specific node.	location node-id	Node whose flow monitor you want to clear. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.
name	(Optional) Identifies a specific cache you want to clear.										
cache	Clears all cache related information.										
force-export	(Optional) Forces the export of flow records on flushing the cache on the specified node.										
statistics	(Optional) Clears cache statistics on a specific node.										
location node-id	Node whose flow monitor you want to clear. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.										
Command Default	None										
Command Modes	EXEC mode										
Command History	<table border="0"> <tr> <th>Release</th> <th>Modification</th> </tr> <tr> <td colspan="2">Release 3.9.1 This command was introduced.</td> </tr> </table>	Release	Modification	Release 3.9.1 This command was introduced.							
Release	Modification										
Release 3.9.1 This command was introduced.											
Usage Guidelines	No specific guidelines impact the use of this command.										
Task ID	<table border="0"> <tr> <th>Task</th> <th>Operations</th> </tr> <tr> <td>ID</td> <td></td> </tr> <tr> <td>netflow</td> <td>read, write</td> </tr> </table>	Task	Operations	ID		netflow	read, write				
Task	Operations										
ID											
netflow	read, write										

Examples

This example shows how to clear the cache-related flow records on a specific node:

```
RP/0/RSP0/CPU0:router# clear flow monitor cache force-export location 0/0/CPU0
Clear cache entries for this monitor on this location. Continue? [confirm]
```

clear flow platform producer statistics location

To clear statistics collected by the NetFlow producer, use the **clear flow platform producer statistics location** command in EXEC mode.

clear flow platform producer statistics location node-id

Syntax Description	<i>node-id</i> Node on which to clear statistics collected by the NetFlow producer. The <i>node-id</i> is expressed in the <i>rack/slot/module</i> notation.
---------------------------	--

Note

Enter the **show platform** command to see the location of all nodes installed in the router.

Command Default	None
------------------------	------

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
------------------------	----------------	---------------------

Release 3.9.1 This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
	netflow	read, write

Examples	This example shows how to clear statistics collected by the NetFlow producer:
-----------------	---

```
RP/0/RSP0/CPU0:router# clear flow platform producer statistics location 0/0/CPU0
```

destination

destination

To configure the collector export destination, enter the **destination** command in flow exporter map configuration mode. To remove a configured export destination, use the **no** form of this command.

destination *hostname_or_IP_address* [**vrf** *vrf_name*]

Syntax Description	<i>hostname_or_IP_address</i> Specify the export destination for the current flow exporter map. Enter the hostname or destination IP address in the <i>A.B.C.D</i> format. vrf <i>vrf_name</i> (Optional) Specify the name of the VRF that is used to reach export destination. This is an optional keyword. If the vrf keyword is specified, then the destination is searched in the VRF that is specified (<i>vrf_name</i>). If the vrf keyword is not specified then, the destination is searched in the default routing table.				
Command Default	None				
Command Modes	Flow exporter map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				

Examples

This example shows how to configure the flow exporter map export destination to be a specific IP address:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem)# destination 172.18.189.38
```

dscp

To configure the differentiated services codepoint (DSCP) value for export packets, enter the **dscp** command in flow exporter map configuration mode. To remove a configured DSCP value, use the **no** form of this command.

dscp *dscp_value*

Syntax Description	<i>dscp_value</i> Specifies the DSCP value for export packets. Replace <i>dscp_value</i> with a number. Range is from 0 through 63.				
Command Default	None				
Command Modes	Flow exporter map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				

Examples

This example shows how to configure the DSCP value for export packets to be 30:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem) # dscp 30
```

exporter

To associate a flow exporter map with the current flow monitor map, enter the **exporter** command in flow monitor map configuration mode. To remove an associated flow exporter map from a flow monitor map, use the **no** form of this command.

exporter *map_name*

Syntax Description

map_name Name of the flow exporter map you want to associate with the current flow monitor map. The exporter map name can be a maximum of 32 characters.

Note

A single flow monitor map supports up to 8 exporters. Only the first five will be used.

Command Default

None

Command Modes

Flow monitor map configuration

Command History

Release	Modification
---------	--------------

Release 3.9.1 This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operations
---------	------------

netflow read,
write

Examples

This example shows how to associate a flow exporter map called “fem_1” with the current flow monitor map:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# exporter fem_1
```

flow

To specify a flow monitor map and a sampler map for the packets on an interface, use the **flow** command in interface configuration mode. To remove a configured flow monitor map, use the **no** form of this command.

```
flow [ipv4 | ipv6 | mpls] monitor name sampler name {egress | ingress}
```

Syntax Description	ipv4 Enables IPV4 NetFlow on the specified interface. ipv6 Enables IPV6 NetFlow on the specified interface. mpls Enables Multiprotocol Label Switching (MPLS)-aware NetFlow on the specified interface. monitor name Specifies the name of the flow monitor map you want to specify for IPv4, IPv6, or MPLS packets. sampler name Name of the sampler map you want to apply to the flow monitor map. egress Applies the flow monitor map on outgoing packets. ingress Applies the flow monitor map on incoming packets.						
Command Default	None						
Command Modes	Interface configuration						
Command History	<table> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 3.9.1</td> <td>This command was introduced.</td> </tr> <tr> <td>Release 4.3.1</td> <td>The support for NetFlow over Bridge-group Virtual Interface was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.	Release 4.3.1	The support for NetFlow over Bridge-group Virtual Interface was introduced.
Release	Modification						
Release 3.9.1	This command was introduced.						
Release 4.3.1	The support for NetFlow over Bridge-group Virtual Interface was introduced.						
Usage Guidelines	No specific guidelines impact the use of this command.						
Task ID	<table> <thead> <tr> <th>Task ID</th> <th>Operations</th> </tr> </thead> <tbody> <tr> <td>netflow</td> <td>read, write</td> </tr> </tbody> </table>	Task ID	Operations	netflow	read, write		
Task ID	Operations						
netflow	read, write						

Examples

This example shows how to enable IPV4 NetFlow on a GigabitEthernet interface, and then apply the flow monitor map, named "map1," on outgoing IPv4 packets:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# interface GigabitEthernet 0/4/0/0
RP/0/RSP0/CPU0:router(config-if)# flow ipv4 monitor map1 sampler smap1 ingress
RP/0/RSP0/CPU0:router(config-if)# flow ipv4 monitor NMS sampler NMS egress
```

This example shows how to enable MPLS NetFlow on a GigabitEthernet interface, and apply the flow monitor map, named "map_mpls1," on outgoing MPLS packets:

```
RP/0/RSP0/CPU0:router# configure  
RP/0/RSP0/CPU0:router(config)# interface gigabit Ethernet 0/0/0/0  
RP/0/RSP0/CPU0:router(config-if)# flow mpls monitor map_mpls1 sampler smap1 egress
```

This example shows how to enable IPv4 NetFlow on a Bridge-group virtual interface, and then apply the flow monitor map on incoming and outgoing IPv4 packets:

```
RP/0/RSP0/CPU0:router# configure  
RP/0/RSP0/CPU0:router(config)# interface BVI 1  
RP/0/RSP0/CPU0:router(config-if)# flow ipv4 monitor NMS sampler NMS ingress  
RP/0/RSP0/CPU0:router(config-if)# flow ipv4 monitor NMS sampler NMS egress
```

This example shows how to enable IPv6 NetFlow on a Bridge-group virtual interface, and then apply the flow monitor map on incoming and outgoing IPv6 packets:

```
RP/0/RSP0/CPU0:router# configure  
RP/0/RSP0/CPU0:router(config)# interface BVI 1  
RP/0/RSP0/CPU0:router(config-if)# flow ipv6 monitor NMS sampler NMS ingress  
RP/0/RSP0/CPU0:router(config-if)# flow ipv6 monitor NMS sampler NMS egress
```

flow datalinkframesection monitor

To monitor and capture information element that carries n octets from the data link frame (IPFIX 315) of a selected frame in the ingress direction of an interface, use**flow datalinkframesection monitor** command in interface configuration mode.

```
flow datalinkframesection monitor monitor-map sampler sampler-map ingress
```

Syntax Description

monitor *monitor-map* Specify flow monitor map name.

sampler *sampler-map* Specify flow sampler map name.

ingress Specify ingress direction. The IPFIX 315 info is captured from incoming traffic on specified interface.

Command Default

None.

Command Modes

Interface configuration mode

Command History

Release	Modification
---------	--------------

Release 6.5.1 This command was introduced.

Usage Guidelines

When datalinkframesection flow type is enabled on an interface, other flows like IPv4, IPv6 and MPLS are not allowed. The option field in the frame indicates the IPFIX 315 info.

Task ID

Task ID	Operation
---------	-----------

netflow read,
write

This sample shows how to enable flow datalinkframesection monitor on hundredGigE interface:

```
RP/0/RSP0/CPU0:router(config)#interface hundredGigE 0/0/0/18
RP/0/RSP0/CPU0:router(config-if)#flow datalinkframesection monitor ipfix-mon sampler ipfix-sam ingress
```

flow exporter-map

flow exporter-map

To create a flow exporter map and enter flow exporter map configuration mode, use the **flow exporter-map** command in Global Configuration mode. To remove a configured flow exporter map, use the **no** form of this command.

flow exporter-map *fem-name*

Syntax Description	<i>fem-name</i> Creates a new exporter map name, or specifies the name of an existing exporter map.
---------------------------	---

Command Default	None
------------------------	------

Command Modes	Global Configuration mode
----------------------	---------------------------

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Usage Guidelines	When you issue the flow exporter-map <i>fem-name</i> command in global configuration mode, the CLI prompt changes to “config-fem,” indicating that you have entered the flow exporter map configuration submode.
-------------------------	---

In this sample output, the question mark (?) online help function displays all the commands available under flow exporter map configuration submode:

```
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem)# ?

RP/0/RSP0/CPU0:routerconfig-fem)#?
  clear      Clear the uncommitted configuration
  commit     Commit the configuration changes to running
  describe   Describe a command without taking real actions
  destination Export destination configuration
  do         Run an exec command
  dscp       Specify DSCP value for export packets
  exit       Exit from this submode
  no         Negate a command or set its defaults
  pwd        Commands used to reach current submode
  root      Exit to the global configuration mode
  show      Show contents of configuration
  source    Source interface
  transport Specify the transport protocol for export packets
  version   Specify export version parameters
```

Task ID	Task Operations ID
	netflow read, write

Examples	This example shows how to create a flow exporter map called “map1,” and then enter the flow exporter map configuration submode for that map:
-----------------	--

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem)#

```

flow monitor-map

flow monitor-map

To create and configure a flow monitor map and enter flow monitor map configuration submode, use the **flow monitor-map** command in Global Configuration mode. To remove a configured flow monitor map, use the **no** form of this command:

flow monitor-map *map_name*

Syntax Description	<i>map_name</i> New monitor map name, or specifies the name of an existing monitor map. The monitor map name can be a maximum 32 characters.				
Command Default	None				
Command Modes	Global Configuration mode				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				

Usage Guidelines When you issue the **flow monitor-map *map_name*** command in Global Configuration mode, the CLI prompt changes to “config-fmm,” indicating that you have entered the flow monitor map configuration submode. In the following sample output, the question mark (?) online help function displays all the commands available under flow monitor map configuration submode:

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)#?

cache      Specify flow cache attributes
clear      Clear the uncommitted configuration
commit     Commit the configuration changes to running
describe   Describe a command without taking real actions
do         Run an exec command
exit       Exit from this submode
exporter   Specify flow exporter map name
no         Negate a command or set its defaults
pwd       Commands used to reach current submode
record     Specify a flow record map name
record ipv4  Encapsulates PE L2-L3 record for ipv4
record ipv6  Encapsulates PE L2-L3 record for ipv6
root      Exit to the global configuration mode
show      Show contents of configuration
```

Task ID	Task Operations ID
	netflow read, write

Examples This example shows how to enter flow monitor map configuration mode for a monitor map called “map1.”

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)#

```

options

To export the tables in the options template and specify export timeout values, enter the **options** command in flow exporter map version configuration mode. To return the options template to its default configuration values, use the **no** form of this command.

options {interface-table | sampler-table | vrf-table} [timeout seconds]

Syntax Description

interface-table Export the interface table.

sampler-table Exports the sampler table.

Use **options sampler-table timeout** command to send IE 305. This command configures the timeout value for the sampler table. This timeout value can be in the range 1–604800 seconds and the default value is 1800 seconds.

You can also use **options sampler-table** command to export the following IEs:

- IE 302—to export selector ID.
- IE 304—to export sampling algorithm.
- IE 309—to export sampling size.
- IE 310—to export sampling population.
- IE 84—to export sampler name.
- IE 335—to export selector name.

IE 309, IE 310, and IE 335 are supported starting from Release 7.8.2

vrf-table Exports the VRF to VRF-Name table.

timeout seconds Specifies the export timeout value. Replace *seconds* with the export timeout value. Range is from 1 through 604800 seconds.

Command Default

Without options command, the default value for timeout is 0 seconds, which means that the template options are not exported by default. Whereas when options command is used without mentioning any timeout, default timeout is 1800 seconds.

Command Modes

Flow exporter map version configuration

Command History

Release	Modification
---------	--------------

Release 3.9.1 This command was introduced.

Release 5.2.0 The keyword vrf-table was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
	netflow	read, write

Examples

This example shows how to export the timeout in the interface table to the options template.

```
RP/0/RSP0/CPU0:router(config)# flow exporter-map f1
RP/0/RSP0/CPU0:router(config-fem)#
RP/0/RSP0/CPU0:router(config-fem)# options interface-table timeout 45
```

Examples

This is the sample output after setting to export the interface table and configure the export timeout value:

```
RP/0/RSP0/CPU0:router(config-fem-ver)# show running-config flow exporter-map f1
flow exporter-map f1
version v9
options vrf-table 50
!
transport udp 9321
source HundredGigE 0/4/3/0
destination 10.64.81.237
!

RP/0/RSP0/CPU0:router(config-fem-ver)# do show flow exporter-map f1

Flow Exporter Map : f1
-----
Id : 21
DestinationIpAddr : 10.64.81.237
SourceIfName : HundredGigE 0/4/3/0
SourceIpAddr : 0.0.0.0
DSCP : 0
TransportProtocol : UDP
TransportDestPort : 9321

Export Version: 9
Common Template Timeout : 1800 seconds
Options Template Timeout : 1800 seconds
Data Template Timeout : 1800 seconds
Interface-Table Export Timeout : 0 seconds
Sampler-Table Export Timeout : 0 seconds
VRF-Table Export Timeout : 50 seconds

RP/0/RSP0/CPU0:router(config-fem-ver)# do show running-config flow exporter-map f1
flow exporter-map f1
version v9
options interface-table
options sampler-table
options vrf-table
!
transport udp 9321
source HundredGigE 0/4/3/0
destination 10.64.81.237
!
RP/0/RSP0/CPU0:router(config-fem-ver)# show flow exporter-map f1
```

options

```
Flow Exporter Map : f1
-----
Id          : 21
DestinationIpAddr : 10.64.81.237
SourceIfName   : HundredGigE 0/4/3/0
SourceIpAddr   : 0.0.0.0
DSCP         : 0
TransportProtocol : UDP
TransportDestPort : 9321

Export Version: 9
Common Template Timeout : 1800 seconds
Options Template Timeout : 1800 seconds
Data Template Timeout : 1800 seconds
Interface-Table Export Timeout : 1800 seconds
Sampler-Table Export Timeout : 1800 seconds
VRF-Table Export Timeout : 1800 seconds
```

option filtered

To enable filtering of the Netflow records, use **option filtered** command in flow monitor map configuration mode.

option filtered

Syntax Description	filtered Enables filtering of records	
Command Default	Flow filtering is disabled.	
Command Modes	Flow monitor map configuration	
Command History	Release	Modification
	6.0.1	This command was introduced.
Usage Guidelines	MPLS netflow filtering is not supported. Since the filtering of packets is based on the ACL, you must define ACL configuration before using option filtered command. Use the capture keyword while defining ACL. For example:	
	<pre>ipv4 access-list nf_ex 10 permit ipv4 10.1.1.1/24 any capture</pre>	
Task ID	Task ID	Operation
	netflow	read, write

This example shows how to create flow monitor map that filters Netflow records with cache entries upto 10000:

```
RP/0/RSP0/CPU0:router# config
RP/0/RSP0/CPU0:router(config)# flow monitor-map fmm1
RP/0/RSP0/CPU0:router(config-fmm) # record ipv4
RP/0/RSP0/CPU0:router(config-fmm) # option filtered
RP/0/RSP0/CPU0:router(config-fmm) # exporter fem1
RP/0/RSP0/CPU0:router(config-fmm) # cache entries 10000
RP/0/RSP0/CPU0:router(config-fmm) # cache timeout active 1800
RP/0/RSP0/CPU0:router(config-fmm) # cache timeout inactive 15
RP/0/RSP0/CPU0:router(config-fmm) # exit
```

random 1 out-of

random 1 out-of

To configure the packet sampling interval for a sampler map, use the **random 1 out-of** command in sampler map configuration submode. To remove a configured sampling interval and return to the default sampling interval, use the **no** form of this command. The limit of sampling rate values per line card per direction is 4, and limit of total samplers per line card per direction is 16.

random 1 out-of *number_of_packets*

Syntax Description	<i>number_of_packets</i> Sampling interval in units of packets. Replace the <i>number_of_packets</i> argument with a number. Range is from 1 through 65535 units.				
Command Default	There is no default value to <i>number_of_packets</i> . However, for optimal performance, the recommended value for <i>number_of_packets</i> is 10000.				
Command Modes	Sampler map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	On Cisco ASR 9000 High Density 100GE Ethernet line cards, when the configured sampling rate is one of the following values, the sampling behavior is random with a deviation of more than 10 percent: <ul style="list-style-type: none"> • 2048 • 4096 • 8192 • 16384 • 32768 • 65535 				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	netflow	read, write
Task ID	Operations				
netflow	read, write				

Examples

This example shows how to configure the sampler map to randomly sample 1 out of every 10 packets:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# sampler map1
RP/0/RSP0/CPU0:router(config-sm)# random 1 out-of 10
```

record ipv4

To activate an IPv4 flow record, use the **record ipv4** command in flow monitor map configuration mode. To deactivate the flow record, use the **no** form of this command.

```
record ipv4 [ peer-as || destination-tos | | [srv6][l2-l3] ]
```

Syntax Description	peer-as (Optional) Records peer AS. Note The Border Gateway Protocol (BGP) AS is not collected unless the bgp attribute download command is configured.								
destination-tos	(Optional) Records IPv4 destination based NetFlow accounting.								
srv6	Records SRv6 based NetFlow data.								
l2-l3	Records L2 and L3 specific NetFlow data.								
Command Default	The default is that no IPv4 flow record is enabled.								
Command Modes	Flow monitor map configuration								
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> <tr> <td>Release 4.2.0</td><td>The destination-tos keyword was added to support destination-based Netflow accounting.</td></tr> <tr> <td>Release 7.10.1</td><td>This command was modified and the following optional keywords were introduced for the record ipv4 option: <ul style="list-style-type: none"> • srv6 • l2-l3 This keywords are supported on 4th generation and later ASR 9000 line cards. </td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.	Release 4.2.0	The destination-tos keyword was added to support destination-based Netflow accounting.	Release 7.10.1	This command was modified and the following optional keywords were introduced for the record ipv4 option: <ul style="list-style-type: none"> • srv6 • l2-l3 This keywords are supported on 4th generation and later ASR 9000 line cards.
Release	Modification								
Release 3.9.1	This command was introduced.								
Release 4.2.0	The destination-tos keyword was added to support destination-based Netflow accounting.								
Release 7.10.1	This command was modified and the following optional keywords were introduced for the record ipv4 option: <ul style="list-style-type: none"> • srv6 • l2-l3 This keywords are supported on 4th generation and later ASR 9000 line cards.								

Usage Guidelines	<ul style="list-style-type: none"> • The BGP AS is not collected unless the bgp attribute download command is configured. • The record ipv4 command exports the BGP AS information in the following format: bgpSourceAsNumber bgpDestinationAsNumber • The record ipv4 peer-as command exports the adjacent BGP AS information in the following format: bgpPrevAdjacentAsNumber bgpNextAdjacentAsNumber
-------------------------	---

record ipv4

Task ID	Task Operations ID
	netflow read, write

Examples

This example shows how to configure an IPv4 flow record:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# record ipv4
```

This example shows how to configure an IPv4 flow record for destination-based NetFlow accounting:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# record ipv4 destination-tos
RP/0/RSP0/CPU0:router(config-fmm)# exit
RP/0/RSP0/CPU0:router(config)# interface Gigabit Ethernet 0/0/0/0
RP/0/RSP0/CPU0:router(config-if)# flow ipv4 monitor monitor1 ingress
RP/0/RSP0/CPU0:router(config-if)# end
```

This example shows how to configure the **srv6** flow record map name for the **record ipv4** option:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config-fem)# flow monitor-map MON-MAP-v6
RP/0/RSP0/CPU0:router(config-fmm)# record ipv6 srv6
RP/0/RSP0/CPU0:router(config-fmm)# exporter EXP
RP/0/RSP0/CPU0:router(config-fmm)# cache timeout inactive 5
RP/0/RSP0/CPU0:router(config-fmm)# !
RP/0/RSP0/CPU0:router(config-fmm)# sampler-map SAMP
RP/0/RSP0/CPU0:router(config-fmm)# random 1 out-of 1000
RP/0/RSP0/CPU0:router(config-fmm)# !
RP/0/RSP0/CPU0:router(config-fmm)# interface GigabitEthernet0/1/0/0
RP/0/RSP0/CPU0:router(config-fmm)# ipv4 address 1.1.1.1 255.255.255.0
RP/0/RSP0/CPU0:router(config-fmm)# flow ipv6 monitor M1 sampler SAMP ingres
```

This example shows how to configure the **12-13** flow record map name for the **record ipv4** option:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config-fem)# flow monitor-map M-IPv4
RP/0/RSP0/CPU0:router(config-fmm)# record ipv4 12-13
RP/0/RSP0/CPU0:router(config-fmm)# exporter EXP-ipfix
RP/0/RSP0/CPU0:router(config-fmm)# !
RP/0/RSP0/CPU0:router(config-fmm)# flow monitor-map M-IPv6
RP/0/RSP0/CPU0:router(config-fmm)# record ipv6 12-13
RP/0/RSP0/CPU0:router(config-fmm)# exporter EXP-ipfix
RP/0/RSP0/CPU0:router(config-fmm)# !
RP/0/RSP0/CPU0:router(config-fmm)# sampler-map SAMP
RP/0/RSP0/CPU0:router(config-fmm)# random 1 out-of 1000
RP/0/RSP0/CPU0:router(config-fmm)# !
RP/0/RSP0/CPU0:router(config-fmm)# interface GigabitEthernet0/1/0/0
```

```
RP/0/RSP0/CPU0:router(config-fmm) # description CE-PE Interface
RP/0/RSP0/CPU0:router(config-fmm) # ipv4 address<>
RP/0/RSP0/CPU0:router(config-fmm) # ipv6 address<>
RP/0/RSP0/CPU0:router(config-fmm) # flow ipv4 monitor M-IPv4 sampler SAMP ingress
RP/0/RSP0/CPU0:router(config-fmm) # flow ipv6 monitor M-IPv6 sampler SAMP ingress
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router
```

record ipv6

record ipv6

To configure the flow record map name for IPv6, use the **record ipv6** command in flow monitor map configuration mode. To remove the configured name from a flow record, use the **no** form of this command.

```
record ipv6 { | [srv6][l2-l3] }
```

Syntax Description	peer-as Records peer AS. srv6 Records SRv6 based NetFlow data. l2-l3 Records L2 and L3 specific NetFlow data.
---------------------------	--

Command Default The default is that originating AS numbers are recorded.

Command Modes Flow monitor map configuration

Command History	Release	Modification
	Release 3.9.1	This command was introduced.
	Release 7.10.1	This command was modified and the following optional keywords were introduced for the record ipv6 option: <ul style="list-style-type: none"> • srv6 • l2-l3 These keywords are supported on 4th generation and later ASR 9000 line cards.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
		netflow read, write

Examples This example shows how to configure the flow record map name for IPv6:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# record ipv6
```

This example shows how to configure the **srv6** flow record map name for the **record ipv6** option:

```
RP/0/RSP0/CPU0:router# configure
```

```

RP/0/RSP0/CPU0:router(config-fem) # flow monitor-map MON-MAP-v6
RP/0/RSP0/CPU0:router(config-fmm) # record ipv6 srv6
RP/0/RSP0/CPU0:router(config-fmm) # exporter EXP
RP/0/RSP0/CPU0:router(config-fmm) # cache timeout inactive 5
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router(config-fmm) # sampler-map SAMP
RP/0/RSP0/CPU0:router(config-fmm) # random 1 out-of 1000
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router(config-fmm) # interface GigabitEthernet0/1/0/0
RP/0/RSP0/CPU0:router(config-fmm) # ipv6 address 2001:DB8:c18:1::/64
RP/0/RSP0/CPU0:router(config-fmm) # flow ipv6 monitor M1 sampler SAMP ingres

```

This example shows how to configure the 12-13 flow record map name for the record ipv6 option:

```

RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config-fem) # flow monitor-map M-IPv4
RP/0/RSP0/CPU0:router(config-fmm) # record ipv4 12-13
RP/0/RSP0/CPU0:router(config-fmm) # exporter EXP-ipfix
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router(config-fmm) # flow monitor-map M-IPv6
RP/0/RSP0/CPU0:router(config-fmm) # record ipv6 12-13
RP/0/RSP0/CPU0:router(config-fmm) # exporter EXP-ipfix
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router(config-fmm) # sampler-map SAMP
RP/0/RSP0/CPU0:router(config-fmm) # random 1 out-of 1000
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router(config-fmm) # interface GigabitEthernet0/1/0/0
RP/0/RSP0/CPU0:router(config-fmm) # description CE-PE Interface
RP/0/RSP0/CPU0:router(config-fmm) # ipv4 address<>
RP/0/RSP0/CPU0:router(config-fmm) # ipv6 address<>
RP/0/RSP0/CPU0:router(config-fmm) # flow ipv4 monitor M-IPv4 sampler SAMP ingres
RP/0/RSP0/CPU0:router(config-fmm) # flow ipv6 monitor M-IPv6 sampler SAMP ingress
RP/0/RSP0/CPU0:router(config-fmm) # !
RP/0/RSP0/CPU0:router

```

record mpls

record mpls

To configure the flow record map name for MPLS, use the **record mpls** command in flow monitor map configuration mode. To remove the configured name from a flow record, use the **no** form of this command.

```
record mpls [ipv4-fields] [ipv6-fields] [ipv4-ipv6-fields] [labels number]
```

Syntax Description	ipv4-fields (Optional) Collects IPv4 fields in the MPLS-aware Netflow when the payload of the MPLS packet has IPv4 fields. It also collects MPLS traffic with no IPv4 payload, but the IPv4 fields are set to zero. ipv6-fields (Optional) Collects IPv6 fields in the MPLS-aware Netflow when the payload of the MPLS packet has IPv6 fields. It also collects MPLS traffic with no IPv6 payload, but the IPv6 fields are set to zero. ipv4-ipv6-fields (Optional) Collects IPv4 and IPv6 fields in the MPLS-aware Netflow when the payload of the MPLS packet has either IPv4 fields or IPv6 fields. It also collects MPLS traffic with no IPv4 or IPv6 payload, but those fields are set to zero. labels number (Optional) Configures the number of labels that are used in hashing. The <i>number</i> argument is the number of labels that are used in hashing. The range is from 1 to 6.
---------------------------	---

Command Default	The default is no IPV4 fields and six labels.				
Command Modes	Flow monitor map configuration				
Command History	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left; padding-bottom: 2px;">Release</th> <th style="text-align: left; padding-bottom: 2px;">Modification</th> </tr> </thead> <tbody> <tr> <td style="padding-top: 2px;">Release 3.9.1</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				

Usage Guidelines	In Cisco IOS XR software, you can have only one MPLS flow monitor running on an interface at a time. If you apply an additional MPLS flow monitor to the interface, the new flow monitor overwrites the existing one.
	You can configure the MPLS flow monitor to collect IPv4 fields, IPv6 fields, or both types of fields.

Task ID	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left; padding-bottom: 2px;">Task ID</th><th style="text-align: left; padding-bottom: 2px;">Operations</th></tr> </thead> <tbody> <tr> <td style="padding-top: 2px;">netflow read, write</td><td></td></tr> </tbody> </table>	Task ID	Operations	netflow read, write	
Task ID	Operations				
netflow read, write					

Examples	This configuration allows you to collect only MPLS fields. No payload information is collected.
-----------------	---

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map MPLS-fmm
RP/0/RSP0/CPU0:router(config-fmm)# record mpls labels 3
RP/0/RSP0/CPU0:router(config-fmm)# cache permanent
RP/0/RSP0/CPU0:router(config)# exit
```

```
RP/0/RSP0/CPU0:router(config)# interface GigabitEthernet 0/0/0/0
RP/0/RSP0/CPU0:router(config-if)# flow mpls monitor MPLS-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with IPv4 fields. It also collects MPLS traffic with no IPv4 payload, but the IPv4 fields are set to zero.

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map MPLS-IPv4-fmm
RP/0/RSP0/CPU0:router(config-fmm)# record mpls IPv4-fields labels 3
RP/0/RSP0/CPU0:router(config-fmm)# cache permanent
RP/0/RSP0/CPU0:router(config-fmm)# exit
RP/0/RSP0/CPU0:router(config)# interface gigabitEthernet 0/0/0/0
RP/0/RSP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv4-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with IPv6 fields. It also collects MPLS traffic with no IPv6 payload, but the IPv6 fields are set to zero.

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map MPLS-IPv6-fmm
RP/0/RSP0/CPU0:router(config-fmm)# record mpls IPv6-fields labels 3
RP/0/RSP0/CPU0:router(config-fmm)# cache permanent
RP/0/RSP0/CPU0:router(config-fmm)# exit
RP/0/RSP0/CPU0:router(config)# interface gigabitEthernet 0/0/0/0
RP/0/RSP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv6-fmm sampler fsm ingress
```

This configuration allows you to collect MPLS traffic with both IPv6 and IPv4 fields. It also collects MPLS traffic with no IPv4 or IPv6 payload, but those fields are set to zero.

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map MPLS-IPv4-IPv6-fmm
RP/0/RSP0/CPU0:router(config-fmm)# record mpls IPv4-IPv6-fields labels 3
RP/0/RSP0/CPU0:router(config-fmm)# cache permanent
RP/0/RSP0/CPU0:router(config-fmm)# exit
RP/0/RSP0/CPU0:router(config)# interface gigabitEthernet 0/0/0/0
RP/0/RSP0/CPU0:router(config-if)# flow mpls monitor MPLS-IPv4-IPv6-fmm sampler fsm ingress
```

This example shows how to configure three labels for hashing:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow monitor-map map1
RP/0/RSP0/CPU0:router(config-fmm)# record mpls labels 3
```

record datalinksection

record datalinksection

To record the information element that carries *n* octets from the data link frame (IPFIX 315), use the **record datalinksection** command in flow monitor map configuration mode. To disable recording, use the **no** form of this command.

record datalinksection

Syntax Description This command has no keywords or arguments.

Command Default None

Command Modes Flow monitor map configuration

Command History

Release	Modification
6.5.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID

Task ID	Operations
netflow	read, write

Task ID

Task ID	Operations
netflow	read, write

Examples This configuration allows you to collect IPFIX 315 element information:

```
RP/0/RSP0/CPU0:router(config)# flow monitor-map ipfix-mon
RP/0/RSP0/CPU0:router(config-fmm)# record datalinkframesection
RP/0/RSP0/CPU0:router(config-fmm)# cache immediate
RP/0/RSP0/CPU0:router(config)# exit
RP/0/RSP0/CPU0:router(config)# interface Gigabit Ethernet 0/0/0/1
RP/0/RSP0/CPU0:router(config-if)# flow datalinkframesection monitor ipfix-mon sampler
ipfix-sm ingress
```

sampler-map

To enter sampler map configuration submode for a specific monitor map, use the **sampler-map** command in Global Configuration mode. To remove a configured sampler map, use the **no** form of this command.

sampler-map map_name

Syntax Description	<i>map_name</i> Name of the sampler map you want to configure. The sampler map name can be a maximum 32 characters.				
Command Default	None				
Command Modes	Global Configuration mode				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 3.9.1</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				

Usage Guidelines When you issue the **sampler-map map_name** command in Global Configuration mode, the CLI prompt changes to “config-sm,” indicating that you have entered the sampler map configuration submode. In this sample output, the question mark (?) online help function displays all the commands available under sampler map configuration submode:

```
RP/0/RSP0/CPU0:router(config)# sampler-map test
RP/0/RSP0/CPU0:router(config-sm)# ?

clear      Clear the uncommitted configuration
commit     Commit the configuration changes to running
describe   Describe a command without taking real actions
do         Run an exec command
exit       Exit from this submode
no         Negate a command or set its defaults
pwd        Commands used to reach current submode
random    Use random mode for sampling packets
root      Exit to the global configuration mode
show      Show contents of configuration
```

These restrictions prevent the NetFlow processes from using up all of the available CPU:

- NetFlow supports a policer rate of 35,000 packets per second per direction for each individual line card.
- NetFlow supports a policer rate of 50,000 packets per second per direction for each individual line card if Sampled NetFlow (SNF) is enabled in one direction (ingress or egress). Note that this limit does not apply if SNF is enabled in both directions. If SNF is enabled in both directions, then NetFlow supports 25,000 packets per second per direction for each individual line card.

Task ID	Task ID	Operations
	netflow	read, write

sampler-map**Examples**

This example shows how to use the **sampler-map** command to enter sampler map configuration submode for the monitor map called “map1:”

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# sampler-map map1
RP/0/RSP0/CPU0:router(config-sm)#
```

show flow exporter

To display flow exporter data, enter the **show flow exporter** command in EXEC mode.

show flow exporter [exporter_name] location node-id

Syntax Description	<p>exporter_name Identifies the flow exporter whose data you want to display.</p> <p>location node-id Location where the cache resides. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.</p> <p>Note Enter the show platform command to see the location of all nodes installed in the router.</p>				
Command Default	None				
Command Modes	EXEC mode				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow read</td><td></td></tr> </tbody> </table>	Task ID	Operations	netflow read	
Task ID	Operations				
netflow read					
Examples	<p>This example shows how to display flow exporter map data:</p> <pre>RP/0/RSP0/CPU0:router# show flow exporter fem1 location 0/0/CPU0 Flow Exporter: NFC Used by flow monitors: fmm4 Status: Normal Transport UDP Destination 12.24.39.0 (50001) Source 12.25.54.3 (5956) Flows exported: 0 (0 bytes) Flows dropped: 0 (0 bytes) Templates exported: 1 (88 bytes) Templates dropped: 0 (0 bytes) Option data exported: 0 (0 bytes) Option data dropped: 0 (0 bytes) Option templates exported: 2 (56 bytes)</pre>				

show flow exporter

```

Option templates dropped: 0 (0 bytes)

Packets exported: 3 (144 bytes)
Packets dropped: 0 (0 bytes)

Total export over last interval of:
  1 hour: 0 pkts
            0 bytes
            0 flows
  1 minute: 3 pkts
             144 bytes
             0 flows
  1 second: 0 pkts
             0 bytes
             0 flows

```

Table 1: show flow exporter Field Descriptions

Field	Description
Id	Identifies the flow exporter map.
Used by flow monitors	Name of the flow monitors associated with the specified flow exporter map.
Status	Status of the exporter. <ul style="list-style-type: none"> • Normal—Exporter is active and can export packets. • Disabled—Exporter cannot send out packets because the collector is unreachable or the configuration is incomplete.
Destination	Export destination address the current flow exporter map.
Flows exported	Flows exported, in bytes.
Flows dropped	Flows dropped, in bytes.
Templates exported	Templates exported, in bytes.
Templates dropped	Templates dropped, in bytes.
Option data exported	Option data exported, in bytes.
Option data dropped	Option data dropped, in bytes.
Option templates exported	Option templates exported, in bytes.
Option templates dropped	Option templates dropped, in bytes.
Packets exported:	Packets exported, in bytes.
Packets dropped	Packets dropped, in bytes.
Average export rate over interval of last:	Average export rate, in bytes/pkts. Information is displayed for intervals of the last hour, minute, and second.

show flow exporter-map

To display flow exporter map information for a specific node, enter the **show flow exporter-map** command in EXEC mode.

show flow exporter-map [name]

Syntax Description	<i>name</i> Name of the exporter map whose information you want to display.	
Command Default	None	
Command Modes	EXEC mode	
Command History	Release	Modification
	Release 3.9.1	This command was introduced.
	Release 6.0.1	This command was updated to display exporter version type IPFIX information.
	Release 7.10.1	The show command output was updated to display router-id information.
Usage Guidelines	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operations
	netflow	read
Examples	<p>This example shows how to configure IPFIX as an exporter verison in the exporter-map fem_ipfix:</p> <pre>RP/0/RSP0/CPU0:router# configure RP/0/RSP0/CPU0:router(config)# flow exporter-map fem_ipfix RP/0/RSP0/CPU0:router(config-fem)# destination 10.17.7.24 RP/0/RSP0/CPU0:router(config-fem)# transport udp 1025 RP/0/RSP0/CPU0:router(config-fem)# version ipfix RP/0/RSP0/CPU0:router(config-fem-ver)# options sampler-table timeout 1800 RP/0/RSP0/CPU0:router(config-fem-ver)# exit RP/0/RSP0/CPU0:router(config-fem)# exit RP/0/RSP0/CPU0:router(config)# exit</pre> <p>The show flow exporter-map command output shows IPFIX as an exporter version that we configured earlier in flow exporter map fem_ipfix:</p> <pre>RP/0/RSP0/CPU0:router# show flow exporter-map fem_ipfix Flow Exporter Map : fem_ipfix ----- Id : 2 DestinationIpAddr : 10.17.7.24</pre>	

show flow exporter-map

```

VRFName          : default
SourceIfName     :
SourceIpAddr    :
DSCP             : 0
TransportProtocol : UDP
TransportDestPort : 1025

Export Version: IPFIX
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout : 1800 seconds
  Interface-Table Export Timeout : 0 seconds
  Sampler-Table Export Timeout : 1800 seconds
  VRF-Table Export Timeout : 0 seconds

```

This example shows how to display flow exporter map information:

```

RP/0/RSP0/CPU0:router# show flow exporter-map map1

Flow Exporter Map : map1
-----
Id           : 2
DestinationIpAddr : 10.1.1.1
SourceIfName   : Loopback0
SourceIpAddr   : 10.1.1.1
DSCP          : 10
TransportProtocol : UDP
TransportDestPort : 1024

Export Version: 9
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout : 600 seconds
  Interface-Table Export Timeout : 1800 seconds
  Sampler-Table Export Timeout : 0 seconds

```

This example shows how to display flow exporter map with **router-id** information:

```

Router# show flow exporter-map E
Fri Mar 24 13:28:13.617 IST

Flow Exporter Map      : E
-----
Id           : 6
Packet-Length   : 1468
DestinationIpAddr :
VRFName        :
SourceIfName    :
SourceIpAddr    : Unsupported family type (0)
DSCP           : 0
TransportProtocol :
TransportDestPort :
TransportSourcePortSelectionMethod   :
Do Not Fragment   : Not Enabled
Router-Id       : 209.165.201.1

Export Version: 9
  Common Template Timeout : 1800 seconds
  Options Template Timeout : 1800 seconds
  Data Template Timeout : 1800 seconds
  Interface-Table Export Timeout : 0 seconds
  Sampler-Table Export Timeout : 0 seconds
  VRF-Table Export Timeout : 0 seconds

```

This table describes the significant fields shown in the display.

Table 2: show flow exporter-map Field Descriptions

Field	Description
Id	Identifies the flow exporter map.
DestinationIpAddr	Exports destination configuration.
SourceIfName	Source interface for this exporter map. You can specify the source interface with the flow exporter-map command.
SourceIpAddr	IP address of the source interface (SourceIfName).
DSCP	Differentiated services codepoint (DSCP) value for export packets. Note You can specify the DSCP with the flow exporter-map command.
TransportProtocol	Displays the configured transport protocol. Note Cisco IOS XR software supports the UDP transport protocol only. Note You can specify the transport protocol with the flow exporter-map command.
TransportDestPort	Displays the configured destination port for UDP packets.
Router-Id	Displays the configured router-id or agent-id.
Export Version	Displays the configured export format. Note Cisco IOS XR software supports export format version 9 only.
Common Template Timeout	Displays the configured common template timeout.
Options Template Timeout	Displays the configured options template timeout. Note You can specify the options template timeout with the flow exporter-map command.
Data Template Timeout	Displays the configured data template timeout. Note You can specify the data template timeout with the flow exporter-map command.

show flow exporter-map

Field	Description
Interface-Table Export Timeout	<p>Displays the export timeout value for the interface table.</p> <p>Note You can specify the export timeout for the interface table with the flow exporter-map command.</p>
Sampler-Table Export Timeout	<p>Displays the export timeout value for the sampler table.</p> <p>Note You can specify the export timeout for the sampler table with the flow exporter-map command.</p>

show flow monitor

To display flow monitor cache data in various formats, enter the **show flow monitor** command in EXEC mode.

To match on Access Control Lists (ACLs) and one or more fields:

```
show flow monitor monitor-name cache match {ipv4 {acl name | source-address match-options | destination-address match-options | protocol match-options | tos match-options} | ipv6 {acl name | source-address match-options | destination-address match-options | protocol match-options | tc match-options} | layer4 {source-port-overloaded match-options | destination-port-overloaded match-options | tcp-flags match-flags-options} | bgp {source-as match-options | destination-as match-options} | interface {ingress match-if-options | egress match-if-options} | timestamp {first match-options | last match-options} | counters {byte match-options | packets match-options} | misc {forwarding-status match-options | direction match-dir-options}}
```

To sort flow record information according to a particular field:

```
show flow monitor monitor-name cache sort {ipv4 {source-address | destination-address | tos | protocol} | ipv4 {source-address | destination-address | tc | protocol} | mpls {label-2 | label-3 | label-4 | label-5 | label-6 | label-type | prefix | top-label} | layer4 {source-port-overloaded | destination-port-overloaded} | bgp {source-as | destination-as} | timestamp {first | last} | counters {bytes | packets} | misc {forwarding-status | direction} {top | bottom} [entries]}
```

To include or exclude one or more fields in the **show flow monitor** command output:

```
show flow monitor monitor-name cache {include | exclude} {ipv4 {source-address | destination-address | tos | protocol} | ipv6 {source-address | destination-address | tc | flow-label | option-headers | protocol} | mpls {label-2 | label-3 | label-4 | label-5 | label-6 | top-label} | layer4 {source-port-overloaded | destination-port-overloaded} | bgp {source-as | destination-as} | timestamp {first | last} | counters {bytes | packets} | misc {forwarding-status match-options | direction match-dir-options}}
```

To display summarized flow record statistics:

```
show flow monitor monitor-name cache summary location node-id
```

To display only key field, packet, and byte information for the flow records:

```
show flow monitor monitor-name cache brief location node-id
```

To display flow record information for a particular node only:

```
show flow monitor monitor-name cache location node-id
```

Syntax Description

If you specified the **show flow monitor monitor-name cache match** command to match on ACL and one or more fields:

<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.

show flow monitor

match	Specifies match criteria for the display. Enter the match keyword followed by the ? command to see a complete list of possible match criteria.
ipv4	Specifies IPv4 fields.
ipv6	Specifies IPv6 fields.
acl <i>name</i>	Specifies an access list. Replace name with the <i>name</i> of the access whose information you want to display.
source-address <i>match-options</i>	Specifies source IP address match options. Possible match options are: <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the source-address keyword followed by the ? command to see a complete list of possible match criteria.</p>
destination-address	Specifies IPV4 or IPv6 destination address match options. Possible match options are: <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the destination-address keyword followed by the ? command to see a complete list of possible match criteria.</p>

tos <i>match-options</i>	<p>Compares fields and matches them based on the type of service value. Range is from 0 through 255. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the tos keyword followed by the ? command to see a complete list of possible match criteria.</p>
protocol <i>match-options</i>	<p>Compares fields and matches them based on the protocol value. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the protocol keyword followed by the ? command to see a complete list of possible match criteria.</p>
layer4	<p>Compares Layer 4 fields and matches them based on specific criteria. You can specify match criteria for any of the following Layer 4 fields:</p> <ul style="list-style-type: none"> • destination-port-overloaded • source-port-overloaded • tcp-flags <p>Note Enter the layer4 keyword followed by the ? command to see a complete list of possible Layer 4 fields to compare and match.</p>

show flow monitor

destination-port-overloaded	<p>Compares fields and matches them based on the destination-port-overloaded value. The destination port is matched if the protocol specified for that port is TCP or UDP.</p> <p>Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the destination-port-overloaded keyword followed by the ? command to see a complete list of possible match criteria.</p>
source-port-overloaded	<p>Compares fields and matches them based on the source-port-overloaded value.</p> <p>The source port is matched if the protocol specified for that port is one of the following:</p> <ul style="list-style-type: none"> • TCP—Range is from 0 through 65535. • UDP—Range is from 0 through 65535. • ICMP—Type or code is in range from 0 through 255. • IGMP—Type is in range from 0 through 255. <p>Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the source-port-overloaded keyword followed by the ? command to see a complete list of possible match criteria.</p>

tcp-flags <i>match-flags-options</i>	<p>Specifies TCP flags, as follows:</p> <ul style="list-style-type: none"> • all —Match all of the fields • any —Match any of the fields • none —Match none of the fields. <p>Note Enter the tcp-flags keyword followed by the ? command to see a complete list of possible match criteria.</p>
bgp	<p>Compares BGP fields and matches them based on specific criteria. You can specify match criteria for any of the following BGP fields:</p> <ul style="list-style-type: none"> • destination-as —Destination as. • source-as —Source as.
source-as <i>match-options</i>	<p>Compares and matches the BGP autonomous system number of the destination address.</p> <p>Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the source-as keyword followed by the ? command to see a complete list of possible match criteria.</p>
destination-as <i>match-options</i>	<p>Compares and matches the BGP autonomous system number of the source address. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the destination-as keyword followed by the ? command to see a complete list of possible match criteria.</p>

show flow monitor

timestamp	Specifies the time stamp for which to compare and match the specified criteria. Enter the first keyword or the last keyword to specify the time stamp whose criteria you want to compare.
first <i>match-options</i>	<p>Compares fields from the first time stamp and matches them based on the match-options value. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the first keyword followed by the ? command to see a complete list of possible match criteria.</p>
last <i>match-options</i>	<p>Compares fields from the last time stamp and matches them based on the match-if-options value. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the last keyword followed by the ? command to see a complete list of possible match criteria.</p>
counters	Specifies the counters for which to compare and match the specified criteria. Enter the byte keyword or the packets keyword to specify the counters whose criteria you want to compare.
byte <i>match-options</i>	<p>Compares bytes counter fields and matches them based on the match-options value. Possible match options are:</p> <ul style="list-style-type: none"> • eq —Match if equal to field value. • gt —Match if greater than field value. • lt —Match if less than field value. • neq —Match if not equal to field value. • range —Match if within the range of field values. <p>Note Enter the byte keyword followed by the ? command to see a complete list of possible match criteria.</p>

packets <i>match-options</i>	Compares packets counter fields and matches them based on the match-options value. Possible match options are: <ul style="list-style-type: none">• eq —Match if equal to field value.• gt —Match if greater than field value.• lt —Match if less than field value.• neq —Match if not equal to field value.• range —Match if within the range of field values. Note Enter the byte keyword followed by the ? command to see a complete list of possible match criteria.
misc	Specifies miscellaneous fields for which to compare and match the specified criteria. Enter the forwarding-status keyword or the direction keyword to specify the field whose criteria you want to compare.
forwarding-status <i>match-options</i>	Compares forwarding status fields and matches them based on the match-options value. Possible match options are: <ul style="list-style-type: none">• eq —Match if equal to field value.• gt —Match if greater than field value.• lt —Match if less than field value.• neq —Match if not equal to field value.• range —Match if within the range of field values. Enter the forwarding-status keyword followed by the ? command to see a complete list of possible match criteria.
direction <i>match-dir-options</i>	Compares information about the direction of the flow and matches it based on the match-options value. Possible match options are: <ul style="list-style-type: none">• eq —Match if equal to field value.• neq —Match if not equal to field value. Note Enter the direction keyword followed by the ? command to see a complete list of possible match criteria.
To sort flow record information according to a particular field:	
<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.

show flow monitor

sort	Determines sorting criteria for the show flow monitor command display.
ipv4	<p>Specifies sorting criteria for one of the following IPv4 fields:</p> <ul style="list-style-type: none"> • destination-address • source-address • protocol • tos <p>Note Enter the ipv4 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
ipv6	<p>Specifies sorting criteria for one of the following IPv6 fields:</p> <ul style="list-style-type: none"> • destination-address • source-address • protocol • tos <p>Note Enter the ipv6 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-address	<p>Displays IPv4 or IPv6 information for the source address according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the source-address keyword followed by the ? command to see a complete list of possible sorting criteria.</p>

destination-address	Displays IPv4 or IPv6 information for the destination address according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. Note Enter the destination-address keyword followed by the ? command to see a complete list of possible sorting criteria.
tos	Displays IPv4 type of service information according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. Note Enter the tos keyword followed by the ? command to see a complete list of possible sorting criteria.
tc	Displays IPv6 traffic class information according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. Note Enter the tc keyword followed by the ? command to see a complete list of possible sorting criteria.
protocol	Displays IPv4 or IPv6 protocol information according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. Note Enter the tos keyword followed by the ? command to see a complete list of possible sorting criteria.

show flow monitor

mpls	Specifies sorting criteria for one of the following MPLS fields: <ul style="list-style-type: none">• label-2• label-3• label-4• label-5• label-6• label-type• prefix• top-label <p>Note Enter the mpls keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
label-2	Displays MPLS information for the second label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.
label-3	Displays MPLS information for the third label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.
label-4	Displays MPLS information for the fourth label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.
label-5	Displays MPLS information for the fifth label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.
label-6	Displays MPLS information for the sixth label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.

label-type	Displays MPLS information for the specified type of label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries.
prefix	Displays MPLS information for the destination address. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries.
top-label	Displays MPLS information for the top label in the MPLS label stack. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries.
layer4	Specifies sorting criteria for one of the following Layer 4 fields: <ul style="list-style-type: none"> • source-port-overloaded • destination-port-overloaded <p>Note Enter the layer4 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-port-overloaded	Displays source port overload information according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the source-port-overloaded keyword followed by the ? command to see a complete list of possible sorting criteria.</p>

show flow monitor

destination-port-overloaded	<p>Displays destination port overload information according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the destination-port-overloaded keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
bgp	<p>Specifies sorting criteria for one of the following BGP fields:</p> <ul style="list-style-type: none"> • source-as • destination-as <p>Note Enter the layer4 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-as	<p>Displays information about the BGP source address autonomous system number according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the source-as keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
destination-as	<p>Displays information about the BGP destination address autonomous system number according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the destination-as keyword followed by the ? command to see a complete list of possible sorting criteria.</p>

timestamp	Specifies sorting criteria for the first or last time stamp. Enter the first keyword or the last keyword to specify the time stamp whose criteria you want to specify. Note Enter the timestamp keyword followed by the ? command to see a complete list of possible sorting criteria.
first	Displays information for the first time stamp according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries. Note Enter the first keyword followed by the ? command to see a complete list of possible sorting criteria.
last	Displays information for the last time stamp according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries. Note Enter the last keyword followed by the ? command to see a complete list of possible sorting criteria.
counters	Specifies sorting criteria for the bytes or packets counters. Follow the counters keyword with the byte keyword or the packets keyword to specify the counters whose criteria you want to compare.
bytes	Displays bytes counter information according to the specified sorting criteria. Possible sorting options are: <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries. Note Enter the bytes keyword followed by the ? command to see a complete list of possible sorting criteria.

show flow monitor

packets	<p>Displays packets counter information according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the packets keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
misc	<p>Specifies sorting criteria for miscellaneous fields. Follow the misc keyword with the forwarding-status keyword or the direction keyword to specify the counters whose criteria you want to compare.</p>
forwarding-status	<p>Displays forwarding status information according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the forwarding-status keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
direction	<p>Displays information about the direction of the flow according to the specified sorting criteria. Possible sorting options are:</p> <ul style="list-style-type: none"> • top —Displays top cache entries. • bottom —Displays bottom cache entries. <p>Note Enter the direction keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
top	<p>Displays top cache entries. Replace records with the number of records you want to display.</p> <p>Note You can follow the top keyword with the optional entries argument to specify the number of records to display.</p>

bottom	Displays bottom cache entries. Replace records with the number of records you want to display. Note You can follow the bottom keyword with the optional entries argument to specify the number of records to display.
<i>entries</i>	Number of records to display. Range is from 1 through 1000.
To include or exclude one or more fields in the show flow monitor command output:	
<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.
include	Includes the specified fields in the display output. Enter the include keyword, followed by the keyword or keywords that specify the fields to include. Note To see a list of fields that can be included, enter the include keyword, followed by the ? command.
exclude	Excludes the specified fields in the display output. Enter the exclude keyword, followed by the keyword or keywords that specify the fields to exclude. Note To see a list of fields that can be excluded, enter the exclude keyword, followed by the ? command.
ipv4	Includes or excludes one of the following IPv4 fields in the command output: <ul style="list-style-type: none">• destination-address• source-address• protocol• tos Note Enter the ipv4 keyword followed by the ? command to see a complete list of possible sorting criteria.

show flow monitor

ipv6	<p>Includes or excludes one of the following IPv6 fields in the command output:</p> <ul style="list-style-type: none"> • destination-address • flow-label • option-headers • source-address • protocol • tos <p>Note Enter the ipv6 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-address	Includes or excludes IPV4 or IPV6 information for the source address in the command output.
destination-address	Includes or excludes IPV4 or IPV6 information for the destination address in the command output.
flow-label	Includes or excludes information about the IPv6 flow label in the command output. The flow label is the 20-bit flow label id present in every IPv6 packet header.
option-headers	Includes or excludes IPV6 information for the option headers in the command output. The option header is a bit mask that indicates which options headers are present in the IPv6 header.
tos	Includes or excludes IPV4 type of service information in the command output.
tc	Includes or excludes IPV6 traffic class information in the command output.
protocol	Includes or excludes IPV4 or IPV6 protocol information in the command output.

mpls	<p>Includes or excludes one of the following MPLS fields in the command output:</p> <ul style="list-style-type: none"> • label-2 • label-3 • label-4 • label-5 • label-6 • top-label <p>Note Enter the mpls keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
label-2	Includes or excludes MPLS information for the second label in the MPLS label stack.
label-3	Includes or excludes MPLS information for the third label in the MPLS label stack.
label-4	Includes or excludes MPLS information for the fourth label in the MPLS label stack.
label-5	Includes or excludes MPLS information for the fifth label in the MPLS label stack.
label-6	Includes or excludes MPLS information for the sixth label in the MPLS label stack.
top-label	Includes or excludes MPLS information for the top label in the MPLS label stack.
layer4	<p>Includes or excludes one of the following the following Layer 4 fields in the command output:</p> <ul style="list-style-type: none"> • source-port-overloaded • destination-port-overloaded <p>Note Enter the layer4 keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-port-overloaded	Includes or excludes source port overload information in the command output.

show flow monitor

destination-port-overloaded	Includes or excludes destination port overload information in the command output. <ul style="list-style-type: none">• top —Displays top cache entries.• bottom —Displays bottom cache entries.
bgp	Includes or excludes the following BGP fields in the command output: <ul style="list-style-type: none">• source-as• destination-as <p>Note Enter the bgp keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
source-as	Includes or excludes information about the BGP source address autonomous system number in the command output.
destination-as	Includes or excludes information about the BGP destination address autonomous system number in the command output.
timestamp	Includes or excludes information from the first or last time stamp in the command output. Enter the first keyword or the last keyword to include or exclude information about a specific time stamp. <p>Note Enter the timestamp keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
first	Includes or excludes information for the first time stamp in the command output.
last	Includes or excludes information for the first time stamp in the command output.
counters	Includes or excludes bytes or packets counters in the command output. Follow the counters keyword with the byte keyword or the packets keyword to include or exclude particular counters. <p>Note Enter the counters keyword followed by the ? command to see a complete list of possible sorting criteria.</p>
bytes	Includes or excludes bytes counter information in the command output.

packets	Includes or excludes packets counter information in the command output.
misc	Includes or excludes information for miscellaneous fields in the command output. Follow the misc keyword with the forwarding-status keyword or the direction keyword to specify the field you want to include or exclude. Note Enter the misc keyword followed by the ? command to see a complete list of possible sorting criteria.
forwarding-status	Includes or excludes forwarding status information in the command output.
direction	Includes or excludes information about the direction of the flow in the command output.
top	Includes or excludes top cache entries in the command output. Replace records with the number of <i>records</i> you want to display.
bottom	Includes or excludes bottom cache entries. Replace records with the number of <i>records</i> you want to display
<i>entries</i>	Number of records to display. Range is from 1 through 1000.
To display summarized flow record statistics:	
<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.
summary	Displays summarized flow monitor information only.
<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.
brief	Abbreviates the show flow monitor command output.
To display flow record information for a particular node only:	
<i>monitor-name</i>	Flow monitor map whose details you want to display.
cache	Displays details about the flow monitor cache.

show flow monitor

location node-id	Identifies the node whose flow exporter statistics you want to clear, or whose flow exporter statistics collector you want to restart. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.
	<p>Note Enter the location keyword followed by the ? command to see a complete list of possible sorting criteria.</p>

Command Default None**Command Modes** EXEC mode**Command History** **Release** **Modification**

Release 4.0.0 The interface keyword options were removed.

Usage Guidelines

Note To collect source and destination AS information, you must enable BGP on the relevant BGP AFI/SAFI. Unless this is done, all AS numbers in the flow records are displayed as 0.

Keep these information in mind when using the **show flow monitor** command:

- The **show flow monitor** command can include combinations of these options:
 - **format**
 - **match**
 - **include**
 - **exclude**
 - **sort**
 - **summary**
 - **location**
- We do not recommend including the **summary** option with the **sort** and **format** options.
- The mutually exclusive options are **summary**, **brief**, **include**, and **exclude**.
- To see a list of fields that can be included after a keyword, enter the **?** command, as shown in this example:

```
RP/0/RSP0/CPU0:router# show flow monitor map1 cache summary ?
```

```
brief      Show just the key fields
exclude    Exclude field
format     Display format
include    Include field
```

location Specify a location
 match Match criteria
 sort Sorting criteria

Task ID	Task Operations ID
	netflow read

Examples

This example shows how to display flow monitor data for a specific monitor map cache in the location 0/0/CPU0 :

```
RP/0/RSP0/CPU0:router# show flow monitor fmm2 cache loc 0/0/CPU0
```

```

Cache summary for Flow Monitor fmm2:
Cache size: 65535
Current entries: 4
High Watermark: 62258
Flows added: 4
Flows not added: 0
Ager Polls: 60
  - Active timeout 0
  - Inactive timeout 0
  - TCP FIN flag 0
  - Watermark aged 0
  - Emergency aged 0
  - Counter wrap aged 0
  - Total 0
Periodic export:
  - Counter wrap 0
  - TCP FIN flag 0
Flows exported 0
Matching entries: 4

IPV4SrcAddr      IPV4DstAddr      L4SrcPort  L4DestPort BGPDstOrigAS BGPSrcOrigAS
IPV4DstPrfxLen
IPV4SrcPrfxLen  IPV4Prot IPV4TOS  InputInterface OutputInterface L4TCPFlags  ForwardStatus
ForwardReason FirstSwitched  LastSwitched ByteCount  PacketCount Dir Sampler ID
17.17.17.2      18.18.18.2      0          0          0          0          24
  24           $                  0          0          0          0          Fwd
  61           normal   HundredGigE /0/0/8      HundredGigE 0/0/0/12      0          Fwd
  0           00
00:02:43:800 00 00:02:49:980 37200      620        In 0
18.18.18.2      17.17.17.2      0          0          0          0          24
  24           $                  0          0          0          0          Fwd
  61           normal   HundredGigE 0/0/0/12      HundredGigE 0/0/0/8      0          Fwd
  0           00
00:02:43:791 00 00:02:49:980 37200      620        In 0
17.17.17.2      18.18.18.2      0          0          0          0          24
  0           $                  0          0          0          0          Fwd
  61           normal   HundredGigE 0/0/0/8      HundredGigE 0/0/0/12      0          Fwd
  0           00
00:02:43:798 00 00:02:49:980 34720      620        Out 0
18.18.18.2      17.17.17.2      0          0          0          0          24
  0           $                  0          0          0          0          Fwd
  61           normal   HundredGigE 0/0/0/12      HundredGigE 0/0/0/8      0          Fwd
  0           00
00:02:43:797 00 00:02:49:980 34720      620        Out 0
L4SrcPort  L4DestPort BGPDstOrigAS BGPSrcOrigAS IPV4DstPrfxLen

```

show flow monitor

This table describes the significant fields shown in the display.

Table 3: show flow monitor Field Descriptions

Field	Description
Cache summary for Flow Monitor fmm2	<p>Displays general cache information for the specified flow monitor. The following information is displayed</p> <ul style="list-style-type: none"> • Cache size for the specified flow monitor map • Current number of entries in the cache • High watermark for this cache • Number of flows added to the cache • Number of flows not added to the cache
Ager Polls	<p>Displays the following ager statistics:</p> <ul style="list-style-type: none"> • Active timeout • Inactive timeout • TCP FIN flag • Watermark aged • Emergency aged • Counter wrap aged • Total
Periodic export	<ul style="list-style-type: none"> • Counter wrap • TCP FIN flag
Cache summary for Flow Monitor fmm2	<p>Displays general cache information for the specified flow monitor. The following information is displayed</p> <ul style="list-style-type: none"> • Cache size for the specified flow monitor map • Current number of entries in the cache • High watermark for this cache • Number of flows added to the cache • Number of flows not added to the cache
FirstSwitched	<p>Displays the system uptime at which the first packet of this flow was switched. The display format is days hours:minutes:seconds:milliseconds</p>
LastSwitched	<p>Displays the system uptime at which the last packet of this flow was switched. The display format is days hours:minutes:seconds:milliseconds</p>

show flow monitor-map

To display flow monitor map data, enter the **show flow monitor-map** command in EXEC mode.

show flow monitor-map *map-name* Optional: [srv6]

Syntax Description	<i>map-name</i> Name of the monitor map whose data you want to display.	
Command Default	None	
Command Modes	EXEC mode	
Command History		
	Release	Modification
	Release 7.8.1	The show flow monitor-map command output was modified to display the monitor-map data for ipv6 srv6 subtypes.
	Release 3.9.1	This command was introduced.
	Release 3.4.1	The ipv4-raw record map name was replaced with ipv4.
Usage Guidelines		
	No specific guidelines impact the use of this command.	
Task ID	Task ID	Operations
	netflow	read
Examples		
	This example shows how to display IPv4 monitor-map data for a specific flow:	
<pre>RP/0/RSP0/CPU0:router# show flow monitor-map map1</pre> <pre>Flow Monitor Map : map1</pre> <pre>-----</pre> <pre>Id: 1 RecordMapName: ipv4 ExportMapName: NFC CacheAgingMode: Permanent CacheMaxEntries: 10000 CacheActiveTout: N/A CacheInactiveTout: N/A CacheUpdateTout: 60 seconds</pre>		
	This example shows how to display SRv6 monitor-map data for a specific flow:	
<pre>RP/0/RSP0/CPU0:router# show flow monitor-map MON-MAP-1</pre> <pre>Flow Monitor Map : MON</pre> <pre>-----</pre> <pre>Id: 1</pre>		

show flow monitor-map

```

RecordMapName:      srv6
ExportMapName:      EXP
CacheAgingMode:    Normal
CacheMaxEntries:   65535
CacheActiveTout:   101 seconds
CacheInactiveTout: 15 seconds
CacheUpdateTout:   N/A
CacheRateLimit:    2000
HwCacheExists:     False
HwCacheInactTout: 50

```

This table describes the significant fields shown in the display.

Table 4: show flow monitor-map Field Descriptions

Field	Description
Flow Monitor Map	Name of the flow monitor map whose information is display in the show flow monitor-map command output.
Id	Number that identifies the flow monitor map.
RecordMapName	Name of the flow record map that is associated with this monitor map. The RecordMapName indicates the type of packets NetFlow captures as they leave the router.
ExportMapName	Name of the export map that is associated with this monitor map.
CacheAgingMode	Current aging mode configured on this cache. “Permanent” indicates that the removal of entries from the monitor map flow cache is disabled. Note To configure the number of entries allowed in the monitor map flow cache, enter the cache entries command in flow monitor map configuration mode. To disable the removal of entries from the monitor map flow cache, enter the cache permanent command in flow monitor map configuration mode.
CacheMaxEntries	Number of flow entries currently allowed in the flow cache before the oldest entry is removed. Note To modify the number of entries in the monitor map flow cache, enter the cache entries command in flow monitor map configuration mode
CacheActiveTout	Active flow timeout configured for this cache, in seconds. Note To modify the configured active flow timeout, use the cache timeout command in flow monitor map configuration mode.
CacheInactiveTout	Inactive flow timeout configured for this cache, in seconds. Note To modify the configured inactive flow timeout, use the cache timeout command in flow monitor map configuration mode.

Field	Description
CacheUpdateTout	Update timeout configured for this cache, in seconds. Note To modify the configured update timeout, use the cache timeout command in flow monitor map configuration mode.

This example shows how to display monitor-map data for a specific IPv6 flow:

```
RP/0/RSP0/CPU0:router# show flow monitor-map map2

Tue Jan 22 00:15:53.424 PST
Flow Monitor Map : map2
-----
Id: 1
RecordMapName: ipv6-destination
CacheAgingMode: Normal
CacheMaxEntries: 65535
CacheActiveTout: 1800 seconds
CacheInactiveTout: 15 seconds
CacheUpdateTout: N/A
```

show flow platform producer statistics location

show flow platform producer statistics location

To display statistics collected by the NetFlow producer, use the **show flow platform producer statistics location** command in EXEC mode.

show flow platform producer statistics location node-id

Syntax Description

node-id Location of the node whose NetFlow producer statistics you want to display. The *node-id* is expressed in the *rack/slot/module* notation.

Note

Enter the **show platform** command to see the location of all nodes installed in the router.

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
---------	--------------

Release 3.9.1 This command was introduced.

Usage Guidelines

No specific guidelines impact the use of this command.

Task ID

Task ID	Operations
---------	------------

netflow read

Examples

This example shows how to display statistics collected by the NetFlow producer for the CPU card in slot 0:

```
# show flow platform producer statistics location 0/0/CPU0
Thu Oct 29 09:49:35.771 UTC
Netflow Platform Producer Counters:
IPv4 Ingress Packets: 41447246
IPv4 Egress Packets: 41447242
IPv6 Ingress Packets: 0
IPv6 Egress Packets: 0
MPLS Ingress Packets: 0
MPLS Egress Packets: 0
Drops (no space): 0
Drops (other): 0
Unknown Ingress Packets: 0
Unknown Egress Packets: 0
Worker waiting: 4677
SPP Packets: 2032602
Flow Packets: 82894488
Flow Packets per SPP Frame: 40
```

This table describes the significant fields shown in the display.

Table 5: show flow platform producer statistics Field Descriptions

Field	Description
IPv4 Ingress Packets	Number of IPV4 packets that were received from the remote end.
IPv4 Egress Packets	Number of transmitted IPV4 packets.
MPLS Ingress Packets	Number of MPLS packets that were received from the remote end.
MPLS Egress Packets	Number of transmitted MPLS packets.
Drops (no space)	Number of packets that the producer could not enqueue to the NetFlow server because the server input ring was full.
Drops (other)	Number of packets that the producer could not enqueue to the NetFlow server due to errors other than the server input ring being full.
Unknown Ingress Packets	Number of unrecognized packets received from the remote end that were dropped.
Unknown Egress Packets	Number of packets transmitted to the remote end that were dropped because they were not recognized by the remote end.
Worker waiting	Number of times that the producer needed to use the server. Note This field is strictly informational and does not indicate any error.
SPP Packets	Number of sequenced packet protocol (SPP) packets transmitted to the remote end.
Flow Packets	Number of flow packets transmitted to the remote end.
Flow Packets per SPP Frame	Number of flow packets per SPP frame transmitted to the remote end.

show flow platform nfea sampler

show flow platform nfea sampler

To display sampler map information, enter the **show sampler-map** command in EXEC mode.

show flow platform nfea sampler [detaillocation]

Syntax Description	<i>detail</i> Displays flow platform nfea sampler detail information				
	<i>location</i> Displays the node number				
Command Default	None				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read</td></tr> </tbody> </table>	Task ID	Operations	netflow	read
Task ID	Operations				
netflow	read				

Examples The following example shows how to display flow platform nfea samp detail :

```
RP/0/RSP0/CPU0:router# show flow platform nfea samp
RP/0/RSP0/CPU0:router#show flow pla nfea samp detail loc 0/1/cpu0
Fri Sep 18 16:30:08.435 UTC
Sampler Name: nf_samp
id: 1, sp_id: 0, interval: 1, ref_count: 2
Attached Interface List Info
Interface Name: GigabitEthernet0/1/0/1, Direction: Ingress, NP ID: 3
Flow Type(s) Configured: IPv4,
Checkpoint Record ID: 12184
Interface Name: GigabitEthernet0/1/0/31, Direction: Ingress, NP ID: 0
Flow Type(s) Configured: IPv4,
Checkpoint Record ID: 12088
Sampler Name: nf_samp1
id: 2, sp_id: 1, interval: 2, ref_count: 1
Attached Interface List Info
Interface Name: GigabitEthernet0/1/0/1, Direction: Egress, NP ID: 3
Flow Type(s) Configured: IPv4,
Checkpoint Record ID: 12248
```

show flow platform nfea interface

To display flow map platfrom information, enter the **show flow platform nfea interface** command in EXEC mode.

```
show flow platform nfea interface type interface-path-id {ingress|egress} location location node id
```

Syntax Description	<i>interface-path-id</i> Physical interface or virtual interface.
	<i>egress</i> Egress direction
	<i>ingress</i> Ingress direction
	<i>location</i> Specifies the location

Command Default	None
------------------------	------

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
		netflow read

Examples	The following example shows how to display flow map platfrom information:
-----------------	---

```
RP/0/RSP0/CPU0:router# show flow platform nfea interface bundle-ether1 ingress location 0/1/CPU0
```

show flow platform nfea sp location

show flow platform nfea sp location

To display sampling profile information, enter the **show flow platform nfea sp location** command in EXEC mode.

show flow platform nfea sp location node-id

Syntax Description	location node-id Specifies the location node number. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.
---------------------------	---

Command Default	Default value for the output when monitor is not configured is all zeros.
------------------------	---

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
------------------------	----------------	---------------------

Release 3.9.1	This command was introduced.
---------------	------------------------------

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
----------------	----------------	-------------------

netflow	read
---------	------

Examples	The following example shows how to display sampling profile information:
-----------------	--

```
RP/0/RSP0/CPU0:router# show flow platform nfea sp location 0/1/CPU0
```

show flow platform nfea policer np

To display policer rate information, enter the **show flow platform nfea policer np** command in EXEC mode.

show flow platform nfea policer np node-id

Syntax Description	<i>node-id</i> Identifies the location node number.				
Command Default	The Default values depends on how many NPs are programmed with the netflow, for example, if the interface is configured on only one NP with netflow, the output will be 100,000; if more NPs are configured, the output will be divided by the number of NPs; if no netflow is configured on a particular NP, the output is 0				
Command Modes	EXEC mode				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 3.9.1</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				

Usage Guidelines When Netflow is applied on PWHE interfaces, the *ing_Lnks* and *egr_Lnks* fields in the **show flow platform nfea policer np** command are not updated.

This issue is observed in the third and fourth generation of ASR 9000 Enhanced Ethernet line cards.



Note The *ing_Lnks* field indicates that the Netflow is configured in ingress direction for a particular interface corresponding to the NP. Similarly, *eng_Lnks* indicates that the Netflow is configured in egress direction.

Task ID	Task ID	Operations
	netflow	read

Examples The following example shows how to display sampler map information for a router:

```
RP/0/RSP0/CPU0:router# show flow platform nfea policer np 3 location 0/0/CPU0
```

show flow platform nfea bundle

show flow platform nfea bundle

To display bundle ether interface location information, enter the **show flow platform nfea bundle** command in EXEC mode.

show flow platform nfea bundle bundle-ether 100 location node-id

Syntax Description	location node-id The node-id is expressed in the rack/slot/module notation.
---------------------------	--

Command Default	None
------------------------	------

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
------------------------	----------------	---------------------

Release 3.9.1	This command was introduced.
---------------	------------------------------

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
----------------	----------------	-------------------

netflow	read
---------	------

Examples

The following example shows how to display bundle ether interface location information:

```
RP/0/RSP0/CPU0:router# show flow platform nfea bundle bundle-ether 100 location 0/$
```

show flow platform nfea chkp

To display checkpoint information, enter the **show flow platform nfea chkp** command in EXEC mode.

show flow platform nfea chkp [*checkpoint table number*] [*intfpolicersp*] [*checkpoint record number*] [**location node-id**]

Syntax Description	<0-2>	Displays checkpoint table number.
	<i>intf</i>	Displays interface checkpoint table.
	<i>policer</i>	Displays policer checkpoint table.
	<i>sp</i>	Displays sp checkpoint table.
	<1-4294967295>	Displays the checkpoint record number.

Command Default Default values should be all zeros, when no interface is configured with monitor in the location.

Command Modes EXEC mode

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Usage Guidelines No specific guidelines impact the use of this command.

Task ID	Task ID	Operations
		netflow read

Examples The following example shows how to display checkpoint information:

```
RP/0/RSP0/CPU0:router# show flow platform nfea chkpt policer all location 0/0/CPU0
RP/0/RSP0/CPU0:router# show flow platform nfea chkpt intf all location 0/0/CPU0
RP/0/RSP0/CPU0:router# show flow platform nfea chkpt sp all location 0/0/CPU0
```

```
show flow platform pal-cpp chkpt object
```

show flow platform pal-cpp chkpt object

To display Netflow CPP platform checkpoint information, use the **show flow platform pal-cpp chkpt object** command in EXEC mode.

```
show flow platform pal-cpp chkpt object [number] location node-id
```

Syntax Description	<p>number Displays checkpoint record number. Range is 1-4294967295.</p> <p>location node-id Specifies the location node number. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation</p>				
Command Default	None				
Command Modes	EXEC mode				
Command History	<table> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 4.0.0</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 4.0.0	This command was introduced.
Release	Modification				
Release 4.0.0	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read</td></tr> </tbody> </table>	Task ID	Operations	netflow	read
Task ID	Operations				
netflow	read				
Examples	The following example shows how to display the checkpoint information for 0/1/CPU0:				

```
RP/0/RSP0/CPU0:router# show flow platform pal-cpp chkpt object location 0/1/CPU0
```

show flow platform pal-cpp object

To display Netflow CPP platform layer object information, use the **show flow platform pal-cpp object** command in EXEC mode.

show flow platform pal-cpp object {all | fmm name | fem name | fsm name} location node-id

Syntax Description	all Displays all flow object information. fmm Displays flow monitor information. fem Displays flow exporter information. fsm Displays flow sampler information. name Flow name. location node-id Specifies the location node number. The node-id argument is expressed in the rack/slot/module notation				
Command Default	None				
Command Modes	EXEC mode				
Command History	<table> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 4.0.0</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 4.0.0	This command was introduced.
Release	Modification				
Release 4.0.0	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				
Task ID	<table> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow read</td><td></td></tr> </tbody> </table>	Task ID	Operations	netflow read	
Task ID	Operations				
netflow read					
Examples	The following example shows how to display all flow object information for location 0/1/CPU0:				

```
RP/0/RSP0/CPU0:router# show flow platform pal-cpp object all location 0/1/CPU0
```

show controllers pse qfp feature fnf datapath

show controllers pse qfp feature fnf datapath

To display QFP Netflow Datapath information on interfaces, use the **show controllers pse qfp feature fnf datapath** command in EXEC mode.

```
show controllers pse qfp feature fnf datapath {all | all-detail | builder-program | cache | cache-state | exporter | monitor | monitor-state | sampler | sampler-state} type interface-path-id
```

Syntax Description	
all	Displays netflow information.
all-detail	Displays detailed netflow information.
builder-program	Displays builder program.
cache	Displays cache structure.
cache-state	Displays cache_state structure.
exporter	Displays exporter.
monitor	Displays monitor structure.
monitor-state	Displays monitor_state structure
sampler	Displays sampler structure.
sampler-state	Displays sampler_state structure.
type	Interface type. For more information, use the question mark (?) online help function.
<i>interface-path-id</i>	Physical interface or virtual interface.

Note

Use the **show interfaces** command to see a list of all interfaces currently configured on the router.

For more information about the syntax for the router, use the question mark (?) online help function.

Command Default	None				
Command Modes	EXEC mode				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 4.0.0</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 4.0.0	This command was introduced.
Release	Modification				
Release 4.0.0	This command was introduced.				
Usage Guidelines	No specific guidelines impact the use of this command.				

Task ID	Task Operations ID
	netflow read

Examples

The following example shows how to display datapath information for all interfaces:

```
RP/0/RSP0/CPU0:router# show controllers pse qfp feature fnf datapath all ?
    ATM           ATM Network Interface(s)
    Bundle-Ether  Aggregated Ethernet interface(s)
    Bundle-POS   Aggregated POS interface(s)
    GigabitEthernet GigabitEthernet/IEEE 802.3 interface(s)
    Loopback      Loopback interface(s)
    MgmtEth       Ethernet/IEEE 802.3 interface(s)
    Multilink     Multilink network interface(s)
    Null          Null interface
    POS           Packet over SONET/SDH network interface(s)
    Serial         Serial network interface(s)
    TenGigE       TenGigabitEthernet/IEEE 802.3 interface(s)
    WORD          Other interface
    tunnel-gte    MPLS Traffic Engineering GMPLS Tunnel interface
    tunnel-ip     GRE/IPinIP Tunnel Interface(s)
    tunnel-ipsec  IPSec Tunnel interface(s)
    tunnel-mte   MPLS Traffic Engineering P2MP Tunnel interface(s)
    tunnel-te    MPLS Traffic Engineering Tunnel interface(s)
```

show flow trace platform producer location

show flow trace platform producer location

To trace the information for all or specified netflow processes on all or specified location.

show flow trace platform producer *location-id*

Syntax Description	<i>location-id</i> Displays the location
---------------------------	--

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
		netflow read

Examples	The following example shows how to display sampler map information for a router:
-----------------	--

```
RP/0/RSP0/CPU0:router# show flow trace platform producer location 0/0/CPU0
```

show flow trace ea location

```
show flow trace platform producer location node-id
```

Syntax Description	<i>node-id</i> The <i>node-id</i> is expressed in the <i>rack/slot/module</i> notation.
---------------------------	---

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
	Release 3.9.1	This command was introduced.

Usage Guidelines	No specific guidelines impact the use of this command.
-------------------------	--

Task ID	Task ID	Operations
		netflow read

Examples	The following example shows how to display sampler map information for a router:
-----------------	--

```
RP/0/RSP0/CPU0:router# show flow trace ea location 0/0/CPU0
```

source (NetFlow)

To configure a source interface for the current collector, use the **source** command in flow exporter map configuration mode. To remove a configured source interface, use the **no** form of this command.

source type interface-path-id

Syntax Description	<p><i>type</i> Interface type. For more information, use the question mark (?) online help function.</p> <p><i>interface-path-id</i> Physical interface or virtual interface.</p> <p>Note Use the show interfaces command to see a list of all interfaces currently configured on the router.</p> <p>For more information about the syntax for the router, use the question mark (?) online help function.</p>				
Command Default	None				
Command Modes	Flow exporter map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.
Release	Modification				
Release 3.9.1	This command was introduced.				
Usage Guidelines	<p>For the <i>interface-path-id</i> argument, use the following guidelines:</p> <ul style="list-style-type: none"> • If specifying T1/E1/DS0 physical interfaces, the naming notation is <i>rack/slot/module/port/t1-num</i>: • <i>channel-group-number</i>. If specifying other physical interface types, the naming notation is <i>rack/slot/module/port</i>. The slash between values is required as part of the notation. An explanation of each component of the naming notation is as follows: <ul style="list-style-type: none"> • <i>rack</i>: Chassis number of the rack. • <i>slot</i>: Physical slot number of the modular services card or line card. • <i>module</i>: Module number. A physical layer interface module (PLIM) is always 0. Shared port adapters (SPAs) are referenced by their subslot number. • <i>port</i>: Physical port number of the T3 controller. • <i>t1-num</i> : T1 or E1 channel number. T1 channels range from 1 to 24; E1 channels range from 1 to 31. • <i>channel-group-number</i> : Time slot number. T1 time slots range from 1 to 24; E1 time slots range from 1 to 31. The <i>channel-group-number</i> is preceded by a colon and not a slash. • If specifying a virtual interface, the number range varies, depending on interface type. 				

Task ID	Task ID	Operations
	netflow	read, write

Examples

This example shows how to configure a physical interface as a source for the current collector:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem) # source GigabitEthernet 0/1/0/0
```

This example shows how to configure a virtual interface as a source for the current collector. In this example, the source is an Ethernet bundle:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem) # source Bundle-Ether 1
```

Related Commands

Command	Description
flow exporter-map, on page 16	Creates a flow exporter map
flow monitor-map, on page 18	Creates and configures a flow monitor map
show flow exporter, on page 35	Displays flow exporter data
show flow exporter-map, on page 37	Displays flow exporter map information for a specific node.

template (NetFlow)

To configure the export timeout value for the data and options templates, enter the **template** command in flow exporter map version configuration mode. To remove a configured template export timeout value, use the **no** form of this command.

template [data | options] timeout seconds

Syntax Description	data (Optional) Specifies the data template. options (Optional) Specifies the options template. timeout seconds Configures the timeout value for the specified template, or for both the data and options templates. Replace <i>seconds</i> with the export timeout value. Range is from 1 through 604800 seconds.								
Command Default	Default timeout value for data and options template is 1800 seconds.								
Command Modes	Flow exporter map version configuration								
Command History	<table border="1"> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.				
Release	Modification								
Release 3.9.1	This command was introduced.								
Usage Guidelines	No specific guidelines impact the use of this command.								
Task ID	<table border="1"> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td>netflow</td><td>read, write</td></tr> </tbody> </table>	Task ID	Operations	netflow	read, write				
Task ID	Operations								
netflow	read, write								
Examples	<p>This example shows how to configure the export timeout value for the data template to be 300 seconds:</p> <pre>RP/0/RSP0/CPU0:router# configure RP/0/RSP0/CPU0:router(config)# flow exporter-map fem1 RP/0/RSP0/CPU0:router(config-fem)# version v9 RP/0/RSP0/CPU0:router(config-fem-ver)# template data timeout 300</pre>								
Related Commands	<table border="1"> <thead> <tr> <th>Command</th><th>Description</th></tr> </thead> <tbody> <tr> <td>flow exporter-map, on page 16</td><td>Creates a flow exporter map</td></tr> <tr> <td>flow monitor-map, on page 18</td><td>Creates and configures a flow monitor map</td></tr> <tr> <td>show flow exporter, on page 35</td><td>Displays flow exporter data</td></tr> </tbody> </table>	Command	Description	flow exporter-map, on page 16	Creates a flow exporter map	flow monitor-map, on page 18	Creates and configures a flow monitor map	show flow exporter, on page 35	Displays flow exporter data
Command	Description								
flow exporter-map, on page 16	Creates a flow exporter map								
flow monitor-map, on page 18	Creates and configures a flow monitor map								
show flow exporter, on page 35	Displays flow exporter data								

Command	Description
show flow exporter-map, on page 37	Displays flow exporter map information for a specific node.

transport udp

transport udp

To configure the destination port for User Datagram Protocol (UDP) packets, enter the **transport udp** command in flow exporter map configuration mode. To remove a configured destination port, use the **no** form of this command.

transport udp *port_value*

Syntax Description	<i>port_value</i> Destination port for UDP packets. Replace <i>port</i> with the destination port value. Range is from 1024 through 65535.										
Command Default	None										
Command Modes	Flow exporter map configuration										
Command History	<table> <thead> <tr> <th>Release</th><th>Modification</th></tr> </thead> <tbody> <tr> <td>Release 3.9.1</td><td>This command was introduced.</td></tr> </tbody> </table>	Release	Modification	Release 3.9.1	This command was introduced.						
Release	Modification										
Release 3.9.1	This command was introduced.										
Usage Guidelines	No specific guidelines impact the use of this command.										
Task ID	<table> <thead> <tr> <th>Task ID</th><th>Operations</th></tr> </thead> <tbody> <tr> <td></td><td>netflow read, write</td></tr> </tbody> </table>	Task ID	Operations		netflow read, write						
Task ID	Operations										
	netflow read, write										
Examples	This example shows how to configure the destination port for UDP packets:										
	<pre>RP/0/RSP0/CPU0:router# configure RP/0/RSP0/CPU0:router(config)# flow exporter-map map1 RP/0/RSP0/CPU0:router(config-fem)# transport udp 1030</pre>										
Related Commands	<table> <thead> <tr> <th>Command</th><th>Description</th></tr> </thead> <tbody> <tr> <td>flow exporter-map, on page 16</td><td>Creates a flow exporter map</td></tr> <tr> <td>flow monitor-map, on page 18</td><td>Creates and configures a flow monitor map</td></tr> <tr> <td>show flow exporter, on page 35</td><td>Displays flow exporter data</td></tr> <tr> <td>show flow exporter-map, on page 37</td><td>Displays flow exporter map information for a specific node.</td></tr> </tbody> </table>	Command	Description	flow exporter-map, on page 16	Creates a flow exporter map	flow monitor-map, on page 18	Creates and configures a flow monitor map	show flow exporter, on page 35	Displays flow exporter data	show flow exporter-map, on page 37	Displays flow exporter map information for a specific node.
Command	Description										
flow exporter-map, on page 16	Creates a flow exporter map										
flow monitor-map, on page 18	Creates and configures a flow monitor map										
show flow exporter, on page 35	Displays flow exporter data										
show flow exporter-map, on page 37	Displays flow exporter map information for a specific node.										

version v9

To enter flow exporter map version configuration submode so that you can configure export version parameters, enter the **version v9** command in flow exporter map configuration mode. To remove the current export version configuration and return to the default configuration, use the **no** form of this command.

version v9

Syntax Description	This command has no keywords or arguments.
---------------------------	--

Command Default	None
------------------------	------

Command Modes	Flow exporter map configuration
----------------------	---------------------------------

Command History	Release	Modification
------------------------	----------------	---------------------

Release 3.9.1	This command was introduced.
---------------	------------------------------

Usage Guidelines	When you issue the version v9 command, the CLI prompt changes to “config-fem-ver,” indicating that you have entered flow exporter map version configuration submode. In this sample output, the question mark (?) online help function displays all the commands available under flow exporter map version configuration submode:
-------------------------	--

```
RP/0/RSP0/CPU0:router(config-fem)# version v9
RP/0/RSP0/CPU0:router(config-fem-ver)#!?

  clear      Clear the uncommitted configuration
  commit     Commit the configuration changes to running
  describe   Describe a command without taking real actions
  do         Run an exec command
  exit       Exit from this submode
  no         Negate a command or set its defaults
  options    Specify export of options template
  pwd        Commands used to reach current submode
  root      Exit to the global configuration mode
  show       Show contents of configuration
  template   Specify template export parameters
```

Task ID	Task ID	Operations
	netflow	read, write

Examples	This example shows how to enter flow exporter map version configuration submode:
-----------------	--

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
```

version v9

```
RP/0/RSP0/CPU0:router(config-fem)# version v9
RP/0/RSP0/CPU0:router(config-fem-ver)#
```

Related Commands	Command	Description
	flow exporter-map, on page 16	Creates a flow exporter map
	flow monitor-map, on page 18	Creates and configures a flow monitor map
	show flow exporter, on page 35	Displays flow exporter data
	show flow exporter-map, on page 37	Displays flow exporter map information for a specific node.

version ipfix

To configure Internet Protocol Flow Information Export (IPFIX) as an export version and configure export version parameters, enter the **version ipfix** command in flow exporter map configuration mode. To remove the current export version configuration and return to the default configuration, use the **no** form of this command.

```
version ipfix [options {interface-table | sampler-table | vrf-table} timeout timeout-value | template {data | options } timeout timeout-value]
```

Syntax Description	options (Optional) Specifies export of options template. Options template provide extra information about the flow records. The options template include these options: <ul style="list-style-type: none"> • interface-table • sampler-table • vrf-table For each options template specify timeout value (in seconds) during which the exporter has to retransmit each active options template.
template	(Optional) Specifies template export parameters such as data template and options template timeout configurations.
timeout <i>timeout-value</i>	Specifies custom timeout value (in seconds) during which the exporter has to retransmit each active template. The range of <i>timeout-value</i> is 1 to 604800 seconds.

Command Default	None				
Command Modes	Flow exporter map configuration				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>Release 6.0.1</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	Release 6.0.1	This command was introduced.
Release	Modification				
Release 6.0.1	This command was introduced.				

Usage Guidelines	When you issue the version ipfix command, the CLI prompt changes to “config-fem-ver,” indicating that you have entered flow exporter map version configuration submode. In this sample output, the question mark (?) online help function displays all the commands available under flow exporter map version configuration submode:
-------------------------	---

```
RP/0/RSP0/CPU0:router(config-fem)# version ipfix
RP/0/RSP0/CPU0:router(config-fem-ver)#?

  clear      Clear the uncommitted configuration
  commit     Commit the configuration changes to running
  describe   Describe a command without taking real actions
  do         Run an exec command
  exit       Exit from this submode
  no         Negate a command or set its defaults
  options    Specify export of options template
```

version ipfix

pwd	Commands used to reach current submode
root	Exit to the global configuration mode
show	Show contents of configuration
template	Specify template export parameters

Task ID	Task ID	Operations
netflow	read, write	

Examples

This example shows how to configure IPFIX as an exporter in an flow exporter map configuration submode:

```
RP/0/RSP0/CPU0:router# configure
RP/0/RSP0/CPU0:router(config)# flow exporter-map map1
RP/0/RSP0/CPU0:router(config-fem)# version ipfix
RP/0/RSP0/CPU0:router(config-fem-ver)#

```