

Revised: June 3, 2025

# Licensing on the Cisco IR807 Industrial Integrated Services Router

## Licensing

This document provides details on the security licensing for the Cisco IR807 Industrial Integrated Services Router.

The IOS feature set is aligned with the IOT 15.x M/T release strategy. They are:

- IR800IUK9-15703M - Cisco IR800L Series UNIVERSAL
- IR800INPEK9-15703M – Cisco IR800L Series UNIVERSAL – NO PAYLOAD ENCRYPTION

### Software License PIDs

The Software License PIDs are shown in the following table:

**Table 1: Software License PIDs**

Software PID	Name	Description
SL-810-AIS	Cisco 800 Series Industrial Routers IP Base License	Routing (BGP, OSPF, RIP, EIGRP, ISIS,), PBR, IGMP/MLD, Multicast, QoS, AAA, Raw Sockets, Manageability
SL-810-ADVSEC	Cisco 800 Series Industrial Routers Security License	SSL, VPN, IPSec, DMVPN, FlexVPN, IOS Firewall

## Install Licenses

To enable the RightToUse license, perform the following steps:

Licenses are installed at manufacturing. If the advsecurity technology-package is not installed, the crypto related functions will not work. See additional information under Hardware Crypto Support.

### Step 1 Check the current version of the license.

```
Router# show version

License Info:
License UDI:
-----
Device#    PID                      SN
-----
*1         IR807G-LTE-GA-K9          FCW2132001S
License Information
  License Level: advipservices   Type: RightToUse
  Next reboot license Level: advipservices
```

### Step 2 Install the license.

```
Router# license install flash:FCW2132001S_201710030808172450.lic
```

**Step 3** Accept the EULA.

```
Router# license accept end user agreement
```

**Step 4** Enable the technology-packages.

```
Router# license boot module ir8001 level advsecurity
Router# license boot module ir8001 level advipservices
```

**Step 5** Reload the IR800 router.

```
Router# reload
```

**Step 6** Verify the licensing status on the router.

```
Router# show license feature
```

Feature name	Enforcement	Evaluation	Subscription	Enabled	RightToUse
advipservices	no	yes	no	yes	yes
advsecurity	no	no	no	no	no
ios-ips-update	yes	yes	yes	no	yes

## Hardware Crypto Support

A security license must be installed to enable hardware based crypto support.

To check which version of cryptographic support is being used on a device, use the following commands:

Use the **show crypto engine configuration** command to find details about the cryptographic engines being used. This command helps to understand the current crypto support status, including acceleration type and configuration.

```
Router# show crypto engine configuration
```

```
crypto engine name: Virtual Private Network (VPN) Module
crypto engine type: hardware
    State: Enabled
    Location: onboard 0
    Product Name: Onboard-VPN
    HW Version: 1.0
    Compression: No
        DES: Yes
        3 DES: Yes
        AES CBC: Yes (128,192,256)
        AES CNTR: No
Maximum buffer length: 4096
    Maximum DH index: 0000
    Maximum SA index: 0000
    Maximum Flow index: 0256
    Maximum RSA key size: 0000
    crypto lib version: 22.0.0
crypto engine in slot: 0
    platform: VPN hardware accelerator
    crypto lib version: 22.0.0
```

Use the **show crypto engine brief** command to get a high-level summary of the cryptographic engines on a router. This is useful for quickly determining the status and type of cryptographic acceleration (software or hardware) that is being used.

```
Router# show crypto engine brief
```

```
crypto engine name: Virtual Private Network (VPN) Module
crypto engine type: hardware
    State: Enabled
```

```

        Location:  onboard 0
    Product Name:  Onboard-VPN
      FW Version:  1
    Time running: 1335 seconds
      Compression: Yes
                DES: Yes
                3 DES: Yes
          AES CBC: Yes (128,192,256)
          AES CNTR: No
Maximum buffer length: 4096
    Maximum DH index: 0500
    Maximum SA index: 0500
    Maximum Flow index: 1000
Maximum RSA key size: 0000
    crypto engine name: Cisco VPN Software Implementation
    crypto engine type: software
          serial number: FF98383A
    crypto engine state: installed
    crypto engine in slot: N/A

```

Use the **show crypto engine config** command to view the configuration settings related to cryptographic features and modules.

```
Router# show crypto engine config
```

```

    crypto engine name: Virtual Private Network (VPN) Module
    crypto engine type: hardware
                State: Enabled
                Location: onboard 0
    Product Name: Onboard-VPN
      FW Version: 1
    Time running: 1358 seconds
      Compression: Yes
                DES: Yes
                3 DES: Yes
          AES CBC: Yes (128,192,256)
          AES CNTR: No
Maximum buffer length: 4096
    Maximum DH index: 0500
    Maximum SA index: 0500
    Maximum Flow index: 1000
Maximum RSA key size: 0000

    crypto lib version: 22_421.0.0

    crypto engine in slot: 0
                platform: VPN hardware accelerator
    crypto lib version: 22_421.0.0

```

Use the **show crypto engine accelerator stat** command to view the status and statistics of the cryptographic accelerators.

```
Router# show crypto engine accelerator stat
```

```
Device: Onboard VPN
```

```
Location: Onboard: 0
```

```

:Statistics for encryption device since the last clear
of counters 1404 seconds ago

```

0 packets in	0 packets out
0 bytes in	0 bytes out
0 paks/sec in	0 paks/sec out
0 Kbits/sec in	0 Kbits/sec out
0 packets decrypted	0 packets encrypted
0 bytes before decrypt	0 bytes encrypted
0 bytes decrypted	0 bytes after encrypt
0 packets decompressed	0 packets compressed

0 bytes before decomp	0 bytes before comp
0 bytes after decomp	0 bytes after comp
0 packets bypass decomp	0 packets bypass compres
0 bytes bypass decompress	0 bytes bypass compressi
0 packets not decompress	0 packets not compressed
0 bytes not decompressed	0 bytes not compressed
1.0:1 compression ratio	1.0:1 overall
Last 5 minutes:	
0 packets in	0 packets out
0 paks/sec in	0 paks/sec out
0 bits/sec in	0 bits/sec out
0 bytes decrypted	0 bytes encrypted
0 Kbits/sec decrypted	0 Kbits/sec encrypted
1.0:1 compression ratio	1.0:1 overall

#### Errors:

```

Total Number of Packet Drops = 0
Pad Error                    = 0
Data Error                   = 0
Packet Error                 = 0
Null IP Error                = 0
Hardware Error               = 0
CP Unavailable               = 0
HP Unavailable               = 0
AH Seq Failure               = 0
Link Down Error              = 0
ESP Seq Failure              = 0
AH Auth Failure              = 0
ESP Auth Failure             = 0
Queue Full Error             = 0
API Request Error            = 0
Invalid Flow Error           = 0
Buffer Unavailable           = 0
QOS Queue Full Error         = 0
Packet too Big Error         = 0
AH Replay Check Failure      = 0
Too Many Particles Error    = 0
ESP Replay Check Failure     = 0
Input Queue Full Error       = 0
Output Queue Full Error      = 0
raw_PAK_alloc                = 0
raw_PAK_free                 = 0
mod_exp_PAK_alloc            = 3
mod_exp_PAK_free             = 3
extropy_PAK_alloc            = 0
entropy_PAK_free             = 0
Pre-batch Queue Full Error   = 0
Post-batch Queue Full Error  = 0
batch_PAK_free               = 0

```

#### BATCHING Statistics:

Batching Allowed  
Batching currently Inactive

```

No of times batching turned on    = 0
No of times batching turned off   = 0
No of Flush Done                  = 0
Flush Timer in Milli Seconds      = 8
Disable Timer in Seconds          = 20
Threshold Crypto Paks/Sec         = 10000
to enable batching

```

```

POST-BATCHING Enabled
Post-batch count, max_count      = 0, 16
Packets queued to post-batch queue = 0
Packets flushed from post-batch queue = 0

The Post-batch Queue Information
The Queue size is                 = 512
The no entries currently being used = 0
The Read Index is                 = 0
The Write Index is                = 0
The entries in use are between Read and Write Index

```

The entries in use are

#### SEC MFIFO Statistics:

```

Channel 0 allocated times      = 3
Channel 1 allocated times      = 0
Channel 2 allocated times      = 0
Channel 3 allocated times      = 0
Channel 0 freed times          = 3
Channel 1 freed times          = 0
Channel 2 freed times          = 0
Channel 3 freed times          = 0
Sec MFIFO flush count          = 3
Sec MFIFO interrupt count      = 3
Sec MFIFO put back count       = 0
Sec MFIFO Timer flush count    = 0
Sec MFIFO Timer put back count = 0
Sec alloc workq count          = 0
Sec free workq count           = 64

```