



Release Notes for Cisco NCS 6000 Series Routers, IOS XR Release 7.2.2

[Release Notes for Cisco NCS 6000 Series Routers, IOS XR Release 7.2.2](#) 2

[What's New in Cisco IOS XR Release](#) 2

[Caveats](#) 3

[Release 7.2.2 Packages](#) 3

[Determining Installed Active Packages](#) 4

[Supported Packages and System Requirements](#) 5

[Other Important Information](#) 18

[Full Cisco Trademarks with Software License](#) 20

Revised: May 6, 2022

Release Notes for Cisco NCS 6000 Series Routers, IOS XR Release 7.2.2

The Cisco Network Convergence System (NCS) 6000 series router delivers outstanding network agility, packet optical convergence, and a system scale measured in petabits per second. It also facilitates the build-out of next-generation core to:

- support elastic capacity at the lowest total ownership cost
- deliver high-bandwidth mobile, video, and cloud services

Running the Cisco IOS XR operating system, Cisco's innovative virtualized operating environment, the Cisco NCS 6000 series router advances the concept of distributed routing and virtualization. With Cisco Virtualized IOS XR, the Cisco NCS 6000 series router brings new levels of programmability and virtualization to:

- enhance application service offerings
- increase provisioning speed
- optimize network economics

The Cisco NCS 6000 series router is engineered for environmental efficiency, with the use of adaptable power consumption. The Cisco NCS 6000 series router is powered by the Cisco nPower Network Processor Units (NPU). These technologies aid the Cisco NCS 6000 series router to achieve the lowest carbon footprint in service provider routing.

The Cisco NCS 6008 router, part of the Cisco NCS 6000 series routers, is the next-generation core routing system that provides industry-leading 8 Tbps of full-duplex network bandwidth through single chassis with eight line cards per chassis.

The Cisco NCS 6008 router runs on Cisco IOS XR software with Linux as the underlying host operating system. A Kernel-based Virtual Machine (KVM) hypervisor provides a virtualized environment to independently run system administration and routing functions on separate virtual machines. This provision makes the new system versatile and robust, and provides immense flexibility for future expansion without the need for a complete system overhaul.

A multi-slice architecture of line cards enables the system to be configured in a mixed operating mode, simultaneously supporting traffic at 10 Gbps and 100 Gbps on slice-level granularity.



Note Cisco IOS XR Release 7.2.2 is an Extended Maintenance Release of [Cisco IOS XR Release 7.2.1](#) for Cisco NCS 6000 Series routers. For more details on the Cisco IOS XR release model and associated support, see [Guidelines for Cisco IOS XR Software](#).

For a list of software caveats that apply to this Release, see the Caveats section. The caveats are updated for every release and are described at <http://www.cisco.com>.

What's New in Cisco IOS XR Release

Cisco is continuously enhancing the product with every release and this section covers a brief description of key features and enhancements. It also includes links to detailed documentation, where available.

Table 1: Software

Feature	Description
MPLS	
MPLS Entropy Label Encapsulation Support	This feature allows you to improve load balancing across MPLS networks using entropy labels. When this feature is configured at the ingress interface where MPLS is encapsulated, a DPI is performed to generate an entropy label. The load balancing is carried out on the entropy label. This eliminates the need for DPI to be performed on transit routers or overloading some network paths.
Segment Routing	
Segment Routing Performance Measurement for Link Delay Measurement on Link Bundles	This enhancement introduces support for Segment Routing Performance Measurement on link bundles for link delay measurement. A link bundle is a group of one or more ports that are aggregated together and treated as a single link. Link bundles allow you to group multiple point-to-point links together into one logical link and provide higher bidirectional bandwidth, redundancy, and load balancing between two routers.

Table 2: Hardware

Feature	Description
Support for CPAK-100G-LR4 Optic.	The Cisco CPAK-100G-LR4 optical module now supports Cisco NCS 6000 series routers. The module is IEEE 802.3ba-compliant and is designed to primarily support 100 Gbps optical links, with lengths of up to 10 km over standard SMF, G.652 that is terminated with SC or LC connectors.

Caveats

Caveats describe unexpected behavior in Cisco IOS XR Software releases. Severity-1 caveats are the most critical caveats; severity-2 caveats are less critical.

Cisco IOS XR Caveats

There are no caveats in this release.

Caveats Specific to the NCS 6000 Series Routers

Caveats describe unexpected behavior in Cisco IOS XR Software releases. These caveats are specific to NCS 6000 Series Routers:

There are no caveats in this release.

Release 7.2.2 Packages

This table lists the Cisco IOS XR Software feature set matrix (packages) and associated filenames available for the Cisco IOS XR Software Release 7.2.2 that is supported on the Cisco NCS 6008 router.

Table 3: Cisco IOS XR Software Release 7.2.2 Packages

Feature Set	Filename	Description
-------------	----------	-------------

Composite Package		
Cisco IOS XR IP Unicast Routing Core Bundle	ncs6k-mini-x.iso-7.2.2	Contains required core packages, including OS, Admin, Base, Forwarding, Modular Services Card, Routing, SNMP Agent, FPD, and Alarm Correlation.
Optional Individual Packages (packages that are installed individually)		
Cisco IOS XR Manageability Package	ncs6k-mgbl.pkg-7.2.2	Extensible Markup Language (XML) Parser and HTTP server packages.
Cisco IOS XR MPLS Package	ncs6k-mpls.pkg-7.2.2	MPLS Traffic Engineering (MPLS-TE), Label Distribution Protocol (LDP), MPLS Forwarding, MPLS Operations, Administration, and Maintenance (OAM), Link Manager Protocol (LMP), Optical User Network Interface (OUNI), Resource Reservation Protocol (RSVP), and Layer-3 VPN.
Cisco IOS XR Multicast Package	ncs6k-mcast.pkg-7.2.2	Multicast Routing Protocols (PIM, Multicast Source Discovery Protocol [MSDP], Internet Group Management Protocol [IGMP], Auto-RP), Tools (SAP, MTrace), and Infrastructure [(Multicast Routing Information Base [MRIB], Multicast-Unicast RIB [MURIB], Multicast forwarding [MFWD]).
Cisco IOS XR Security Package	ncs6k-k9sec.pkg-7.2.2	Support for Encryption, Decryption, IP Security (IPSec), Secure Shell (SSH), Secure Socket Layer (SSL), and Public-key infrastructure (PKI) (Software based IPSec support—maximum of 500 tunnels)
Cisco IOS XR Lawful Intercept (LI) Package	ncs6k-li.pkg-7.2.2	Supports Lawful Intercept (LI) features.
Cisco IOS XR Documentation Package	ncs6k-doc.pkg-7.2.2	.man pages for Cisco IOS XR Software.

Determining Installed Active Packages

To determine active software packages installed on the router, log in to the router and enter the **show install active summary** command in EXEC mode:

```
RP/0/RP0/CPU0:router# show install active
Active Packages: 8
ncs6k-xr-7.2.2 version=7.2.2 [Boot image]
ncs6k-mgbl-1.0.0.0-r722
ncs6k-li-1.0.0.0-r722
ncs6k-mcast-1.0.0.0-r722
ncs6k-k9sec-1.0.0.0-r722
```

```

ncs6k-doc-1.0.0.0-r722
ncs6k-mps-1.0.0.0-r722
ncs6k-infra-test-1.0.0.0-r722

```

Supported Packages and System Requirements

This section describes the system requirements for Cisco NCS 6000 Series Routers for Software Release .

Memory Requirements

The minimum memory requirements for a Cisco NCS 6008 router running Cisco IOS XR Software Release 7.2.2 consist of the following:

- 48 GB memory on the NCS 6008 Route Processors (NCS6-RP)
- 16 GB memory on 1T line cards
- 32 GB memory on 2T line cards

In order to avoid low memory conditions during system operations, it is recommended that you have 2000MB of free memory available on the Route Processors.

Supported Hardware

The following table lists the supported hardware components on the Cisco NCS 6000 Series Router and the minimum required software release. For more information, see the *Firmware Support* section.

Table 4: Cisco NCS 6008 Router Hardware and Software Compatibility Matrix

Component	Part Number	Support from Release
Second-generation S2 fabric card for the FCC with 32 CXP2 ports for 270GE SR25 CXP2s	NCS-F-FC2	6.3.2
CXP2 - 270GE SR25 transceiver module	ONS-CXP2-SR25	6.3.2
96 ONS-CXP2-SR25 optical modules	NCS-FAB-OPT2	6.3.2
Cisco 100GBASE SR4 QSFP Transceiver Cisco 100GBASE LR4 QSFP Transceiver	QSFP-100G-SR4-S QSFP-100G-LR4-S	6.2.2
20-port 100Gbps Lean Core	NC6-20X100GE-L-C	6.2.2
20-port 100Gbps Multi-Service Core	NC6-20X100GE-M-C	6.2.2
Universal Fabric Card	NC6-FC2-U	6.2.1
Cisco NCS 6008 FT, version 2	NC6-FANTRAY-2	6.1.2
CPAK optical transceiver module, 100GBASE-SR4, 100m OM4	CPAK-100G-SR4	6.1.2

Component	Part Number	Support from Release
S13 fabric card for LCC with 16 CXP ports for 100GE SR optics	NC6-FC-MC	5.2.1
S13 fabric card for LCC with 16 CXP ports for 100GE SR optics Spare	NC6-FC-MC=	5.2.1
S2 fabric card for the FCC with 32 CXP ports for 100GE SR12 CXPs	NCS-F-FC	5.2.1
S2 fabric card for the FCC with 32 CXP ports for 100GE SR12 CXPs Spare	NCS-F-FC=	5.2.1
FCC shelf controllers	NCS-F-SC	5.2.1
FCC shelf controllers Spare	NCS-F-SC=	5.2.1
FCC shelf controller and switch (SC-SW) card	NCS-F-SCSW	5.2.1
FCC shelf controller and switch (SC-SW) card Spare	NCS-F-SCSW=	5.2.1
Short reach SFP 10GE transceiver module	SFP-10G-SR	5.2.1
Long reach SFP 10GE transceiver module	SFP-10G-LR	5.2.1
Short reach QSFP 40GE optical module (SC-SW card only)	QSFP-40G-SR4	5.2.1
Long reach QSFP 40GE optical module (SC-SW card only)	QSFP-40G-LR4	5.2.1
96 CXP-100G-SR12 optical module	NCS-FAB-OPT	5.2.1
2X100GE MS PAYG Card with CPAK	NC6-2-10x100G-M-K	5.2.1
2X100GE LSR PAYG Card with CPAK	NC6-2-10x100G-L-K	5.2.1
30x10GE MS PAYG Card with SFPP	NC6-30x10G-M-S	5.2.1
30x10GE LSR PAYG Card with SFPP	NC6-30x10G-L-S	5.2.1
Craft Panel	NCS-CRFT	5.2.1
60-port 10Gbps SFP+ Lean Core Line card	NC6-60X10GE-L-S	5.0.1
60-port 10Gbps SFP+ Multi-Service Core Line card	NC6-60X10GE-M-S	5.0.1
Cisco 10GBASE-SR SFP+ Module for MMF	SFP-10G-SR	5.0.1
Cisco 10GBASE-SR SFP+ Module for MMF, extended temperature range	SFP-10G-SR-X	5.0.1

Component	Part Number	Support from Release
Cisco 10GBASE-LR SFP+ Module for SMF	SFP-10G-LR	5.0.1
Cisco multirate 10GBASE-LR, 10GBASE-LW and OTU2e SFP+ Module for SMF, extended temperature range	SFP-10G-LR-X	5.0.1
Cisco 10GBASE-ER SFP+ Module for SMF	SFP-10G-ER	5.0.1
Cisco 10GBASE-ZR SFP+ Module for SMF	SFP-10G-ZR	5.0.1
NCS 6008 - 8-Slot Chassis	NCS-6008	5.0.0
NCS 6008 Fabric Card	NC6-FC	5.0.0
NCS 6008 Route Processor	NC6-RP	5.0.0
NCS 6008 Chassis Fan Tray	NC6-FANTRAY	5.0.0
NCS AC Power Tray	NCS-AC-PWRTRAY	5.0.0
NCS DC Power Tray	NCS-DC-PWRTRAY	5.0.0
NCS PDU Bracket	NCS-PDU-BRKT	5.0.0
NCS 6008 3-to-1 Phase DELTA PDU	NCS-PDU-DELTA	5.0.0
NCS 6008 3-to-1 Phase WYE PDU	NCS-PDU-WYE	5.0.0
NCS 100x10GE Patch Panel Short Reach	NCS-PP-100X10-SR	5.0.0
NCS 6000 10x100G Multi-Service CPAK	NC6-10X100G-M-K	5.0.0
NCS 6000 10x100G Multi-Service CXP	NC6-10X100G-M-P	5.0.0
NCS 6000 10x100G LSR CPAK	NC6-10X100G-L-K	5.0.0
NCS 6000 10x100G LSR CXP	NC6-10X100G-L-P	5.0.0
NCS Craft Panel Display Kit	NCS-CRFT	5.0.0
NCS 6008 Chassis Front Doors	NC6-DOOR-F	5.0.0
NCS 6008 Chassis Rear Doors	NC6-DOOR-R	5.0.0
NCS 6008 Chassis Drill Template	NC6-DRILLTEMP	5.0.0
NCS 6008 Chassis Front-Bottom Grille	NC6-GRILLE-FB	5.0.0
NCS 6008 Chassis Front-Top Grille	NC6-GRILLE-FT	5.0.0
NCS 6008 Chassis Rear Grille	NC6-GRILLE-R	5.0.0

Component	Part Number	Support from Release
NCS 6008 Power Control Module	NC6-PCM	5.0.0
NCS 6008 Chassis Trough	NC6-TROUGH	5.0.0
NCS 6008 Chassis Trough Wide	NC6-TROUGH-W	5.0.0
NCS 6008 & NCS Fabric Chassis Lift Dolly	NCS-LIFT	5.0.0
10X10G-LR Cisco CPAK module for SMF	CPAK-10X10G-LR	5.0.0
CPAK-100G-LR4 Transceiver module, 10 km SMF	CPAK-100G-LR4	5.0.0
CXP-100G-SR10 transceiver Module	CXP-100G-SR10	5.0.0

Firmware Support

To check the firmware code running on the Cisco NCS 6000 Series Router, run the **show fpd package** command in admin mode.

```
RP/0/RP0/CPU0:router (sysadmin) #show fpd package
```

```
=====
                          Field Programmable Device Package
=====
```

Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
NC6-10X100G-L-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
S4-GN2411	YES	7.58	7.58	0.0	
SMART-iSATA	NO	7.05	7.05	0.0	
SMART-SATA	NO	7.05	7.05	0.0	
NC6-10X100G-L-P	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0

	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	Slice-0-GN2411	YES	5.86	5.86	2.0
	Slice-0-GN2411	YES	7.58	7.58	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	Slice-2-GN2411	YES	5.86	5.86	2.0
	Slice-2-GN2411	YES	7.58	7.58	0.0
	Slice-3-GN2411	YES	5.86	5.86	2.0
	Slice-3-GN2411	YES	7.58	7.58	0.0
	Slice-4-GN2411	YES	5.86	5.86	2.0
	Slice-4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-10X100G-M-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-10X100G-M-P	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	Slice-0-GN2411	YES	5.86	5.86	2.0
	Slice-0-GN2411	YES	7.58	7.58	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	Slice-2-GN2411	YES	5.86	5.86	2.0
	Slice-2-GN2411	YES	7.58	7.58	0.0
	Slice-3-GN2411	YES	5.86	5.86	2.0
	Slice-3-GN2411	YES	7.58	7.58	0.0

	Slice-4-GN2411	YES	5.86	5.86	2.0
	SLice-4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-2/10X100G-L-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-2/10X100G-M-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-20X100GE-L-C	Backup-BIOS	YES	1.08	1.08	0.1
	Backup-CCC-PwrOn	NO	1.11	1.10	0.0
	Backup-EthSwitch	YES	1.00	1.00	0.0
	Backup-EthSwitch	YES	1.14	1.14	0.2
	Backup-SolDBfpga	NO	1.04	1.04	0.0
	Backup-SolMBfpga	NO	1.04	1.04	0.0
	CCC-Bootloader	YES	1.08	1.08	0.0
	CCC-FPGA	YES	1.08	1.08	0.0
	CCC-Power-On	NO	1.11	1.11	0.0
	Ethernet-Switch	YES	1.00	1.00	0.0
	Ethernet-Switch	YES	1.14	1.14	0.2
	PLX-8749	YES	0.06	0.06	0.1
	Primary-BIOS	YES	1.08	1.08	0.1
	SOL-DB-FPGA	NO	1.04	1.04	0.0
	SOL-MB-FPGA	NO	1.04	1.04	0.0

NC6-20X100GE-M-C	Backup-BIOS	YES	1.08	1.08	0.1
	Backup-CCC-PwrOn	NO	1.11	1.10	0.0
	Backup-EthSwitch	YES	1.00	1.00	0.0

	Backup-EthSwitch	YES	1.14	1.14	0.2
	Backup-SolDBfpga	NO	1.04	1.04	0.0
	Backup-SolMBfpga	NO	1.04	1.04	0.0
	CCC-Bootloader	YES	1.08	1.08	0.0
	CCC-FPGA	YES	1.08	1.08	0.0
	CCC-Power-On	NO	1.11	1.11	0.0
	Ethernet-Switch	YES	1.00	1.00	0.0
	Ethernet-Switch	YES	1.14	1.14	0.2
	PLX-8749	YES	0.06	0.06	0.1
	Primary-BIOS	YES	1.08	1.08	0.1
	SOL-DB-FPGA	NO	1.04	1.04	0.0
	SOL-MB-FPGA	NO	1.04	1.04	0.0

NC6-30/60X10G-L-S	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	0.29	0.29	0.0
	BAO-MB-FPGA	NO	0.29	0.29	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	Modena-0-PHY	YES	0.13	0.13	0.0
	Modena-1-PHY	YES	0.13	0.13	0.0
	Modena-10-PHY	YES	0.13	0.13	0.0
	Modena-11-PHY	YES	0.13	0.13	0.0
	Modena-12-PHY	YES	0.13	0.13	0.0
	Modena-13-PHY	YES	0.13	0.13	0.0
	Modena-14-PHY	YES	0.13	0.13	0.0
	Modena-15-PHY	YES	0.13	0.13	0.0
	Modena-2-PHY	YES	0.13	0.13	0.0
	Modena-3-PHY	YES	0.13	0.13	0.0
	Modena-4-PHY	YES	0.13	0.13	0.0
	Modena-5-PHY	YES	0.13	0.13	0.0
	Modena-6-PHY	YES	0.13	0.13	0.0
	Modena-7-PHY	YES	0.13	0.13	0.0
	Modena-8-PHY	YES	0.13	0.13	0.0
	Modena-9-PHY	YES	0.13	0.13	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	Slice-0-GN2411	YES	5.86	5.86	2.0
	Slice-0-GN2411	YES	7.58	7.58	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	Slice-2-GN2411	YES	5.86	5.86	2.0
	Slice-2-GN2411	YES	7.58	7.58	0.0
	Slice-3-GN2411	YES	5.86	5.86	2.0
	Slice-3-GN2411	YES	7.58	7.58	0.0
	Slice-4-GN2411	YES	5.86	5.86	2.0
	Slice-4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-30/60X10G-M-S	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	0.29	0.29	0.0
	BAO-MB-FPGA	NO	0.29	0.29	0.0

	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	Modena-0-PHY	YES	0.13	0.13	0.0
	Modena-1-PHY	YES	0.13	0.13	0.0
	Modena-10-PHY	YES	0.13	0.13	0.0
	Modena-11-PHY	YES	0.13	0.13	0.0
	Modena-12-PHY	YES	0.13	0.13	0.0
	Modena-13-PHY	YES	0.13	0.13	0.0
	Modena-14-PHY	YES	0.13	0.13	0.0
	Modena-15-PHY	YES	0.13	0.13	0.0
	Modena-2-PHY	YES	0.13	0.13	0.0
	Modena-3-PHY	YES	0.13	0.13	0.0
	Modena-4-PHY	YES	0.13	0.13	0.0
	Modena-5-PHY	YES	0.13	0.13	0.0
	Modena-6-PHY	YES	0.13	0.13	0.0
	Modena-7-PHY	YES	0.13	0.13	0.0
	Modena-8-PHY	YES	0.13	0.13	0.0
	Modena-9-PHY	YES	0.13	0.13	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-4-10X100G-M-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-6-10X100G-L-K	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	1.06	1.06	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0

	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-60X10GE-L-S	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	0.29	0.29	0.0
	BAO-MB-FPGA	NO	0.29	0.29	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	Modena-0-PHY	YES	0.13	0.13	0.0
	Modena-1-PHY	YES	0.13	0.13	0.0
	Modena-10-PHY	YES	0.13	0.13	0.0
	Modena-11-PHY	YES	0.13	0.13	0.0
	Modena-12-PHY	YES	0.13	0.13	0.0
	Modena-13-PHY	YES	0.13	0.13	0.0
	Modena-14-PHY	YES	0.13	0.13	0.0
	Modena-15-PHY	YES	0.13	0.13	0.0
	Modena-2-PHY	YES	0.13	0.13	0.0
	Modena-3-PHY	YES	0.13	0.13	0.0
	Modena-4-PHY	YES	0.13	0.13	0.0
	Modena-5-PHY	YES	0.13	0.13	0.0
	Modena-6-PHY	YES	0.13	0.13	0.0
	Modena-7-PHY	YES	0.13	0.13	0.0
	Modena-8-PHY	YES	0.13	0.13	0.0
	Modena-9-PHY	YES	0.13	0.13	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	S4-GN2411	YES	5.86	5.86	2.0
	S4-GN2411	YES	7.58	7.58	0.0
	Slice-0-GN2411	YES	5.86	5.86	2.0
	Slice-0-GN2411	YES	7.58	7.58	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	Slice-2-GN2411	YES	5.86	5.86	2.0
	Slice-2-GN2411	YES	7.58	7.58	0.0
	Slice-3-GN2411	YES	5.86	5.86	2.0
	Slice-3-GN2411	YES	7.58	7.58	0.0
	Slice-4-GN2411	YES	5.86	5.86	2.0
	Slice-4-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-60X10GE-M-S	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-DB-FPGA	NO	0.29	0.29	0.0
	BAO-MB-FPGA	NO	0.29	0.29	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	Modena-0-PHY	YES	0.13	0.13	0.0
	Modena-1-PHY	YES	0.13	0.13	0.0
	Modena-10-PHY	YES	0.13	0.13	0.0
	Modena-11-PHY	YES	0.13	0.13	0.0

	Modena-12-PHY	YES	0.13	0.13	0.0
	Modena-13-PHY	YES	0.13	0.13	0.0
	Modena-14-PHY	YES	0.13	0.13	0.0
	Modena-15-PHY	YES	0.13	0.13	0.0
	Modena-2-PHY	YES	0.13	0.13	0.0
	Modena-3-PHY	YES	0.13	0.13	0.0
	Modena-4-PHY	YES	0.13	0.13	0.0
	Modena-5-PHY	YES	0.13	0.13	0.0
	Modena-6-PHY	YES	0.13	0.13	0.0
	Modena-7-PHY	YES	0.13	0.13	0.0
	Modena-8-PHY	YES	0.13	0.13	0.0
	Modena-9-PHY	YES	0.13	0.13	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	S2-GN2411	YES	5.86	5.86	2.0
	S2-GN2411	YES	7.58	7.58	0.0
	S3-GN2411	YES	5.86	5.86	2.0
	S3-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NC6-FANTRAY	Fantray-FPGA	NO	2.01	2.01	0.0

NC6-FANTRAY-2	Fantray-FPGA	NO	3.05	3.05	0.0

NC6-FC	CCC-FPGA	YES	1.29	1.29	0.0
	CCC-Power-On	NO	1.39	1.39	0.0
	PLX-8713	YES	1.03	1.03	0.1

NC6-FC-MC	Back-CRE-FPGA-MB	YES	1.00	1.00	0.0
	CCC-FPGA	YES	1.29	1.29	0.0
	CCC-Power-On	NO	1.39	1.39	0.0
	CRE-FPGA-MB	YES	1.00	1.00	0.0
	GN2411-BUS-0	YES	5.86	5.86	2.0
	GN2411-BUS-0	YES	7.58	7.58	0.0
	GN2411-BUS-1	YES	5.86	5.86	2.0
	GN2411-BUS-1	YES	7.58	7.58	0.0
	GN2411-BUS-2	YES	5.86	5.86	2.0
	GN2411-BUS-2	YES	7.58	7.58	0.0
	PLX-8713	YES	1.03	1.03	0.1

NC6-FC2-U	CCC-FPGA	YES	2.11	2.11	0.0
	CCC-Power-On	NO	1.39	1.39	0.0
	PLX-8713	YES	1.05	1.05	0.0

NC6-RP	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.42	1.32	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.2
	Backup-EthSwitch	YES	1.33	1.32	0.1
	CCC-Bootloader	YES	2.07	2.03	0.0
	CCC-FPGA	YES	2.07	2.07	0.0
	CCC-Power-On	NO	1.42	1.42	0.0
	CPU-Complex-BOOT	YES	4.08	4.04	0.1
	CPU-Complex-BOOT	YES	0.01	0.01	0.0
	CPU-Complex-FPGA	YES	4.08	4.08	0.1
	CPU-Complex-FPGA	YES	0.01	0.01	0.0
	Ethernet-Switch	YES	1.33	1.33	0.2
	Ethernet-Switch	YES	1.33	1.33	0.1
	PLX-8748	YES	0.05	0.05	0.0
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

NCS-CRFT	Craft-FCC	NO	1.06	1.06	0.1

	Craft-LCC	NO	1.06	1.06	0.1
NCS-F-FANTRAY	Fantray-FPGA	NO	2.01	2.01	0.0
NCS-F-FC	Back-CRE-FPGA-DC	YES	1.00	1.00	0.0
	Back-CRE-FPGA-MB	YES	1.00	1.00	0.0
	CCC-FPGA	YES	1.29	1.29	0.0
	CCC-Power-On	NO	1.39	1.39	0.0
	CRE-FPGA-DC	YES	1.00	1.00	0.0
	CRE-FPGA-MB	YES	1.00	1.00	0.0
	GN2411-BUS-0	YES	5.86	5.86	2.0
	GN2411-BUS-0	YES	7.58	7.58	0.0
	GN2411-BUS-1	YES	5.86	5.86	2.0
	GN2411-BUS-1	YES	7.58	7.58	0.0
	GN2411-BUS-2	YES	5.86	5.86	2.0
	GN2411-BUS-2	YES	7.58	7.58	0.0
	GN2411-BUS-3	YES	5.86	5.86	2.0
	GN2411-BUS-3	YES	7.58	7.58	0.0
	GN2411-BUS-4	YES	5.86	5.86	2.0
	GN2411-BUS-4	YES	7.58	7.58	0.0
	PLX-8713	YES	1.04	1.04	0.1
NCS-F-FC2	Back-CRE2-FPGA-DC	YES	1.00	1.00	0.0
	CCC-FPGA	YES	1.10	1.10	0.0
	CCC-Power-On	NO	1.05	1.05	0.0
	CRE2-FPGA-DC	YES	1.03	1.03	0.0
	PLX-8713	YES	1.05	1.05	0.1
NCS-F-SC	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.41	1.38	0.0
	Backup-EthSwitch	YES	1.33	1.33	0.0
	CCC-Bootloader	YES	2.03	2.01	0.0
	CCC-FPGA	YES	2.03	2.03	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	CPU-Complex-BOOT	YES	4.08	4.04	0.1
	CPU-Complex-BOOT	YES	0.01	0.01	0.0
	CPU-Complex-FPGA	YES	4.08	4.08	0.1
	CPU-Complex-FPGA	YES	0.01	0.01	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8625	YES	0.02	0.02	0.0
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0
NCS-F-SCSW	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.41	1.38	0.0
	Backup-EthSwitch	YES	1.33	1.33	0.0
	CCC-Bootloader	YES	2.03	2.01	0.0
	CCC-FPGA	YES	2.03	2.03	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	CPU-Complex-BOOT	YES	4.08	4.04	0.1
	CPU-Complex-BOOT	YES	0.01	0.01	0.0
	CPU-Complex-FPGA	YES	4.08	4.08	0.1
	CPU-Complex-FPGA	YES	0.01	0.01	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8625	YES	0.02	0.02	0.0
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0
NCS-F-SCSW (SW)	CCC-FPGA	YES	1.03	1.03	0.0
	CCC-Power-On	NO	1.39	1.39	0.0
	PLX-8614	YES	0.03	0.03	0.0

P-L-20X40G-QSFP	Backup-BIOS	YES	14.09	14.00	0.0	
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0	
	Backup-EthSwitch	YES	1.33	1.32	0.0	
	BAO-DB-FPGA	NO	0.29	0.29	0.0	
	BAO-MB-FPGA	NO	0.29	0.29	0.0	
	CCC-Bootloader	YES	2.12	2.07	0.0	
	CCC-FPGA	YES	2.12	2.12	0.0	
	CCC-Power-On	NO	1.41	1.41	0.0	
	Ethernet-Switch	YES	1.33	1.33	0.0	
	PLX-8748	YES	0.05	0.05	0.1	
	Primary-BIOS	YES	14.09	14.09	0.0	
	S2-GN2411	YES	5.86	5.86	2.0	
	S2-GN2411	YES	7.58	7.58	0.0	
	S3-GN2411	YES	5.86	5.86	2.0	
	S3-GN2411	YES	7.58	7.58	0.0	
	S4-GN2411	YES	5.86	5.86	2.0	
	S4-GN2411	YES	7.58	7.58	0.0	
	Slice-0-GN2411	YES	5.86	5.86	2.0	
	Slice-0-GN2411	YES	7.58	7.58	0.0	
	Slice-1-GN2411	YES	5.86	5.86	2.0	
	Slice-1-GN2411	YES	7.58	7.58	0.0	
	Slice-2-GN2411	YES	5.86	5.86	2.0	
	Slice-2-GN2411	YES	7.58	7.58	0.0	
	Slice-3-GN2411	YES	5.86	5.86	2.0	
	Slice-3-GN2411	YES	7.58	7.58	0.0	
	Slice-4-GN2411	YES	5.86	5.86	2.0	
	Slice-4-GN2411	YES	7.58	7.58	0.0	
SMART-iSATA	NO	7.05	7.05	0.0		
SMART-SATA	NO	7.05	7.05	0.0		

PROTO-1XPAT-QSFP	Backup-BIOS	YES	14.09	14.00	0.0	
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0	
	Backup-EthSwitch	YES	1.33	1.32	0.0	
	BAO-MB-FPGA	NO	0.29	0.29	0.0	
	CCC-Bootloader	YES	2.12	2.07	0.0	
	CCC-FPGA	YES	2.12	2.12	0.0	
	CCC-Power-On	NO	1.41	1.41	0.0	
	Ethernet-Switch	YES	1.33	1.33	0.0	
	PLX-8748	YES	0.05	0.05	0.1	
	Primary-BIOS	YES	14.09	14.09	0.0	
	SMART-iSATA	NO	7.05	7.05	0.0	
	SMART-SATA	NO	7.05	7.05	0.0	

	PROTO-1XPAT-SFP	Backup-BIOS	YES	14.09	14.00	0.0
Backup-CCC-PwrOn		NO	1.39	1.31	0.0	
Backup-EthSwitch		YES	1.33	1.32	0.0	
BAO-MB-FPGA		NO	0.29	0.29	0.0	
CCC-Bootloader		YES	2.12	2.07	0.0	
CCC-FPGA		YES	2.12	2.12	0.0	
CCC-Power-On		NO	1.41	1.41	0.0	
Ethernet-Switch		YES	1.33	1.33	0.0	
PLX-8748		YES	0.05	0.05	0.1	
Primary-BIOS		YES	14.09	14.09	0.0	
SMART-iSATA		NO	7.05	7.05	0.0	
SMART-SATA		NO	7.05	7.05	0.0	

PROTO-2XPAT-SFP		Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0	
	Backup-EthSwitch	YES	1.33	1.32	0.0	
	BAO-MB-FPGA	NO	0.29	0.29	0.0	
	CCC-Bootloader	YES	2.12	2.07	0.0	
	CCC-FPGA	YES	2.12	2.12	0.0	
	CCC-Power-On	NO	1.41	1.41	0.0	
	Ethernet-Switch	YES	1.33	1.33	0.0	

	Modena-0-PHY	YES	0.13	0.13	0.0
	Modena-1-PHY	YES	0.13	0.13	0.0
	Modena-2-PHY	YES	0.13	0.13	0.0
	Modena-3-PHY	YES	0.13	0.13	0.0
	Modena-4-PHY	YES	0.13	0.13	0.0
	Modena-5-PHY	YES	0.13	0.13	0.0
	Modena-6-PHY	YES	0.13	0.13	0.0
	Modena-7-PHY	YES	0.13	0.13	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

PROTO-2XPAT-SFP-L	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-MB-FPGA	NO	0.29	0.29	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

PROTO-CXP-1XPITA	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

PROTO-CXP-2XPITA	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-MB-FPGA	NO	1.06	1.06	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8748	YES	0.05	0.05	0.1
	Primary-BIOS	YES	14.09	14.09	0.0
	Slice-0-GN2411	YES	5.86	5.86	2.0
	Slice-0-GN2411	YES	7.58	7.58	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

PROTO-F-SC	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.41	1.38	0.0
	Backup-EthSwitch	YES	1.33	1.33	0.0
	CCC-Bootloader	YES	2.03	2.01	0.0
	CCC-FPGA	YES	2.03	2.03	0.0
	CCC-Power-On	NO	1.41	1.41	0.0

	CPU-Complex-BOOT	YES	4.08	4.04	0.1
	CPU-Complex-BOOT	YES	0.01	0.01	0.0
	CPU-Complex-FPGA	YES	4.08	4.08	0.1
	CPU-Complex-FPGA	YES	0.01	0.01	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	PLX-8625	YES	0.02	0.02	0.0
	Primary-BIOS	YES	14.09	14.09	0.0
	SMART-iSATA	NO	7.05	7.05	0.0
	SMART-SATA	NO	7.05	7.05	0.0

PROTO-NC6K-ATV	Backup-BIOS	YES	14.09	14.00	0.0
	Backup-CCC-PwrOn	NO	1.39	1.31	0.0
	Backup-EthSwitch	YES	1.33	1.32	0.0
	BAO-MB-FPGA	NO	1.00	1.00	0.0
	CCC-Bootloader	YES	2.12	2.07	0.0
	CCC-FPGA	YES	2.12	2.12	0.0
	CCC-Power-On	NO	1.41	1.41	0.0
	Ethernet-Switch	YES	1.33	1.33	0.0
	Primary-BIOS	YES	14.09	14.09	0.0
	Slice-1-GN2411	YES	5.86	5.86	2.0
	Slice-1-GN2411	YES	7.58	7.58	0.0

PWR-2KW-DC-V2	DT-PriMCU	NO	6.03	6.03	0.12
	DT-Sec54vMCU	NO	6.02	6.02	0.12
	DT-Sec5vMCU	NO	6.03	6.03	0.12
	EM-PriMCU	NO	3.12	3.12	0.21
	EM-Sec54vMCU	NO	3.19	3.19	0.21
	EM-Sec5vMCU	NO	3.19	3.19	0.21

PWR-3KW-AC-V2	DT-PriMCU	NO	6.02	6.02	1.0
	DT-Sec54vMCU	NO	6.02	6.02	1.0
	DT-Sec5vMCU	NO	6.04	6.04	1.0
	EM-Sec54vMCU	NO	3.12	3.12	0.21
	EM-Sec5vMCU	NO	3.18	3.18	0.21

Minimum Firmware Requirement

The following table provides the procedures and resources for minimum firmware requirements:

After completing an Return Material Authorization (RMA), upgrade the firmware as per the matrix in this link, which also links to PDF copies of the IOS XR Firmware Upgrade Guides	http://www.cisco.com/web/Cisco_IOS_XR_Software/index.html
For the upgrade procedure, see the <i>Performing System Upgrade and Installing Feature Packages</i> chapter of the <i>Cisco NCS 6008 System Setup and Software Installation Guide</i>	http://www.cisco.com/en/US/products/ps13132/tsd_products_support_series_home.html

Other Important Information

- To uniquely identify a line card as a Cisco device, all Cisco IOS XR supported platforms are shipped with a non-tamper-able Trust Anchor Module (TAM) in the hardware. The Cisco Trust Anchor module (TAm) helps verify that Cisco hardware is

authentic and provides additional security services. This feature is supported from Cisco IOS XR Release 7.1.x on Cisco NCS 6000 platform.

- From Release 6.0, the onePK toolkit is not supported.
- Country-specific laws, regulations, and licenses—In certain countries, use of these products may be prohibited and subject to laws, regulations, or licenses, including requirements applicable to the use of the products under telecommunications and other laws and regulations; customers must comply with all such applicable laws in the countries in which they intend to use the products.
- BFD limitation—If the current PPS (packets per second) is more than 7000 packets per line card (LC) then on upgrading the Cisco IOS XR software to release 5.2.5 or later the BFD sessions may shut down. You can avoid this scenario by adjusting the PPS per LC so that the load on a LC does not exceed more than 7000 PPS.

To know the current load (PPS value), use **show bfd summary** command. Use the **bfd address-family ipv4 minimum-interval** command to configure BFD timer.

- Field replaceable unit (FRU) removal—For all card removal and replacement (including fabric cards, line cards, fan controller, and RP) follow the instructions provided by Cisco to avoid impact to traffic. See the *Cisco Network Convergence System 6000 Series Routers Hardware Installation Guide* for procedures.
- Exceeding Cisco testing—If you intend to test beyond the combined maximum configuration tested and published by Cisco, contact your Cisco Technical Support representative to discuss how to engineer a large-scale configuration for your purpose.

Full Cisco Trademarks with Software License

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

The documentation set for this product strives to use bias-free language. For purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on standards documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA 95134-1706
USA

Asia Pacific Headquarters
CiscoSystems(USA)Pte.Ltd.
Singapore

Europe Headquarters
CiscoSystemsInternationalBV
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.