



Track Static Routes for Service VPNs

Table 1: Feature History

Feature Name	Release Information	Description
Static Route Tracker for Service VPNs for Cisco vEdge Devices	Cisco SD-WAN Release 20.4.1 Cisco vManage Release 20.4.1	This feature enables you to configure IPv4 static route endpoint tracking for service VPNs. For static routes, endpoint tracking determines whether the configured endpoint is reachable before adding that route to the route table of the device.
TCP/UDP Endpoint Tracker and Dual Endpoint Static Route Tracker for Cisco vEdge devices	Cisco SD-WAN Release 20.7.1 Cisco vManage Release 20.7.1	This feature enables you to configure the TCP/UDP static route endpoint trackers. Using this feature you can also configure IPv4, TCP/UDP dual endpoint static-route tracker groups for service VPNs to enhance the reliability of probes.

- [Information About Static Route Tracking, on page 1](#)
- [Restrictions for IPv4 Static Route Tracking, on page 2](#)
- [Workflow to Configure IPv4 Static Route Tracking, on page 2](#)
- [Configure Static Routes Using CLI, on page 6](#)
- [Configuration Examples for Static Route Tracking Using the CLI, on page 8](#)
- [Verify Static Route Tracking Configuration Using CLI, on page 9](#)

Information About Static Route Tracking

Static-route tracking for service VPNs enables you to track the availability of the configured endpoint address to determine if the static route can be included in the routing table of a device. This is applicable when a site uses a static route in a service VPN to advertise its route over Overlay Management Protocol (OMP). The static route tracker periodically sends ICMP ping probes to the configured endpoint. If the tracker does not receive a response, the static route is not included in the routing table and is not advertised to OMP. You can

configure an alternative next-hop address or a static route with a higher administrative distance to provide a backup path. This path is advertised over OMP.



Note From Cisco SD-WAN Release 20.7.1, you can configure TCP/UDP individual endpoint trackers and configure a tracker group with dual endpoints (using two trackers), and associate the trackers and tracker group to a static route. Dual endpoints help in avoiding false negatives that might be introduced because of the unavailability of the routes.

Restrictions for IPv4 Static Route Tracking

- Only one endpoint tracker is supported per static route per next-hop address.
- IPv6 static routes are not supported.
- You cannot link the same endpoint-tracker to static routes in different VPNs. Endpoint-tracker is identified by a name and can be used for multiple static routes in a single VPN.

Workflow to Configure IPv4 Static Route Tracking

1. Configure an endpoint tracker using the System template.
2. Configure a static route using the VPN template.
3. Apply the tracker to the next-hop address.

Create a Static Route Tracker

Use the **System Template** to create a tracker for static routes.

1. From Cisco vManage menu, choose **Configuration > Templates**.
2. Click **Feature Templates**.



Note In Cisco vManage Release 20.7.x and earlier releases, **Feature Templates** is titled **Feature**.

3. Navigate to the **Cisco System** template for the device.



Note For information about creating a System template, see [Create System Template](#).

4. Click **Tracker**. Click **New Endpoint Tracker** to configure the tracker parameters.

Table 2: Tracker Parameters

Field	Description
Name	Name of the tracker. The name can be up to 128 alphanumeric characters.
Threshold	Wait time for the probe to return a response before declaring that the configured endpoint is down. Range is from 100 to 1000 milliseconds. Default is 300 milliseconds.
Interval	Time interval between probes to determine the status of the configured endpoint. Default is 60 seconds (1 minute). Range is from 10 to 600 seconds.
Multiplier	Number of times probes are sent before declaring that the endpoint is down. Range is from 1 to 10. Default is 3.
Tracker Type	From the drop-down, choose Global . From the Tracker Type field drop-down, choose Static Route . From Cisco SD-WAN Release 20.7.1, you can configure a tracker group with dual endpoints on Cisco vEdge devices and associate this tracker group to a static route.
Endpoint Type	Choose endpoint type IP Address.
End-Point Type: IP Address	IP address of the static route end point. This is the destination on the internet to which the router sends probes to determine the status of the route.

5. Click **Add**.
6. Click **Save**.
7. To create a tracker group, click **New Endpoint Tracker**.

From the **Tracker Type** drop-down list, choose **tracker-group** and configure the tracker group parameters.



Note Ensure that you have created two trackers to form a tracker group.

Table 3: Tracker Group Parameters

Fields	Description
Name	Name of the tracker group.
Tracker Type	From the drop-down, choose Global . From the Tracker Type field drop-down, choose Static Route . From Cisco SD-WAN Release 20.7.1, you can configure a tracker group with dual endpoints on Cisco vEdge devices and associate this tracker group to a static route.

Fields	Description
Tracker Elements	This field is displayed only if you chose Tracker-group as the tracker type. Add the existing interface tracker names (separated by a space). When you add this tracker to the template, the tracker group is associated with these individual trackers, and you can then associate the tracker group to a static route.
Tracker Boolean	From the drop-down list, choose Global . This field is displayed only if you chose tracker-group as the Tracker Type . By default, the OR option is selected. Choose AND or OR . OR ensures that the static route status is reported as active if either one of the associated trackers of the tracker group report that the route is active. If you select AND , the static route status is reported as active if both the associated trackers of the tracker group report that the route is active.

8. Click **Add**.

9. Click **Save**.



Note Complete all the mandatory actions before you save the template.

Configure a Next Hop Static Route with Tracker

Use the **VPN** template to associate a tracker to a static route next hop.



Note You can apply only one tracker per static route next hop.

1. From the Cisco vManage menu, choose **Configuration > Templates**.
2. Click **Feature Templates**.



Note In Cisco vManage Release 20.7.x and earlier releases, **Feature Templates** is titled **Feature**.

3. Navigate to the **Cisco VPN Template** for the device.



Note For information about creating a VPN template, see [Create VPN Template](#).

4. Enter **Template Name** and **Description** as required.

- In Basic Configuration, by default, VPN is set to 0. Set a VPN value within (1–511, 513–65530) range for service VPNs, for service-side data traffic on Cisco IOS XE SD-WAN devices.



Note You can configure static route tracker only on service VPNs.

- Click **IPv4 Route**.
- Click **New IPv4 Route**.
- In the **IPv4 Prefix** field, enter a value.
- Click **Next Hop**.
- Click **Add Next Hop** and enter values for the fields listed in the table.

Parameter Name	Description
Address	Specify the next-hop IPv4 address.
Distance	Specify the administrative distance for the route.
Tracker	Enter the name of the gateway tracker to determine whether the next hop is reachable before adding that route to the route table of the device.
Add Next Hop	Enter the name of the gateway tracker with the next hop address to determine whether the next hop is reachable before adding that route to the route table of the device.

- Click **Add** to create the static route with the next-hop tracker.



Note Configuring a static route with a next-hop 'X.X.X.255' is not supported. Cisco vEdge device does not implement RFC 3021.

- Click **Save**.



Note You need to fill all the mandatory fields in the form to save the VPN template.

Monitor Static Route Tracker Configuration

View Static Route Tracker

To view information about a static tracker on a transport interface:

- From the Cisco vManage menu, choose **Monitor > Devices**.

Cisco vManage Release 20.6.x and earlier: From the Cisco vManage menu, choose **Monitor > Network**.

2. Choose a device from the list of devices.
3. Click **Real Time**.
4. From the **Device Options** drop-down list, choose **Static Route Tracker Info**.

Configure Static Routes Using CLI

The following sections provide information about how to configure static routes using the CLI.

Configure a Static Route Tracker



Note You can configure static route tracking using the Cisco vManage CLI Add-on feature templates and CLI device templates. For more information on configuring using CLI templates, see [CLI Templates](#).

```
Device# config terminal
Device(config)# system tracker <tracker-name>
Device(config-tracker-trackername)# tracker-type <tracker-type>
Device(config-tracker-trackername)# endpoint-ip <ip-address>
Device(config-tracker-trackername)# threshold <value>
Device(config-tracker-trackername)# multiplier <value>
Device(config-tracker-trackername)# interval <value>
Device(config-tracker-trackername)# exit
```

Configure a Static Route Tracker with TCP Port as the Endpoint

```
Device# config terminal
Device(config)# system tracker <tracker-name>
Device(config-tracker-trackername)# tracker-type <tracker-type>
Device(config-tracker-trackername)# endpoint-ip <ip-address> tcp <port-number>
Device(config-tracker-trackername)# threshold <value>
Device(config-tracker-trackername)# multiplier <value>
Device(config-tracker-trackername)# interval <value>
Device(config-tracker-trackername)# exit
```

Configure a Static Route Tracker with UDP Port as the Endpoint

```
Device# config terminal
Device(config)# system tracker <tracker-name>
Device(config-tracker-trackername)# tracker-type <tracker-type>
Device(config-tracker-trackername)# endpoint-ip <ip-address> udp <port-number>
Device(config-tracker-trackername)# threshold <value>
Device(config-tracker-trackername)# multiplier <value>
Device(config-tracker-trackername)# interval <value>
Device(config-tracker-trackername)# exit
```

Configure Tracker Groups



Note You can create tracker groups to probe static routes from Cisco SD-WAN Release 20.7.1 and Cisco vManage Release 20.7.1.

```
Device# config terminal
Device(config)# system tracker <tracker-name1>
Device(config-tracker-trackername1)# tracker-type <tracker-type>
Device(config-tracker-trackername1)# endpoint-ip <ip-address> tcp <port-number>
Device(config-tracker-trackername1)# threshold <value>
Device(config-tracker-trackername1)# multiplier <value>
Device(config-tracker-trackername1)# interval <value>
Device(config-tracker-trackername1)# exit

Device(config)# system tracker <tracker-name2>
Device(config-tracker-trackername2)# tracker-type <tracker-type>
Device(config-tracker-trackername2)# endpoint-ip <ip-address> udp <port-number>
Device(config-tracker-trackername2)# threshold <value>
Device(config-tracker-trackername2)# multiplier <value>
Device(config-tracker-trackername2)# interval <value>
Device(config-tracker-trackername2)# exit

Device(config)# system tracker <tracker-group-name>
Device(config-tracker-tracker-group-name)# tracker-type <tracker-group>
Device(config-tracker-tracker-group-name)# tracker-elements <tracker-name1> <tracker-name2>
Device(config-tracker-tracker-group-name)# boolean {and | or}
Device(config-tracker-tracker-group-name)# exit
```

Configure a Next Hop Static Route with Tracker

```
Device(config)# system
Device(config)# vpn <vpn-number>
Device(config-vpn-vpn-number)# ip route <ipv4address/prefix> <ip-address>
<administrative-distance> tracker <tracker-name>
```



Note Configuring a static route with a next-hop 'X.X.X.255' is not supported.
Cisco vEdge device does not implement RFC 3021.



Note

- Use the **ip route** command to bind a tracker or tracker group with a static route and to configure a backup route for administrative distance that is higher than the default value of 1.
- You can apply only one tracker to an endpoint.
- A tracker group can have a mix of endpoint trackers. For example, you can create a tracker group with an IP address tracker and UDP tracker.

Configuration Examples for Static Route Tracking Using the CLI

Configure Tracker

This example shows how to configure a single static route tracker:

```

config terminal
!
system tracker tracker1
!
  tracker-type static-route
  endpoint-ip 10.1.1.1
  threshold 100
  multiplier 5
  interval 60
  exit
!
vpn 1
ip route 192.0.2.0/24 10.20.24.17 tracker tracker1
ip route 172.16.0.0/12 10.20.24.16 100

```

This example shows how to configure a tracker with TCP port as endpoint:

```

config terminal
!
system tracker tcp-10001
!
  tracker-type static-route
  endpoint-ip 10.0.0.1 tcp 10001
  threshold 100
  interval 10
  multiplier 1
  exit
!
vpn 1
ip route 192.0.0.4/24 10.20.25.18 tracker tcp-10001

```

This example shows how to configure a tracker with UDP port as endpoint:

```

config terminal
!
system tracker udp-10001
!
  tracker-type static-route
  endpoint-ip 10.0.0.1 udp 10001
  threshold 100
  interval 10
  multiplier 1
  exit
!
vpn 1
ip route 192.0.0.4/24 10.20.30.19 tracker udp-10001

```

Configure Tracker Groups

This example shows how to configure a tracker group with two trackers (two endpoints). You can create tracker groups to probes static routes from Cisco SD-WAN Release 20.7.1.


```
config terminal
!
 system tracker tcp-10001
!
   tracker-type static-route
   endpoint-ip 10.1.1.1 tcp 10001
   threshold 100
   multiplier 5
   interval 20
!
 system tracker udp-10002
!
   tracker-type static-route
   endpoint-ip 10.2.2.2 udp 10002
   threshold 100
   multiplier 5
   interval 20
!
system tracker group-tcp-10001-udp-10002
!
   tracker-type tracker-group
   boolean and
   tracker-elements tcp-10001 udp-10002
   exit
!
vpn 1
 ip route 192.168.2.0/16 10.20.24.17 tracker group-tcp-10001-udp-10002
 ip route 192.168.2.0/16 10.20.24.16 100
```

**Note**

- You must configure an administrative distance when you are configuring through CLI templates.
- Use the **ip route** command to bind the tracker or tracker group with a static route and to configure a backup route for administrative distance when it is higher than the default value of 1.
- You can apply only one tracker to an endpoint.
- Configuring a static route with a next-hop 'X.X.X.255' is not supported.
Cisco vEdge device does not implement RFC 3021.

Verify Static Route Tracking Configuration Using CLI

Command Verification

Use the following command to verify if the configuration is committed. The following sample configuration shows tracker definition for a static route tracker and it's application to an IPv4 static route:

```
Device# show running-config system tracker
system
 tracker tracker1
 endpoint-ip 10.1.1.1
 interval 60
 multiplier 5
 tracker-type static-route
```

```

tracker tracker2
endpoint-ip 10.1.1.12
interval 40
multiplier 2
tracker-type static-route

```

Use the following command to verify the IPv4 route:

```
Device# show running-config vpn 1 ip route
```

```

vpn 1
ip route 10.20.30.0/24 10.20.30.1
ip route 192.168.2.0/16 10.20.24.16 100
ip route 192.168.2.0/16 10.20.24.17 tracker tracker1
!

```

The following is a sample output from the **show tracker static-route** command displaying individual static route tracker status:

```

Device# show tracker static-route
TRACKER          RTT IN
NAME            VPN  STATUS  MSEC
-----
tcp-10001      1    UP      0
udp-10002      1    UP      0

```

The following is a sample output from the **show tracker static-route-group** command displaying tracker group status:

```

Device# show tracker static-route-group
TRACKER NAME          VPN  BOOLEAN  STATUS  TRACKER ELEMENT NAME  TRACKER ELEMENT STATUS  TRACKER ELEMENT RTT
-----
group-tcp-10001-udp-10002  1    and      UP      tcp-10001            UP      0
                                udp-10002            UP      0

```

The following is a sample output from the **show ip route static** command:

```

Device# show ip route static
Codes Proto-sub-type:
  IA -> ospf-intra-area, IE -> ospf-inter-area,
  E1 -> ospf-external1, E2 -> ospf-external2,
  N1 -> ospf-nssa-external1, N2 -> ospf-nssa-external2,
  e -> bgp-external, i -> bgp-internal
Codes Status flags:
  F -> fib, S -> selected, I -> inactive,
  B -> blackhole, R -> recursive, L -> import

```

VPN	PREFIX	PROTOCOL	SUB TYPE	IF NAME	NEXTHOP ADDR	NEXTHOP VPN	NEXTHOP TLOC IP	COLOR
1	192.168.2.0/16	STATIC	-	ge0/4	10.20.24.17	-	-	-
-	F,S							
1	192.168.2.0/16	STATIC	-	ge0/4	10.20.24.16	-	-	-
-	F,S							