



Cisco ACI Multi-Site Troubleshooting Guide, Release 2.0(x)

First Published: 2018-10-24

Last Modified: 2019-03-14

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com go trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2018–2019 Cisco Systems, Inc. All rights reserved.



CONTENTS

PREFACE

Preface vii

Audience vii

Document Conventions vii

Related Documentation ix

Documentation Feedback x

Obtaining Documentation and Submitting a Service Request x

CHAPTER 1

New and Changed Information 1

New and Changed Information 1

CHAPTER 2

Overview 3

Troubleshooting Basics 3

Determining If the Issue is With Multi-Site 4

Determining Which Part of Multi-Site has an Issue 4

CHAPTER 3

Troubleshooting Installations Upgrades and Reboots 7

Disaster and Recovery for Multi-Site 7

Restarting a Single Node of the Cluster if it Goes Down Temporarily 7

Replacing a Single Node of the Cluster with a New Node 7

Restarting Two Nodes of Cluster that Go Down Temporarily 9

Replacing Two Existing Nodes of the Cluster with New Nodes 9

Backing Up the MongoDB for Cisco ACI Multi-Site 10

Restoring the MongoDB for Cisco ACI Multi-Site 10

Changing the Cisco ACI Multi-Site Secret and Key Files 11

Relocating Multi-Site Nodes to a Different Subnet 11

CHAPTER 4	Troubleshooting Users	15
	Troubleshooting Cisco ACI Multi-Site External User Authentication	15

CHAPTER 5	Troubleshooting Platform Health Issues	17
	Generating Troubleshooting Report and Logs	17
	Logging Into the VM for Troubleshooting	18
	Troubleshooting Missing Node Labels	19
	Troubleshooting Intersite Packet Flow in a Stretched BD Network	20
	Troubleshooting Inter-Site BGP Sessions	25
	Troubleshooting Unicast or Multicast Traffic Failures	26
	Troubleshooting Multi-Site Multicast Functionality	26

CHAPTER 6	Troubleshooting Tenants and Schemas	31
	Troubleshooting Deployment Errors From APIC	31
	Generating a Tenant Policy Report Using the REST API	31
	Undeploying Schemas and Templates	32

CHAPTER 7	Troubleshooting Tools	33
	Consistency Checker Overview	33
	Supported Use Cases	34
	Verifying a Template that has Been Deployed Across Sites	34
	Setting Up a Scheduled Verification for Every Deployed Template	36
	Troubleshooting an Error	37
	Generating a Troubleshooting Report	39
	Generating the API Call Logs	40
	Log on to a VM to Collect Data	41
	Reading the Execution Log	41
	Verifying that the Cisco ACI Multi-Site Microservices are Active	42
	Verifying Policy Resolution on APIC Sites	43

CHAPTER 8	Troubleshooting Multipod and Multi-Site Issues	47
	Troubleshooting Multipod and Multi-Site	47

CHAPTER 9**Verifying NXOS Hardware Tables 49**

Verifying End Point Manager Learning 49

Verifying BGP EVPN Routing Table 50

Verifying VNID, S-Class, and VTEP Mappings 52

Verifying LC Hardware Tables 55



Preface

This preface includes the following sections:

- [Audience, on page vii](#)
- [Document Conventions, on page vii](#)
- [Related Documentation, on page ix](#)
- [Documentation Feedback, on page x](#)
- [Obtaining Documentation and Submitting a Service Request, on page x](#)

Audience

This guide is intended primarily for data center administrators with responsibilities and expertise in one or more of the following:

- Virtual machine installation and administration
- Server administration
- Switch and network administration

Document Conventions

Command descriptions use the following conventions:

Convention	Description
bold	Bold text indicates the commands and keywords that you enter literally as shown.
<i>Italic</i>	Italic text indicates arguments for which the user supplies the values.
[x]	Square brackets enclose an optional element (keyword or argument).
[x y]	Square brackets enclosing keywords or arguments separated by a vertical bar indicate an optional choice.
{x y}	Braces enclosing keywords or arguments separated by a vertical bar indicate a required choice.

Convention	Description
[x {y z}]	Nested set of square brackets or braces indicate optional or required choices within optional or required elements. Braces and a vertical bar within square brackets indicate a required choice within an optional element.
<i>variable</i>	Indicates a variable for which you supply values, in context where italics cannot be used.
string	A nonquoted set of characters. Do not use quotation marks around the string or the string will include the quotation marks.

Examples use the following conventions:

Convention	Description
<code>screen font</code>	Terminal sessions and information the switch displays are in screen font.
boldface screen font	Information you must enter is in boldface screen font.
<i>italic screen font</i>	Arguments for which you supply values are in italic screen font.
< >	Nonprinting characters, such as passwords, are in angle brackets.
[]	Default responses to system prompts are in square brackets.
!, #	An exclamation point (!) or a pound sign (#) at the beginning of a line of code indicates a comment line.

This document uses the following conventions:



Note Means *reader take note*. Notes contain helpful suggestions or references to material not covered in the manual.



Caution Means *reader be careful*. In this situation, you might do something that could result in equipment damage or loss of data.



Warning IMPORTANT SAFETY INSTRUCTIONS

This warning symbol means danger. You are in a situation that could cause bodily injury. Before you work on any equipment, be aware of the hazards involved with electrical circuitry and be familiar with standard practices for preventing accidents. Use the statement number provided at the end of each warning to locate its translation in the translated safety warnings that accompanied this device.

SAVE THESE INSTRUCTIONS

Related Documentation

Application Policy Infrastructure Controller (APIC) Documentation

The following companion guides provide documentation for APIC:

- *Cisco APIC Getting Started Guide*
- *Cisco APIC Basic Configuration Guide*
- *Cisco ACI Fundamentals*
- *Cisco APIC Layer 2 Networking Configuration Guide*
- *Cisco APIC Layer 3 Networking Configuration Guide*
- *Cisco APIC NX-OS Style Command-Line Interface Configuration Guide*
- *Cisco APIC REST API Configuration Guide*
- *Cisco APIC Layer 4 to Layer 7 Services Deployment Guide*
- *Cisco ACI Virtualization Guide*
- *Cisco Application Centric Infrastructure Best Practices Guide*

All these documents are available at the following URL: <http://www.cisco.com/c/en/us/support/cloud-systems-management/application-policy-infrastructure-controller-apic/tsd-products-support-series-home.html>

Cisco Application Centric Infrastructure (ACI) Documentation

The broader ACI documentation is available at the following URL: <http://www.cisco.com/c/en/us/support/cloud-systems-management/application-policy-infrastructure-controller-apic/tsd-products-support-series-home.html>.

Cisco Application Centric Infrastructure (ACI) Simulator Documentation

The Cisco ACI Simulator documentation is available at <http://www.cisco.com/c/en/us/support/cloud-systems-management/application-centric-infrastructure-simulator/tsd-products-support-series-home.html>.

Cisco Nexus 9000 Series Switches Documentation

The Cisco Nexus 9000 Series Switches documentation is available at <http://www.cisco.com/c/en/us/support/switches/nexus-9000-series-switches/tsd-products-support-series-home.html>.

Cisco Application Virtual Switch Documentation

The Cisco Application Virtual Switch (AVS) documentation is available at <http://www.cisco.com/c/en/us/support/switches/application-virtual-switch/tsd-products-support-series-home.html>.

Cisco Application Centric Infrastructure (ACI) Integration with OpenStack Documentation

Cisco ACI integration with OpenStack documentation is available at <http://www.cisco.com/c/en/us/support/cloud-systems-management/application-policy-infrastructure-controller-apic/tsd-products-support-series-home.html>.

Documentation Feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to apic-docfeedback@cisco.com. We appreciate your feedback.

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see *What's New in Cisco Product Documentation* at: <http://www.cisco.com/c/en/us/td/docs/general/whatsnew/whatsnew.html>

Subscribe to *What's New in Cisco Product Documentation*, which lists all new and revised Cisco technical documentation as an RSS feed and delivers content directly to your desktop using a reader application. The RSS feeds are a free service.



CHAPTER 1

New and Changed Information

This chapter contains the following sections:

- [New and Changed Information, on page 1](#)

New and Changed Information

This chapter provides release-specific information for each new and changed feature in the guide.

Table 1: New Features and Changed Behavior in the Cisco ACI Multi-Site Troubleshooting Guide

Cisco ACI Multi-Site Version	Feature	Description	Where Documented
2.0(1)	--	This guide is released.	--



CHAPTER 2

Overview

The chapters in this guide describe common troubleshooting tips for specific Cisco ACI Multi-Site features and provide information about tools you can use for troubleshooting problems.

The features, issues, and tasks covered in this guide:

- **Installations, Upgrades, and Reboots**—Explains how to recover from various disaster scenarios with respect to the Multi-Site cluster, which includes both Docker Swarm and MongoDB cluster. Also describes how to change the Cisco ACI Multi-Site secret and key files.
 - **Users**—Explains how to troubleshoot user authentication issues.
 - **Platform Health**—Explains how to generate and download a troubleshooting report, log in to the VM to inspect all Docker services and inspect the logs for specific containers, and read the execution log. Also describes how to troubleshoot intersite packet flow in a stretched BD network, BGP sessions, unicast or multicast traffic failures, and the multicast functionality.
 - **Tenants and Schemas**—Explains how to troubleshoot errors received when deploying tenant policies configured in a Multi-Site schema, generate a tenant policy report using the Multi-Site REST API, and undeploy templates and schemas.
 - **Troubleshooting Tools**—Explains how to use the Multi-Site troubleshooting tools to generate a troubleshooting report, generate API call logs, log on to a VM for data collection, read the execution log, verify that microservices are active, and verify policy resolution on Cisco APIC sites.
 - **Multipod and Multi-Site**—Explains how to troubleshoot Multipod and Multi-Site issues.
 - **Hardware Tables**—Explains how to verify endpoint manager learning, BGP EVPN routing tables, VNID, S-Class, and VTEP mappings, and line card (LC) hardware tables.
- [Troubleshooting Basics, on page 3](#)
 - [Determining If the Issue is With Multi-Site, on page 4](#)
 - [Determining Which Part of Multi-Site has an Issue, on page 4](#)

Troubleshooting Basics

For issues with a specific feature, check the main contents of this guide for your feature. Troubleshooting tips are listed per-feature.

Before you begin

Become familiar with the tools listed in [Troubleshooting Tools](#), on page 33.

-
- Step 1** [Determining If the Issue is With Multi-Site](#), on page 4
- Step 2** [Determining Which Part of Multi-Site has an Issue](#), on page 4
- Step 3** [Undeploying Schemas and Templates](#), on page 32
- Step 4** Correct the schema or template then redeploy.
-

Determining If the Issue is With Multi-Site

For three trouble types, to determine if they are Multi-Site related, investigate the following questions. If the answer is no to one of the questions, the issue might be Multi-Site related. If all the answers are no, then it could be related to APIC, a switch, the intersite network, or the WAN.

-
- Step 1** Is Multi-Site accessible?
- Step 2** If traffic is not flowing, also investigate the following (See [Generating a Tenant Policy Report Using the REST API](#), on page 31):
- Are all the expected MOs deployed to the APIC sites?
 - Do all the expected MOs have the correct property values on the APIC sites?
 - Do the VRFs, BDs, EPGs, and L3InstPs have the correct mappings on all the sites?
 - Do the EPGs have the correct peer context Dn?
- Step 3** If traffic is flowing, but should not, investigate the following (See [Verifying Policy Resolution on APIC Sites](#), on page 43):
- Are all the MOs expected not to be there, actually not deployed to the APIC sites?
 - Do all the related MOs have the correct property values on the APIC sites?
-

Determining Which Part of Multi-Site has an Issue

This section provides methods for determining which part of Multi-Site has an issue.

-
- Step 1** Gather Multi-Site logs. For information, see [Log on to a VM to Collect Data](#), on page 41 and [Reading the Execution Log](#), on page 41.
- Check the logs of all microservices from Multi-Site (Both from the UI and inside the VM). For information, see [Verifying that the Cisco ACI Multi-Site Microservices are Active](#), on page 42.
 - [Generating a Tenant Policy Report Using the REST API](#), on page 31
 - Run the docker commands inside the VM. For information, see [Log on to a VM to Collect Data](#), on page 41.

Step 2

If you encounter errors on the Dashboard tab, mousing over red **CONNECTIVITY** arrows, see the following topics to troubleshoot the errors:

- No sites configured with BGP peering or BGP Session Failed—see [Troubleshooting Inter-Site BGP Sessions, on page 25](#)
 - Unicast/Multicast Failure—see [Troubleshooting Unicast or Multicast Traffic Failures, on page 26](#) or [Troubleshooting Multi-Site Multicast Functionality, on page 26](#)
-



CHAPTER 3

Troubleshooting Installations Upgrades and Reboots

This chapter contains the following sections:

- [Disaster and Recovery for Multi-Site, on page 7](#)
- [Changing the Cisco ACI Multi-Site Secret and Key Files, on page 11](#)
- [Relocating Multi-Site Nodes to a Different Subnet, on page 11](#)

Disaster and Recovery for Multi-Site

This section describes the various disaster and recovery scenarios with respect to the Multi-Site cluster which includes both Docker Swarm and MongoDB cluster. Multi-Site Docker Swarm is a 3 node cluster.

Restarting a Single Node of the Cluster if it Goes Down Temporarily

This section describes how to restart a single node of the cluster if it goes down temporarily.

Restart the node which was down. No additional steps are required and the cluster recovers by itself.

Replacing a Single Node of the Cluster with a New Node

This section describes how to replace a single node of the cluster with a new node.

In this scenario node 1 goes down and you want to replace node 1 with a new node.

Step 1 On any existing node, get the ID of the node that is down (node1). Execute the following command:

```
root@node2 ~]# docker node ls
ID                               HOSTNAME  STATUS  AVAILABILITY  MANAGER STATUS
11624powztg5t19nlfoubydtp *    node2    Ready  Active        Leader
fsrca74n17byt5jcv93ndebc0      node3    Ready  Active        Reachable
wnfs9oc687vuusbzd3o7id1lw      node1    Down   Active        Unreachable
```

Step 2 You must demote node1, execute the following command:

Replacing a Single Node of the Cluster with a New Node

```
[root@node2 ~]# docker node demote <node ID>
Manager <node ID> demoted in the swarm.
```

<node ID> is where you received the node ID from step 1.

Step 3 Remove node1 which is down before adding the new node, execute the following command:

```
[root@node2 ~]# docker node rm <node ID>
```

Step 4 On any existing node, change to the /opt/cisco/msc/builds/<build_number>/prodha directory:

Example:

```
# cd /opt/cisco/msc/builds/<build_number>/prodha
```

Step 5 Take note of the token. On any existing node, execute the following command:

```
[root@node1 prodha]# docker swarm join-token manager
docker swarm join --token
SWMTKN-1-4yaodn4nj8nek0qghh4dfzn6zm9o9p29rjisdikhjpvwu8bgmw-0ig2g62e0fe62cq2hbexk6xgv \
1.1.1.1:2376
```

Step 6 Taken note of IP address of the new leader. On any existing node, enter the following command:

Example:

```
[root@node1 prodha]# docker node ls
ID                HOSTNAME          STATUS    AVAILABILITY    MANAGER STATUS
pjicielwlcgkoeflx9s0td7ac  node1            Down     Active           Reachable
qy6peh6wtsbsaf9cpyh2wr5f6  node2            Ready    Active           Leader
tfhhvzt7qx9lxxqalbxfwknsq  node3            Ready    Active           Reachable
```

Step 7 On the leader node (node2), take note of the IP address:

```
# ifconfig
inet 10.23.230.152 netmask 255.255.255.0 broadcast 192.168.99.255
```

Step 8 Prepare the new third node. Set the correct hostname for the new node:

Example:

```
# hostnamectl set-hostname <node name>
```

Step 9 Change to the /opt/cisco/msc/builds/<build_number>/prodha directory:

Example:

```
# cd /opt/cisco/msc/builds/<build_number>/prodha
```

Step 10 Join the new node to the swarm:

Example:

```
[root@node1 prodha]# ./msc_cfg_join.py <token> <address of leader>
```

<token> is where you received the token information from step 5.

<address of leader> is where you received the leader IP address in step 7.

Step 11 On any node, change to the /opt/cisco/msc/builds/<build_number>/prodha directory:

Example:

```
# cd /opt/cisco/msc/builds/<build_number>/prodha
```

Step 12 On any node, execute the following command:

```
[root@node1 prodha]# ./msc_deploy.py
```

At this point all service should be up and database replicated.

Restarting Two Nodes of Cluster that Go Down Temporarily

This sections describes how to restart two nodes of the cluster that go down temporarily.

- Step 1** At this point due to lack of a quorum of 3 manager nodes in the Docker swarm, Multi-Site will not be available. Cisco recommends that you back up the MongoDB prior to any recovery attempts.
For more information, see [Backing Up the MongoDB for Cisco ACI Multi-Site, on page 10](#).
- Step 2** Restart the 2 nodes which were down. No additional steps are required and the cluster recovers by itself.

Replacing Two Existing Nodes of the Cluster with New Nodes

This section describes how to replace two existing nodes of the cluster with new nodes.

- Step 1** At this point due to lack of a quorum of 3 manager nodes in the Docker swarm, Multi-Site will not be available. Cisco recommends that you back up the DB prior to any recovery attempts.
For more information, see [Backing Up the MongoDB for Cisco ACI Multi-Site, on page 10](#).
- Step 2** Bring up 2 new nodes and set appropriate node names for each new node using the following commands:
- Example:**
- ```
hostnamectl set-hostname <node1, node2, or node3>
```
- Step 3** On the only live node which was previously part of swarm, execute the following command:
- ```
# docker swarm leave --force
```
- Step 4** SSH into node1 and change to the `/opt/cisco/msc/builds/<build number>/prodha` directory:
- Example:**
- ```
[root@node1]# cd /opt/cisco/msc/builds/<build number>/prodha
```
- Step 5** On node1, execute the following command:
- ```
[root@node1 prodha]# ./msc_cfg_init.py
```
- Step 6** On node1, execute the `docker node ls` command and delete any nodes marked as **Down**.

Example:

```
[root@node1 prodha]# docker node ls
```

ID	HOSTNAME	STATUS	AVAILABILITY	MANAGER	STATUS
g3mebdulaed2n0cyywjrtum31	node2	Down	Active	Reachable	
ucgd7mm2e2divnw9kvm4in7r7	node1	Ready	Active	Leader	
zjt4dsodu3bfff3ipn0dg5h3po *	node3	Down	Active	Reachable	

```
# docker node rm <id>
```

Step 7 On the 2 new nodes, using the token generated from `docker init` command, execute the `/opt/cisco/msc/builds/<build number>/prodha/msc_cfg_join.py` script. The nodes will join as workers.

Example:

```
# ./msc_cfg_join.py <token> <address of first node>
```

Step 8 On any node, SSH into node1 and execute the following from the `/opt/cisco/msc/builds/<build number>/prodha` directory:

```
# ./msc_deploy.py
```

At this point all service should be up and database replicated.

Backing Up the MongoDB for Cisco ACI Multi-Site

Cisco recommends that you back up the MongoDB prior to any Cisco ACI Multi-Site Orchestrator upgrades or downgrades, as described in this section.

Step 1 Log in to the Cisco ACI Multi-Site Orchestrator virtual machine (VM).

Step 2 Execute the Cisco ACI Multi-Site Orchestrator backup script:

```
# ~/msc_scripts/msc_db_backup.sh
```

The `msc_backup_<date+%Y%m%d%H%M>.archive` file is created.

Step 3 Copy the `msc_backup_<date+%Y%m%d%H%M>.archive` file to a safe place.

Restoring the MongoDB for Cisco ACI Multi-Site

This section describes how to restore the MongoDB for Cisco ACI Multi-Site.

Step 1 Log in to the Multi-Site virtual machine (VM).

Step 2 Copy your `msc_backup_<date+%Y%m%d%H%M>.archive` file to the VM.

Step 3 Execute the Multi-Site DB restore script:

```
# ~/msc_scripts/msc_db_restore.sh
```

Step 4 Push the schemas again by executing the python script:

```
# msc_push_schemas.py
```

Changing the Cisco ACI Multi-Site Secret and Key Files

Before you begin

This section describes how to change the Cisco ACI Multi-Site secret and key files.

The Cisco ACI Multi-Site supports HTTPS connection on TCP port 443. This comes built in with a certificate and a key file.



Note Changing the key and the crt file is an optional step that can be done after the execution of the `msc_cfg_init.py` script and before the Multi-Site service stack is deployed.

Step 1 Change to the `/opt/cisco/msc/builds/<build_number>/lib/secrets` directory.

Example:

```
# cd /opt/cisco/msc/builds/<build_number>/lib/secrets
```

The `secrets` directory contains the following files:

- `msc.crt`
- `msc.key`
- `create.secrets.sh`

Step 2 Delete the docker secrets, enter the following commands:

```
# docker secret rm msc_key  
# docker secret rm msc.crt
```

The above commands will succeed, if there is not a Multi-Site service stack running. If it is running, the stack has to be removed first. Removing a stack could cause traffic to be impacted and the Multi-Site stack will have to be re-deployed using the `msc_deploy.py` script.

Step 3 Over-write the `msc.crt` and `msc.key` files with the desired certificate and key files.


Step 4 Execute the `create_secrets.sh` script.

Step 5 At this point proceed to complete the next steps of the installer.

Relocating Multi-Site Nodes to a Different Subnet

This section describes how to relocate one or more Multi-Site nodes from one subnet to another. This is a common task when Multi-Site is deployed within a single data center and the goal is to spread the nodes across one or more data centers. It is important to move a single node at a time to maintain redundancy during the migration.

Figure 1: Cisco ACI Multi-Site Deployments



The example procedure below shows the relocation of Multi-Site node3 from data center 1 where the management subnet uses a 10.1.1.1/24 subnet, to data center 2 where the management subnet uses a 11.1.1.1/24 subnet.

SUMMARY STEPS

1. On node1, demote node3:
2. Power down node3 virtual machine (VM).
3. Remove node3 from the cluster:
4. Deploy the new Multi-Site VM (same version as node1 and node2) to the data center. Configure with the new IP details and ensure the hostname 'node3' gets assigned.
5. Power up node3 in data center 2 and test the connectivity to node1 and node2:
6. On node1, get the join token from node1 to join node3 to the cluster:
7. On node3, join swarm using the join token from step 6.
8. On any node, make sure the nodes are healthy. Verify that the STATUS is Ready, the AVAILABILITY is Active for each node, and the MANAGER STATUS is Reachable except for only one showing Leader:
9. Update the swarm label for node3:
10. On any node, check the status of all the docker services. For example, make sure it states 1/1 (1 out of 1) or 3/3 (3 out of 3). This may take up to 15 minutes to sync up.
11. Delete the original node3 VM that you powered down in data center 1.

DETAILED STEPS

Step 1 On node1, demote node3:

Example:

```
[root@node1 prodha]# docker node demote node3
```

Step 2 Power down node3 virtual machine (VM).

Step 3 Remove node3 from the cluster:

Example:

```
[root@node1 prodha]# docker node rm node3
```

Step 4 Deploy the new Multi-Site VM (same version as node1 and node2) to the data center. Configure with the new IP details and ensure the hostname 'node3' gets assigned.

Step 5 Power up node3 in data center 2 and test the connectivity to node1 and node2:

Example:

```
[root@node3 prodha]# ping [node1_IP]
[root@node3 prodha]# ping [node2_IP]
```

Step 6 On node1, get the join token from node1 to join node3 to the cluster:

Example:

```
[root@node1 prodha]# docker swarm join-token manager
To add a manager to this swarm, run the following command:
```

```
docker swarm join --token \
SWMTKN-1-4plaanp2uqpkjm2nidsxg9u7it0dd8hkihjwq9wvrz5heyk12n-98eo0onpacvxrrgf84juczdv \
10.1.1.1:2377
```

```
[root@node1 prodha~]#
```

Step 7 On node3, join swarm using the join token from step 6.

Example:

```
[root@node3 prodha]# docker swarm join --token \
SWMTKN-1-4plaanp2uqpkjm2nidsxg9u7it0dd8hkihjwq9wvrz5heyk12n-98eo0onpacvxrrgf84juczdv \
10.1.1.1:2377
```

Step 8 On any node, make sure the nodes are healthy. Verify that the STATUS is Ready, the AVAILABILITY is Active for each node, and the MANAGER STATUS is Reachable except for only one showing Leader:

Example:

```
[root@node1 ~]# docker node ls
```

ID	HOSTNAME	STATUS	AVAILABILITY	MANAGER STATUS
p71zqw77kwnu8z6srlw0uq2g0	node2	Ready	Active	Leader
q5orn9hd4f0vxneqeehixwt	node3	Ready	Active	Reachable
ryaglu9ej33pfvrjvqgj4tjr4 *	node1	Ready	Active	Reachable

```
[root@node1 ~]#
```

Step 9 Update the swarm label for node3:

Example:

```
[root@node1 prodha]# docker node update node3 --label-add msc-node=msc-node3
```

Step 10 On any node, check the status of all the docker services. For example, make sure it states 1/1 (1 out of 1) or 3/3 (3 out of 3). This may take up to 15 minutes to sync up.

Example:

```
[root@node1 ~]# docker service ls
```

ID	NAME	MODE	REPLICAS	IMAGE
3kv2qtu3gjm	msc_kongdb	replicated	1/1	msc-postgres:9.4
5fs0l99bbbgl	msc_kong	global	3/3	msc-kong:1.1
jrxade8o2nwn	msc_schemaservice	global	3/3	msc-schemaservice:1.2.0.206
kyq1myno38ry	msc_backupservice	global	3/3	msc-backupservice:1.2.0.206
ltx85gitz85u	msc_executionengine	replicated	1/1	msc-executionengine:1.2.0.206
n4skpiij90t1	msc_ui	global	3/3	msc-ui:1.2.0.206
*:80->80/tcp, *:443->443/tcp				
o2h8vp3clznd	msc_mongodb1	replicated	1/1	msc-mongo:3.4
q2udphffzb7g	msc_consistencyservice	replicated	1/1	msc-consistencyservice:1.2.0.206
qrlzbd0y18ul	msc_platformservice	global	3/3	msc-platformservice:1.2.0.206

```
rsb7ki0zxafa msc_mongodb2 replicated 1/1 msc-mongo:3.4
uiu25mz5h7m9 msc_userservice global 3/3 msc-userservice:1.2.0.206
xjrp2jbws4pz msc_audit-service replicated 1/1 msc-audit-service:1.2.0.206
xtsdns1iy52i msc_syncengine replicated 1/1 msc-syncengine:1.2.0.206
ypie99rviej msc_mongodb3 replicated 1/1 msc-mongo:3.4
zn03gxpleuls msc_siteservice global 3/3 msc-siteservice:1.2.0.206
[root@node1 ~]#
```

Step 11 Delete the original node3 VM that you powered down in data center 1.



CHAPTER 4

Troubleshooting Users

This chapter contains the following sections:

- [Troubleshooting Cisco ACI Multi-Site External User Authentication, on page 15](#)

Troubleshooting Cisco ACI Multi-Site External User Authentication

Use the following tips to troubleshoot external user authentication problems.

-
- Step 1** To investigate the error `Authentication method failed`, verify the following:
- The key given in the Provider configuration is correct
 - The Multi-Site (client) IP address is registered in the remote Cisco ACS server
- Step 2** To investigate the error `Invalid user credentials`, verify the following:
- The username entered on the Multi-Site login screen is correct and matches one that is configured on the Cisco ACS server
 - The password entered on the Multi-Site login screen is correct and matches one that is configured on the Cisco ACS server
- Step 3** If the user sees a Loading icon, followed by the errors `Loading ...` and `Authentication method failed`, verify the following:
- The IP address in the Provider configuration is correct
 - The IP addresses for the Provider and Cisco ACS are reachable
 - The port and protocol in the Provider configuration is correct
 - The correct authentication method (TACACS+ or RADIUS) is selected on the remote ACS server under **...Network Devices and AAA Clients > Authentication Options**
 - The correct shared secret is provided in the remote ACS server user configuration, and it is not empty

- Step 4** If the user is able to login, but is not able to see anything or is not able to see any tabs on the Multi-Site GUI, verify that the Cisco AV Pair and the roles are configured correctly for that user, on the remote ACS server.
-



CHAPTER 5

Troubleshooting Platform Health Issues

This chapter contains the following sections:

- [Generating Troubleshooting Report and Logs, on page 17](#)
- [Logging Into the VM for Troubleshooting, on page 18](#)
- [Troubleshooting Missing Node Labels, on page 19](#)
- [Troubleshooting Intersite Packet Flow in a Stretched BD Network, on page 20](#)
- [Troubleshooting Inter-Site BGP Sessions, on page 25](#)
- [Troubleshooting Unicast or Multicast Traffic Failures, on page 26](#)
- [Troubleshooting Multi-Site Multicast Functionality, on page 26](#)

Generating Troubleshooting Report and Logs

This section describes how to generate a troubleshooting report and infrastructure logs file for all the schemas, sites, tenants, and users that are managed by Cisco ACI Multi-Site Orchestrator.

Step 1 Log in to your Multi-Site Orchestrator GUI.

Step 2 In the top right corner, click the **Options** icon and select **System Logs**.

Step 3 Check the logs you want to download.

Check the **Database Backup** to download a backup of the Orchestrator database.

Check the **Server Logs** to download the Orchestrator logs.

Step 4 Click **DOWNLOAD**.

An archive of the selected items will be downloaded to your system. The report contains the following information:

- All schemas in JSON format
 - All sites definitions in JSON format
 - All tenants definitions in JSON format
 - All users definitions in JSON format
 - All logs of the containers in the `infra_logs.txt` file
-

Logging Into the VM for Troubleshooting

For troubleshooting, log into the VM to inspect all Docker services and inspect the logs for specific containers. Check the useful commands for Docker in the Docker command cheat sheet: https://www.docker.com/sites/default/files/Docker_CheatSheet_08.09.2016_0.pdf.

To inspect the health of Docker services, use the **docker service ls** CLI command. The output of the command is the expected health status. All services should have at least 1 container replicated as displayed in the REPLICAS column. If any of them is down, the system might not work correctly.

Figure 2: Inspecting the Health of Docker Services

```

➔ /tmp docker service ls
ID                NAME                MODE                REPLICAS            IMAGE                PORTS
99tdb043c9f0     msc_sitesservice    replicated          1/1                 msc-sitesservice:latest    *:9010->9010/tcp
a3und1no9gws2     msc_kong            replicated          1/1                 msc-kong:1.1              *:8000->8000/tcp, *:8001->8001/tcp
jgp6p39r3v8v     msc_kongdb          replicated          1/1                 postgres:9.4               *:5432->5432/tcp
mvhcf46tv572     msc_executionengine replicated          1/1                 msc-executionengine:latest *:9030->9030/tcp
bxggeba7tv8y     msc_ui              replicated          1/1                 msc-ui:latest              *:80->80/tcp, *:443->443/tcp
qk2ta0vxop9e     msc_userservice    replicated          1/1                 msc-userservice:latest    *:9040->9040/tcp
pkhl346ttidp     msc_syncengine     replicated          1/1                 msc-syncengine:latest     *:9060->9060/tcp
qmw88qvr7tzk     msc_mongod         replicated          1/1                 mongo:3.4                  *:27017->27017/tcp
w2nd7j92c1p6     msc_platformservice replicated          1/1                 msc-platformservice:latest *:9050->9050/tcp
vuvanahjo715q    msc_schemaservice replicated          1/1                 msc-schemaservice:latest *:9020->9020/tcp
    
```

Get the running container ID for a service using the **docker ps | grep <service name>** CLI command.

Figure 3: Getting the Running Container ID for a Service

```

➔ /tmp docker ps | grep executionengine
24e1003eebc2     msc_executionengine:latest    "bin/executionengine"    18 hours ago    Up 18 hours (healthy)    9030/tcp
    
```

Get all container IDs for a service, including the ones that are exited using the **docker ps -a | grep <service name>** CLI command.

Use the **docker logs <containerId>** CLI command to view for a container. The logs for a container could be large. Therefore, consider the network speed when you run the command. As there are many text files to be transferred, the connection can be slow.

The sample location of the log files for a container is `/var/lib/docker/containers/containerId`. There can be multiple `.xxx.json` log files and all of them are required.

Figure 4: Viewing the Location of the Log Files for a Container

```

/var/lib/docker/containers/86c8b380c42dfb660e8e05db5480e972cfc57aab41b7e9637c414e07672a6277 # ls -lh
total 276
-rw-r----- 1 root root 233.3K Jul 11 00:48 86c8b380c42dfb660e8e05db5480e972cfc57aab41b7e9637c414e07672a6277-json.log
drwx----- 2 root root 4.0K Jul 11 00:00 checkpoints
-rw-r--r-- 1 root root 6.1K Jul 11 00:48 config.v2.json
-rw-r--r-- 1 root root 1.2K Jul 11 00:48 hostconfig.json
-rw-r--r-- 1 root root 13 Jul 11 00:00 hostname
-rw-r--r-- 1 root root 173 Jul 11 00:48 hosts
-rw-r--r-- 1 root root 38 Jul 11 00:00 resolv.conf
-rw-r--r-- 1 root root 71 Jul 11 00:00 resolv.conf.hash
drwx----- 2 root root 4.0K Jul 11 00:00 shm
/var/lib/docker/containers/86c8b380c42dfb660e8e05db5480e972cfc57aab41b7e9637c414e07672a6277 #
    
```

Troubleshooting Missing Node Labels

If you cannot log in to your Multi-Site Orchestrator GUI, but the Orchestrator nodes are still reachable via SSH, one of the nodes may have lost its label. This section describes how to diagnose this issue and resolve it by re-applying the proper node label.

Step 1 Log in to one of the Multi-Site Orchestrator nodes via SSH.

You can log in to any one of the nodes.

Step 2 Check if the MongoDB containers are properly replicated on all nodes.

```
# docker service ls
ID                NAME                MODE                REPLICAS    IMAGE
[...]
jvzt10waek4c     msc_mongodb1       replicated          1/1         msc-mongo:3.6
x1tkpwf1qldf     msc_mongodb2       replicated          1/1         msc-mongo:3.6
zbi376btmjbg     msc_mongodb3       replicated          0/1         msc-mongo:3.6
[...]
```

In the above output, you can see that the MongoDB container is not properly replicated on one of the nodes.

Step 3 Find the hostnames of all the nodes.

```
# docker node ls
ID                HOSTNAME            STATUS             AVAILABILITY    MANAGER STATUS  ENGINE VERSION
z3b6sqc38gfgoerte8cx1w17r  node1              Ready             Active           Reachable        18.06.1-ce
mb3hqelg0r55oa2zoe32yyfiw * node2              Ready             Active           Leader           18.06.1-ce
ur5vq2gli8zfc8ngafjn8plej  node3              Ready             Active           Reachable        18.06.1-ce
```

Step 4 Inspect each node.

Repeat the following command for each node, replacing `<node-name>` with the hostname of the node from the previous step.

```
# docker inspect <node-name>
```

Example:

```
# docker inspect node3
[
  {
    "ID": "ur5vq2gli8zfc8ngafjn8plej",
    "Version": {
      "Index": 317093
    },
    "CreatedAt": "2018-01-19T11:00:41.522951756Z",
    "UpdatedAt": "2019-03-17T07:38:35.487509349Z",
    "Spec": {
      "Labels": {},
      "Role": "manager",
      "Availability": "active"
    },
    [...]
  ]
]
```

If one or more nodes are missing a label, the `Labels` field will be empty.

Step 5 Restore the missing label for the node.

In the following command:

- Replace `<node-label>` with the label appropriate for the node.

While the hostname of each node can be customized, the labels must be `msc-node1`, `msc-node2`, or `msc-node3`.

- Replace `<node-name>` with the hostname of the node that is missing a label.

```
# docker node update --label-add "msc-node=<node-label>" <node-name>
```

Example:

```
# docker node update --label-add "msc-node=msc-node3" node3
```

Step 6 Verify that the label was added correctly.

```
# docker inspect node3
[
  {
    "ID": "ur5vq2gli8zfc8ngafjn8plej",
    "Version": {
      "Index": 317093
    },
    "CreatedAt": "2018-01-19T11:00:41.522951756Z",
    "UpdatedAt": "2019-03-17T07:38:35.487509349Z",
    "Spec": {
      "Labels": {
        "msc-node": "msc-node3"
      },
      "Role": "manager",
      "Availability": "active"
    },
    [...]
  ]
]
```

Troubleshooting Intersite Packet Flow in a Stretched BD Network

Figure 1 shows a stretched bridge domain (BD) network with Layer 2 Broadcast extension between sites. The BD is an L3 BD with ARP flood enabled, using L2 Unknown Unicast Proxy.

Figure 5: Intersite ARP Flow




Figure 2 shows the same stretched BD network with focus on the unicast packet flow.

3	vlan-201	0000.6666.1716 L	eth1/40
msite-site:vrf1	vlan-201	172.17.15.106 L	eth1/40

Step 2

If both the local and remote EPs have been learned, and the policy permits the EPs to communicate (using the default contract permitting intra-EPG traffic), site5-leaf101 encapsulates the ICMP packet with the following data, and forwards the packet out through the fabric uplink port towards the spine switch:

- VXLAN header's outer destination IP address, 6.6.6.1
- VXLAN ID (VNID), 15794150
- src-class (sclass), 16387
- Source IP address, which is the site5-leaf101 TEP address through the VRF overlay-1

When the spine switch receives a packet from the VRF overlay-1, it verifies that the destination IP address (DIP) belongs to the MAC proxy address. For example, if the DIP 6.6.6.1 does not belong to the MAC proxy address of spine501, the spine switch forwards the packet like a normal IP packet, based on the longest match in the routing table. In this case, since the DIP matches a remote site's spine overlay unicast TEP address, spine501 rewrites the outer source IP (SIP) address from site5-leaf101's TEP to site5's unicast overlay unicast TEP (5.5.5.1). In this process, Spine501 should have learnt 6.6.6.1 through OSPF in the interpod network (IPN), so spine501 forwards the packet to the next hop, which is the IPN switch in this case.

Step 3

If there is a concern about the packet being forwarded, run ERSPAN in fabric mode on the APIC, in the NX-OS style CLI, to capture the outgoing packet from the uplink interface, using commands such as in the following example.

Example:

This example configures Fabric ERSPAN to capture outgoing packets from switch 101, interface eth1/1, with focus on VRF vrf1, and BD bd1, in tenant t1.

```

apic1# configure terminal
apic1(config)# monitor access session mySession
apic1(config-monitor-fabric)# description "This is my fabric ERSPAN session"
apic1(config-monitor-fabric)# destination tenant t1 application appl epg epg1 destination-ip
192.0.20.123 source-ip-prefix 10.0.20.1
apic1(config-monitor-fabric-dest)# erspan-id 100
apic1(config-monitor-fabric-dest)# ip dscp 42
apic1(config-monitor-fabric-dest)# ip ttl 16
apic1(config-monitor-fabric-dest)# mtu 9216
apic1(config-monitor-fabric-dest)# exit
apic1(config-monitor-fabric)# source interface eth 1/1 switch 101
apic1(config-monitor-fabric-source)# direction tx
apic1(config-monitor-fabric-source)# filter tenant t1 bd bd1
apic1(config-monitor-fabric-source)# filter tenant t1 vrf vrf1
apic1(config-monitor-fabric-source)# exit
apic1(config-monitor-fabric)# no shut
    
```

For more information, see *Configuring SPAN in Cisco APIC NX-OS Style Command-Line Interface Configuration Guide*.

Step 4

To verify whether the routing table contains an explicit entry for 6.6.6.1, use the NX-OS style command, **show ip route 6.6.6.1 vrf overlay-1**.

Step 5

When the next-hop interface has been found, use the **show lldp neighbor** command to determine whether the next hop of the interface, where 6.6.6.1 is learned from, is the expected IPN interface.

Use the Fabric ERSPAN to confirm that spine501 has received the packet from the leaf switch or forwarded it through the correct egress interface.

- Step 6** When the packet arrives at IPN, because it is a unicast packet, IPN forwards the IP packet based on the routing table. To confirm the routing table has the correct/expected next-hop interface, use the command **show ip route 6.6.6.1**.
- Use Fabric ERSPAN to capture one packet or a multiple packets from different interfaces. The next-hop interface from IPN in the topology above is spine601's interface.
- If the packet arrives at the site6 switch, spine601, it maps the remote site's ID based on the outer SIP, 5.5.5.1 to site5, together with the source VNID to 15794150. Also, spine601 translates that VNID to the VNID of the local BD, 16449430, and translates the src-class ID, 16387, to the local EP src-clas, 32770. Then it performs a look up based on the destination-MAC address, within the scope of the translated VNID.
- Step 7** To verify the VNID translation between site5 and site6, on spine601 enter the **show dcimgr repo vnid-maps verbose** command.
- Step 8** To verify the sclass translation between site5 and site6, on spine601 enter the **show dcimgr repo sclass-maps** command. Finally, spine601 rewrites the outer destination to the TEP of site6-leaf101 and forwards the packet there.
- Step 9** To determine if the packet was forwarded properly, go to the expected leaf switch (site6-leaf101) run Fabric ERSPAN to capture the packet.
- Step 10** If the packet arrives at site6-leaf101, leaf101 performs a local lookup, based on the destination MAC within the scope of VNID, 16449430, to determine the egress interface. To determine the egress interface, enter the **show endpoint mac mac-address** command.
- Step 11** To determine if the packet was forwarded properly, use access SPAN to capture the outgoing packet on the expected interface, using commands such as in the following example.

Example:

This example configures SPAN in access mode to capture packets being sent on leaf 101, interface eth1/2, with focus on EPG epg1 in tenant t1.

```
apic1# configure terminal
apic1(config)# monitor access session mySession
apic1(config-monitor-access)# description "This is my SPAN session"
apic1(config-monitor-access)# destination interface eth 1/2 leaf 101
apic1(config-monitor-access)# source interface eth 1/1 leaf 101
apic1(config-monitor-access-source)# direction tx
apic1(config-monitor-access-source)# filter tenant t1 application appl epg epg1
apic1(config-monitor-access-source)# exit
apic1(config-monitor-access)# no shut
apic1(config-monitor-access)# show run
```

This is the traditional SPAN configuration, local to an Access leaf node. Traffic originating from one or more access ports or port-channels can be monitored and sent to a destination port local to the same leaf node.

In the ACI fabric, you can also use an access mode ERSPAN configuration to monitor traffic originating from access ports, port-channels, and vPCs in one or more leaf nodes. For an ERSPAN session, the destination is always an EPG which can be deployed anywhere in the fabric. The monitored traffic is forwarded to the destination wherever the EPG is moved.

For more information, see *Configuring SPAN in Cisco APIC NX-OS Style Command-Line Interface Configuration Guide*.

Troubleshooting Inter-Site BGP Sessions

For Multi-Site BGP sessions to be established on site spine switches, the following settings are required:

- The update source should have the `mscp-etep` flag set
- The BGP peer type should be `inter-site`
- The node role should be `msite-speaker`

To troubleshoot inter-site BGP session failures, verify the following MOs on the spines, using Visore:

- `fvNodeDef`
- `bgpInfraPeerDef`
- `bgpAsP`
- `fvIntersitePeeringDef`
- `l3extIntersiteLoopBackIfPDef`
- `l3LbRtdIf` with `type` set to `inter-site`
- `LoopBackId`
- `ipv4If` with the same loopback ID has the `modeExtn` property set to `mscp-etep`

If any of these MOs are missing, the BGP sessions do not come up.

For information about entering queries using Visore, see *Accessing REST API Tools in Using the REST API in the Cisco APIC REST API Configuration Guide*.



Note Visore is supported on the Firefox, Chrome, and Safari browsers.

Step 1 In a supported browser, enter the URL of the spine switch followed by `/visore.html`, as in the following example:

Example:

```
https://spine-ip-address/visore.html
```

Step 2 When prompted, log in using the same credentials you would use to log in to the spine CLI interface.

Step 3 Enter a query for `l3LbRtdIf` to verify that the `type` is `inter-site`.

Step 4 Enter a query for `Ipv4If` to verify that the `mode` is `cp-etep` and the `modeExtn` is `mscp-etep`.

Step 5 Enter a query for `Intersite BgpPeers` to verify it was created with the `inter-site` type and uses the CP-TEP loopback address as the source interface.

Step 6 If any of these values is incorrect, go to the APIC for the site and correct the values. Return to the Sites tab in Multi-Site and click **CONFIGURE INFRA**, and then click **Apply**.

Troubleshooting Unicast or Multicast Traffic Failures

Use these steps in Visore to troubleshoot inter-site Unicast and Multicast traffic failures.

For information about entering queries using Visore, see *Accessing REST API Tools* in *Using the REST API* in the *Cisco APIC REST API Configuration Guide*.



Note Visore is supported on the Firefox, Chrome, and Safari browsers.

Step 1 In a supported browser, enter the URL of the spine switch followed by `/visore.html`, as in the following example:

Example:

```
https://spine-ip-address/visore.html
```

Step 2 When prompted, log in using the same credentials you would use to log in to the spine CLI interface.

Step 3 Enter a query to verify the `fvIntersiteConnPDef` and `fvIntersiteMcastConnPDef` MOs are under `fvSiteConnPDef`.

These are the remote site unicast and multicast DP TEPs.

Step 4 Enter a query to verify that the `tunnelIf` MO was created with the type `dci-ucast` or `dci-mcast-hrep`, and the destination is the same as the remote site DP TEPs.

Step 5 Check the local site unicast and multicast DP TEPs. Enter a query for `fvIntersiteConnPDef` under `fvPodConnPDef` and `fvIntersiteMcastConnPDef` under `fvFabricExtConnPDef`.

Step 6 Enter a query for the `SiteLocal ipv4If` MOs to verify they were created with the mode `dci-ucast` and `dci-mcast-hrep` and the `ipv4Addr` MO was configured under it with the same address as the DP TEP's.

Step 7 If any of these values is incorrect, go to the APIC for the site and correct the values. Return to the Sites tab in Multi-Site and click **CONFIGURE INFRA**, and then click **Apply**.

Troubleshooting Multi-Site Multicast Functionality

This task provides the steps for troubleshooting the Multi-Site multicast functionality in a stretched bridge domain (BD) use case. This topic assumes that the `L2STRETCH` and `INTERSITEBUMTRAFFICALLOW` options are enabled in the stretched BD.



Note In release 1.0(1), multicast routing is not supported. If you use the fabric as a querier, the fabric ID on each site must be the same. Check the release notes for the Cisco ACI Multi-Site release you have deployed, for other guidelines or restrictions that might affect multicast traffic.

Multicast traffic flows between sites in the following process:

- **TX (Sending) from local to remote site**

The Group IP Outer address (GIPo) traffic (part of Layer 2 Broadcast, Unknown Unicast, Multicast traffic) from the local site is Head-End Replicated (HREP) to each remote site from the Spine switch.

The Destination IP address of the outer header (DIPO) is rewritten to a unicast address called as Multicast HREP TEP IP (also called Multicast DP-TEP IP) of the remote site. The Source IP address of the outer header (SIPO) is rewritten with the Unicast ETEP IP.

• **RX (Receiving) by remote from local site**

Incoming traffic destined to the local site Multicast HREP TEP IP address is translated. The APIC on the site derives the local site BD-GIPO from that data, and follows the regular GIPO lookup path from then on.

To troubleshoot problems in this process, log on to the spine switch CLIs and use the following steps:

Step 1

To verify the locally configured Multi-Site TEP IP addresses, log on to the Supervisor module, and enter a command such as the following example:

Example:

```
swmp11-spine6# show ip interface vrf overlay-1
loopback11, Interface status: protocol-up/link-up/admin-up, iod: 126, mode: dci-ucast, vrf_vnid:
16777199
  IP address: 33.20.1.1, IP subnet: 33.20.1.1/32
  IP primary address route-preference: 1, tag: 0
loopback12, Interface status: protocol-up/link-up/admin-up, iod: 127, mode: mcast-hrep, vrf_vnid:
16777199
  IP address: 33.30.1.1, IP subnet: 33.30.1.1/32
```

Step 2

To confirm the MFDM on the spine switch, log on to the Supervisor module and enter a command such as the following example:

Example:

```
swmp11-spine6# show forwarding distribution multicast hrep
MFDM HREP NODE TABLE
-----
IP Address: 0xble0101
Table Id: 2
Flags: 0x0
IfIndex: 0x18010009
Internal BD 0x1001
Internal encap 0xb54
Nexthop Information: (num: 5)
Address          Ifindex          Dvif
0x14950a02      0x1a018019      0x1eb (Selected) <== Selected NH to reach the HREP TEP IP
0x14950602      0x1a00e00f      0x0
0x14950802      0x1a010011      0x0
0x14950902      0x1a011012      0x0
0x14950b02      0x1a01901a      0x0
```

Step 3

To verify HREP TEP IP address reachability, log on to the Supervisor module, and enter a command such as the following example:

Example:

```
swmp11-spine6# show ip route 11.30.1.1 vrf overlay-1
11.30.1.1/32, ubest/mbest: 5/0
 *via 20.149.6.2, Eth1/15.15, [110/9], 1d21h, ospf-default, intra
 *via 20.149.8.2, Eth1/17.17, [110/9], 1d21h, ospf-default, intra
 *via 20.149.9.2, Eth1/18.18, [110/9], 1d21h, ospf-default, intra
 *via 20.149.10.2, Eth1/25.25, [110/9], 1d21h, ospf-default, intra
 *via 20.149.11.2, Eth1/26.26, [110/9], 1d21h, ospf-default, intra
  via 10.0.112.95, Eth2/21.77, [115/65], 1d21h, isis-isis_infra, L1
  via 10.0.112.95, Eth1/24.35, [115/65], 1d21h, isis-isis_infra, L1
```

```
via 10.0.112.92, Eth2/19.76, [115/65], 1d21h, isis-isis_infra, L1
via 10.0.112.92, Eth1/21.36, [115/65], 1d21h, isis-isis_infra, L1
via 10.0.112.90, Eth2/17.75, [115/65], 1d21h, isis-isis_infra, L1
via 10.0.112.90, Eth1/23.33, [115/65], 1d21h, isis-isis_infra, L1
```

Step 4 To verify the MFIB on the spine switch line card module, log on to the module as root and use an (`vsh_lc`) command such as the following example:

Example:

```
root@module-1# show forwarding multicast hrep tep_routes

****HREP TEP ROUTES****
-----
| Tep Ip      |  Tep If      |  NH Ip      |  NH If      |  NH dmac     |  NH dvif    |  Vlan Id
| Bd Id      |              |              |              |              |             |
-----
|22.30.1.1   | |0x1801000b  | |20.149.11.2 | |0x1a01901a  | |00c8.8bba.54bc | |490  |2901  |4098
|
|11.30.1.1   | |0x18010009  | |20.149.10.2 | |0x1a018019  | |00c8.8bba.54bc | |491  |2900  |4097  |
```

Step 5 To verify the multicast HREP TEP details for remote sites, log on to the spine switch line card module to investigate the SDK, by entering a command such as the following example:

Example:

```
root@module-1# show platform internal hal objects mcast hreptep
## Get Objects for mcast hreptep for Asic 0
OBJECT 1:
Handle                : 52303
tepifindex            : 0x18010009
tepipaddr            : 11.30.1.1/0
intbdid               : 0x1001
intvlanid             : 0xb54
nexthopipaddr       : 20.149.10.2/0
nexthopifindex       : 0x1a018019
nexthopmacaddr     : 00:c8:8b:ba:54:bc
```

Step 6 To verify the GIPo route having HREP tunnels for the remote sites, log on to the spine switch Supervisor module and examine IS-IS details on the spine switch with a command, such as the following example:

Example:

```
swmp11-spine6# show isis internal mcast routes gipo
GIPo: 225.0.6.176 [TRANSIT]
OIF List:
Ethernet1/21.36
Ethernet1/23.33
Ethernet1/24.35
Tunnel9 <== Multicast HREP tunnel for Remote Site 1
Tunnel1 <== Multicast HREP tunnel for Remote Site 2
Ethernet2/17.75
Ethernet2/19.76
Ethernet2/21.77
```

Step 7 To verify the GIPo route having HREP tunnels for the remote sites, examine the MRIB on the spine switches using a command, such as the following example:

Example:

```
swmp11-spine6# show ip mroute 225.0.6.176 vrf overlay-1
IP Multicast Routing Table for VRF "overlay-1"
(*, 225.0.6.176/32), uptime: 1d02h, isis
Incoming interface: Null, RPF nbr: 0.0.0.0
Outgoing interface list: (count: 8)
```

```
Tunnel9, uptime: 1d01h
Tunnel11, uptime: 1d02h
Ethernet2/21.77, uptime: 1d02h
Ethernet2/19.76, uptime: 1d02h
Ethernet2/17.75, uptime: 1d02h
Ethernet1/24.35, uptime: 1d02h
Ethernet1/23.33, uptime: 1d02h
Ethernet1/21.36, uptime: 1d02h
```

Step 8 To verify the MFIB on an FC, log on to the module as root, and use a command such as the following example:

Example:

```
root@module-24# show forwarding multicast route group 225.0.6.176 vrf all
(*, 225.0.6.176/32), RPF Interface: NULL, flags: Dc
Received Packets: 0 Bytes: 0
Number of Outgoing Interfaces: 8
Outgoing Interface List Index: 484
Ethernet1/21.36 Outgoing Packets:N/A Bytes:N/A
Ethernet1/23.33 Outgoing Packets:N/A Bytes:N/A
Ethernet1/24.35 Outgoing Packets:N/A Bytes:N/A
Tunnel9 Outgoing Packets:0 Bytes:0
Tunnel11 Outgoing Packets:0 Bytes:0
Ethernet2/17.75 Outgoing Packets:N/A Bytes:N/A
Ethernet2/19.76 Outgoing Packets:N/A Bytes:N/A
Ethernet2/21.77 Outgoing Packets:N/A Bytes:N/A
```

Step 9 To verify the GIPo route having HREP tunnels for the remote sites, examine the SDL on FC, using a command such as the following example:

Example:

```
root@module-24# show platform internal hal objects mcast l3mcastroute groupaddr 225.0.6.176/32
extensions
## Get Extended Objects for mcast l3mcastroute for Asic 0
OBJECT 0:
Handle : 78705
groupaddr : 225.0.6.176/32
grpplen : 0x20
sourceaddr : 0.0.0.0/32
ispimbidir : Enabled
ctrlflags : UseMetFlag,
rtflags : none, UseMetEntry,
acirtpolicy : none
- - - - -
Relation Object replistnextobj :
rel-repllistnextobj-mcast-mcast_mcast_repl_list-handle : 78702
rel-repllistnextobj-mcast-mcast_mcast_repl_list-id : 0x600001e4
```

Step 10 To verify the GIPo route to the remote sites, examine the replication list identified in the last step, using a command such as the following example:

Example:

```
root@module-24# show platform internal hal objects mcast mcastrepllist id 0x600001e4
## Get Objects for mcast mcastrepllist for Asic 0
- - - - -
Repl-List Asicpd Debug :
Entry-Num 0
Repl Entry Id: 0x1e5 Hw Epg Id: 4050 Hw Bd Id: 4050
Mc Id: 484 Met Id: 485 Encap Id: -1
Sh Grp: 0 Next Met Id: 749
Entry-Num 1
Repl Entry Id: 0x2ed Hw Epg Id: 4098 Hw Bd Id: 4098
Mc Id: 490 Met Id: 749 Encap Id: -1
```

```
Sh Grp:                0 Next Met Id: 1191
Entry-Num 2
Repl Entry Id:        0x3a4 Hw Epg Id: 4097 Hw Bd Id: 4097
Mc Id: 491 Met Id:    1191 Encap Id:  -1
Sh Grp:                0 Next Met Id:  0
```

Step 11

To verify the VNID and GIPo mappings on the local (TX) and remote (RX) sites, enter a command such as the following example:

Example:

```
root@module-2# show platform internal hal objects dci vnidmap extensions | grep -B 5 -A 5 225.1.148.0
```

```
OBJECT 182:
Handle                : 26456
isbdvniid            : Enabled
localvniid           : 0xe78007
localgipo             : 225.1.148.0/32
remotevniid         : 0xe1000c
remotevrfvniid       : 0x208019
islocalbdctrl        : Enabled
siteid                : 0x3

OBJECT 1285:
Handle                : 29468
isbdvniid            : Enabled
localvniid         : 0xe78007
localgipo         : 225.1.148.0/32
remotevniid          : 0xee7fa8
remotevrfvniid       : 0x2e000e
islocalbdctrl        : Enabled
siteid                : 0x2
```



CHAPTER 6

Troubleshooting Tenants and Schemas

This chapter contains the following sections:

- [Troubleshooting Deployment Errors From APIC, on page 31](#)
- [Generating a Tenant Policy Report Using the REST API, on page 31](#)
- [Undeploying Schemas and Templates, on page 32](#)

Troubleshooting Deployment Errors From APIC

When deploying tenant policies you have configured in a Cisco ACI Multi-Site schema, you may receive errors or issues may occur. To troubleshoot these errors and issues follow these steps.

-
- Step 1** If you receive an APIC error after clicking **DEPLOY TO SITES**, correct any problems and try to deploy the schema/template again. For example, errors can be of two kinds:
- Misconfiguration—for example, a required association has not been defined, such as forgetting to choose the VRF for a BD.
 - Site problem—there may be problems such as network failures, communication failures, or problems with the Infra settings. Save the schema, address the site problem, then return to deploy the schema again.
- Step 2** If the schema is deployed successfully, but traffic does not flow, perform the following steps:
- a) Generate a Troubleshooting Report and examine it for errors; see [Generating a Troubleshooting Report, on page 39](#)
 - b) Generate a policy report and examine the tenant policy configuration; see [Generating a Tenant Policy Report Using the REST API, on page 31](#)
 - c) Log on to the Multi-Site VM and generate the execution log to find errors; see [Log on to a VM to Collect Data, on page 41](#) and [Reading the Execution Log, on page 41](#).
- Step 3** If you find no errors, the problem may be with APIC, switches, the IPN or the WAN.
-

Generating a Tenant Policy Report Using the REST API

To generate a tenant policy report, use the Multi-Site REST API, to enter a query such as the following example.

When receiving the query, Multi-Site queries APIC for all policies defined in the tenant, generating traffic between Multi-Site and APIC. You may want to do this during a maintenance window.

To list the tenants with issues, enter a query such as the following example and copy the output:

Example:

```
GET https://multi-site-ip-address/api/v1/policy-report?
tenants=tenant1,tenant2&validate=true
```

Undeploying Schemas and Templates

In troubleshooting, if you find that some tenant policies are incorrectly configured, you may want to undeploy a template or schema and later recreate it. To undeploy templates and schemas follow these steps.

-
- Step 1** Undeploy a template that is deployed to one site:
- In the Schema tab click the three dots on a site-specific template.
 - Click **YES** to confirm.
- Step 2** Undeploy a template on one site, that is deployed to multiple sites:
- In the Schema tab click the template.
 - Click + to open the sites-selection panel.
 - On the row for the site, click **X** on the template.
 - Click **SAVE**.
 - Redeploy the remaining templates to the site.
- Step 3** Remove a schema from all sites:
- In the Schemas tab, click the schema.
 - Click **Actions** and choose **Delete**.
 - Confirm you want to undeploy the schema and click **YES**.
-

What to do next

Correct the schema or template then redeploy.



CHAPTER 7

Troubleshooting Tools


This chapter contains the following sections:

- [Consistency Checker Overview](#), on page 33
- [Generating a Troubleshooting Report](#), on page 39
- [Generating the API Call Logs](#), on page 40
- [Log on to a VM to Collect Data](#), on page 41
- [Reading the Execution Log](#), on page 41
- [Verifying that the Cisco ACI Multi-Site Microservices are Active](#), on page 42
- [Verifying Policy Resolution on APIC Sites](#), on page 43

Consistency Checker Overview

The Consistency Checker verifies deployments after the initial deploy operation, and integrates the results of this tool within the Cisco ACI Multi-Site user interface. This feature verifies cross mappings. Only usable on a template that has been deployed, that is stretched across at least two sites and contains at least one of the following policies:

- EPG
- VRF
- BD
- External EPG



Supported Use Cases

Verifying a Template that has Been Deployed Across Sites

This section describes how to verify a template that has been deployed across sites.

Before you begin


- The template that has been depolyed across at least two stretched sites and contains at least one of the following policies:
 - EPG
 - VRF
 - BD
 - External EPG

SUMMARY STEPS

1. Log in to the Multi-Site GUI.
2. In the **Main Menu**, click **Schemas**, and on the Schema List page, choose the appropriate *schema_name*.
3. Click on a deployed template.
4. In the top right corner, click on **unverified**.
5. In the **TEMPLATE VERIFICATION SUMMARY** dialog box, click **VERIFY**.
6. The verification status will either be:

DETAILED STEPS

- Step 1** Log in to the Multi-Site GUI.
- Step 2** In the **Main Menu**, click **Schemas**, and on the Schema List page, choose the appropriate *schema_name*.
- Step 3** Click on a deployed template.
- Step 4** In the top right corner, click on **unverified**.



Step 5 In the **TEMPLATE VERIFICATION SUMMARY** dialog box, click **VERIFY**.

A popup message appears:

Consistency verification has been successfully triggered.

Step 6 The verification status will either be:

- **VERIFICATION SUCCESSFUL**—No action is needed.
 - **VERIFICATION FAILED**—Action is needed.
- a) If the verification failed, click **VERIFICATION FAILED**.
 - b) In the **TEMPLATE VERIFICATION SUMMARY** dialog box, for the site(s) that did fail, click on the pencil icon for a more detailed report of the template.

Example:

Template1 New York		VERIFICATION FAILED		Last Verified: 03/12/18 1:14 pm
POLICY	VERIFICATION	NEW YORK	SAN FRANCISCO	
BD1	APIC	✓	✓	
	Switch	✗	✗	
EP1	APIC	✓	✓	
	Switch	✗	✗	
EP2	APIC	✓	✓	
	Switch	✗	✗	
VRF1	APIC	✓	✓	
	Switch	✗	✗	

DOWNLOAD VERIFY TEMPLATE

Hover over the red x for the description of the issue. The issue can either be **Not Found** (unable to locate) or **Mismatch** (misconfigured).

- c) You can either click **DOWNLOAD** or **VERIFY TEMPLATE**.
 - **DOWNLOAD**—Provides you the report for only the current site.
 - **VERIFY TEMPLATE**—Provides you the verified template across all sites.

Setting Up a Scheduled Verification for Every Deployed Template

This section describes how to set up a scheduled verification for every deployed template on a per tenant basis.

SUMMARY STEPS

1. Log in to the Multi-Site GUI.
2. In the **Main Menu**, click **Tenant**, and on the Tenant List page, click **Set Schedule** for the appropriate *tenant_name*.
3. In the **Consistency Checker Scheduler Settings**, uncheck the **Disabler Schedule**, select the time and frequency.

DETAILED STEPS

- Step 1** Log in to the Multi-Site GUI.
- Step 2** In the **Main Menu**, click **Tenant**, and on the Tenant List page, click **Set Schedule** for the appropriate *tenant_name*.
- Step 3** In the **Consistency Checker Scheduler Settings**, uncheck the **Disabler Schedule**, select the time and frequency.
 - a) Click **OK**.

Troubleshooting an Error

This section describes how to troubleshoot an error.

SUMMARY STEPS

1. Log in to the Multi-Site GUI.
2. In the **Dashboard**, in the **SCHEMA HEALTH** section, in the view by field, click on the schema verification icon.
3. Expand the schema that contains a site in red to show the templates.
4. If you hover over the red sites, it displays **FAILED**.
5. You can click on the **FAILED** site and it will bring up a more detailed report.
6. You can also see which templates passed, failed or are unverified.
7. (Optional) You can verify the entire schema, click on the ... and choose **Verify Schema**.
8. (Optional) You can search by EPG, BD, VRF, or External EPG to find out which schema contains this policy.

DETAILED STEPS

Step 1 Log in to the Multi-Site GUI.

Step 2 In the **Dashboard**, in the **SCHEMA HEALTH** section, in the view by field, click on the schema verification icon.

The small squares in a site represents the templates within the schema.

At a first glance, you can see what has passed, failed, or is unverified.

- **PASSED**—is in green.
- **FAILED**—is in red.
- **UNVERIFIED**—is in yellow.

Step 3 Expand the schema that contains a site in red to show the templates.

Step 4 If you hover over the red sites, it displays **FAILED**.

Step 5 You can click on the **FAILED** site and it will bring up a more detailed report.

Example:


Template1 New York		VERIFICATION FAILED		Last Verified: 03/12/18 1:14 pm	✕
POLICY	VERIFICATION	NEW YORK	SAN FRANCISCO		
BD1	APIC	✓	✓		
	Switch	✕	✕		
EP1	APIC	✓	✓		
	Switch	✕	✕		
EP2	APIC	✓	✓		
	Switch	✕	✕		
VRF1	APIC	✓	✓		
	Switch	✕	✕		

[DOWNLOAD](#) [VERIFY TEMPLATE](#)

If you hover over the red x for the description of the issue. The issue can either be **Not Found** (unable to locate) or **Mismatch** (misconfigured).

- a) You can either click **DOWNLOAD** or **VERIFY TEMPLATE**.
 - **DOWNLOAD**—Provides you the report for only the current site.
 - **VERIFY TEMPLATE**—Provides you the verified template across all sites.

Step 6 You can also see which templates passed, failed or are unverified.



Step 7 (Optional) You can verify the entire schema, click on the ... and choose **Verify Schema**.

Step 8 (Optional) You can search by EPG, BD, VRF, or External EPG to find out which schema contains this policy.

Generating a Troubleshooting Report

When submitting a Cisco ACI Multi-Site issue to Technical Support, generate a troubleshooting report in the GUI to include with the support request. The following information is included in the report:

- **schemas**—All schemas in JSON format
- **sites**—Site definitions in JSON format
- **tenants**—Tenant definitions in JSON format
- **users**—User definitions in JSON format
- **infra_logs.txt**—Logs of all containers, including API call logs

Step 1 In the Multi-Site GUI, click the **Welcome, Name** button and choose **Troubleshooting Report**.

Step 2 Choose the objects to include in the report (Schemas, Sites, Tenants, Users, or Infra Logs)

- Sites
- Tenants
- Schemas
- Users
- Infra Logs

Step 3 Click **Download**.

Step 4 Save the report to a local drive to enable attaching it to your support request.

You can also open the file for immediate investigation.

Generating the API Call Logs

You can access the Multi-Site API call logs through the Infra Logs in a Troubleshooting Report. For information, see [Generating a Troubleshooting Report, on page 39](#).

You can also access the API call logs Multi-Site with the following steps:

Before you begin

Access to the VMWare Virtual Machine Multi-Site VMs is available.

Step 1 Locate the worker node that has the `msc-executionengine` service running, as in the following example:

Example:

```
[root@worker1 ~]# docker ps
CONTAINER ID   IMAGE                                COMMAND                                CREATED        STATUS
PORTS         NAMES
1538a9289381   msc-kong:latest                     "/docker-entrypoin..." 2 weeks ago   Up 2 weeks
7946/tcp,    msc_kong.1.ksdw45p0qhb6c08i3c8i4ketc
8000-8001/tcp, 8443/tcp
cc693965f502   msc-executionengine:latest         "bin/executionengine"    2 weeks ago   Up 2 weeks (healthy)
9030/tcp      msc_executionengine.1.nv4j5uj5786yj621wjxsxvxml
00f627c6804c   msc-platformservice:latest         "bin/platformservice"    2 weeks ago   Up 2 weeks (healthy)
9050/tcp      msc_platformservice.1.fw58jvr62dfcme4noh67am0s73
```

In this case, on `cc693965f502` the image is `msc-executionengine:latest`, find the `-json.log`, that contains the API calls from Multi-Site to the APIC controllers.

Step 2 Enter the command in the following example:

Example:

```
[root@worker1 ~]# cd
/var/lib/docker/containers/cc693965f5027f291d3af4a6f2706b19f4ccdf6610de3f7ccd32e1139e31e712
[root@worker1 cc693965f5027f291d3af4a6f2706b19f4ccdf6610de3f7ccd32e1139e31e712]# ls
cc693965f5027f291d3af4a6f2706b19f4ccdf6610de3f7ccd32e1139e31e712-json.log checkpoints config.v2.json
hostconfig.json hostname
hosts resolv.conf resolv.conf.hash shm
```

```
[root@worker1 cc693965f5027f291d3af4a6f2706b19f4ccdf6610de3f7ccd32e1139e31e712]# less \
cc693965f5027f291d3af4a6f2706b19f4ccdf6610de3f7ccd32e1139e31e712-json.log | grep intersite
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"proxy\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-25T08:41:51.241428676Z"}
{"log": " \"intersiteBumTrafficAllow\" :
true,\n", "stream": "stdout", "time": "2017-07-27T07:17:55.418934202Z"}
{"log": " \"intersiteBumTrafficAllow\" :
true,\n", "stream": "stdout", "time": "2017-07-29T10:46:15.077426434Z"}
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"proxy\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-29T10:46:15.334099333Z"}
{"log": " \"intersiteBumTrafficAllow\" :
true,\n", "stream": "stdout", "time": "2017-07-29T11:57:09.361401249Z"}
{"log": " \"intersiteBumTrafficAllow\" :
true,\n", "stream": "stdout", "time": "2017-07-29T11:58:05.491624285Z"}
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"flood\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-29T11:58:05.673341176Z"}
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"flood\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-29T11:58:05.680167766Z"}
{"log": " \"intersiteBumTrafficAllow\" :
true,\n", "stream": "stdout", "time": "2017-07-29T11:58:44.826160838Z"}
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"proxy\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-29T11:58:45.008739316Z"}
{"log": " \u003cfvBD name=\"internal\" arpFlood=\"yes\" intersiteBumTrafficAllow=\"yes\"
unkMacUcastAct=\"proxy\"
intersiteL2Stretch=\"yes\" \u003e\n", "stream": "stdout", "time": "2017-07-29T11:58:45.008812862Z"}

```

Log on to a VM to Collect Data

There are 3 VMs for each Multi-Site instance, differentiated by role: a Manager and two workers. To collect Multi-Site system data, on the VMWare Virtual Machine, you can access the master or worker VMs, run docker commands and copy the output.

Log on to each VM and perform the following steps:

- Zip the whole folder and copy `/var/lib/docker/containers`.
- To generate a list of services, run the **docker service list** command.
- To generate a list of running containers, run the **docker ps** command.
- To generate a list of networks, run the **docker network list** command.

Reading the Execution Log

The execution log provides three different kinds of log information:

- Websocket refresh information that is printed out every 5 minutes.

```

2017-07-11 18:02:45,541 [debug] execution.serice.monitor.WSAPicActor - WebSocket
connection open
2017-07-11 18:02:45,542 [debug] execution.serice.monitor.WSAPicActor - Client 3 intialized
2017-07-11 18:02:45,551 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message Monitor Policy(WSMonitorQuery(/api/class/fvRsNodeAtt,?subscript
2017-07-11 18:02:45,551 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message RefreshClientTokenFailed())
2017-07-11 18:02:45,551 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message RefreshClientToken()
2017-07-11 18:02:45,551 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message RefreshClientToken()
2017-07-11 18:02:50,042 [debug] execution.serice.monitor.WSAPicActor - Websocket
connection open
2017-07-11 18:02:50,042 [debug] execution.serice.monitor.WSAPicActor - Client 3 intialized
2017-07-11 18:02:50,043 [debug] execution.serice.monitor.WSAPicActor - Initiate WS
subscription for WSMonitorQuery(/api/class/fvRsNodeAtt,?subscript=yes&page=s
2017-07-11 18:02:50,047 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message RefreshClientToken()
2017-07-11 18:02:50,047 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message RefreshClientToken()
2017-07-11 18:02:50,180 [debug] execution.serice.monitor.WSAPicActor - WSAPicActor
stashing message akka.actor.LightArrayRevolverScheduler$TaskHolder@13d740ff
2017-07-11 18:02:55,221 [debug] execution.serice.monitor.WSAPicActor - Websocket
connection open
2017-07-11 18:02:55,222 [debug] execution.serice.monitor.WSAPicActor - Client 3 intialized
2017-07-11 18:02:55,233 [debug] execution.serice.monitor.WSAPicActor - Token Refreshed
2017-07-11 18:02:55,323 [debug] execution.serice.monitor.WSAPicActor - Token Refreshed

```

- The schema to push and the plan being generated.
- Websocket monitoring VNID for cross VNID programming.

Note the following signs of errors:

- Log lines starting with a red error.
- Stacktrace for exceptions.

Verifying that the Cisco ACI Multi-Site Microservices are Active

This section describes how to verify that the Cisco ACI Multi-Site microservices are active on the VMware Virtual Machine, access the master VM. There are 3 VMs for each Multi-Site instance, differentiated by role: a Manager and two workers.

Verify that the Cisco ACI Multi-Site microservices are active, enter the following command:

Example:

```

[root@manager containers]# docker service list

```

ID	NAME	MODE	REPLICAS	IMAGE	PORTS
0x2trundn0pd	m_sc_kongdb	replicated	1/1	postgres:9.4	*:5432->5432/tcp
39a5wt5f0t97	m_sc_executionengine	replicated	1/1	m_sc_executionengine:latest	*:9030->9030/tcp
6599jktwvq2r	m_sc_platformservice	replicated	1/1	m_sc_platformservice:latest	*:9050->9050/tcp
6qab953k331q	m_sc_kong	replicated	1/1	m_sc_kong:latest	
:8000->8000/tcp,:8001->8001/tcp					
kumogcalk7a5	m_sc_ui	replicated	1/1	m_sc_ui:latest	
:80->80/tcp,:443->443/tcpt					
7jmqchg9rup	m_sc_schemaservice	replicated	1/1	m_sc_schemaservice:latest	*:9020->9020/tcpt
jnluemky85q	m_sc_userservice	replicated	1/1	m_sc_userservice:latest	*:9040->9040/tcp

```
xlybltju9dar msc_mongodb replicated 1/1 mongo:3.4 *:27017->27017/tcp
ye4i314irzw5 msc_siteservice replicated 1/1 msc-siteservice:latest *:9010->9010/tcp
```

Verifying Policy Resolution on APIC Sites

In this task, use a REST API MO query on local APIC sites or switches to view the policies resolved on an APIC, for a site managed by Cisco ACI Multi-Site.

For diagrams of the managed objects (MO) relationships, see the *Cisco APIC Management Information Model Reference* (MIM). For example, in the MIM, see the diagram for `fv:FabricExtConnP`.

Step 1 To view details for the logical MOs under the Fabric External Connection Profile (`fabricExtConnP`), log on to the APIC CLI and enter the following MO query:

Example:

```
admin@apic1:~> moquery -c fvFabricExtConnP -x "query-target=subtree"
| egrep "#|dn"
# fv.IntersiteMcastConnP
dn: uni/tn-infra/fabricExtConnP-1/intersiteMcastConnP
# fv.IntersitePeeringP
dn: uni/tn-infra/fabricExtConnP-1/ispeeringP
# fv.IntersiteConnP
dn: uni/tn-infra/fabricExtConnP-1/podConnP-1/intersiteConnP-[5.5.5.1/32]
# fv.Ip
dn: uni/tn-infra/fabricExtConnP-1/podConnP-1/ip-[5.5.5.4/32]
# fv.PodConnP
dn: uni/tn-infra/fabricExtConnP-1/podConnP-1
# fv.IntersiteConnP
dn: uni/tn-infra/fabricExtConnP-1/siteConnP-6/intersiteConnP-[6.6.6.1/32]
# fv.IntersiteMcastConnP
dn : uni/tn-infra/fabricExtConnP-1/siteConnP-6/intersiteMcastConnP
# fv.SiteConnP
dn: uni/tn-infra/fabricExtConnP-1/siteConnP-6
# l3ext.FabricExtRoutingP
dn: uni/tn-infra/fabricExtConnP-1/fabricExtRoutingP-default
# fv.FabricExtConnP
dn: uni/tn-infra/fabricExtConnP-1
```

Step 2 To view the logical MOs for the L3Out used for Multi-Site connections, log on to the APIC CLI and enter an MO query, such as the following:

Example:

```
admin@apic1:~> moquery -c l3extOut -x "query-target=subtree" | egrep
"#|dn.*intersite" | grep -B 1 dn
# bgp.ExtP
dn: uni/tn-infra/out-intersite/bgpExtP
# fv.RsCustQosPol
dn: uni/tn-infra/out-intersite/instP-intersiteInstP/rscustQosPol
# l3ext.InstP
dn: uni/tn-infra/out-intersite/instP-intersiteInstP
# bgp.AsP
dn: uni/tn-infra/out-intersite/lndep-node-501-profile/infraPeerP-[6.6.6.3]/as
# bgp.RsPeerPfxPol
dn: uni/tn-infra/out-intersite/lndep-node-501-profile/infraPeerP-[6.6.6.3]/rspeerPfxPol
# bgp.InfraPeerP
```

```

dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/infraPeerP-[6.6.6.3]
# l3ext.RsEgressQosDppPol
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/rsegressQosDppPol
# l3ext.RsIngressQosDppPol
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/rsingressQosDppPol
# l3ext.RsNdIfPol
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/rsNdIfPol
# l3ext.RsPathL3OutAtt
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/rspathL3OutAtt-
[topology/pod-1/paths-501/pathep-[eth1/1]]
# ospf.RsIfPol
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/ospfIfP/rsIfPol
# ospf.IfP
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1/ospfIfP
# l3ext.LIfP
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/lifp-port-1-1
# l3ext.InfraNodeP
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/rsnodeL3OutAtt-
[topology/pod-1/node-501]/infranodep
# l3ext.IntersiteLoopBackIfP
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/rsnodeL3OutAtt-
[topology/pod-1/node-501]/sitelbp-[5.5.5.3]
# l3ext.RsNodeL3OutAtt
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile/rsnodeL3OutAtt-
[topology/pod-1/node-501]
# l3ext.LNodeP
dn: uni/tn-infra/out-intersite/lnodep-node-501-profile
# l3ext.RsEctx
dn: uni/tn-infra/out-intersite/rsectx
# l3ext.RsL3DomAtt
dn: uni/tn-infra/out-intersite/rsl3DomAtt
# ospf.ExtP
dn: uni/tn-infra/out-intersite/ospfExtP
# l3ext.Out
dn: uni/tn-infra/out-intersite--
# l3ext.ConfigOutDef
dn: uni/tn-infra/out-intersite/instP-intersiteInstP/configOutDef

```

Step 3 To view the resolved MOs for an APIC local site, log on to the APIC CLI and enter an MO query such as the following:

Example:

```

admin@apic1:~> moquery -c fvSite -x "query-target=subtree" | egrep "#|dn"
# fv.RemoteBdDef
dn: resPolCont/sitecont/site-6/remotebddef-[uni/tn-msite-tenant-welkin/BD-internal]
# fv.RemoteCtxDef
dn: resPolCont/sitecont/site-6/remotectxdef-[uni/tn-msite-tenant-welkin/ctx-dev]
# fv.RemoteEPgDef
dn: resPolCont/sitecont/site-6/remoteepgdef-[uni/tn-msite-tenant-welkin/ap-Ebiz/epg-data]
# fv.RemoteEPgDef
dn: resPolCont/sitecont/site-6/remoteepgdef-[uni/tn-msite-tenant-welkin/ap-Ebiz/epg-web]
# fv.Site
dn: resPolCont/sitecont/site-6
# fv.LocalBdDef
dn: resPolCont/sitecont/site-5/localbddef-[uni/tn-msite-tenant-welkin/BD-internal]
# fv.LocalCtxDef
dn: resPolCont/sitecont/site-5/localctxdef-[uni/tn-msite-tenant-welkin/ctx-dev]
# fv.LocalEPgDef
dn: resPolCont/sitecont/site-5/localepgdef-[uni/tn-msite-tenant-welkin/ap-Ebiz/epg-web]
# fv.LocalEPgDef
dn: resPolCont/sitecont/site-5/localepgdef-[uni/tn-msite-tenant-welkin/ap-Ebiz/epg-data]
# fv.Site
dn: resPolCont/sitecont/site-5

```

Step 4 To view the concrete MOs on a switch for a Multi-Site site, log on to the switch and enter an MO query such as the following:

Example:

```
spine501# moquery -c dci.LocalSite -x "query-target=subtree" | egrep "#|dn"
# 12.RtToLocalBdSubstitute //(site5 vrf 2195456 -> bd 15794150 is translated to
site6 vrf 2326528 -> bd 16449430)
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localBdSubstitute-
[vxlan-15794150]/rttoLocalBdSubstitute-[sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-
[vxlan-2326528]/remoteBdSubstitute-[vxlan-16449430]]
# 12.LocalBdSubstitute
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localBdSubstitute-
[vxlan-15794150]
# 12.RtToLocalPcTagSubstitute //(site5 vrf 2195456 -> pcTag 49154 is translated to
site6 vrf 2326528 -> pcTag 32770)
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localPcTagSubstitute-
49154/rttoLocalPcTagSubstitute-[sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-
[vxlan-2326528]/remotePcTagSubstitute-32770]
# 12.LocalPcTagSubstitute
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localPcTagSubstitute-
49154# 12.RtToLocalPcTagSubstitute //(site5 vrf 2195456 -> pcTag 16387 is translated to site6
vrf 2326528 -> pcTag 16386)
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localPcTagSubstitute-
16387/rttoLocalPcTagSubstitute-[sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-
[vxlan-2326528]/remotePcTagSubstitute-16386]
# 12.LocalPcTagSubstitute
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/localPcTagSubstitute-
16387# 13.RtToLocalCtxSubstitute //(site5 vrf 2195456 is translated to site6 vrf 2326528)
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]/rttoLocalCtxSubstitute-
[sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]]
# 13.LocalCtxSubstitute
dn: sys/inst-overlay-1/localSite-5/localCtxSubstitute-[vxlan-2195456]
# dci.LocalSite
dn: sys/inst-overlay-1/localSite-5
```

What to look for: The output displays the data translated between sites. In this example, the original data on the sites was as follows:

- site5 vrf msite-tenant-welkin:dev -> vxlan 2195456, bd internal -> vxlan 15794150, epg web: access-encap 200 → pcTag 49154, access-encap 201 → pcTag 16387
- site6 vrf msite-tenant-welkin:dev -> vxlan 2326528, bd internal -> vxlan 16449430, epg web: access-encap 200 ->pcTag 32770,access-encap 201 ->pcTag 16386

Step 5 To verify the concrete MOs for a remote site, enter an MO query such as the following:

Example:

```
spine501# moquery -c dci.RemoteSite -x "query-target=subtree"
| egrep "#|dn"
# dci.AnycastExtn
dn: sys/inst-overlay-1/remoteSite-6/anycastExtn-[6.6.6.1/32]
// attribute is_unicast is Yes, Unicast ETEP
# dci.AnycastExtn
dn: sys/inst-overlay-1/remoteSite-6/anycastExtn-[6.6.6.2/32]
// attribute is_unicast is No, Multicast ETEP
# 12.RsToLocalBdSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remoteBdSubstitute-
[vxlan-16449430]/rsToLocalBdSubstitute
# 12.RemoteBdSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remoteBdSubstitute-
[vxlan-16449430]
```

```
# 12.RsToLocalPcTagSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remotePcTagSubstitute-32770/rsToLocalPcTagSubstitute
# 12.RemotePcTagSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remotePcTagSubstitute-32770# 12.RsToLocalPcTagSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remotePcTagSubstitute-16386/rsToLocalPcTagSubstitute
# 12.RemotePcTagSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/remotePcTagSubstitute-16386# 13.RsToLocalCtxSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]/rsToLocalCtxSubstitute
# 13.RemoteCtxSubstitute
dn: sys/inst-overlay-1/remoteSite-6/remoteCtxSubstitute-[vxlan-2326528]
# dci.RemoteSite
dn: sys/inst-overlay-1/remoteSite-6
```



CHAPTER 8

Troubleshooting Multipod and Multi-Site Issues

This chapter contains the following sections:

- [Troubleshooting Multipod and Multi-Site, on page 47](#)

Troubleshooting Multipod and Multi-Site

This section describes how to troubleshoot Multipod and Multi-Site.

If you receive the following error:

Error:400 - Invalid Configuration Following Intersite Spines are not configured as Mpod Spines: 1202

You must enable the fabric external connectivity for all the existing spines and if you are trying to add new spines use the Setup Multipod method.

There are two ways to resolve this issue.

- Enable all the spines under the external routed network:
 - In the APIC GUI, on the menu bar, click **Tenant > infra**.
 - In the **Navigation** pane, expand **Networking > External Routed Networks**, right-click on the external routed network and choose **Enable Fabric External Connectivity**.
- Add new spines under the external routed network:
 - In the APIC GUI, on the menu bar, click **Fabric**.
 - In the **Navigation** pane, expand **Quick Start > Node or Pod Setup > Setup Multipod** and complete the Multipod setup.



CHAPTER 9

Verifying NXOS Hardware Tables

This chapter contains the following sections:

- [Verifying End Point Manager Learning, on page 49](#)
- [Verifying BGP EVPN Routing Table, on page 50](#)
- [Verifying VNID, S-Class, and VTEP Mappings, on page 52](#)
- [Verifying LC Hardware Tables, on page 55](#)

Verifying End Point Manager Learning

Use the following commands to verify End Point Manager (EPM) learning.

In the following example, you can use the command to verify that source EP 172.17.15.105 is discovered in site5, leaf101. This output shows that for EP 172.17.15.105, the BD-VNID is 15794150, VRF-VNID is 2195456, and the pcTag or sclass is 16387.

```
leaf101# show sys int epm end mac 0000.5555.1715
```

```
MAC : 0000.5555.1715 ::: Num IPs : 1
IP# 0 : 172.17.15.105 ::: IP# 0 flags :
Vlan id : 18 ::: Vlan vnid : 8393 ::: VRF name : msite-tenant-welkin:dev
BD vnid : 15794150 ::: VRF vnid : 2195456
Phy If : 0x1a000000 ::: Tunnel If : 0
Interface : Ethernet1/1
Flags : 0x80004c04 ::: sclass : 16387 ::: Ref count : 5
EP Create Timestamp : 07/30/2017 07:28:40.535135
EP Update Timestamp : 07/30/2017 08:05:56.769126
EP Flags : local|IP|MAC|sclass|timer|
:::
```

```
leaf101# show sys int epm end ip 172.17.15.106
```

```
MAC : 0000.6666.1716 ::: Num IPs : 1
IP# 0 : 172.17.15.106 ::: IP# 0 flags :
Vlan id : 9 ::: Vlan vnid : 8193 ::: VRF name : msite-tenant-welkin:dev
BD vnid : 16449430 ::: VRF vnid : 2326528
Phy If : 0x1a027000 ::: Tunnel If : 0
Interface : Ethernet1/40
Flags : 0x80005c04 ::: sclass : 16386 ::: Ref count : 5
EP Create Timestamp : 07/31/2017 05:15:24.179330
EP Update Timestamp : 08/01/2017 10:45:06.108770
```

```
EP Flags : local|IP|MAC|host-tracked|sclass|timer|
:::
```

Verifying BGP EVPN Routing Table

Use the following commands to verify the BGP EVPN routing table.

In this example, the end point 172.17.15.105 discovered from leaf101 is published to spine501 via COOP by EPM (Endpoint manager). COOP process on the spine and then syncs the EP to L2vpn EVPN. The command output show us that EP 172.17.15.105 is local to site 5 and being advertised to site 6 by BGP EVPN.

```
spine501# show bgp l2vpn evpn 172.17.15.105 vrf overlay-1
Route Distinguisher: 1:99680230 (L2VNI 15794150)
BGP routing table entry for [2]:[0]:[15794150]:[48]:[0000.5555.1715]:[32]:[172.17.15.105]/272,
  version 719 dest ptr 0xab0a63de
MSITE RD: 1:99680230 (L2VNI 15794150)
Local Route Distinguisher: 5.5.5.4:65005 (L2VNI 1)
Paths: (1 available, best #1)
Flags: (0x00010a 00000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP
```

```
  Advertised path-id 1
  Path type: local 0x4000008c 0x0 ref 0, path is valid, is best path
  AS-Path: NONE, path locally originated
  5.5.5.4 (metric 0) from 0.0.0.0 (5.5.5.3)
  Origin IGP, MED not set, localpref 100, weight 32768
  Received label 15794150 2195456
  Extcommunity:
  RT:5:5
```

```
  Path-id 1 advertised to peers:
  6.6.6.3
```

```
Route Distinguisher: 5.5.5.4:65005 (L2VNI 1)
BGP routing table entry for [2]:[0]:[15794150]:[48]:[0000.5555.1715]:[32]:[172.17.15.105]/272,
  version 719 dest ptr 0xab0a63de
MSITE RD: 1:99680230 (L2VNI 15794150)
Local Route Distinguisher: 5.5.5.4:65005 (L2VNI 1)
Paths: (1 available, best #1)
Flags: (0x00010a 00000000) on xmit-list, is not in rib/evpn
Multipath: eBGP iBGP
```

```
  Advertised path-id 1
  Path type: local 0x4000008c 0x0 ref 0, path is valid, is best path
  AS-Path: NONE, path locally originated
  5.5.5.4 (metric 0) from 0.0.0.0 (5.5.5.3)
  Origin IGP, MED not set, localpref 100, weight 32768
  Received label 15794150 2195456
  Extcommunity:
  RT:5:5
```

```
  Path-id 1 advertised to peers:
  6.6.6.3
```

```
spine501# show bgp internal evi 15794150
```

```
*****
```

```

Global EVI : 1
Number of EVI : 1
L2RIB bound / VNI Req to L2RIB : Yes / 1
VNI Adds / Dels from L2RIB : 9 / 6
Topo global/mpod/wan/avs/msite reg pending: 0/0/0/0/0
Topo global/mpod/wan/avs/msite registered: 1/0/0/0/1
L2RIB is up/registered/local-req: 1/1
L2RIB down: in-prg/up-defer: 0/0
L2RIB register/failures: 1/0
L2RIB deregister/failures: 0/0
L2RIB flow control (#enabled/#disabled): Disabled (0/0)
*****
L2RIB Emulation Library Info
-----
L2RIB Service BGP state UP BIND PEERBIND
Global EVI 134217729, MPOD SHARD shard [0, 0]
Global EVI 134217729, MSITE SHARD shard [0, 4294967295] --- --- The global EVI is same for
the identical across multi-sites.
Global EVI 134217729, GOLF SHARD shard [0, 0]
Global EVI 134217729, EXT_SRC SHARD shard [0, 0]
MTS: total 1 bufs 1 free 0 full 0 working
MTS TX: 408 (Fail 0) RX: 229
MTS PAUSE: 0 (Flush Fail 0)
Peer service COOP state UP BIND PEERBIND
BIND TX: 61 RX: 0
REGISTER TX: 61 RX: 0
TOPO TX: 0 RX: 21
MAC TX: 395 RX: 208
IP TX: 19 RX: 39
IMET TX: 0 RX: 0
SMAD TX: 0 RX: 0
Peer service ISIS state DOWN UNBIND PEERUNBIND
BIND TX: 0 RX: 0
REGISTER TX: 0 RX: 0
TOPO TX: 0 RX: 0
MAC TX: 0 RX: 0
IP TX: 0 RX: 0
IMET TX: 0 RX: 0
SMAD TX: 0 RX: 0
*****
BGP L2VPN/EVPN RD Information for 1:99680230
L2VNI ID : 15794150 (vni_15794150)
#Prefixes Local/BRIB : 2 / 4
#Paths L3VPN->EVPN/EVPN->L3VPN : 0 / 0
*****
=====
BGP Configured VNI Information:
VNI ID (Index) : 15794150 (0)
RD : 1:99680230
Export RTs : 1
Export RT cfg list: 65005:99680230(refcount:1
Import RTs : 1
Import RT cfg list: 65006:117112726(refcount:1
Topo Id : 15794150
VTEP IP : 0.0.0.0
VTEP VPC IP : 0.0.0.0
Enabled : Yes
Delete Pending : No
RD/Import RT/Export RT : Yes/Yes/Yes
Type : 3
Usage : 2
L2 stretch enabled : 1
VRF Vnid : 2195456
RefCount : 00000003

```

```
Encap : VxLAN
```

```
=====
+++++
BGP VNI Information for vni_15794150
L2VNI ID : 15794150 (vni_15794150)
RD : 1:99680230
VRF Vnid : 2195456
Prefixes (local/total) : 2/4
VNID registered with COOP : Yes
Enabled : Yes
Delete pending : 0
Stale : No
Import pending : 0
Import in progress : 0
Encap : VxLAN
Topo Id : 15794150
VTEP IP : 0.0.0.0
VTEP VPC IP : 0.0.0.0
Active Export RTs : 1
Active Export RT list : 65005:99680230
Config Export RTs : 1
Export RT cfg list: 65005:99680230(refcount:1
Export RT chg/chg-pending : 0/0
Active Import RTs : 1
Active Import RT list : 65006:117112726
Config Import RTs : 1
Import RT cfg list: 65006:117112726(refcount:1
Import RT chg/chg-pending : 0/0
IMET Reg/Unreg from L2RIB : 1/0
MAC Reg/Unreg from L2RIB : 1/0
MAC IP Reg/Unreg from L2RIB : 1/0
IP-only Reg/Unreg from L2RIB : 0/0
SMAD Reg/Unreg from L2RIB : 1/0
IMET Add/Del from L2RIB : 0/0
MAC Add/Del from L2RIB : 97/96
MAC IP Add/Del from L2RIB : 3/2
SMAD Add/Del from L2RIB : 0/0
IMET Dnld/Wdraw to L2RIB : 0/0
IMET Dnld/Wdraw to L2RIB failures : 0/0
MAC Dnld/Wdraw to L2RIB : 190/189
MAC Dnld/Wdraw to L2RIB failures : 0/0
SMAD Dnld/Wdraw to L2RIB : 0/0
SMAD Dnld/Wdraw to L2RIB failures : 0/0
MAC-IP/SMAD Msite-RD routes : 4
MAC-IP WAN-RD routes : 0
MAC-IP network host routes : 0
Type : 3
```

Verifying VNID, S-Class, and VTEP Mappings

Use the following command to verify remote site ID.

For VNID and pcTag or s-class translation between sites, the translation should be verified from the destination site. For example, if the packet is sending from site5 to site6, the translation is done by the site6's spine. To verify if the translation is pushed to site5, use the following command.

```
spine501# show dcmgr repo eteps
```

```
Remote site=6 :
```

```
Rem Etep=6.6.6.1/32, is_ucast=yes
Rem Etep=6.6.6.2/32, is_ucast=no
```

Use the following command to verify sclass-map between the remote and local site.

```
spine501# show dcimgr repo sclass-maps
-----
      Remote          |          Local
site  Vrf            PcTag | Vrf            PcTag      Rel-state
-----
   6   2326528       32770 | 2195456       49154    [formed]
   6   2326528       16386 | 2195456       16387    [formed]
```

Use the following commands to verify VRF or BD VNID map between remote and local site.

```
spine501# show dcimgr repo vnid-maps detail
-----
      Remote          |          Local
site  Vrf            Bd      | Vrf            Bd      Rel-state
-----
   6   2326528         | 2195456         [formed]
      0x238000         | 0x218000
-----
   6   2326528 16449430 | 2195456 15794150 [formed]
      0x238000 0xfaff96 | 0x218000 0xf0ffe6
-----
```

```
spine501# show dcimgr repo vnid-maps verbose

Local site=5 Remote site=6:
Loc vrfvniid=2195456 Rem vrfvniid=2326528 rel-state=formed
  BD Vnids:
  Loc vniid=15794150 Rem vniid=16449430 rel-state=formed
```

Use the following commands to verify DCI HAL objects.

```
module-1# show plat int hal objects dci all
Dumping dci objects
## Get Objects for dci remotesite for Asic 0

  OBJECT 0:
Handle                               : 23967
siteid                                : 0x6
iswan                                  : Disabled

## Get Objects for dci remotesiteetep for Asic 0

  OBJECT 0:
Handle                               : 23970
ucastetep                             : 6.6.6.1/32
siteid                                  : 0x6

## Get Objects for dci vnidmap for Asic 0

  OBJECT 0:
Handle                               : 23977
isbdvniid                             : Disabled
localvniid                             : 0x218000
localgipo                               : 0.0.0.0/32
remotevniid                             : 0x238000
remotevrfvniid                         : 0x238000
```

```

islocalbdctrl           : Disabled
siteid                  : 0x6

OBJECT 1:
Handle                  : 23980
isbdvnmid              : Enabled
localvnmid             : 0xf0ffe6
localgipo               : 225.0.225.160/32
remotevnmid            : 0xfaff96
remotevrfrvnmid       : 0x238000
islocalbdctrl         : Enabled
siteid                  : 0x6

## Get Objects for dci remotevrfrvnmid for Asic 0

OBJECT 0:
Handle                  : 23972
remotevnmid            : 0x238000
siteid                  : 0x6

## Get Objects for dci sclassmap for Asic 0

OBJECT 0:
Handle                  : 23986
localsclass            : 0x4003 //18387
remotesclass           : 0x4002 //16386
remotevnmid           : 0x238000
siteid                  : 0x6

OBJECT 1:
Handle                  : 23974
localsclass            : 0x1
remotesclass           : 0x1
remotevnmid           : 0x238000
siteid                  : 0x6

OBJECT 2:
Handle                  : 23983
localsclass            : 0xc002 //49154
remotesclass           : 0x8002 //32770
remotevnmid           : 0x238000
siteid                  : 0x6

```

Use the following commands to verify VXLAN objects.

```
module-1# show plat int hal objects vxlan mytep | egrep -B 13 -A 8 5.5.5.1
```

```

OBJECT 11:
Handle                  : 23964
useforvpc              : Disabled
usefornonvpc           : Disabled
useforvteps            : Disabled
proxyforv4             : Disabled
proxyforv6             : Disabled
isdciucastetep        : Enabled
isdcimcastetep        : Disabled
isdcieteplocal        : Enabled
proxyformac            : Disabled
outerbdid              : 0x2
rmac                   : 00:0d:0d:0d:0d:0d

```

```

csouterbdid           : 0x1
address               : 5.5.5.1/32
encaptype             : iVxlan
id                    : 0x1400000b
lid                   : 0x0
iftype                : none
ifname                : Lol1
Relation Object ipteptovrf :
    rel-ipteptovrf-13-13_vrf-handle : 6983
    rel-ipteptovrf-13-13_vrf-id    : 0x2

```

```

module-1# show plat int hal objects vxlan remotetep | egrep -B 28 -A 8
6.6.6.1

```

```

OBJECT 1:
Handle                : 25810
operst                : up
enablelearning        : Disabled
enablebindlearn       : Disabled
enablesclasslearn     : Disabled
drop                  : Disabled
isvpcpeer             : Disabled
islocal               : Disabled
proxyforv4            : Disabled
proxyforv6            : Disabled
proxyformac           : Disabled
unicastreplication    : Disabled
splithorizongroupid   : 0x0
trustqosmarking       : Disabled
trustsclass           : Disabled
trustlb               : Disabled
trustdl               : 0x1
istepscale            : Disabled
usedfhash              : Disabled
dismark                : Disabled
hwencapidx            : 0x5
srcnat                 : Disabled
isingressonly         : Disabled
isipn                 : Disabled
isdciucastetep        : Enabled
isdcmcastetep         : Disabled
address               : 6.6.6.1/32
encaptype             : iVxlan
id                    : 0x18010004
lid                   : 0x0
iftype                : none
ifname                : Tunnel4
Relation Object ipteptovrf :
    rel-ipteptovrf-13-13_vrf-handle : 6983
    rel-ipteptovrf-13-13_vrf-id    : 0x2

```

Verifying LC Hardware Tables

Use the following commands to verify LC hardware tables.

```

module-1# show platform internal hal dci sclassmap
Non-Sandbox Mode

Sandbox_ID: 0 Asic Bitmap: 0x0

```

```

--- DCI Sclass table ---
Site Remote Local Remote Remote Local
ID Vnid Sclass Sclass Sclass Sclass Scope
-----+-----+-----+-----+-----+-----
6 2326528 16387 16386 16386 16387 1
6 2326528 1 1 1 1 1
6 2326528 49154 32770 32770 49154 1
next asic

```

```
module-1# show platform internal hal dci vnidmap
```

```
Non-Sandbox Mode
```

```
Sandbox_ID: 0 Asic Bitmap: 0x0
```

```

Site POD isBD Local Remote ----EPG table---- BD State Table
ID ID vnid vnid idx Localvnid idx isBD
-----+-----+-----+-----+-----+-----+-----
6 1 0 2195456 2326528 15360 2195456 15360 0
6 1 1 15794150 16449430 15361 15794150 15361 1

```

```
module-1# show platform internal sug tile-table dci-sclass
```

```

=====
SLICE : 0 FP : 6
TILE : 0
=====
ENTRY[001208] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x1
                tile_entry_dci_sclass_entry_0_data_sclass_out=0x1
ENTRY[001645] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x4002
                tile_entry_dci_sclass_entry_0_data_sclass_out=0x4003
ENTRY[001713] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x8002
                tile_entry_dci_sclass_entry_0_data_sclass_out=0xc002
=====
SLICE : 1 FP : 6
TILE : 0
=====
ENTRY[001208] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x1
                tile_entry_dci_sclass_entry_0_data_sclass_out=0x1
ENTRY[001645] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x4002
                tile_entry_dci_sclass_entry_0_data_sclass_out=0x4003
ENTRY[001713] = tile_entry_dci_sclass_entry_0_key_valid=0x1
                tile_entry_dci_sclass_entry_0_key_scope=0x1
                tile_entry_dci_sclass_entry_0_key_sclass_in=0x8002
                tile_entry_dci_sclass_entry_0_data_sclass_out=0xc002
=====

```