



# Cisco APIC OpenStack Plug-in Release Notes, Release 5.1(1)

This document describes the features, bugs, and limitations for the Cisco Application Policy Infrastructure Controller (APIC) OpenStack Plug-in.

Cisco APIC OpenStack Plug-in allows policy deployment automation across Cisco Application Centric Infrastructure (ACI) and OpenStack, enabling a complete undercloud and overcloud visibility on Cisco ACI. The Cisco APIC OpenStack Plug-in allows dynamic creation of networking constructs to be driven directly from OpenStack, while providing additional visibility and control from the Cisco APIC.

Release notes are sometimes updated with new information about restrictions and bugs. See the following website for the most recent version of this document:

<https://www.cisco.com/c/en/us/support/cloud-systems-management/application-policy-infrastructure-controller-apic/tsd-products-support-series-home.html>

Note: The documentation set for this product strives to use bias-free language. For the purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on RFP documentation, or language that is used by a referenced third-party product.

Date	Description
2020-11-18	Added restriction for feature Neutron SVI support for dual-stack IP addressing.
2020-11-17	Release 5.1(1) became available.

## Contents

This document includes the following sections:

- [Cisco ACI Virtualization Compatibility Matrix](#)
- [New and Changed Information](#)
- [Supported Scale](#)
- [Known Limitations](#)
- [Usage Guidelines](#)
- [Bugs](#)
- [Related Documentation](#)
- [New Documentation](#)

## Cisco ACI Virtualization Compatibility Matrix

For information about Cisco ACI and OpenStack, see the *Cisco Virtualization Compatibility Matrix* at the following URL:

- <https://www.cisco.com/c/dam/en/us/td/docs/Website/datacenter/aci/virtualization/matrix/virtmatrix.html>

## New and Changed Information

This section lists the new and changed features in this release and includes the following topics:

- [New Software Features](#)
- [Changes In Behavior](#)

## New Software Features

Feature	Description	Guidelines and Restrictions
Neutron SVI support for dual-stack IP addressing	OpenStack supports dual-stack IP addressing—the ability configure IPv4 and IPv6 traffic at the same time—on Switched Virtual Interface (SVI) networks. Using dual-stack IP addressing provides the advantages of IPv6—increased network efficiency and larger address space—while supporting hosts or applications that do not support IPv6.	See the section “Dual Stack with SVI Integration” in the chapter “Neutron SVI Integration” in the Cisco ACI OpenStack Plugin User Guide on Cisco.com.  Note: Stateless Address Auto Configuration (SLAAC) is not orchestrated by OpenStack for SVI-type networks.

## Changes in Behavior

There are no new behaviors in this release.

## New Behaviors in Previous Releases

See the OpenStack Release Notes for previous releases for information about new behaviors in those releases.

## Supported Scale

For the verified scalability limits (except for CLI limits), see the *Verified Scalability Guide* for this release. For Kubernetes-based Integrations (including Docker, OpenShift, and Rancher), and OpenStack Platform Scale Limits, see the following table.

Note: The scalability information in the following table applies to Kubernetes or OpenStack resources integrated with OpFlex into the Cisco ACI fabric. It does not apply to Microsoft SCVMM hosts or Cisco ACI Virtual Edge instances.

Limit Type	Maximum Supported
Number of OpFlex hosts per leaf	120
Number of OpFlex hosts per port	20
Number of vPC links per leaf	40
Number of endpoints per leaf	10,000
Number of endpoints per host	400
Number of virtual endpoints per leaf	40,000

Notes:

- For containers, an **endpoint corresponds to a pod's network interface**.
- For OpenStack, an endpoint corresponds to any of the following:
  - A virtual machine (VM) interface (also known as vnic)
  - **A DHCP agent's port in OpenStack (if in DHCP namespace on the network controller)**
  - A floating IP address
- Total virtual endpoints on a leaf can be calculated as  $\text{virtual endpoints / leaf} = \text{VPCs} \times \text{EPGs}$ , where:
  - VPCs is the number of VPC links on the switch in the attachment profile used by the OpenStack Virtual Machine Manager (VMM).
  - EPGs is the number of EPGs provisioned for the OpenStack VMM.

For the CLI verified scalability limits, see the *Cisco NX-OS Style Command-Line Interface Configuration Guide* for this release.

## Known Limitations

This section lists the known limitations.

- Cisco ACI Unified Plug-in for OpenStack does not support the following features:
  - ESX hypervisor support
  - ASR1K edgeNAT support
  - GBP/NFP Service chaining
  - ML2 Network constraints
- Dual-stack operation requires that all IPv4 and IPv6 subnets - both for internal and external networks - use the same VRF in Cisco ACI. The one exception to this is when separate external networks are used for IPv4 and IPv6 traffic. In that workflow, the IPv4 and IPv6 subnets used for internal networks plus the IPv6 subnets used for external networks all belong to one VRF, while the subnets for the IPv4 external network belong to a different VRF. IPv4 NAT can then be used for external networking.
- For installations with B-series that use VXLAN encapsulation, Layer 2 Policies (for example, bridge domains) should each contain only one Policy Target Group (that is, Endpoint Group) to ensure a functional data plane.
- The Cisco ACI OpenStack Plug-in is not integrated with the Multi-Site Orchestrator. When deploying to a Multi-Site deployment, the Cisco ACI configurations implemented by the plug-in must not be affected by the Multi-Site Orchestrator.
- NFV features, including SVI networks, trunk ports, and Service Function Chaining plug-in and workflow, are supported starting with the Ocata release of the plug-in.
- When you delete the Overcloud Heat stack, the Overcloud nodes are freed but the virtual machine manager (VMM) domain remains present in Cisco APIC. The VMM appears in Cisco APIC as a stale VMM domain along with the tenant unless you delete the VMM domain manually. Before you delete the VMM domain, verify that the stack has been deleted from the undercloud, and check that any hypervisors appearing under the VMM domain are no longer in the connected state. Once both of these conditions are met, you can safely delete the VMM domain Cisco APIC.
- Due to a bug in upstream Neutron, support bindings are not cleaned up in trunk workflows. This has existed in earlier releases and is equally applicable to usage with Open vSwitch (OVS) reference implementation agents as well as OpFlex agents. For more information about the Neutron bug, see bug 1639111 on the Launchpad.net website.

## Usage Guidelines

- We recommend that service VMs used in service function chaining (SFC) workflows use static IP addressing and not rely on DHCP. When the service VM becomes part of a service chain in OpenStack and correspondingly a service graph on Cisco ACI, the associated EPG is removed. Thus, services such as DHCP are not available for the endpoint. This is applicable with OVS reference implementation agents as well as OpFlex agents.
- When you run the host report ansible-playbook (`/opt/ciscoaci-tripleo-heat-templates/tools/report.yml`), the step to copy files from a running container may return an error, causing the host report to fail. If this happens, rerun the playbook until it succeeds. The failure is due to a known issue in Red Hat OpenStack Platform (OSP) 13 Director.

For more information, see the Red Hat Bugzilla bug 1767289. You can find the related product note in the Red Hat Customer portal **knowledge base article “docker cp command sometimes failed with invalid argument.”**

- If you are using Cisco ACI Virtual Edge with OpenStack or Kubernetes OpFlex on the same leaf, do not use Cisco APIC version 4.2(3), or you will encounter the bug CSCvs49419. If you have that configuration and need features from the Cisco APIC 4.2(x) release train, use the 4.2(2) or 4.2(4) version.
- JuJu charms users must first update the Charms before installing the updated plug-in.
- Newer RHEL installations limit the maximum number of multicast group subscriptions to 20. This is configured with the `net.ipv4.igmp_max_memberships` sysctl variable. Installations using VXLAN encapsulation for OpenStack VMM domains should set this value higher than the total number of endpoint groups (EPGs) that might appear on the node (one for each Neutron network with Neutron workflow, or one for each Policy Target Group with Group Based Policy workflow).

Note: Controller hosts running DHCP agents that are connected to OpFlex networks have an EPG for each network.

- When using the allowed address pair feature with the Cisco ACI plug-in, be aware of the following differences from upstream implementation:
  - As OpenStack allows the same `allowed_address_pair` to be configured on multiple interfaces for HA, the OpFlex agent requires that the specific VNIC that currently owns a specific `allowed_address_pair` to assert that address ownership using Gratuitous ARP.
  - When using the promiscuous mode, the vSwitch stops enforcing the port security check. To get reverse traffic for a different IP or MAC address, you still need to use the `allowed-address-pair` feature. If you are running `tempest`, you will see `test_port_security_macspoofing_port` fail in scenario testing, as that test does not use the `allowed-address-pair` feature.
- Before performing an upgrade from 3.1(1) using OpenStack Director or attempting a Cisco APIC ID recovery procedure, all AIM processes on all controllers need to be shut down. To shut down all the AIM processes on all controllers, run the following command on the undercloud:

```
for IP in $(nova list | grep ACTIVE | sed 's/.*ctlplane=//' | sed 's/|//'); do
ssh -o UserKnownHostsFile=/dev/null -o StrictHostKeyChecking=no heat-admin@$IP \

"sudo systemctl stop aim-event-service-rpc; sudo systemctl stop aim-aid; sudo systemctl stop
aim-event-service-polling" ;

done
```

If upgrading, you do not need to explicitly restart the AIM processes as the upgrade will automatically restart them.

If attempting a Cisco APIC ID recovery, you must restart the AIM processes on all the controllers manually after ID Recovery is complete.

- Keystone configuration update

When the OpenStack plug-in is installed in the unified mode, the Cisco installer adds the required configuration for keystone integration with AIM. When not using unified mode, or when using your own installer, the configuration section must be provisioned manually:

```
[apic_aim_auth]
auth_plugin=v3password
```

```

auth_url=http://<IP Address of controller>:35357/v3
username=admin
password=<admin_password>
user_domain_name=default
project_domain_name=default
project_name=admin

```

- When using optimized DHCP, the DHCP lease times are set by the configuration variable `apic_optimized_dhcp_lease_time` under the `[ml2_apic_aim]` section.
  - This requires a restart of `neutron-server` to take effect
  - If this value is updated, existing instances will continue using the old lease time, provided their neutron port is not changed (e.g. rebooting the instance would trigger a port change, and cause it to get the updated lease time). New instances will however use the updated lease time.
- In upstream Neutron, the "advertise\_mtu" option has been removed.

Since the `aim_mapping` driver still uses this configuration, the original configuration which appeared in the default section should be moved to the `aim_mapping` section. For example:

```

[aim_mapping]
advertise_mtu = True

```

It is set to `True` by default in the code (if not explicitly specified in the config file).

- The Unified Plug-in allows coexistence of GBP and ML2 networking models on a single OpenStack Cloud installation. However, they must operate on different VRFs. We recommend using a single model per OpenStack Project.
- If a default VRF is implicitly created for a tenant in ML2, it is not implicitly deleted until the tenant is deleted (even if it not being used anymore).
- Unified model impact of the transaction Model Updates in Newton.

When GBP and ML2 co-exist, GBP implicitly created some neutron resources. In Newton, the neutron transaction model has been updated and has added various checks. Some of those checks spuriously see this nested transaction usage as an error and log and raise an exception. The exception is handled correctly by GBP and there is no functional impact but unfortunately the neutron code also logs some exceptions in neutron log file – leading to the impression that the action had failed.

While most such exceptions are logged at the `DEBUG` level, occasionally you might see some exceptions being logged at the `ERROR` level. If such an exception log is followed by a log message which indicates that the operation is being retried, the exception is being handled correctly. One such example is the following:

Delete of `policy-target` on a `policy-target-group` associated to a `network-service-policy` could raise this exception:

```

2017-03-18 12:52:34.421 27767 ERROR neutron.api.v2.resource [...] delete failed

2017-03-18 12:52:34.421 27767 ERROR neutron.api.v2.resource Traceback ...:

2017-03-18 12:52:34.421 27767 ERROR neutron.api.v2.resource File "/usr/lib/python2.7/site-
packages/neutron/api/v2/resource.py", line 84, ...

...

2017-03-18 12:52:34.421 27767 ERROR neutron.api.v2.resource raise ...

```

```
2017-03-18 12:52:34.421 27767 ERROR neutron.api.v2.resource ResourceClosedError: This
transaction is closed
```

Note: Cisco is working with the upstream community for further support on Error level logs.

- When a Layer 2 policy is deleted in GBP, some implicit artifacts related to it may not be deleted (resulting in unused BDs/subnets on Cisco APIC). If you hit that situation, the workaround is to create a new empty Layer 2 policy in the same context and delete it.
- If you use tempest to validate OpenStack, the following tests are expected to fail and can be ignored:

```
tempest.scenario.test_network_basic_ops.TestNetworkBasicOps.test_update_router_admin_state
```

- Neutron-server logs may show the following message when DEBUG level is enabled:

```
Timed out waiting for RPC response: Timeout while waiting on RPC response - topic:
"<unknown>", RPC method: "<unknown>" info: "<unknown>"
```

This message can be ignored.

- High Availability LBaaSv2 is not supported.
- OpenStack Newton is the last version to support non-unified plug-in. OpenStack Ocata and future releases will only be supported with the unified plug-in.
- For deployments running Cisco ACI version 4.1(2g) and using the Group Based Policy workflow and associated APIs, contract filters set **to an EtherType of ARP can result in the filter being incorrectly set as “Unspecified” on the leaf**. If an EtherType of ARP is required, then you must use a Cisco ACI release other than 4.1(2g).
- **Some deployments require installation of an “allow” entry in IP Tables for IGMP. This must be added to all hosts running an OpFlex agent and using VXLAN encapsulation to the leaf.** The rule must be added using the following command:

```
# iptables -A INPUT -p igmp -j ACCEPT
```

In order to make this change persistent across reboots, add the command either to `/etc/rc.d/rc.local` or to a cron job that runs after reboot.

- For deployments that use B-series servers, an additional service must be started on the hosts to ensure that connectivity is maintained with the leaf at all times. Complete the following steps:
  1. Install the Cisco APIC API package (python-apicapi for Debian packaging, apicapi for RPM packaging) for any servers running an OpFlex agent.
  2. Add the OpFlex uplink bond name to `/etc/environments` (that is, `opflex_bondif=bond1`).

This is needed if the interface is other than default (bond0).

3. Enable the apic-bond-watch service using the following command:

```
sudo systemctl enable apic-bond-watch
```

4. Start the apic-bond-watch service using the following command:

```
sudo systemctl start apic-bond-watch
```

For OpenStack Director installations using VXLAN encapsulation for VMM domains, two additional configuration items may be needed to handle large installations. The number of multicast groups should be

configured to match the maximum number of endpoint groups for the host, and the maximum auxiliary memory for sockets needs to be increased for IPC. These are configured using the `extra-config.yaml` file, with the following parameters:

```
ControllerParameters:

  ExtraSysctlSettings:
    net.ipv4.igmp_max_memberships:
      value: 4096
    net.core.optmem_max:
      value: 1310720
  ComputeParameters:
    ExtraSysctlSettings:
      net.ipv4.igmp_max_memberships:
        value: 1024
```

The IGMP max memberships value should be greater than or equal to the number of Neutron networks that the host has Neutron ports on. For example, if a compute host has 100 instances, and each instance is on a different Neutron network, then this number must be set to at least 100. Controller hosts running the `neutron-dhcp-agent` will need set this value to match the number of Neutron networks managed by that agent, which means this number will probably need to be higher on controller hosts than compute hosts.

- For installations not using OpenStack Director, the maximum allowed packet size for the database must be configured to support database transactions for tenants in AIM with large configurations. The default value installed by OpenStack director in `/etc/my.cnf.d/galera.cnf` is sufficient for most installations:

```
[mysqld]
...
max_allowed_packet = 16M

[mysqldump]
max_allowed_packet = 16M"
```

- After deploying Queens with Juju charms (18 or 19), sometimes a VM spawn fails. The failure is due to a `neutron-opflex-agent` failing to start on the host that the VM was scheduled to. The host can be determined using the `neutron agent-list` command: The `neutron-opflex-agent` is missing for the effected compute node.

Restart of `neutron-opflex-agent` on the affected node fixes the problem and can be used as a workaround after a fresh deployment.

- When you do an upgrade involving Red Hat OSP13, the installer **doesn't delete the** `/var/www/html/acirpo` directory. This causes problems when building new containers. When performing an upgrade using OSP13, be sure to manually delete this directory before installing the new RPM.

## Issues

This section contains lists of issues and known behaviors.

- [Resolved Issues](#)
- [Known Behaviors](#)

## Resolved Issues

The following table lists the resolved bugs for this release. Click the bug ID to access the Bug Search tool and see additional information about the bug.

Bug ID	Description
<a href="#">CSCvw35593</a>	An ICMP filter with parameters --icmp-type 3 --icmp-code 4 triggers an unsupported request to Cisco APIC.

## Related Documentation

The Cisco Application Policy Infrastructure Controller (APIC) documentation can be accessed from the following website:

<https://www.cisco.com/c/en/us/support/cloud-systems-management/application-policy-infrastructure-controller-apic/tsd-products-support-series-home.html>

The documentation includes installation, upgrade, configuration, programming, and troubleshooting guides, technical references, release notes, and knowledge base (KB) articles, as well as other documentation. KB articles provide information about a specific use case or a specific topic.

By using the "Choose a topic" and "Choose a document type" fields of the Cisco APIC documentation website, you can narrow down the displayed documentation list to make it easier to find the desired document.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2020 Cisco Systems, Inc. All rights reserved.