

Send documentation comments to mdsfeedback-doc@cisco.com



CHAPTER 1

A Commands

The commands in this chapter apply to the Cisco MDS 9000 Family of multilayer directors and fabric switches. All commands are shown here in alphabetical order regardless of command mode. See [“About the CLI Command Modes”](#) section on page 1-3 to determine the appropriate mode for each command.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa accounting logsize

To set the size of the local accounting log file, use the **aaa accounting logsize** command to set the size of the local accounting log file. To revert to the default logsize 250000 bytes, use the **no** form of the command.

aaa accounting logsize *integer*

no aaa accounting logsize

Syntax Description	logsize	Configures local accounting log file size (in bytes).
	<i>integer</i>	Sets the size limit of the local accounting log file in bytes from 0 to 250000.

Defaults	25,0000.
----------	----------

Command Modes	Configuration mode.
---------------	---------------------

Command History	Release	Modification
	1.0(2)	This command was introduced.
	2.0	This command was deprecated.

Usage Guidelines	None.
------------------	-------

Examples	The following example shows the log file size configured at 29000 bytes:
----------	--

```
switch# config terminal
switch(config)# aaa accounting logsize 29000
```

Related Commands	Command	Description
	show accounting logsize	Displays the configured log size.
	show accounting log	Displays the entire log file.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa accounting default

To configure the default accounting method, use the **aaa accounting default** command. To revert to the default local accounting, use the **no** form of the command.

```
aaa accounting default {group group-name [none] | none} | local [none] | none}
```

```
no aaa accounting default {group group-name [none] | none} | local [none] | none}
```

Syntax Description	group group-name	Specifies the group authentication method. The group name is a maximum of 127 characters.
	local	Specifies the local authentication method.
	none	(Optional) No authentication, everyone permitted.

Defaults Local accounting.

Command Modes Configuration mode.

Command History	Release	Modification
	1.3(1)	This command was introduced.

Usage Guidelines Specify the currently configured command preceded by a **no** in order to revert to the factory default.

Examples The following example enables accounting to be performed using remote TACACS+ servers which are members of the group called TacServer, followed by the local accounting method:

```
switch# config t
switch(config)# aaa accounting default group TacServer
```

The following example turns off accounting:

```
switch(config)# aaa accounting default none
```

The following example reverts to the local accounting (default):

```
switch(config)# no aaa accounting default group TacServer
```

Related Commands	Command	Description
	show aaa accounting	Displays the configured accounting methods.

Send documentation comments to mdsfeedback-doc@cisco.com

aaa authentication login chap enable

To enable CHAP authentication for login, use the **aaa authentication login chap enable** command. To disable CHAP authentication, use the **no** form of the command.

aaa authentication login chap enable

no aaa authentication login chap enable

Syntax Description This command has no arguments or keywords.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	NX-OS 5.0(1a)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to enable CHAP authentication for login:

```
switch(config)# aaa authentication login chap enable
switch(config)#
```

Related Commands	Command	Description
	show aaa authentication login CHAP	Displays CHAP authentication for login.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa authentication dhchap default

To configure DHCHAP authentication method, use the **aaa authentication dhchap default** command in configuration mode. To revert to factory defaults, use the **no** form of the command.

```
aaa authentication dhchap default {group group-name [none] | none} | local [none] | none}
```

```
no aaa authentication dhchap default {group group-name [none] | none} | local [none] | none}
```

Syntax Description

group <i>group-name</i>	Specifies the group name authentication method. The group name is a maximum of 127 characters.
local	Specifies local user name authentication (default).
none	(Optional) Specifies no authentication.

Defaults

Local user name authentication.

Command Modes

Configuration mode.

Command History

Release	Modification
1.3(1)	This command was introduced.

Usage Guidelines

The **local** option disables other authentication methods and configures local authentication to be used exclusively.

Specify the currently configured command preceded by a **no** in order to revert to the factory default.

Examples

The following example enables all DHCHAP authentication to be performed using remote TACACS+ servers which are members of the group called TacServers, followed by the local authentication:

```
switch# config terminal
switch(config)# aaa authentication dhchap default group TacServer
```

The following example reverts to the local authentication method (default):

```
switch(config)# no aaa authentication dhchap default group TacServer
```

Related Commands

Command	Description
show aaa authentication	Displays the configured authentication methods.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa authentication iscsi default

To configure the iSCSI authentication method, use the **aaa authentication iscsi default** command in configuration mode. To negate the command or revert to factory defaults, use the **no** form of this command.

```
aaa authentication iscsi default {group group-name [none] | none} | local [none] | none}
```

```
no aaa authentication iscsi default {group group-name [none] | none} | local [none] | none}
```

Syntax Description

group <i>group-name</i>	Specifies the group name. The group name is a maximum of 127 characters.
local	Specifies local user name authentication (default).
none	(Optional) Specifies no authentication.

Defaults

Local user name authentication.

Command Modes

Configuration mode.

Command History

Release	Modification
1.3(1)	This command was introduced.

Usage Guidelines

The **local** option disables other authentication methods and configures local authentication to be used exclusively.

Specify the currently configured command preceded by a **no** in order to revert to the factory default.

Examples

The following example enables all iSCSI authentication to be performed using remote TACACS+ servers which are members of the group called TacServers, followed by the local authentication:

```
switch# config terminal
switch(config)# aaa authentication iscsi default group TacServer
```

The following example reverts to the local authentication method (default):

```
switch(config)# no aaa authentication iscsi default group TacServer
```

Related Commands

Command	Description
show aaa authentication	Displays the configured authentication methods.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa authentication login

To configure the authentication method for a login, use the **aaa authentication login** command in configuration mode. To revert to local authentication, use the **no** form of the command.

```
aaa authentication login { default | fallback | error | local | group group-name [none] | none } |
local [none] | none } | console { fallback | error | local | group-name [none] | none } | local
[none] | none } | error-enable | mschap enable }
```

```
no aaa authentication login { default | fallback | error | local | group group-name [none] | none }
| local [none] | none } | console { fallback | error | local | group-name [none] | none } | local
[none] | none } | error-enable | mschap enable }
```

Syntax Description

default	Specifies the default method.
fallback	Specifies the fallback mechanism configuration error.
error	Specifies the authentication error. The maximum size is 32 characters.
local	Specifies the fallback to local authentication.
group group-name	Specifies the group name. The group name is a maximum of 127 characters.
none	(Optional) Sets no authentication; everyone is permitted.
local	Specifies the local authentication method.
console	Configures the console authentication login method.
error-enable	Enables login error message display.
mschap enable	Enables MS-CHAP authentication for login.

Defaults

Local user name authentication.

Command Modes

Configuration mode.

Command History

Release	Modification
NX-OS 5.0(1a)	Added fallback , error , and local keywords to the syntax description
1.3(1)	This command was introduced.
3.0(1)	Added the mschap option.

Usage Guidelines

Use the **console** option to override the console login method.

Specify the currently configured command preceded by a **no** to revert to the factory default.

Examples

The following example shows how to configure a default method:

```
switch# config t
switch(config)# aaa authentication login default fallback error local
switch(config)#
```

Send documentation comments to mdsfeedback-doc@cisco.com

The following example shows how to configure a console method:

```
switch# config t
switch(config)# aaa authentication login console fallback error local
switch(config)#
```

The following example enables all login authentication to be performed using remote TACACS+ servers, which are members of the group called TacServer, followed by the local login method:

```
switch# config t
switch(config)# aaa authentication login default group TacServer
```

The following example enables console authentication to use the group called TacServer, followed by the local login method:

```
switch(config)# aaa authentication login console group TacServer
```

The following example turns off password validation:

```
switch(config)# aaa authentication login default none
```

The following example reverts to the local authentication method (default):

```
switch(config)# no aaa authentication login default group TacServer
```

The following example enables MS-CHAP authentication for login:

```
switch(config)# aaa authentication login mschap enable
```

The following example reverts to the default authentication method for login, which is the Password Authentication Protocol (PAP):

```
switch(config)# no aaa authentication login mschap enable
```

Related Commands

Command	Description
show aaa authentication	Displays the configured authentication methods.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa authentication login ascii-authentication

To enable ASCII authentication, use the **aaa authentication login ascii-authentication** command. To disable this feature, use the **no** form of the command.

aaa authentication login ascii-authentication

no aaa authentication login ascii-authentication

Syntax Description This command has no arguments or keywords.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	NX-OS 4.1(3a)	aaa authentication login password-aging enable command changed to aaa authentication login ascii-authentication .

Usage Guidelines Password aging notification is initiated when the user authenticates to a Cisco MDS 9000 switch via a TACACS+ account. The user is notified when a password is about to expire or has expired. If the password has expired, user is prompted to change the password.



Note

As of Cisco MDS SAN-OS Release 3.2(1), only TACACS+ supports password aging notification. If you try to use RADIUS servers by enabling this feature, RADIUSs will generate a SYSLOG message and authentication will fall back to the local database. Cisco ACS TACACS+ server must have chpass enabled as well.

- Password change—You can change your password by entering a blank password.
- Password aging notification—Notifies password aging. Notification happens only if the AAA server is configured and MSCHAP and MSCHAPv2 is disabled.
- Password change after expiration—Initiates password change after the old password expires. Initiation happens from the AAA server.



Note

Password aging notification fails if you do not disable MSCHAP and MSCHAPv2 authentication.

Examples The following example shows how to enable ASCII authentication:

```
switch(config)# aaa authentication login ascii-authentication
switch#(config)#
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands	Command	Description
	show aaa authentication login ascii-authentication	Displays the configured ASCII authentication method.

Send documentation comments to mdsfeedback-doc@cisco.com

aaa authentication login mschapv2 enable

To enable MS-CHAPv2 authentication for login, use the **aaa authentication login mschapv2 enable** command. To disable MS-CHAPv2 authentication, use the **no** form of the command.

aaa authentication login mschapv2 enable

no aaa authentication login mschapv2 enable

Syntax Description This command has no arguments or keywords.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	NX-OS 4.2(1)	This command was introduced.

Usage Guidelines MS-CHAPv2 cannot be configured when MS-CHAP or ASCII authentication is configured and also when a TACACS group is configured for authentication.

Examples The following example shows how to enable MS-CHAPv2 authentication for login:

```
switch(config)# aaa authentication login mschapv2 enable
switch(config)#
```

Related Commands	Command	Description
	show aaa authentication login mschapv2	Displays MS-CHAPv2 authentication for login.

Send documentation comments to mdsfeedback-doc@cisco.com

auth-mechanism plain

To set the authentication mechanism as plain, use the **auth-mechanism plain** command in configuration mode. To disable this feature, use the **no** form of the command.

auth-mechanism plain

no auth-mechanism plain

Syntax Description This command has no arguments or keywords.

Defaults plain.

Command Modes Configurationmode.

Command History	Release	Modification
	NX-OS 5.0(1)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to set the authentication mechanism as plain:

```
switch(config-ldap)# auth-mechanism plain
switch(config-ldap)#
```

Related Commandss	Command	Description
	show ldap-server groups	Displays the configured LDAP server groups.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa authorization

To configure authorization for a function, use the **aaa authorization** command. To disable authorization for a function, use the **no** form of the command.

```
aaa authorization {commands | config-commands} {default} {[group group-name] | [local]}
                {[group group-name] | [none]}
```

```
no aaa authorization {commands | config-commands} {default} {[group group-name] | [local]}
                    {[group group-name] | [none]}
```

Syntax Description

commands	Specifies authorization for all exec-mode commands.
config-commands	Specifies authorization for all commands under config mode L2 and L3.
default	Specifies the default methods.
group	(Optional) Specifies the server group.
<i>group-name</i>	Specifies the group name.
local	(Optional) Specifies the local username authentication.
none	(Optional) Specifies no authorization.

Defaults

Authorization is disabled for all actions (equivalent to the method keyword **none**). If the **aaa authorization** command for a particular authorization type is entered without a named method list specified, the default method list is automatically applied to all interfaces or lines (where this authorization type applies) except those that have a named method list explicitly defined. A defined method list overrides the default method list if no default method list is defined, then no authorization takes place.

Command Modes

Configuration mode.

Command History

Release	Modification
NX-OS 4.2(1)	This command was introduced.

Usage Guidelines

None.

Examples

The following example shows how to configure authorization for a configuration command function:

```
switch(config)# aaa authorization config-commands default group tac1 local
switch(config)#
```

The following example shows how to configure authorization for a command function:

```
switch(config)# aaa authorization commands default group tac1 local none
switch(config)#
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands	Command	Description
	show aaa authorization all	Displays all authorization information.

Send documentation comments to mdsfeedback-doc@cisco.com

aaa authorization ssh-certificate

To configure SSH certificate authorization, use the **aaa authorization ssh-certificate** command. To disable this feature, use the **no** form of the command.

```
aaa authorization ssh-certificate default [group | local ]
```

Syntax Description	default	Specifies default SSH methods.
	group	Specifies server groups.
	local	Specifies local user name authentication.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	NX-OS 5.0(1)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to use local user name authentication:

```
switch(config)# aaa authorization ssh-certificate default local
switch(config)#
```

The following example shows how to specify server groups:

```
switch(config)# aaa authorization ssh-certificate default group ldap1
switch#
```

Related Commands	Command	Description
	show aaa	Displays all authorization information.
	authorization all	

Send documentation comments to mdsfeedback-doc@cisco.com

aaa authorization ssh-publickey

To configure SSH publickey authorization, use the **aaa authorization ssh-publickey** command. To disable this feature, use the **no** form of the command.

aaa authorization ssh-publickey default [group | local]

no aaa authorization ssh-publickey default [group | local]

Syntax Description	default	Specifies default SSH methods.
	group	Specifies server groups.
	local	Specifies local user name authentication.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	NX-OS 5.0(1)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to use local user name authentication:

```
switch(config)# aaa authorization ssh-publickey default local
switch(config)#
```

The following example shows how to specify server groups:

```
switch(config)# aaa authorization ssh-publickey default group ldap1
switch#
```

Command	Description
show aaa authorization all	Displays all authorization information.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

aaa group server

To configure one or more independent server groups, use the **aaa group server** command in configuration mode. To remove the server group, use the **no** form of this command to remove the server group.

```
aaa group server { radius | tacacs+ | ldap } group-name server server-name no server server-name
```

```
no aaa group server { radius | tacacs+ | ldap } group-name server server-name no server
server-name
```

Syntax Description		
	radius	Specifies the RADIUS server group.
	tacacs+	Specifies the TACACS+ server group.
	ldap	Specifies LDAP server group name.
	<i>group-name</i>	Identifies the specified group of servers with a user-defined name. The name is limited to 64 alphanumeric characters.
	server server-name	Specifies the server name to add or remove from the server group.

Defaults None.

Command Modes Sub configuration mode.

Command History	Release	Modification
	NX-OS 5.0(1)	Added ldap keyword to the syntax description.
	1.3(1)	This command was introduced.

Usage Guidelines You can configure these server groups at any time but they only take effect when you apply them to a AAA service using the **aaa authentication login** or the **aaa accounting** commands:
LDAP groups cannot be used for **AAA accounting** commands.

Examples The following example shows how to configure LDAP server group name:

```
switch(config)# aaa group server ldap a
switch(config-ldap)#
```

You can configure these server groups at any time but they only take effect when you apply them to a AAA service using the **aaa authentication** or the **aaa accounting** commands:

```
switch# config terminal
switch(config)# aaa group server tacacs+ TacacsServer1
switch(config-tacacs+)# server ServerA
switch(config-tacacs+)# exit
switch(config)# aaa group server radius RadiusServer19
switch(config-radius)# server ServerB
```

Send documentation comments to mdsfeedback-doc@cisco.com

```
switch(config-radius)# no server ServerZ
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands	Command	Description
	show aaa groups	Displays all configured server groups.
	show radius-server groups	Displays configured RADIUS server groups.
	show tacacs-server groups	Displays configured TACACS server groups.

Send documentation comments to mdsfeedback-doc@cisco.com

abort

To discard a Call Home configuration session in progress, use the **abort** command in Call Home configuration submode.

abort

Syntax Description This command has no other arguments or keywords.

Defaults None.

Command Modes Call Home configuration submode

Command History	Release	Modification
	2.0(1b)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to discard a Call Home configuration session in progress:

```
switch# config terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# callhome
switch(config-callhome)# abort
```

Related Commands	Command	Description
	callhome	Configures the Call Home function.
	callhome test	Sends a dummy test message to the configured destination(s).
	show callhome	Displays configured Call Home information.

Send documentation comments to mdsfeedback-doc@cisco.com

action cli

To configure a VSH command string to be executed when an Embedded Event Manager (EEM) applet is triggered, use the **action cli** command. To disable the VSH command string, use the **no** form of the command.

action *number* [*.number2*] **cli** *command1* [*command2...*] [**local**]

no action *number* [*.number2*] **cli** *command1* [*command2...*] [**local**]

Syntax Description

<i>number</i>	Number can be any number up to 16 digits. The range for number2 is from 0 to 9.
local	(Optional) Specifies the action that is to be executed in the same module on which the event occurs.

Defaults

None.

Command Modes

Embedded Event Manager mode.

Command History

Release	Modification
NX-OS 4.1(3)	This command was introduced.

Usage Guidelines

None.

Examples

The following example shows how to configure a CLI command:

```
switch# configure terminal
switch(config)# event manager applet cli-applet
switch(config-applet)# action 1.0 cli "show interface e 3/1"
switch(config-applet)#
```

Related Commands

Command	Description
event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

action counter

To specify setting or modifying a named counter when an Embedded Event Manager (EEM) applet is triggered, use the **action counter** command. To restore the default value to the counter, use the **no** form of the command.

```
action number [.number2] counter name counter value val op {dec | inc | nop | set}
```

```
no action number [.number2] counter name counter value val op {dec | inc | nop | set}
```

Syntax Description

number <i>.number2</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
name <i>name</i>	The counter name can be any case-sensitive, alphanumeric string up to 32 characters.
value <i>val</i>	Specifies the value of the counter. The <i>val</i> can be an integer from 0 to 2147483647 or a substituted parameter.
op { dec inc nop set }	The following operations can be performed: <ul style="list-style-type: none"> •dec—Decrement the counter by the specified value. •inc—Increment the counter by the specified value. •nop—Only print the specified value. •set—Set the counter to the specified value.

Defaults

None.

Command Modes

Embedded Event Manager mode.

Command History

Release	Modification
NX-OS 4.1(3)	This command was introduced.

Usage Guidelines

None.

Examples

The following example shows how to set or modify the counter when the EEM counter applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet counter-applet
switch(config-applet)# action 2.0 counter name mycounter value 20 op
switch(config-applet)#
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands

Command

Description

event manager applet

Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

action event-default

To execute the default action for the associated event, use the **action event-default** command. To disable the default action, use the **no** form of the command.

action *number* [*.number2*] **event-default**

no action *number* [*.number2*] **event-default**

Syntax Description	<i>number</i> . <i>number2</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
---------------------------	--------------------------------	--

Defaults	None.
-----------------	-------

Command Modes	Embedded Event Manager mode.
----------------------	------------------------------

Command History	Release	Modification
	NX-OS 4.2(1)	Added a note.
NX-OS 4.1(3)	This command was introduced.	

Usage Guidelines	None.
-------------------------	-------



Note

If you want to allow the triggered event to process any default actions, you must configure the **EEM** policy to allow the event default action statement. For example, if you match a **CLI** command in a match statement, you must add the event-default action statement to the **EEM** policy or **EEM** will not allow the **CLI** command to execute.

Examples	The following example shows how to specify that the default action of the event be performed when an EEM applet is triggered:
-----------------	---

```
switch# configure terminal
switch(config)# event manager applet default-applet
switch(config-applet)# action 1.0 event-default
switch(config-applet)#
```

Related Commands	Command	Description
	event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

Send documentation comments to mdsfeedback-doc@cisco.com

action exception log

To log an exception if the specific conditions are encountered when an Embedded Event Manager (EEM) applet is triggered, use the **action exception log** command.

```
action number [.number2] exception log module module syserr error devid id errtype type
errcode code phylayer layer ports list harderror error [desc string]
```

Syntax Description		
number <i>.number2</i>		Number can be any number up to 16 digits. The range for number2 is from 0 to 9.
module <i>module</i>		Records an exception for the specified module. Enter a module word.
syserr <i>error</i>		Records an exception for the specified system error. Enter an error word.
devid <i>id</i>		Records an exception for the specified device ID. Enter an ID word.
errtype <i>type</i>		Records an exception for the specified error type. Enter a type word.
errcode <i>code</i>		Records an exception for the specified error code. Enter a code word.
phylayer <i>layer</i>		Records an exception for the specified physical layer. Enter a layer word.
ports <i>list</i>		Records an exception for the specified ports. Enter a list word.
harderror <i>error</i>		The reset reason is a quoted alphanumeric string upto 80 characters.
desc <i>string</i>		(Optional) Describes the exception logging condition.

Defaults None.

Command Modes Embedded Event Manager mode.

Command History	Release	Modification
	NX-OS 4.1(3)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to log an EEM applet exception:

```
switch# configure terminal
switch(config)# event manager applet exception-applet
switch(config-applet)# action 1.42 exceptionlog module 1 syserr 13 devid 1 errtype fatal
errcode 13 phylayer 2 ports 1-42 harderror 13 desc "fatal exception logging"
switch(config-applet)#
```

Related Commands	Command	Description
	event manager applet	Displays an applet with the Embedded Event Manager.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

action forceshut

To configure a forced shutdown of a module, a crossbar, ASCII or the entire switch when an Embedded Event Manager (EEM) applet is triggered, use the **action forceshut** command.

```
action number [.number2] forceshut [module slot | xbar xbar-number] reset-reason string
```

Syntax Description		
<i>number</i> <i>.number2</i>		Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
forceshut		Forces a module, crossbar or entire system to shut down.
module <i>slot</i>		(Optional) Specifies slot range. The range is from 1 to 10, or a substituted parameter.
xbar <i>xbar-number</i>		(Optional) Specifies xbar-number. The range is from 1 to 4 or a substituted parameter.
reset-reason <i>string</i>		Specifies reset reason. The reason is a alphanumeric string up to 80 characters.

Defaults None.

Command Modes Embedded Event Manager mode.

Command History	Release	Modification
	NX-OS 4.1(3)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to log an EEM applet exception:

```
switch# configure terminal
switch(config)# event manager applet exception-applet
switch(config-applet)# action 1.0 forceshut module 2 reset-reason "flapping links"
switch(config-applet)#
```

Related Commands	Command	Description
	event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

action overbudgetshut

To configure the shutdown of a module or the entire switch due to an overbudget power condition when an Embedded Event Manager (EEM) applet is triggered, use the **action overbudgetshut** command.

```
action number [.number2] overbudgetshut [module slot [- slot]]
```

Syntax Description

<i>number</i> <i>.number2</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
module <i>slot</i> - <i>slot</i>	(Optional) Specifies the slot range. For 6slot : The range is from 1 to 6. For 9slot : The range is from 1 to 9. For 13slot : The range is from 1 to 13.

Defaults

(The default action is to powerdown just the linecards starting from slot_1 till the switch recovers from overbudget condition. In other words, skip both the supervisors (active and standby) and skip all spine/xbars, powerdown lcs starting from slot 1 onwards, till the Available power recovers from overbudget condition).

Command Modes

Embedded Event Manager.

Command History

Release	Modification
NX-OS 4.1(3)	This command was introduced.

Usage Guidelines

None.

Examples

The following example shows how to configure a power overbudget shutdown of module 3-5 when an EEM applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet overbudget-applet
switch(config-applet)# action 1.0 overbudgetshut module 3-5
switch(config-applet)#
```

Related Commands

Command	Description
event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

Send documentation comments to mdsfeedback-doc@cisco.com

action policy-default

To enable the default action(s) of the policy being overridden, use the **action policy-default** command.

action *number* [*.number2*] **policy-default**

Syntax Description	<i>number</i> <i>.number2</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
---------------------------	-------------------------------	--

Defaults	None.
-----------------	-------

Command Modes	Embedded Event Manager mode.
----------------------	------------------------------

Command History	Release	Modification
	NX-OS 4.1(3)	This command was introduced.

Usage Guidelines	None.
-------------------------	-------

Examples The following example shows how to enable the default action of a policy being overridden when an EEM applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet default-applet
switch(config-applet)# action 1.0 policy-default
switch(config-applet)#
```

Related Commands	Command	Description
		event manager applet

Send documentation comments to mdsfeedback-doc@cisco.com

action reload

To configure the reloading or to reload the switch software when an Embedded Event Manager (EEM) applet is triggered, use the **action reload** command. To remove the switch software of reload configuration, use the **no** form of this command.

```
action number [.number2] reload [module slot [- slot]]
```

Syntax Description	
<i>number .number2</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
module <i>slot -slot</i>	(Optional) Specifies the slot range. The range is from 1 to 10, or a substituted parameter.

Defaults None.

Command Modes Embedded Event Manager mode.

Command History	Release	Modification
	NX-OS 4.1(3)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to enable the default action of a policy being overridden when an EEM applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet default-applet
switch(config-applet)# action 1.0 policy-default
switch(config-applet)#
```

Related Commands	Command	Description
	event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

action snmp-trap

To specify the generation of a Simple Network Management Protocol (SNMP) trap when an Embedded Event Manager (EEM) applet is triggered, use the **action snmp-trap** command. To disable the SNMP trap, use the **no** form of this command.

```
action number[.number2] snmp-trap {[intdata1 integer [intdata2 integer] [strdata string]]}
```

```
no action number[.number2] snmp-trap {[intdata1 integer [intdata2 integer] [strdata string]]}
```

Syntax Description

<i>number</i> . <i>number2</i>	Number can be any number up to 16 digits. The range for number2 is from 0 to 9.
intdata1 <i>integer</i>	(Optional) Specifies an integer to be sent in the SNMP trap message to the SNMP agent.
intdata2 <i>integer</i>	(Optional) Specifies a second integer to be sent in the SNMP trap message to the SNMP agent.
strdata <i>string</i>	(Optional) Specifies a string to be sent in the SNMP trap message to the SNMP agent. If the string contains embedded blanks, enclose it in double quotation marks.

Defaults

None.

Command Modes

Embedded Event Manager mode.

Command History

Release	Modification
NX-OS 4.1(3)	This command was introduced.

Usage Guidelines

None.

Examples

The following example shows how to specify an SNMP trap to generate when an EEM applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet snmp-applet
switch(config-applet)# action 1.0 snmp-trap strdata "temperature problem"
switch(config-applet)#
```

Related Commands

Command	Description
event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

action syslog

To configure a syslog message to generate when an Embedded Event Manager (EEM) applet is triggered, use the **action syslog** command. To disable the syslog message, use the **no** form of this command.

action *number*[.*number2*] **syslog** [**priority** *prio-val*] **msg** *error-message*

no action *number*[.*number2*] **syslog** [**priority** *prio-val*] **msg** *error-message*

Syntax Description	
<i>number</i>	Number can be any number up to 16 digits. The range for <i>number2</i> is from 0 to 9.
priority <i>prio-val</i>	<p>(Optional) Specifies the priority level of the syslog messages. If this keyword is not selected, all syslog messages are set at the informational priority level. If this keyword is selected, the priority level argument must be defined. There are three ways of defining the priority level:</p> <ul style="list-style-type: none"> Define the priority level using one of these methods: <ul style="list-style-type: none"> – 0—System is unusable. – 1—Immediate action is needed. – 2—Critical conditions. – 3—Error conditions. – 4—Warning conditions. – 5—Normal but significant conditions. – 6—Informational messages. This is the default. – 7—Debugging messages. Enter the priority by selecting one of the priority keywords: <ul style="list-style-type: none"> – emergencies—System is unusable. – alerts—Immediate action is needed. – critical—Critical conditions. – errors—Error conditions. – warnings—Warning conditions. – notifications—Normal but significant conditions. – informational—Informational messages. This is the default. – debugging—Debugging messages.
msg <i>error message</i>	Specifies the error message. The message can be any quoted alphanumeric string up to 80 characters.

Defaults None.

Command Modes Embedded Event Manager mode.

Send documentation comments to mdsfeedback-doc@cisco.com

Command History	Release	Modification
	NX-OS 4.1(3)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to configure a syslog message to save when an EEM applet is triggered:

```
switch# configure terminal
switch(config)# event manager applet syslog-applet
switch(config-applet)# action 1.0 syslog priority notifications msg "cpu high"
switch(config-applet)#
```

Related Commands	Command	Description
	event manager applet	Displays an applet with the Embedded Event Manager.

Send documentation comments to mdsfeedback-doc@cisco.com

active equals saved

To automatically write any changes to the block, prohibit or port address name to the IPL file, use the **active equals saved** command. To disable the configuration or to revert to factory defaults, use the **no** form of the command.

active equals saved

no active equals saved

Syntax Description

This command has no other arguments or keywords.

Defaults

Disabled.

Enabled. (when a FICON VSAN is configured).

Command Modes

FICON configuration submode.

Command History

Release	Modification
1.3(1)	This command was introduced.

Usage Guidelines

Enabling **active equals saved** ensures that you do not have to perform the **copy running-config startup-config** command to save the FICON configuration as well as the running configuration. If your switch or fabric consists of multiple FICON-enabled VSANs, and one of these VSANs has **active equals saved** enabled, changes made to the non-FICON configuration causes all FICON-enabled configurations to be saved to the IPL file.

The following example enables the automatic save feature for a VSAN:

```
switch(config)# ficon vsan 2
switch(config-ficon)# active equals saved
```

The following example disables the automatic save feature for this VSAN:

```
switch(config-ficon)# no active equals saved
```

Related Commands

Command	Description
copy running-config startup-config	Saves the running configuration to the startup configuration.
ficon vsan	Enables FICON on the specified VSAN.
show ficon	Displays configured FICON details.

Send documentation comments to mdsfeedback-doc@cisco.com

alert-group

To customize a Call Home alert group with user-defined **show** commands, use the **alert-group** command in Call Home configuration submode. To remove the customization, use the **no** form of the command.

alert-group *event-type* **user-def-cmd** *command*

no alert-group *event-type* **user-def-cmd** *command*

Syntax Description

<i>event-type</i>	Specifies event types by the following alert groups.
Avanti	Displays Avanti events.
Environmental	Displays power, fan, and temperature related events.
Inventory	Displays inventory status events.
License	Displays events related to licensing.
RMON	Displays events related to Remote Monitoring (RMON).
Supervisor-Hardware	Displays supervisor related events.
Syslog-group-port	Displays events relate to syslog messages filed by the the port manager.
System	Displays software related events.
test	Displays user-generated test events.
user-def-cmd <i>command</i>	Configures a CLI command for an alert-group. The maximum size is 512.

Defaults

None.

Command Modes

Call Home configuration submode.

Command History

Release	Modification
3.0(1)	This command was introduced.

Usage Guidelines

The **user-def-cmd** argument allows you to define a command whose outputs should be attached to the Call Home message being sent. Only **show** commands can be specified and they must be associated with an alert group. Five commands can be specified per alert group. Invalid commands are rejected.



Note

Make sure the destination profiles for the non-Cisco-TAC alert group, with a predefined **show** command, and the Cisco-TAC alert group are not the same.

Examples

The following example configures a user-defined command, called **show license usage**, for an alert group license:

```
switch(config-callhome)# alert-group license user-def-cmd "show license usage"
```

Send documentation comments to mdsfeedback-doc@cisco.com

The following example removes a user-defined command, called **show license usage**, for an alert group license:

```
switch(config-callhome)# no alert-group license user-def-cmd "show license usage"
```

Related Commands

Command	Description
callhome	Configures the Call Home function.
callhome test	Sends a dummy test message to the configured destination(s).
show callhome	Displays configured Call Home information.

Send documentation comments to mdsfeedback-doc@cisco.com

arp

To enable the Address Resolution Protocol (ARP) for the switch, use the **arp** command. To disable ARP for the switch, use the **no** form of the command.

arp *hostname*

no arp *hostname*

Syntax Description	<i>hostname</i>	Specifies the name of the host. Maximum length is 20 characters.
--------------------	-----------------	--

Defaults	Enabled.
----------	----------

Command Modes	Configuration mode.
---------------	---------------------

Command History	Release	Modification
	1.0(2)	This command was introduced.

Usage Guidelines	None.
------------------	-------

Examples	The following example disables the Address Resolution Protocol configured for the host with the IP address 10.1.1.1:
----------	--

```
switch(config)# no arp 10.1.1.1
switch(config)#
```

Related Commands	Command	Description
	clear arp	Deletes a specific entry or all entries from the ARP table.
	show arp	Displays the ARP table.

Send documentation comments to mdsfeedback-doc@cisco.com

attach

To connect to a specific module, use the **attach** command in EXEC mode.

attach module *slot-number*

Syntax Description	module <i>slot-number</i>	Specifies the slot number of the module.
--------------------	---------------------------	--

Defaults	None.
----------	-------

Command Modes	EXEC mode.
---------------	------------

Command History	Release	Modification
	1.0(2)	This command was introduced.

Usage Guidelines	<p>You can use the attach module command to view the standby supervisor module information, but you cannot configure the standby supervisor module using this command.</p> <p>You can also use the attach module command on the switching module portion of the Cisco MDS 9216 supervisor module, which resides in slot 1 of this two-slot switch.</p> <p>To disconnect, use the exit command at the <code>module-number#</code> prompt, or type \$. to forcibly abort the attach session.</p>
------------------	--

Examples	<p>The following example connects to the module in slot 2. Note that after you connect to the image on the module using the attach module command, the prompt changes to <code>module-number#</code>:</p>
----------	--

```
switch# attach module 1
Attaching to module 1 ...
To exit type 'exit', to abort type '$.'
module-1# exit
switch#
```

Related Commands	Command	Description
	exit	Disconnects from the module.
	show module	Displays the status of a module.

Send documentation comments to mdsfeedback-doc@cisco.com

attachpriv

To connect to a specific ILC linecard as a privilege, use the **attachpriv** command in EXEC mode.

attachpriv module *slot-number*

Syntax Description	module <i>slot-number</i> Specifies the slot number of the module.						
Defaults	None.						
Command Modes	EXEC mode.						
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>3.1(3)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	3.1(3)	This command was introduced.		
Release	Modification						
3.1(3)	This command was introduced.						
Usage Guidelines	None.						
Examples	<p>The following example shows how to connect to a specific ILC linecard as a privilege:</p> <pre>switch# attachpriv module 1 Attaching to module 1 ... To exit type 'exit', to abort type '\$.' module-1# exit</pre>						
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>exit</td> <td>Disconnects from the module.</td> </tr> <tr> <td>show module</td> <td>Displays the status of a module.</td> </tr> </tbody> </table>	Command	Description	exit	Disconnects from the module.	show module	Displays the status of a module.
Command	Description						
exit	Disconnects from the module.						
show module	Displays the status of a module.						

Send documentation comments to mdsfeedback-doc@cisco.com

attributes (DMM job configuration submode)

To set the attributes of a data migration job, use the **attributes** command in DMM job configuration submode. To remove the attributes of a data migration job, use the **no** form of the command.

```
attributes job_type {1 | 2} job_mode {1 | 2} job_rate {1 | 2 | 3 | 4} job_method {1|2}
```

```
no attributes job_type {1 | 2} job_mode {1 | 2} job_rate {1 | 2 | 3 | 4} job_method {1|2}
```

Syntax Description		
job_type 1 2	Specifies the job type. Specify 1 for a server type job and 2 for a storage type job.	
job_mode 1 2	Specifies the job mode. Specify 1 for an online job and 2 for an offline job.	
job_rate 1 2 3 4	Specifies the job rate. Specify 1 for the default rate, 2 for a slow rate, 3 for a medium rate, and 4 for a fast rate.	
job_method 1 2	Specifies the job method. Specify 1 for Method 1 and 2 for Method 2.	

Defaults None.

Command Modes DMM job configuration submode.

Command History	Release	Modification
	3.3(1a)	This command was introduced.

Usage Guidelines None.

Examples The following example sets the job type to storage, the job mode to online, and the job rate to fast:

```
switch# config t
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# dmm module 3 job 1 create
Started New DMM Job Configuration.
Do not exit sub-mode until configuration is complete and committed
switch(config-dmm-job)# attributes job_type 2 job_mode 1 job_rate 4 job_method 1
switch(config-dmm-job)#
```

Related Commands	Command	Description
	show dmm job	Displays job information.
	show dmm srvr-vt-login	Displays server VT login information.

Send documentation comments to mdsfeedback-doc@cisco.com

attribute failover auto

To configure an automatic fallback failover for a virtual device, use the **attribute failover auto** command. To revert to the default, use the **no** form of the command.

attribute failover auto [fallback]

no attribute failover auto [fallback]

Syntax Description	fallback (Optional) Enables a switchback with an automatic failover.				
Defaults	Disabled.				
Command Modes	Virtual device submode.				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>NX-OS 4.1(1b)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	NX-OS 4.1(1b)	This command was introduced.
Release	Modification				
NX-OS 4.1(1b)	This command was introduced.				
Usage Guidelines	None.				

Examples

The following example shows how to configure an automatic failover for a specific virtual device:

```
switch# config t
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# sdv virtual-device name vdev1 vsan 1
switch(config-sdv-virt-dev)# attribute failover auto
switch(config-sdv-virt-dev)#
```

The following example shows how to configure an attribute of a virtual device:

```
switch# config t
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# sdv virtual-device name vdev1 vsan 1
switch(config-sdv-virt-dev)# attribute failover auto fallback
switch(config-sdv-virt-dev)#
```

Send documentation comments to mdsfeedback-doc@cisco.com

attribute qos

To configure a QoS attribute, use the **attribute qos** command in Inter-VSAN Routing (IVR) zone configuration submode. To disable this feature, use the **no** form of this command.

attribute qos {high | low | medium}

no attribute qos {high | low | medium}

Syntax Description	high	Configures frames matching zone to get high priority.
	low	Configures frames matching zone to get low priority (Default).
	medium	Configures frames matching zone to get medium priority.

Defaults Disabled.

Command Modes IVR zone configuration submode.

Command History	Release	Modification
	2.1(1a)	This command was introduced.

Usage Guidelines None.

Examples The following example shows how to configure an IVR zone QoS attribute to low priority:

```
switch# config terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# ivr zone name IvrZone
switch(config-ivr-zone)# attribute qos priority low
```

Related Commands	Command	Description
	show ivr zone	Displays IVR zone configuration.

Send documentation comments to mdsfeedback-doc@cisco.com

authentication

To change the authentication behaviour, use the **authentication** command. To disable this feature, use the **no** form of the command.

```
authentication { compare [password-attribute password-attribute] | bind-first
  [append-with-baseDN string] }
```

```
no authentication { compare [password-attribute password-attribute] | bind-first
  [append-with-baseDN string] }
```

Syntax Description

compare	Specifies the compare option to be used for authentication.
password-attribute <i>password-attribute</i>	Overrides the default password attribute. The maximum length is 128 characters.
bind-first	Specifies client to use bind and search instead of search and bind.
append-with-baseDN <i>string</i>	Overrides the default string appended with baseDN.

Defaults

userPassword.
append-with-baseDN default value is (cn=\$userid).

Command Modes

Configuration submode.

Command History

Release	Modification
NX-OS 5.0(1)	This command was introduced.

Usage Guidelines

The password-attribute option provides a way to change the attribute type of password.

Examples

The following example shows how to change the default attribute:

```
switch(config-ldap) # authentication compare password-attribute 1
switch(config-ldap) #
```

Related Commandss

Command	Description
show aaa	Displays the configured authentication methods.
authentication	

Send documentation comments to mdsfeedback-doc@cisco.com

authentication (IKE policy configuration submode)

To configure the authentication method for an IKE protocol policy, use the **authentication** command in IKE policy configuration submode. To revert to the default authentication method, use the **no** form of the command.

```
authentication {pre-share | rsa-sig}
```

```
no authentication {pre-share | rsa-sig}
```

Syntax Description		
	pre-share	Configures the preshared key as the authentication method.
	rsa-sig	Configures RSA signatures as the authentication method.

Defaults	
	Preshared key.

Command Modes	
	IKE policy configuration submode.

Command History	Release	Modification
	3.0(1)	This command was introduced.

Usage Guidelines	
	To use this command, enable the IKE protocol using the crypto ike enable command. In addition, you must configure the identity authentication mode using the fully qualified domain name (FQDN) before you can use RSA signatures for authentication. Use the identity hostname command for this purpose.

Examples	
	The following example shows how to configure the authentication method using the preshared key:

```
switch# config terminal
switch(config)# crypto ike domain ipsec
switch(config-ike-ipsec)# policy 1
switch(config-ike-ipsec-policy)# authentication pre-share
```

The following example shows how to configure the authentication method using the RSA signatures:

```
switch(config-ike-ipsec-policy)# authentication rsa-sig
```

The following example shows how to revert to the default authentication method (preshared key):

```
switch(config-ike-ipsec-policy)# no authentication rsa-sig
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands	Command	Description
	crypto ike domain ipsec	Enters IKE configuration mode.
	crypto ike enable	Enables the IKE protocol.
	identity hostname	Configures the identity for the IKE protocol.
	show crypto ike domain ipsec	Displays IKE information for the IPsec domain.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

autonomous-fabric-id (IVR topology database configuration)

To configure an autonomous fabric ID (AFID) into the Inter-VSAN Routing (IVR) topology database, use the **autonomous-fabric-id** command. To remove the fabric ID, use the **no** form of the command.

autonomous-fabric-id *fabric-id* **switch-wwn** *swwn* **vsan-ranges** *vsan-id*

no autonomous-fabric-id *fabric-id* **switch-wwn** *swwn* **vsan-ranges** *vsan-id*

Syntax Description		
<i>fabric-id</i>		Specifies the fabric ID for the IVR topology. Note For Cisco MDS SAN-OS images prior to release 2.1(1a), the <i>fabric-id</i> value is limited to 1. For Releases 2.1(1a) and later images, the <i>fabric-id</i> range is 1 to 64.
switch-wwn <i>swwn</i>		Configures the switch WWN in dotted hex format.
vsan-ranges <i>vsan-id</i>		Configures up to five ranges of VSANs to be added to the database. The range is 1 to 4093.

Defaults None.

Command Modes IVR topology database configuration submode.

Command History	Release	Modification
	1.3(1)	This command was introduced.
	2.1(1a)	Modified range for <i>fabric-id</i> .

Usage Guidelines The following rules apply to configuring AFIDs to VSANs:

- The default AFID of a VSAN is 1.
- Each VSAN belongs to one and only one AFID.
- A switch can be a member of multiple AFIDs.
- AFIDs at a switch must not share any VSAN identifier (for example, a VSAN at a switch can belong to only one AFID).
- A VSAN identifier can be reused in different AFIDs, without merging the VSANs, as long as those AFIDs do not share a switch.

You can have up to 64 VSANs (or 128 VSANs for Cisco MDS SAN-OS Release 2.1(1a) or later) in an IVR topology. Specify the IVR topology using the following information:

- The switch WWNs of the IVR-enabled switches.
- A minimum of two VSANs to which the IVR-enabled switch belongs.

Send documentation comments to mdsfeedback-doc@cisco.com

- The autonomous fabric ID (AFID), which distinguishes two VSANs that are logically and physically separate, but have the same VSAN number. Cisco MDS SAN-OS Release 1.3(1) and NX-OS Release 4.1(1b) supports only one default AFID (AFID 1) and does not support non-unique VSAN IDs in the network. As of Cisco MDS SAN-OS Release 2.1(1a), you can specify up to 64 AFIDs.

**Note**

Two VSANs with the same VSAN number but different fabric IDs are counted as two VSANs out of the 128 total VSANs allowed in the fabric.

Examples

The following command enters the configuration mode, enables the IVR feature, enters the VSAN topology database, and configures the pWWN-VSAN association for VSANs 2 and 2000:

```
switch# config terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# ivr enable
switch(config)# ivr vsan-topology database
switch(config-ivr-topology-db)# autonomous-fabric-id 1 switch 20:00:00:00:30:00:3c:5e
vsan-ranges 2,2000
```

Related Commands

Command	Description
ivr enable	Enables the Inter-VSAN Routing (IVR) feature.
ivr vsan-topology database	Configures a VSAN topology database.
show autonomous-fabric-id database	Displays the contents of the AFID database.
show ivr	Displays IVR feature information.

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

autonomous-fabric-id (IVR service group configuration)

To configure an autonomous fabric ID (AFID) into an IVR service group, use the **autonomous-fabric-id** command in IVR service group configuration submode. To remove the autonomous fabric ID, use the **no** form of the command.

autonomous-fabric-id *afid vsan-ranges vsan-id*

no autonomous-fabric-id *afid vsan-ranges vsan-id*

Syntax Description		
	<i>afid</i>	Specifies the AFID to the local VSAN.
	vsan-ranges <i>vsan-id</i>	Configures up to five ranges of VSANs to be added to the service group. The range is 1 to 4093.

Defaults None.

Command Modes IVR service group configuration submode.

Command History	Release	Modification
	2.1	This command was introduced.

Usage Guidelines Before configuring an IVR service group, you must enable the following:

- IVR using the **ivr enable** command
- IVR distribution using the **ivr distribute** command
- Automatic IVR topology discovery using the **ivr vsan-topology auto** command

To change to IVR service group configuration submode, use the **ivr service-group activate** command.

Examples The following command enters the IVR service group configuration submode and configures AFID 10 to be in IVR service group serviceGroup1:

```
switch# config terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# ivr enable
switch(config)# ivr distribute
switch(config)# ivr vsan-topology auto
switch(config)# ivr service-group name serviceGroup1
switch(config-ivr-sg)# autonomous-fabric-id 10 vsan 1-4
```

Send documentation comments to mdsfeedback-doc@cisco.com

Related Commands	Command	Description
	ivr enable	Enables the Inter-VSAN Routing (IVR) feature.
	ivr service-group name	Configures an IVR service group and changes to IVR service group configuration submode.
	show autonomous-fabric-id database	Displays the contents of the AFID database.
	show ivr	Displays IVR feature information.

Send documentation comments to mdsfeedback-doc@cisco.com

autonomous-fabric-id database

To configure an autonomous fabric ID (AFID) database, use the **autonomous-fabric-id database** command. To remove the fabric AFID database, use the **no** form of the command.

autonomous-fabric-id database

no autonomous-fabric-id database

Syntax Description This command has no arguments or keywords.

Defaults None.

Command Modes Configuration mode.

Command History	Release	Modification
	2.1(1a)	This command was introduced.

Usage Guidelines You must configure the IVR VSAN topology to auto mode, using the **ivr vsan-topology auto** command, before you can use the **autonomous-fabric-id database** command to modify the database. The **autonomous-fabric-id database** command also enters AFID database configuration submode.



Note

In user-configured VSAN topology mode, the AFIDs are specified in the IVR VSAN topology configuration itself and a separate AFID configuration is not needed.

Examples The following example shows how to create an AFID database and enters AFID database configuration submode:

```
switch# config terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# autonomous-fabric-id database
switch(config-afid-db)#
```

Related Commands	Command	Description
	ivr vsan-topology auto	Configures a VSAN topology for Inter-VSAN Routing (IVR) to auto configuration mode.
	switch-wwn	Configures a switch WWN in the autonomous fabric ID (AFID) database
	show autonomous-fabric-id database	Displays the contents of the AFID database.
	show ivr	Displays IVR feature information.

Send documentation comments to mdsfeedback-doc@cisco.com

auto-volgrp

To configure the automatic volume grouping, use the **auto-volgrp** command. To disable this feature, use the **no** form of the command.

auto-volgrp

no auto-volgrp

Syntax Description This command has no arguments or keywords.

Defaults Disabled.

Command Modes Cisco SME cluster configuration submode.

Command History	Release	Modification
	3.2(2)	This command was introduced.

Usage Guidelines If Cisco SME recognizes that the tape's barcode does not belong to an existing volume group, then a new volume group is created when automatic volume grouping is enabled.

Examples The following example enables automatic volume grouping:

```
switch# config t
switch(config)# sme cluster c1
switch(config-sme-cl)# auto-volgrp
switch(config-sme-cl)#
```

The following example disables automatic volume grouping:

```
switch# config t
switch(config)# sme cluster c1
switch(config-sme-cl)# auto-volgrp
switch(config-sme-cl)#
```

Related Commands	Command	Description
	show sme cluster	Displays Cisco SME cluster information.