



S Commands

This chapter describes the Cisco Nexus 1000V commands that begin with the letter S.

segment distribution mac

To configure MAC distribution mode globally and per bridge domain.

segment distribution mac

Syntax Description	<i>distribution</i> Configure MAC distribution mode. <i>mac</i>
---------------------------	--

Defaults	None
-----------------	------

Command Modes	Global configuration (config) Bridge Domain configuration (config-bd)
----------------------	--

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.2(1)SV2(2.1)	This command was introduced.

Usage Guidelines	This command specifies the mac distribution mode globally and per bridge-domain
-------------------------	---

Examples This example shows how to configure the mac distribution mode globally:

```
n1000v(config)# segment mode unicast-only
n1000v(config)# segment distribution mac
```

This example shows how to configure the mac distribution mode per bridge-domain:

```
n1000v(config)# bridge-domain tenant-red
n1000v(config-bd)# segment mode unicast-only
n1000v(config-bd)# segment distribution mac
```

Related Commands	Command	Description
	segment mode unicast-only	Configures the segment mode unicast-only globally and per bridge-domain.

segment id

To specify a segment ID to a VXLAN, use the **segment id** command. To remove the segment ID, use the **no** form of this command.

segment id *segment-id*

no segment id

Syntax Description	<i>segment-id</i>	The segment id of the VXLAN. The valid values are 4096 to 16777215. (Values 1 - 4095 are reserved for VLANs)
---------------------------	-------------------	--

Defaults	None
-----------------	------

Command Modes	Bridge Domain configuration (config-bd)
----------------------	---

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.2(1)SV1(5.1)	This command was introduced.

Usage Guidelines	Only one Bridge Domain can use a particular segment id value.
-------------------------	---

Examples This example shows how to specify a segment ID to a VXLAN:

```
n1000v# configure terminal
n1000v(config)# bridge-domain tenant-red
n1000v(config-bd)# segment id 20480
n1000v(config-bd)#
```

Related Commands	Command	Description
	show bridge-domain	Displays bridge domain information.

segment mode unicast-only

To configure unicast mode globally and per bridge domain with no MAC distribution enabled.

segment mode unicast-only

Syntax Description	<i>unicast-only</i> Specifies the segment mode in unicast only.
---------------------------	---

Defaults	None
-----------------	------

Command Modes	Global configuration (config) Bridge Domain configuration (config-bd)
----------------------	--

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.2(1)SV2(2.1)	This command was introduced.

Usage Guidelines	This command configures the segment mode as unicast-only mode globally and per bridge-domain.
-------------------------	---

Examples	This example shows how to configure the segment mode unicast-only globally:
-----------------	---

```
n1000v(config)# segment mode unicast-only
```

This example shows how to configure the segment mode unicast-only per bridge-domain:

```
n1000v(config)# bridge-domain tenant-red  
n1000v(config-bd)# segment mode unicast-only
```

Related Commands	Command	Description
	segment distribution mac	Configure MAC distribution mode globally and per bridge-domain.
	segment-id	The segment id of the VXLAN.

segment transport-mode native

To set the transport-mode to native (VDP) at the global configuration level on the Cisco Nexus 1000V, use the **segment transport-mode native** command.

segment transport- mode native

Syntax Description	<i>native</i>	Configures the segment transport mode to native (VDP) to enable network-based overlays.
---------------------------	---------------	---

Defaults	None
-----------------	------

Command Modes	Global configuration (config)
----------------------	-------------------------------

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.2(1)SV2(2.2)	This command was introduced.

Usage Guidelines The default segment transport-mode is set to VXLAN. Use this command to set it to native (VDP) at the global configuration level, to employ network based overlays.

Examples This example shows the output where the segment transport-mode is set to native globally.:

```
n1000V(config)# segment transport-mode native
n1000V(config)# no segment transport-mode native
```

This example shows the running configuration for the segment transport-mode set to native globally.

```
switch # show run
!Command: show running-config
version 4.2(1)SV2(2.2)
svs switch edition essential
feature telnet
feature segmentation
no segment mode unicast-only
segment transport-mode native
feature evb
feature fabric forwarding
...
```

Related Commands

Command	Description
segment transport-mode {native vxlan}	Specifies the segmentation transport-mode for a bridge-domain configuration.
segment-id	The segment id of the VXLAN.

segment transport-mode

To configure the transport-mode to native (VDP) or VXLAN for a bridge-domain on the Cisco Nexus 1000V, use the **segment transport-mode native** command.

segment transport-mode {native | VXLAN}

Syntax Description	native	Sets the transport-mode to VDP to employ the network based overlays.
	VXLAN	Set the transport-mode to VXLAN

Defaults The segment transport mode (VXLAN or native) set globally by executing the **segment transport-mode native** command.

Command Modes bridge-domain configuration (bd-config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.2(1)SV2(2.2)	This command was introduced.

Usage Guidelines None.

Examples This example shows running configuration for a bridge-domain with the segment transport-mode set to native(VDP) :

```
n1000v # show run bridge-domain
version 4.2(1)SV2(2.2)
feature segmentation
no segment mode unicast-only
bridge-domain seg22222
segment id 22222
group 239.1.1.1
segment transport-mode native
fabric forwarding mode proxy-gateway
```

Related Commands	Command	Description
	segment transport-mode native	Specifies the segmentation transport-mode to native globally.
	show running-config bridge-domain	Displays the running configuration for bridge-domain..

send

To send a message to an open session, use the **send** command.

```
send {message | session device message}
```

Syntax Description		
	<i>message</i>	Message.
	session	Specifies a specific session.
	<i>device</i>	Device type.

Defaults	
	None

Command Modes	
	Any

Supported User Roles	
	network-admin network-operator

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples	
	This example shows how to send a message to an open session:

```
n1000v# send session sessionOne testing
n1000v#
```

Related Commands	Command	Description
	show banner	Displays a banner.

server

To configure the RADIUS server as a member of the RADIUS server group, use the **server** command. To remove a server, use the **no** form of this command.

```
server {ipv4-address | server-name}
```

```
no server {ipv4-address | server-name}
```

Syntax Description

<i>ipv4-address</i>	IPv4 address of the RADIUS server.
<i>server-name</i>	Name that identifies the RADIUS server.

Defaults

None

Command Modes

Radius configuration (config-radius)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Examples

This example shows how to configure the RADIUS server as a member of the RADIUS server group:

```
n1000v# config t
n1000v(config)# aaa group server radius RadServer
n1000v(config-radius)# server 10.10.1.1
n1000v(config-radius)#
```

This example shows how to remove the server configuration:

```
n1000v# config t
n1000v(config)# aaa group server radius RadServer
n1000v(config)# no server 10.10.1.1
```

Related Commands

Command	Description
aaa group server radius	Creates a RADIUS server group and enters the RADIUS server group configuration submode for that group.
deadtime	Configures the monitoring dead time.
use-vrf	Specifies the Virtual Routing and Forwarding (VRF) to use to contact the servers in the server group.
show radius-server groups	Displays the RADIUS server group configuration.

service ha-cluster clusterNo switchover

Triggers a switchover from an Active service module to a Standby service module paired in HA.

service ha-cluster *clusterNo* **switchover**

Syntax Description	<i>clusterNo</i> HA cluster number (1-8).
---------------------------	---

Defaults	None
-----------------	------

Command Modes	Global configuration (config)
----------------------	-------------------------------

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.2(1)SV2(2.1)	This command was introduced.

Usage Guidelines	Use this command to initiate a switchover between service modules in HA.
-------------------------	--

Examples	This example shows how to configure a switchover of an active service module on a HA cluster:
-----------------	---

```
n1000v# config t
n1000v(config)# service ha-cluster 1 switchover
```



Note

Command is applicable for service modules configured in HA.

Related Commands	Command	Description
	service instance	Defines a place holder for mappings.
	service mod	Configure the service module in high availabilty (HA) pair.

Command	Description
service <mod> update port-profile type ethernet name <Service module uplink port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.
service <mod> update port-profile type vethernet name <Service module VTEP port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway VTEP.

service instance

Defines a place holder for mappings. The range is from 1 to 4096.

service instance (1 - 4096)

no service instance (1 - 4096)

Syntax Description	<i>1- 4096</i> ID of the service instance.				
Defaults	None.				
Command Modes	Port-profile configuration (config-port-prof)				
SupportedUserRoles	network-admin				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.2(1)SV2(2.1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.2(1)SV2(2.1)	This command was introduced.
Release	Modification				
4.2(1)SV2(2.1)	This command was introduced.				
Usage Guidelines	Service instance command is a place holder for mappings.				

Examples

This example shows how to configure a service instance:

```
n1000v# config t
n1000v(config)# port-profile type vethernet csr-access
n1000v(config-port-prof)# switchport mode access
n1000v(config-port-prof)# switchport access bridge-domain bd-701
n1000v(config-port-prof)# service instance 10
n1000v(config-port-prof-srv)# encapsulation dot1q 600 bridge-domain bd-600
n1000v(config-port-prof-srv)# encapsulation dot1q 601 bridge-domain bd-601
n1000v(config-port-prof-srv)# encapsulation dot1q 602 bridge-domain bd-602
n1000v(config-port-prof-srv)# no shutdown
n1000v(config-port-prof-srv)# state enabled
n1000v(config-port-prof)# end
```

This example shows how to remove the service instance:

```
n1000v# config t
n1000v(config)# port-profile type vethernet csr-access
n1000v(config-port-prof)# switchport mode access
n1000v(config-port-prof)# switchport access bridge-domain bd-701
n1000v(config-port-prof)# no service instance 10
```

**Note**

Port profiles containing the service instance keyword cannot be used for a non-VXLAN Gateway module.

Related Commands

Command	Description
service instance (1-4096)	Defines a place holder for mappings. The range is from 1 to 4096.
no service instance (1-4096)	Defines a place holder for remove mappings. The range is from 1 to 4096.

service mod

Configure the service module in high availability (HA) pair.

[no] **service mod role standalone**

[no] **service modNo1 role primary ha-cluster clusterNo**

[no] **service modNo2 role secondary ha-cluster clusterNo**

[no] **service mod**

Syntax Description

<i>(mod)</i>	gateway module number
<i>(modNo1)</i>	
<i>(modNo2)</i>	
<i>primary</i>	Configures service module in HA with the specified cluster-id and role as Primary.
<i>secondary</i>	Configures service module in HA with the specified cluster-id and role as Secondary.
<i>clusterNo</i>	Configures the service module in HA belonging to a unique Cluster-id.
<i>standalone</i>	Configure the service module as a Standalone mode.

Defaults

None.

Command Modes

Global configuration (config)

SupportedUserRoles

network-admin

Command History

Release	Modification
4.2(1)SV2(2.1)	This command was introduced.

Usage Guidelines

Roles can be pre-configured to module numbers in the VSM. When a VXLAN gateway is attached to the VSM on that module, it inherits the Role and Status of that VSM.

Examples

This example shows how to configure service mod role standalone:

```
n1000v# config t
n1000v(config)# service 4 role standalone
```

This example shows how to configure service modNo1 role primary ha-cluster clusterNo:

```
n1000v# config t
n1000v(config)# service 4 role primary ha-cluster 1
```

This example shows how to configure service modNo2 role secondary ha-cluster clusterNo:

```
n1000v# config t
n1000v(config)# service 5 role secondary ha-cluster 1
```

This example shows how to remove the HA related configuration:

```
n1000v# config t
n1000v(config)# no service mod
```

Related Commands	Command	Description
	service instance	Defines a place holder for mappings.
	service ha-cluster clusterNo switchover	Triggers a switchover from an Active service module to a Standby service module paired in HA.
	service <mod> update port-profile type ethernet name <Service module uplink port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.
	service <mod> update port-profile type vethernet name <Service module VTEP port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway VTEP.

■ `service <mod> update port-profile type ethernet name <Service module uplink port-profile>`

service <mod> update port-profile type ethernet name <Service module uplink port-profile>

To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.

`service <mod> update port-profile type ethernet name <Service module uplink port-profile>`

Syntax Description	<code><mod></code> service module number	
	Service module uplink port-profile	Uplink port-profile of the service module.
Defaults	None.	
Command Modes	Global configuration (config)	
Supported User Roles	network-admin	
Command History	Release	Modification
	4.2(1)SV2(2.1)	This command was introduced.
Usage Guidelines	Port-profile name of the service module/VXLAN gateway uplink are changed by using this command.	
Examples	<p>This example shows how to change the currently assigned port-profile name of the service module/VXLAN gateway uplink.</p> <pre>n1000v(config)# service 37 update port-profile type ethernet name Uplink-All-VXGW</pre>	
Related Commands	Command	Description
	<code>service <mod> update port-profile type vethernet name <Service module VTEP port-profile></code>	To change the currently assigned port-profile name of the service module/VXLAN gateway VTEP.

service <mod> update port-profile type vethernet name <Service module VTEP port-profile>

To change the currently assigned port-profile name of the service module/VXLAN gateway VTEP.

service <mod> update port-profile type vethernet name <Service module VTEP port-profile>

Syntax Description	<mod> service module number				
	Service module VTEP port-profile of the service module. VTEP port-profile				
Defaults	None.				
Command Modes	Global configuration (config)				
SupportedUserRoles	network-admin				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.2(1)SV2(2.1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.2(1)SV2(2.1)	This command was introduced.
Release	Modification				
4.2(1)SV2(2.1)	This command was introduced.				
Usage Guidelines	Port-profile name of the service module/VXLAN gateway VTEP are changed by using this command.				
Examples	<p>This example shows how to change the currently assigned port-profile name of the service module/VXLAN gateway VTEP.</p> <pre>n1000v (config)# service 37 update port-profile type ethernet name vmknuc_vtep14_vlan1546</pre>				
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>service <mod> update port-profile type ethernet name <Service module uplink port-profile></td> <td>To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.</td> </tr> </tbody> </table>	Command	Description	service <mod> update port-profile type ethernet name <Service module uplink port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.
Command	Description				
service <mod> update port-profile type ethernet name <Service module uplink port-profile>	To change the currently assigned port-profile name of the service module/VXLAN gateway uplink.				

service-policy

To configure a service policy for an interface, use the **service-policy** command. To remove the service policy configuration, use the **no** form of this command.

```
service-policy { input name [no-stats] | output name [no-stats] | type qos { input name [no-stats] | output name [no-stats] } }
```

```
no service-policy { input name [no-stats] | output name [no-stats] | type qos { input name [no-stats] | output name [no-stats] } }
```

Syntax Description	input	Specifies an input service policy.
	<i>name</i>	Policy name. The range of valid values is 1 to 40.
	no-stats	(Optional) Specifies no statistics.
	output	Specifies an output service policy.
	type qos	Specifies a QoS service policy.

Defaults None

Command Modes Interface configuration (config-if)
Port profile configuration (config-port-prof)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4) SV1(1)	This command was introduced.

Examples This example shows how to add an input QoS service policy called sp10 to vEthernet interface 10 with no statistics:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 10
n1000v(config-if)# service-policy type qos input sp10 no-stats
n1000v(config-if)#
```

This example shows how to remove the input QoS service policy called sp10 with no statistics from vEthernet interface 10:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 10
n1000v(config-if)# no service-policy type qos input sp10 no-stats
n1000v(config-if)#
```

Related Commands	Command	Description
	show running-config interface	Displays interface configuration information.
	interface vethernet	Creates a vEthernet interface configuration.
	port-profile	Creates a port profile configuration.

service-port

To configure an inside or outside interface in a virtual service domain (VSD) port profile, use the **service-port** command. To remove the configuration, use the **no** form of this command.

```
service-port {inside | outside} [default-action {drop | forward}]
```

```
no service-port
```

Syntax Description

inside	Inside Network
outside	Outside Network
default-action	(Optional) Action to be taken if service port is down. <ul style="list-style-type: none"> • drop: drops packets • forward: forwards packets (the default)

Defaults

forward default-action

Command Modes

Port profile configuration (config-port-prof)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(2)	This command was introduced.

Usage Guidelines

If a port profile without a service port is configured on an SVM, it will flood the network with packets. When configuring a port profile on an SVM, first bring the SVM down. This prevents a port-profile that is mistakenly configured without a service port from flooding the network with packets. The SVM can be returned to service after the configuration is complete and verified.

Examples

This example shows how to configure an inside interface on a VSD port profile that drops packets if the service port is down:

```
n1000v# config t
n1000v(config)# port-profile svm_vsd1_in
n1000v(config-port-prof)# service-port inside default-action drop
n1000v(config-port-prof)#
```

This example shows how to remove a service port configuration:

```
n1000v# config t
n1000v(config)# port-profile svm_vsd1_in
n1000v(config-port-prof)# no service-port
```

```
n1000v(config-port-prof)#
```

Related Commands

Command	Description
show virtual-service-domain	Displays a list of the VSDs currently configured in the VSM, including VSD names and port profiles.

session-limit

To limit the number of VSH sessions, use the **session-limit** command. To remove the limit, use the **no** form of this command.

session-limit *number*

no session-limit *number*

Syntax Description	<i>number</i>	Number of VSH sessions. The range of valid values is 1 to 64
--------------------	---------------	--

Defaults	No limit is set.
----------	------------------

Command Modes	Line configuration (config-line)
---------------	----------------------------------

SupportedUserRoles	network-admin
--------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to limit the number of VSH sessions:

```
n1000v# configure terminal
n1000v(config)# line vty
n1000v(config-line)# session-limit 10
n1000v(config-line)#
```

This example shows how to remove the limit:

```
n1000v# configure terminal
n1000v(config)# line vty
n1000v(config-line)# no session-limit 10
n1000v(config-line)#
```

set

To set QoS class attributes, use the **set** command. To remove class attributes, use the **no** form of this command.

```
set {{ cos cos-val } | { dscp [tunnel] { dscp-val | dscp-enum } } | { precedence [tunnel] { prec-val |
prec-enum } } | { discard-class dis-class-val } | { qos-group qos-grp-val } | {{ cos cos } | { dscp
dscp } | { precedence precedence } | { discard-class discard-class } } table table-map-name } |
{ cos1 {{ dscp table cos-dscp-map } | { precedence table cos-precedence-map } |
{ discard-class table cos-discard-class-map } } } | { dscp1 {{ cos table dscp-cos-map } | { prec3
table dscp-precedence-map } | { dis-class3 table dscp-discard-class-map } } } | { prec1 {{ cos3
table precedence-cos-map } | { dscp3 table precedence-dscp-map } | { dis-class3 table
precedence-discard-class-map } } } | { dis-class1 {{ cos3 table discard-class-cos-map } |
{ dscp3 table discard-class-dscp-map } | { prec3 table discard-class-precedence-map } } } }
```

```
no set {{ cos cos-val } | { dscp [tunnel] { dscp-val | dscp-enum } } | { precedence [tunnel] { prec-val |
prec-enum } } | { discard-class dis-class-val } | { qos-group qos-grp-val } | {{ cos cos } | { dscp
dscp } | { precedence precedence } | { discard-class discard-class } } table table-map-name } |
{ cos1 {{ dscp table cos-dscp-map } | { precedence table cos-precedence-map } |
{ discard-class table cos-discard-class-map } } } | { dscp1 {{ cos table dscp-cos-map } | { prec3
table dscp-precedence-map } | { dis-class3 table dscp-discard-class-map } } } | { prec1 {{ cos3
table precedence-cos-map } | { dscp3 table precedence-dscp-map } | { dis-class3 table
precedence-discard-class-map } } } | { dis-class1 {{ cos3 table discard-class-cos-map } |
{ dscp3 table discard-class-dscp-map } | { prec3 table discard-class-precedence-map } } } }
```

Syntax Description

cos	Specifies IEEE 802.1Q CoS (Class of Service).
<i>cos-value</i>	CoS value. The range of valid values is 0 to 7.
dscp	Specifies DSCP (Differentiated Services Code Point) in IPv4 and IPv6 packets.
tunnel	(Optional) Specifies DSCP in tunnel encapsulation.
<i>dscp-value</i>	DSCP value.
<i>dscp-enum</i>	
precedence	Precedence in IP(v4) and IPv6 packets.
<i>prec-val</i>	IP Precedence value.
<i>prec-enum</i>	.
discard-class	Discard class + Discard class value.
<i>dis-class-val</i>	
qos-group	Qos-group + Qos-group value.
<i>qos-grp-val</i>	
table	Table defining mapping from input to output + Table-map name.
<i>table-map-name</i>	
cos1	IEEE 802.1Q class of service.
cos-dscp-map	Cos to DSCP Mutation map.
cos-precedence-map	Cos to Precedence Mutation map.
cos-discard-class-map	Cos to Discard Class Mutation map.

dscp1	DSCP in IP(v4) and IPv6 packets.
dscp-cos-map	DSCP to COS Mutation map.
prec3	Precedence in IP(v4) and IPv6 packets.
dscp-precedence-map	DSCP to Precedence Mutation map.
dis-class3	Discard class.
dscp-discard-class-map	DSCP to Discard Class Mutation map.
prec1	Precedence in IP(v4) and IPv6 packets.
cos3	IEEE 802.1Q class of service.
precedence-cos-map	Precedence to COS Mutation map.
dscp3	DSCP in IP(v4) and IPv6 packets.
precedence-dscp-map	Precedence to DSCP Mutation map.
precedence-discard-class-map	Precedence to Discard Class Mutation map.
dis-class1	Discard class.
discard-class-cos-map	Discard Class to COS Mutation map.
discard-class-dscp-map	Discard Class to DSCP Mutation map.
discard-class-precedence-map	Discard Class to Precedence Mutation map.

Defaults

None

Command Modes

Policy map class configuration (config-pmap-c-qos)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Examples

This example shows how to set class attributes:

```
n1000v# configure terminal
n1000v(config)# policy-map pml
n1000v(config-pmap-qos)# class class-default
n1000v(config-pmap-c-qos)# set qos-group 1
```



```
n1000v(config-pmap-c-qos)#
```

This example shows how to remove class attributes:

```
n1000v# configure terminal
n1000v(config)# policy-map pm1
n1000v(config-pmap-qos)# class class-default
n1000v(config-pmap-c-qos)# no set qos-group 1
n1000v(config-pmap-c-qos)#
```

Related Commands

Command	Description
show policy-map	Displays policy maps.

setup

To use the Basic System Configuration Dialog for creating or modifying a configuration file, use the **setup** command.

setup

Syntax Description This command has no arguments or keywords, but the Basic System Configuration Dialog prompts you for complete setup information (see the example below).

Defaults None

Command Modes Any

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines The Basic System Configuration Dialog assumes the factory defaults. Keep this in mind when using it to modify an existing configuration.

All changes made to your configuration are summarized for you at the completion of the setup sequence with an option to save the changes or not.

You can exit the setup sequence at any point by pressing Ctrl-C.

Examples This example shows how to use the setup command to create or modify a basic system configuration:

```
n1000v# setup
```

```
Enter the domain id<1-4095>: 400
```

```
Enter HA role[standalone/primary/secondary]: standalone
```

```
[#####] 100%
```

```
---- Basic System Configuration Dialog ----
```

```
This setup utility will guide you through the basic configuration of
the system. Setup configures only enough connectivity for management
of the system.
```

```
*Note: setup is mainly used for configuring the system initially,
```

when no configuration is present. So setup always assumes system defaults and not the current system configuration values.

Press Enter at anytime to skip a dialog. Use ctrl-c at anytime to skip the remaining dialogs.

Would you like to enter the basic configuration dialog (yes/no): y

Create another login account (yes/no) [n]: n

Configure read-only SNMP community string (yes/no) [n]: n

Configure read-write SNMP community string (yes/no) [n]: n

Enter the switch name : n1000v

Continue with Out-of-band (mgmt0) management configuration? (yes/no) [y]:

Mgmt0 IPv4 address :

Configure the default gateway? (yes/no) [y]: n

Configure advanced IP options? (yes/no) [n]:

Enable the telnet service? (yes/no) [y]:

Enable the ssh service? (yes/no) [n]:

Configure the ntp server? (yes/no) [n]:

Configure vem feature level? (yes/no) [n]:

Configure svcs domain parameters? (yes/no) [y]:

Enter SVS Control mode (L2 / L3) : L2

Invalid SVS Control Mode

Enter SVS Control mode (L2 / L3) : L2

Enter control vlan <1-3967, 4048-4093> : 400

Enter packet vlan <1-3967, 4048-4093> : 405

The following configuration will be applied:

```
switchname n1000v
feature telnet
no feature ssh
svs-domain
  svcs mode L2
  control vlan 400
  packet vlan 405
  domain id 400
vlan 400
vlan 405
```

Would you like to edit the configuration? (yes/no) [n]:

Use this configuration and save it? (yes/no) [y]: n

n1000v#

Related Commands

Command	Description
show running-config	Displays the running configuration.

shutdown (VLAN)

To shutdown switching on a VLAN, use the **shutdown** command. To turn on switching, use the **no** form of this command.

shutdown

no shutdown

Syntax Description This command has no arguments or keywords.

Defaults no shutdown

Command Modes VLAN configuration (config-vlan)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4) SV1(1)	This command was introduced.

Usage Guidelines You cannot shut down the default VLAN, VLAN1, or VLANs 1006 to 4094.

Examples This example shows how to shutdown switching on VLAN 10:

```
n1000v# configure terminal
n1000v(config)# vlan 10
n1000v(config-vlan)# shutdown
n1000v(config-vlan)#
```

This example shows how to turn on switching on VLAN 10:

```
n1000v# configure terminal
n1000v(config)# vlan 10
n1000v(config-vlan)# no shutdown
n1000v(config-vlan)#
```

Related Commands	Command	Description
	show vlan	Displays VLAN information.
	vlan	Creates a VLAN configuration.

shutdown (interface)

To disable an interface, use the **shutdown** command. To enable an interface, use the **no** form of this command.

shutdown [**force**]

no shutdown [**force**]

Syntax	Description
force	(Optional) Administratively enables or disables an interface.

Defaults	No shutdown
----------	-------------

Command Modes	Interface configuration (config-if)
---------------	-------------------------------------

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.0(4) SV1(1)	This command was introduced.

Usage Guidelines	This command shuts down the interface. No traffic passes and the interface displays as administratively down.
------------------	---

Examples	This example shows how to administratively disable Ethernet interface 3/1:
----------	--

```
n1000v# config t
n1000v(config)# interface ethernet 3/1
n1000v(config-if)# shutdown
n1000v(config-if)#
```

This example shows how to administratively enable Ethernet interface 3/1:

```
n1000v# config t
n1000v(config)# interface ethernet 3/1
n1000v(config-if)# no shutdown
n1000v(config-if)#
```

Related Commands	Command	Description
	show interface	Displays the interface configuration.
	interface ethernet	Creates an Ethernet interface configuration.
	interface vethernet	Creates a vEthernet interface configuration.

shutdown (port profile)

To disable all ports in a port profile, use the **shutdown** command. To enable ports in a port profile, use the **no** form of this command.

shutdown [**force**]

no shutdown [**force**]

Syntax	Description
force	(Optional) Administratively enables or disables all ports in the profile.

Defaults	all ports administratively disabled
----------	-------------------------------------

Command Modes	Port profile configuration (config-port-prof)
---------------	---

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.0(4) SV1(1)	This command was introduced.

Usage Guidelines	This command administratively disables all ports in the profile. No traffic passes and the ports display as administratively down.
------------------	--

Examples	This example shows how to administratively enable all ports in the TrunkProf port profile:
----------	--

```
n1000v# config t
n1000v(config)# port-profile TrunkProf
n1000v(config-port-prof)# no shutdown
n1000v(config-port-prof)#
```

This example shows how to administratively disable all ports in the TrunkProf port profile:

```
n1000v# config t
n1000v(config)# port-profile TrunkProf
n1000v(config-port-prof)# shutdown
n1000v(config-port-prof)#
```

Related Commands	Command	Description
	show port-profile name	Displays the named port profile configuration.
	port-profile	Creates a port profile configuration.

sleep

To set a sleep time, use the **sleep** command.

sleep *time*

Syntax Description	<i>time</i>	Sleep time, in seconds. The range of valid values is 0 to 2147483647.
---------------------------	-------------	---

Defaults	Sleep time is not set.
-----------------	------------------------

Command Modes	Any
----------------------	-----

SupportedUserRoles	network-admin network-operator
---------------------------	-----------------------------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines	When you set <i>time</i> to 0, sleep is disabled.
-------------------------	---

Examples	This example shows how to set a sleep time:
-----------------	---

```
n1000v# sleep 100
n1000v#
```

This example shows how to disable sleep:

```
n1000v# sleep 0
n1000v#
```

snmp-server aaa-user cache-timeout

To configure how long the AAA-synchronized user configuration stays in the local cache, use the **snmp-server aaa-user cache-timeout** command. To revert back to the default value of 3600 seconds, use the **no** form of this command.

snmp-server user aaa-user cache-timeout *seconds*

no snmp-server user aaa-user cache-timeout *seconds*

Syntax Description	<i>seconds</i>	Length of the time for the user configuration to remain in the local cache. The range is 1 to 86400 seconds.
---------------------------	----------------	--

Defaults	The default timeout is 3600 seconds.
-----------------	--------------------------------------

Command Modes	Global configuration (config)
----------------------	-------------------------------

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to configure the AAA-synchronized user configuration to stay in the local cache for 1200 seconds:

```
n1000v# config t
n1000v(config)# snmp-server aaa-user cache-timeout 1200
```

This example shows how to revert back to the default value of 3600 seconds:

```
n1000v# config t
n1000v(config)# no snmp-server aaa-user cache-timeout 1200
```

Related Commands	Command	Description
	show snmp	Displays SNMP information.
	snmp-server contact	Configures sysContact, (the SNMP contact).
	snmp-server protocol enable	Enables the SNMP protocol.
	snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
	snmp-server host	Configures a host receiver for SNMP traps or informs.
	snmp-server location	Configures sysLocation (the SNMP location).

Command	Description
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server community

To create an SNMP community string, use the **snmp-server community** command. To remove the community, use the **no** form of this command.

```
snmp-server community string [group group-name] [ro | rw]
```

```
no snmp-server community string [group group-name] [ro | rw]
```

Syntax Description

<i>string</i>	SNMP community string, which identifies the community.
group	(Optional) Specifies a group to which this community belongs.
<i>group-name</i>	Name that identifies an existing group.
ro	(Optional) Specifies read-only access for this community.
rw	(Optional) Specifies read-write access for this community.

Defaults

None

Command Modes

Global configuration (config)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4) SV1(1)	This command was introduced.

Usage Guidelines

You can create SNMP communities for SNMPv1 or SNMPv2c.

Examples

This example shows how to configure read-only access for the SNMP community called public:

```
n1000v# config t
n1000v(config)# snmp-server community public ro
```

This example shows how to remove the SNMP community called public:

```
n1000v# config t
n1000v(config)# no snmp-server community public
```

Related Commands

Command	Description
show snmp	Displays SNMP information.
snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.

Command	Description
snmp-server contact	Configures sysContact, (the SNMP contact).
snmp-server protocol enable	Enables SNMP.
snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
snmp-server host	Configures a host receiver for SNMP traps or informs.
snmp-server location	Configures sysLocation (the SNMP location).
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.
snmp-server community	Creates an SNMP community string and assigns access privileges for the community.

snmp-server contact

To configure the sysContact, which is the SNMP contact name, use the **snmp-server contact** command.

To remove or modify the sysContact, use the **no** form of this command.

```
snmp-server contact [name]
```

```
no snmp-server contact [name]
```

Syntax Description	<i>name</i> (Optional) SNMP contact name (sysContact), which can contain a maximum of 32 characters.								
Defaults	None								
Command Modes	Global configuration (config)								
Supported User Roles	network-admin								
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0(4)SV1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.0(4)SV1(1)	This command was introduced.				
Release	Modification								
4.0(4)SV1(1)	This command was introduced.								
Usage Guidelines	You can create SNMP communities for SNMPv1 or SNMPv2c.								
Examples	<p>This example shows how to configure the sysContact to be Admin:</p> <pre>n1000v# config t n1000v(config)# snmp-server contact Admin</pre> <p>This example shows how to remove the sysContact:</p> <pre>n1000v# config t n1000v(config)# no snmp-server contact</pre>								
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>show snmp</td> <td>Displays SNMP information.</td> </tr> <tr> <td>snmp-server aaa-user cache-timeout</td> <td>Configures how long the AAA-synchronized user configuration stays in the local cache.</td> </tr> <tr> <td>snmp-server protocol enable</td> <td>Enables SNMP.</td> </tr> </tbody> </table>	Command	Description	show snmp	Displays SNMP information.	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.	snmp-server protocol enable	Enables SNMP.
Command	Description								
show snmp	Displays SNMP information.								
snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.								
snmp-server protocol enable	Enables SNMP.								

Command	Description
snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
snmp-server host	Configures a host receiver for SNMP traps or informs.
snmp-server location	Configures sysLocation (the SNMP location).
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server globalEnforcePriv

To enforce SNMP message encryption for all users, use the **snmp-server globalEnforcePriv** command.

snmp-server globalEnforcePriv

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to enforce SNMP message encryption for all users:

```
n1000v# config t
n1000v(config)# snmp-server mib globalEnforcePriv
```

Related Commands	Command	Description
	show snmp	Displays SNMP information.
	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.
	snmp-server contact	Configures sysContact, (the SNMP contact).
	snmp-server protocol enable	Enables SNMP.
	snmp-server host	Configures a host receiver for SNMP traps or informs.
	snmp-server location	Configures sysLocation (the SNMP location).
	snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
	snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server host

To configure a host receiver for SNMPv1 or SNMPv2c traps, use the **snmp-server host** command. To remove the host, use the **no** form of this command.

```
snmp-server host ip-address {traps | informs} {version {1 | 2c | 3}} [auth | noauth | priv]
community [udp_port number]
```

```
no snmp-server host ip-address {traps | informs} {version {1 | 2c | 3}} [auth | noauth | priv]
community [udp_port number]
```

Syntax Description		
<i>ip-address</i>		IPv4 address, IPv6 address, or DNS name of the SNMP notification host.
informs		Specifies Inform messages to this host.
traps		Specifies Traps messages to this host.
version		Specifies the SNMP version to use for notification messages.
1		Specifies SNMPv1 as the version.
2c		Specifies SNMPv2c as the version.
3		Specifies SNMPv3 as the version.
auth	(Optional)	Specifies (for SNMPv3) the authNoPriv Security Level.
noauth	(Optional)	Specifies (for SNMPv3) the noAuthNoPriv Security Level.
priv	(Optional)	Specifies (for SNMPv3) the authPriv Security Level.
<i>community</i>		SNMPv1/v2c community string or SNMPv3 user name. The community string can be any alphanumeric string up to 255 characters.
udp-port	(Optional)	Specifies an existing UDP port.
<i>number</i>		Number that identifies the UDP port of the notification host. The range is 0 to 65535.

Defaults None

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(1)	This command was introduced.

Examples This example shows how to configure the host receiver, 192.0.2.1, for SNMPv1 traps:

```
n1000v# config t
n1000v(config)# snmp-server host 192.0.2.1 traps version 1 public
```

This example shows how to remove the configuration:

```
n1000v# config t
n1000v(config)# no snmp-server host 192.0.2.1 traps version 1 public
```

Related Commands

Command	Description
show snmp	Displays SNMP information.
snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.
snmp-server contact	Configures sysContact, (the SNMP contact).
snmp-server protocol enable	Enables SNMP.
snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
snmp-server location	Configures sysLocation (the SNMP location).
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server location

To configure the sysLocation, which is the SNMP location name, use the **snmp-server location** command.

To remove the sysLocation, use the **no** form of this command.

```
snmp-server location [name]
```

```
no snmp-server location [name]
```

Syntax Description	<i>name</i> (Optional) SNMP location name (sysLocation), which can contain a maximum of 32 characters.												
Defaults	None												
Command Modes	Global configuration (config)												
SupportedUserRoles	network-admin												
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0(4)SV1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.0(4)SV1(1)	This command was introduced.								
Release	Modification												
4.0(4)SV1(1)	This command was introduced.												
Examples	<p>This example shows how to configure the sysLocation to be Lab-7:</p> <pre>n1000v# config t n1000v(config)# snmp-server location Lab-7</pre> <p>This example shows how to remove the sysLocation:</p> <pre>n1000v# config t n1000v(config)# no snmp-server location</pre>												
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>show snmp</td> <td>Displays SNMP information.</td> </tr> <tr> <td>snmp-server aaa-user cache-timeout</td> <td>Configures how long the AAA-synchronized user configuration stays in the local cache.</td> </tr> <tr> <td>snmp-server contact</td> <td>Configures sysContact (the SNMP contact).</td> </tr> <tr> <td>snmp-server protocol enable</td> <td>Enables SNMP.</td> </tr> <tr> <td>snmp-server globalEnforcePriv</td> <td>Enforces SNMP message encryption for all users.</td> </tr> </tbody> </table>	Command	Description	show snmp	Displays SNMP information.	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.	snmp-server contact	Configures sysContact (the SNMP contact).	snmp-server protocol enable	Enables SNMP.	snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
Command	Description												
show snmp	Displays SNMP information.												
snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.												
snmp-server contact	Configures sysContact (the SNMP contact).												
snmp-server protocol enable	Enables SNMP.												
snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.												

Command	Description
snmp-server host	Configures a host receiver for SNMP traps or informs.
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server protocol enable

To enable SNMP protocol operations, use the **snmp-server protocol enable** command. To disable SNMP protocol operations, use the **no** form of this command.

snmp-server protocol enable

no snmp-server protocol enable

Syntax Description This command has no arguments or keywords.

Defaults This command is enabled by default.

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to enable SNMP protocol operations:

```
n1000v# config t
n1000v(config)# snmp-server protocol enable
```

This example shows how to disable SNMP protocol operations:

```
n1000v# config t
n1000v(config)# no snmp-server protocol enable
```

Related Commands	Command	Description
	show snmp	Displays SNMP information.
	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.
	snmp-server contact	Configures sysContact (the SNMP contact).
	snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
	snmp-server host	Configures a host receiver for SNMP traps or informs.
	snmp-server location	Configures sysLocation (the SNMP location).

Command	Description
snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.
snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server tcp-session

To enable authentication for SNMP over TCP, use the **snmp-server tcp-session** command. To disable authentication for SNMP over TCP, use the **no** form of this command.

snmp-server tcp-session [auth]

no snmp-server tcp-session

Syntax Description	auth	(Optional) Enables one-time authentication for SNMP over the entire TCP session (rather than on a per-command basis).
--------------------	------	---

Defaults This command is disabled by default.

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to enable one-time authentication for SNMP over TCP:

```
n1000v# config t
n1000v(config)# snmp-server tcp-session auth
```

This example shows how to disable one-time authentication for SNMP over TCP:

```
n1000v# config t
n1000v(config)# no snmp-server tcp-session
```

Related Commands	Command	Description
	show snmp	Displays SNMP information.
	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.
	snmp-server contact	Configures sysContact, (the SNMP contact).
	snmp-server protocol enable	Enables SNMP.
	snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
	snmp-server host	Configures a host receiver for SNMP traps or informs.
	snmp-server location	Configures sysLocation (the SNMP location).
	snmp-server user	Configures an SNMP user with authentication and privacy parameters.

snmp-server user

To define a user who can access the SNMP engine, use the **snmp-server user** command. To deny a user access to the SNMP engine, use the **no** form of this command.

```
snmp-server user name [auth { md5 | sha } passphrase-1 [priv [aes-128] passphrase-2] [engineID id] [localizedkey]]
```

```
no snmp-server user name
```

Syntax Description

<i>name</i>	Name of a user who can access the SNMP engine.
auth	(Optional) Enables one-time authentication for SNMP over a TCP session
md5	(Optional) Specifies HMAC MD5 algorithm for authentication.
sha	(Optional) Specifies HMAC SHA algorithm for authentication.
<i>passphrase-1</i>	Authentication passphrase for this user. The passphrase can be any case-sensitive alphanumeric string up to 64 characters.
priv	(Optional) Specifies encryption parameters for the user.
aes-128	(Optional) Specifies a 128-byte AES algorithm for privacy.
<i>passphrase-2</i>	Encryption passphrase for this user. The passphrase can be any case-sensitive alphanumeric string up to 64 characters.
engineID	(Optional) Specifies the engineID for configuring the notification target user (for V3 informs).
<i>id</i>	Number that identifies the engineID, in a 12-digit, colon-separated decimal format.
localizedkey	(Optional) Specifies the passphrase as any case-sensitive alphanumeric string up to 130 characters.

Defaults

None

Command Modes

Global configuration (config)

SupportedUserRoles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Examples

This example shows how to provide one-time SNMP authorization for the user, Admin, using the HMAC SHA algorithm for authentication:

```
n1000v# config t
n1000v(config)# snmp-server user Admin auth sha abcd1234 priv abcdefgh
```

This example shows how to deny a user access to the SNMP engine:

```
n1000v# config t
n1000v(config)# no snmp-server user Admin
```

Related Commands	Command	Description
	show snmp	Displays SNMP information.
	snmp-server aaa-user cache-timeout	Configures how long the AAA-synchronized user configuration stays in the local cache.
	snmp-server contact	Configures sysContact (the SNMP contact).
	snmp-server protocol enable	Enables SNMP.
	snmp-server globalEnforcePriv	Enforces SNMP message encryption for all users.
	snmp-server host	Configures a host receiver for SNMP traps or informs.
	snmp-server location	Configures sysLocation (the SNMP location).
	snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.

snmp trap link-status

To enable SNMP link-state traps for the interface, use the **snmp trap link-status** command. To disable SNMP link-state traps for the interface, use the **no** form of this command.

snmp trap link-status

no snmp trap link-status

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes CLI interface configuration (config-if)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines This command is enabled by default.

Examples This example shows how to enable SNMP link-state traps for the interface:

```
n1000v# config t
n1000v(config)# interface veth 2
n1000v(config-if)# snmp trap link-status
n1000v(config-if)#
```

This example shows how to disable SNMP link-state traps for the interface:

```
n1000v# config t
n1000v(config)# interface veth 2
n1000v(config-if)# no snmp trap link-status
n1000v(config-if)#
```

Related Commands	Command	Description
	interface vethernet	Creates a virtual Ethernet interface and enters interface configuration mode.
	snmp-server enable traps	Enables all SNMP notifications.
	snmp-server tcp-session	Enables a one-time authentication for SNMP over a TCP session.

source-interface

To specify a source interface for reaching a RADIUS or TACACS+ server group, use the **source-interface** command. To remove the source interface, use the **no** form of this command.

source-interface *interface-type interface-id*

no source-interface

Syntax Description

<i>interface-type</i>	Specifies the interface type. <ul style="list-style-type: none"> • loopback = Loopback interface • mgmt = Management interface • null = Null interface • port-channel = Port Channel interface
<i>interface-id</i>	Specifies the interface ID, such as slot/port or number. <ul style="list-style-type: none"> • loopback = Virtual interface number from 0 to 1023 • mgmt = Management interface 0 • null = Null interface 0 • port-channel = Port channel number from 1 to 4096

Defaults

None

Command Modes

RADIUS server group configuration (config-radius)
TACACS+ server group configuration (config-tacacs+)

Supported User Roles

network-admin

Command History

Release	Modification
4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Examples

This example shows how to specify source interface mgmt0 to reach the RADIUS server for the RadServer RADIUS server group:

```
n1000v # configure terminal
n1000v(config)# aaa group server radius RadServer
n1000v(config-radius)# source-interface mgmt0
n1000v(config-radius)#
```

This example shows how to remove the source interface from the configuration:

```
n1000v # configure terminal
n1000v(config)# aaa group server radius RadServer
n1000v(config-radius)# no source-interface
n1000v(config-radius)#
```

Related Commands

Command	Description
aaa group server radius	Creates a RADIUS server group.
aaa group server tacacs+	Creates a TACACS+ server group.
show radius-server groups	Displays the RADIUS server group configuration.
show tacacs-server groups	Displays the TACACS+ server group configuration.

source mgmt (NetFlow)

To add an interface to a flow exporter designating it as the source for NetFlow flow records, use the **source** command. To remove the source interface from the flow exporter, use the **no** form of this command.

```
source mgmt 0
```

```
no source
```

Syntax Description	mgmt 0 Adds the mgmt 0 interface to the flow exporter.
---------------------------	---

Defaults	None
-----------------	------

Command Modes	NetFlow flow exporter configuration (config-flow-exporter)
----------------------	--

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines	The mgmt0 interface is the only interface that can be added to the flow exporter.
-------------------------	---

Examples	This example shows how to add source management interface 0 to the ExportTest flow exporter:
-----------------	--

```
n1000v# config t
n1000v(config)# flow exporter ExportTest
n1000v(config-flow-exporter)# source mgmt 0
```

This example shows how to remove source management interface 0 from the ExportTest flow exporter:

```
n1000v# config t
n1000v(config)# flow exporter ExportTest
n1000v(config-flow-exporter)# no source mgmt 0
```

Related Commands	Command	Description
	flow exporter	Creates a Flexible NetFlow flow exporter.
	flow record	Creates a Flexible NetFlow flow record.
	flow monitor	Creates a Flexible NetFlow flow monitor.
	show flow exporter	Displays information about the NetFlow flow exporter.

Command	Description
show flow record	Displays information about NetFlow flow records.
show flow monitor	Displays information about the NetFlow flow monitor.

speed

To set the speed for an interface, use the **speed** command. To automatically set both the speed and duplex parameters to auto, use the **no** form of this command.

```
speed {speed_val | auto [10 100 [1000]]}
```

```
no speed [{speed_val | auto [10 100 [1000]]}]
```

Syntax Description

<i>speed_val</i>	Port speed on the interface, in Mbps.
auto	Sets the interface to autonegotiate the speed with the connecting port.
10	(Optional) Specifies a speed of 10 Mbps.
100	(Optional) Specifies a speed of 100 Mbps.
1000	(Optional) Specifies a speed of 1000 Mbps.

Defaults

None

Command Modes

Interface configuration (config-if)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Usage Guidelines

If you configure an Ethernet port speed to a value other than auto (for example, 10, 100, or 1000 Mbps), you must configure the connecting port to match. Do not configure the connecting port to negotiate the speed.

Examples

This example shows how to set the speed of Ethernet port 1 on the module in slot 3 to 1000 Mbps:

```
n1000v config t
n1000v(config)# interface ethernet 2/1
n1000v(config-if)# speed 1000
```

This example shows how to automatically set the speed to auto:

```
n1000v config t
n1000v(config)# interface ethernet 2/1
n1000v(config-if)# no speed 1000
```

Related Commands	Command	Description
	interface	Specifies the interface that you are configuring.
	duplex	Specifies the duplex mode as full, half, or autonegotiate.
	show interface	Displays the interface status, which includes the speed and duplex mode parameters.

ssh

To create a Secure Shell (SSH) session, use the **ssh** command.

```
ssh [username@]{ipv4-address | hostname} [vrf vrf-name]
```

Syntax Description		
<i>username</i>	(Optional) Username for the SSH session. The user name is not case sensitive.	
<i>ipv4-address</i>	IPv4 address of the remote device.	
<i>hostname</i>	Hostname of the remote device. The hostname is case sensitive.	
vrf <i>vrf-name</i>	(Optional) Specifies the virtual routing and forwarding (VRF) name to use for the SSH session. The VRF name is case sensitive.	

Defaults	Default VRF
-----------------	-------------

Command Modes	Any
----------------------	-----

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines	The NX-OS software supports SSH version 2.
-------------------------	--

Examples	<p>This example shows how to start an SSH session:</p> <pre>n1000v# ssh 10.10.1.1 vrf management The authenticity of host '10.10.1.1 (10.10.1.1)' can't be established. RSA key fingerprint is 9b:d9:09:97:f6:40:76:89:05:15:42:6b:12:48:0f:d6. Are you sure you want to continue connecting (yes/no)? yes Warning: Permanently added '10.10.1.1' (RSA) to the list of known hosts. User Access Verification Password:</pre>
-----------------	--

Related Commands	Command	Description
	clear ssh session	Clears SSH sessions.
	feature ssh	Enables the SSH server.

ssh key

To generate the key pair for the switch, which is used if SSH server is enabled, use the **ssh key** command. To remove the SSH server key, use the **no** form of this command.

```
ssh key {dsa [force] | rsa [length [force]]}
```

```
no ssh key [dsa | rsa]
```

Syntax Description	
dsa	Specifies the Digital System Algorithm (DSA) SSH server key.
force	(Optional) Forces the replacement of an SSH key.
rsa	Specifies the Rivest, Shamir, and Adelman (RSA) public-key cryptography SSH server key.
<i>length</i>	(Optional) Number of bits to use when creating the SSH server key. The range is from 768 to 2048.

Defaults 1024-bit length

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines The NX-OS software supports SSH version 2.
If you want to remove or replace an SSH server key, you must first disable the SSH server using the **no feature ssh** command.

Examples This example shows how to create an SSH server key using DSA:

```
n1000v# config t
n1000v(config)# ssh key dsa
generating dsa key(1024 bits).....
..
generated dsa key
```

This example shows how to create an SSH server key using RSA with the default key length:

```
n1000v# config t
n1000v(config)# ssh key rsa
generating rsa key(1024 bits).....
.
```

```
generated rsa key
```

This example shows how to create an SSH server key using RSA with a specified key length:

```
n1000v# config t
n1000v(config)# ssh key rsa 768
generating rsa key(768 bits).....
.
generated rsa key
```

This example shows how to replace an SSH server key using DSA with the force option:

```
n1000v# config t
n1000v(config)# no feature ssh
n1000v(config)# ssh key dsa force
deleting old dsa key.....
generating dsa key(1024 bits).....
.
generated dsa key
n1000v(config)# feature ssh
```

This example shows how to remove the DSA SSH server key:

```
n1000v# config t
n1000v(config)# no feature ssh
XML interface to system may become unavailable since ssh is disabled
n1000v(config)# no ssh key dsa
n1000v(config)# feature ssh
```

This example shows how to remove all SSH server keys:

```
n1000v# config t
n1000v(config)# no feature ssh
XML interface to system may become unavailable since ssh is disabled
n1000v(config)# no ssh key
n1000v(config)# feature ssh
```

Related Commands

Command	Description
show ssh key	Displays the SSH server key information.
feature ssh	Enables the SSH server.

state (VLAN)

To set the operational state of a VLAN, use the **state** command. To disable state configuration, use the **no** form of this command.

```
state { active | suspend }
```

```
no state
```

Syntax Description	active	Specifies the active state.
	suspend	Specifies the suspended state.

Defaults	None
----------	------

Command Modes	VLAN configuration (config-vlan)
---------------	----------------------------------

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to set the operational state of a VLAN:

```
n1000v# configure terminal
n1000v(config)# vlan 10
n1000v(config-vlan)# state active
n1000v(config-vlan)#
```

This example shows how to disable state configuration:

```
n1000v# configure terminal
n1000v(config)# vlan 10
n1000v(config-vlan)# no state
n1000v(config-vlan)#
```

Related Commands	Command	Description
	show vlan	Displays VLAN information.

state (Port Profile)

To set the operational state of a port profile, use the **state** command.

state enabled

Syntax Description	enabled	Enables or disables the port profile.
---------------------------	----------------	---------------------------------------

Defaults	Disabled
-----------------	----------

Command Modes	Port profile configuration (config-port-prof)
----------------------	---

SupportedUserRoles	network-admin
---------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to enable or disable the operational state of a port profile:

```
n1000v# configure terminal
n1000v(config)# port-profile testprofile
n1000v(config-port-prof)# state enabled
n1000v(config-port-prof)#
```

Related Commands	Command	Description
	show port-profile	Displays port profile information.

statistics per-entry

To collect statistics for each ACL entry, use the **statistics per-entry** command. To remove statistics, use the **no** form of this command.

statistics per-entry

no statistics per-entry

Syntax Description This command has no arguments or keywords.

Defaults No statistics are collected.

Command Modes ACL configuration (config-acl)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to collect statistics for each ACL entry:

```
n1000v# configure terminal
n1000v(config)# ip access-list 1
n1000v(config-acl)# statistics per-entry
n1000v(config-acl)#
```

This example shows how to remove statistics:

```
n1000v# configure terminal
n1000v(config)# ip access-list 1
n1000v(config-acl)# no statistics per-entry
n1000v(config-acl)#
```

Related Commands	Command	Description
	show statistics	Displays statistics.

sub-group

To configure interface port channel subgroup assignment, use the **sub-group** command. To remove this configuration, use the **no** form of this command.

```
sub-group {cdp | manual}
```

```
no sub-group
```

Syntax Description	cdp	manual
	Specifies that Cisco Discovery Protocol (CDP) information is used to automatically create subgroups for managing the traffic flow.	Specifies that subgroups are configured manually. This option is used if CDP is not configured on the upstream switches.

Defaults	None
----------	------

Command Modes	Interface configuration (config-if)
---------------	-------------------------------------

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.0	This command was introduced.
	4.0(4)SV1(2)	The manual keyword was added.

Usage Guidelines	Use this command to identify the port channel as being in vPC-HM, which requires traffic to be managed separately for each upstream switch connected to the member ports. If the upstream switches have CDP enabled, the Cisco Nexus 1000V can use this information to automatically assign subgroups. If the upstream switches do not have CDP enabled, then you must configure subgroups manually.
------------------	--

This command overrides any subgroup configuration specified in the port-profile inherited by the port channel interface.

Examples	This example shows how to configure a subgroup type for a port channel interface:
----------	---

```
h1000v# config t
n1000v(config)# interface port-channel 1
n1000v(config-if)# sub-group cdp
```

This example shows how to remove the configuration:

```
h1000v# config t
n1000v(config)# interface port-channel 1
n1000v(config-if)# no sub-group
```

Related Commands	Command	Description
	show interface port channel <i>channel-number</i>	Displays port-channel information.

sub-group-id

To configure subgroup IDs for Ethernet member ports of vPC-HM, use the **sub-group-id** command. To remove the subgroup IDs, use the **no** form of this command.

sub-group-id *group_id*

no sub-group-id

Syntax Description	<i>group_id</i> Subgroup ID number. Range is from 0 to 31.						
Defaults	None						
Command Modes	Interface configuration (config-if)						
Supported User Roles	network-admin						
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0</td> <td>This command was introduced.</td> </tr> <tr> <td>4.0(4)SV1(2)</td> <td>The number of subgroups was increased to 32.</td> </tr> </tbody> </table>	Release	Modification	4.0	This command was introduced.	4.0(4)SV1(2)	The number of subgroups was increased to 32.
Release	Modification						
4.0	This command was introduced.						
4.0(4)SV1(2)	The number of subgroups was increased to 32.						
Examples	<p>This example shows how to configure an Ethernet member port on subgroup 5:</p> <pre>n1000v# config t n1000v(config)# interface Ethernet 3/2 n1000v(config-if)# sub-group-id 1</pre> <p>This example shows how to remove the configuration:</p> <pre>n1000v# config t n1000v(config)# interface Ethernet 3/2 n1000v(config-if)# no sub-group-id</pre>						
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>show interface ethernet slot/port</td> <td>Displays information about Ethernet interfaces.</td> </tr> </tbody> </table>	Command	Description	show interface ethernet slot/port	Displays information about Ethernet interfaces.		
Command	Description						
show interface ethernet slot/port	Displays information about Ethernet interfaces.						

svs connection

To enable an SVS connection, use the **svs connection** command. To disable an SVS connection, use the **no** form of this command.

svs connection *name*

no svs connection *name*

Syntax Description	<i>name</i> Connection name.				
Defaults	None				
Command Modes	Global configuration (config)				
SupportedUserRoles	network-admin				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0(4)SV1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.0(4)SV1(1)	This command was introduced.
Release	Modification				
4.0(4)SV1(1)	This command was introduced.				
Usage Guidelines	Only one SVS connection can be enabled per session.				
Examples	<p>This example shows how to enable an SVS connection:</p> <pre>n1000v# configure terminal n1000v(config)# svs connection conn1 n1000v(config-svs-conn)#</pre> <p>This example shows how to disable an SVS connection:</p> <pre>n1000v# configure terminal n1000v(config)# no svs connection conn1 n1000v(config)#</pre>				
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>show svs</td> <td>Displays SVS information.</td> </tr> </tbody> </table>	Command	Description	show svs	Displays SVS information.
Command	Description				
show svs	Displays SVS information.				

svs-domain

To configure an SVS domain and enter SVS domain configuration mode, use the **svs-domain** command.

svs-domain

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to enter SVS domain configuration mode to configure an SVS domain:

```
n1000v# configure terminal
n1000v(config)# svs-domain
n1000v(config-svs-domain)#
```

Related Commands	Command	Description
	show svs	Displays SVS information.

svs license transfer src-vem

To transfer licenses from a specified source VEM to another VEM, or to transfer an unused license to the VSM license pool, use the **svs license transfer src-vem** command.

```
svs license transfer src-vem module number [ dst-vem module number | license_pool ]
```

Syntax Description	Parameter	Description
	dst-vem <i>module-number</i>	Specifies the VEM to receive the transferred license.
	license_pool	Transfers a license back to the VSM license pool.

Defaults None

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

- Usage Guidelines**
- Licenses cannot be transferred to a VEM unless there are sufficient licenses in the pool for all CPUs on that VEM.
 - When licenses are successfully transferred from one VEM to another, then the following happens:
 - The virtual Ethernet interfaces on the source VEM are removed from service.
 - The virtual Ethernet interfaces on the destination VEM are brought into service.
 - When licenses are successfully transferred from a VEM to the VSM license pool, then the following happens:
 - The virtual Ethernet interfaces on the source VEM are removed from service.

Examples This example shows how to transfer a license from VEM 3 to VEM 5, and then display the license configuration:

```
n1000v# config t
n1000v(config)# svs license transfer src-vem 3 dst-vem 5
n1000v(config)# show license usage NEXUS1000V_LAN_SERVICES_PKG
Application
-----
VEM 5 - Socket 1
VEM 5 - Socket 2
VEM 4 - Socket 1
VEM 4 - Socket 2
```

```

-----
n1000v#

```

This example shows how to transfer a license from VEM 3 to the VSM license pool, and then display the license configuration:

```

n1000v# config t
n1000v(config)# svs license transfer src-vem 3 license_pool
n1000v(config)# show license usage NEXUS1000V_LAN_SERVICES_PKG
Application
-----
VEM 4 - Socket 1
VEM 4 - Socket 2
-----

n1000v#

```

Related Commands

Command	Description
show license usage	Displays the number and location of CPU licenses in use on your VEMs.
logging level license	Designates the level of severity at which license messages should be logged.
install license	Installs a license file(s) on a VSM.
svs license transfer src-vem	Transfers licenses from a source VEM to another VEM, or to the VSM pool of available licenses.

svs license volatile

To enable volatile licenses so that, whenever a VEM is taken out of service, its licenses are returned to the VSM pool of available licenses, use the **svs license volatile** command. To disable volatile licenses, use the **no** form of this command.

svs license volatile

no svs license volatile

Syntax Description This command has no arguments or keywords.

Defaults Disabled

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines



Caution

Service Disruption

Volatile licenses are removed from a VEM during a loss in connectivity and are not returned to the VEM when connectivity resumes. Cisco recommends that the volatile license feature remain disabled and that you, instead, transfer unused licenses using the **svs license transfer src-vem** command.

Examples

This example shows how to enable the volatile license feature for a VSM:

```
n1000v(config)# svs license volatile
n1000v(config)#
```

This example shows how to disable the volatile license feature for a VSM:

```
n1000v(config)# no svs license volatile
```

Related Commands	Command	Description
	show license	Displays the license configuration for the VSM.
	logging level license	Designates the level of severity at which license messages should be logged.
	install license	Installs a license file(s) on a VSM.
	svl license transfer src-vem	Transfers licenses from a source VEM to another VEM, or to the VSM pool of available licenses.

svs mode

To configure a transport mode for control and packet traffic in the virtual supervisor module (VSM) domain, use the **svs mode** command.

```
svs mode {L2 | L3 interface {mgmt0 | control0}}
```

Syntax Description

L2	Specifies Layer 2 as the transport mode for the VSM domain.
L3 interface	Specifies Layer 3 as the transport mode for the VSM domain and configures the Layer 3 transport interface.
mgmt0	Specifies mgmt0 as the Layer 3 transport interface.
control0	Specifies control0 as the Layer 3 transport interface.

Defaults

Layer 2 mode

Command Modes

SVS domain configuration (config-svs-domain)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(2)	This command was introduced.

Usage Guidelines

If you use mgmt0 as the Layer 3 control interface, then in the VSM VM, Ethernet adapters 1 and 3 are not used.

If you use control0 as the Layer 3 control interface, then in the VSM VM, Ethernet adapter 3 is not used.

Examples

This example shows how to configure mgmt0 as the Layer 3 transport interface for the VSM domain:

```
n1000v# config t
n1000v(config)# svs-domain
n1000v(config-svs-domain)# svs mode l3 interface mgmt0
n1000v(config-svs-domain)#
```

Related Commands

Command	Description
show svs-domain	Displays the VSM domain configuration.
svs-domain	Creates and configures the VSM domain.

svs switch edition

To configure the Cisco Nexus 1000V switch edition, use the **svs switch edition** command.

```
svs switch edition [essential | advanced]
```

Syntax Description

essential	Configures the Cisco Nexus 1000V switch in the essential edition.
advanced	Configures the Cisco Nexus 1000V switch in the advanced edition.

Command Modes

Global configuration (config)

Supported User Roles

network-admin

Command History

Release	Modification
4.2(1)SV2(1.1)	This command was introduced.

Usage Guidelines

When the Release 4.2.1SV2(1.1) software is installed, the Essential edition is the default edition. When the switch is configured in the Essential edition, all the features (other than the advanced features) are available for free. No licenses are required to operate the Essential edition. The switch edition configuration is global and not per module. In Essential edition, all the modules are automatically licensed. A new command is provided to move the switch from the Essential edition to the Advanced edition and vice versa. The licenses are required only when switch edition is configured as the Advanced edition.

Examples

This example shows how to complete the VSM upgrade, notify hosts to switch to the upgraded datapath, and then display the upgrade status:

```
n1000v(config)# svs switch edition advanced
```

Related Commands

Command	Description
show switch edition	Displays the switch edition..

svs upgrade complete

To complete a VSM software upgrade, and notify hosts to switch to the upgraded datapath, use the **svs upgrade complete** command.

svs upgrade complete

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Examples This example shows how to complete the VSM upgrade, notify hosts to switch to the upgraded datapath, and then display the upgrade status:

```
n1000v(config)# svs upgrade complete
Warning: Config saved but not pushed to vCenter Server due to inactive connection!
n1000v(config)# show running-config | in svs
svs-domain
  svs mode L2
  svs upgrade complete
svs connection vcenter
```

Related Commands	Command	Description
	show svs upgrade status	Monitors the upgrade of the VSM to a new software version.
	svs upgrade start	Starts a manual VSM upgrade and saves upgrade information at the standby.

svs upgrade start

To start a manual VSM upgrade and save upgrade information at the standby, use the **svs upgrade start** command. To stop a manual upgrade, use the no form of this command.

```
svs upgrade start mgmt0 { ip ipaddress | ipv6 ipv6address } + [control0 ip ipaddr]
```

```
no svs upgrade start
```

Syntax Description

mgmt0	Specifies the management interface.
ip <i>ipaddress</i>	Specifies an IP address.
ipv6 <i>ipv6address</i>	Specifies an IPv6 address.
control0 ip	(Optional) Specifies the control0 ip address.

Defaults

None

Command Modes

Global configuration (config)

Supported User Roles

network-admin

Command History

Release	Modification
4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Before starting a manual VSM upgrade:

- Stop all configuration of the system, and do not change the configuration for the duration of the upgrade.
- Save all changes in the running configuration to the startup configuration to be preserved through the upgrade.
- Save a copy of your running configuration in external storage.
- Make sure all VSM ports, uplinks, vmknics, and vsifs used for control, packet, management, and storage are configured with system profiles.
- Make sure there is network connectivity between VC, VSM pair, and hosts or modules.
- Make sure all hosts or modules are upgraded to the concurrent VEM software version.
- If you are upgrading VSMs on a Cisco Nexus 1010, make sure the secondary VSM2 is active and the primary VSM1 is standby.
- If upgrading VSMs on a Cisco Nexus 1010, the Cisco Nexus 1010s must be in an HA configuration.

To preserve access to VSM2 during software upgrade, this process requires you to assign an alternate management IP address to VSM2.

Examples

This example shows how to start a manual VSM upgrade and assign a temporary IP address.

```
n1000v# configure terminal
n1000v(config)# svs upgrade start mgmt0 ip 10.78.109.44
WARNING!
1. Please do not change the configuration of the system from this point onwards
2. Ensure that all relevant ports, including uplinks, vmknics, and vsifs used for control,
packet, management, storage as well as VSM ports, are all configured with system profiles
3. Ensure there is network connectivity between VC, VSM pair, and the hosts/modules
4. Ensure all the hosts/modules are upgraded with the next version of VEM software package
n1000v(config)#
```

Related Commands

Command	Description
show svs upgrade status	Monitors the upgrade of the VSM to a new software version.
svs upgrade complete	Completes a VSM software upgrade, and notifies hosts to switch to the upgraded datapath.
show module	Displays information about all available VSMS and VEMs in the system.
reload	Reboots both the primary and secondary VSM.
show system redundancy status	Displays the HA status of the system.
boot kickstart	Configures the kickstart boot variable.
boot system	Configures the system boot variable.
system redundancy role primary	Configures the primary redundant role for a VSM.
show svs connections	Displays the current connections to the Cisco Nexus 1000V.

svs veth auto-config-purge

To enable the VSM to remove all manual configuration on a vEthernet interface when the system administrator changes a port profile on the interface, use the **svs veth auto-config-purge** command. To remove this control, use the **no** form of this command.

svs veth auto-config-purge

no svs veth auto-config-purge

Syntax Description This command has no arguments or keywords.

Defaults Enabled

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Examples This example shows how to enable the VSM to remove all manual configuration on a vEthernet interface when the system administrator changes a port profile on the interface:

```
n1000v(config)# svs veth auto-config-purge
n1000v(config)#
```

This example shows how to remove the xxx configuration:

```
n1000v(config)# no svs veth auto-config-purge
n1000v(config)#
```

Related Commands	Command	Description
	interface vethernet <i>interface-number</i>	Creates a vEthernet interface.
	show running-config	Displays information about the configuration currently running on the system.
	show interface vethernet	Displays information about vEthernet interfaces.

Command	Description
svs veth auto-delete	Enables the VSM to automatically delete DVPorts no longer used by a vNIC or hypervisor port.
svs veth auto-setup	Enable the VSM to automatically create a vEthernet interface when a new port is activated on a host.

svs veth auto-delete

To enable the VSM to automatically delete DVPorts no longer used by a vNIC or hypervisor port, use the **svs veth auto-delete** command. To disable this control, use the **no** form of this command.

svs veth auto-delete

no svs veth auto-delete

Syntax Description This command has no arguments or keywords.

Defaults Enabled

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Examples This example shows how to enable the VSM to automatically delete DVPorts no longer used by a vNIC or hypervisor port:

```
n1000v(config)# svs veth auto-delete
n1000v(config)#
```

This example shows how to disable the automatic deletion of DVPorts that are no longer used by a vNIC or hypervisor port:

```
n1000v(config)# no svs veth auto-delete
n1000v(config)#
```

Related Commands	Command	Description
	interface vethernet <i>interface-number</i>	Creates a vEthernet interface.
	show running-config	Displays information about the configuration currently running on the system.
	show interface vethernet	Displays information about vEthernet interfaces.

Command	Description
svs veth auto-config-purge	Enables the VSM to remove all manual configuration on a vEthernet interface when the system administrator changes a port profile on the interface.
svs veth auto-setup	Enable the VSM to automatically create a vEthernet interface when a new port is activated on a host.

svcs veth auto-setup

To enable the VSM to automatically create a vEthernet interface when a new port is activated on a host, use the **svcs veth auto-setup** command. To remove this control, use the **no** form of this command.

svcs veth auto-setup

no svcs veth auto-setup

Syntax Description This command has no arguments or keywords.

Defaults Enabled

Command Modes Global configuration (config)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.2(1)SV1(4)	This command was introduced.

Usage Guidelines

Examples This example shows how to configure xxx:

```
n1000v(config)# xxx
```

This example shows how to remove the xxx configuration:

```
n1000v(config)# no xxx
```

Related Commands	Command	Description
	interface vethernet <i>interface-number</i>	Creates a vEthernet interface.
	show running-config	Displays information about the configuration currently running on the system.
	show interface vethernet	Displays information about vEthernet interfaces.

Command	Description
svs veth auto-delete	Enables the VSM to automatically delete DVPorts no longer used by a vNIC or hypervisor port.
svs veth auto-config-purge	Enables the VSM to remove all manual configuration on a vEthernet interface when the system administrator changes a port profile on the interface.

switchname

To configure the hostname for the device, use the **switchname** command. To revert to the default, use the **no** form of this command.

switchname *name*

no switchname

Syntax Description	<i>name</i>	Name for the device. The name is alphanumeric, case sensitive, can contain special characters, and can have a maximum of 32 characters.
---------------------------	-------------	---

Defaults	switch
-----------------	--------

Command Modes	Global configuration (config)
----------------------	-------------------------------

Supported User Roles	network-admin
-----------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines The Cisco NX-OS software uses the hostname in command-line interface (CLI) prompts and in default configuration filenames.

The **switchname** command performs the same function as the **hostname** command.

Examples This example shows how to configure the device hostname:

```
n1000v# configure terminal
n1000v(config)# switchname Engineering2
Engineering2(config)#
```

This example shows how to revert to the default device hostname:

```
Engineering2# configure terminal
Engineering2(config)# no switchname
n1000v(config)#
```

Related Commands	Command	Description
	hostname	Configures the device hostname.
	show switchname	Displays the device hostname.

switchport access bridge-domain

To assign a VXLAN bridge domain to a port profile, use the **switchport access bridge-domain** command. To remove the VXLAN bridge domain, use the **no** form of this command.

switchport access bridge-domain *bd-name*

no switchport access bridge-domain

Syntax	Description
<i>bd-name</i>	The name of the VXLAN bridge domain.

Defaults	None
----------	------

Command Modes	Port profile configuration (config-port-prof)
---------------	---

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.2(1)SV1(5.1)	This command was introduced.

Usage Guidelines

Examples This example shows how to assign a VXLAN bridge domain to a port profile:

```
n1000v# configure terminal
n1000v(config)# port-profile tenant-profile
n1000v(config-port-prof)# switchport mode access
n1000v(config-port-prof)# switchport access bridge-domain tenant-red
n1000v(config-port-prof)#
```

Related Commands	Command	Description
	show bridge-domain	Displays bridge domain information.
	show running-config port-profile profile-name	Displays the running configuration of the specified port profile.
	show port-profile name	Displays the port profile configuration.

switchport access vlan

To set the access mode of an interface, use the **switchport access vlan** command. To remove access mode configuration, use the **no** form of this command.

switchport access vlan *id*

no switchport access vlan

Syntax Description	<i>id</i>	VLAN identification number. The range of valid values is 1 to 3967.
--------------------	-----------	---

Defaults	Access mode is not set.
----------	-------------------------

Command Modes	Interface configuration (config-if) Port profile configuration (config-port-prof)
---------------	--

SupportedUserRoles	network-admin
--------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to set the access mode of an interface:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# switchport access vlan 10
n1000v(config-if)#
```

This example shows how to remove access mode configuration:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# no switchport access vlan
n1000v(config-if)#
```

Related Commands	Command	Description
	show interface	Displays interface information.

switchport mode

To set the port mode of an interface, use the **switchport mode** command. To remove the port mode configuration, use the **no** form of this command.

```
switchport mode {access | private-vlan {host | promiscuous} | trunk}
```

```
no switchport mode {access | private-vlan {host | promiscuous} | trunk}
```

Syntax Description

access	Sets port mode access.
private-vlan	Sets the port mode to private VLAN.
host	Sets the port mode private VLAN to host.
promiscuous	Sets the port mode private VLAN to promiscuous.
trunk	Sets the port mode to trunk.

Defaults

Switchport mode is not set.

Command Modes

Interface configuration (config-if)
Port profile configuration (config-port-prof)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Examples

This example shows how to set the port mode of an interface:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# switchport mode private-vlan host
n1000v(config-if)#
```

This example shows how to remove mode configuration:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# no switchport mode private-vlan host
n1000v(config-if)#
```

Related Commands

Command	Description
show interface	Displays interface information.

switchport port-security

To set the port security characteristics of an interface, use the **switchport port-security** command. To remove the port security configuration, use the **no** form of this command.

switchport port-security [**aging** {**time** *time* | **type** {**absolute** | **inactivity**}}] | **mac-address** {*address* [*vlan id*] | **sticky**} | **maximum** *number* [*vlan id*] | **violation** {**protect** | **shutdown**}}

no switchport port-security [**aging** {**time** *time* | **type** {**absolute** | **inactivity**}}] | **mac-address** {*address* [*vlan id*] | **sticky**} | **maximum** *number* [*vlan id*] | **violation** {**protect** | **shutdown**}}

Syntax Description		
aging		Configures port security aging characteristics.
time		Specifies the port security aging time.
<i>time</i>		Aging time in minutes, in the range of 0 to 1440.
type		Specifies the type of timers.
absolute		Specifies an absolute timer.
inactivity		Specifies an inactivity timer.
mac-address		Specifies a 48-bit MAC address in the format <i>HHHH.HHHH.HHHH</i> .
<i>address</i>		
vlan		Specifies the VLAN where the MAC address should be secured.
<i>id</i>		VLAN identification number. The range of valid values is 1 to 4094.
sticky		Specifies a sticky MAC address.
maximum		Specifies the maximum number of addresses, in the range of 1 to 1025.
<i>number</i>		
violation		Specifies the security violation mode.
protect		Specifies the security violation protect mode.
shutdown		Specifies the security violation shutdown mode.

Defaults None

Command Modes Interface configuration (config-if)
Port profile configuration (config-port-prof)

Supported User Roles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to set the port security aging inactivity timer:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# switchport port-security aging type inactivity
n1000v(config-if)#
```

This example shows how to remove the port security aging inactivity timer:

```
n1000v# configure terminal
n1000v(config)# interface vethernet 1
n1000v(config-if)# no switchport port-security aging type inactivity
n1000v(config-if)#
```

Related Commands

Command	Description
show interface	Displays interface information.
show port-security	Displays port security information.

switchport private-vlan host-association

To define a private VLAN association for an isolated or community port, use the **switchport private-vlan host-association** command. To remove the private VLAN association from the port, use the **no** form of this command.

```
switchport private-vlan host-association {primary-vlan-id} {secondary-vlan-id}
```

```
no switchport private-vlan host-association
```

Syntax Description

<i>primary-vlan-id</i>	Number of the primary VLAN of the private VLAN relationship.
<i>secondary-vlan-id</i>	Number of the secondary VLAN of the private VLAN relationship.

Defaults

None

Command Modes

Interface configuration (config-if)
Port profile configuration (config-port-prof)

Supported User Roles

network-admin

Command History

Release	Modification
4.0(4)SV1(1)	This command was introduced.

Usage Guidelines

There is no run-time effect on the port unless it is in private VLAN-host mode. If the port is in private VLAN-host mode but neither of the VLANs exist, the command is allowed but the port is made inactive. The port also may be inactive when the association between the private VLANs is suspended.

The secondary VLAN may be an isolated or community VLAN.

Examples

This example shows how to configure a host private VLAN port with a primary VLAN (VLAN 18) and a secondary VLAN (VLAN 20):

```
n1000v(config-if)# switchport private-vlan host-association 18 20
n1000v(config-if)#
```

This example shows how to remove the private VLAN association from the port:

```
n1000v(config-if)# no switchport private-vlan host-association
n1000v(config-if)#
```


Related Commands

Command	Description
show vlan private-vlan [type]	Displays information on private VLANs.

switchport private-vlan mapping

To define the private VLAN association for a promiscuous port, use the **switchport private-vlan mapping** command. To clear all mapping from the primary VLAN, use the **no** form of this command.

```
switchport private-vlan mapping {primary-vlan-id} {[add] secondary-vlan-list |  
remove secondary-vlan-list}
```

```
no switchport private-vlan mapping
```

Syntax Description		
	<i>primary-vlan-id</i>	Number of the primary VLAN of the private VLAN relationship.
	add	Associates the secondary VLANs to the primary VLAN.
	<i>secondary-vlan-list</i>	Number of the secondary VLAN of the private VLAN relationship.
	remove	Clears the association between the secondary VLANs and the primary VLAN.

Defaults	
	None

Command Modes	
	Interface configuration (config-if) Port profile configuration (config-port-prof)

SupportedUserRoles	
	network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines	
	There is no run-time effect on the port unless it is in private VLAN-promiscuous mode. If the port is in private VLAN-promiscuous mode but the primary VLAN does not exist, the command is allowed but the port is made inactive.

The secondary VLAN may be an isolated or community VLAN.

Examples

This example shows how to configure the associate primary VLAN 18 to secondary isolated VLAN 20 on a private VLAN promiscuous port:

```
n1000v(config-if) # switchport private-vlan mapping 18 20  
n1000v(config-if) #
```

This example shows how to add a VLAN to the association on the promiscuous port:

```
n1000v(config-if) # switchport private-vlan mapping 18 add 21  
n1000v(config-if) #
```

This example shows how to remove the all private VLAN association from the port:

```
n1000v(config-if) # no switchport private-vlan mapping  
n1000v(config-if) #
```

Related Commands

Command	Description
show interface switchport	Displays information on all interfaces configured as switchports.
show interface private-vlan mapping	Displays the information about the private VLAN mapping for VLAN interfaces, or SVIs.

switchport private-vlan mapping trunk

To designate the primary private VLAN, use the **switchport private-vlan trunk mapping trunk** command. To remove the primary private VLAN, use the **no** form of this command.

switchport private-vlan trunk native vlan *id*

no switchport private-vlan trunk native vlan

Syntax Description	<i>id</i> VLAN identification number. The range of valid values is 1 to 3967.				
Defaults	None				
Command Modes	Interface configuration (config-if) Port profile configuration (config-port-prof)				
Supported User Roles	network-admin				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0(4)SV1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.0(4)SV1(1)	This command was introduced.
Release	Modification				
4.0(4)SV1(1)	This command was introduced.				
Usage Guidelines	When you use this command, you must either add a secondary VLAN, or remove a VLAN.				
Examples	<p>This example shows how to designate the primary private VLAN:</p> <pre>n1000v# configure terminal n1000v(config)# interface vethernet 1 n1000v(config-if)# n1000v(config-if)# switchport private-vlan mapping trunk 10 add 11 n1000v(config-if)#</pre> <p>This example shows how to remove the primary private VLAN:</p> <pre>n1000v# configure terminal n1000v(config)# interface vethernet 1 n1000v(config-if)# n1000v(config-if)# no switchport private-vlan mapping trunk 10 n1000v(config-if)#</pre>				
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>show vlan</td> <td>Displays VLAN information.</td> </tr> </tbody> </table>	Command	Description	show vlan	Displays VLAN information.
Command	Description				
show vlan	Displays VLAN information.				

switchport private-vlan trunk allowed vlan

To set the allowed VLANs when the interface is in private-vlan promiscuous trunking mode, use the **switchport private-vlan trunk allowed** command. To clear all VLANs from the private-vlan promiscuous trunking mode, use the **no** form of this command.

```
switchport private-vlan trunk allowed vlan {vlan-ids | add vlan-ids | all | except vlan-ids | none
| remove vlan-ids}
```

```
no switchport private-vlan trunk allowed vlan vlan-ids
```

Syntax Description		
	<i>vlan-ids</i>	VLAN IDs of the allowed VLANs when interface is in trunking mode.
	add	Adds the VLANs to the interface.
	all	Allows all the VLANs on the interface.
	except	Allows all the VLANs on the interface except the specified ones.
	none	Allows no VLANs on the interface.
	remove	Removes VLAN IDs from existing allowed VLANs on the interface.

Defaults None

Command Modes Port profile configuration (config-port-prof)
Interface configuration (config-if)

Supported User Roles network-admin

Command History	Releases	Modifications
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines This command is used to allow only the normal VLANs on the promiscuous trunk port.

Examples This example shows how to set the allowed VLANs when the interface is in private VLAN trunking mode:

```
switch# config t
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# port-profile type ethernet PVLAN-UPLINK
switch(config-port-prof)# vmware port-group
switch(config-port-prof)# switchport mode private-vlan trunk promiscuous
switch(config-port-prof)# switchport private-vlan trunk allowed vlan 155-156
switch(config-port-prof)# switchport private-vlan mapping 156 155
switch(config-port-prof)# switchport private-vlan mapping trunk 156 155
switch(config-port-prof)# channel-group auto mode on mac-pinning
switch(config-port-prof)# no shutdown
```

■ switchport private-vlan trunk allowed vlan

```
switch(config-port-prof) # state enabled
```

Related Commands

Command	Description
--	--

switchport trunk allowed vlan

To set the list of allowed VLANs on the trunking interface, use the **switchport trunk allowed vlan** command. To allow *all* VLANs on the trunking interface, use the **no** form of this command.

switchport trunk allowed vlan {*vlan-list* | **all** | **none** | [**add** | **except** | **remove** {*vlan-list*}]}

no switchport trunk allowed vlan

Syntax Description	<i>vlan-list</i>	Allowed VLANs that transmit through this interface in tagged format when in trunking mode; the range of valid values is from 1 to 4094.
all		Allows all appropriate VLANs to transmit through this interface in tagged format when in trunking mode.
none		Blocks all VLANs transmitting through this interface in tagged format when in trunking mode.
add		(Optional) Adds the defined list of VLANs to those currently set instead of replacing the list.
except		(Optional) Allows all VLANs to transmit through this interface in tagged format when in trunking mode except the specified values.
remove		(Optional) Removes the defined list of VLANs from those currently set instead of replacing the list.

Defaults All VLANs

Command Modes Interface configuration (config-if)
Port profile configuration (config-port-prof)

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines You must enter the **switchport** command without any keywords to configure the LAN interface as a Layer 2 interface before you can enter the **switchport trunk allowed vlan** command. This action is required only if you have not entered the **switchport** command for the interface.

If you remove VLAN 1 from a trunk, the trunk interface continues to send and receive management traffic in VLAN 1.

Examples

This example shows how to add a series of consecutive VLANs to the list of allowed VLANs on a trunking port:

```
n1000v(config-if)# switchport trunk allowed vlan add 40-50
n1000v(config-if)#
```

Related Commands

Command	Description
show interface switchport	Displays the administrative and operational status of a switching (nonrouting) port.

switchport trunk native vlan

To configure trunking parameters on an interface, use the **switchport trunk native vlan** command. To remove the configuration, use the **no** form of this command.

switchport trunk native vlan *id*

no switchport trunk native vlan

Syntax Description	<i>id</i>	VLAN identification number. The range of valid values is 1 to 3967.
Defaults	None	
Command Modes	Interface configuration (config-if) Port profile configuration (config-port-prof)	
Supported User Roles	network-admin	
Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.
Examples	This example shows how to configure trunking parameters on an interface: <pre>n1000v# configure terminal n1000v(config)# interface vethernet 10 n1000v(config-if)# switchport trunk native vlan 20 n1000v(config-if)#</pre>	
Related Commands	Command	Description
	show vlan	Displays VLAN information.

system jumbomtu

To configure a system-wide jumbo frame size, specifying the maximum frame size that Ethernet ports can process, use the **system jumbomtu** command.

system jumbomtu *size*

Syntax Description	<i>size</i>	Size, in bytes, of the Layer 2 Ethernet interface jumbo maximum transmission unit (MTU). Frames larger than this are dropped. The setting must be an even number between 1500 and 9000 bytes.
--------------------	-------------	---

Defaults	9000 bytes
----------	------------

Command Modes	Global configuration (config)
---------------	-------------------------------

Supported User Roles	network-admin
----------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

- | Usage Guidelines | <ul style="list-style-type: none"> For transmissions to occur between two ports, you must configure the same MTU size for both ports. A port drops any frames that exceed its MTU size. If you do not configure a system jumbo MTU size, it defaults to 1500 bytes. For a Layer 2 port, you can configure an MTU size as the system default of 1500 bytes or the system default jumbo MTU size of 9000 bytes. If you change the system jumbo MTU size, Layer 2 ports automatically use the system default MTU size of 1500 bytes unless you specifically configure the MTU size differently per port. |
|------------------|--|
|------------------|--|

Examples	This example shows how to configure a system-wide maximum frame size of 8000 bytes:
----------	---

```
n1000v# config t
n1000v(config)# system jumbomtu 8000
n1000v#
```

Related Commands	Command	Description
	show interface ethernet	Displays information about Ethernet interfaces, including the configured MTU size.
	show running-config	Displays the current operating configuration, which includes the system jumbo MTU size.

Command	Description
interface ethernet	Specifies an interface to configure and enters interface configuration mode.
mtu	Specifies the system jumbo MTU size.

system redundancy role

To configure a redundancy role for the VSM, use the **system redundancy role** command. To revert to the default setting, use the **no** form of the command.

```
system redundancy role {primary | secondary | standalone}
```

```
no system redundancy role {primary | secondary | standalone}
```

Syntax Description		
	primary	Specifies the primary redundant VSM.
	secondary	Specifies the secondary redundant VSM.
	standalone	Specifies no redundant VSM.

Command Default	None
-----------------	------

Command Modes	EXEC
---------------	------

SupportedUserRoles	network-admin
--------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples	This example shows how to configure no redundant VSM: <pre>n1000v# system redundancy role standalone n1000v#</pre>
----------	---

Related Commands	Command	Description
	show system redundancy	Displays the system redundancy status.

system storage-loss

To detect and configure storage connectivity losses, use the **system storage-loss** command. To disable storage loss checking, use the **no** form of the command.

```
system storage-loss { log | reboot } [ time <interval> ]
```

```
no system storage-loss { log | reboot } [ time <interval> ]
```

Syntax Description	log	Displays a system log when storage loss is detected.
	reboot	Reloads the VSM when storage loss is detected.
	time	The time interval at which the VSM checks for storage connectivity status. The default time interval is 30 seconds.

Command Default The default time interval is 30 seconds.

Command Modes EXEC

Supported User Roles network-admin

Command History	Release	Modification
	4.2(1)SV1(5.1)	This command was introduced.

Examples This example shows how to enable storage loss detection to be performed every 50 seconds.

```
n1000v# system storage-loss log time 50
n1000v#
```

This example shows how to disable the storage loss checking:

```
n1000v# no system storage-loss
```

Related Commands	Command	Description
	show system redundancy	Displays the system redundancy status.

system switchover

To switch over to the standby supervisor, use the **system switchover** command.

system switchover

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC

SupportedUserRoles network-admin

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Examples This example shows how to switch over to the standby supervisor:

```
n1000v# system switchover
n1000v#
```

Related Commands	Command	Description
	show system redundancy	Displays the system redundancy status.

system update vem feature level

To change the software version supported on VEMs, use the **system update vem feature level** command.

```
system update vem feature level [version_number]
```

Syntax Description	<i>version_number</i> (Optional) version number index from the list above.				
Defaults	None				
Command Modes	Any				
SupportedUserRoles	network-admin				
Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0(4)SV1(2)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	4.0(4)SV1(2)	This command was introduced.
Release	Modification				
4.0(4)SV1(2)	This command was introduced.				
Examples	<p>This example shows how to change the software version supported:</p> <pre>n1000v# system update vem feature level Error : the feature level is set to the highest value possible n1000v#</pre>				
Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td><code>show system vem feature level</code></td> <td>Displays the current software release supported.</td> </tr> </tbody> </table>	Command	Description	<code>show system vem feature level</code>	Displays the current software release supported.
Command	Description				
<code>show system vem feature level</code>	Displays the current software release supported.				

system vlan

To add the system VLAN to a port profile, use the **system vlan** command. To remove the system VLAN from a port profile, use the **no** form of this command.

```
system vlan vlan-ID-list
```

```
no system vlan
```

Syntax Description	<i>vlan-ID-list</i> List of VLAN IDs, separated by commas. The allowable range is 1–3967 and 4048–4093.
---------------------------	---

Defaults	None
-----------------	------

Command Modes	Port profile configuration (config-port-prof)
----------------------	---

Supported User Roles	network-admin
-----------------------------	---------------

Command History	Release	Modification
	4.0(4)SV1(1)	This command was introduced.

Usage Guidelines	A system VLAN is used to configure and bring up physical or vEthernet ports before the Virtual Supervisor Module (VSM) has established communication with the Virtual Ethernet Module (VEM).
-------------------------	--

Examples	This example shows how to add system VLANs 260 and 261 to the port profile:
-----------------	---

```
n1000v# config t
n1000v (config)# port-profile system-uplink
n1000v(config-port-prof)# system vlan 260, 261
n1000v(config-port-prof)#
```

This example shows how to remove all system VLANs from the port profile:

```
n1000v# config t
n1000v (config)# port-profile system-uplink
n1000v(config-port-prof)# no system vlan
n1000v(config-port-prof)#
```


Related Commands	Command	Description
	vlan	Creates a VLAN and enters the VLAN configuration mode.
	show vlan all-ports	Displays the status of all VLANs and the ports that are configured on them.
	show vlan private-vlan	Displays private VLAN information.
	show vlan summary	Displays VLAN summary information.

