

Send documentation comments to nexus5kdocs@cisco.com



Cisco Nexus 5000 Series Configuration Limits

for Cisco NX-OS Release 5.0(3)N2(1)

Release Date: June 13, 2011
Part Number: OL-25324-01
Current Release: Cisco NX-OS Release 5.0(3)N2(1)

This document describes the Cisco Cisco Nexus 5000 Series switch configuration limits for Cisco NX-OS Release 5.0(3)N2(1). Use this document in combination with documents listed in the [“Related Documentation” section on page 7](#).

Contents

This document includes the following sections:

- [Introduction, page 1](#)
- [Layer 2 Topology Configuration Limits, page 2](#)
- [Layer 2 and Layer 3 Topology Configuration Limits, page 4](#)
- [Layer 2 Switching, Fibre Channel, and FCoE Topology Configuration Limits, page 6](#)
- [Related Documentation, page 7](#)
- [Obtaining Documentation and Submitting a Service Request, page 9](#)

Introduction

The Cisco Nexus 5000 Series switches include a family of line-rate, low-latency, lossless 10-Gigabit Ethernet, Cisco Data Center Ethernet, Fibre Channel over Ethernet (FCoE), and now native Fibre Channel switches for data center applications. The Cisco Nexus 5000 Series includes the Cisco Nexus 5500 Platform and the Cisco Nexus 5000 Platform.

Cisco NX-OS Software Release 5.0(3)N2(1) introduces two new Cisco Nexus 5500 Platform switches that extend the versatility of the data-center class Cisco Nexus 5000 Series switches and provide higher density, lower latency, multilayer services.



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

[Send documentation comments to nexus5kdocs@cisco.com](mailto:nexus5kdocs@cisco.com)

The Cisco Nexus 5000 Platform includes the following switches:

- Cisco Nexus 5020 switch
- Cisco Nexus 5010 switch

For information about the Cisco Nexus 5000 Series, see the *Cisco Nexus 5000 Series and Cisco Nexus 5500 Platform Hardware Installation Guide*.

Cisco Nexus 5000 Series and Cisco Nexus 5500 Platform switches have been tested for scaling purposes under the following deployment scenarios:

- Layer 2-only deployments
- Layer 2 and Layer 3 combined deployments
- Fibre Channel and FCOE deployments



Note

Verification topologies included all listed features configured to the Verified Limits simultaneously. The Maximum Limit for a given feature is the configuration limit or the hardware limit on a specific platform.

Layer 2 Topology Configuration Limits

This section describes the configuration limits in topologies that include only Layer 2 feature configurations.

[Table 1](#) shows the Layer 2 configuration limits for Cisco NX-OS Release 5.0(3)N2(1):

Table 1 Cisco NX-OS Release 5.0(3) Layer 2 Topology Configuration Limits

| Feature | Cisco Nexus 5000 Platform | | Cisco Nexus 5500 Platform | |
|------------------------------------|--------------------------------|--|--|--|
| | Verified Topology ¹ | Maximum Limits ² | Verified Topology ¹ | Maximum Limits ² |
| Active VLANs/VSANs per switch | 504 | 507 (504 when FCoE is enabled) 31 are set aside for VSANs and the remaining are for VLANs. | 4013 (31 are set aside for VSANs and the remaining are for VLANs) | 4013 (31 are set aside for VSANs and the remaining are for VLANs) |
| VLAN/VSAN ID Space | 4,013 Unreserved Space | 4,013 Unreserved Space | 4013 Unreserved Space | 4013 Unreserved Space |
| Logical Interfaces ³ | 12,000 | 12,000 | 14,500 | 14,500 |
| VLAN ACLs (VACLs) per switch | 128 (10 unique VACLs) | 1024 (128 unique VACLs) | 128 (10 unique VACLs) | 1024 (62 unique VACLs with up to 2048 ACE entries across all VACLs) |
| Port ACLs (PACLs) per switch | 576 | 576 | 1152 | 1152 |
| Member interfaces per EtherChannel | 16 | 16 | 16 | 16 |
| IGMP Snooping groups | 1,000 | 1,000 | 3,700 | 4,000 |

[Send documentation comments to nexus5kdocs@cisco.com](mailto:nexus5kdocs@cisco.com)

Table 1 Cisco NX-OS Release 5.0(3) Layer 2 Topology Configuration Limits (continued)

| Feature | Cisco Nexus 5000 Platform | | Cisco Nexus 5500 Platform | |
|---|--|--|---|--|
| | Verified Topology ¹ | Maximum Limits ² | Verified Topology ¹ | Maximum Limits ² |
| Maximum Fabric Extenders per Cisco Nexus 5000 Series or Nexus 5500 Series switch | 12 units | 12 units | 24 units | 24 units in Layer 2 mode 8 units in Layer 3 mode |
| Maximum Fabric Extenders dual-homed to a vPC Cisco Nexus 5000 Series or Nexus 5500 Series switch pair | 12 units | 12 units | 24 units | 24 units in Layer 2 mode 8 units in Layer 3 mode |
| MAC Table Size | 13,800 ⁴ | 16,000 ⁴ | 29,000 ⁵ | 32,000 ⁵ |
| Number of Switchport EtherChannels | 16 (with the combination not exceeding 16, and not more than a total of 16 ports per EtherChannel) | 16 (with the combination not exceeding 16, and not more than a total of 16 ports per EtherChannel) | 48—Nexus 5548 or Nexus 5548UP switch 96—Nexus 5596 switch | 48—Nexus 5548 or Nexus 5548UP switch 96—Nexus 5596 switch |
| Number of FEX Port channels/VPCs (across maximum number of FEXs) | 576 | 576 | 900 in FEX-active/active configuration 750 in FEX-straight through configuration | 1152 |
| SPAN Sessions | 2 active sessions 32 source VLANs as a TX source | 2 active sessions 32 source VLANs as a TX source | 2 active sessions 32 source VLANs as a TX source | 4 active sessions 32 source VLANs as a TX source |
| Configurable QoS groups (including class default) | 5 | 5 | 6 | 6 |
| No-drop qos-groups | 1 class - FCoE no-drop | 3 (including FCoE) | 1 class - FCoE no-drop | 4 |

1. Verified Topology—Indicates the verified scaling capabilities with **all listed features enabled at the same time**. The numbers listed here exceed that used by most customers in their topologies. The scale numbers listed here are not the maximum verified values if each feature is viewed in isolation.
2. Maximum Limits—Indicates the maximum scale capability tested for the corresponding feature **individually**. This number is the absolute maximum currently supported by Cisco NX-OS Release 5.0(3)N2(1) software for the corresponding feature. If the hardware is capable of a higher scale, future software releases may increase this maximum limit.
3. Logical interfaces are a product of the number of VLANs times the number of ports. This parameter reflects the load of handling port programming, and is not dependent on the spanning-tree mode or configuration.
4. 2,200 entries are reserved multicast MAC addresses. The usable limit for unicast MAC addresses is 13,800.
5. 4,000 entries are reserved multicast MAC addresses; 25,000 entries are reserved unicast entries.

[Send documentation comments to nexus5kdocs@cisco.com](mailto:nexus5kdocs@cisco.com)

Layer 2 and Layer 3 Topology Configuration Limits

Table 2 shows the configuration limits when using a Layer 3 module (N55-D160L3, N55-M160L3) on the Cisco Nexus 5500 Platform switch with Cisco NX-OS Release 5.0(3)N2(1):

Table 2 Cisco NX-OS Release 5.0(3) Layer 2 and Layer 3 Configuration Limits

| Feature | Cisco Nexus 5500 Platform | |
|---|--|--|
| | Verified Topology ¹ | Maximum Limits ² |
| Active VLANs/VSANs per switch | 4,013 (31 are reserved for VSANs and the remaining are for VLANs) | 4,013 (31 are reserved for VSANs and the remaining are for VLANs) |
| VLAN/VSAN ID Space | 4,013 Unreserved Space | 4,013 Unreserved Space |
| Logical Interfaces ³ | 10,000 | 10,000 |
| Member interfaces per EtherChannel | 16 | 16 |
| IGMP Snooping groups | 3,400 | 4,000 |
| Maximum Fabric Extenders per Cisco Nexus 5000 Series or Nexus 5500 Series switch | 16 | 16 |
| Maximum Fabric Extenders dual-homed to a vPC Cisco Nexus 5000 Series or Nexus 5500 Platform switch pair | 16 per Nexus 5000 Series switch | 16 per Nexus 5000 Series switch |
| MAC table size | 27,400 ⁴ | 32,000 ⁴ |
| Number of Switchport EtherChannels | 48—Nexus 5548P and Nexus 5548UP switch 96—Nexus 5596UP switch | 48—Nexus 5548P and Nexus 5548UP switch 96—Nexus 5596UP switch |
| Number of FEX port channels/vPCs (across the maximum number of FEXs) | 512 | 768 |
| SPAN Sessions | 2 active sessions 32 source VLANs as a TX source | 4 active sessions 32 source VLANs as a TX source |
| Configurable QoS groups (including class default) | 6 | 6 |
| No-drop qos-groups | 1 class - FCoE no-drop | 4 |
| Layer 3 Configuration Limits | | |
| BGP | 7,200 ⁵ | 8,000 |
| RIP | 7,200 ⁵ | 8,000 |
| Multicast routes | 2,000 | 2,000 |
| RACLs | 62 Ingress RACLs with up to 1664 ACE entries across all the RACLs | 62 Ingress RACLs with up to 1664 ACE entries across all the RACLs |

Send documentation comments to nexus5kdocs@cisco.com

Table 2 Cisco NX-OS Release 5.0(3) Layer 2 and Layer 3 Configuration Limits (continued)

| Feature | Cisco Nexus 5500 Platform | |
|-----------------------|--------------------------------|-----------------------------|
| | Verified Topology ¹ | Maximum Limits ² |
| VRFs | 25 | 1,000 |
| Layer 3 Subinterfaces | 100 | 100 |
| ARPs | 6,500 ⁶ | 8,000 |

1. Verified Topology—Indicates the verified scaling capabilities with **all listed features enabled at the same time**. The numbers listed here exceed that used by most customers in their topologies. The scale numbers listed here are not the maximum verified values if each feature is viewed in isolation.
2. Maximum Limits—Indicates the maximum scale capability tested for the corresponding feature **individually**. This number is the absolute maximum currently supported by Cisco NX-OS Release 5.0(3)N2(1) software for the corresponding feature. If the hardware is capable of a higher scale, future software releases may increase this maximum limit.
3. Logical interfaces are a product of the number of VLANs times the number of ports. This parameter reflects the load of handling port programming, and is not dependent on the spanning-tree mode or configuration.
4. 24,000 entries are reserved for unicast MAC entries and 3,400 entries are reserved for IGMP groups.
5. 7,200 is the maximum number of dynamic routes supported regardless of protocol.
6. The maximum LPM entries plus ARP entries plus SVI route entries is 12,000 entries.

[Send documentation comments to nexus5kdocs@cisco.com](mailto:nexus5kdocs@cisco.com)

Layer 2 Switching, Fibre Channel, and FCoE Topology Configuration Limits

Table 3 shows the configuration limits in topologies that include Layer 2 switching, Fibre Channel, and FCoE configurations.

Table 3 Cisco NX-OS Release 5.0(3) Layer 2 Switching, Fibre Channel, and FCoE Configuration Limits

| Feature | Cisco Nexus 5000 Platform | | Cisco Nexus 5500 Platform | |
|--|---|---|---|---|
| | Verified Topology ¹ | Maximum Limits ² | Verified Topology ¹ | Maximum Limits ² |
| Active VLANs/VSANs per switch | 504 | 507 (504 when FCoE is enabled) 31 are reserved for VSANs and the remaining are for VLANs. | 512 | 4,013 (31 are reserved for VSANs and the remaining are for VLANs) |
| VLAN/VSAN ID space | 4,013 unreserved space | 4,013 unreserved space | 4,013 unreserved space | 4,013 unreserved space |
| Logical interfaces ³ | 12,000 | 12,000 | 12,000 | 14,500 |
| IGMP groups | 1,000 | 1,000 | 1,000 | 4,000 |
| Maximum Fabric Extenders per Cisco Nexus 5000 Series or Nexus 5500 Platform switch | 5 | 12 | 5 | 24 |
| MAC table size | 14,000 ⁴ | 16,000 ⁴ | 14,000 ⁴ | 32,000 ⁴ |
| Number of Switchport EtherChannels | 8 | 16 (with the combination not exceeding 16, and not more than a total of 16 ports per EtherChannels) | 8 | 48—Nexus 5548P and Nexus 5548UP switch 96—Nexus 5596UP switch |
| SPAN Sessions | 2 active sessions 32 source VLANs as a TX source | 2 active sessions 32 source VLANs as a TX source | 2 active sessions 32 source VLANs as a TX source | 4 active sessions 32 source VLANs as a TX source |
| Configurable QoS groups (including class default) | 2 | 5 | 2 | 6 |
| No-drop qos-groups | 1 - FCoE | 3 (including FCoE) | 1 - FCoE | 4 |
| Native FC links per switch | 16 | 16 | 8 on N5548 | 8—Nexus 5548 switch 48—Nexus 5548UP switch 96—Nexus 5596UP switch |
| FLOGIs or FDISCs per NPV port group | 106 | 255 | 106 | 255 |
| Zones per virtual or physical F port (includes all VSANs) | 32 | 32 | 32 | 32 |

Send documentation comments to nexus5kdocs@cisco.com

Table 3 Cisco NX-OS Release 5.0(3) Layer 2 Switching, Fibre Channel, and FCoE Configuration Limits (continued)

| Feature | Cisco Nexus 5000 Platform | | Cisco Nexus 5500 Platform | |
|---|--------------------------------|-----------------------------|--------------------------------|---|
| | Verified Topology ¹ | Maximum Limits ² | Verified Topology ¹ | Maximum Limits ² |
| Zone sets per switch (includes all VSANs) | 32 | 500 | 32 | 500 |
| Zone members per physical fabric (includes all VSANs) | 1,280 | 8,000 | 1,280 | 8,000 |
| Zones per switch (includes all VSANs) | 640 | 8,000 | 640 | 8,000 |
| Maximum diameter of a SAN Fabric | 7 | 12 | 7 | 12 |
| FSPF interface instances per switch | 192 | 512 | 192 | 256—Nexus 5548 switch 1,536—Nexus 5548UP switch 3,072—Nexus 5596UP switch |
| ISL instances per switch | 6 | 16 | 6 | 8—Nexus 5548 switch 48—Nexus 5548UP switch 96—Nexus 5596UP switch |
| Virtual Fibre Channel interfaces | 160 | 160 | 160 | 160 |
| Max FCIDs allocated | 320 | 2,048 | 320 | 2,048 |
| Fibre Channel Flows | 32 | 32 | 32 | 32 |
| SAN port channels | - | - | 4 | 4 |

1. Verified Topology—Indicates the verified scaling capabilities with **all listed features enabled at the same time**. The numbers listed here exceed that used by most customers in their topologies. The scale numbers listed here are not the maximum verified values if each feature is viewed in isolation.
2. Maximum Limits—Indicates the maximum scale capability tested for the corresponding feature **individually**. This number is the absolute maximum currently supported by Cisco NX-OS Release 5.0(3)N2(1) software for the corresponding feature. If the hardware is capable of a higher scale, future software releases may increase this maximum limit.
3. Logical interfaces are a product of the number of VLANs times the number of ports. This parameter reflects the load of handling port programming, and is not dependent on the spanning-tree mode or configuration.
4. 24,000 entries are reserved for unicast MAC entries and 3,400 entries are reserved for IGMP groups.

Related Documentation

Documentation for Cisco Nexus 5000 Series Switches and Cisco Nexus 2000 Series Fabric Extenders is available at the following URL:

http://www.cisco.com/en/US/products/ps9670/tsd_products_support_series_home.html

The following are related Cisco Nexus 5000 Series and Cisco Nexus 2000 Series Fabric Extender documents:

[Send documentation comments to nexus5kdocs@cisco.com](mailto:nexus5kdocs@cisco.com)

Release Notes

Cisco Nexus 5000 Series and Cisco Nexus 2000 Series Release Notes

Cisco Nexus 5000 Series Switch Release Notes

Configuration Guides

Cisco Nexus 5000 Series Configuration Limits for Cisco NX-OS Release 5.0(3)N1(1)

Cisco Nexus 5000 Series Configuration Limits for Cisco NX-OS Release 5.0(2)N1(1)

Cisco Nexus 5000 Series Configuration Limits for Cisco NX-OS Release 4.2(1)N1(1) and Release 4.2(1)N2(1)

Cisco Nexus 5000 Series NX-OS Fibre Channel over Ethernet Configuration Guide

Cisco Nexus 5000 Series NX-OS Layer 2 Switching Configuration Guide

Cisco Nexus 5000 Series NX-OS Multicast Routing Configuration Guide

Cisco Nexus 5000 Series NX-OS Quality of Service Configuration Guide

Cisco Nexus 5000 Series NX-OS SAN Switching Configuration Guide

Cisco Nexus 5000 Series NX-OS Security Configuration Guide

Cisco Nexus 5000 Series NX-OS System Management Configuration Guide

Cisco Nexus 5000 Series NX-OS Unicast Routing Configuration Guide

Cisco Nexus 5000 Series Switch NX-OS Software Configuration Guide

Cisco Nexus 5000 Series Fabric Manager Configuration Guide, Release 3.4(1a)

Cisco Nexus 7000 Series NX-OS Fundamentals Configuration Guide, Release 4.2

Cisco Nexus 2000 Series Fabric Extender Software Configuration Guide

Maintain and Operate Guides

Cisco Nexus 5000 Series NX-OS Operations Guide

Installation and Upgrade Guides

Cisco Nexus 5000 Series and Cisco Nexus 5500 Platform Hardware Installation Guide

Cisco Nexus 2000 Series Hardware Installation Guide

Cisco Nexus 5000 Series NX-OS Software Upgrade and Downgrade Guide, Release 4.2(1)N1(1)

Regulatory Compliance and Safety Information for the Cisco Nexus 5000 Series Switches and Cisco Nexus 2000 Series Fabric Extenders

Licensing Guide

Cisco NX-OS Licensing Guide

Send documentation comments to nexus5kdocs@cisco.com

Command References

Cisco Nexus 5000 Series Command Reference

Technical References

Cisco Nexus 5000 Series and Cisco Nexus 2000 Series Fabric Extender MIBs Reference

Error and System Messages

Cisco NX-OS System Messages Reference

Troubleshooting Guide

Cisco Nexus 5000 Troubleshooting Guide

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see *What's New in Cisco Product Documentation* at: <http://www.cisco.com/c/en/us/td/docs/general/whatsnew/whatsnew.html>.

Subscribe to *What's New in Cisco Product Documentation*, which lists all new and revised Cisco technical documentation as an RSS feed and delivers content directly to your desktop using a reader application. The RSS feeds are a free service.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

©2011 Cisco Systems, Inc. All rights reserved.

Send documentation comments to nexus5kdocs@cisco.com