



# Service Registry Faults

---

**First Published:** July 23, 2014  
**Last Updated:** July 23, 2014

## **fltExtpolProviderProviderLostConnectivity**

**Fault Code:** F10000190

### **Message**

Service provider ([capability], [ip], [ipv6]) lost connectivity

### **Explanation**

This provider is not reachable from UCS Central registry. This fault typically occurs if the provider process has crashed or too busy to respond to heartbeat message sent by registry.

### **Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** In the Cisco UCS Central CLI, check the provider process state through **show pmon state in local-mgmt** shell. You can check the same information through GUI from **Administrator** in UCS Central.
  - Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### **Fault Details**

```
Severity: critical  
Cause: provider-lost-connectivity  
mibFaultCode: 10000190  
mibFaultName: fltExtpolProviderProviderLostConnectivity  
moClass: extpol:Provider  
Type: network  
Auto Cleared: true  
Affected MO: extpol/reg/providers/prov-[type]
```

## **fltExtpolControllerControllerLostConnectivity**

**Fault Code:** F10000191

### **Message**

Management controller ([capability], [ip], [ipv6]) lost connectivity

**Explanation**

This controller is not reachable from UCS Central registry. This fault typically occurs if the controller process has crashed or too busy to respond to heartbeat message sent by registry.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** In the Cisco UCS Central CLI, check the provider process state through **show pmon state in local-mgmt** shell. You can check the same information through GUI from **Administrator** in UCS Central.
  - Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

**Fault Details**

```
Severity: critical
Cause: controller-lost-connectivity
mibFaultCode: 10000191
mibFaultName: fltExtpolControllerControllerLostConnectivity
moClass: extpol:Controller
Type: network
Auto Cleared: true
Affected MO: extpol/reg/controllers/contro-[id]
```

**fltExtpolClientClientLostConnectivity**

**Fault Code: F10000192**

**Message**

Managed endpoint ([capability], [ip], [ipv6]) lost connectivity

**Explanation**

This registered UCS Domain is not reachable from UCS Central registry. This fault typically occurs if the UCS Domain has lost network access or UCS Domain DME process has crashed or too busy to respond to heartbeat message sent by registry.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** In the Cisco UCS Central CLI, check the client process state through **show clients detail in service-reg** shell. You can check the same information through GUI from **Administrator** in UCS Central.
  - Step 2** Check the network connectivity from UCS domain to UCS Central. Also check, if UCSM is busy processing a bulkier, lengthy transaction.
  - Step 3** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

**Fault Details**

```
Severity: major
Cause: client-lost-connectivity
mibFaultCode: 10000192
mibFaultName: fltExtpolClientClientLostConnectivity
moClass: extpol:Client
Type: network
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolRegistryServiceRegistryVersionMismatch

**Fault Code:** F10000193

### Message

Service Registry ([capability], [ip], [ipv6]) software version is not compatible

### Explanation

UCS Central registry is not running the compatible version in the package.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Upgrade to a valid UCS Central package or contact Cisco TAC.

### Fault Details

**Severity:** critical  
**Cause:** service-registry-version-mismatch  
**mibFaultCode:** 10000193  
**mibFaultName:** fltExtpolRegistryServiceRegistryVersionMismatch  
**moClass:** extpol:Registry  
**Type:** network  
**Auto Cleared:** true  
**Affected MO:** extpol/reg

## fltExtpolProviderProviderVersionMismatch

**Fault Code:** F10000194

### Message

Service provider ([capability], [ip], [ipv6]) software version is not compatible

### Explanation

UCS Central provider is not running the compatible version in the package.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Upgrade to a valid UCS Central package or contact Cisco TAC.

### Fault Details

**Severity:** critical  
**Cause:** provider-version-mismatch  
**mibFaultCode:** 10000194  
**mibFaultName:** fltExtpolProviderProviderVersionMismatch  
**moClass:** extpol:Provider  
**Type:** network  
**Auto Cleared:** true  
**Affected MO:** extpol/reg/providers/prov-[type]

## fltExtpolControllerControllerVersionMismatch

**Fault Code:** F10000195

**Message**

Management controller ([capability], [ip], [ipv6]) software version is not compatible

**Explanation**

UCS Central controller is not running the compatible version in the package.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** Upgrade to a valid UCS Central package or contact Cisco TAC.

**Fault Details**

**Severity:** critical  
**Cause:** controller-version-mismatch  
**mibFaultCode:** 10000195  
**mibFaultName:** fltExtpolControllerControllerVersionMismatch  
**moClass:** extpol:Controller  
**Type:** network  
**Auto Cleared:** true  
**Affected MO:** extpol/reg/controllers/contro-[id]

## fltExtpolClientClientVersionMismatch

**Fault Code:** F10000196

**Message**

Managed endpoint ([capability], [ip], [ipv6]) software version is not compatible

**Explanation**

UCS Domain is not running the compatible software version to UCS Central.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** Upgrade UCS Domain to a compatible version, in order to get it registered with UCS Central.

**Fault Details**

**Severity:** critical  
**Cause:** client-version-mismatch  
**mibFaultCode:** 10000196  
**mibFaultName:** fltExtpolClientClientVersionMismatch  
**moClass:** extpol:Client  
**Type:** network  
**Auto Cleared:** true  
**Affected MO:** extpol/reg/clients/client-[id]

## fltCommSvcEpCommSvcNotDeployed

**Fault Code:** F10000339

### Message

Communication Service configuration can't be deployed. Error: [configStatusMessage]

### Explanation

This fault typically occurs because Cisco UCS Manager has detected an invalid communication policy configuration.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Verify that ports configured across all communication services is unique.

### Fault Details

**Severity:** major  
**Cause:** comm-svc-config-error  
**mibFaultCode:** 10000339  
**mibFaultName:** fltCommSvcEpCommSvcNotDeployed  
**moClass:** comm:SvcEp  
**Type:** comm-svc-not-deployed  
**Auto Cleared:** true  
**Affected MO:** sys/svc-ext

## fltLicenseInstanceGracePeriodWarning1

**Fault Code:** F10000362

### Message

license for feature [feature] on UCS Central [scope] has entered into the grace period.

### Explanation

At least one UCS domain is registered with UCS Central without having a license. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under license scope from **service-reg** session.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

**Severity:** warning  
**Cause:** license-graceperiod-entered

```

mibFaultCode: 10000362
mibFaultName: fltLicenseInstanceGracePeriodWarning1
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]

```

## fltLicenseInstanceGracePeriodWarning2

**Fault Code:** F10000363

### Message

license for feature [feature] on UCS Central [scope] is running in the grace period for more than 10 days

### Explanation

At least one UCS domain is registered with UCS Central without having a license. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
  - Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

```

Severity: warning
Cause: license-graceperiod-10days
mibFaultCode: 10000363
mibFaultName: fltLicenseInstanceGracePeriodWarning2
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]

```

## fltLicenseInstanceGracePeriodWarning3

**Fault Code:** F10000364

### Message

license for feature [feature] on UCS Central [scope] is running in the grace period for more than 30 days

### Explanation

At least one UCS Domain with UCS Central has been running in the grace period for more than 30 days. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 120 days.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Manager GUI, you can access the licensing information from the Admin tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

**Fault Details**

```
Severity: warning
Cause: license-graceperiod-30days
mibFaultCode: 10000364
mibFaultName: fltLicenseInstanceGracePeriodWarning3
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]
```

**fltLicenseInstanceGracePeriodWarning4**

**Fault Code: F10000365**

**Message**

license for feature [feature] on UCS Central [scope] is running in the grace period for more than 60 days

**Explanation**

At least one UCS Domain with UCS Central has been running in the grace period for more than 60 days. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 60 days.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

**Fault Details**

```
Severity: warning
Cause: license-graceperiod-60days
mibFaultCode: 10000365
mibFaultName: fltLicenseInstanceGracePeriodWarning4
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]
```

## fltLicenseInstanceGracePeriodWarning5

**Fault Code:** F10000366

### Message

license for feature [feature] on UCS Central [scope] is running in the grace period for more than 90 days

### Explanation

At least one UCS Domain with UCS Central has been running in the grace period for more than 90 days. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 90 days.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed by UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

```
Severity: major
Cause: license-graceperiod-90days
mibFaultCode: 10000366
mibFaultName: fltLicenseInstanceGracePeriodWarning5
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]
```

## fltLicenseInstanceGracePeriodWarning6

**Fault Code:** F10000367

### Message

license for feature [feature] on UCS Central [scope] is running in the grace period for more than 119 days

### Explanation

At least one UCS Domain with UCS Central has been running in the grace period for more than 119 days. This fault typically occurs if one or more UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 119 days.

### Recommended Action

If you see this fault, take the following actions:



- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

#### Fault Details

```
Severity: critical
Cause: license-graceperiod-119days
mibFaultCode: 10000367
mibFaultName: fltLicenseInstanceGracePeriodWarning6
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]
```

## fltLicenseInstanceGracePeriodWarning7

**Fault Code: F10000368**

#### Message

Grace period for feature [feature] on UCS Central [scope] is expired. Please acquire a license for the same.

#### Explanation

At least one UCS Domain with UCS Central has been running in the grace period for more than 120 days. UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 120 days. At this stage, the system licensing state is set to expired.

#### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Admin tab for UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** Disable the unlicensed UCS Domains to bring the number of enabled Domains down to the number of total licenses.
- Step 3** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC immediately to procure more licenses.

#### Fault Details

```
Severity: critical
Cause: license-graceperiod-expired
mibFaultCode: 10000368
mibFaultName: fltLicenseInstanceGracePeriodWarning7
moClass: license:Instance
Type: management
Auto Cleared: true
Affected MO: sys/license/feature-[name]-[vendor]-[version]/inst-[scope]
```

## fltLicenseFileBadLicenseFile

**Fault Code:** F1000369

### Message

license file [name] on UCS Central [scope] can not be installed

### Explanation

The installation of a license file on UCS Central failed. This fault typically occurs if the license file is badly formatted or its host ID does not match that of the UCS Domain.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** In the Cisco UCS Central CLI, check the host IDs for UCS Domains. You can access the host ID information by entering the **show server-host-id detail** command under the license scope.
- Step 2** Match the host IDs with the contents of the license file. If the host ID matches that of one of the UCS Domain, create a **show tech-support** file and contact Cisco TAC. If it does not match, contact Cisco TAC to obtain the correct license File.

### Fault Details

```
Severity: critical
Cause: license-file-uninstallable
mibFaultCode: 10000369
mibFaultName: fltLicenseFileBadLicenseFile
moClass: license:File
Type: management
Auto Cleared: false
Affected MO: sys/license/file-[scope]:[id]
```

## fltLicenseFileFileNotDeleted

**Fault Code:** F1000370

### Message

license file [name] from UCS Central [scope] could not be deleted

### Explanation

The deletion of a license file on UCS Central has failed. This fault typically occurs if license framework is not able to delete a file.

### Recommended Action

If you see this fault, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

```
Severity: critical
Cause: license-file-not-deleted
mibFaultCode: 10000370
mibFaultName: fltLicenseFileFileNotDeleted
moClass: license:File
Type: management
```

```
Auto Cleared: false
Affected MO: sys/license/file-[scope]:[id]
```

## fltExtpolClientGracePeriodWarning

**Fault Code:** F10000372

### Message

UCS domain [name] registered with UCS Central has entered into the grace period.

### Explanation

A UCS domain is registered with UCS Central without having a license. This fault typically occurs if this UCS domain is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under license scope from **service-reg** session.
  - Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

```
Severity: warning
Cause: license-graceperiod-entered
mibFaultCode: 10000372
mibFaultName: fltExtpolClientGracePeriodWarning
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning2

**Fault Code:** F10000373

### Message

UCS Domain [name] registered with UCS Central is running in the grace period for more than 10 days

### Explanation

This UCS domain is registered with UCS Central without having a license. This fault typically occurs if this UCS domain is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

#### Fault Details

```
Severity: warning
Cause: license-graceperiod-10days
mibFaultCode: 10000373
mibFaultName: fltExtpolClientGracePeriodWarning2
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning3

**Fault Code: F10000374**

#### Message

UCS Domain [name] registered with UCS Central is running in the grace period for more than 30 days

#### Explanation

This UCS Domain registered with UCS Central has been running in the grace period for more than 30 days. This fault typically occurs if this UCS domain is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 120 days.

#### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Manager GUI, you can access the licensing information from the Operations Management tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

#### Fault Details

```
Severity: warning
Cause: license-graceperiod-30days
mibFaultCode: 10000374
mibFaultName: fltExtpolClientGracePeriodWarning3
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning4

**Fault Code:** F1000375

### Message

UCS Domain [name] registered with UCS Central is running in the grace period for more than 60 days

### Explanation

This UCS Domain registered with UCS Central has been running in the grace period for more than 60 days. This fault typically occurs if this UCS domain is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 60 days.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

### Fault Details

```
Severity: warning
Cause: license-graceperiod-60days
mibFaultCode: 10000375
mibFaultName: fltExtpolClientGracePeriodWarning4
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning5

**Fault Code:** F1000376

### Message

UCS Domain [name] registered with UCS Central is running in the grace period for more than 90 days

### Explanation

This UCS Domain registered with UCS Central has been running in the grace period for more than 90 days. This fault typically occurs if this UCS domains is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 90 days.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed by UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for the UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

#### Fault Details

```
Severity: major
Cause: license-graceperiod-90days
mibFaultCode: 10000376
mibFaultName: fltExtpolClientGracePeriodWarning5
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning6

**Fault Code: F10000377**

#### Message

UCS Domain [name] registered with UCS Central is running in the grace period for more than 119 days

#### Explanation

This UCS Domain registered with UCS Central has been running in the grace period for more than 119 days. This fault typically occurs if this UCS domain is registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 119 days.

#### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

#### Fault Details

```
Severity: critical
Cause: license-graceperiod-119days
mibFaultCode: 10000377
mibFaultName: fltExtpolClientGracePeriodWarning6
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning7

**Fault Code:** F1000378

### Message

Grace period for UCS Domain [name] registered with UCS Central has expired. Please acquire a license for the same.

### Explanation

This UCS Domain registered with UCS Central has been running in the grace period for more than 120 days. UCS domains are registered with UCS Central after all default (and procured) licenses are assigned to other UCS domains and the unlicensed UCS Domains have been running for more than 120 days. At this stage, the system licensing state is set to expired.

### Recommended Action

If you see this fault, take the following actions:

- 
- Step 1** Check the number of licenses installed and consumed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
  - Step 2** Disable the unlicensed UCS Domains to bring the number of enabled Domains down to the number of total licenses.
  - Step 3** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC immediately to procure more licenses.

### Fault Details

```
Severity: critical
Cause: license-graceperiod-expired
mibFaultCode: 10000378
mibFaultName: fltExtpolClientGracePeriodWarning7
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltExtpolClientGracePeriodWarning1

**Fault Code:** F1000379

### Message

UCS Domain [name] is registered with UCS Central without a valid license.

### Explanation

This UCS domain is registered with UCS Central without having a license. This fault typically occurs if this UCS domain is registered with UCS Central without the initial activation license and after all default licenses are assigned to other UCS domains.

### Recommended Action

If you see this fault, take the following actions:

- Step 1** Check if the initial activation license is installed on UCS Central. In the Cisco UCS Central GUI, you can access the licensing information from the Operations Management tab for UCS Central. In the Cisco UCS Central CLI, you can access the licensing information by entering the **show usage detail** command under the license scope.
- Step 2** Disable the unlicensed UCS Domains to bring the number of enabled Domains down to the number of total licenses.
- Step 3** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC immediately to procure more licenses.

#### Fault Details

```
Severity: critical
Cause: license-insufficient
mibFaultCode: 10000379
mibFaultName: fltExtpolClientGracePeriodWarning1
moClass: extpol:Client
Type: management
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```

## fltPkiTPStatus

**Fault Code: F10000591**

#### Message

[name] Trustpoint's cert-chain is invalid, reason: [certStatus].

#### Explanation

This fault occurs when certificate status of TrustPoint has become invalid.

#### Recommended Action

None set.

#### Fault Details

```
Severity: major
Cause: invalid-trustpoint-cert-chain
mibFaultCode: 10000591
mibFaultName: fltPkiTPStatus
moClass: pki:TP
Type: security
Auto Cleared: true
Affected MO: sys/pki-ext/tp-[name]
```

## fltPkiKeyRingStatus

**Fault Code: F10000592**

#### Message

[name] Keyring's certificate is invalid, reason: [certStatus].



**Explanation**

This fault occurs when certificate status of Keyring has become invalid.

**Recommended Action**

None set.

**Fault Details**

```
Severity: major
Cause: invalid-keyring-certificate
mibFaultCode: 10000592
mibFaultName: fltPkiKeyRingStatus
moClass: pki:KeyRing
Type: security
Auto Cleared: true
Affected MO: sys/pki-ext/keyring-[name]
```

**fltExtpolClientClientNotReachable**

**Fault Code: F10000644**

**Message**

Managed endpoint ([capability], [ip], [ipv6]) is not reachable

**Explanation**

This registered UCS Domain is not reachable from UCS Central registry. This fault typically occurs if the UCS Domain has lost network access.

**Recommended Action**

If you see this fault, take the following actions:

- 
- Step 1** In the Cisco UCS Central CLI, check the client process state through **show clients detail** in **service-reg** shell. You can check the same information through GUI from **Administrator** in UCS Central.
  - Step 2** Check the network connectivity from UCS domain to UCS Central.
  - Step 3** If the above action did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

**Fault Details**

```
Severity: info
Cause: client-lost-connectivity
mibFaultCode: 10000644
mibFaultName: fltExtpolClientClientNotReachable
moClass: extpol:Client
Type: network
Auto Cleared: true
Affected MO: extpol/reg/clients/client-[id]
```