



Cisco Emergency Responder Version 11.5(2a) Release Notes

First Published: 2016-08-10

Last Modified: 2018-02-26

Introduction

Cisco Emergency Responder Release 11.5(2a) supports the following new features:

- **Enhanced security**—The security settings can now be enhanced for all local and remote user accounts by modifying the default policy settings either in Credential Policy or in Enhanced Security Mode Credential Policy.
- **Utils filebeat command**—This command uses the filebeat client to upload logs from the Cisco Emergency Responder server to an external logstash server.
- **Utils EnhancedSecurityMode**—This command allows you to change and check Enhanced Security Mode status on a particular node.

Requirements

Supported Hardware and Software

The information in the following sections discuss Hardware and Software requirements for Cisco Emergency Responder 11.5(2). Read these sections before you perform an upgrade.

Required Software

The following table lists required software that you must install to use Emergency Responder.

Table 1: Required Software

| Item | Supported Software Release | Description |
|--------------------------------------|---|--|
| Cisco Unified Communications Manager | <ul style="list-style-type: none"> • Cisco Unified Communications Manager 11.5(x) • Cisco Unified Communications Manager 11.0(x) • Cisco Unified Communications Manager 10.5(x) • Cisco Unified Communications Manager 10.0(x) • Cisco Unified Communications Manager 9.1(x) | The software that runs the telephony network. |
| Cisco Prime License Manager | Cisco Prime License Manager 11.5(x) | Software installed as a standalone application or on the Cisco Unified Communications Manager system, which manages the licenses for Emergency Responder Release 11.5(x) . |

| Item | Supported Software Release | Description |
|-------------|---|-------------|
| Web browser | <ul style="list-style-type: none"> • Microsoft Internet Explorer (IE) 11.0 • Microsoft Internet Explorer (IE) 10.0 • Microsoft Internet Explorer (IE) 9.0 • Microsoft Internet Explorer (IE) 8.0 • Chrome • Mozilla Firefox 24 • Mozilla Firefox 10.0 • Safari (On MAC) <p>Note Microsoft IE 8.0 is supported in Cisco Emergency Responder 9.0 and later when running on Microsoft Windows XP SP3 and Windows 7.</p> <p>Microsoft IE 9.0 is not supported in Windows XP.</p> | |

Recommended Software

The following table lists optional software that is recommended for use with Emergency Responder.

Table 2: Recommended Software

| Item | Minimum software release | Description |
|--------------|--------------------------|--|
| Email server | Any SMTP email server | Used to send email notifications to onsite alert (security) personnel. If you use an SMTP email paging server, personnel are paged instead of emailed. |

Supported Phones

The following table lists the different types of phones that support Emergency Responder. The support that Emergency Responder supplies differs depending on the type of phone and the type of switch port to which the phone is attached.

Table 3: Supported Phones

| Phones | Description |
|---|---|
| <p>Phones that are automatically tracked using Cisco Discovery Protocol</p> <ul style="list-style-type: none"> • Skinny Call Control Protocol (SCCP) on Cisco Unified IP Phone 8945, 8941, 7985, 7975, 7971, 7970, 7965, 7962, 7961, 7960, 7945, 7942, 7941, 7940, 7937, 7936, 7935, 7931, 7912, 7911, 7910, 7906, 6961, 6945, 6941, 6921, 6911, 6901 • Session Initiation Protocol (SIP) on Cisco Unified IP Phone 9971, 9951, 8961, 8945, 8941, 8811, 8831, 8841, 8851, 8861, 8865, 7975, 7971, 7970, 7965, 7962, 7961, 7960, 7945, 7942, 7941, 7940, 7912, 7911, 7906, 6961, 6945, 6941, 6921, 6911, 6901, 3911, 3905; Cisco IP Phone 7821, 7841, 7861; Cisco IP Video Phone E20; Cisco TelePresence EX60, EX90, and MX200; Cisco TelePresence System Quick Set C20 and Cisco TelePresence Codec C40, C60, and C90 • VXC 6215 • SPA Phones: 525G, 512G • Cisco IP Communicator • Cisco Desktop Collaboration Experience DX650, DX70, DX80 | <p>These phones do not require any special Emergency Responder configuration. However, you must enable Cisco Discovery Protocol on the switches.</p> <p>Note Although Cisco Analog Telephone Adapter (ATA) phones support Cisco Discovery Protocol and SCCP, Emergency Responder cannot automatically track them. You can add ATA phones manually and assign them to an Emergency Response Location (ERL). Emergency Responder will route calls from ATA phones based on the assigned ERL.</p> <p>Note Cisco IP Communicator can be tracked using Cisco Discovery Protocol only when it is installed with the Device ID containing the MAC address of the wired network interface and operating over a wired network interface.</p> |
| <p>Phones that you can track using IP subnet</p> <ul style="list-style-type: none"> • Cisco Unified Wireless IP Phone 7920, 7921G, 7925G, 7925G-EX, 7926G, and Cisco Cius • VXC 6215 • Cisco IP Communicator • Cisco UC Integration for Microsoft Office Communicator, Cisco UC Integration for Microsoft Lync, Cisco Jabber, Cisco Unified Personal Communicator, and third-party SIP phones • Any Cisco Unified IP Phone or third-party SIP phone that is connected to Cisco or third-party switches that are not discovered or supported by Emergency Responder | <p>To track these phones, you must configure the subnet and then assign ERLs to the configured subnets.</p> <p>Note Any IP endpoint can be tracked at call time using the IP subnet provided that the Use IP Address from Call Signaling Telephony setting is enabled.</p> |
| <p>Phones that you can manually define or track using IP subnet</p> <ul style="list-style-type: none"> • Phones that are connected to analog line gateways such as Cisco VG350 or VG224 series or ATA 180 series or ATA190 series • Any H.323 endpoints | <p>These phones are supported only if their calls are routed by Cisco Unified Communications Manager.</p> <p>Note Any IP endpoint can be tracked at call time using the IP subnet provided that the Use IP Address From Call Signaling Telephony setting is enabled.</p> |

| Phones | Description |
|--|--|
| <p>Phones supported for off-premises location confirmation and update with the Remote Worker Emergency Calling feature in Unified Communications Manager 9.0 and later</p> <ul style="list-style-type: none"> • Cisco IP Communicator • Cisco Unified IP Phone 9971, 9951, 8961, 8945, 8941, 7975, 7971, 7970, 7965, 7962, 7961, 7945, 7942, and 7941 | <p>When configured for off-premises use in Unified Communications Manager 9.0 and later, these phones provide displays for off-premises users to confirm or update their off-premises location.</p> <p>Note If the user dismisses the display before confirming or updating the location, the location can be recovered by selecting Running Applications from the Services menu or by resetting the phone.</p> |
| <p>Phones supported for Access Point based tracking with Unified Communications Manager 11.5 and later</p> <p>Cisco Unified Wireless IP Phone 7925G, 7925G-EX, 7926G</p> | <p>Wireless Access Points need to be defined in Unified Communications Manager 11.5 and later, these phones will provide their upstream infrastructure information (like BSSID) through Station Info messages to UCM. Cisco Emergency Responder through AXL Change Notification can track these phones through the associated Access Point.</p> |

Supported Voice Ready Lan Switches

The following table lists the LAN switch models that Emergency Responder supports. A LAN switch model is supported only if the SNMP System Object ID appears in this table, regardless of the LAN switch configuration or software release.



Note Emergency Responder requires SNMP Version 1, Version 2, Version 2c, or Version 3 for automatic tracking of Cisco Unified IP Phones by connected switch ports.

Table 4: Supported Voice-Ready LAN Switches

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---------------------------------|------------------|---|
| Catalyst 2940 | 2940-8TF | 1.3.6.1.4.1.9.1.542 |
| | 2940-8TT | 1.3.6.1.4.1.9.1.540 |
| Catalyst 2950 | 2950-12 | 1.3.6.1.4.1.9.1.323 |
| | 2950-24 | 1.3.6.1.4.1.9.1.324 |
| | 2950C-24 | 1.3.6.1.4.1.9.1.325 |
| | 2950G-24-EI-DC | 1.3.6.1.4.1.9.1.472 |
| | 2950S-24 | 1.3.6.1.4.1.9.1.430 |
| | 2950SX-24 | 1.3.6.1.4.1.9.1.480 |
| | 2950SX-48 | 1.3.6.1.4.1.9.1.560 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 2960 | 2960-24LT-L | 1.3.6.1.4.1.9.1.951 |
| | 2960-24PC-L | 1.3.6.1.4.1.9.1.950 |
| | 2960-24-S | 1.3.6.1.4.1.9.1.929 |
| | 2960-24TC-L | 1.3.6.1.4.1.9.1.694 |
| | 2960-24TC-S | 1.3.6.1.4.1.9.1.928 |
| | 2960-24TT-L | 1.3.6.1.4.1.9.1.716 |
| | 2960-48PST-L | 1.3.6.1.4.1.9.1.1016 |
| | 2960-48TC-L | 1.3.6.1.4.1.9.1.695 |
| | 2960-48TC-S | 1.3.6.1.4.1.9.1.927 |
| | 2960-48TT-L | 1.3.6.1.4.1.9.1.717 |
| | 2960-8TC-L | 1.3.6.1.4.1.9.1.798 |
| | 2960-8TC-S | 1.3.6.1.4.1.9.1.1006 |
| | 2960G-24TC-L | 1.3.6.1.4.1.9.1.696 |
| | 2960G-48TC-L | 1.3.6.1.4.1.9.1.697 |
| | 2960G-8TC-L | 1.3.6.1.4.1.9.1.799 |
| | 2960PD-8TT-L | 1.3.6.1.4.1.9.1.952 |
| | 2960-48PST-S | 1.3.6.1.4.1.9.1.1148 |
| | 2960-24LC-S | 1.3.6.1.4.1.9.1.1146 |
| | 2960-24PC-S | 1.3.6.1.4.1.9.1.1147 |
| | Catalyst 2960-C | 2960CPD-8PT-L |
| 2960C-8PC-L | | 1.3.6.1.4.1.9.1.1366 |
| 2960C-12PC-L | | 1.3.6.1.4.1.9.1.1367 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 2960-Plus | 2960-Plus 48PST-L | 1.3.6.1.4.1.9.1.1748 |
| | 2960-Plus 24PC- | 1.3.6.1.4.1.9.1.1749 |
| | 2960-Plus 24LC-L | 1.3.6.1.4.1.9.1.1750 |
| | 2960-Plus 48PST-S | 1.3.6.1.4.1.9.1.1753 |
| | 2960-Plus 24PC-S | 1.3.6.1.4.1.9.1.1754 |
| | 2960-Plus 24LC-S | 1.3.6.1.4.1.9.1.1755 |
| Catalyst 2960-S | 2960S Stack | 1.3.6.1.4.1.9.1.1208 |
| | 2960S-24PD-L | 1.3.6.1.4.1.9.1.1261 |
| | 2960S-24PS-L | 1.3.6.1.4.1.9.1.1265 |
| | 2960S-48FPD-L | 1.3.6.1.4.1.9.1.1258 |
| | 2960S-48FPS-L | 1.3.6.1.4.1.9.1.1263 |
| | 2960S-48LPD-L | 1.3.6.1.4.1.9.1.1259 |
| | 2960S-48LPS-L | 1.3.6.1.4.1.9.1.1264 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 2960X | Catalyst 2960X-48LPD-L | 1.3.6.1.4.1.9.1.1691 |
| | Catalyst 2960X-48TD-L | 1.3.6.1.4.1.9.1.1692 |
| | Catalyst 2960X-24TD-L | 1.3.6.1.4.1.9.1.1694 |
| | Catalyst 2960X-48FPS-L | 1.3.6.1.4.1.9.1.1695 |
| | Catalyst 2960X-48LPS-L | 1.3.6.1.4.1.9.1.1696 |
| | Catalyst 2960X-48TS-L | 1.3.6.1.4.1.9.1.1698 |
| | Catalyst 2960X-24TS-L | 1.3.6.1.4.1.9.1.1699 |
| | Catalyst 2960X-24PSK-L | 1.3.6.1.4.1.9.1.1700 |
| | Catalyst 2960X-48LPS-S | 1.3.6.1.4.1.9.1.1701 |
| | Catalyst 2960X-24PS-S | 1.3.6.1.4.1.9.1.1702 |
| | Catalyst 2960X-48TS-LL | 1.3.6.1.4.1.9.1.1703 |
| | Catalyst 2960X-24TS-LL | 1.3.6.1.4.1.9.1.1704 |
| | Catalyst 2960X-24PS-L | 1.3.6.1.4.1.9.1.1697 |
| | Catalyst 2960X-24PD-L | 1.3.6.1.4.1.9.1.1693 |
| | Catalyst 2960X-48FPD-L | 1.3.6.1.4.1.9.1.1690 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 2960XR | Catalyst 2960XR-24PD-I | 1.3.6.1.4.1.9.1.1800 |
| | Catalyst 2960XR-24TD-I | 1.3.6.1.4.1.9.1.1801 |
| | Catalyst 2960XR-48FPS-I | 1.3.6.1.4.1.9.1.1802 |
| | Catalyst 2960XR-48LPS-I | 1.3.6.1.4.1.9.1.1803 |
| | Catalyst 2960XR-48TS-I | 1.3.6.1.4.1.9.1.1804 |
| | Catalyst 2960XR-24PS-I | 1.3.6.1.4.1.9.1.1805 |
| | Catalyst 2960XR-24TS-I | 1.3.6.1.4.1.9.1.1806 |
| | Catalyst 2960XR-48FPD-L | 1.3.6.1.4.1.9.1.1807 |
| | Catalyst 2960XR-48LPD-L | 1.3.6.1.4.1.9.1.1808 |
| | Catalyst 2960XR-48PD-L | 1.3.6.1.4.1.9.1.1809 |
| | Catalyst 2960XR-24PD-L | 1.3.6.1.4.1.9.1.1810 |
| | Catalyst 2960XR-24TD-L | 1.3.6.1.4.1.9.1.1811 |
| | Catalyst 2960XR-48FPS-L | 1.3.6.1.4.1.9.1.1812 |
| | Catalyst 2960XR-48LPS-L | 1.3.6.1.4.1.9.1.1813 |
| | Catalyst 2960XR-48TS-L | 1.3.6.1.4.1.9.1.1814 |
| | Catalyst 2960XR-24PS-L | 1.3.6.1.4.1.9.1.1815 |
| | Catalyst 2960XR-24TS-L | 1.3.6.1.4.1.9.1.1816 |
| | Catalyst 2960XR-48FPD-I | 1.3.6.1.4.1.9.1.1797 |
| | Catalyst 2960XR-48LPD-I | 1.3.6.1.4.1.9.1.1798 |
| | Catalyst 2960XR-48TD-I | 1.3.6.1.4.1.9.1.1799 |
| Catalyst 2975 | 2975GS-48PS-L | 1.3.6.1.4.1.9.1.1067 |
| | 2975GS-48PS-L-Stack | 1.3.6.1.4.1.9.1.1068 |
| Catalyst 3550 | 3550-24-DC | 1.3.6.1.4.1.9.1.452 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 3560 | 3560-12PC-S | 1.3.6.1.4.1.9.1.1015 |
| | 3560-24PS | 1.3.6.1.4.1.9.1.563 |
| | 3560-24TS | 1.3.6.1.4.1.9.1.633 |
| | 3560-48PS | 1.3.6.1.4.1.9.1.564 |
| | 3560-48TS | 1.3.6.1.4.1.9.1.634 |
| | 3560-8PC | 1.3.6.1.4.1.9.1.797 |
| | 3560G-24PS | 1.3.6.1.4.1.9.1.614 |
| | 3560G-24TS | 1.3.6.1.4.1.9.1.615 |
| | 3560G-48PS | 1.3.6.1.4.1.9.1.616 |
| | 3560G-48TS | 1.3.6.1.4.1.9.1.617 |
| | 3560V2-24PS | 1.3.6.1.4.1.9.1.1021 |
| | 3560V2-48PS | 1.3.6.1.4.1.9.1.1025 |
| | 3560CX-12TC-S | 1.3.6.1.4.1.9.1.2133 |
| | 3560CX-8XPD-S | 1.3.6.1.4.1.9.1.2131 |
| | 3560CX-8PT-S | 1.3.6.1.4.1.9.1.2130 |
| Catalyst 3560-C | 3560CG-8PC-S | 1.3.6.1.4.1.9.1.1317 |
| | 3560CPD-8PT-S | 1.3.6.1.4.1.9.1.1368 |
| | 3560C-8PC-S | 1.3.6.1.4.1.9.1.1466 |
| | 3560C-12PC-S | 1.3.6.1.4.1.9.1.1465 |
| Catalyst 3560-E | 3560E-12D | 1.3.6.1.4.1.9.1.930 |
| | 3560E-12SD | 1.3.6.1.4.1.9.1.956 |
| | 3560E-24PD | 1.3.6.1.4.1.9.1.795 |
| | 3560E-24TD | 1.3.6.1.4.1.9.1.793 |
| | 3560E-48PD | 1.3.6.1.4.1.9.1.796 |
| | 3560E-48TD | 1.3.6.1.4.1.9.1.794 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------------|--|
| Catalyst 3560-X | 3560X-24P (-L/S/E) | 1.3.6.1.4.1.9.1.1228 |
| | 3560X-48PF (-L/S/E) | 1.3.6.1.4.1.9.1.1229 |
| | 3560X-48P (-L/S/E) | 1.3.6.1.4.1.9.1.1229 |
| | 3560X-48U | 1.3.6.1.4.1.9.1.1710 |
| | 3560X-48TS | 1.3.6.1.4.1.9.1.2066 |
| | WS-C3560X-48T-S | 1.3.6.1.4.1.9.1.1227 |
| Catalyst 3650 | Catalyst C3650-24TS (-L/S/E) | 1.3.6.1.4.1.9.1.1823 |
| | Catalyst C3650-48TS (-L/S/E) | 1.3.6.1.4.1.9.1.1824 |
| | Catalyst C3650-24PS (-L/S/E) | 1.3.6.1.4.1.9.1.1825 |
| | Catalyst C3650-48PS (-L/S/E) | 1.3.6.1.4.1.9.1.1826 |
| | Catalyst C3650-24TD (-L/S/E) | 1.3.6.1.4.1.9.1.1827 |
| | Catalyst C3650-48TD (-L/S/E) | 1.3.6.1.4.1.9.1.1828 |
| | Catalyst C3650-24PD (-L/S/E) | 1.3.6.1.4.1.9.1.1829 |
| | Catalyst C3650-48PD (-L/S/E) | 1.3.6.1.4.1.9.1.1830 |
| | Catalyst C3650-Stack (-L/S/E) | 1.3.6.1.4.1.9.1.1830 |
| | Catalyst C3650-48PQ (-L/S/E) | 1.3.6.1.4.1.9.1.1881 |
| | Catalyst C3650-48TQ (-L/S/E) | 1.3.6.1.4.1.9.1.1882 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-------------------------|--|
| Catalyst 3750 | 3750 Stack | 1.3.6.1.4.1.9.1.516 |
| | 3750-24FS | 1.3.6.1.4.1.9.1.656 |
| | 3750-24PS | 1.3.6.1.4.1.9.1.536 |
| | 3750-24TS | 1.3.6.1.4.1.9.1.513 |
| | 3750-48PS | 1.3.6.1.4.1.9.1.535 |
| | 3750-48TS | 1.3.6.1.4.1.9.1.512 |
| | 3750G-12S | 1.3.6.1.4.1.9.1.530 |
| | 3750G-12S-SD | 1.3.6.1.4.1.9.1.688 |
| | 3750G-16TD | 1.3.6.1.4.1.9.1.591 |
| | 3750G-24PS | 1.3.6.1.4.1.9.1.602 |
| | 3750G-24T | 1.3.6.1.4.1.9.1.514 |
| | 3750G-24TS | 1.3.6.1.4.1.9.1.511 |
| | 3750G-24TS-1U | 1.3.6.1.4.1.9.1.624 |
| | 3750G-24WS-S25 | 1.3.6.1.4.1.9.1.778 |
| | 3750G-24WS-S50 | 1.3.6.1.4.1.9.1.779 |
| | 3750G-48PS | 1.3.6.1.4.1.9.1.603 |
| | 3750G-48TS | 1.3.6.1.4.1.9.1.604 |
| | 3750V2-24PS | 1.3.6.1.4.1.9.1.1023 |
| | 3750V2-48PS | 1.3.6.1.4.1.9.1.1027 |
| | Catalyst 3750-X | 3750X-48P (-L/E) |
| 3750X-48PF (-L/S/E) | | 1.3.6.1.4.1.9.1.1225 |
| 3750X-48P (-L/S) | | 1.3.6.1.4.1.9.1.1225 |
| 3750X-24P (-L/S/E) | | 1.3.6.1.4.1.9.1.1224 |
| Catalyst 3750 Metro | 3750-24TE-M | 1.3.6.1.4.1.9.1.574 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|-----------------------------|--|
| Catalyst 3750-E | 3750E-24PD | 1.3.6.1.4.1.9.1.792 |
| | 3750E-24TD | 1.3.6.1.4.1.9.1.789 |
| | 3750E-48PD | 1.3.6.1.4.1.9.1.791 |
| | 3750E-48TD-S | 1.3.6.1.4.1.9.1.790 |
| Catalyst 3850 | Catalyst C3850-24U (-L/S/E) | 1.3.6.1.4.1.9.1.1767 |
| | Catalyst C3850-48U (-L/S/E) | 1.3.6.1.4.1.9.1.1768 |
| | 3850-48P (-L/S/E) | 1.3.6.1.4.1.9.1.1641 |
| | 3850-24P (-L/S/E) | 1.3.6.1.4.1.9.1.1642 |
| | 3850-48T (-L/S/E) | 1.3.6.1.4.1.9.1.1643 |
| | 3850-24T (-L/S/E) | 1.3.6.1.4.1.9.1.1644 |
| | Catalyst 3850-12S-S | 1.3.6.1.4.1.9.1.1880 |
| | Catalyst 3850-12S-E | 1.3.6.1.4.1.9.1.1880 |
| | Catalyst 3850-24S-S | 1.3.6.1.4.1.9.1.1879 |
| | Catalyst 3850-24S-E | 1.3.6.1.4.1.9.1.1879 |
| | Catalyst C3850-12X48U | 1.3.6.1.4.1.9.1.1745 |
| Catalyst 4500 | 4503 | 1.3.6.1.4.1.9.5.58 |
| | 4503 | 1.3.6.1.4.1.9.1.503 |
| | 4506 | 1.3.6.1.4.1.9.5.59 |
| | 4506 | 1.3.6.1.4.1.9.1.502 |
| | 4507 | 1.3.6.1.4.1.9.1.501 |
| | 4510 | 1.3.6.1.4.1.9.1.537 |
| Catalyst 4500-E | 4503-E | 1.3.6.1.4.1.9.1.874 |
| | 4506-E | 1.3.6.1.4.1.9.1.875 |
| | 4507R-E | 1.3.6.1.4.1.9.1.876 |
| | 4510R-E | 1.3.6.1.4.1.9.1.877 |
| | 4507R+E | 1.3.6.1.4.1.9.1.1286 |
| | 4510R+E | 1.3.6.1.4.1.9.1.1287 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|------------------------------|--|
| Catalyst 4900 | 4948 | 1.3.6.1.4.1.9.1.626 |
| | 4948-10GE | 1.3.6.1.4.1.9.1.659 |
| Catalyst 6500 | 6503 | 1.3.6.1.4.1.9.5.56 |
| | 6503 | 1.3.6.1.4.1.9.1.449 |
| | 6504 | 1.3.6.1.4.1.9.1.657 |
| | 6506 | 1.3.6.1.4.1.9.5.45 |
| | 6506 | 1.3.6.1.4.1.9.1.282 |
| | 6509 | 1.3.6.1.4.1.9.5.44 |
| | 6509 | 1.3.6.1.4.1.9.1.283 |
| | 6509-NEB | 1.3.6.1.4.1.9.5.61 |
| | 6513 | 1.3.6.1.4.1.9.5.50 |
| | 6513 | 1.3.6.1.4.1.9.1.400 |
| Catalyst 6500-E | 6509-E | 1.3.6.1.4.1.9.1.283 |
| | 6506-E | 1.3.6.1.4.1.9.1.282 |
| | 6504-E | 1.3.6.1.4.1.9.1.657 |
| | 6503-E | 1.3.6.1.4.1.9.1.449 |
| Catalyst 6800ia | Catalyst 6800ia-48FPD-L | 1.3.6.1.4.1.9.1.1866 |
| | Catalyst 6800ia-48TD-L | 1.3.6.1.4.1.9.1.1867 |
| Catalyst 68xx | Catalyst 68xx Virtual Switch | 1.3.6.1.4.1.9.1.1934 |
| Catalyst 6880-X | Catalyst 6880-XLE | 1.3.6.1.4.1.9.1.1784 |
| Catalyst 6807-XL | Catalyst 6807-XL | 1.3.6.1.4.1.9.1.1765 |
| Catalyst Express 500 | 500-24LC | 1.3.6.1.4.1.9.1.725 |
| | 500-24PC | 1.3.6.1.4.1.9.1.726 |
| | 500-24TT | 1.3.6.1.4.1.9.1.724 |
| | 500G-12TC | 1.3.6.1.4.1.9.1.727 |

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---|------------------------------|--|
| Catalyst Express 520 | 520-24LC | 1.3.6.1.4.1.9.1.933 |
| | 520-24PC | 1.3.6.1.4.1.9.1.934 |
| | 520-24TT | 1.3.6.1.4.1.9.1.932 |
| | 520-8PC | 1.3.6.1.4.1.9.1.897 |
| | 520G-24TC | 1.3.6.1.4.1.9.1.935 |
| Cisco ME 4900 | ME 4924-10GE | 1.3.6.1.4.1.9.1.788 |
| Catalyst C6880x | ciscoC6880x | 1.3.6.1.4.1.9.1.1936 |
| Catalyst 3560CX | Cisco Catalyst 3560CX-8XPD-S | 1.3.6.1.4.1.9.1.2131 |
| | Cisco Catalyst 3560CX-8PT-S | 1.3.6.1.4.1.9.1.2130 |
| Catalyst C3560 | catwsC3560CX12pdS | 1.3.6.1.4.1.9.1.2132 |
| | catwsC3560CX12pcS | 1.3.6.1.4.1.9.1.2134 |
| | catwsC3560CX8tcS | 1.3.6.1.4.1.9.1.2135 |
| | catwsC3560CX8pcS | 1.3.6.1.4.1.9.1.2136 |
| Catalyst C2960 | catwsC2960CX8tcL | 1.3.6.1.4.1.9.1.2137 |
| Catalyst 2960CX | Cisco Catalyst 2960CX-8PC-L | 1.3.6.1.4.1.9.1.2191 |

Supported Cisco Routers

The following table lists the Cisco routers Emergency Responder supports.

Table 5: Supported Cisco Routers

| Series (Ethernet Ports Only) | Supported Device | System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB |
|---------------------------------|------------------------|---|
| Cisco 1800 | Cisco 1861-SRST-B/K9 | 1.3.6.1.4.1.9.1.904 |
| | Cisco 1861-SRST-C-B/K9 | 1.3.6.1.4.1.9.1.939 |
| | Cisco 1861-SRST-C-F/K9 | 1.3.6.1.4.1.9.1.940 |
| | Cisco 1861-SRST-F/K9 | 1.3.6.1.4.1.9.1.905 |
| | Cisco 1861-UC-2BRI-K9 | 1.3.6.1.4.1.9.1.902 |
| | Cisco 1861-UC-4FXO-K9 | 1.3.6.1.4.1.9.1.903 |
| | Cisco1861 | 1.3.6.1.4.1.9.1.1065 |
| Cisco 1900 | Cisco 1905 | 1.3.6.1.4.1.9.1.1192 |
| | Cisco 1921 | 1.3.6.1.4.1.9.1.1191 |
| | Cisco 1941 | 1.3.6.1.4.1.9.1.1047 |
| Cisco 2800 | Cisco 2811 | 1.3.6.1.4.1.9.1.576 |
| | Cisco 2821 | 1.3.6.1.4.1.9.1.577 |
| | Cisco 2851 | 1.3.6.1.4.1.9.1.578 |
| Cisco 2900 | Cisco 2911 | 1.3.6.1.4.1.9.1.1045 |
| | Cisco 2921 | 1.3.6.1.4.1.9.1.1044 |
| | Cisco 2951 | 1.3.6.1.4.1.9.1.1043 |
| Cisco 3800 | Cisco 3825 | 1.3.6.1.4.1.9.1.543 |
| | Cisco 3845 | 1.3.6.1.4.1.9.1.544 |
| Cisco 3900 | Cisco 3925 | 1.3.6.1.4.1.9.1.1042 |
| | Cisco 3925E | 1.3.6.1.4.1.9.1.1144 |
| | Cisco 3945 | 1.3.6.1.4.1.9.1.1041 |
| | Cisco 3945E | 1.3.6.1.4.1.9.1.1145 |

Supported Switch Modules and Network Modules

Emergency Responder supports the following switch modules and network modules.

Table 6: Supported Switch Modules and Network Modules

| Switch Modules and Network Modules | System Object ID from CISCO-PRODUCTS-MIB |
|------------------------------------|--|
| Cisco SM-ES2-16-P | 1.3.6.1.4.1.9.1.1048 |
| Cisco SM-ES3-16-P | 1.3.6.1.4.1.9.1.1049 |
| Cisco SM-ES3G-16-P | 1.3.6.1.4.1.9.1.1050 |
| Cisco SM-ES2-24-P | 1.3.6.1.4.1.9.1.1052 |
| Cisco SM-ES3-24-P | 1.3.6.1.4.1.9.1.1053 |
| Cisco SM-ES3G-24-P | 1.3.6.1.4.1.9.1.1054 |
| Cisco SM-D-ES3-48-P | 1.3.6.1.4.1.9.1.1056 |
| Cisco SM-D-ES3G-48-P | 1.3.6.1.4.1.9.1.1057 |
| NME-16ES-1G | 1.3.6.1.4.1.9.1.702 |
| NME-16ES-1G-P | 1.3.6.1.4.1.9.1.663 |
| NME-X-23ES-1G | 1.3.6.1.4.1.9.1.703 |
| NME-X-23ES-1G-P | 1.3.6.1.4.1.9.1.664 |
| NME-XD-24ES-2S-P | 1.3.6.1.4.1.9.1.665 |
| NME-XD-48ES-2S-P | 1.3.6.1.4.1.9.1.666 |



Note Switch modules and network modules use the System Object IDs of the routers into which they are inserted. Support for ISR-G2 SM and NM requires installation of the Cisco Options Package (COP) file. Download the COP file from the [Download Software](#) page on Cisco.com

Supported Cisco UCS Platforms

For information about supported Cisco Unified Computing System (UCS) platforms, see the [Unified Communications Virtualization Supported Applications](#) section of the Cisco documentation wiki.

VMware Support

For information about VMware, see the Unified Communications VMWare Requirements section of the Cisco documentation wiki at http://docwiki.cisco.com/wiki/Unified_Communications_VMWare_Requirements.

Supported OVAs and Capacity

For information about OVAs, administrators should see the Unified Communications Virtualization Downloads (including OVA/OVF Templates) section of the Cisco documentation wiki at [http://docwiki.cisco.com/wiki/Unified_Communications_Virtualization_Downloads_\(including_OVA/OVF_Templates\)](http://docwiki.cisco.com/wiki/Unified_Communications_Virtualization_Downloads_(including_OVA/OVF_Templates)).

Related Documentation

Cisco Emergency Responder Documentation

See the publications for Cisco Emergency Responder. Navigate from the following documentation URL:

http://www.cisco.com/en/US/products/sw/voicesw/ps842/tsd_products_support_series_home.html

Cisco Unified Communications Manager Documentation

See the *Cisco Unified Communications Manager Documentation Guide* and other publications specific to your Cisco Unified Communications Manager release. Navigate from the following URL:

http://www.cisco.com/en/US/products/sw/voicesw/ps556/tsd_products_support_series_home.html

Important Notes

Cisco Emergency Responder 11.5(x) Supported Upgrades

Cisco Emergency Responder 10.x and later is supported on Cisco Unified Computing System (UCS) and other virtual platforms only. All existing installations on Media Convergence Servers (MCS) should be migrated to UCS before upgrading to Cisco Emergency Responder 10.x or later.

Direct upgrades to Cisco Emergency Responder 11.5(x) are supported only from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 or Cisco Emergency Responder 8.7 or Cisco Emergency Responder 9.0(1) or Cisco Emergency Responder 9.0(2) or Cisco Emergency Responder 10.0(1) or Cisco Emergency Responder 10.0(2) or Cisco Emergency Responder 10.5(1) or Cisco Emergency Responder 11.0(1). All existing installations on MCS should be migrated to UCS before upgrading to Cisco Emergency Responder 11.5(x).



Note

To improve software integrity protection, Cisco Emergency Responder 11.5 has been signed with new RSA v3 keys to resolve CDET “CSCuo53520”. Cisco Emergency Responder 10.0(2) and later releases have the fix for this and when upgrading to Cisco Emergency Responder 10.5 or later, it does not require any COP file installation. Upgrade from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 or Cisco Emergency Responder 8.7 or Cisco Emergency Responder 9.0(1) or Cisco Emergency Responder 9.0(2) or Cisco Emergency Responder 10.0(1) requires the installation of RSA v3 Cisco Options Package (COP) before you upgrade to Cisco Emergency Responder 10.5 or later. For information on the COP file, see <http://www.cisco.com/web/software/282204704/18582/RSA3ver4.pdf>.

Also, when upgrading from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 it requires the installation of a Refresh Upgrade Cisco Options Package (COP) before you upgrade to Cisco Emergency Responder 10.5 or later. Upgrade to Cisco Emergency Responder 10.5 or later is a Refresh Upgrade and may require longer downtime.

Direct upgrades from Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x or Cisco Emergency Responder 8.0 to Cisco Emergency Responder 11.5(x) are not supported. Customers must first complete an upgrade to Cisco Emergency Responder 8.6.

- If existing Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x, or Cisco Emergency Responder 8.0 is installed on an MCS model that is supported by Cisco Emergency Responder 8.6 or supported through Bridge Upgrade of the system, the customer must first upgrade to Cisco Emergency Responder 8.6, then migrate to UCS or virtual platform, and then upgrade to Cisco Emergency Responder 11.5(x).

- If existing Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x or Cisco Emergency Responder 8.0 is installed on MCS, which is not supported by Cisco Emergency Responder 8.6, customer must perform a fresh installation of Cisco Emergency Responder 11.5(x).

Licensing

Cisco Prime License Manager centralizes all of the licensing for Emergency Responder 10.0 and onwards. Emergency Responder communicates the licensing requirements to Cisco Prime License Manager. Emergency Responder attempts to discover all phones on Unified Communications Manager, excluding subnets not tracked by Emergency Responder. Together with the manually configured phones, these constitute the license requirements sent by Emergency Responder to the Cisco Prime License Manager. The Cisco Prime License Manager then compares the Emergency Responder license requirements with the licenses installed and reports back license compliance or noncompliance.



Note Emergency Responder always requires its own specific licenses. It is not included in Cisco Unified Workspace Licensing (UWL) or Cisco User Connect Licensing (UCL).

For more information on Cisco Prime License Manager, see the *Cisco Prime License Manager Documentation Guide* at http://www.cisco.com/en/US/partner/products/ps13081/tsd_products_support_series_home.html.

Cisco Emergency Responder 10.5 and onwards support Licenses Management in Cisco HCS License Manager.

For more information on Cisco HCS License Manager, see the Cisco Hosted Collaboration Mediation at <http://www.cisco.com/c/en/us/support/cloud-systems-management/hosted-collaboration-mediation/tsd-products-support-series-home.html>

Caveats

This section contains information about accessing the Cisco Bug Search to find open caveats and resolved caveats.

Access Cisco Bug Search

Known problems (bugs) are graded according to severity level. These release notes contain descriptions of the following:

- All severity level 1 or 2 bugs
- Significant severity level 3 bugs

You can search for problems by using Cisco Bug Search.

Before you begin

To access Cisco Bug Search, you need the following items:

- Internet connection
- Web browser
- Cisco.com user ID and password

Procedure

-
- Step 1** To access Cisco Bug Search, go to:
<https://tools.cisco.com/bugsearch>
- Step 2** Log in with your Cisco.com user ID and password.
- Step 3** To look for information about a specific problem, enter the bug ID number in the Search for field, then press **Enter**.
-

Open Caveats

There are no known issues in this release.

Resolved Caveats

The following table lists severity 1, 2, and 3 defects that are resolved for Cisco Emergency Responder 11.5(2a).

For more information about an individual caveat, click the Identifier. You must be a registered Cisco.com user to access this online information.

Because a caveat's status continually changes, this table only reflects a snapshot of the caveats that were resolved at the time this report was compiled. For an updated view of resolved caveats, access Bug Toolkit as described in [Access Cisco Bug Search, on page 19](#).

Table 7: Resolved Caveats for Cisco Emergency Responder 11.5(2a)

| Identifier | Headline |
|----------------------------|--|
| CSCuz10828 | VMware Tools update fails on CER 10.5 and 11.0 with selinux denials. |
| CSCuz70826 | Add support for asymmetric RTP for Cisco Emergency Responder onsite alerts. |
| CSCva01951 | Cisco Emergency Responder security onsite alert emails do not support french characters. |
| CSCva90090 | Cisco Emergency Responder 11.5.2 restoration fails. |

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS Version 2.0.

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The following information is for FCC compliance of Class A devices: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case users will be required to correct the interference at their own expense.

The following information is for FCC compliance of Class B devices: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment causes interference to radio or television reception, which can be determined by turning the equipment off and on, users are encouraged to try to correct the interference by using one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Modifications to this product not authorized by Cisco could void the FCC approval and negate your authority to operate the product

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com go trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2018 Cisco Systems, Inc. All rights reserved.