



Cisco Emergency Responder Version 11.5(3) Release Notes

First Published: 2017-06-28

Last Modified: 2018-02-26

Introduction

Cisco Emergency Responder Release 11.5(3) supports the following update:

- Fixes for security vulnerabilities in Red Hat libraries.

Requirements

Supported Hardware and Software

The information in the following sections discuss Hardware and Software requirements for Cisco Emergency Responder 11.5(3). Read these sections before you perform an upgrade.

Required Software

The following table lists required software that you must install to use Emergency Responder.

Table 1: Required Software

Item	Supported Software Release	Description
Cisco Unified Communications Manager	<ul style="list-style-type: none">• Cisco Unified Communications Manager 11.5(x)• Cisco Unified Communications Manager 11.0(x)• Cisco Unified Communications Manager 10.5(x)• Cisco Unified Communications Manager 10.0(x)• Cisco Unified Communications Manager 9.1(x)	The software that runs the telephony network.

Item	Supported Software Release	Description
Cisco Prime License Manager	Cisco Prime License Manager 11.5(x)	Software installed as a standalone application or on the Cisco Unified Communications Manager system, which manages the licenses for Emergency Responder Release 11.5(x) .
Web browser	<ul style="list-style-type: none"> • Microsoft Internet Explorer (IE) 11.0 • Microsoft Internet Explorer (IE) 10.0 • Microsoft Internet Explorer (IE) 9.0 • Microsoft Internet Explorer (IE) 8.0 • Chrome • Mozilla Firefox 24 • Mozilla Firefox 10.0 • Safari (On MAC) <p>Note Microsoft IE 8.0 is supported in Cisco Emergency Responder 9.0 and later when running on Microsoft Windows XP SP3 and Windows 7.</p> <p>Microsoft IE 9.0 is not supported in Windows XP.</p>	

Recommended Software

The following table lists optional software that is recommended for use with Emergency Responder.

Table 2: Recommended Software

Item	Minimum software release	Description
Email server	Any SMTP email server	Used to send email notifications to onsite alert (security) personnel. If you use an SMTP email paging server, personnel are paged instead of emailed.

Supported Phones

The following table lists the different types of phones that support Emergency Responder. The support that Emergency Responder supplies differs depending on the type of phone and the type of switch port to which the phone is attached.

Table 3: Supported Phones

Phones	Description
<p>Phones that are automatically tracked using Cisco Discovery Protocol</p> <ul style="list-style-type: none"> • Skinny Call Control Protocol (SCCP) on Cisco Unified IP Phone 8945, 8941, 7985, 7975, 7971, 7970, 7965, 7962, 7961, 7960, 7945, 7942, 7941, 7940, 7937, 7936, 7935, 7931, 7912, 7911, 7910, 7906, 6961, 6945, 6941, 6921, 6911, 6901 • Session Initiation Protocol (SIP) on Cisco Unified IP Phone 9971, 9951, 8961, 8945, 8941, 8811, 8831, 8841, 8851, 8861, 8865, 7975, 7971, 7970, 7965, 7962, 7961, 7960, 7945, 7942, 7941, 7940, 7912, 7911, 7906, 6961, 6945, 6941, 6921, 6911, 6901, 3911, 3905; Cisco IP Phone 7821, 7841, 7861; Cisco IP Video Phone E20; Cisco TelePresence EX60, EX90, and MX200; Cisco TelePresence System Quick Set C20 and Cisco TelePresence Codec C40, C60, and C90 • VXC 6215 • SPA Phones: 525G, 512G • Cisco IP Communicator • Cisco Desktop Collaboration Experience DX650, DX70, DX80 	<p>These phones do not require any special Emergency Responder configuration. However, you must enable Cisco Discovery Protocol on the switches.</p> <p>Note Although Cisco Analog Telephone Adapter (ATA) phones support Cisco Discovery Protocol and SCCP, Emergency Responder cannot automatically track them. You can add ATA phones manually and assign them to an Emergency Response Location (ERL). Emergency Responder will route calls from ATA phones based on the assigned ERL.</p> <p>Note Cisco IP Communicator can be tracked using Cisco Discovery Protocol only when it is installed with the Device ID containing the MAC address of the wired network interface and operating over a wired network interface.</p>
<p>Phones that you can track using IP subnet</p> <ul style="list-style-type: none"> • Cisco Unified Wireless IP Phone 7920, 7921G, 7925G, 7925G-EX, 7926G, and Cisco Cius • VXC 6215 • Cisco IP Communicator • Cisco UC Integration for Microsoft Office Communicator, Cisco UC Integration for Microsoft Lync, Cisco Jabber, Cisco Unified Personal Communicator, and third-party SIP phones • Any Cisco Unified IP Phone or third-party SIP phone that is connected to Cisco or third-party switches that are not discovered or supported by Emergency Responder 	<p>To track these phones, you must configure the subnet and then assign ERLs to the configured subnets.</p> <p>Note Any IP endpoint can be tracked at call time using the IP subnet provided that the Use IP Address from Call Signaling Telephony setting is enabled.</p>

Phones	Description
Phones that you can manually define or track using IP subnet <ul style="list-style-type: none"> Phones that are connected to analog line gateways such as Cisco VG350 or VG224 series or ATA 180 series or ATA190 series Any H.323 endpoints 	These phones are supported only if their calls are routed by Cisco Unified Communications Manager. Note Any IP endpoint can be tracked at call time using the IP subnet provided that the Use IP Address From Call Signaling Telephony setting is enabled.
Phones supported for off-premises location confirmation and update with the Remote Worker Emergency Calling feature in Unified Communications Manager 9.0 and later <ul style="list-style-type: none"> Cisco IP Communicator Cisco Unified IP Phone 9971, 9951, 8961,8945, 8941, 7975, 7971, 7970, 7965, 7962, 7961, 7945, 7942, and 7941 	When configured for off-premises use in Unified Communications Manager 9.0 and later, these phones provide displays for off-premises users to confirm or update their off-premises location. Note If the user dismisses the display before confirming or updating the location, the location can be recovered by selecting Running Applications from the Services menu or by resetting the phone.
Phones supported for Access Point based tracking with Unified Communications Manager 11.5 and later Cisco Unified Wireless IP Phone 7925G, 7925G-EX, 7926G	Wireless Access Points need to be defined in Unified Communications Manager 11.5 and later, these phones will provide their upstream infrastructure information (like BSSID) through Station Info messages to UCM. Cisco Emergency Responder through AXL Change Notification can track these phones through the associated Access Point.

Supported Voice Ready Lan Switches

The following table lists the LAN switch models that Emergency Responder supports. A LAN switch model is supported only if the SNMP System Object ID appears in this table, regardless of the LAN switch configuration or software release.



Note Emergency Responder requires SNMP Version 1, Version 2, Version 2c, or Version 3 for automatic tracking of Cisco Unified IP Phones by connected switch ports.

Table 4: Supported Voice-Ready LAN Switches

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 2940	2940-8TF	1.3.6.1.4.1.9.1.542
	2940-8TT	1.3.6.1.4.1.9.1.540

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 2950	2950-12	1.3.6.1.4.1.9.1.323
	2950-24	1.3.6.1.4.1.9.1.324
	2950C-24	1.3.6.1.4.1.9.1.325
	2950G-24-EI-DC	1.3.6.1.4.1.9.1.472
	2950S-24	1.3.6.1.4.1.9.1.430
	2950SX-24	1.3.6.1.4.1.9.1.480
	2950SX-48	1.3.6.1.4.1.9.1.560
Catalyst 2960	2960-24LT-L	1.3.6.1.4.1.9.1.951
	2960-24PC-L	1.3.6.1.4.1.9.1.950
	2960-24-S	1.3.6.1.4.1.9.1.929
	2960-24TC-L	1.3.6.1.4.1.9.1.694
	2960-24TC-S	1.3.6.1.4.1.9.1.928
	2960-24TT-L	1.3.6.1.4.1.9.1.716
	2960-48PST-L	1.3.6.1.4.1.9.1.1016
	2960-48TC-L	1.3.6.1.4.1.9.1.695
	2960-48TC-S	1.3.6.1.4.1.9.1.927
	2960-48TT-L	1.3.6.1.4.1.9.1.717
	2960-8TC-L	1.3.6.1.4.1.9.1.798
	2960-8TC-S	1.3.6.1.4.1.9.1.1006
	2960G-24TC-L	1.3.6.1.4.1.9.1.696
	2960G-48TC-L	1.3.6.1.4.1.9.1.697
	2960G-8TC-L	1.3.6.1.4.1.9.1.799
	2960PD-8TT-L	1.3.6.1.4.1.9.1.952
	2960-48PST-S	1.3.6.1.4.1.9.1.1148
	2960-24LC-S	1.3.6.1.4.1.9.1.1146
	2960-24PC-S	1.3.6.1.4.1.9.1.1147

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 2960-C	2960CPD-8PT-L	1.3.6.1.4.1.9.1.1315
	2960C-8PC-L	1.3.6.1.4.1.9.1.1366
	2960C-12PC-L	1.3.6.1.4.1.9.1.1367
Catalyst 2960-Plus	2960-Plus 48PST-L	1.3.6.1.4.1.9.1.1748
	2960-Plus 24PC-	1.3.6.1.4.1.9.1.1749
	2960-Plus 24LC-L	1.3.6.1.4.1.9.1.1750
	2960-Plus 48PST-S	1.3.6.1.4.1.9.1.1753
	2960-Plus 24PC-S	1.3.6.1.4.1.9.1.1754
	2960-Plus 24LC-S	1.3.6.1.4.1.9.1.1755
Catalyst 2960-S	2960S Stack	1.3.6.1.4.1.9.1.1208
	2960S-24PD-L	1.3.6.1.4.1.9.1.1261
	2960S-24PS-L	1.3.6.1.4.1.9.1.1265
	2960S-48FPD-L	1.3.6.1.4.1.9.1.1258
	2960S-48FPS-L	1.3.6.1.4.1.9.1.1263
	2960S-48LPD-L	1.3.6.1.4.1.9.1.1259
	2960S-48LPS-L	1.3.6.1.4.1.9.1.1264

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 2960X	Catalyst 2960X-48LPD-L	1.3.6.1.4.1.9.1.1691
	Catalyst 2960X-48TD-L	1.3.6.1.4.1.9.1.1692
	Catalyst 2960X-24TD-L	1.3.6.1.4.1.9.1.1694
	Catalyst 2960X-48FPS-L	1.3.6.1.4.1.9.1.1695
	Catalyst 2960X-48LPS-L	1.3.6.1.4.1.9.1.1696
	Catalyst 2960X-48TS-L	1.3.6.1.4.1.9.1.1698
	Catalyst 2960X-24TS-L	1.3.6.1.4.1.9.1.1699
	Catalyst 2960X-24PSK-L	1.3.6.1.4.1.9.1.1700
	Catalyst 2960X-48LPS-S	1.3.6.1.4.1.9.1.1701
	Catalyst 2960X-24PS-S	1.3.6.1.4.1.9.1.1702
	Catalyst 2960X-48TS-LL	1.3.6.1.4.1.9.1.1703
	Catalyst 2960X-24TS-LL	1.3.6.1.4.1.9.1.1704
	Catalyst 2960X-24PS-L	1.3.6.1.4.1.9.1.1697
	Catalyst 2960X-24PD-L	1.3.6.1.4.1.9.1.1693
	Catalyst 2960X-48FPD-L	1.3.6.1.4.1.9.1.1690

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 2960XR	Catalyst 2960XR-24PD-I	1.3.6.1.4.1.9.1.1800
	Catalyst 2960XR-24TD-I	1.3.6.1.4.1.9.1.1801
	Catalyst 2960XR-48FPS-I	1.3.6.1.4.1.9.1.1802
	Catalyst 2960XR-48LPS-I	1.3.6.1.4.1.9.1.1803
	Catalyst 2960XR-48TS-I	1.3.6.1.4.1.9.1.1804
	Catalyst 2960XR-24PS-I	1.3.6.1.4.1.9.1.1805
	Catalyst 2960XR-24TS-I	1.3.6.1.4.1.9.1.1806
	Catalyst 2960XR-48FPD-L	1.3.6.1.4.1.9.1.1807
	Catalyst 2960XR-48LPD-L	1.3.6.1.4.1.9.1.1808
	Catalyst 2960XR-48PD-L	1.3.6.1.4.1.9.1.1809
	Catalyst 2960XR-24PD-L	1.3.6.1.4.1.9.1.1810
	Catalyst 2960XR-24TD-L	1.3.6.1.4.1.9.1.1811
	Catalyst 2960XR-48FPS-L	1.3.6.1.4.1.9.1.1812
	Catalyst 2960XR-48LPS-L	1.3.6.1.4.1.9.1.1813
	Catalyst 2960XR-48TS-L	1.3.6.1.4.1.9.1.1814
	Catalyst 2960XR-24PS-L	1.3.6.1.4.1.9.1.1815
	Catalyst 2960XR-24TS-L	1.3.6.1.4.1.9.1.1816
	Catalyst 2960XR-48FPD-I	1.3.6.1.4.1.9.1.1797
	Catalyst 2960XR-48LPD-I	1.3.6.1.4.1.9.1.1798
	Catalyst 2960XR-48TD-I	1.3.6.1.4.1.9.1.1799
Catalyst 2975	2975GS-48PS-L	1.3.6.1.4.1.9.1.1067
	2975GS-48PS-L-Stack	1.3.6.1.4.1.9.1.1068
Catalyst 3550	3550-24-DC	1.3.6.1.4.1.9.1.452

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 3560	3560-12PC-S	1.3.6.1.4.1.9.1.1015
	3560-24PS	1.3.6.1.4.1.9.1.563
	3560-24TS	1.3.6.1.4.1.9.1.633
	3560-48PS	1.3.6.1.4.1.9.1.564
	3560-48TS	1.3.6.1.4.1.9.1.634
	3560-8PC	1.3.6.1.4.1.9.1.797
	3560G-24PS	1.3.6.1.4.1.9.1.614
	3560G-24TS	1.3.6.1.4.1.9.1.615
	3560G-48PS	1.3.6.1.4.1.9.1.616
	3560G-48TS	1.3.6.1.4.1.9.1.617
	3560V2-24PS	1.3.6.1.4.1.9.1.1021
	3560V2-48PS	1.3.6.1.4.1.9.1.1025
	3560CX-12TC-S	1.3.6.1.4.1.9.1.2133
	3560CX-8XPD-S	1.3.6.1.4.1.9.1.2131
	3560CX-8PT-S	1.3.6.1.4.1.9.1.2130
Catalyst 3560-C	3560CG-8PC-S	1.3.6.1.4.1.9.1.1317
	3560CPD-8PT-S	1.3.6.1.4.1.9.1.1368
	3560C-8PC-S	1.3.6.1.4.1.9.1.1466
	3560C-12PC-S	1.3.6.1.4.1.9.1.1465
Catalyst 3560-E	3560E-12D	1.3.6.1.4.1.9.1.930
	3560E-12SD	1.3.6.1.4.1.9.1.956
	3560E-24PD	1.3.6.1.4.1.9.1.795
	3560E-24TD	1.3.6.1.4.1.9.1.793
	3560E-48PD	1.3.6.1.4.1.9.1.796
	3560E-48TD	1.3.6.1.4.1.9.1.794

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 3560-X	3560X-24P (-L/S/E)	1.3.6.1.4.1.9.1.1228
	3560X-48PF (-L/S/E)	1.3.6.1.4.1.9.1.1229
	3560X-48P (-L/S/E)	1.3.6.1.4.1.9.1.1229
	3560X-48U	1.3.6.1.4.1.9.1.1710
	3560X-48TS	1.3.6.1.4.1.9.1.2066
	WS-C3560X-48T-S	1.3.6.1.4.1.9.1.1227
Catalyst 3650	Catalyst C3650-24TS (-L/S/E)	1.3.6.1.4.1.9.1.1823
	Catalyst C3650-48TS (-L/S/E)	1.3.6.1.4.1.9.1.1824
	Catalyst C3650-24PS (-L/S/E)	1.3.6.1.4.1.9.1.1825
	Catalyst C3650-48PS (-L/S/E)	1.3.6.1.4.1.9.1.1826
	Catalyst C3650-24TD (-L/S/E)	1.3.6.1.4.1.9.1.1827
	Catalyst C3650-48TD (-L/S/E)	1.3.6.1.4.1.9.1.1828
	Catalyst C3650-24PD (-L/S/E)	1.3.6.1.4.1.9.1.1829
	Catalyst C3650-48PD (-L/S/E)	1.3.6.1.4.1.9.1.1830
	Catalyst C3650-Stack (-L/S/E)	1.3.6.1.4.1.9.1.1830
	Catalyst C3650-48PQ (-L/S/E)	1.3.6.1.4.1.9.1.1881
	Catalyst C3650-48TQ (-L/S/E)	1.3.6.1.4.1.9.1.1882

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 3750	3750 Stack	1.3.6.1.4.1.9.1.516
	3750-24FS	1.3.6.1.4.1.9.1.656
	3750-24PS	1.3.6.1.4.1.9.1.536
	3750-24TS	1.3.6.1.4.1.9.1.513
	3750-48PS	1.3.6.1.4.1.9.1.535
	3750-48TS	1.3.6.1.4.1.9.1.512
	3750G-12S	1.3.6.1.4.1.9.1.530
	3750G-12S-SD	1.3.6.1.4.1.9.1.688
	3750G-16TD	1.3.6.1.4.1.9.1.591
	3750G-24PS	1.3.6.1.4.1.9.1.602
	3750G-24T	1.3.6.1.4.1.9.1.514
	3750G-24TS	1.3.6.1.4.1.9.1.511
	3750G-24TS-1U	1.3.6.1.4.1.9.1.624
	3750G-24WS-S25	1.3.6.1.4.1.9.1.778
	3750G-24WS-S50	1.3.6.1.4.1.9.1.779
	3750G-48PS	1.3.6.1.4.1.9.1.603
	3750G-48TS	1.3.6.1.4.1.9.1.604
	3750V2-24PS	1.3.6.1.4.1.9.1.1023
	3750V2-48PS	1.3.6.1.4.1.9.1.1027
	Catalyst 3750-X	3750X-48P (-L/E)
3750X-48PF (-L/S/E)		1.3.6.1.4.1.9.1.1225
3750X-48P (-L/S)		1.3.6.1.4.1.9.1.1225
3750X-24P (-L/S/E)		1.3.6.1.4.1.9.1.1224
Catalyst 3750 Metro	3750-24TE-M	1.3.6.1.4.1.9.1.574

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 3750-E	3750E-24PD	1.3.6.1.4.1.9.1.792
	3750E-24TD	1.3.6.1.4.1.9.1.789
	3750E-48PD	1.3.6.1.4.1.9.1.791
	3750E-48TD-S	1.3.6.1.4.1.9.1.790
Catalyst 3850	Catalyst C3850-24U (-L/S/E)	1.3.6.1.4.1.9.1.1767
	Catalyst C3850-48U (-L/S/E)	1.3.6.1.4.1.9.1.1768
	3850-48P (-L/S/E)	1.3.6.1.4.1.9.1.1641
	3850-24P (-L/S/E)	1.3.6.1.4.1.9.1.1642
	3850-48T (-L/S/E)	1.3.6.1.4.1.9.1.1643
	3850-24T (-L/S/E)	1.3.6.1.4.1.9.1.1644
	Catalyst 3850-12S-S	1.3.6.1.4.1.9.1.1880
	Catalyst 3850-12S-E	1.3.6.1.4.1.9.1.1880
	Catalyst 3850-24S-S	1.3.6.1.4.1.9.1.1879
	Catalyst 3850-24S-E	1.3.6.1.4.1.9.1.1879
	Catalyst C3850-12X48U	1.3.6.1.4.1.9.1.1745
Catalyst 4500	4503	1.3.6.1.4.1.9.5.58
	4503	1.3.6.1.4.1.9.1.503
	4506	1.3.6.1.4.1.9.5.59
	4506	1.3.6.1.4.1.9.1.502
	4507	1.3.6.1.4.1.9.1.501
	4510	1.3.6.1.4.1.9.1.537
Catalyst 4500-E	4503-E	1.3.6.1.4.1.9.1.874
	4506-E	1.3.6.1.4.1.9.1.875
	4507R-E	1.3.6.1.4.1.9.1.876
	4510R-E	1.3.6.1.4.1.9.1.877
	4507R+E	1.3.6.1.4.1.9.1.1286
	4510R+E	1.3.6.1.4.1.9.1.1287

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst 4900	4948	1.3.6.1.4.1.9.1.626
	4948-10GE	1.3.6.1.4.1.9.1.659
Catalyst 6500	6503	1.3.6.1.4.1.9.5.56
	6503	1.3.6.1.4.1.9.1.449
	6504	1.3.6.1.4.1.9.1.657
	6506	1.3.6.1.4.1.9.5.45
	6506	1.3.6.1.4.1.9.1.282
	6509	1.3.6.1.4.1.9.5.44
	6509	1.3.6.1.4.1.9.1.283
	6509-NEB	1.3.6.1.4.1.9.5.61
	6513	1.3.6.1.4.1.9.5.50
	6513	1.3.6.1.4.1.9.1.400
Catalyst 6500-E	6509-E	1.3.6.1.4.1.9.1.283
	6506-E	1.3.6.1.4.1.9.1.282
	6504-E	1.3.6.1.4.1.9.1.657
	6503-E	1.3.6.1.4.1.9.1.449
Catalyst 6800ia	Catalyst 6800ia-48FPD-L	1.3.6.1.4.1.9.1.1866
	Catalyst 6800ia-48TD-L	1.3.6.1.4.1.9.1.1867
Catalyst 68xx	Catalyst 68xx Virtual Switch	1.3.6.1.4.1.9.1.1934
Catalyst 6880-X	Catalyst 6880-XLE	1.3.6.1.4.1.9.1.1784
Catalyst 6807-XL	Catalyst 6807-XL	1.3.6.1.4.1.9.1.1765
Catalyst Express 500	500-24LC	1.3.6.1.4.1.9.1.725
	500-24PC	1.3.6.1.4.1.9.1.726
	500-24TT	1.3.6.1.4.1.9.1.724
	500G-12TC	1.3.6.1.4.1.9.1.727

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Catalyst Express 520	520-24LC	1.3.6.1.4.1.9.1.933
	520-24PC	1.3.6.1.4.1.9.1.934
	520-24TT	1.3.6.1.4.1.9.1.932
	520-8PC	1.3.6.1.4.1.9.1.897
	520G-24TC	1.3.6.1.4.1.9.1.935
Cisco ME 4900	ME 4924-10GE	1.3.6.1.4.1.9.1.788
Catalyst C6880x	ciscoC6880x	1.3.6.1.4.1.9.1.1936
Catalyst 3560CX	Cisco Catalyst 3560CX-8XPD-S	1.3.6.1.4.1.9.1.2131
	Cisco Catalyst 3560CX-8PT-S	1.3.6.1.4.1.9.1.2130
Catalyst C3560	catwsC3560CX12pdS	1.3.6.1.4.1.9.1.2132
	catwsC3560CX12pcS	1.3.6.1.4.1.9.1.2134
	catwsC3560CX8tcS	1.3.6.1.4.1.9.1.2135
	catwsC3560CX8pcS	1.3.6.1.4.1.9.1.2136
Catalyst C2960	catwsC2960CX8tcL	1.3.6.1.4.1.9.1.2137
Catalyst 2960CX	Cisco Catalyst 2960CX-8PC-L	1.3.6.1.4.1.9.1.2191

Supported Cisco Routers

The following table lists the Cisco routers Emergency Responder supports.

Table 5: Supported Cisco Routers

Series (Ethernet Ports Only)	Supported Device	System Object ID from CISCO-PRODUCTS-MIB or CISCO-STACK-MIB
Cisco 1800	Cisco 1861-SRST-B/K9	1.3.6.1.4.1.9.1.904
	Cisco 1861-SRST-C-B/K9	1.3.6.1.4.1.9.1.939
	Cisco 1861-SRST-C-F/K9	1.3.6.1.4.1.9.1.940
	Cisco 1861-SRST-F/K9	1.3.6.1.4.1.9.1.905
	Cisco 1861-UC-2BRI-K9	1.3.6.1.4.1.9.1.902
	Cisco 1861-UC-4FXO-K9	1.3.6.1.4.1.9.1.903
	Cisco1861	1.3.6.1.4.1.9.1.1065
Cisco 1900	Cisco 1905	1.3.6.1.4.1.9.1.1192
	Cisco 1921	1.3.6.1.4.1.9.1.1191
	Cisco 1941	1.3.6.1.4.1.9.1.1047
Cisco 2800	Cisco 2811	1.3.6.1.4.1.9.1.576
	Cisco 2821	1.3.6.1.4.1.9.1.577
	Cisco 2851	1.3.6.1.4.1.9.1.578
Cisco 2900	Cisco 2911	1.3.6.1.4.1.9.1.1045
	Cisco 2921	1.3.6.1.4.1.9.1.1044
	Cisco 2951	1.3.6.1.4.1.9.1.1043
Cisco 3800	Cisco 3825	1.3.6.1.4.1.9.1.543
	Cisco 3845	1.3.6.1.4.1.9.1.544
Cisco 3900	Cisco 3925	1.3.6.1.4.1.9.1.1042
	Cisco 3925E	1.3.6.1.4.1.9.1.1144
	Cisco 3945	1.3.6.1.4.1.9.1.1041
	Cisco 3945E	1.3.6.1.4.1.9.1.1145

Supported Switch Modules and Network Modules

Emergency Responder supports the following switch modules and network modules.

Table 6: Supported Switch Modules and Network Modules

Switch Modules and Network Modules	System Object ID from CISCO-PRODUCTS-MIB
Cisco SM-ES2-16-P	1.3.6.1.4.1.9.1.1048
Cisco SM-ES3-16-P	1.3.6.1.4.1.9.1.1049
Cisco SM-ES3G-16-P	1.3.6.1.4.1.9.1.1050
Cisco SM-ES2-24-P	1.3.6.1.4.1.9.1.1052
Cisco SM-ES3-24-P	1.3.6.1.4.1.9.1.1053
Cisco SM-ES3G-24-P	1.3.6.1.4.1.9.1.1054
Cisco SM-D-ES3-48-P	1.3.6.1.4.1.9.1.1056
Cisco SM-D-ES3G-48-P	1.3.6.1.4.1.9.1.1057
NME-16ES-1G	1.3.6.1.4.1.9.1.702
NME-16ES-1G-P	1.3.6.1.4.1.9.1.663
NME-X-23ES-1G	1.3.6.1.4.1.9.1.703
NME-X-23ES-1G-P	1.3.6.1.4.1.9.1.664
NME-XD-24ES-2S-P	1.3.6.1.4.1.9.1.665
NME-XD-48ES-2S-P	1.3.6.1.4.1.9.1.666



Note Switch modules and network modules use the System Object IDs of the routers into which they are inserted. Support for ISR-G2 SM and NM requires installation of the Cisco Options Package (COP) file. Download the COP file from the [Download Software](#) page on Cisco.com

Supported Cisco UCS Platforms

For information about supported Cisco Unified Computing System (UCS) platforms, see the [Unified Communications Virtualization Supported Applications](#) section of the Cisco documentation wiki.

VMware Support

For information about VMware, see the Unified Communications VMWare Requirements section of the Cisco documentation wiki at http://docwiki.cisco.com/wiki/Unified_Communications_VMWare_Requirements.

Supported OVAs and Capacity

For information about OVAs, administrators should see the Virtualization for Cisco Emergency Responder (CER) at http://www.cisco.com/c/dam/en/us/td/docs/voice_ip_comm/uc_system/virtualization/virtualization-cisco-emergency-responder.html.

Related Documentation

Cisco Emergency Responder Documentation

See the publications for Cisco Emergency Responder. Navigate from the following documentation URL:

http://www.cisco.com/en/US/products/sw/voicesw/ps842/tsd_products_support_series_home.html

Cisco Unified Communications Manager Documentation

See the *Cisco Unified Communications Manager Documentation Guide* and other publications specific to your Cisco Unified Communications Manager release. Navigate from the following URL:

http://www.cisco.com/en/US/products/sw/voicesw/ps556/tsd_products_support_series_home.html

Important Notes

Cisco Emergency Responder 11.5(x) Supported Upgrades

Cisco Emergency Responder 10.x and later is supported on Cisco Unified Computing System (UCS) and other virtual platforms only. All existing installations on Media Convergence Servers (MCS) should be migrated to UCS before upgrading to Cisco Emergency Responder 10.x or later.

Direct upgrades to Cisco Emergency Responder 11.5(x) are supported only from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 or Cisco Emergency Responder 8.7 or Cisco Emergency Responder 9.0(1) or Cisco Emergency Responder 9.0(2) or Cisco Emergency Responder 10.0(1) or Cisco Emergency Responder 10.0(2) or Cisco Emergency Responder 10.5(1) or Cisco Emergency Responder 11.0(1). All existing installations on MCS should be migrated to UCS before upgrading to Cisco Emergency Responder 11.5(x).



Note

To improve software integrity protection, Cisco Emergency Responder 11.5 has been signed with new RSA v3 keys to resolve CDET “CSCUo53520”. Cisco Emergency Responder 10.0(2) and later releases have the fix for this and when upgrading to Cisco Emergency Responder 10.5 or later, it does not require any COP file installation. Upgrade from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 or Cisco Emergency Responder 8.7 or Cisco Emergency Responder 9.0(1) or Cisco Emergency Responder 9.0(2) or Cisco Emergency Responder 10.0(1) requires the installation of RSA v3 Cisco Options Package (COP) before you upgrade to Cisco Emergency Responder 10.5 or later. For information on the COP file, see <http://www.cisco.com/web/software/282204704/18582/RSA3ver4.pdf>.

Also, when upgrading from Cisco Emergency Responder 8.5 or Cisco Emergency Responder 8.6 it requires the installation of a Refresh Upgrade Cisco Options Package (COP) before you upgrade to Cisco Emergency Responder 10.5 or later. Upgrade to Cisco Emergency Responder 10.5 or later is a Refresh Upgrade and may require longer downtime.

Direct upgrades from Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x or Cisco Emergency Responder 8.0 to Cisco Emergency Responder 11.5(x) are not supported. Customers must first complete an upgrade to Cisco Emergency Responder 8.6.

- If existing Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x, or Cisco Emergency Responder 8.0 is installed on an MCS model that is supported by Cisco Emergency Responder 8.6 or supported through Bridge Upgrade of the system, the customer must first upgrade to Cisco Emergency Responder 8.6, then migrate to UCS or virtual platform, and then upgrade to Cisco Emergency Responder 11.5(x).

- If existing Cisco Emergency Responder 1.x, Cisco Emergency Responder 2.x, Cisco Emergency Responder 7.x or Cisco Emergency Responder 8.0 is installed on MCS, which is not supported by Cisco Emergency Responder 8.6, customer must perform a fresh installation of Cisco Emergency Responder 11.5(x).

Licensing

Cisco Prime License Manager centralizes all of the licensing for Emergency Responder 10.0 and onwards. Emergency Responder communicates the licensing requirements to Cisco Prime License Manager. Emergency Responder attempts to discover all phones on Unified Communications Manager, excluding subnets not tracked by Emergency Responder. Together with the manually configured phones, these constitute the license requirements sent by Emergency Responder to the Cisco Prime License Manager. The Cisco Prime License Manager then compares the Emergency Responder license requirements with the licenses installed and reports back license compliance or noncompliance.



Note Emergency Responder always requires its own specific licenses. It is not included in Cisco Unified Workspace Licensing (UWL) or Cisco User Connect Licensing (UCL).

For more information on Cisco Prime License Manager, see the *Cisco Prime License Manager Documentation Guide* at http://www.cisco.com/en/US/partner/products/ps13081/tsd_products_support_series_home.html.

Cisco Emergency Responder 10.5 and onwards support Licenses Management in Cisco HCS License Manager.

For more information on Cisco HCS License Manager, see the Cisco Hosted Collaboration Mediation at <http://www.cisco.com/c/en/us/support/cloud-systems-management/hosted-collaboration-mediation/tsd-products-support-series-home.html>

Caveats

This section contains information about accessing the Cisco Bug Search to find open caveats and resolved caveats.

Access Cisco Bug Search

Known problems (bugs) are graded according to severity level. These release notes contain descriptions of the following:

- All severity level 1 or 2 bugs
- Significant severity level 3 bugs

You can search for problems by using Cisco Bug Search.

Before you begin

To access Cisco Bug Search, you need the following items:

- Internet connection
- Web browser
- Cisco.com user ID and password

Procedure

-
- Step 1** To access Cisco Bug Search, go to:
<https://tools.cisco.com/bugsearch>
- Step 2** Log in with your Cisco.com user ID and password.
- Step 3** To look for information about a specific problem, enter the bug ID number in the Search for field, then press **Enter**.
-

Open Caveats

There are no known issues in this release.

Resolved Caveats

Identifier	Headline
CSCve08643	Authentication Bypass Using HTTP Verb Tampering
CSCvf64322	Cisco Emergency Responder Disk Utilization Denial of Service Vulnerability
CSCvg55112	Cisco Emergency Responder unauthorized access vulnerability
CSCvf84441	CER Support for switch WS-C3560X-48T-S of OID 1.3.6.1.4.1.9.1.1227

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS Version 2.0.

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The following information is for FCC compliance of Class A devices: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case users will be required to correct the interference at their own expense.

The following information is for FCC compliance of Class B devices: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment causes interference to radio or television reception, which can be determined by turning the equipment off and on, users are encouraged to try to correct the interference by using one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Modifications to this product not authorized by Cisco could void the FCC approval and negate your authority to operate the product

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com go trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2018 Cisco Systems, Inc. All rights reserved.