



Installation

- [Virtual Appliance Installation, page 1](#)
- [Activate Services, page 1](#)
- [Log In To Application, page 2](#)

Virtual Appliance Installation

To deploy and install the Prime Collaboration Provisioning virtual machine, see the *Installation Guide for Cisco Business Edition 6000*:

http://www.cisco.com/en/US/partner/products/ps11369/prod_installation_guides_list.html

The complete installation time for the Prime Collaboration Provisioning application is approximately 30 minutes.

Activate Services

For Cisco Prime Collaboration Provisioning to interact with Cisco Unified Communications Manager and IM and Presence Service servers, you must activate the Cisco AXL Web Service on both servers.

Procedure

Step 1 Perform the following actions to enable services on Cisco Unified Communications Manager:

- a) Log on to Cisco Unified Communications Manager web interface.
- b) Go to **Navigation > Cisco Unified Serviceability** and click **Go**.
- c) Click **Tools > Service Activation**.
- d) Enable the following services, as per the site requirements:
 - Cisco CallManager
 - Cisco CTIManager
 - Cisco Extension Mobility
 - Cisco TFTP

- Cisco AXL Web Services
- Cisco DirSync

e) Click **Save**.

Step 2 Perform the following actions to enable services on IM and Presence Service:

- a) Log on to IM and Presence web interface.
- b) At the top right corner, go to **Navigation > Cisco Unified IM and Presence Serviceability** and click **Go**.
- c) Select **Tools > Service Activation**.
- d) Enable the following services, as per the site requirements:

- Cisco SIP Proxy
- Cisco Presence Engine
- Cisco Sync Agent
- Cisco AXL Web Services
- Cisco XCP Connection Manager
- Cisco XCP Directory Service
- Cisco XCP Authentication Service

e) Click **Save**.

Log In To Application

Procedure

Step 1 Open a browser session on your PC.

Step 2 Enter `http://<Prime Collaboration IP Address>`.
The Prime Collaboration login page appears.

Step 3 Log in as a globaladmin, using the same the credentials that you specified during initial configuration.
