



LTE HeNBGW MME Pool Configuration Mode Commands



Important

In Release 20, 21.0 and 21.1, HeNBGW is not supported. Commands in this configuration mode must not be used in these releases. For more information, contact your Cisco account representative.

The MME Pool configuration is used to configure one or more MMEs to which the HeNB-GW is to communicate. This configuration is available under `lte-policy` configuration mode. Adding or modifying an MME pool instance puts the user into the MME Pool configuration mode.

Command Modes

Exec > Global Configuration > LTE Policy Configuration > HeNBGW MME Pool Configuration

configure > **lte-policy** > **henbgw mme-pool** *mme_pool_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(mme-pool) #
```



Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



Important

For information on common commands available in this configuration mode, refer to the [Common Commands](#) chapter.

- [mme](#), on page 1

mme

Configures a specific MME to HeNBGW.

Product

HeNB-GW

Privilege

Administrator

Command Modes

Exec > Global Configuration > LTE Policy Configuration > HeNBGW MME Pool Configuration

configure > lte-policy > henbgw mme-pool *mme_pool_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(mme-pool) #
```

Syntax Description

```
[ no ] mme mme_name { ipv4-address ipv4_address [ ipv4-address ipv4_address ] |
  ipv6-address ipv6_address [ ipv6-address ipv6_address ] [ sctp port port_val ]
}
```

no

Removes the configured MME to HeNBGW.

mme_name

Specifies the MME name as an alphanumeric string of size 1 through 63 characters.

ipv4-address *ipv4_address*Specifies the remote SCTP IPv4 Address for S1 association to MME. *ipv4_address* is specified using a dotted-decimal notation.**ipv6-address *ipv6_address***Specifies the remote SCTP IPv6 Address for S1 association to MME. *ipv6_address* is specified using a colon-separated hexadecimal notation.**sctp**

Configures the S1-MME SCTP parameters.

port *port_val*

Designates the SCTP port.

port_val is an integer ranging from 1 through 65535.**Usage Guidelines**

Use this command to configure a specific MME to HeNBGW.

ExampleThe following command configures the MME with name *mme1*, IPv4 address *10.0.0.1* with SCTP port value *302*:

```
mme mme1 ipv4-address 10.0.0.1 sctp port 302
```