



RAC Profile Configuration Mode Commands

The Routing Area Code (RAC) Profile Configuration Mode is used to configure RAC profiles on a per-context basis. This mode enables to select a Virtual APN (vAPN) based on RAC range and discrete values, and thereby a specific UP group and/or IP pool associated with vAPN.

Command Modes

Exec > Global Configuration > Context Configuration > RAC Profile Configuration

configure > **context** *context_name* > **rac-profile** *profile_name*

[*context_name*]*host_name*(config-rac-profile) #



Important Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [do show, on page 1](#)
- [end, on page 2](#)
- [exit, on page 2](#)
- [rac, on page 2](#)

do show

Executes all **show** commands while in Configuration mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

do show

Usage Guidelines

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

end

Exits the current configuration mode and returns to the Exec mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

end

Usage Guidelines

Use this command to return to the Exec mode.

exit

Exits the current mode and returns to the parent configuration mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

exit

Usage Guidelines

Use this command to return to the parent configuration mode.

rac

Configures Routing Area Code (RAC) profile with discrete values and range.

Product

SAEGW

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration > Context Configuration > RAC Profile Configuration

configure > **context** *context_name* > **rac-profile** *profile_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-rac-profile)#
```

Syntax Description `[no] rac { range start_range to end_range | value }`

no

Including **no** with the command disables the specified configuration.

range *start_range* to *end_range*

Specifies the RAC start and end range of discrete integer value ranging from 0 to 255.

value

The number of discrete RAC values supported per CLI command is 16.

Usage Guidelines

Use this command to configure RAC profiles per context. The maximum number of RAC discrete values supported in a profile are 100. Memory usage is fixed per profile. RAC range or discrete values can overlap between profiles to support maintenance activities like split existing profile or others. Multiple profiles can be associated with an APN.

Example

The following command configures RAC range of 1 to 10:

```
rac range 1 to 10
```

