



## Fabric in a Box with External Fabric Edge

- [Introduction to Fabric in a Box with External Fabric Edge, on page 1](#)
- [Configuring a Fabric Profile \(CLI\), on page 1](#)
- [Configuring a Policy Profile \(CLI\) , on page 2](#)
- [Configuring a Site Tag \(CLI\), on page 3](#)
- [Configuring a WLAN \(CLI\), on page 4](#)
- [Configuring a Policy Tag \(CLI\), on page 4](#)
- [Configuring an AP Profile, on page 5](#)
- [Configuring Map Server and AP Subnet \(CLI\), on page 5](#)
- [Configuring Fabric on FiaB Node, on page 6](#)
- [Configuring a Fabric Edge Node, on page 12](#)
- [Verifying Fabric Configuration, on page 19](#)

## Introduction to Fabric in a Box with External Fabric Edge

From Cisco IOS XE Amsterdam 17.2.1, the Fabric in a Box (FiaB) topology supports external fabric edge nodes. In a fabric-enabled wireless environment using FiaB (border node, control plane, fabric edge, and wireless controller in the same box), you can expand the network by adding external fabric edge nodes. The external fabric edge helps to increase the port density and extend the wireless reach by adding more APs. The APs and clients can exist on both the FiaB and the external fabric edge nodes. Also, the clients can roam between the APs on the FiaB and the external fabric edge nodes.

## Configuring a Fabric Profile (CLI)

### Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters global configuration mode.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 2</b>	<b>wireless profile fabric <i>fabric-profile-name</i></b>  <b>Example:</b> Device(config)# wireless profile fabric test-fabric-profile	Configures the wireless fabric profile parameters.
<b>Step 3</b>	<b>client-l2-vnid <i>client-l2-vnid</i></b>  <b>Example:</b> Device(config-wireless-fabric)# client-l2-vnid 8189	Configures client L2-VNID.  Here, <i>client-l2-vnid</i> refers to the client L2-VNID value. The valid range is from 0 to 16777215.
<b>Step 4</b>	<b>description <i>description</i></b>  <b>Example:</b> Device(config-wireless-fabric)# description test-fabric-profile	Adds a description for the fabric profile.
<b>Step 5</b>	<b>end</b>  <b>Example:</b> Device(config-wireless-fabric)# end	Returns to privileged EXEC mode.

## Configuring a Policy Profile (CLI)

### Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>wireless profile policy <i>profile-policy</i></b>  <b>Example:</b> Device(config)# wireless profile policy test-policy-profile	Configures wireless policy profile and enters wireless policy configuration mode.  <b>Note</b> In Fabric deployments, local mode, local authentication, and local association are not supported.
<b>Step 3</b>	<b>no central dhcp</b>  <b>Example:</b> Device(config-wireless-policy)# no central dhcp	Configures local DHCP mode, where the DHCP is performed in an AP.
<b>Step 4</b>	<b>no central switching</b>  <b>Example:</b>	Configures a WLAN for local switching.

	<b>Command or Action</b>	<b>Purpose</b>
	Device(config-wireless-policy) # no central switching	
<b>Step 5</b>	<b>fabric <i>fabric-name</i></b>  <b>Example:</b> Device(config-wireless-fabric) # fabric test-fabric-profile	Applies the fabric profile.
<b>Step 6</b>	<b>no shutdown</b>  <b>Example:</b> Device(config-wireless-fabric) # no shutdown	Enables the policy profile.
<b>Step 7</b>	<b>end</b>  <b>Example:</b> Device(config-wireless-fabric) # end	Returns to privileged EXEC mode.

## Configuring a Site Tag (CLI)

### Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters the global configuration mode.
<b>Step 2</b>	<b>wireless tag site <i>site-tag</i></b>  <b>Example:</b> Device(config)# wireless tag site default-site-tag-fabric	Configures site tag and enters site tag configuration mode.
<b>Step 3</b>	<b>ap-profile <i>ap-profile-name</i></b>  <b>Example:</b> Device(config-site-tag) # ap-profile default-ap-profile-fabric	Assigns an AP profile to the wireless site.
<b>Step 4</b>	<b>description <i>description</i></b>  <b>Example:</b> Device(config-site-tag) # description fabric-site	Adds a description to the AP profile.
<b>Step 5</b>	<b>end</b>  <b>Example:</b> Device(config-site-tag) # end	Returns to privileged EXEC mode.

# Configuring a WLAN (CLI)

## Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>wlan wlan-name wlan-id SSID-name</b>  <b>Example:</b> Device(config)# wlan test-wlan 1 test-wlan	Configures a WLAN and enters WLAN configuration submode.
<b>Step 3</b>	<b>no shutdown</b>  <b>Example:</b> Device(config-wlan)# no shutdown	Enables the WLAN.

# Configuring a Policy Tag (CLI)

## Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>wireless tag policy policy-tag-name</b>  <b>Example:</b> Device(config)# wireless tag policy test-policy-tag	Configures policy tag and enters policy tag configuration mode.
<b>Step 3</b>	<b>wlan wlan-name policy profile-policy-name</b>  <b>Example:</b> Device(config-policy-tag)# wlan test-wlan policy test-policy-profile	Maps a policy profile to a WLAN profile.
<b>Step 4</b>	<b>end</b>  <b>Example:</b> Device(config-site-tag)# end	Returns to privileged EXEC mode.

# Configuring an AP Profile

## Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters the global configuration mode.
<b>Step 2</b>	<b>ap profile <i>ap-profile-name</i></b>  <b>Example:</b> Device(config)# ap profile test-ap-profile	Configures an AP profile and enters AP profile configuration mode.
<b>Step 3</b>	<b>ap <i>ap-ether-mac</i></b>  <b>Example:</b> Device(config-ap-profile)# ap 006b.f126.036e	Enters AP configuration mode.
<b>Step 4</b>	<b>policy-tag <i>policy-tag</i></b>  <b>Example:</b> Device(config-ap-profile)# policy-tag test-policy-tag	Specifies the policy tag that is to be attached to the AP.
<b>Step 5</b>	<b>end</b>  <b>Example:</b> Device(config-ap-profile)# end	Returns to privileged EXEC mode.

# Configuring Map Server and AP Subnet (CLI)

## Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> Device# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>wireless fabric</b>  <b>Example:</b> Device(config)# wireless fabric	Enables SD-Access wireless globally.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 3</b>	<b>wireless fabric name</b> <i>name l2-vnid l2-vnid-value l3-vnid l3-vnid-value ip network-ip subnet-mask</i>  <b>Example:</b> Device(config)# wireless fabric name 40_40_0_0-INFRA_VN 12-vnid 8188 13-vnid 4097 ip 40.40.0.0 255.255.0.0	Configures AP subnet Layer 2 and Layer 3 VNIDs.
<b>Step 4</b>	<b>wireless fabric name</b> <i>name l2-vnid l2-vnid-value</i>  <b>Example:</b> Device(config)# wireless fabric name 41_41_0_0-DEFAULT_VN 12-vnid 8189	Defines client Layer 2 VNID AAA override.
<b>Step 5</b>	<b>wireless fabric control-plane</b> <i>name</i>  <b>Example:</b> Device(config)# wireless fabric control-plane default-control-plane	Configures the control plane name.
<b>Step 6</b>	<b>ip address</b> <i>ip-address key shared-key</i>  <b>Example:</b> Device((config-wireless-cp)# ip address 5.5.5.5 key 0 3a18df	Configures the map server IP address and authentication key shared with the map server.
<b>Step 7</b>	<b>end</b>  <b>Example:</b> Device(config)# end	Returns to privileged EXEC mode. Alternatively, you can also press <b>Ctrl-Z</b> to exit global configuration mode.

## Configuring Fabric on FiaB Node

### Procedure

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> FiaB# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>router lisp</b>  <b>Example:</b> FiaB(config)# router lisp	Enters LISP configuration mode.
<b>Step 3</b>	<b>locator-table default</b>  <b>Example:</b>	Associates a default Virtual Routing and Forwarding (VRF) table through which the routing locator address space is reachable to a

	<b>Command or Action</b>	<b>Purpose</b>
	FiaB(config-router-lisp)# locator-table default	router Locator ID Separation Protocol (LISP) instantiation.
<b>Step 4</b>	<b>locator-set <i>locator-set-name</i></b>  <b>Example:</b> FiaB(config-router-lisp)# locator-set WLC	Specifies a named locator set and enters LISP locator-set configuration mode.
<b>Step 5</b>	<b>ip-address</b>  <b>Example:</b> FiaB(config-router-lisp-locator-set)# 5.5.5.5	Specifies an IP address of loopback or other egress tunnel router (ETR) interface.
<b>Step 6</b>	<b>exit-locator-set</b>  <b>Example:</b> FiaB(config-router-lisp-locator-set)# exit-locator-set	Exits LISP locator-set configuration mode.
<b>Step 7</b>	<b>locator-set rloc_loopback</b>  <b>Example:</b> FiaB(config-router-lisp)# locator-set rloc_loopback	Specifies an existing locator set and enters LISP locator-set configuration mode.
<b>Step 8</b>	<b>ipv4-interface <i>interface</i></b>  <b>Example:</b> FiaB(config-router-lisp-locator-set)# IPv4-interface Loopback0	Configures a locator address by creating a locator entry.
<b>Step 9</b>	<b>auto-discover-rlocs</b>  <b>Example:</b> FiaB(config-router-lisp-locator-set)# auto-discover-rlocs	Configures the ETR to auto discover the locators registered by other xTRs. (Ingress tunnel router (ITR) and an ETR are known as an xTR.)
<b>Step 10</b>	<b>exit-locator-set</b>  <b>Example:</b> FiaB(config-router-lisp-locator-set)# exit-locator-set	Exits LISP locator-set configuration mode.
<b>Step 11</b>	<b>service ipv4</b>  <b>Example:</b> FiaB(config-router-lisp)# service ipv4	Enables Layer 3 network services for the IPv4 address family and enters service submode.
<b>Step 12</b>	<b>encapsulation vxlan</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4)# encapsulation vxlan	Configures VXLAN as encapsulation type for data packets.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 13</b>	<b>itr map-resolver <i>map-resolver-address</i></b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # itr map-resolver 5.5.5.5	Configures map resolver address for sending map requests.
<b>Step 14</b>	<b>etr map-server <i>map-server-address</i> key <i>key-type authentication-key</i></b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # etr map-server 5.5.5.5 key 7 #####	Configures the map server for ETR registration.
<b>Step 15</b>	<b>etr</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # etr	Configures a LISP ETR.
<b>Step 16</b>	<b>sgt</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # sgt	Enables security group tag propagation in LISP-encapsulated traffic.
<b>Step 17</b>	<b>no map-cache away-eids send-map-request</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # no map-cache away-eids send-map-request	Removes the address family-specific map cache configuration.
<b>Step 18</b>	<b>proxy-itr <i>ip-address</i></b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # proxy-itr 5.5.5.5	Enables the Proxy Ingress Tunnel Router (PITR) functionality and specifies the address to use when LISP encapsulating packets to LISP sites.
<b>Step 19</b>	<b>map-server</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # map-server	Configures a LISP map server.
<b>Step 20</b>	<b>map-resolver</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # map-resolver	Configures a LISP map resolver.
<b>Step 21</b>	<b>map-cache away-eids send-map-request</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4) # map-cache 40.40.0.0/16 send-map-request	Exports table entries into the map cache, with the action set to send-map-request.
<b>Step 22</b>	<b>route-export site-registrations</b>  <b>Example:</b>	Exports LISP site registrations to the routing information base (RIB).

	<b>Command or Action</b>	<b>Purpose</b>
	FiaB(config-lisp-srv-ipv4)# route-export site-registrations	
<b>Step 23</b>	<b>distance site-registrations num</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4)# distance site-registrations 250	Configures LISP installed routes of type site registrations.
<b>Step 24</b>	<b>map-cache site-registration</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4)# map-cache site-registration	Installs the map cache to a map request for site registrations.
<b>Step 25</b>	<b>exit-service-ipv4</b>  <b>Example:</b> FiaB(config-lisp-srv-ipv4)# exit-service-ipv4	Exits LISP service-ipv4 configuration mode.
<b>Step 26</b>	<b>service ethernet</b>  <b>Example:</b> FiaB(config-router-lisp)# service ethernet	Selects service type as Ethernet and enters service submode.
<b>Step 27</b>	<b>database-mapping limit dynamic limit</b>  <b>Example:</b> FiaB(config-lisp-srv-eth)# database-mapping limit dynamic 5000	Configures the maximum number of dynamic local endpoint identifier (EID) prefix database entries.
<b>Step 28</b>	<b>itr map-resolver map-resolver-address</b>  <b>Example:</b> FiaB(config-lisp-srv-eth)# itr map-resolver 5.5.5.5	Configures the map-resolver address for sending map requests.
<b>Step 29</b>	<b>itr</b>  <b>Example:</b> FiaB(config-lisp-srv-eth)# itr	Enables the LISP ITR functionality.
<b>Step 30</b>	<b>etr map-server map-server-address key key-type authentication-key</b>  <b>Example:</b> FiaB(config-lisp-srv-eth)# etr map-server 5.5.5.5 key 7 1234	Configures a map server for ETR registration.
<b>Step 31</b>	<b>etr</b>  <b>Example:</b> FiaB(config-lisp-srv-eth)# etr	Enables the LISP ETR functionality.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 32</b>	<b>map-server</b>  <b>Example:</b> FiaB(config-lisp-srv-eth) # map-server	Enables the LISP map server functionality.
<b>Step 33</b>	<b>map-resolver</b>  <b>Example:</b> FiaB(config-lisp-srv-eth) # map-resolver	Enables the LISP map resolver functionality.
<b>Step 34</b>	<b>exit-service-ethernet</b>  <b>Example:</b> FiaB(config-lisp-srv-eth) # exit-service-ethernet	Exits LISP service-ethernet configuration mode.
<b>Step 35</b>	<b>instance-id <i>instance</i></b>  <b>Example:</b> FiaB(config-router-lisp) # instance-id 101	Creates a LISP EID instance to group multiple services.
<b>Step 36</b>	<b>remote-rloc-probe on-route-change</b>  <b>Example:</b> FiaB(config-lisp-inst) # remote-rloc-probe on-route-change	Configures the parameters for probing of remote routing locators (RLOCs).
<b>Step 37</b>	<b>dynamic-eid <i>dynamic-eid-name</i></b>  <b>Example:</b> FiaB(config-lisp-inst) # dynamic-eid 40_40_0_0-INFRA_VN-IPV4	Configures a dynamic EID and enters dynamic EID configuration mode.
<b>Step 38</b>	<b>database-mapping <i>eid locator-set rloc_loopback</i></b>  <b>Example:</b> FiaB(config-router-lisp-dynamic-eid) # database-mapping 40.40.0.0/16 locator-set rloc_loopback	Configures EID prefix and locator-set for dynamic EID.
<b>Step 39</b>	<b>exit-dynamic-id</b>  <b>Example:</b> FiaB(config-router-lisp-dynamic-eid) # exit-dynamic-eid	Exits LISP dynamic-eid configuration mode.
<b>Step 40</b>	<b>exit-instance-id</b>  <b>Example:</b> FiaB(config-router-lisp-instance) # exit-instance-id	Exits LISP instance-id configuration mode.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 41</b>	<b>instance-id <i>instance</i></b>  <b>Example:</b> FiaB(config-router-lisp)# instance-id 101	Creates a LISP EID instance to group multiple services.
<b>Step 42</b>	<b>remote-rloc-probe on-route-change</b>  <b>Example:</b> FiaB(config-lisp-inst)# remote-rloc-probe on-route-change	Configures parameters for probing remote RLOCs.
<b>Step 43</b>	<b>service ethernet</b>  <b>Example:</b> FiaB(config-lisp-inst)# service ethernet	Enables Layer 2 network services and enters service submode.
<b>Step 44</b>	<b>eid-table vlan <i>vlan-number</i></b>  <b>Example:</b> FiaB(config-lisp-inst-srv-eth)# eid-table vlan 101	Binds an EID table to VLAN.
<b>Step 45</b>	<b>database-mapping mac locator-set <i>rloc_lopbac</i></b>  <b>Example:</b> FiaB(config-lisp-inst-srv-eth)# database-mapping mac locator-set rloc_lopbac	Configures an address family-specific local EID prefixes database.
<b>Step 46</b>	<b>exit-service-ethernet</b>  <b>Example:</b> FiaB(config-lisp-inst-srv-eth)# exit-service-ethernet	Exits LISP service-ethernet configuration mode.
<b>Step 47</b>	<b>exit-instance-id</b>  <b>Example:</b> FiaB(config-lisp-inst)# exit-instance-id	Exits LISP instance-id configuration mode.
<b>Step 48</b>	<b>map-server session passive-open <i>server</i></b>  <b>Example:</b> FiaB(config-router-lisp)# map-server session passive-open WLC	Configures a map server with open passive TCP sockets to listen for incoming connections.
<b>Step 49</b>	<b>site <i>site-name</i></b>  <b>Example:</b> FiaB(config-router-lisp)# site site_uci	Configures a LISP site on a map server.
<b>Step 50</b>	<b>description <i>map-server-description</i></b>  <b>Example:</b>	Specifies a description text for the LISP site.

	<b>Command or Action</b>	<b>Purpose</b>
	FiaB(config-router-lisp-site)# description map-server configured from Cisco DNA-Center	
<b>Step 51</b>	<b>authentication-key <i>key</i></b>  <b>Example:</b> FiaB(config-router-lisp-site)# authentication-key 7 #####	Configures the authentication key used by the LISP site.
<b>Step 52</b>	<b>eid-record instance-id <i>instance-id</i> <i>address</i> accept-more-specifics</b>  <b>Example:</b> FiaB(config-router-lisp-site)# eid-record instance-id 4097 0.0.0.0/0 accept-more-specifics	Specifies that any EID prefix that is more specific than the EID prefix configured is accepted and tracked.
<b>Step 53</b>	<b>eid-record instance-id <i>instance-id</i> any-mac</b>  <b>Example:</b> FiaB(config-router-lisp-site)# eid-record instance-id 8188 any-mac	Accepts registrations, if any, for Layer 2 EID records.
<b>Step 54</b>	<b>exit-site</b>  <b>Example:</b> FiaB(config-router-lisp-site)# exit-site	Exits LISP site configuration mode.
<b>Step 55</b>	<b>ipv4 locator reachability exclude-default</b>  <b>Example:</b> FiaB(config-router-lisp)# ipv4 locator reachability exclude-default	Configures the IPv4 locator address of the LISP.
<b>Step 56</b>	<b>ipv4 source-locator <i>interface-name</i></b>  <b>Example:</b> FiaB(config-router-lisp)# ipv4 source-locator Loopback0	Configures the IPv4 source locator address of the interface.
<b>Step 57</b>	<b>exit-router-lisp</b>  <b>Example:</b> FiaB(config-router-lisp)# exit-router-lisp	Exits LISP router-lisp configuration mode.

## Configuring a Fabric Edge Node



**Note** You can perform the following configuration tasks only from Fabric Edge Node, and not from your controller.

**Procedure**

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>configure terminal</b>  <b>Example:</b> FabricEdge# configure terminal	Enters global configuration mode.
<b>Step 2</b>	<b>router lisp</b>  <b>Example:</b> FabricEdge(config)# router lisp	Enters LISP configuration mode.
<b>Step 3</b>	<b>locator-table default</b>  <b>Example:</b> FabricEdge(config-router-lisp)# locator-table default	Associates a default VRF table through which the routing locator address space is reachable to a router LISP instantiation.
<b>Step 4</b>	<b>locator-set rloc_loopback</b>  <b>Example:</b> FabricEdge(config-router-lisp)# locator-set rloc_loopback	Specifies a named locator set and enters LISP locator-set configuration mode.
<b>Step 5</b>	<b>ipv4-interface interface-num priority priority weight weight</b>  <b>Example:</b> FabricEdge(config-router-lisp-locator-set)# IPv4-interface Loopback 0 priority 10 weight 10	Configures the IPv4 address of the interface as locator.
<b>Step 6</b>	<b>exit-locator-set</b>  <b>Example:</b> FabricEdge(config-router-lisp-locator-set)# exit-locator-set	Exits LISP locator-set configuration mode.
<b>Step 7</b>	<b>exit-router-lisp</b>  <b>Example:</b> FabricEdge(config-router-lisp-# exit-router-lisp	Exits LISP router-lisp configuration mode.
<b>Step 8</b>	<b>interface vlan interface-num</b>  <b>Example:</b> FabricEdge(config)# interface Vlan 2045	Configures an interface.
<b>Step 9</b>	<b>description description</b>  <b>Example:</b> FabricEdge(config-if)# description Configured from Cisco DNA-Center	Specifies a description text for the interface.

## Configuring a Fabric Edge Node

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 10</b>	<b>mac-address <i>mac-address</i></b>  <b>Example:</b> FabricEdge(config-if) # mac-address 0000.0c9f.f85c	Sets an interface MAC address manually.
<b>Step 11</b>	<b>ip address <i>ip-address mask</i></b>  <b>Example:</b> FabricEdge(config-if) # ip address 192.168.1.1 255.255.255.252	Configures an IP address for the interface.
<b>Step 12</b>	<b>ip helper-address <i>ip-address</i></b>  <b>Example:</b> FabricEdge(config-if) # ip helper-address 9.9.9.9	Specifies a destination address for UDP broadcasts.
<b>Step 13</b>	<b>no ip redirects</b>  <b>Example:</b> FabricEdge(config-if) # no ip redirects	Disables sending of ICMP redirect messages.
<b>Step 14</b>	<b>ip route-cache same-interface</b>  <b>Example:</b> FabricEdge(config-if) # ip route-cache same-interface	Enables fast-switching cache for outgoing packets on the same interface.
<b>Step 15</b>	<b>no lisp mobility liveness test</b>  <b>Example:</b> FabricEdge(config-if) # no lisp mobility liveness test	Removes liveness test on dynamic EID discovered on this interface.
<b>Step 16</b>	<b>lisp mobility <i>dynamic-eid-name</i></b>  <b>Example:</b> FabricEdge(config-if) # lisp mobility 40_40_0_0-INFRA_VN-IPV4	Allows EID mobility on the interface.
<b>Step 17</b>	<b>exit</b>  <b>Example:</b> FabricEdge(config-if) # exit	Exits from interface configuration mode.
<b>Step 18</b>	<b>router lisp</b>  <b>Example:</b> FabricEdge(config) # router lisp	Enters LISP configuration mode.
<b>Step 19</b>	<b>locator-set <i>locator-set-name</i></b>  <b>Example:</b> FabricEdge(config-router-lisp) # locator-set rloc_824ecb7	Specifies a locator set and enters LISP locator-set configuration mode.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 20</b>	<b>exit-locator-set</b>  <b>Example:</b> FabricEdge(config-router-lisp-locator-set)# exit-locator-set	Exits LISP locator-set configuration mode.
<b>Step 21</b>	<b>service ipv4</b>  <b>Example:</b> FabricEdge(config-router-lisp)# service ipv4	Enables Layer 3 network services for the IPv4 address family and enters service submode.
<b>Step 22</b>	<b>use-petr ip-address</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# use-petr 5.5.5.5	Configures the loopback IP address of the Proxy Egress Tunnel Router (PETR).
<b>Step 23</b>	<b>encapsulation vxlan</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# encapsulation vxlan	Selects the encapsulation type as VXLAN for data packets.
<b>Step 24</b>	<b>itr map-resolver map-resolver-address</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# itr map-resolver 5.5.5.5	Configures the map resolver address for sending map requests.
<b>Step 25</b>	<b>etr map-server map-server-address key key-type authentication-key</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# etr map-server 5.5.5.5 key 7 #####	Configures the map server for ETR registration.
<b>Step 26</b>	<b>etr map-server map-server-address proxy-reply authentication-key</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# etr map-server 5.5.5.5 proxy-reply	Configures the locator address of the LISP map server and the authentication key that this router, acting as a LISP ETR, will use to register with the LISP mapping system.
<b>Step 27</b>	<b>etr</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# etr	Configures a LISP Egress Tunnel Router (ETR).
<b>Step 28</b>	<b>sgt</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# sgt	Enable security group tag propagation in LISP encapsulated traffic.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 29</b>	<b>no map-cache away-eids send-map-request</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# no map-cache away-eids send-map-request	Removes the address family-specific map cache configuration.
<b>Step 30</b>	<b>proxy-itr ip-address</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# proxy-itr 5.5.5.5	Enables the Proxy Ingress Tunnel Router (PITR) functionality and specifies the address to use when LISP encapsulating packets to LISP sites.
<b>Step 31</b>	<b>exit-service-ipv4</b>  <b>Example:</b> FabricEdge(config-lisp-srv-ipv4)# exit-service-ipv4	Exits LISP service-ipv4 configuration mode.
<b>Step 32</b>	<b>service ethernet</b>  <b>Example:</b> FabricEdge(config-router-lisp)# service ethernet	Selects the service type as Ethernet.
<b>Step 33</b>	<b>itr map-resolver map-resolver-address</b>  <b>Example:</b> FabricEdge(config-lisp-srv-eth)# itr map-resolver 5.5.5.5	Configures the map-resolver address for sending map requests.
<b>Step 34</b>	<b>itr</b>  <b>Example:</b> FabricEdge(config-lisp-srv-eth)# itr	Enables the LISP ITR functionality.
<b>Step 35</b>	<b>etr map-server map-server-address key key-type authentication-key</b>  <b>Example:</b> FabricEdge(config-lisp-srv-eth)# etr map-server 5.5.5.5 key 7 1234	Configures the map server for ETR registration.
<b>Step 36</b>	<b>etr</b>  <b>Example:</b> FabricEdge(config-lisp-srv-eth)# etr	Enables the LISP ETR functionality.
<b>Step 37</b>	<b>exit-service-ethernet</b>  <b>Example:</b> FabricEdge(config-lisp-srv-eth)# exit-service-ethernet	Exits LISP service-ethernet configuration mode.
<b>Step 38</b>	<b>instance-id instance</b>  <b>Example:</b>	Creates a LISP EID instance to group multiple services.

	<b>Command or Action</b>	<b>Purpose</b>
	FabricEdge (config-router-lisp) # instance-id 101	
<b>Step 39</b>	<b>remote-rloc-probe on-route-change</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # remote-rloc-probe on-route-change	Configures the parameters for probing remote Routing locators (RLOCs).
<b>Step 40</b>	<b>dynamic-eid dynamic-eid-name</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # dynamic-eid 40_40_0_0-INFRA_VN-IPV4	Configures a dynamic EID and enters dynamic EID configuration mode.
<b>Step 41</b>	<b>database-mapping eid locator-set rloc_loopback</b>  <b>Example:</b> FabricEdge (config-router-lisp-dynamic-eid) # database-mapping 40.40.0.0/16 locator-set rloc_loopback	Configures the EID prefix and locator set for the dynamic EID.
<b>Step 42</b>	<b>exit-dynamic-id</b>  <b>Example:</b> FabricEdge (config-router-lisp-dynamic-eid) # exit-instance-id	Exits dynamic instance submode.
<b>Step 43</b>	<b>service ipv4</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # service ipv4	Selects service type as IPv4.
<b>Step 44</b>	<b>eid-table default</b>  <b>Example:</b> FabricEdge (config-lisp-inst-srv-ipv4) # eid-table default	Binds an EID table.
<b>Step 45</b>	<b>exit-service-ipv4</b>  <b>Example:</b> FabricEdge (config-lisp-inst-srv-ipv4) # exit-service-ipv4	Exits LISP service-ipv4 configuration mode.
<b>Step 46</b>	<b>exit-instance-id</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # exit-instance-id	Exits LISP instance-id configuration mode.
<b>Step 47</b>	<b>service ipv4</b>  <b>Example:</b>	Selects service type as IPv4.

## Configuring a Fabric Edge Node

	<b>Command or Action</b>	<b>Purpose</b>
	FabricEdge (config-router-lisp) # service ipv4	
<b>Step 48</b>	<b>map-cache away-eids map-request</b>  <b>Example:</b> FabricEdge (config-lisp-srv-ipv4) # map-cache 40.40.0.0/16 map-request	Exports away table entries into the map cache, with the action set to send-map-request.
<b>Step 49</b>	<b>exit-service-ipv4</b>  <b>Example:</b> FabricEdge (config-lisp-srv-ipv4) # exit-service-ipv4	Exits LISP service-ipv4 configuration mode.
<b>Step 50</b>	<b>instance-id <i>instance</i></b>  <b>Example:</b> FabricEdge (config-router-lisp) # instance-id 8188	Creates a LISP EID instance to group multiple services.
<b>Step 51</b>	<b>remote-rloc-probe on-route-change</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # remote-rloc-probe on-route-change	Configures parameters for probing remote RLOCs.
<b>Step 52</b>	<b>service ethernet</b>  <b>Example:</b> FabricEdge (config-lisp-inst) # service ethernet	Enables Layer 2 network services and enters service submode.
<b>Step 53</b>	<b>eid-table <i>vlan</i> <i>vlan-number</i></b>  <b>Example:</b> FabricEdge (config-lisp-inst-srv-eth) # eid-table vlan 101	Binds an EID table to VLAN.
<b>Step 54</b>	<b>database-mapping maclocator-set <i>rloc_loopbac</i></b>  <b>Example:</b> FabricEdge (config-lisp-inst-srv-eth) # database-mapping mac locator-set rloc_loopbac	Configures address family-specific local EID prefixes database.
<b>Step 55</b>	<b>exit-service-ethernet</b>  <b>Example:</b> FabricEdge (config-lisp-inst-srv-eth) # exit-service-ethernet	Exits LISP service-ethernet configuration mode.
<b>Step 56</b>	<b>exit-instance-id</b>  <b>Example:</b>	Exits from LISP instance-id configuration mode.

	<b>Command or Action</b>	<b>Purpose</b>
	FabricEdge(config-lisp-inst) # exit-instance-id	
<b>Step 57</b>	<b>ipv4 locator reachability minimum-mask-length <i>length</i></b>  <b>Example:</b> FabricEdge(config-router-lisp) # ipv4 locator reachability minimum-mask-length 32	Configures the IPv4 locator address of the LISP.
<b>Step 58</b>	<b>ipv4 source-locator <i>interface-name</i></b>  <b>Example:</b> FabricEdge(config-router-lisp) # ipv4 source-locator Loopback0	Configures the IPv4 source locator address of the interface.
<b>Step 59</b>	<b>exit-router-lisp</b>  <b>Example:</b> FabricEdge(config-router-lisp) # exit-router-lisp	Exits LISP router-lisp configuration mode.

## Verifying Fabric Configuration

Use the following commands to verify the fabric configuration.

To verify the LISP configuration on a device, use the following command:

```
FabricEdge# show running-config | section router lisp

router lisp
  locator-table default
  locator-set default
    exit-locator-set
  !
  locator-set rloc_loopback
    IPv4-interface Loopback0 priority 10 weight 10
    exit-locator-set
  !
  locator default-set rloc_loopback
  service ipv4
    encapsulation vxlan
    itr map-resolver 21.21.21.21
    itr
    etr map-server 21.21.21.21 key tasman
    etr map-server 21.21.21.21 proxy-reply
    etr
    use-petr 21.21.21.21 priority 1 weight 100
    exit-service-ipv4
  !
  service ethernet
    itr map-resolver 5.5.5.5
    itr map-resolver 21.21.21.21
    itr
    etr map-server 21.21.21.21 key tasman
    etr map-server 21.21.21.21 proxy-reply
```

## Verifying Fabric Configuration

```

        etr
        exit-service-ethernet
    !
instance-id 0
    loc-reach-algorithm lsb-reports ignore
    dynamic-eid eid_10_56_25
        database-mapping 10.56.25.0/24 locator-set rloc_loopback
        exit-dynamic-eid
    !
service ipv4
    eid-table default
    database-mapping 26.26.26.26/32 locator-set rloc_loopback
    exit-service-ipv4
    !
exit-instance-id
!
instance-id 1
    service ethernet
    eid-table vlan 25
    flood arp-nd
    database-mapping mac locator-set rloc_loopback
    exit-service-ethernet
    !
exit-instance-id
!
instance-id 101
    service ipv4
    exit-service-ipv4
    !
exit-instance-id
!
instance-id 8188
    exit-instance-id
!
loc-reach-algorithm lsb-reports ignore
exit-router-lisp

```

To verify the operational status of LISP as configured on a device, use the following command:

FabricEdge# **show ip lisp**

Information applicable to all EID instances:	
Router-lisp ID:	0
Locator table:	default
Ingress Tunnel Router (ITR):	enabled
Egress Tunnel Router (ETR):	enabled
Proxy-ITR Router (PITR):	disabled
Proxy-ETR Router (PETR):	disabled
NAT-traversal Router (NAT-RTR):	disabled
Mobility First-Hop Router:	disabled
Map Server (MS):	disabled
Map Resolver (MR):	disabled
Mr-use-petr:	disabled
Delegated Database Tree (DDT):	disabled
Publication-Subscription:	enabled
Publisher(s):	*** NOT FOUND ***
ITR Map-Resolver(s):	21.21.21.21
ETR Map-Server(s):	21.21.21.21
xTR-ID:	0xD89893A6-0x98749B2C-0x89810431-0x92F33C9C
site-ID:	unspecified
ITR local RLOC (last resort):	*** NOT FOUND ***
ITR use proxy ETR RLOC(Encap IID):	21.21.21.21
ITR Solicit Map Request (SMR):	accept and process
Max SMRs per map-cache entry:	8 more specifics

```

Multiple SMR suppression time: 20 secs
ETR accept mapping data: disabled, verify disabled
ETR map-cache TTL: 1d00h
Locator Status Algorithms:
    RLOC-probe algorithm: disabled
    RLOC-probe on route change: N/A (periodic probing disabled)
    RLOC-probe on member change: disabled
    LSB reports: ignore
    IPv4 RLOC minimum mask length: /0
    IPv6 RLOC minimum mask length: /0
Map-cache:
    Map-cache limit: 32768
    Map-cache activity check period: 60 secs
    Persistent map-cache: disabled
Source locator configuration:
    GigabitEthernet1/0/1: 24.24.24.24 (Loopback0)
    Vlan25: 24.24.24.24 (Loopback0)
Database:
    Dynamic database mapping limit: 25000

```

To verify the operational status of the map cache on a device configured as an ITR or PITR, use the following command:

```

FabricEdge# show lisp instance-id iid ipv4 map-cache

LISP IPv4 Mapping Cache for EID-table default (IID 0), 5 entries

0.0.0.0/0, uptime: 2w5d, expires: never, via static-send-map-request
    Encapsulating to proxy ETR

10.56.25.0/24, uptime: 2w0d, expires: never, via dynamic-EID, send-map-request
    Encapsulating to proxy ETR

10.56.25.25/32, uptime: 2w5d, expires: 23:10:06, via map-reply, complete
    Locator      Uptime      State   Pri/Wgt     Encap-IID
    21.21.21.21  2w5d       up        0/0          -
    
22.0.0.0/8, uptime: 2w5d, expires: 00:04:54, via map-reply, forward-native
    Encapsulating to proxy ETR

26.26.26.26/32, uptime: 09:48:33, expires: 14:11:26, via map-reply, self, complete
    Locator      Uptime      State   Pri/Wgt     Encap-IID
    24.24.24.24  09:48:33   up, self  50/50        -

```

To verify the operational status of the database mapping on a device configured as an ETR, use the following command:

```

FabricEdge# show lisp instance-id iid ipv4 database

LISP ETR IPv4 Mapping Database for EID-table default (IID 0), LSBs: 0x1
Entries total 3, no-route 0, inactive 0

10.56.25.27/32, dynamic-eid eid_10_56_25, skip reg, inherited from default locator-set
rloc_loopback
    Uptime: 00:25:11, Last-change: 00:25:11
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10    cfg-intf   site-self, reachable

10.56.25.67/32, dynamic-eid eid_10_56_25, inherited from default locator-set rloc_loopback
    Uptime: 00:24:47, Last-change: 00:24:47
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State

```

## Verifying Fabric Configuration

```

24.24.24.24  10/10  cfg-intf  site-self, reachable

26.26.26.26/32, locator-set rloc_loopback
  Uptime: 2w5d, Last-change: 00:50:36
  Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10    cfg-intf   site-self, reachable

```

To verify the configured LISP sites on a LISP map server, use the following command:

```
FabricEdge# show lisp instance-id iid ipv4 server
```

```
LISP Site Registration Information
* = Some locators are down or unreachable
# = Some registrations are sourced by reliable transport
```

Site Name	Last Register	Up	Who Last Registered	Inst ID	EID Prefix
eca	never	no	--	0	10.56.25.0/24
	04:52:53	yes#	21.21.21.21:40875	0	10.56.25.25/32
	04:07:09	yes#	27.27.27.27:24949	0	10.56.25.64/32
	03:21:16	yes#	24.24.24.24:23672	0	10.56.25.67/32
	04:52:53	yes#	21.21.21.21:40875	0	23.23.23.23/32
	03:47:04	yes#	24.24.24.24:23672	0	26.26.26.26/32
	2w0d	yes#	27.27.27.27:24949	0	29.29.29.29/32
site_uci	never	no	--	4097	0.0.0.0/0

To verify the operational status of LISP sites, use the following command in FiaB node:

```
FabricEdge# show lisp instance-id 1 ethernet server
```

```
=====
Output for router lisp 0 instance-id 1
=====
LISP Site Registration Information
```

```
=====
Output for router lisp 0 instance-id 1
=====
LISP Site Registration Information
* = Some locators are down or unreachable
# = Some registrations are sourced by reliable transport
```

Site Name	Last Register	Up	Who Last Registered	Inst ID	EID Prefix
eca	never	no	--	1	any-mac
	04:10:37	yes#	27.27.27.27:24949	1	00b0.e19c.2578/48
	04:09:20	yes#	22.22.22.22:64083	1	00b0.e19c.fc40/48
	03:24:52	yes#	24.24.24.24:23672	1	dcce.c130.0b70/48
	03:23:39	yes#	22.22.22.22:64083	1	dcce.c130.9820/48

To verify the operational status of LISP sites, use the following command in FiaB node:

```
FabricEdge# show lisp instance-id 0 ipv4 server
```

```
LISP Site Registration Information
* = Some locators are down or unreachable
# = Some registrations are sourced by reliable transport
```

Site Name	Last Register	Up	Who Last Registered	Inst ID	EID Prefix
-----------	---------------	----	---------------------	---------	------------

eca	never	no	--	0	10.56.25.0/24
	6d18h	yes#	21.21.21.21:40875	0	10.56.25.25/32
	01:23:56	yes#	27.27.27.27:24949	0	10.56.25.64/32
	00:24:40	yes#	24.24.24.24:23672	0	10.56.25.72/32
	6d18h	yes#	21.21.21.21:40875	0	23.23.23.23/32
	6d17h	yes#	24.24.24.24:23672	0	26.26.26.26/32
	3w0d	yes#	27.27.27.27:24949	0	29.29.29.29/32

To verify the operational status of LISP sites on IPv4 database, use the following command in fabric edge node:

```
FabricEdge# show lisp instance-id 0 ipv4 database

LISP ETR IPv4 Mapping Database for EID-table default (IID 0), LSBs: 0x1
Entries total 3, no-route 0, inactive 0

10.56.25.27/32, dynamic-eid eid_10_56_25, skip reg, inherited from default locator-set
rloc_loopback
    Uptime: 00:25:54, Last-change: 00:25:54
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10   cfg-intf   site-self, reachable
10.56.25.72/32, dynamic-eid eid_10_56_25, inherited from default locator-set rloc_loopback
    Uptime: 00:25:25, Last-change: 00:25:25
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10   cfg-intf   site-self, reachable
26.26.26.26/32, locator-set rloc_loopback
    Uptime: 3w5d, Last-change: 6d17h
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10   cfg-intf   site-self, reachable
```

To verify the operational status of LISP sites on mac mapping database, use the following command on the FE node:

```
FabricEdge# show lisp instance-id 1 ethernet database

LISP ETR MAC Mapping Database for EID-table Vlan 25 (IID 1), LSBs: 0x1
Entries total 2, no-route 0, inactive 0

cc98.911b.73f1/48, dynamic-eid Auto-L2-group-1, skip reg, inherited from default locator-set
rloc_loopback
    Uptime: 00:00:49, Last-change: 00:00:49
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10   cfg-intf   site-self, reachable
dcce.c130.0b70/48, dynamic-eid Auto-L2-group-1, inherited from default locator-set
rloc_loopback
    Uptime: 00:00:50, Last-change: 00:00:50
    Domain-ID: unset
    Locator      Pri/Wgt  Source      State
    24.24.24.24  10/10   cfg-intf   site-self, reachable
```

