



Mobile Policy Infrastructure Commands

- [db balance, on page 1](#)
- [db global-settings, on page 1](#)
- [db global-settings timers, on page 2](#)
- [db spr, on page 3](#)

db balance

Configures the Balance database.

Privilege Security Administrator, Administrator

Command Modes Exec > Global Config

Syntax Description `db balance shard-count balance_db_shard_count`

shard-count *balance_db_shard_count*

Specify the Balance database's shard count.

Must be an integer.

Default Value: 1.

Usage Guidelines Use this command to configure the Balance database.

Example

The following command configures the Balance database's shard count to 1:

```
db balance shard-count 1
```

db global-settings

Configures global DB settings.

db global-settings timers

Privilege	Security Administrator, Administrator
Command Modes	Exec > Global Config
Syntax Description	<pre>global-settings db-replica replica_count</pre> <p>db-replica replica_count Specify the global DB replica count. Must be an integer. Default Value: 3.</p>
Usage Guidelines	Use this command to configure the global DB settings.

db global-settings timers

Configures global MongoDB timers.

Privilege	Security Administrator, Administrator
Command Modes	Exec > Global Config
Syntax Description	<pre>db global-settings timers { catchup-timeout-millis catchup_timeout election-timeout-millis election_timeout heartbeat-interval-millis heartbeat_interval }</pre> <p>heartbeat-interval-millis heartbeat_interval Specify the global heartbeat interval period, in milliseconds. Must be an integer. Default Value: 300.</p> <p>catchup-timeout-millis catchup_timeout Specify the global catchup timeout period, in milliseconds. Must be an integer. Default Value: 2000.</p> <p>election-timeout-millis election_timeout Specify the global election timeout period, in milliseconds. Must be an integer. Default Value: 2000.</p>
Usage Guidelines	Use this command to configure the global MongoDB timers.

db spr

Configures the SPR database.

Privilege Security Administrator, Administrator

Command Modes Exec > Global Config

Syntax Description **db spr shard-count *shard_count***

shard-count *shard_count*

Specify the SPR database's shard count.

Must be an integer.

Default Value: 1.

Usage Guidelines Use this command to configure the SPR database.

Example

The following command configures the SPR database's shard count to 20:

```
db spr shard-count 20
```

