

# Puenteo de respaldo sobre ISDN

## Contenido

[Introducción](#)

[prerrequisitos](#)

[Requisitos](#)

[Componentes Utilizados](#)

[Productos Relacionados](#)

[Convenciones](#)

[Configurar](#)

[Diagrama de la red](#)

[Configuraciones](#)

[Verificación](#)

[Comandos show en ROUTER1 cuando Serial0 está activo.](#)

[Comandos show en ROUTER1 cuando Serial0 está inactivo.](#)

[Troubleshooting](#)

[Recursos de resolución de problemas](#)

[Comandos para resolución de problemas](#)

[depurar salida en ENRUTADOR1 cuando serial0 desciende e ISDN se levanta](#)

[depurar salida en ENRUTADOR 1 cuando Serial0 regrese e ISDN interrumpe la llamada](#)

[Información Relacionada](#)

## Introducción

Este documento explica y proporciona un ejemplo de cómo configurar el puenteo de respaldo con ISDN. Esta configuración usa el método de interfaz de respaldo para identificar que el link principal está desactivado. Para más información sobre el respaldo, vea [configurar y resolver problemas el backup DDR](#).

En los entornos WAN interligados, la única solución de backup del Dial-on-Demand Routing (DDR) disponible es el uso del ISDN, pues el interligar sobre el async no se soporta.

Sea consciente que el interligar en una conexión ISDN tiende a mantener la conexión activa por mismo los períodos prolongados, si no permanentemente. Si la compañía telefónica (compañía telefónica) carga para el ISDN basado en el tiempo de conexión y el link serial se sigue que está abajo por mismo un tiempo prolongado, éste puede dar lugar a una cuenta muy grande.

**Nota:** Esta configuración es para un sitio y un canal B. Para más de un canal B, usted debe utilizar los Perfiles de marcado. (Refiera a los [Perfiles de marcado que configuran para interligar usando Configuración de isdn](#).)

Para la información sobre el configuración de Bridging en un entorno del NON-respaldo, vea el [Bridging Across ISDN](#).

# prerrequisitos

## Requisitos

Antes de utilizar esta configuración, asegúrese de que cumple con los siguientes requisitos:

- Poseer un conocimiento básico de ISDN.

## Componentes Utilizados

La información que contiene este documento se basa en las siguientes versiones de software y hardware.

- Cisco 2500 Series Router con una interfaz serial PÁLIDA y una interfaz BRI cada uno.
- Software Release 12.2(7b) de Cisco IOS®.

**Nota:** Esta configuración puede usarse con cualquier router que tenga un link de WAN (de serie) y un puerto BRI.

La información que contiene este documento se creó a partir de los dispositivos en un ambiente de laboratorio específico. Todos los dispositivos que se utilizan en este documento se pusieron en funcionamiento con una configuración verificada (predeterminada). Si la red está funcionando, asegúrese de haber comprendido el impacto que puede tener cualquier comando.

## Productos Relacionados

Esta configuración puede utilizarse con cualquier par de routers que ejecuten el software del IOS de Cisco y cada uno debe tener al menos una interfaz serial WAN y una interfaz BRI.

## Convenciones

Para obtener más información sobre las convenciones del documento, consulte [Convenciones de Consejos Técnicos de Cisco](#).

## Configurar

En esta sección encontrará la información para configurar las funciones descritas en este documento.

**Nota:** Para obtener información adicional sobre los comandos que se utilizan en este documento, use la Command Lookup Tool (solo para clientes [registrados](#)).

## Diagrama de la red

En este documento, se utiliza esta configuración de red:

## Configuraciones

En este documento, se utilizan estas configuraciones:

- [Router1](#)
- [Router2](#)

## Router1

```

!
hostname ROUTER1
!
!
username ROUTER2 password 0 same
!--- This is required for PPP Challenge Handshake
Authentication Protocol !--- (CHAP) authentication
during dial backup. !! isdn switch-type basic-5ess !---
The ISDN switch type for this circuit. !--- Obtain this
information from the Telco. !--- This ISDN switch type
is specific to the United States, !--- and could change
based on the requirements of the country and Telco. !
interface Ethernet0 ip address 172.16.55.33
255.255.255.240 no ip directed-broadcast no ip mroute-
cache bridge-group 1 !--- Assign this interface to
bridge-group 1. !--- Frames are bridged only among
interfaces in the same group. !--- Note that the BRI
interface and serial interface are also !--- in this
bridge-group 1. ! interface Serial0 description Serial
link to ROUTER2 backup interface BRI0 !--- This defines
the backup interface. !--- Cisco IOS Software tracks the
Serial0 interface, and !--- uses BRI0 if Serial0 fails.
ip address 172.16.54.1 255.255.255.0 no ip directed-
broadcast no ip mroute-cache no fair-queue bridge-group
1 !--- Enable bridging on Serial0 for normal operation.
! interface BRI0 description ISDN to ROUTER2 ip address
172.16.53.19 255.255.255.240 no ip directed-broadcast
encapsulation ppp no ip mroute-cache dialer map bridge
name ROUTER2 broadcast 5552000 !--- The broadcast
keyword is required to initiate the ISDN call. !---
Dialer map bridge to the remote router. The statement
includes !--- the name of the remote router and the
phone number to be dialed. !--- Note that this dialer
map statement includes the keyword bridge, !--- and does
not include the IP address of the peer, as required for
!--- IP routing-based dialer maps. dialer-group 1 !---
Defines the interesting traffic as configured in the
dialer-list. isdn switch-type basic-5ess !--- Check with
your Telco for the correct values. ppp authentication
chap bridge-group 1 !--- Enable bridging on BRI0. !
dialer-list 1 protocol bridge permit !--- Defines the
interesting traffic. In this case, all bridged traffic.
bridge 1 protocol ieee !--- Defines the type of Spanning
Tree Protocol (STP) used for the !--- interface in
bridge-group 1. Here, the IEEE STP is used. !--- The
IEEE 802.1D STP is the preferred way to run the bridge.
!

```

## Router2

```

hostname router2
!
!
username ROUTER1 password 0 same
!--- Required for PPP CHAP Authentication during dial
backup. ! isdn switch-type basic-5ess !--- Check with
your Telco at the Router2 side for the correct values. !
interface Ethernet0 ip address 172.16.55.2
255.255.255.240 bridge-group 1 !--- Enable bridging on

```

```

Ethernet0. ! interface Serial0 description Serial link
to ROUTER1 !--- The backup interface bri0 command is not
required on this side, !--- because it is sufficient if
one side tracks the serial interface. ip address
172.16.54.2 255.255.255.0 no fair-queue bridge-group 1
!--- Enable bridging on Serial0 for normal operation.
interface BRI0 description ISDN to ROUTER1 ip address
172.16.53.17 255.255.255.240 encapsulation ppp no ip
mroute-cache dialer map bridge name ROUTER1 broadcast
5551000 !--- The broadcast keyword is required to
initiate the ISDN call. dialer-group 1 !--- Defines the
interesting traffic as configured in the dialer-list.
isdn switch-type basic-5ess !--- Check with your Telco
at the Router2 side for the correct values. ppp
authentication chap bridge-group 1 !--- Enable bridging
on BRI0. ! dialer-list 1 protocol bridge permit !---
Defines the interesting traffic. In this case, all
bridged traffic. bridge 1 protocol ieee !--- Defines the
type of STP used for the interface in !--- bridge-group
1. Here the IEEE STP is used. !--- The IEEE 802.1D STP
is the preferred way to run the bridge. !

```

## Verificación

En esta sección encontrará información que puede utilizar para comprobar que su configuración funcione correctamente.

La herramienta [Output Interpreter](#) (sólo para clientes [registrados](#)) permite utilizar algunos comandos “show” y ver un análisis del resultado de estos comandos.

- **isdn status de la demostración** — visualiza el Layer 1 (L1), la capa 2 (L2), y acoda 3 el estatus (L3) de las interfaces de ISDN.
- **marcador de la demostración** — visualiza el estatus del marcador y el estado individual de los canales ISDN.
- **Bridge de la demostración** — clases de las visualizaciones de entradas en el Bridge Forwarding Database.
- **interfaz de la demostración** — visualiza el estatus de las diversas interfaces, tales como el serial y las interfaces BRI.
- **atravesar-árbol de la demostración** — visualiza la topología del árbol de expansión sabida al router.

## Comandos show en ROUTER1 cuando Serial0 está activo.

```

ROUTER1# show isdn status Global ISDN Switchtype = basic-5ess ISDN BRI0 interface dsl 0,
interface ISDN Switchtype = basic-5ess Layer 1 Status: DEACTIVATED Layer 2 Status: Layer 2 NOT
Activated Layer 3 Status: 0 Active Layer 3 Call(s) Activated dsl 0 CCBs = 0 The Free Channel
Mask: 0x80000003 Number of L2 Discards = 36, L2D_Task Discards = 35 Total Allocated ISDN CCBS =
0 ROUTER1# show dialer BRI0 - dialer type = ISDN Dial String Successes Failures Last DNIS Last
status 5552000 29 977 00:45:08 successful 0 incoming call(s) have been screened. 0 incoming
call(s) rejected for callback. BRI0:1 - dialer type = ISDN Idle timer (120 secs), Fast idle
timer (20 secs) Wait for carrier (30 secs), Re-enable (15 secs) Dialer state is shutdown BRI0:2
- dialer type = ISDN Idle timer (120 secs), Fast idle timer (20 secs) Wait for carrier (30
secs), Re-enable (15 secs) Dialer state is shutdown ROUTER1# show bridge Total of 300 station
blocks, 298 free Codes: P - permanent, S - self Bridge Group 1: Address Action Interface Age RX
count TX count 0000.0c76.2882 forward Serial0 0 5 4 !--- Bridging traffic goes through Serial0.
00d0.58ad.ae13 forward Ethernet0 0 42 5

```

## Comandos show en ROUTER1 cuando Serial0 está inactivo.

```
ROUTER1# show isdn status Global ISDN Switchtype = basic-5ess ISDN BRI0 interface dsl 0,
interface ISDN Switchtype = basic-5ess Layer 1 Status: ACTIVE Layer 2 Status: TEI = 114, Ces =
1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED !--- ISDN L1 and L2 will be up (when Serial0
fails) !--- even if interesting traffic is not present. Layer 3 Status: 1 Active Layer 3 Call(s)
Activated dsl 0 CCBS = 1 CCB:callid=8484, sapi=0, ces=1, B-chan=1, calltype=DATA The Free
Channel Mask: 0x80000002 Total Allocated ISDN CCBS = 1 ROUTER1# show dialer BRI0 - dialer type =
ISDN Dial String Successes Failures Last DNIS Last status 5552000 30 977 00:00:16 successful 0
incoming call(s) have been screened. 0 incoming call(s) rejected for callback. BRI0:1 - dialer
type = ISDN Idle timer (120 secs), Fast idle timer (20 secs) Wait for carrier (30 secs), Re-
enable (15 secs) Dialer state is data link layer up Dial reason: bridge (0xFFFF) Time until
disconnect 106 secs Connected to 5552000 (ROUTER2) BRI0:2 - dialer type = ISDN Idle timer (120
secs), Fast idle timer (20 secs) Wait for carrier (30 secs), Re-enable (15 secs) Dialer state is
idle ROUTER1# show bridge Total of 300 station blocks, 298 free Codes: P - permanent, S - self
Bridge Group 1: Address Action Interface Age RX count TX count 0000.0c76.2882 forward BRI0 0 5 4
!--- Bridging traffic now goes through BRI0. 00d0.58ad.ae13 forward Ethernet0 0 5 5
```

## Troubleshooting

En esta sección encontrará información que puede utilizar para solucionar problemas de configuración.

### Recursos de resolución de problemas

Utilice estos recursos como sea necesario:

- [Soporte de tecnología ISDN](#)
- [Resolución de problemas de líneas en serie](#)
- [Conexión adosada HDLC](#)

### Comandos para resolución de problemas

La herramienta [Output Interpreter](#) (sólo para clientes [registrados](#)) permite utilizar algunos comandos “show” y ver un análisis del resultado de estos comandos.

**Nota:** [Antes de ejecutar un comando de depuración, consulte Información importante sobre comandos de depuración.](#)

- **debug dialer** — proporciona la información sobre los eventos de la interfaz del dialer.
- **debug isdn event** — las visualizaciones hacen el debug de los mensajes relacionados con la actividad ISDN que ocurre en el lado del usuario de la interfaz de ISDN.
- **debug ISDN q931** — proporciona la información sobre la configuración de la llamada y cierre de las conexiones de red ISDN (L3) entre el router local (lado del usuario) y la red.
- **el debug isdn q921** — las visualizaciones hace el debug de los mensajes relacionados con los procedimientos de acceso de la capa del link de datos (L2) que ocurren en el router en el canal D (LAPD) de su interfaz de ISDN.
- **negociación ppp del debug** — las visualizaciones hacen el debug de los mensajes relacionados con la negociación de opciones PPP y los parámetros del protocolo network control (NCP).
- **autenticación PPP del debug** — Los mensajes del debug de las visualizaciones se relacionaron con el intercambio de los paquetes de la GRIETA y del protocolo password

authentication (PAP).

## depurar salida en ENRUTADOR1 cuando serial0 desciende e ISDN se levanta

```
ROUTER1# show debug Dial on demand: Dial on demand events debugging is on PPP: PPP
authentication debugging is on PPP protocol negotiation debugging is on ISDN: ISDN events
debugging is on ISDN Q921 packets debugging is on ISDN Q931 packets debugging is on ROUTER1# !--
- Interface serial0 goes down. ROUTER1# 00:56:53: %LINK-3-UPDOWN: Interface Serial0, changed
state to down *Mar 1 00:56:53.103: ISDN BR0 EVENT: isdn_sw_cstate: State = 0, Old State = 6
00:56:53: %LINK-3-UPDOWN: Interface BRI0:1, changed state to down *Mar 1 00:56:53.107: BR0:1
LCP: State is Closed *Mar 1 00:56:53.111: BR0:1 DDR: disconnecting call 00:56:53: %LINK-3-
UPDOWN: Interface BRI0:2, changed state to down *Mar 1 00:56:53.119: BR0:2 LCP: State is Closed
*Mar 1 00:56:53.119: BR0:2 DDR: disconnecting call *Mar 1 00:56:53.127: ISDN BR0 EVENT:
isdn_sw_cstate: State = 4, Old State = 6 *Mar 1 00:56:53.135: ISDN BR0 EVENT: isdn_sw_cstate:
State = 4, Old State = 6 *Mar 1 00:56:53.567: ISDN BR0: RX <- IDCKRQ ri=0 ai=127 *Mar 1
00:56:53.567: ISDN Recvd L1 prim 3 dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.571: ISDN BR0: L1
persistent Deactivated *Mar 1 00:56:53.571: ISDN Recvd L1 prim 7 dsl 0 state 3 ctrl_state 0 *Mar
1 00:56:53.575: ISDN BR0: Recvd MPH_IIC_IND from L1 *Mar 1 00:56:53.575: ISDN Recvd L1 prim 7
dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.579: ISDN BR0: Recvd MPH_IIC_IND from L1 *Mar 1
00:56:53.579: ISDN Recvd L1 prim 1 dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.583: ISDN BR0: L1
is IF_ACTIVE *Mar 1 00:56:53.583: ISDN BR0 EVENT: isdn_sw_cstate: State = 4, Old State = 6 *Mar
1 00:56:53.587: ISDN BR0: L2-TERM: ces/tei=1/0 AWAIT_ESTABLISH->TERM_DOWN *Mar 1 00:56:53.591:
ISDN BR0: Incoming call id = 0x0010, dsl 0 *Mar 1 00:56:53.595: ISDN BR0: L2-TERM: ces/tei=1/0
TERM_DOWN->AWAIT_ESTABLISH 00:56:53: %LINK-3-UPDOWN: Interface BRI0, changed state to up *Mar 1
00:56:53.631: ISDN BR0 EVENT: isdn_sw_cstate: State = 4, Old State = 6 *Mar 1 00:56:53.655: ISDN
BR0: TX -> IDREQ ri=48769 ai=127 00:56:54: %LINEPROTO-5-UPDOWN: Line protocol on Interface
Serial0, changed state to down *Mar 1 00:56:54.387: ISDN BR0: RX <- IDCKRQ ri=0 ai=127 *Mar 1
00:56:55.655: ISDN BR0: TX -> IDREQ ri=42642 ai=127 *Mar 1 00:56:55.699: ISDN BR0: RX <- IDASSN
ri=42642 ai=68 *Mar 1 00:56:55.791: ISDN BR0: TX -> SABMEp c/r=0 sapi=0 tei=68 *Mar 1
00:56:55.823: ISDN BR0: RX <- Uaf c/r=0 sapi=0 tei=68 00:56:55: %ISDN-6-LAYER2UP: Layer 2 for
Interface BR0, TEI 68 changed to up *Mar 1 00:56:55.831: ISDN BR0: L2-TERM: ces/tei=1/68
AWAIT_ESTABLISH->ESTABLISHED !--- Interesting traffic has not arrived yet from Host1, !--- but
ISDN L1 and L2 are up now. ROUTER1# show isdn stat Global ISDN Switchtype = basic-5ess ISDN BRI0
interface dsl 0, interface ISDN Switchtype = basic-5ess Layer 1 Status: ACTIVE Layer 2 Status:
TEI = 68, Ces = 1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED I_Queue_Len 0, UI_Queue_Len 0
Layer 3 Status: 0 Active Layer 3 Call(s) Active dsl 0 CCBs = 0 The Free Channel Mask: 0x80000003
Number of L2 Discards = 0, L2 Session ID = 34 Total Allocated ISDN CCBs = 0 ROUTER1# *Mar 1
00:57:25.839: ISDN BR0: TX -> RRP sapi=0 tei=68 nr=0 *Mar 1 00:57:25.871: ISDN BR0: RX <- RRF
sapi=0 tei=68 nr=0 ROUTER1# !--- Interesting traffic arrives now, !--- which triggers ISDN
Dialup (see below). *Mar 1 00:57:32.519: BR0 DDR: Dialing cause bridge (0xFFFF) *Mar 1
00:57:32.519: BR0 DDR: Attempting to dial 5552000 *Mar 1 00:57:32.523: ISDN BR0: Outgoing call
id = 0x800E, dsl 0 *Mar 1 00:57:32.527: ISDN BR0: Event: Call to 5552000 at 64 Kb/s *Mar 1
00:57:32.527: ISDN BR0: process_bri_call(): call id 0x800E, called_number 5552000, speed 64,
call type DATA *Mar 1 00:57:32.531: CCBRI_Go Fr Host InPkgInfo (Len=22) : *Mar 1 00:57:32.535: 1
0 1 80 E 0 4 2 88 90 18 1 83 2C 7 35 35 35 32 30 30 30 *Mar 1 00:57:32.543: *Mar 1 00:57:32.547:
CC_CHAN_GetIdleChanbri: dsl 0 *Mar 1 00:57:32.547: Found idle channel B1 *Mar 1 00:57:32.563:
ISDN BR0: TX -> INFOc sapi=0 tei=68 ns=0 nr=0 i=0x08010E05040288901801832C0735353532303030 *Mar
1 00:57:32.583: SETUP pd = 8 callref = 0x0E *Mar 1 00:57:32.591: Bearer Capability i = 0x8890
*Mar 1 00:57:32.599: Channel ID i = 0x83 *Mar 1 00:57:32.603: Keypad Facility i = '5552000' *Mar
1 00:57:32.867: ISDN BR0: RX <- INFOc sapi=0 tei=68 ns=0 nr=1 i=0x08018E02180189 *Mar 1
00:57:32.875: CALL_PROC pd = 8 callref = 0x8E *Mar 1 00:57:32.883: Channel ID i = 0x89 *Mar 1
00:57:32.899: ISDN BR0: TX -> RRR sapi=0 tei=68 nr=1 *Mar 1 00:57:32.907: CCBRI_Go Fr L3 pkt
(Len=7) : *Mar 1 00:57:32.907: 2 1 E 98 18 1 89 *Mar 1 00:57:32.911: *Mar 1 00:57:32.915: ISDN
BR0: LIF_EVENT: ces/callid 1/0x800E HOST_PROCEEDING *Mar 1 00:57:32.919: ISDN BR0:
HOST_PROCEEDING *Mar 1 00:57:32.919: ISDN BR0: HOST_MORE_INFO *Mar 1 00:57:33.159: ISDN BR0: RX
<- INFOc sapi=0 tei=68 ns=1 nr=1 i=0x08018E07 *Mar 1 00:57:33.167: CONNECT pd = 8 callref = 0x8E
*Mar 1 00:57:33.183: ISDN BR0: TX -> RRR sapi=0 tei=68 nr=2 *Mar 1 00:57:33.191: CCBRI_Go Fr L3
pkt (Len=4) : *Mar 1 00:57:33.191: 7 1 E 91 *Mar 1 00:57:33.195: *Mar 1 00:57:33.199: ISDN BR0:
LIF_EVENT: ces/callid 1/0x800E HOST_CONNECT 00:57:33: %LINK-3-UPDOWN: Interface BRI0:1, changed
state to up *Mar 1 00:57:33.215: ISDN: get_isdn_service_state(): idb 0x19F4D8 bchan 2 is_isdn 1
Not a Pri *Mar 1 00:57:33.215: BR0:1 PPP: Treating connection as a callout *Mar 1 00:57:33.219:
BR0:1 PPP: Phase is ESTABLISHING, Active Open [0 sess, 1 load] *Mar 1 00:57:33.223: BR0:1 LCP: O
```

```
CONFREQ [Closed] id 27 len 15 *Mar 1 00:57:33.227: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar
1 00:57:33.231: BR0:1 LCP: MagicNumber 0x6091A5F6 (0x05066091A5F6) *Mar 1 00:57:33.235: ISDN
BR0: Event: Connected to 5552000 on B1 at 64 Kb/s *Mar 1 00:57:33.247: ISDN BR0: TX -> INFOc
sapi=0 tei=68 ns=1 nr=2 i=0x08010E0F *Mar 1 00:57:33.251: CONNECT_ACK pd = 8 callref = 0x0E *Mar
1 00:57:33.267: BR0:1 LCP: I CONFREQ [REQsent] id 4 len 15 *Mar 1 00:57:33.271: BR0:1 LCP:
AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.275: BR0:1 LCP: MagicNumber 0x6062D6EA
(0x05066062D6EA) *Mar 1 00:57:33.279: BR0:1 LCP: O CONFACK [REQsent] id 4 len 15 *Mar 1
00:57:33.283: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.287: BR0:1 LCP:
MagicNumber 0x6062D6EA (0x05066062D6EA) *Mar 1 00:57:33.291: BR0:1 LCP: I CONFACK [ACKsent] id
27 len 15 *Mar 1 00:57:33.291: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.295:
BR0:1 LCP: MagicNumber 0x6091A5F6 (0x05066091A5F6) *Mar 1 00:57:33.299: BR0:1 LCP: State is Open
*Mar 1 00:57:33.303: BR0:1 PPP: Phase is AUTHENTICATING, by both [0 sess, 1 load] *Mar 1
00:57:33.307: BR0:1 CHAP: O CHALLENGE id 14 len 28 from "ROUTER1" *Mar 1 00:57:33.319: BR0:1
CHAP: I CHALLENGE id 4 len 28 from "ROUTER2" *Mar 1 00:57:33.327: BR0:1 CHAP: O RESPONSE id 4
len 28 from "ROUTER1" *Mar 1 00:57:33.335: ISDN BR0: RX <- RRr sapi=0 tei=68 nr=2 *Mar 1
00:57:33.351: BR0:1 CHAP: I SUCCESS id 4 len 4 *Mar 1 00:57:33.367: BR0:1 CHAP: I RESPONSE id 14
len 28 from "ROUTER2" *Mar 1 00:57:33.371: BR0:1 CHAP: O SUCCESS id 14 len 4 *Mar 1
00:57:33.375: BR0:1 PPP: Phase is UP [0 sess, 0 load] *Mar 1 00:57:33.379: BR0:1 BNCP: O CONFREQ
[Closed] id 14 len 4 *Mar 1 00:57:33.387: BR0:1 CDPCP: O CONFREQ [Closed] id 14 len 4 *Mar 1
00:57:33.395: BR0:1 BNCP: I CONFREQ [REQsent] id 4 len 4 *Mar 1 00:57:33.399: BR0:1 BNCP: O
CONFACK [REQsent] id 4 len 4 *Mar 1 00:57:33.403: BR0:1 IPCP: I CONFREQ [Not negotiated] id 4
len 10 *Mar 1 00:57:33.407: BR0:1 IPCP: Address 172.16.53.17 (0x0306AC103511) *Mar 1
00:57:33.415: BR0:1 LCP: O PROTREJ [Open] id 28 len 16 protocol IPCP
(0x80210104000A0306AC103511) *Mar 1 00:57:33.419: BR0:1 CDPCP: I CONFREQ [REQsent] id 4 len 4
*Mar 1 00:57:33.423: BR0:1 CDPCP: O CONFACK [REQsent] id 4 len 4 *Mar 1 00:57:33.427: BR0:1
BNCP: I CONFACK [ACKsent] id 14 len 4 *Mar 1 00:57:33.431: BR0:1 BNCP: State is Open *Mar 1
00:57:33.435: BR0:1 CDPCP: I CONFACK [ACKsent] id 14 len 4 *Mar 1 00:57:33.439: BR0:1 CDPCP:
State is Open *Mar 1 00:57:33.443: BR0:1 DDR: dialer protocol up 00:57:34: %LINEPROTO-5-UPDOWN:
Line protocol on Interface BRI0:1, changed state to up 00:57:39: %ISDN-6-CONNECT: Interface
BRI0:1 is now connected to 5552000 ROUTER2 ROUTER1# ROUTER1# show isdn status Global ISDN
Switchtype = basic-5ess ISDN BRI0 interface dsl 0, interface ISDN Switchtype = basic-5ess Layer
1 Status: ACTIVE Layer 2 Status: TEI = 68, Ces = 1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED
I_Queue_Len 0, UI_Queue_Len 0 Layer 3 Status: 1 Active Layer 3 Call(s) CCB:callid=800E, sapi=0,
ces=1, B-chan=1, calltype=DATA Active dsl 0 CCBs = 1 The Free Channel Mask: 0x80000002 Number of
L2 Discards = 0, L2 Session ID = 34 Total Allocated ISDN CCBs = 1 *Mar 1 00:58:03.343: ISDN BR0:
TX -> RRp sapi=0 tei=68 nr=2 *Mar 1 00:58:03.379: ISDN BR0: RX <- RRf sapi=0 tei=68 nr=2pann
ROUTER1# show spanning-tree Bridge group 1 is executing the ieee compatible Spanning Tree
protocol Bridge Identifier has priority 32768, address 0060.5cf4.a9a8 Configured hello time 2,
max age 20, forward delay 15 Current root has priority 32768, address 0060.5cf4.a955 Root port
is 3 (BRI0), cost of root path is 15625 Topology change flag set, detected flag not set Number
of topology changes 10 last change occurred 00:01:15 ago from Serial0 Times: hold 1, topology
change 35, notification 2 hello 2, max age 20, forward delay 15 Timers: hello 0, topology change
0, notification 0, aging 15 Port 2 (Ethernet0) of Bridge group 1 is forwarding Port path cost
100, Port priority 128, Port Identifier 128.2. Designated root has priority 32768, address
0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8 Designated port id
is 128.2, designated path cost 15625 Timers: message age 0, forward delay 0, hold 0 Number of
transitions to forwarding state: 2 BPDU: sent 751, received 0 Port 3 (BRI0) of Bridge group 1 is
forwarding !--- BRI Interface forwards the bridged traffic now. Port path cost 15625, Port
priority 128, Port Identifier 128.3. Designated root has priority 32768, address 0060.5cf4.a955
Designated bridge has priority 32768, address 0060.5cf4.a955 Designated port id is 128.3,
designated path cost 0 Timers: message age 2, forward delay 0, hold 0 Number of transitions to
forwarding state: 3 BPDU: sent 1014, received 608 Port 6 (Serial0) of Bridge group 1 is down
Port path cost 647, Port priority 128, Port Identifier 128.6. Designated root has priority
32768, address 0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8
Designated port id is 128.6, designated path cost 15625 Timers: message age 0, forward delay 0,
hold 0 Number of transitions to forwarding state: 1 BPDU: sent 15, received 27 ROUTER1# *Mar 1
00:58:33.387: ISDN BR0: TX -> RRp sapi=0 tei=68 nr=2 *Mar 1 00:58:33.423: ISDN BR0: RX <- RRF
sapi=0 tei=68 nr=2
```

## [depurar salida en ENRUTADOR 1 cuando Serial0 regrese e ISDN interrumpe la llamada](#)

```
00:58:37: %LINK-3-UPDOWN: Interface Serial0, changed state to up *Mar 1 00:58:37.671: BR0:1 DDR:
```

disconnecting call \*Mar 1 00:58:37.675: BR0:2 DDR: disconnecting call \*Mar 1 00:58:37.675: ISDN  
BR0: Event: Hangup call to call id 0x800E \*Mar 1 00:58:37.679: ISDN BR0: process\_disconnect():  
call id 0x800E, call type is DATA, b\_idb 0x19F4D8, ces 1, cause Normal call clearing(0x10)  
00:58:37: %ISDN-6-DISCONNECT: Interface BRI0:1 disconnected from 5552000 ROUTER2, call lasted 64  
seconds \*Mar 1 00:58:37.691: ISDN: get\_isdn\_service\_state(): idb 0x19F4D8 bchan 2 is\_isdn 1 Not  
a Pri \*Mar 1 00:58:37.695: CCBRI\_Go Fr Host InPkgInfo (Len=13) : \*Mar 1 00:58:37.699: 5 0 1 80 E  
3 8 1 90 8 2 80 90 \*Mar 1 00:58:37.703: \*Mar 1 00:58:37.719: ISDN BR0: TX -> INFOc sapi=0 tei=68  
ns=2 nr=2 i=0x08010E4508028090 \*Mar 1 00:58:37.727: DISCONNECT pd = 8 callref = 0x0E \*Mar 1  
00:58:37.735: Cause i = 0x8090 - Normal call clearing \*Mar 1 00:58:37.743: ISDN BR0 EVENT:  
isdn\_sw\_cs!!!!!!!!!!!!!!!!!!!!!!!!!!!!tate: State = 6, Old State = 4 00:58:37: %LINK-3-UPDOWN: Interface  
BRI0:1, changed state to down \*Mar 1 00:58:37.751: BR0:1 BNCP: State is Closed \*Mar 1  
00:58:37.755: BR0:1 CDPCP: State is Closed \*Mar 1 00:58:37.755: BR0:1 PPP: Phase is TERMINATING  
[0 sess, 1 load] \*Mar 1 00:58:37.759: BR0:1 LCP: State is Closed \*Mar 1 00:58:37.763: BR0:1 PPP:  
Phase is DOWN [0 sess, 1 load] \*Mar 1 00:58:37.763: BR0:1 DDR: disconnecting call \*Mar 1  
00:58:37.775: ISDN Recvd L1 prim 3 dsl 0 state 1 ctrl\_state 0 \*Mar 1 00:58:37.779: ISDN BR0:  
Physical layer is IF\_DOWN \*Mar 1 00:58:37.783: ISDN BR0: Shutting down ME 00:58:37: %ISDN-6-  
LAYER2DOWN: Layer 2 for Interface BRI0, TEI 68 changed to down \*Mar 1 00:58:37.791: ISDN BR0:  
L2-TERM: ces/tei=1/68 ESTABLISHED->TERM\_DOWN \*Mar 1 00:58:37.795: ISDN BR0: LIF\_EVENT:  
ces/callid 1/0x800E HOST\_DISCONNECT\_ACK \*Mar 1 00:58:37.803: ISDN: get\_isdn\_service\_state(): idb  
0x19F4D8 bchan 2 is\_isdn 1 Not a Pri \*Mar 1 00:58:37.807: ISDN BR0: HOST\_DISCONNECT\_ACK: call  
type is DATA 00:58:37: %LINK-3-UPDOWN: Interface BRI0:1, changed state to down \*Mar 1  
00:58:37.815: BR0:1 LCP: State is Closed \*Mar 1 00:58:37.815: BR0:1 DDR: disconnecting call \*Mar  
1 00:58:37.819: ISDN BR0: Shutting down ISDN Layer 3 00:58:37: %ISDN-6-LAYER2DOWN: Layer 2 for  
Interface BR0, TEI 68 changed to down 00:58:37: %LINK-5-CHANGED: Interface BRI0, changed state  
to standby mode \*Mar 1 00:58:37.847: ISDN BR0 EVENT: isdn\_sw\_cstate: State = 6, Old State = 4  
00:58:37: %LINK-3-UPDOWN: Interface BRI0:2, changed state to down \*Mar 1 00:58:37.855: BR0:2  
LCP: State is Closed \*Mar 1 00:58:37.855: BR0:2 DDR: disconnecting call \*Mar 1 00:58:37.895:  
ISDN BR0: Incoming call id = 0x0011, dsl 0 \*Mar 1 00:58:37.895: ISDN BR0: L2-TERM: ces/tei=1/0  
TERM\_DOWN->AWAIT\_ESTABLISH \*Mar 1 00:58:37.935: ISDN BR0: Activating 00:58:38: %LINEPROTO-5-  
UPDOWN: Line protocol on Interface Serial0, changed state to up 00:58:38: %LINEPROTO-5-UPDOWN:  
Line protocol on Interface BRI0:1, changed state to down \*Mar 1 00:58:39.939: ISDN BR0: Could  
not bring up interface \*Mar 1 00:58:39.943: ISDN BR0: Shutting down ISDN Layer 3 \*Mar 1  
00:58:39.963: ISDN BR0: Activating \*Mar 1 00:58:41.943: ISDN BR0: Could not bring up interface  
\*Mar 1 00:58:41.947: ISDN BR0: Shutting down ISDN Layer 3 \*Mar 1 00:58:41.947: ISDN BR0:  
Activating ROUTER1# ROUTER1# **show isdn status** Global ISDN Switchtype = basic-5ess ISDN BRI0  
interface dsl 0, interface ISDN Switchtype = basic-5ess Layer 1 Status: **DEACTIVATED** Layer 2  
Status: **Layer 2 NOT Activated !---** *ISDN L1 and L2 are back to the deactivated state.* Layer 3  
Status: 0 Active Layer 3 Call(s) Active dsl 0 CCBs = 0 The Free Channel Mask: 0x80000003 Number  
of L2 Discards = 0, L2 Session ID = 39 Total Allocated ISDN CCBs = 0 ROUTER1# \*Mar 1  
00:58:49.951: ISDN BR0: Could not bring up interface \*Mar 1 00:58:49.951: ISDN BR0: Shutting  
down ISDN Layer 3 ROUTER1# ROUTER1# **show spanning-tree** Bridge group 1 is executing the ieee  
compatible Spanning Tree protocol Bridge Identifier has priority 32768, address 0060.5cf4.a9a8  
Configured hello time 2, max age 20, forward delay 15 Current root has priority 32768, address  
0060.5cf4.a955 Root port is 6 (Serial0), cost of root path is 647 Topology change flag not set,  
detected flag not set Number of topology changes 13 last change occurred 00:28:23 ago from  
Serial0 Times: hold 1, topology change 35, notification 2 hello 2, max age 20, forward delay 15  
Timers: hello 0, topology change 0, notification 0, aging 300 Port 2 (Ethernet0) of Bridge group  
1 is forwarding Port path cost 100, Port priority 128, Port Identifier 128.2. Designated root  
has priority 32768, address 0060.5cf4.a955 Designated bridge has priority 32768, address  
0060.5cf4.a9a8 Designated port id is 128.2, designated path cost 647 Timers: message age 0,  
forward delay 0, hold 0 Number of transitions to forwarding state: 2 BPDU: sent 1633, received 0  
Port 3 (BRI0) of **Bridge group 1 is down !---** *BRI0 is in the down state when Serial 0 is up.* Port  
path cost 15625, Port priority 128, Port Identifier 128.3. Designated root has priority 32768,  
address 0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8 Designated  
port id is 128.3, designated path cost 647 Timers: message age 0, forward delay 0, hold 0 Number  
of transitions to forwarding state: 3 BPDU: sent 1014, received 622 Port 6 (Serial0) of **Bridge  
group 1 is forwarding !---** *Serial0 forwards the bridged traffic now.* Port path cost 647, Port  
priority 128, Port Identifier 128.6. Designated root has priority 32768, address 0060.5cf4.a955  
Designated bridge has priority 32768, address 0060.5cf4.a955 Designated port id is 128.6,  
designated path cost 0 Timers: message age 1, forward delay 0, hold 0 Number of transitions to  
forwarding state: 2 BPDU: sent 18, received 896 ROUTER1#

## [Información Relacionada](#)



- [Conexión mediante puentes a través de ISDN](#)
- [Copia de seguridad de BRI ISDN con interfaz de copia de seguridad](#)
- [Configuración de respaldo ISDA multilink BRI con vigilancia de marcador](#)
- [Configuración de respaldo BRI ISDN con vigilancia de programas dialer](#)
- [Configuración de respaldo ISDN con rutas estáticas flotantes](#)
- [DDR de respaldo mediante BRI y el comando backup interface](#)
- [Configuración de la interfaz de respaldo BRI con perfiles de marcado](#)
- [Configuración de respaldo DDR mediante BRI y la función de control de discado](#)
- [Configuración de respaldo ISDN para links WAN mediante el uso de rutas flotantes](#)
- [Configuración de respaldo para Frame Relay](#)
- [Configuración de Dial Backup para Líneas Seriales](#)
- [El dial del Cisco IOS mantiene los comandos](#)
- [Soporte de Tecnología de Discado y Acceso](#)
- [Soporte Técnico y Documentación - Cisco Systems](#)