

Depuración del proveedor de servicio de telefonía de voz

Contenido

[Introducción](#)

[Antes de comenzar](#)

[Convenciones](#)

[prerrequisitos](#)

[Componentes Utilizados](#)

[Comando T.38 debug vtsp all que muestra la descarga de Fax Codec](#)

[Ejemplo de trabajo del comando debug vtsp all de VoFR](#)

[Router de origen](#)

[Router de terminación](#)

[Información Relacionada](#)

[Introducción](#)

Este documento proporciona dos capturas de la salida del comando debug vtsp all para una sola llamada que pasó con éxito un fax. El primer está para el fax de T.38, pero es también relevante para el Fax Relay sobre la voz sobre IP (VoIP). Este resultado contiene comentarios para ejemplificar el proceso para identificar que el códec del fax se ha descargado y utilizado. La segunda decodificación es para Voz sobre Frame Relay (VoFR) y se deja sin comentarios. El vtsp del debug toda la salida no contiene mucha información de una perspectiva del protocolo T.30, sino que proporciona la información del estado útil del router por ejemplo:

- Confirmación que el router ha ingresado al modo fax.
- Velocidad de fax, códec y si se usó ECM (Modo de corrección de errores)
- Confirmación que el gateway de terminación recibió un tono del fax de la máquina de fax terminal

[Antes de comenzar](#)

[Convenciones](#)

Para obtener más información sobre las convenciones del documento, consulte [Convenciones de Consejos Técnicos de Cisco](#).

[prerrequisitos](#)

No hay requisitos previos específicos para este documento.

Componentes Utilizados

La información en este documento se basa principalmente en la versión de software del IOS de Cisco 12.2(5), sin embargo, la mayor parte de la información también debería ser útil para otras versiones de software del IOS de Cisco.

La información que se presenta en este documento se originó a partir de dispositivos dentro de un ambiente de laboratorio específico. Todos los dispositivos que se utilizan en este documento se pusieron en funcionamiento con una configuración verificada (predeterminada). Si la red está funcionando, asegúrese de haber comprendido el impacto que puede tener un comando antes de ejecutarlo.

Comando T.38 debug vtsp all que muestra la descarga de Fax Codec

Se mostrarán mensajes similares a los siguientes para el T.38 para relé de fax luego de que la llamada se conecte y el router detecte la depuración del tono del fax.

Comando debug vtsp all

```
!--- Prior to the ccCallConnect message and during the
capabilities !--- exchange phase, the fax_rate message
may be displayed as follows: .Jun 4 21:06:43.677:
cc_api_caps_ack (dstVdbPtr=0x62F07650, dstCallId=0x18,
srcCallId=0x19, caps={codec=0x4, fax_rate=0x2, vad=0x2,
modem=0x0 codec_bytes=20, signal_type=2}) !--- In this
case the fax rate 0x02 refers to the voice rate, which
!--- with this codec (g.729), is less than or equal to 8
kbps. !--- Listed below are the other possible fax rate
values. !--- Below is a listing of fax rate values for
Cisco IOS Software Release 12.2.x or earlier: !--- hex
value fax rate value !--- 0x2 Voice !--- 0x4 14400 !---
0x8 9600 !--- 0x10 7200 !--- 0x20 4800 !--- 0x40 2400 !-
-- 0x80 1200 !--- Below is a listing of new fax rate
values for Cisco IOS Software Release 12.3.x or later:
!--- Note the hex values now map to slightly different
speeds than the list above. !--- !--- #define
CC_CAP_FAX_NONE 0x01 !--- #define CC_CAP_FAX_VOICE 0x02
!--- #define CC_CAP_FAX_24 0x04 !--- #define
CC_CAP_FAX_48 0x08 !--- #define CC_CAP_FAX_72 0x10 !---
#define CC_CAP_FAX_96 0x20 !--- #define CC_CAP_FAX_120
0x40 !--- #define CC_CAP_FAX_144 0x80 !--- Usually,
after the call is connected, the ccCallConnect debug !--
- message is seen as follows: .Jun 4 21:06:44.841:
ccCallConnect (callID=0x18), prog_ind = 0 .Jun 4
21:06:44.841: ssaFlushPeerTagQueue cid(24) peer list:
(empty) .Jun 4 21:06:47.437: vtsp_process_dsp_message:
MSG_TX_GET_TX_STAT: rtp_timestamp=0xD4D85071 .Jun 4
21:06:47.437: vtsp:[4/0:15 (25), S_CONNECT,
E_DSP_GET_TX] .Jun 4 21:06:49.049:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
rtp_timestamp=0xD4D882D1 .Jun 4 21:06:49.049:
vtsp:[4/0:15 (25), S_CONNECT, E_DSP_GET_TX] .Jun 4
21:06:50.129: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0 .Jun 4
21:06:50.129: vtsp:[4/0:15 (25), S_CONNECT,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.129:
```

```
vtsp_modem_proto_from_cdb: cap_modem_proto 0 .Jun 4
21:06:50.129: cc_api_call_feature: (vdbPtr=0x63387EDC,
callID=0x19,feature_ind.type=1 .Jun 4 21:06:50.129:
act_lfax_switch: cap_modem_proto=16, fax_relay_on=1,
state=19 .Jun 4 21:06:50.129: vtsp_t38_switchover:2 -
data_mode:1 !--- Note that 2 means T.38; 1 means Cisco
proprietary. .Jun 4 21:06:50.129: cc_api_t38_fax_start
(dstVdbPtr=0x62F07650, dstCallId=0x18, srcCallId=0x19,
caps={codec=0x10000, fax_rate=0x2, vad=0x2, modem=0x0
codec_bytes=20, signal_type=2}) .Jun 4 21:06:50.129:
vtsp_timer: 20362254 .Jun 4 21:06:50.129: sess_appl:
ev(28=CC_EV_CALL_FEATURE), cid(25), disp(0) .Jun 4
21:06:50.129:
cid(25)st(SSA_CS_ACTIVE)ev(SSA_EV_CALL_FEATURE)
oldst(SSA_CS_CONFERENCED_ALERT)cfid(8)csize(0)in(0)fDest
(0) .Jun 4 21:06:50.129: -
cid2(24)st2(SSA_CS_ACTIVE)oldst2
(SSA_CS_CONFERENCING_ALERT) .Jun 4 21:06:50.129:
ccCallFeature (callID=0x18, feature.type=1) .Jun 4
21:06:50.249: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=0 tone_id=0 .Jun 4
21:06:50.249: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.249:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT .Jun 4
21:06:50.389: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0 .Jun 4
21:06:50.389: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.389:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT .Jun 4
21:06:50.489: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=0 tone_id=0 .Jun 4
21:06:50.489: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.489:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT Invalid
FSM Input on channel 4/0:15 (25) .Jun 4 21:06:50.529:
cc_api_t38_fax_start (dstVdbPtr=0x63387EDC,
dstCallId=0x19, srcCallId=0x18, caps={codec=0x10000,
fax_rate=0x2, vad=0x2, modem=0x0 codec_bytes=160,
signal_type=2}) .Jun 4 21:06:50.529: vtsp:[4/0:15 (25),
S_LFAX_WAIT_CAPS_ACK, E_CC_T38_START] .Jun 4
21:06:50.529: act_caps_ack_lfax_dnld .Jun 4
21:06:50.529: vtsp_timer_stop: 20362294 .Jun 4
21:06:50.529: dsp_idle_mode: [4/0:15 (25)] packet_len=8
channel_id=1 packet_id=68 .Jun 4 21:06:50.529:
vtsp:[4/0:15 (25), S_LFAX_DOWNLOAD,
E_DSPRM_PEND_SUCCESS] .Jun 4 21:06:50.529: act_lfax_mode
.Jun 4 21:06:50.529: cc_api_local_codec_dnld_done
(dstVdbPtr=0x62F07650, dstCallId=0x18, srcCallId=0x19)
!--- The previous three messages confirm that the fax
codec was successfully !--- downloaded into the DSP. You
may not see all the messages above !--- and below. The
important point is that you do not see error !---
messages saying that the fax codec was not downloaded
correctly. .Jun 4 21:06:50.529: vtsp_timer: 20362294
.Jun 4 21:06:50.929: cc_api_t38_fax_start
(dstVdbPtr=0x63387EDC, dstCallId=0x19, srcCallId=0x18,
caps={codec=0x10000, fax_rate=0x2, vad=0x2, modem=0x0
codec_bytes=160, signal_type=2}) .Jun 4 21:06:50.929:
cc_api_remote_codec_dnld_done (dstVdbPtr=0x63387EDC,
dstCallId=0x19, srcCallId=0x18) .Jun 4 21:06:50.929:
vtsp:[4/0:15 (25), S_LFAX_WAIT_FAX, E_CC_T38_START] .Jun
```

```

4 21:06:50.929: vtsp:[4/0:15 (25), S_LFAX_WAIT_FAX,
E_CC_T30_CAP_ACK] .Jun 4 21:06:50.929: act_t38_lfax_mode
.Jun 4 21:06:50.929: vtsp_timer_stop: 20362334 .Jun 4
21:06:50.929: dsp_idle_mode: [4/0:15 (25)] packet_len=8
channel_id=1 packet_id=68 .Jun 4 21:06:50.929:
dsp_encap_config: T38 .Jun 4 21:06:50.929: dsp_fax_mode:
[4/0:15 (25)] FaxRate 0x2, Codec 0x10000 dsp_fax_mode()
ECM_DISABLE not set, debug_info requested .Jun 4
21:06:50.929: dsp_fax_mode: [] packet_len=28
channel_id=1 packet_id=69 max_trans=3 info_size=20,
fax_protocol_type=3, ls_data_red=0, hs_data_red=0,
tcf_handling=2, fax_relay_cntl=0x2 nsf_country = 0xAD,
nsf_mfg = 0x0051 !--- During the fax transmission the
Cisco IOS Software polls the DSP !--- statistics
periodically, and the following message appears: .Jun 4
21:06:50.929: vtsp:[4/0:15 (25), S_FAX, E_DSP_GET_TX

```

El rastro puede verse diferente en distintas versiones del software Cisco IOS pero siempre debería poder saber si el códec del fax fue cargado correctamente y qué protocolo de fax fue utilizado según el resultado obtenido después de la palabra clave "FAX".

Si el códec de fax no se cargó correctamente, probablemente exista un problema de software. Asegúrese de que se use la última versión de mantenimiento y, si aún hay un problema, abra un caso con el Centro de asistencia técnica (TAC).

[Ejemplo de trabajo del comando debug vtsp all de VoFR](#)

[Router de origen](#)

debug vtsp all: router de origen

```

vdt1-2600-2d#
Jun  5 10:10:34.053: vtsp_tsp_call_setup_ind
(sdb=0x81FD48DC, tdm_info=0x0,
tsp_info=0x81FF74DC, calling_number= calling_oct3 =
0x0,
called_number= called_oct3 = 0x81, oct3a=0x0):
peer_tag=0
Jun  5 10:10:34.053: : ev.clg.clir is 0
ev.clg.clid_transparent
is 0 ev.clg.null_orig_clg is 1
ev.clg.calling_translated is false

Jun  5 10:10:34.057: vtsp_do_call_setup_ind
Jun  5 10:10:34.057: vtsp_allocate_cdb,cdb 0x821D9344
Jun  5 10:10:34.057: vtsp_do_call_setup_ind: Call
ID=65589, guid=821D9874
Jun  5 10:10:34.057: vtsp_do_call_setup_ind: type=0,
under_spec=-2119571356,
name=f<0HNhf< 1=@, id0=1, id1=1, id2=-32567, calling=,
called= subscriber=RegularLine
Jun  5 10:10:34.057: vtsp_do_normal_call_setup_ind
Jun  5 10:10:34.057: vtsp_insert_cdb,cdb 0x821D9344
Jun  5 10:10:34.057: vtsp_open_voice_and_set_params
Jun  5 10:10:34.057: dsp_close_voice_channel: [1/1:0:27]
packet_len=8
channel_id=2 packet_id=75
Jun  5 10:10:34.057: dsp_open_voice_channel_20:
[1/1:0:27] packet_len=16

```

```
channel_id=2 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=129 time_slot=1
serial_port=0
Jun  5 10:10:34.057: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun  5 10:10:34.057: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun  5 10:10:34.057: dsp_encap_config: [1/1:0:27]
packet_len=30
channel_id=2 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
redundancy=0
Jun  5 10:10:34.061: dsp_set_playout_delay
Jun  5 10:10:34.061: dsp_set_playout: [1/1:0:27]
packet_len=18
channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
dsp_set_playout_delay_config
Jun  5 10:10:34.061: dsp_set_playout_config
Jun  5 10:10:34.061: mode 0, init 60, min 40, max 200
playout default

Jun  5 10:10:34.061: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:34.061: dsp_set_playout_config: [1/1:0:27]
packet_len=18
channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:34.061: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:34.061: dsp_echo_canceler_control:
[1/1:0:27] echo_cancel 1,
disable_hpf 0, flags=0x0
Jun  5 10:10:34.061: dsp_echo_canceler_control:
[1/1:0:27] packet_len=10
channel_id=2 packet_id=66 flags=0x0
Jun  5 10:10:34.061: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:34.061: dsp_set_gains: [1/1:0:27]
packet_len=12
channel_id=2 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:34.061: dsp_vad_enable: [1/1:0:27] enable:
packet_len=12
channel_id=2 packet_id=78 thresh=-38
Jun  5 10:10:34.061: vtsp_report_digit_control:
enable=1: digit reporting enabled
Jun  5 10:10:34.061: : vtsp_get_digit_timeouts
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_SETUP_INDICATED,
E_CC_SETUP_ACK]
Jun  5 10:10:34.065: act_setup_ind_ack
Jun  5 10:10:34.065: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:34.065: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:34.065: dsp_encap_config: [1/1:0:27]
packet_len=30
channel_id=2 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
redundancy=0
Jun  5 10:10:34.065: dsp_voice_mode: [1/1:0:27] cdb
```

```
821D9344,
 cdb->codec_params.modem 2, inband_detect flags 0x21
Jun  5 10:10:34.065: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:34.065: dsp_voice_mode: [1/1:0:27]
packet_len=24
 channel_id=2 packet_id=73 coding_type=1
voice_field_size=80 VAD_flag=0
 echo_length=64 comfort_noise=1 inband_detect=33
digit_relay_mode=2
 AGC_flag=0act_setup_ind_ack: modem_mode = 0,
fax_relay_on = 1
Jun  5 10:10:34.065: act_setup_ind_ack():
 dsp_dtmf_mode()dsp_dtmf_mode(VTSP_TONE_DTMF_MODE)

Jun  5 10:10:34.065: dsp_dtmf_mode: [1/1:0:27]
packet_len=10
 channel_id=2 packet_id=65 dtmf_or_mf=0
Jun  5 10:10:34.065: vtsp_timer: 43525550
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_CC_GEN_TONE]
Jun  5 10:10:34.065: act_gen_tone
Jun  5 10:10:34.065: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
 channel_id=2 packet_id=71
Jun  5 10:10:34.065: dsp_cp_tone_on: [1/1:0:27]
packet_len=38
 channel_id=2 packet_id=72 tone_id=4 n_freq=2
freq_of_first=350
 freq_of_second=440 amp_of_first=5514 amp_of_second=5514
direction=1
 on_time_first=65535 off_time_first=0 on_time_second=0
off_time_second=0
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_CC_GEN_TONE]
Jun  5 10:10:34.069: act_gen_tone
Jun  5 10:10:34.069: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
 channel_id=2 packet_id=71
Jun  5 10:10:34.069: dsp_cp_tone_on: [1/1:0:27]
packet_len=38
 channel_id=2 packet_id=72 tone_id=4 n_freq=2
freq_of_first=350
 freq_of_second=440 amp_of_first=5514 amp_of_second=5514
direction=1
 on_time_first=65535 off_time_first=0 on_time_second=0
off_time_second=0
Jun  5 10:10:35.544: vtsp_process_dsp_message:
 MSG_TX_DTMF_DIGIT_BEGIN: digit=4,
rtp_timestamp=0xD455BA67

Jun  5 10:10:35.544: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.544: act_report_digit_begin
Jun  5 10:10:35.612: vtsp_process_dsp_message:
 MSG_TX_DTMF_DIGIT_OFF: digit=4, duration=120
Jun  5 10:10:35.616: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT]
Jun  5 10:10:35.616: act_report_digit_end
Jun  5 10:10:35.616: vtsp_timer_stop: 43525705
Jun  5 10:10:35.616: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
 channel_id=2 packet_id=71
Jun  5 10:10:35.616: vtsp_timer: 43525705
```

```
Jun  5 10:10:35.732: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=0,
  rtp_timestamp=0xD455BA67
Jun  5 10:10:35.732: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.732: act_report_digit_begin
Jun  5 10:10:35.792: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=0, duration=110
Jun  5 10:10:35.792: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT]
Jun  5 10:10:35.792: act_report_digit_end
Jun  5 10:10:35.792: vtsp_timer_stop: 43525722
Jun  5 10:10:35.796: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:35.796: vtsp_timer: 43525723
Jun  5 10:10:35.933: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=0,
  rtp_timestamp=0xD455BA67
Jun  5 10:10:35.933: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.933: act_report_digit_begin
Jun  5 10:10:36.005: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=0, duration=120
Jun  5 10:10:36.005: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT]
Jun  5 10:10:36.005: act_report_digit_end
Jun  5 10:10:36.005: vtsp_timer_stop: 43525744
Jun  5 10:10:36.005: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:36.005: vtsp_timer: 43525744
Jun  5 10:10:36.133: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=1,
  rtp_timestamp=0xD455BA67
Jun  5 10:10:36.133: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:36.133: act_report_digit_begin
Jun  5 10:10:36.193: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=1, duration=110
Jun  5 10:10:36.193: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT]
Jun  5 10:10:36.193: act_report_digit_end
Jun  5 10:10:36.193: vtsp_timer_stop: 43525762
Jun  5 10:10:36.193: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:36.193: vtsp_timer: 43525762
Jun  5 10:10:36.197: vtsp_report_digit_control:
  enable=0: digit reporting disabled
Jun  5 10:10:36.197: : vtsp_get_digit_timeouts
Jun  5 10:10:36.197: vtsp_save_dialpeer_tag: tag = 4001
Jun  5 10:10:36.197: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_CC_PROCEEDING]
Jun  5 10:10:36.197: act_dcollect_proc
Jun  5 10:10:36.205: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:36.890: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_PROGRESS]
Jun  5 10:10:36.890: act_progress
Jun  5 10:10:36.890: vtsp_timer_stop: 43525832
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_BRIDGE]
Jun  5 10:10:36.890: act_bridge
```

```
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
E_CC_CAPS_IND]
Jun  5 10:10:36.890: act_caps_ind
Jun  5 10:10:36.890: act_caps_ind: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.890: act_caps_ind:CC_CAP_ENCAP_FRF11
Encap 2, Vad 2,
  Codec 0x4, CodecBytes 30, FaxRate 2, FaxBytes 30,
FaxNsf 0xAD0051
  Sub-channel 8, Bitmask 0x0 SignalType 2, SeqNumStart
0x0
Jun  5 10:10:36.890: act_caps_ind: [ mode:0,init:60,
min:40, max:200]
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
E_CC_CAPS_ACK]
Jun  5 10:10:36.890: act_caps_ack
Jun  5 10:10:36.894: act_caps_ack: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.894: dsp_idle_mode: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=68
Jun  5 10:10:36.894: act_caps_ack: codec = 16, ret = 2
Jun  5 10:10:36.894: vtsp_timer: 43525833
Jun  5 10:10:36.894: vtsp:[1/1:0:27, S_NULL,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:36.894: act_pend_codec_success
Jun  5 10:10:36.894: vtsp_timer_stop: 43525833
Jun  5 10:10:36.894: vtsp_open_voice_and_set_params
Jun  5 10:10:36.894: dsp_close_voice_channel: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=75
Jun  5 10:10:36.894: dsp_open_voice_channel_20:
[1/1:0:27] packet_len=16
  channel_id=2 packet_id=74 alaw_ulaw_select=0
  associated_signaling_channel=129 time_slot=1
  serial_port=0
Jun  5 10:10:36.894: dsp_encap_config: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=92 TransportProtocol 3
  SID_support=0
  sequence_number=0 rotate_flag=0 header_bytes 0x80
Jun  5 10:10:36.894: dsp_set_playout_delay
Jun  5 10:10:36.894: dsp_set_playout: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
  dsp_set_playout_delay_config
Jun  5 10:10:36.894: dsp_set_playout_config
Jun  5 10:10:36.894: mode 0, init 60, min 40, max 200
playout default
Jun  5 10:10:36.894: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.894: dsp_set_playout_config: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.894: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.894: dsp_echo_canceler_control:
[1/1:0:27] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.898: dsp_echo_canceler_control:
```



```
[1/1:0:27] packet_len=10
  channel_id=2 packet_id=66 flags=0x0
Jun  5 10:10:36.898: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.898: dsp_set_gains: [1/1:0:27]
packet_len=12
  channel_id=2 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.898: dsp_vad_enable: [1/1:0:27] enable:
packet_len=12
  channel_id=2 packet_id=78 thresh=-38
Jun  5 10:10:36.898: dsp_voice_mode: [1/1:0:27] cdb
821D9344,
  cdb->codec_params.modem 0, inband_detect flags 0x1
Jun  5 10:10:36.898: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:36.898: dsp_voice_mode: [1/1:0:27]
packet_len=24
  channel_id=2 packet_id=73 coding_type=19
voice_field_size=30
  VAD_flag=250 echo_length=64 comfort_noise=1
inband_detect=1
  digit_relay_mode=2 AGC_flag=0
Jun  5 10:10:43.024: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:43.024: vtsp:[1/1:0:27, S_PROCEEDING,
E_CC_CONNECT]
Jun  5 10:10:43.024: act_connect
Jun  5 10:10:43.024: vtsp_ring_noan_timer_stop: 43526446

Jun  5 10:10:48.710: vtsp:[1/1:0:27, S_CONNECT,
E_PH_CODEC_FAX]
Jun  5 10:10:48.710: act_rfax_switch
Jun  5 10:10:48.710: dsp_idle_mode: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=68
Jun  5 10:10:48.710: vtsp_timer_stop: 43527014
Jun  5 10:10:48.910: vtsp:[1/1:0:27, S_RFAX_DOWNLOAD,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:48.910: act_rfax_mode
Jun  5 10:10:48.910: vtsp:[1/1:0:27, S_RFAX_WAIT_ACK,
E_PH_CODEC_ACK]
Jun  5 10:10:48.910: act_wait_ack_ack
Jun  5 10:10:48.910: vtsp_timer_stop: 43527034
Jun  5 10:10:48.914: dsp_fax_mode: [1/1:0:27] FaxRate
0x2, Codec 0x4
  dsp_fax_mode() ECM_DISABLE not set, debug_info not
requested
Jun  5 10:10:48.914: dsp_fax_mode: [1/1:0:27]
packet_len=28
  channel_id=2 packet_id=69 max_trans=3 info_size=30,
fax_protocol_type=2,
  hs_data_len=0, ls_data_red=0, hs_data_red=0,
tcf_handling=0,
fax_relay_cntl=0x0 nsf_country = 0xAD, nsf_mfg = 0x0051
  !--- fax codecs: enum { !--- DSP_TELELOGY_FAX = 1, !---
DSP_FRF11_FAX, !--- DSP_T38_FAX vdt1-2600-2d# vdt1-2600-
2d# vdt1-2600-2d# Jun  5 10:11:21.516:
vtsp_process_dsp_message: MSG_TX_FAX_CLEARDOWN: Jun  5
10:11:21.516: vtsp:[1/1:0:27, S_FAX,
E_DSP_FAX_CLEARDOWN] Jun  5 10:11:21.516:
act_fax_to_voice Jun  5 10:11:21.516: vtsp_timer_stop:
43530295 Jun  5 10:11:21.520: dsp_idle_mode: [1/1:0:27]
packet_len=8 channel_id=2 packet_id=68 Jun  5
10:11:21.520: dsp_close_voice_channel: [1/1:0:27]
packet_len=8 channel_id=2 packet_id=75act_fax_to_voice
```

```
codec= 16 Jun 5 10:11:21.520: vtsp_timer: 43530295 Jun 5
10:11:21.520: vtsp:[1/1:0:27, S_FAX_TERM,
E_DSPRM_PEND_SUCCESS] Jun 5 10:11:21.520:
vtsp_timer_stop: 43530295 Jun 5 10:11:21.520:
act_fax_complete Jun 5 10:11:21.520:
vtsp_open_voice_and_set_params Jun 5 10:11:21.520:
dsp_close_voice_channel: [1/1:0:27] packet_len=8
channel_id=2 packet_id=75 Jun 5 10:11:21.520:
dsp_open_voice_channel_20: [1/1:0:27] packet_len=16
channel_id=2 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=129 time_slot=1
serial_port=0 Jun 5 10:11:21.520: dsp_encap_config:
[1/1:0:27] packet_len=18 channel_id=2 packet_id=92
TransportProtocol 3 SID_support=0 sequence_number=0
rotate_flag=0 header_bytes 0x80 Jun 5 10:11:21.520:
dsp_set_playout_delay Jun 5 10:11:21.520:
dsp_set_playout: [1/1:0:27] packet_len=18 channel_id=2
packet_id=76 mode=1 initial=60 min=40 max=200
fax_nom=300 dsp_set_playout_delay_config Jun 5
10:11:21.520: dsp_set_playout_config Jun 5 10:11:21.520:
mode 0, init 60, min 40, max 200 playout default Jun 5
10:11:21.520: dsp_set_playout_config:mode 0, init 60,
min 40, max 200 Jun 5 10:11:21.520:
dsp_set_playout_config: [1/1:0:27] packet_len=18
channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300 Jun 5 10:11:21.520:
dsp_echo_canceler_control: echo_cancel: 1 Jun 5
10:11:21.520: dsp_echo_canceler_control: [1/1:0:27]
echo_cancel 1, disable_hpf 0, flags=0x0 Jun 5
10:11:21.525: dsp_echo_canceler_control: [1/1:0:27]
packet_len=10 channel_id=2 packet_id=66 flags=0x0 Jun 5
10:11:21.525: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0 Jun 5 10:11:21.525:
dsp_set_gains: [1/1:0:27] packet_len=12 channel_id=2
packet_id=91 in_gain=0 out_gain=0 Jun 5 10:11:21.525:
dsp_vad_enable: [1/1:0:27] enable: packet_len=12
channel_id=2 packet_id=78 thresh=-38 Jun 5 10:11:21.525:
dsp_voice_mode: [1/1:0:27] cdb 821D9344, cdb-
>codec_params.modem 0, inband_detect flags 0x1 Jun 5
10:11:21.525: map_dtmf_relay_type--digit relay mode: 2
Jun 5 10:11:21.525: dsp_voice_mode: [1/1:0:27]
packet_len=24 channel_id=2 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250 echo_length=64
comfort_noise=1 inband_detect=1 digit_relay_mode=2
AGC_flag=0 Jun 5 10:11:24.033: vtsp:[1/1:0:27,
S_CONNECT, E_TSP_DISCONNECT_IND] Jun 5 10:11:24.033:
act_generate_disc Jun 5 10:11:24.033:
vtsp_ring_noan_timer_stop: 43530546 Jun 5 10:11:24.033:
vtsp_timer_stop: 43530546 Jun 5 10:11:24.033:
vtsp_pcm_tone_detect_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_pcm_switchover_timer_stop: 43530546
Jun 5 10:11:24.033: vtsp:[1/1:0:27, S_CONNECT,
E_CC_BRIDGE_DROP] Jun 5 10:11:24.033: act_bdrop Jun 5
10:11:24.033: vtsp:[1/1:0:27, S_CONNECT,
E_CC_DISCONNECT] Jun 5 10:11:24.033: act_disconnect Jun
5 10:11:24.033: vtsp_ring_noan_timer_stop: 43530546 Jun
5 10:11:24.033: vtsp_pcm_tone_detect_timer_stop:
43530546 Jun 5 10:11:24.033:
vtsp_pcm_switchover_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_cot_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_timer: 43530546 Jun 5 10:11:24.037:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_ERROR] Jun 5
10:11:24.037: act_get_error Jun 5 10:11:24.037:
```

```

1/1:0:27: rx_dropped=0 tx_dropped=0 rx_control=51
tx_control=14 tx_control_dropped=0 dsp_mode_channel_1=0
dsp_mode_channel_2=2 c[0]=68 c[1]=3 c[2]=10 c[3]=69
c[4]=68 c[5]=75 c[6]=75 c[7]=74 c[8]=92 c[9]=76 c[10]=76
c[11]=66 c[12]=91 c[13]=78 c[14]=73 c[15]=6 Jun 5
10:11:24.037: dsp_get_levels: [1/1:0:27] packet_len=8
channel_id=2 packet_id=89 Jun 5 10:11:24.041:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_LEVELS] Jun 5
10:11:24.041: act_get_levels Jun 5 10:11:24.045:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
rtp_timestamp=0xFD908919 Jun 5 10:11:24.045:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_TX] Jun 5
10:11:24.049: act_stats_complete Jun 5 10:11:24.049:
vtsp_timer_stop: 43530548 Jun 5 10:11:24.049:
vtsp_ring_noan_timer_stop: 43530548 Jun 5 10:11:24.049:
dsp_idle_mode: [1/1:0:27] packet_len=8 channel_id=2
packet_id=68 Jun 5 10:11:24.049: vtsp_timer: 43530548
Jun 5 10:11:24.850: vtsp:[1/1:0:27, S_WAIT_RELEASE,
E_TSP_CALL_FEATURE_IND] Jun 5 10:11:24.850:
act_call_feature_ind Jun 5 10:11:24.850: vtsp:[1/1:0:27,
S_WAIT_RELEASE, E_TSP_DISCONNECT_CONF] Jun 5
10:11:24.850: act_wrelease_release Jun 5 10:11:24.850:
vtsp_timer_stop: 43530628 Jun 5 10:11:24.854:
dsp_cp_tone_off: [1/1:0:27] packet_len=8 channel_id=2
packet_id=71 Jun 5 10:11:24.854: dsp_idle_mode:
[1/1:0:27] packet_len=8 channel_id=2 packet_id=68 Jun 5
10:11:24.854: dsp_close_voice_channel: [1/1:0:27]
packet_len=8 channel_id=2
packet_id=75vtsp_do_call_historyvtsp_do_call_history
CoderRate 20 Jun 5 10:11:24.854: vtsp:[1/1:0:27,
S_CLOSE_DSPRM, E_DSPRM_CLOSE_COMPLETE] Jun 5
10:11:24.854: act_terminate Jun 5 10:11:24.854:
vtsp_free_cdb,cdb 0x821D9344 vdt1-2600-2d#

```

Router de terminación

debug vtsp all - Router de terminación

```

vdt1-7200-2c#
Jun 5 10:10:36.200: vtsp_do_call_setup_req
Jun 5 10:10:36.200: vtsp_allocate_cdb,cdb 0x620F01FC
Jun 5 10:10:36.200: vtsp_insert_cdb,cdb 0x620F01FC
Jun 5 10:10:36.200: vtsp_do_call_setup_req calling oct3
0x0, called oct3 0x0
Jun 5 10:10:36.200: vtsp_do_call_setup_req: Call ID=55,
guid=62F8AC6C
Jun 5 10:10:36.200: digit_strip:1, pcn:4001, poa:4001
Jun 5 10:10:36.200: pcn:, poa:
Jun 5 10:10:36.200: Final pcn:, poa:, dial_string:
Jun 5 10:10:36.200: calling oct3 0x0, called oct3 0x0
Jun 5 10:10:36.200: vtsp:[2/1:0 (39), S_SETUP_REQUEST,
E_TSP_PROCEEDING]
Jun 5 10:10:36.200: act_setup_pend_proceeding
Jun 5 10:10:36.200: vtsp_open_voice_and_set_params
Jun 5 10:10:36.200: dsp_close_voice_channel: [2/1:0
(39)] packet_len=8
channel_id=1 packet_id=75
Jun 5 10:10:36.200: dsp_open_voice_channel_20: [2/1:0
(39)] packet_len=16
channel_id=1 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=128 time_slot=0
serial_port=0
Jun 5 10:10:36.200: vtsp_modem_proto_from_cdb:

```

```
cap_modem_proto 1073741824
Jun  5 10:10:36.204: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun  5 10:10:36.204: dsp_encap_config: [2/1:0 (39)]
packet_len=30
  channel_id=1 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
  t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
  redundancy=0
Jun  5 10:10:36.204: dsp_set_playout_delay
Jun  5 10:10:36.204: dsp_set_playout: [2/1:0 (39)]
packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
  dsp_set_playout_delay_config
Jun  5 10:10:36.204: dsp_set_playout_config
Jun  5 10:10:36.204: mode 0, init 60, min 40, max 200
playout default

Jun  5 10:10:36.204: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.204: dsp_set_playout_config: [2/1:0
(39)] packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.204: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.204: dsp_echo_canceler_control: [2/1:0
(39)] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.204: dsp_echo_canceler_control: [2/1:0
(39)] packet_len=10
  channel_id=1 packet_id=66 flags=0x0
Jun  5 10:10:36.204: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.204: dsp_set_gains: [2/1:0 (39)]
packet_len=12
  channel_id=1 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.204: dsp_vad_enable: [2/1:0 (39)]
enable: packet_len=12
  channel_id=1 packet_id=78 thresh=-38
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_TSP_PROGRESS]
Jun  5 10:10:36.888: act_setup_pend_progress
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_CC_BRIDGE]
Jun  5 10:10:36.888: act_bridge
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_CC_CAPS_IND]
Jun  5 10:10:36.888: act_caps_ind
Jun  5 10:10:36.888: act_caps_ind: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.888: act_caps_ind:CC_CAP_ENCAP_FRF11
Encap 2, Vad 2,
  Codec 0x4, CodecBytes 30,
    FaxRate 2, FaxBytes 30, FaxNsf 0xAD0051
    Sub-channel 8, Bitmask 0x0
    SignalType 2, SeqNumStart 0x0
Jun  5 10:10:36.888: act_caps_ind: [ mode:0,init:60,
min:40, max:200]
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
```

```
E_CC_CAPS_ACK]
Jun  5 10:10:36.888: act_caps_ack
Jun  5 10:10:36.888: act_caps_ack: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.888: dsp_idle_mode: [2/1:0 (39)]
packet_len=8
  channel_id=1 packet_id=68
Jun  5 10:10:36.888: act_caps_ack: codec = 16, ret = 2

Jun  5 10:10:36.888: vtsp_timer: 94714681
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_NULL,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:36.888: act_pend_codec_success
Jun  5 10:10:36.888: vtsp_timer_stop: 94714681
Jun  5 10:10:36.888: vtsp_open_voice_and_set_params
Jun  5 10:10:36.888: dsp_close_voice_channel: [2/1:0
(39)] packet_len=8
  channel_id=1 packet_id=75
Jun  5 10:10:36.888: dsp_open_voice_channel_20: [2/1:0
(39)] packet_len=16
  channel_id=1 packet_id=74 alaw_ulaw_select=0
  associated_signaling_channel=128 time_slot=0
  serial_port=0
Jun  5 10:10:36.888: dsp_encap_config: [2/1:0 (39)]
packet_len=18
  channel_id=1 packet_id=92 TransportProtocol 3
  SID_support=0
  sequence_number=0 rotate_flag=0 header_bytes 0x80
Jun  5 10:10:36.888: dsp_set_playout_delay
Jun  5 10:10:36.888: dsp_set_playout: [2/1:0 (39)]
packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
  dsp_set_playout_delay_config
Jun  5 10:10:36.888: dsp_set_playout_config
Jun  5 10:10:36.888: mode 0, init 60, min 40, max 200
playout default

Jun  5 10:10:36.888: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.888: dsp_set_playout_config: [2/1:0
(39)] packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.888: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.888: dsp_echo_canceler_control: [2/1:0
(39)] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.888: dsp_echo_canceler_control: [2/1:0
(39)] packet_len=10
  channel_id=1 packet_id=66 flags=0x0
Jun  5 10:10:36.888: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.888: dsp_set_gains: [2/1:0 (39)]
packet_len=12 channel_id=1
  packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.888: dsp_vad_enable: [2/1:0 (39)]
enable: packet_len=12
  channel_id=1 packet_id=78 thresh=-38
Jun  5 10:10:36.888: dsp_voice_mode: [2/1:0 (39)] cdb
620F01FC,
  cdb->codec_params.modem 0, inband_detect flags 0x1
```

```
Jun  5 10:10:36.888: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:36.888: dsp_voice_mode: [2/1:0 (39)]
packet_len=24
  channel_id=1 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250
  echo_length=64 comfort_noise=1
  inband_detect=1 digit_relay_mode=2 AGC_flag=0
Jun  5 10:10:43.024: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_TSP_CONNECT]
Jun  5 10:10:43.024: act_setup_pend_connect
Jun  5 10:10:43.024: vtsp_ring_noan_timer_stop: 94715294
Jun  5 10:10:43.024: dsp_cp_tone_off: [2/1:0 (39)]
packet_len=8
  channel_id=1 packet_id=71

Jun  5 10:10:48.492: vtsp_process_dsp_message:
  MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0
Jun  5 10:10:48.492: vtsp:[2/1:0 (39), S_CONNECT,
E_DSP_TONE_DETECT]
Jun  5 10:10:48.492: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:48.492: act_lfax_switch:
cap_modem_proto=16,
  fax_relay_on=1, state=19
  !--- sys/if/dsp_cntl_msgs.h * Definitions for the tone
detect !--- */ !--- #define TONE_TYPE_V_21 0x0000 !---
#define TONE_TYPE_CED 0x0001 !--- #define TONE_TYPE_CNG
0x0002 !--- #define TONE_SDT_DISC 0x0003 !--- #define
TONE_TYPE_COT 0x0004 !--- #define TONE_TYPE_MODEM 0x0005
!--- #define SILENCE_DETECTED 0x0006 !--- #define
VOICE_DETECTED 0x0007 !--- #define DUAL_TONE_DETECTED
0x0008 !--- #define SEQ_TONE_DETECTED 0x0009 !---
#define TONE_DETECT_ON 0x0001 !--- #define
TONE_DETECT_OFF ~TONE_DETECT_ Jun  5 10:10:48.492:
vtsp_timer: 94715841 Jun  5 10:10:48.492: vtsp:[2/1:0
(39), S_LFAX_WAIT_ACK, E_PH_CODEEC_ACK] Jun  5
10:10:48.492: act_lfax_download Jun  5 10:10:48.492:
vtsp_timer_stop: 94715841 Jun  5 10:10:48.492:
dsp_idle_mode: [2/1:0 (39)] packet_len=8 channel_id=1
packet_id=68 Jun  5 10:10:48.492: vtsp:[2/1:0 (39),
S_LFAX_DOWNLOAD, E_DSPRM_PEND_SUCCESS] Jun  5
10:10:48.492: act_lfax_mode Jun  5 10:10:48.492:
vtsp:[2/1:0 (39), S_LFAX_WAIT_FAX, E_PH_CODEEC_FAX] Jun  5
10:10:48.492: act_wait_fax_fax ph_set_codec_ack Jun  5
10:10:48.492: dsp_fax_mode: [2/1:0 (39)] FaxRate 0x2,
Codec 0x4 dsp_fax_mode() ECM_DISABLE not set, debug_info
not requested Jun  5 10:10:48.492: dsp_fax_mode: [2/1:0
(39)] packet_len=28 channel_id=1 packet_id=69
max_trans=3 info_size=30, fax_protocol_type=2,
hs_data_len=0, ls_data_red=0, hs_data_red=0,
tcf_handling=0, fax_relay_cntl=0x0 nsf_country = 0xAD,
nsf_mfg = 0x0051 vdt1-7200-2c# vdt1-7200-2c# vdt1-7200-
2c# Jun  5 10:11:21.736: vtsp_process_dsp_message:
MSG_TX_FAX_CLEARDOWN: Jun  5 10:11:21.740: vtsp:[2/1:0
(39), S_FAX, E_DSP_FAX_CLEARDOWN] Jun  5 10:11:21.740:
act_fax_to_voice Jun  5 10:11:21.740: vtsp_timer_stop:
94719166 Jun  5 10:11:21.740: dsp_idle_mode: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=68 Jun  5
10:11:21.740: dsp_close_voice_channel: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=75act_fax_to_voice
codec= 16 Jun  5 10:11:21.740: vtsp_timer: 94719166 Jun  5
10:11:21.740: vtsp:[2/1:0 (39), S_FAX_TERM,
E_DSPRM_PEND_SUCCESS] Jun  5 10:11:21.740:
```

```
vtsp_timer_stop: 94719166 Jun 5 10:11:21.740:
act_fax_complete Jun 5 10:11:21.740:
vtsp_open_voice_and_set_params Jun 5 10:11:21.740:
dsp_close_voice_channel: [2/1:0 (39)] packet_len=8
channel_id=1 packet_id=75 Jun 5 10:11:21.740:
dsp_open_voice_channel_20: [2/1:0 (39)] packet_len=16
channel_id=1 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=128 time_slot=0
serial_port=0 Jun 5 10:11:21.740: dsp_encap_config:
[2/1:0 (39)] packet_len=18 channel_id=1 packet_id=92
TransportProtocol 3 SID_support=0 sequence_number=0
rotate_flag=0 header_bytes 0x80 Jun 5 10:11:21.740:
dsp_set_playout_delay Jun 5 10:11:21.740:
dsp_set_playout: [2/1:0 (39)] packet_len=18 channel_id=1
packet_id=76 mode=1 initial=60 min=40 max=200
fax_nom=300 dsp_set_playout_delay_config Jun 5
10:11:21.740: dsp_set_playout_config Jun 5 10:11:21.740:
mode 0, init 60, min 40, max 200 playout default Jun 5
10:11:21.740: dsp_set_playout_config:mode 0, init 60,
min 40, max 200 Jun 5 10:11:21.740:
dsp_set_playout_config: [2/1:0 (39)] packet_len=18
channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300 Jun 5 10:11:21.740:
dsp_echo_canceler_control: echo_cancel: 1 Jun 5
10:11:21.740: dsp_echo_canceler_control: [2/1:0 (39)]
echo_cancel 1, disable_hpf 0, flags=0x0 Jun 5
10:11:21.740: dsp_echo_canceler_control: [2/1:0 (39)]
packet_len=10 channel_id=1 packet_id=66 flags=0x0 Jun 5
10:11:21.740: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0 Jun 5 10:11:21.740:
dsp_set_gains: [2/1:0 (39)] packet_len=12 channel_id=1
packet_id=91 in_gain=0 out_gain=0 Jun 5 10:11:21.740:
dsp_vad_enable: [2/1:0 (39)] enable: packet_len=12
channel_id=1 packet_id=78 thresh=-38 Jun 5 10:11:21.740:
dsp_voice_mode: [2/1:0 (39)] cdb 620F01FC, cdb-
>codec_params.modem 0, inband_detect flags 0x1 Jun 5
10:11:21.740: map_dtmf_relay_type--digit relay mode: 2
Jun 5 10:11:21.740: dsp_voice_mode: [2/1:0 (39)]
packet_len=24 channel_id=1 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250 echo_length=64
comfort_noise=1 inband_detect=1 digit_relay_mode=2
AGC_flag=0 Jun 5 10:11:24.036: vtsp:[2/1:0 (39),
S_CONNECT, E_CC_BRIDGE_DROP] Jun 5 10:11:24.036:
act_bdrop Jun 5 10:11:24.036: vtsp:[2/1:0 (39),
S_CONNECT, E_CC_DISCONNECT] Jun 5 10:11:24.036:
act_disconnect Jun 5 10:11:24.036:
vtsp_ring_noan_timer_stop: 94719396 Jun 5 10:11:24.036:
vtsp_pcm_tone_detect_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_pcm_switchover_timer_stop: 94719396
Jun 5 10:11:24.036: vtsp_cot_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_timer: 94719396 Jun 5 10:11:24.036:
vtsp:[2/1:0 (39), S_WAIT_STATS, E_DSP_GET_ERROR] Jun 5
10:11:24.036: act_get_error Jun 5 10:11:24.036: 2/1:0
(39): rx_dropped=1 tx_dropped=0 rx_control=39
tx_control=5 tx_control_dropped=0 dsp_mode_channel_1=2
dsp_mode_channel_2=0 c[0]=0 c[1]=0 c[2]=73 c[3]=71
c[4]=68 c[5]=69 c[6]=68 c[7]=75 c[8]=75 c[9]=74 c[10]=92
c[11]=76 c[12]=76 c[13]=66 c[14]=91 c[15]=78 Jun 5
10:11:24.036: dsp_get_levels: [2/1:0 (39)] packet_len=8
channel_id=1 packet_id=89 Jun 5 10:11:24.036:
vtsp:[2/1:0 (39), S_WAIT_STATS, E_DSP_GET_LEVELS] Jun 5
10:11:24.036: act_get_levels Jun 5 10:11:24.040:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
```

```
rtp_timestamp=0x94D00079 Jun 5 10:11:24.040: vtsp:[2/1:0
(39), S_WAIT_STATS, E_DSP_GET_TX] Jun 5 10:11:24.040:
act_stats_complete Jun 5 10:11:24.040: vtsp_timer_stop:
94719396 Jun 5 10:11:24.040: vtsp_ring_noan_timer_stop:
94719396 Jun 5 10:11:24.040: dsp_idle_mode: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=68 Jun 5
10:11:24.040: vtsp_timer: 94719396 Jun 5 10:11:24.840:
vtsp:[2/1:0 (39), S_WAIT_RELEASE,
E_TSP_CALL_FEATURE_IND] Jun 5 10:11:24.840:
act_call_feature_ind Jun 5 10:11:24.840: vtsp:[2/1:0
(39), S_WAIT_RELEASE, E_TSP_DISCONNECT_CONF] Jun 5
10:11:24.840: act_wrelease_release Jun 5 10:11:24.840:
vtsp_timer_stop: 94719476 Jun 5 10:11:24.840:
dsp_cp_tone_off: [2/1:0 (39)] packet_len=8 channel_id=1
packet_id=71 Jun 5 10:11:24.840: dsp_idle_mode: [2/1:0
(39)] packet_len=8 channel_id=1 packet_id=68 Jun 5
10:11:24.840: dsp_close_voice_channel: [2/1:0 (39)]
packet_len=8 channel_id=1
packet_id=75vtsp_do_call_historyvtsp_do_call_history
CoderRate 20 Jun 5 10:11:24.840: vtsp:[2/1:0 (39),
S_CLOSE_DSPRM, E_DSPRM_CLOSE_COMPLETE] Jun 5
10:11:24.840: act_terminate Jun 5 10:11:24.840:
vtsp_free_cdb,cdb 0x620F01FC
```

[Información Relacionada](#)

- [Voz – Configuración del Fax Relay con VoIP \(T.38\)](#)
- [Soporte de tecnología de voz](#)
- [Soporte de Productos de Voice and Unified Communications](#)
- [Troubleshooting de Cisco IP Telephony](#)
- [Soporte Técnico - Cisco Systems](#)