

Dépannez le courant alternatif - Réinitialisation de serveur de gamme

Contenu

[Introduction](#)

[Conditions préalables](#)

[Composants utilisés](#)

[Informations générales](#)

[Réinitialisations prévues](#)

[Réinitialisations inattendues](#)

[Points clé](#)

[Paquets de log de rassemblement pour l'analyse](#)

[Sortie prévue pour différents états de réinitialisation et d'arrêt](#)

[Réinitialisation de SYSTÈME D'EXPLOITATION - ESXi, RHEL, et Windows](#)

[Log OBFL](#)

[RHEL - /var/log/messages](#)

[Windows - Journal d'événements](#)

[Arrêt de SYSTÈME D'EXPLOITATION - ESXi, RHEL, et Windows](#)

[Log OBFL :](#)

[ESXi - /var/log/hostd.log](#)

[RHEL - /var/log/messages](#)

[Windows - Journal d'événements](#)

[Mettez sous tension de CIMC](#)

[Log OBFL :](#)

[Arrêt et redémarrage de CIMC](#)

[Log OBFL](#)

[Mettez hors tension de CIMC](#)

[Log OBFL](#)

[Coupure de courant de panne de bloc d'alimentation](#)

[Log OBFL](#)

[Le bouton avant mettent hors tension](#)

[Log OBFL](#)

[Le bouton avant mettent sous tension](#)

[Log OBFL](#)

[Informations connexes](#)

Introduction

Ce document décrit comment déterminer si une réinitialisation ou un arrêt a été initiée dans le matériel ou du système d'exploitation (SYSTÈME D'EXPLOITATION).

Il y a plusieurs bons emplacements de log à concentrer sur quand vous déterminez pourquoi un serveur redémarré ou arrêté. Quand vous recherchez par le support technique de Contrôleur de

gestion intégré de Cisco (CIMC), regardez ou /var/log/messages ou à bord de la panne se connectant les logs (OBFL).

L'exemple de sortie fourni dans ce document est ou de /var/log/messages ou OBFL aussi bien que SYSTÈME D'EXPLOITATION se connecte pour ESXi, RHEL, et Windows.

Conditions préalables

Aucune spécification déterminée n'est requise pour ce document.

Composants utilisés

Les informations contenues dans ce document sont basées sur les versions de matériel et de logiciel suivantes :

- Version 1.4(3w) des micrologiciels C200-M1 du Système d'informatique unifiée Cisco (UCS)
- Version 1.4(3w) de micrologiciels du Cisco UCS C210-M2
- Version 2.0(3d) de micrologiciels du Cisco UCS C220-M3
- Version 2.0(3f) de micrologiciels du Cisco UCS C220-M4
- ESXi 5.0 U2
- RHEL 6.6
- Windows 2008 R2

Les informations contenues dans ce document ont été créées à partir des périphériques d'un environnement de laboratoire spécifique. Tous les périphériques utilisés dans ce document ont démarré avec une configuration effacée (par défaut). Si votre réseau est opérationnel, assurez-vous que vous comprenez l'effet potentiel de toute commande.

Informations générales

Une réinitialisation peut être prévue ou inattendue. Quand une réinitialisation est prévue, il pourrait être que non tous les ayants droit l'attendent. Il est important d'avoir un processus de contrôle de modification pour n'importe quelle réinitialisation ou les tâches de maintenance d'arrêt afin d'assurer chacun se rend compte de l'action.

Réinitialisations prévues

C'est n'importe quel événement de réinitialisation ou d'arrêt qui a été initié par une personne, un processus, ou un script intentionnellement. Ceci peut être initié dans une de plusieurs manières. Ces extraits de log peuvent aider aux identifier qui redémarrant le scénario se sont produits, de sorte que vous puissiez dépister qui ou ce qui a pris la mesure :

- Par le GUI CIMC
- Du SYSTÈME D'EXPLOITATION
- Quand vous appuyez sur le bouton de panneau avant sur l'avant du serveur

Réinitialisations inattendues

C'est n'importe quelle réinitialisation qui n'est pas prévue ou est prévue, mais elle peut encore être

prévue par la personne ou le processus qui ont initié l'action. Également, il pourrait y avoir eu une défaillance matérielle comme une panne de bloc d'alimentation ou coupure de courant au centre de traitement des données. Ceux-ci peuvent être initiés de plusieurs manières.

Si on le détermine que le bouton de panneau avant a été appuyé sur, vous pouvez dépister qui a eu accès physique au centre de traitement des données au moment de la réinitialisation. Si c'est une question d'alimentation, engagez l'équipe de Data Center voir s'il y avait une panne d'alimentation alors.

- Par le GUI CIMC
- Du SYSTÈME D'EXPLOITATION
- Quand vous appuyez sur le bouton de panneau avant sur l'avant du serveur
- De la défaillance matérielle telle qu'une panne de bloc d'alimentation ou un mauvais câble d'alimentation
- Panne de l'Unité de distribution d'alimentation (PDU) dans Data Center
- Panne d'alimentation d'alimentation sans coupure (UPS) ou coupure de courant ou chute de tension chez Data Center

Points clé

- Les réinitialisations, les arrêts, et les ons d'alimentation initiés par CIMC incluent toujours le mot clé de « do_power » dans les logs.
- Les presses de bouton de panneau avant incluent "passthrough_pin2_isr" quand vous exécutez les versions de firmware postérieures. En outre, il y a probable aucun événement niveau du système d'exploitation le corrélant de ceci.
- Les réinitialisations et les arrêts initiés par SYSTÈME D'EXPLOITATION ont un événement niveau du système d'exploitation associé. Notez également que le « do_power » n'est pas connecté, et « le mode à haute tension » peut sont enregistré à la place.

Paquets de log de rassemblement pour l'analyse

Avant que vous passiez en revue les logs appropriés, vous le premier besoin de générer le log empaquette. Employez ces ressources afin de créer les logs nécessaires pour la référence pour quand vous comparez aux exemples de sortie dans ce document :

Support technique de la série C CIMC

[Guide visuel pour collecter des fichiers de support technique \(B et séries C\)](#)

ESXi

[base de connaissances de vmware](#)

RHEL

[Quel est un sosreport et comment créer un à Red Hat Enterprise Linux 4.6 et plus tard ?](#)

Windows

[Archivez un journal d'événements de Windows](#)

Sortie prévue pour différents états de réinitialisation et d'arrêt

Réinitialisation de SYSTÈME D'EXPLOITATION - ESXi, RHEL, et Windows

Log OBFL

```
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[readPostData]:525:BIOS_POST_CMPLT Asserted --> BIOS has
completed
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4740 : Filename =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4740 : FName =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:129:[lpc_reset_seen]
LPC Reset Count is Different [0x77:0x78] Asserted LPC Reset Seen
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:200:[transition_function]
Starting Transition to [High Voltage Mode] from [Unknown Mode]
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:220:[transition_function]
Transition to [High Voltage Mode] Success
...
5:2017 Mar 2 09:47:01:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/DimmTempOffset
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_usb1_1.c:2290:
USB FS: VDD Power WAKEUP- Power Good = OFF
5:2017 Mar 2 09:47:06:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = OFF
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4756 : FName =
BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:IPMI:1497: Rack_FanCtrl.c:1183:fscUpdateActualFanPolicyFile:
Applied Policy: N/A, Configuration Status: PENDING - Host powered off
5:2017 Mar 2 09:47:06:BMC:IPMI:1466: Pilot2SrvPower.c:466:Blade Power Changed To: [ OFF ]
5:2017 Mar 2 09:47:06:BMC:selparser:1547: selparser.c:710:
```

```
# 7E 03 00 00 01 02 00 00 6A 30 B8 58 20 00 04 25 05 00 00 00 08 00 FF FF # 37e | 03/02/2017
09:47:06
| CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Absent | Asserted
...
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = ON
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:2685:Failed USB2.0 register
test
5:2017 Mar  2 09:47:12:BMC:kernel:--:last message repeated 2 times
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4778 : Filename =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4778 : FName =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:selparser:1547: selparser.c:710:
# 7F 03 00 00 01 02 00 00 6F 30 B8 58 20 00 04 25 05 00 00 00 08 01 FF FF # 37f
| 03/02/2017 09:47:11 | CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Present | Asserted
5:2017 Mar  2 09:47:12:BMC:IPMI:1495: Pilot2SrvPower.c:466:Blade Power Changed To: [ ON ]
```

Vérifiez les logs d'ESXi pour plus d'informations sur pourquoi le SYSTÈME D'EXPLOITATION a initié cet événement.

- /var/log/vmksmmary.log
- /var/log/vmkernel.log
- /var/log/hostd.log
- /var/log/shell.log

[KO de VMware](#)

RHEL - /var/log/messages

```
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoting known real-time threads.
May 12 12:55:00 localhost rtkit-daemon[10450]: Successfully demoted thread
10987 of process 10987 (/usr/bin/pulseaudio).
May 12 12:55:00 localhost console-kit-daemon[10311]: WARNING: no sender#012
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoted 1 threads.
May 12 12:55:00 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w" May 12 12:55:00 localhost init:
Disconnected from system bus
May 12 12:55:00 localhost auditd[3587]: The audit daemon is exiting.
May 12 12:55:00 localhost kernel: type=1305 audit(1431453300.949:33):
audit_pid=0 old=3587 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditd_t:s0 res=1
May 12 12:55:01 localhost kernel: type=1305 audit(1431453301.053:34):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditctl_t:s0 res=1
May 12 12:55:01 localhost kernel: Kernel logging (proc) stopped.
May 12 12:55:01 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3617" x-info="http://www.rsyslog.com"] exiting on signal 15.
May 12 12:58:27 localhost kernel: imklog 5.8.10, log source = /proc/kmsg started.
May 12 12:58:27 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3631" x-info="http://www.rsyslog.com"] start
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpuset
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpu
May 12 12:58:27 localhost kernel: Linux version 2.6.32-504.el6.x86_64
```

```
(mockbuild@x86-023.build.eng.bos.redhat.com) (gcc version 4.4.7 20120313
(Red Hat 4.4.7-11) (GCC) ) #1 SMP Tue Sep 16 01:56:35 EDT 2014
May 12 12:58:27 localhost kernel: Command line:
ro root=/dev/mapper/VolGroup-lv_root rd_NO_LUKS LANG=en_US.UTF-8
rd_NO_MD rd_LVM_LV=VolGroup/lv_swap SYSPFONT=latacyrheb-sun16 crashkernel=auto
rd_LVM_LV=VolGroup/lv_root KEYBOARDTYPE=pc KEYTABLE=us rd_NO_DM rhgb quiet
```

Pour plus de conseils sur la façon dont dépanner des réinitialisations RHEL, voir le ce [Red Hat KBarticle](#).

Windows - Journal d'événements

Event 1074

The process **Explorer.EXE has initiated the restart** of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: restart
Comment: C-Series Test

Event 1074

The **process C:\Windows\system32\winlogon.exe (WIN-5JPBKNMMRNF) has initiated the restart** of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: restart Comment:

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:26:32.778837300Z.

Event 12

The operating system started at system time ?2015?-?05?-?18T08:28:28.610798500Z.

Pour plus de conseils sur des journaux d'événements de Windows, contrôlez cet [article de TechNet](#).

Arrêt de SYSTÈME D'EXPLOITATION - ESXi, RHEL, et Windows

Log OBFL :

```
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs
Fn:0x6 Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:03:38:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC
Reset ISR -> ResetState: 1
5:2015 May 12 18:03:38:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_
CMPLT Asserted --> BIOS has completed
5:2015 May 12 18:03:38:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS:
VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 18:03:38:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
```

```
5:2015 May 12 18:03:38:BMC:IPMI:1563: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 18:03:38:BMC:video_trigger-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 11 04 00 00 01 02 00 00 7A 40 52 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 411 | 05/12/2015 18:03:38 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 12 04 00 00 01 02 00 00 7A 40 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF # 412 |
05/12/2015 18:03:38 | CIMC | Entity presence MAIN_POWER_PRS #0xa9 | Device Absent | Asserted
```

ESXi - /var/log/hostd.log

```
2015-05-15T00:46:01.809Z [28B69B90 info 'TaskManager'] Task Created :
    haTask--vim.host.AutoStartManager.autoPowerOff-245137084
2015-05-15T00:46:01.810Z [28AE7B90 info 'TaskManager'] Task Completed :
haTask--vim.host.AutoStartManager.autoPowerOff-245137084 Status success
2015-05-15T00:46:01.814Z [28AE7B90 verbose 'Default']
CloseSession called for session id=526869fe-3f96-f54a-4bb6-41250fa3242b
2015-05-15T00:46:01.814Z [28AE7B90 info 'ha-eventmgr'] Event 107 : User dcui logged out
2015-05-15T00:46:01.822Z [28AA6B90 verbose 'Proxysvc Req00060'] New proxy client SSL
(TCP(local=127.0.0.1:0, peer=127.0.0.1:58274))
2015-05-15T00:46:01.822Z [28AA6B90 warning 'Proxysvc Req00060'] Error reading from
client while waiting for header: N7Vmacore15SystemExceptionE(Connection reset by peer)
2015-05-15T00:46:02.077Z [29441B90 verbose 'Proxysvc Req00061'] New proxy client
SSL(TCP(local=127.0.0.1:443, peer=127.0.0.1:58877))
2015-05-15T00:46:02.088Z [28AE7B90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket issued for dcui
2015-05-15T00:46:02.090Z [2930AB90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket used
Accepted password for user dcui from 127.0.0.1
2015-05-15T00:46:02.090Z [2930AB90 info 'Vimsvc'] [Auth]: User dcui
2015-05-15T00:46:02.091Z [2930AB90 info 'ha-eventmgr'] Event 108 :
User dcui@127.0.0.1 logged in
2015-05-15T00:46:02.093Z [29366B90 info 'InternalServiceInstance'] Shutting down service
2015-05-15T00:46:22.104Z [FFAB2AD0 error 'Default'] SSLStreamImpl::
BIORead (291a1000) timed out
Section for VMware ESX, pid=2882, version=5.0.0, build=build-914586, option=Release
```

RHEL - /var/log/messages

```
May 12 13:03:24 localhost init: tty (/dev/tty2) main process
(10152) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty3) main process
(10154) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty4) main process
(10156) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty5) main process
(10158) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty6) main process
(10162) killed by TERM signal
May 12 13:03:25 localhost abrttd: Got signal 15, exiting
May 12 13:03:29 localhost acpid: exiting
May 12 13:03:30 localhost NetworkManager[9732]: <info>
    caught signal 15, shutting down normally.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): taking down device.
```

```

May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> exiting (success)
May 12 13:03:31 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w"
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoting known real-time threads.
May 12 13:03:31 localhost rtkit-daemon[10367]: Successfully demoted thread 1
0365 of process 10365 (/usr/bin/pulseaudio).
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoted 1 threads.
May 12 13:03:31 localhost console-kit-daemon[10228]: WARNING: no sender#012
May 12 13:03:31 localhost init: Disconnected from system bus
May 12 13:03:31 localhost auditd[3601]: The audit daemon is exiting.
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.355:22):
audit_pid=0 old=3601 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditd_t:s0 res=1
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.459:23):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditctl_t:s0 res=1
May 12 13:03:31 localhost kernel: Kernel logging (proc) stopped.
May 12 13:03:31 localhost rsyslogd: [origin software="rsyslogd"
swVersion="5.8.10" x-pid="3631" x-info="http://www.rsyslog.com"] exiting on signal 15.

```

Windows - Journal d'événements

Event 1074

The process C:\Windows\system32\winlogon.exe (WIN-5JPBKNMMRNF) **has initiated the power off of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator** for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: power off
Comment

Event 1074

The **process Explorer.EXE has initiated the shutdown** of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: shutdown
Comment: Shut down Test

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:38:13.237425300Z.

Mettez sous tension de CIMC

Log OBFL :

5:2015 May 12 18:08:31:BMC:kernel:-:<5>[__do_power_on]:340:__do_power_on


```
5:2015 May 12 18:08:31:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0 Cmd:0x2
Data&colon; 0x1
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:345:Power Driver:
Power On Logic Pulse for 250ms @ 25164275955:2015 May 12 18:08:31:BMC:IPMI:
1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:08:31:BMC:IPMI:20723: Server power state modify (op:power-on)
5:2015 May 12 18:08:31:BMC:kernel:--<5>drivers/bmc/usb/usbl1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]
:2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:484:Blade
Power Changed To: [ ON ]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 18:08:31:BMC:IPMI:1566: Pilot3SrvPower.c:191:Pilot2SrvPowerOn
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:375:
Power Driver: Power On Logic Done @ 2516427846
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1406 : Filename = BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1406 : FName = BiosTech_7.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1408 : Filename = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1408 : FName = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:262:Sending
event_ipmi_power_state_change (ON) ..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:137:Sending
event_server_boot_start..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:148:
Will be able to send event_server_crash..
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 13 04 00 00 01 02 00 00 A0 41 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 413 | 05/12/2015 18:08:32 | Unknown
#0x602c | Unknown #0x1a |
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 14 04 00 00 01 02 00 00 A0 41 52 55 20 00 04 25 00 00 00 00 08 00 FF FF
# 414 | 05/12/2015 18:08:32 | CIMC | Entity presence BIOS_POST_CMPLT
#0x00 | Device Absent | Asserted
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1410 : Filename = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1410 : FName = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
```

Arrêt et redémarrage de CIMC

Log OBFL

```
5:2015 May 12 19:18:45:BMC:kernel:--<5>[do_cycle]:560:do_cycle
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x2
5:2015 May 12 19:18:45:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 19:18:45:BMC:kernel:--<5>[__do_power_off]:300:Power Driver:
Power Off Logic @ 2520641182
5:2015 May 12 19:18:45:BMC:IPMI:1566: Pilot3SrvPower.c:539:
Pilot2SrvPowerCycle
5:2015 May 12 19:18:45:BMC:AUDIT:20723: Server power state modify
(op:power-cycle)
5:2015 May 12 19:18:49:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 19:18:49:BMC:kernel:--<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 12 19:18:49:BMC:kernel:--<5>drivers/bmc/usb/
usb1.1/se_pilot2_udc_usb1.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 19:18:49:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 19:18:49:BMC:video_trigger:-- video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 19:18:49:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 12 19:18:49:BMC:selparser:1602: selparser.c:678:
# 1A 04 00 00 01 02 00 00 19 52 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 41a | 05/12/2015 19:18:49 | CIMC | Entity presence MAIN_POWER_PRS #0xa9
| Device Absent | Asserted
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
# 1B 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 DC 1A 00 00 00 74 03 00 00
# 41b | 05/12/2015 19:18:54 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
# 1C 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 16 16 00 00 00 0A 00 00 00
# 41c | 05/12/2015 19:18:54 | Unknown
#0x602c | Microcontroller/Coprocessor
#0x16 | Transition to Running | Asserted
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]:345:
Power Driver: Power On Logic Pulsefor 250ms @ 2520661694
5:2015 May 12 19:19:05:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1.1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 19:19:05:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:542:Pilot2SrvPowerCycle
5:2015 May 12 19:19:05:BMC:kernel:--<5>[__do_power_on]
:375:Power Driver: Power On Logic Done @ 2520661945
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:481:
-> Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 19:19:05:BMC:IPMI:1566: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
```

```
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:242:
File Open : BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1466 : Filename = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1944:block_transfer_fetch_host_request_for_app :
BT_FILE_CLOSE : HostBTDescr = 1466 : FName = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:selparser:1602: selparser.c:678:
# 1D 04 00 00 01 02 00 00 29 52 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 41d | 05/12/2015 19:19:05 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:148:
Will be able to send event_server_crash ..
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1468 : Filename = BiosTech_6.txt
```

Mettez hors tension de CIMC

Log OBFL

```
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x0
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:300:Power Driver:
Power Off Logic@ 2524221543
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 20:18:25:BMC:AUDIT:20723: Server power state modify (op:power-off)
5:2015 May 12 20:18:30:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 20:18:30:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 12 20:18:30:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 20:18:30:BMC:IPMI:1567: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 20:18:30:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 12 20:18:30:BMC:selparser:1602: selparser.c:678:
# 24 04 00 00 01 02 00 00 16 60 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 424 | 05/12/2015 20:18:30 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:2015 May 12 20:18:30:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 20:18:31:BMC:vkcs_mux:1582: vkcs_mux.c:76:[REQ] 00 01
5:2015 May 12 20:18:36:BMC:IPMI:1566: Pilot3SrvPower.c:348:Pilot2SrvPowerOff
5:2015 May 12 20:18:37:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:37:BMC:blade-power:11311: host-power.c:53:POWER Off
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:511:Run-update Process Starting.
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:44:Setting FP Button Lock: current state 0
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1373:Front Panel Power Button is now permanently locked.
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1378:Front Panel Reset Button is now permanently locked.
```

Coupure de courant de panne de bloc d'alimentation

Log OBFL

```
5:2015 May 15 14:29:12:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:29:12:BMC:kernel:--<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 15 14:29:12:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/
se_pilot2_udc_usbl_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:29:12:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 15 14:29:12:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:29:12:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 33 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 27 00 00 00 03 00 FF FF
# 433 | 05/15/2015 14:29:12 | CIMC | Power supply PSU1_AC_OK
#0x27 | State Deasserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 34 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 42 00 00 00 04 01 FF FF
# 434 | 05/15/2015 14:29:12 | CIMC | Power supply PMBUS_ALERT #0x42
| Predictive Failure asserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 35 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 435 | 05/15/2015 14:29:12 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:1970 Jan 1 00:02:48:BMC:kernel:--<5>Linux version 2.6.35.10
(buildsa@savbu-swbmc-vb1) (gcc version 3.4.5)
#2 Tue Nov 18 07:09:13 PST 2014 Unversioned directory
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: ARM926EJ-S [41069265]
revision 5 (ARMv5TEJ), cr=00053177
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: VIVT data cache, VIVT instruction cache
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Machine: ServerEngines PILOT3 Hornet Board
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Memory policy: ECC disabled, Data cache writeback
```

Le bouton avant mettent hors tension

Log OBFL

```
5:2015 May 15 14:50:19:BMC:kernel:--<5>[passthrough_pin2_isr]:158:x86
Host Power Button Press
5:2015 May 15 14:50:19:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:50:19:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:
USB HS: VDD Power = ON
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1478:audit from:kcs Fn:0x6
Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1484:audit Resp:0x0
5:2015 May 15 14:50:35:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:50:35:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 15 14:50:35:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:50:35:BMC:kernel:--<5>drivers/bmc/usb/usbl.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:50:35:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
```

```
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:50:35:BMC:IPMI:1531: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A2 04 00 00 01 02 00 00 BB 07 56 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 4a2 | 05/15/2015 14:50:35 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A3 04 00 00 01 02 00 00 BB 07 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 4a3 | 05/15/2015 14:50:35 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
```

Le bouton avant mettent sous tension

Log OBFL

```
5:2015 May 15 14:51:18:BMC:kernel:--<5>[passthrough_pin2_isr]:
:158:x86 Host Power Button Press
5:2015 May 15 14:51:18:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2
_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:51:18:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:51:19:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_
udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
:2561:USB HS: VDD Power = ON
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 0
5:2015 May 15 14:51:19:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCoff[0]
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 118 : Filename = BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 119 : Filename = BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 120 : Filename = BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 121 : Filename = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 121 : FName = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:video_trigger:-- video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 15 14:51:19:BMC:video_trigger:-- video_trigger.c:137:
Sending event_server_boot_start ..
```

```
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:148
:Will be able to send event_server_crash ..
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 123 : Filename = BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 123 : FName = BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_3.txt
```

[Informations connexes](#)

- [Dépannage de réinitialisation de série C](#)
- [Support et documentation techniques - Cisco Systems](#)