

Determinazione del numero di serie dei componenti dello switch Catalyst

Sommario

[Introduzione](#)

[Prerequisiti](#)

[Requisiti](#)

[Componenti usati](#)

[Convenzioni](#)

[Premesse](#)

[Catalyst 6500](#)

[Catalyst 4500](#)

[Catalyst 4500 con Supervisor Engine 2](#)

[Catalyst 4500 Supervisor Engine II+/III/IV](#)

[Catalyst 3750](#)

[Catalyst 3560](#)

[Catalyst 3550](#)

[Catalyst 2950/2970/2940](#)

[Catalyst 2900XL/3500XL](#)

[Catalyst 2948GL3/4908G-L3/4980G-L3](#)

[Catalyst 9000](#)

[Informazioni correlate](#)

Introduzione

In questo documento viene descritto come determinare i numeri di serie di vari componenti sostituibili sugli switch Cisco Catalyst.

Prerequisiti

Requisiti

Nessun requisito specifico previsto per questo documento.

Componenti usati

Le informazioni fornite in questo documento si basano sulle seguenti versioni software e hardware:

- Vari switch Catalyst
- Varie versioni del software

Le informazioni discusse in questo documento fanno riferimento a dispositivi usati in uno specifico ambiente di emulazione. Su tutti i dispositivi menzionati nel documento la configurazione è stata ripristinata ai valori predefiniti. Se la rete è operativa, valutare attentamente eventuali conseguenze derivanti dall'uso dei comandi.

Convenzioni

Per ulteriori informazioni sulle convenzioni usate, consultare il documento [Cisco sulle convenzioni nei suggerimenti tecnici](#).

Premesse

I numeri di serie sono necessari per creare un database dei componenti della rete. Quando si crea una richiesta di assistenza con il [supporto tecnico Cisco](#), è necessario avere a portata di mano il numero di serie dei dispositivi interessati. Questo requisito si applica in particolare quando è necessario un componente sostitutivo o un'autorizzazione per la restituzione del materiale (RMA).

Non è possibile modificare il numero di serie degli switch Cisco Catalyst. A scopo di gestione, è possibile configurare gli switch Cisco Catalyst con software Cisco IOS® in modo che restituiscano una stringa personalizzata. Per creare una stringa personalizzata, usare il comando **snmp-server chassis-id** in modalità di configurazione globale.

Nota: per informazioni specifiche sui comandi show, vedere [Comandi show](#).

Catalyst 6500

Per determinare il numero di serie dello chassis e di altri componenti, usare il comando `show idprom` comando:

```
<#root>
6506#
show idprom ?

  all           selects all FRU-types
  backplane     specify backplane
  clock         specify clock <number>
  earl          specify earl <slot>
  fan-tray      specify fan-tray <number>
  interface     interface name
  module        specify module <slot>
  power-supply specify power-supply <number>
  rp            specify RP (MSFC) <slot>
  supervisor    specify supervisor <slot>
  vtt           specify VTT <number>
```

Per ottenere il numero di serie dello chassis, usare il comando **show idprom backplane**:

```
<#root>
6506#
show idprom backplane

IDPROM for backplane #0
(FRU is 'Catalyst 6500 6-slot backplane')
OEM String = 'Cisco Systems'
```

Product Number = 'WS-C6506'

Serial Number = 'TBA03270652'

Manufacturing Assembly Number = '73-3436-01'

Manufacturing Assembly Revision = 'A0'

Hardware Revision = 1.0

Current supplied (+) or consumed (-) = -A

Per ottenere il numero di serie del modulo, usare il comando **show idprom module slot<slot number>**. In alternativa, è possibile usare il comando **show module**:

<#root>

6506#

show module

Mod	Ports	Card Type	Model
1	2	Catalyst 6000 supervisor 2 (Active)	WS-X6K-S2U-MSFC2
SAD055006NE			
3	0	2 port adapter FlexWAN	WS-X6182-2PA
SAD04350EEU			
4	48	SFM-capable 48-port 10/100 Mbps RJ45	WS-X6548-RJ-45
SAD055108C2			

Mod	MAC addresses	Hw	Fw	Sw	Status
1	0001.6415.a602 to 0001.6415.a603	3.2	6.1(3)	7.5(0.6)HUB6	Ok
3	0001.6413.c86b to 0001.6413.c8aa	1.5	12.1(13)E1	12.1(13)E1	Ok
4	0001.63d3.e77a to 0001.63d3.e7a9	4.0	6.3(1)	7.5(0.6)HUB6	Ok

Mod	Sub-Module	Model	Serial	Hw	Status
1	Policy Feature Card 2	WS-F6K-PFC2	SAD055004VA	3.0	Ok
1	Cat6k MSFC 2 daughterboard	WS-F6K-MSFC2	SAD055006VF	2.0	Ok

Mod Online Diag Status

1 Pass
3 Not Supported
4 Pass

Nota: utilizzare `show diagbus` per determinare il numero di serie degli adattatori di porte sul modulo Flex WAN.

Catalyst 4500

Catalyst 4500 con Supervisor Engine 2

Sugli switch Catalyst 4500/4000 Supervisor 2, il numero di serie dello chassis è disponibile tramite CLI nelle versioni 5.5(10), 6.3(2) e successive. Nelle versioni precedenti, il comando **show version** restituisce il numero di serie del Supervisor Engine al posto del numero di serie dello chassis. Per ottenere il numero di serie dello chassis in queste versioni precedenti, controllare l'adesivo esterno sullo chassis.

Catalyst 4500 Supervisor Engine II+/III/IV

Per determinare il numero di serie dello chassis e di altri componenti, usare il comando **show idprom:**

```
<#root>
```

```
Switch#
```

```
show idprom ?
```

```
all          show all non-interface IDPROMs
chassis      show IDPROM for chassis
fan-tray     show IDPROM for system fan tray
interface    show contents of gbic connected to this interface
module       show IDPROM for module
power-supply show IDPROM for power supply
supervisor   show IDPROM for supervisor
```

Per ottenere il numero di serie dello chassis, utilizzare il `show idprom chassis` comando:

```
<#root>
```

```
Switch#
```

```
show idprom chassis
```

```
Chassis Idprom :
Common Block Signature = 0xABAB
Common Block Version = 1
Common Block Length = 144
Common Block Checksum = 4081
Idprom Size = 256
Block Count = 2
FRU Major Type = 0x4001
FRU Minor Type = 37
OEM String = Cisco Systems, Inc.
Product Number = WS-C4506
Serial Number = FOX0627A001
Part Number = 73-8107-04
Part Revision = 01
Manufacturing Deviation String = 0
Hardware Revision = 0.4
Manufacturing Bits = 0x0000
Engineering Bits = 0x0000
Snmp OID = 0.0.0.0.0.0.0
Power Consumption = 0
```

```
RMA Failure Code = 0 0 0 0
Chassis Block Signature = 0x4001
Chassis Block Version = 1
Chassis Block Length = 22
Chassis Block Checksum = 628
Feature Bits = 0x0000000000000000
MAC Base = 000a.4172.df40
MAC Count = 64
```

Per ottenere il numero di serie dell'alimentatore, usare il comando **show idprom power-supply {1} | 2}** comando:

```
<#root>
```

```
Switch#
```

```
show idprom power-supply 1
```

```
Power Supply 1 Idprom :
Common Block Signature = 0xABAB
Common Block Version = 1
Common Block Length = 144
Common Block Checksum = 5857
Idprom Size = 256
Block Count = 2
FRU Major Type = 0x4501
FRU Minor Type = 1
OEM String = Cisco Systems, Inc.
```

```
Product Number = PWR-C4K-1400AC
```

```
Serial Number = ABC06260005
```

```
Part Number = 34-1846-01
Part Revision = 45
Manufacturing Deviation String =
Hardware Revision = 1.0
Manufacturing Bits = 0x0000
Engineering Bits = 0x0000
Snmp OID = 22616.22616.22616.22616.22616.22616.22616.22616
Power Consumption = 1400
RMA Failure Code = 0 0 0 0
Power Supply Block Signature = 0x4501
PowerSupply Block Version = 1
PowerSupply Block Length = 20
PowerSupply Block Checksum = 293
Feature Bits = 0x0000000000000000
Current @ 110V = 17
Current @ 220V = 9
StackMIB OID = 22616
```

Per ottenere il numero di serie del modulo, usare il comando **show idprom module slot<slot number>**. In alternativa, è possibile utilizzare il comando **show module**:

```
<#root>
```

Switch#

show module

Mod	Ports	Card Type	Model	Serial No.
1	2	1000BaseX (GBIC) Supervisor(active)	WS-X4014	JAB054109H1
3	48	10/100BaseTX (RJ45)	WS-X4148	JAB025202M6
4	6	1000BaseX (GBIC)	WS-X4306	JAB023403BG

M	MAC addresses	Hw	Fw	Sw	Status
1	000a.4172.df40 to 000a.4172.df41	0.5	12.1(12r)EW	12.1(13)EW(0.34)	Ok
3	0050.730b.2340 to 0050.730b.236f	1.0			Ok
4	0010.7bfa.7ca4 to 0010.7bfa.7ca9	2.0			Ok

Catalyst 3750

Utilizzare il comando **show version** per determinare il numero di serie dello chassis e il tipo di modello dello switch, come mostrato nell'esempio. L'output contiene tutte le informazioni sui membri dello stack di switch, sullo chassis e sul numero di serie:

<#root>

3750#

show version

```
Cisco Internetwork Operating System Software
Cisco IOS (tm) C3750 Software (C3750-I5-M), Version 12.1(14)EA1, RELEASE SOFTWARE (fc1)
)
Copyright (c) 1986-2003 by cisco Systems, Inc.
Compiled Tue 22-Jul-03 13:17 by antonino
Image text-base: 0x00003000, data-base: 0x008F0CF8
```

```
ROM: Bootstrap program is C3750 boot loader
BOOTLDR: C3750 Boot Loader (C3750-HBOOT-M) Version 12.1(11r)AX, RELEASE SOFTWARE
(fc1)
```

```
3750RJ uptime is 1 hour, 29 minutes
System returned to ROM by power-on
System image file is "flash:c3750-i5-mz.121.14-EA1/c3750-i5-mz.121.14-EA1.bin"
```

```
cisco WS-C3750-24TS (PowerPC405) processor (revision A0) with 120822K/10240K bytes of memory.
Processor board ID CAT0726R0ZU
```

Last reset from power-on
Bridging software.
2 Virtual Ethernet/IEEE 802.3 interface(s)
48 FastEthernet/IEEE 802.3 interface(s)
16 Gigabit Ethernet/IEEE 802.3 interface(s)
The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.

Base ethernet MAC Address : 00:0D:29:B4:18:00

Motherboard assembly number : 73-7055-06

Power supply part number : 341-0034-01

Motherboard serial number : CAT0726043V

Power supply serial number : PHI0708009K

Model revision number : A0

Motherboard revision number : A0

Model number : WS-C3750-24TS-E

System serial number : CAT0726R0ZU

Switch Ports Model SW Version SW Image

```
-----  
* 1 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
2 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
3 12 WS-C3750G-12S 12.1(14)EA1 C3750-I5-M
```

Switch 02

Switch Uptime : 1 hour, 29 minutes

Base ethernet MAC Address : 00:0D:29:B4:3F:00

Motherboard assembly number : 73-7055-06

Power supply part number : 341-0034-01

Motherboard serial number : CAT07260438

Power supply serial number : PHI0708008X

Model revision number : A0

Motherboard revision number : A0

Model number : WS-C3750-24TS-E

System serial number : CAT0726R10A

Switch 03

Switch Uptime : 1 hour, 29 minutes

Base ethernet MAC Address : 00:0D:BD:6A:3E:00

Motherboard assembly number : 73-8307-06

Power supply part number : 341-0048-01

Motherboard serial number : CAT073205S2

Power supply serial number : DTH0731055Z

Model revision number : A0

Motherboard revision number : A0

Model number : WS-C3750G-12S-E

System serial number : CAT0732R0M4

Top assembly part number : 800-23419-01

Top assembly revision number : A0

Configuration register is 0xF

3750#

Catalyst 3560

Per determinare il numero di serie dello chassis e il tipo di modello dello switch, usare il comando **show version**:

<#root>

3560#

show version

Cisco Internetwork Operating System Software
Cisco IOS (tm) C3560 Software (C3560-I5-M), Version 12.1(19)EA1c, RELEASE SOFTWARE (fc2)
Copyright (c) 1986-2004 by cisco Systems, Inc.
Compiled Tue 03-Feb-04 05:56 by yenanh
Image text-base: 0x00003000, data-base: 0x0091D404

ROM: Bootstrap program is C3560 boot loader
BOOTLDR: C3560 Boot Loader (C3560-HB00T-M) Version 12.1(19r)EA1b, RELEASE SOFTWARE (fc2)

3-8-03-CATS3560 uptime is 8 weeks, 4 days, 18 hours, 16 minutes
System returned to ROM by power-on
System image file is "flash:c3560-i5-mz.121-19.EA1c.bin"

cisco WS-C3560-24PS (PowerPC405) processor (revision D0) with 118776K/12288K bytes of memory.
Processor board ID CSG0802P0G4
Last reset from power-on
Bridging software.
1 Virtual Ethernet/IEEE 802.3 interface(s)
24 FastEthernet/IEEE 802.3 interface(s)
2 Gigabit Ethernet/IEEE 802.3 interface(s)
The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.
Base ethernet MAC Address : 00:0E:39:E9:32:80
Motherboard assembly number : 73-9299-01
Power supply part number : 341-0029-03
Motherboard serial number : CAT075108EK
Power supply serial number : LIT074900K3
Model revision number : D0
Motherboard revision number : C0

Model number : WS-C3560-24PS-E
System serial number : CSG0802P0G4

Top Assembly Part Number : 800-24814-01
Top Assembly Revision Number : D0
Version ID : N/A
Hardware Board Revision Number : 0x08

Catalyst 3550

Per determinare il numero di serie dello chassis e il tipo di modello dello switch, usare il comando **show version**:

```
<#root>
```

```
Cat3550#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3550 Software (C3550-I5Q3L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Mon 25-Nov-02 00:07 by antonino  
Image text-base: 0x00003000, data-base: 0x0075FE48
```

```
ROM: Bootstrap program is C3550 boot loader
```

```
Cat3550 uptime is 4 days, 2 hours, 57 minutes  
System returned to ROM by power-on  
System image file is "flash:c3550-i5q3l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C3550-48 (PowerPC) processor (revision G0) with 65526K/8192K bytes of memory.  
Processor board ID CHK0642W02B  
Last reset from warm-reset  
Bridging software.  
Running Layer2/3 Switching Image
```

```
Ethernet-controller 1 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 2 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 3 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 4 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 5 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
Ethernet-controller 6 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
The password-recovery mechanism is enabled.  
384K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:0B:46:8A:2F:80  
Motherboard assembly number: 73-5701-07  
Power supply part number: 34-0967-01  
Motherboard serial number: CAT0641027L  
Power supply serial number: DCA06392BU2  
Model revision number: G0  
Motherboard revision number: A0
```

```
Model number: WS-C3550-48-SMI
```

```
System serial number: CHK0642W02B
```

```
Configuration register is 0x10F
```

Catalyst 2950/2970/2940

Per determinare il numero di serie dello chassis e il tipo di switch, utilizzare il `show version` comando:

```
<#root>
```

```
Cat2950#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C2950 Software (C2950-I6Q4L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Sun 24-Nov-02 23:31 by antonino  
Image text-base: 0x80010000, data-base: 0x80562000
```

```
ROM: Bootstrap program is CALHOUN boot loader
```

```
Cat2950 uptime is 4 days, 2 hours, 52 minutes  
System returned to ROM by power-on  
System image file is "flash:c2950-i6q4l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C2950G-48-EI (RC32300) processor (revision C0) with 21002K bytes of memory.  
Processor board ID FHK0624W0HS  
Last reset from system-reset  
Running Enhanced Image  
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
32K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:09:E8:89:4A:40  
Motherboard assembly number: 73-7409-08  
Power supply part number: 34-0965-01  
Motherboard serial number: FOC06230ERQ  
Power supply serial number: DAB062143BP  
Model revision number: C0  
Motherboard revision number: B0
```

```
Model number: WS-C2950G-48-EI
```

```
System serial number: FHK0624W0HS
```

```
Configuration register is 0xF
```

Catalyst 2900XL/3500XL

Per determinare il numero di serie dello chassis e il tipo di switch, utilizzare il `show version` comando:

```
<#root>
```

```
Switch#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3500XL Software (C3500XL-C3H2S-M), Version 12.0(5.2)XU, MAINTENANCE  
INTERIM SOFTWARE
```

Copyright (c) 1986-2000 by cisco Systems, Inc.
Compiled Mon 17-Jul-00 18:29 by ayounes
Image text-base: 0x00003000, data-base: 0x00301F3C

ROM: Bootstrap program is C3500XL boot loader

Switch uptime is 4 days, 3 hours, 4 minutes
System returned to ROM by power-on
System image file is "flash:c3500XL-c3h2s-mz-120.5.2-XU.bin"

Cisco WS-C3548-XL (PowerPC403) processor (revision 0x01) with 16384K/1024K bytes of memory. Processor board ID FOC0616X0RG, with hardware revision 0x00
Last reset from power-on

Processor is running Enterprise Edition Software
Cluster command switch capable
Cluster member switch capable
48 FastEthernet/IEEE 802.3 interface(s)
2 Gigabit Ethernet/IEEE 802.3 interface(s)

32K bytes of flash-simulated non-volatile configuration memory.
Base ethernet MAC Address: 00:09:7C:8E:78:80
Motherboard assembly number: 73-3903-09
Power supply part number: 34-0971-02
Motherboard serial number: FOC06160L07
Power supply serial number: APQ061200VZ
Model revision number: M0
Motherboard revision number: A0

Model number: WS-C3548-XL-EN

System serial number: FOC0616X0RG

Configuration register is 0xF

Catalyst 2948GL3/4908G-L3/4980G-L3

Per determinare il numero di serie dello chassis, utilizzare il `show hardware` comando:

```
<#root>
```

```
2948g-l3#
```

```
show hardware
```

```
Model: Cat-2948G-L3 Date: 17:49:42 UTC Tue Mar 18 2003
```

```
XPIF FPGA File:          xpif_fpga_0_72b_CClk.rbt  
XPIF FPGA Date:         Wed Dec  8 17:05:42 1999
```

```
Slot 0/0:
```

Chip 0	Reset Count: 0	Chip 1	Reset Count: 0
Chip 2	Reset Count: 0	Chip 3	Reset Count: 0
Chip 4	Reset Count: 0	Chip 5	Reset Count: 0
Chip 6	Reset Count: 0	Chip 7	Reset Count: 0
Chip 8	Reset Count: 0	Chip 9	Reset Count: 0
Chip 10	Reset Count: 0	Chip 11	Reset Count: 0

```
EPIF Version      : 0                CAM size: 32 KB
Ucode Version    : 1.0
Ucode Image      : EPIF_UCODE_RUNTIME
Port Phy Setup
  Port1 :DONE      Port2 :DONE      Port3 :DONE      Port4 :DONE
  Port5 :DONE      Port6 :DONE      Port7 :DONE      Port8 :DONE
  Port9 :DONE      Port10:DONE     Port11:DONE     Port12:DONE
  Port13:DONE     Port14:DONE     Port15:DONE     Port16:DONE
  Port17:DONE     Port18:DONE     Port19:DONE     Port20:DONE
  Port21:DONE     Port22:DONE     Port23:DONE     Port24:DONE
  Port25:DONE     Port26:DONE     Port27:DONE     Port28:DONE
  Port29:DONE     Port30:DONE     Port31:DONE     Port32:DONE
  Port33:DONE     Port34:DONE     Port35:DONE     Port36:DONE
  Port37:DONE     Port38:DONE     Port39:DONE     Port40:DONE
  Port41:DONE     Port42:DONE     Port43:DONE     Port44:DONE
  Port45:DONE     Port46:DONE     Port47:DONE     Port48:DONE
```

```
Slot 0/1:
XPIF Version      : 0                CAM size: 128 KB
Ucode Version    : 1.0
Ucode Image      : XPIF_UCODE_RUNTIME
Port Phy Setup
  Port49:DONE     Port50:DONE
```

```
IDPROM Contents  :
  FRU Type       : 0x0.0x0
  OEM String     : Cisco_Systems
```

```
Product Number   : WS-C2948G-L3
```

```
Serial Number    : FOX05330ADH
```

```
  Mfg. Assembly No. : 73-4083-07
  Mfg. Assembly Ver. : A0
  Hardware Version   : 1.7
  FPGA Version       : 0
  SNMP IOD           : 9.5.1.3.1.1.2.275
  RMA Code           : 0
  Feature Bits       : 0x00000000
  MAC Address Base   : 00:07:85:07:DC:00
  Total MAC Addrs.   : 1024
```

Catalyst 9000

Per determinare il numero di serie dello chassis, usare il comando **show version**. In alternativa, è possibile utilizzare il comando **show module** per visualizzare un output più piccolo:

```
<#root>
```

```
C9300#
```

```
show version
```

```
Cisco IOS XE Software, Version 17.06.04
Cisco IOS Software [Bengaluru], Catalyst L3 Switch Software (CAT9K_IOSXE), Version 17.6.4, RELEASE SOFTWARE
```

Technical Support: <http://www.cisco.com/techsupport>
Copyright (c) 1986-2022 by Cisco Systems, Inc.
Compiled Sun 14-Aug-22 08:58 by mcpre

Cisco IOS-XE software, Copyright (c) 2005-2022 by cisco Systems, Inc.
All rights reserved. Certain components of Cisco IOS-XE software are licensed under the GNU General Public License ("GPL") Version 2.0. The software code licensed under GPL Version 2.0 is free software that comes with ABSOLUTELY NO WARRANTY. You can redistribute and/or modify such GPL code under the terms of GPL Version 2.0. For more details, see the documentation or "License Notice" file accompanying the IOS-XE software, or the applicable URL provided on the flyer accompanying the IOS-XE software.

ROM: IOS-XE ROMMON
BOOTLDR: System Bootstrap, Version 17.8.1r[FC2], RELEASE SOFTWARE (P)

C9300 uptime is 1 week, 2 days, 17 hours, 51 minutes
Uptime for this control processor is 1 week, 2 days, 17 hours, 54 minutes
System returned to ROM by Reload Command at 07:14:20 jst Wed Aug 2 2023
System restarted at 07:29:56 jst Wed Aug 2 2023
System image file is "flash:packages.conf"
Last reload reason: Reload Command

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at:
<http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>

If you require further assistance please contact us by sending email to export@cisco.com.

Technology Package License Information:

Technology-package Current	Type	Technology-package Next reboot
network-advantage	Smart License	network-advantage
dna-advantage	Subscription Smart License	dna-advantage

AIR License Level: AIR DNA Advantage
Next reload AIR license Level: AIR DNA Advantage

Smart Licensing Status: Registration Not Applicable/Not Applicable

cisco C9300-24UX (X86) processor with 1317097K/6147K bytes of memory.
Processor board ID FJC2325E0HB
5 Virtual Ethernet interfaces
8 Gigabit Ethernet interfaces

64 Ten Gigabit Ethernet interfaces
4 TwentyFive Gigabit Ethernet interfaces
4 Forty Gigabit Ethernet interfaces
2048K bytes of non-volatile configuration memory.
8388608K bytes of physical memory.
1638400K bytes of Crash Files at crashinfo:.
11264000K bytes of Flash at flash:.

Base Ethernet MAC Address : c4:c6:03:9a:bd:80
Motherboard Assembly Number : 73-18276-03
Motherboard Serial Number : FJZ23210BTF
Model Revision Number : D0
Motherboard Revision Number : B0

Model Number : C9300-24UX

System Serial Number : FJC2325E0HB

CLEI Code Number :

Switch	Ports	Model	SW Version	SW Image	Mode
*	1 41	C9300-24UX	17.06.04	CAT9K_IOSXE	INSTALL

C9300#

show module

Switch	Ports	Model	Serial No.	MAC address	Hw Ver.	Sw Ver.
1	41					

C9300-24UX

FJC2325E0HB

c4c6.039a.bd80 V02 17.06.04
C9300#

Informazioni correlate

- [Comandi show](#)
- [Supporto tecnico e download Cisco](#)

Informazioni su questa traduzione

Cisco ha tradotto questo documento utilizzando una combinazione di tecnologie automatiche e umane per offrire ai nostri utenti in tutto il mondo contenuti di supporto nella propria lingua. Si noti che anche la migliore traduzione automatica non sarà mai accurata come quella fornita da un traduttore professionista. Cisco Systems, Inc. non si assume alcuna responsabilità per l'accuratezza di queste traduzioni e consiglia di consultare sempre il documento originale in inglese (disponibile al link fornito).